

AS IEC 61800.5.1:2024
IEC 61800-5-1:2022
IEC 61800-5-1:2022/COR1:2023



STANDARDS
Australia



Adjustable speed electrical power drive systems

Part 5.1: Safety requirements — Electrical, thermal and energy



AS IEC 61800.5.1:2024

This Australian Standard® was prepared by EL-027, Power Electronics. It was approved on behalf of Standards Australia's Standards Development and Accreditation Committee on 12 June 2024.

This Standard was published on 28 June 2024.

The following are represented on Committee EL-027:

- Australian Industry Group
- Bureau of Steel Manufacturers of Australia
- Department of Defence (Australian Government)
- Energy Networks Australia
- Engineers Australia
- University of Newcastle

This Standard was issued in draft form for comment as DR AS IEC 61800.5.1:2024.

Keeping Standards up-to-date

Ensure you have the latest versions of our publications and keep up-to-date about Amendments, Rulings, Withdrawals, and new projects by visiting:

www.standards.org.au

ISBN 978 1 76139 748 6

Adjustable speed electrical power drive systems

Part 5.1: Safety requirements — Electrical, thermal and energy

Originated as AS IEC 61800.5.1—2013.
Second edition 2024.



© IEC Geneva Switzerland 2024 — All rights reserved
© Standards Australia Limited 2024

All rights are reserved. No part of this work may be reproduced or copied in any form or by any means, electronic or mechanical, including photocopying, without the written permission of either the IEC or the publisher, unless otherwise permitted under the Copyright Act 1968 (Cth). If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please see the contact details on the back cover or the contact us page of the website for further information.

Preface

This Standard was prepared by the Standards Australia Committee EL-027, Power Electronics, to supersede AS IEC 61800.5.1:2013.

The objective of this document is to specify requirements for adjustable speed electrical power drive systems (PDS) or their elements, with respect to electrical, thermal, fire, mechanical, energy and other relevant hazards. It does not cover the driven equipment except for interface requirements. It applies to adjustable speed electrical PDS which include the power conversion, basic drive module (BDM)/complete drive module (CDM) control, and a motor or motors.

Excluded are traction and electric vehicle BDM/CDM.

It applies to low-voltage adjustable speed electrical PDS intended to feed a motor or motors from a BDM/CDM connected to phase-to-phase voltages of up to and including 1,0 kV AC (50 Hz or 60 Hz) and up to and including 1,5 kV DC. It also applies to high-voltage adjustable speed electrical PDS intended to feed a motor or motors from a BDM/CDM connected to phase-to-phase voltages of up to and including 35 kV AC (50 Hz or 60 Hz) and up to and including 52 kV DC.

This document also applies to PDS which intentionally emits or receives radio waves for the purpose of radio communication.

This document is identical with, and has been reproduced from, IEC 61800-5-1:2022, *Adjustable speed electrical power drive systems — Part 5-1: Safety requirements — Electrical, thermal and energy* and its Corrigendum No. 1 (2023) which has been added at the end of the source text.

As this document has been reproduced from an international document, the following apply:

- (a) In the source text “this part of IEC 61800” should read “this document”.
- (b) A full point substitutes for a comma when referring to a decimal marker.

Australian or Australian/New Zealand Standards that are identical adoptions of international normative references may be used interchangeably. Refer to the online catalogue for information on specific Standards.

The terms “normative” and “informative” are used in Standards to define the application of the appendices or annexes to which they apply. A “normative” appendix or annex is an integral part of a Standard, whereas an “informative” appendix or annex is only for information and guidance.

NOTES

CONTENTS

FOREWORD.....	15
INTRODUCTION.....	17
0.1 General.....	17
0.2 Feedback from industry and national committees.....	19
0.3 Requirement covered by other relevant parts of the IEC 61800 series	19
1 Scope.....	20
2 Normative references	20
3 Terms and definitions	24
4 Protection against hazards	40
4.1 General.....	40
4.2 <i>Single-fault conditions</i> and <i>abnormal operating conditions</i>	41
4.3 Short-circuit and overload protection.....	42
4.3.1 General	42
4.3.2 Input short-circuit rating and available <i>output short-circuit current</i>	43
4.3.3 Short-circuit coordination (upstream protection).....	44
4.3.4 Protection by several devices	44
4.3.5 Motor overload and overtemperature protection	45
4.3.6 <i>BDM/CDM</i> providing current limiting control.....	46
4.4 Protection against electric shock.....	46
4.4.1 General	46
4.4.2 <i>Decisive voltage class (DVC)</i>	46
4.4.3 Provision for <i>basic protection</i>	53
4.4.4 Provision for <i>fault protection</i>	56
4.4.5 Provisions for <i>enhanced protection</i>	64
4.4.6 Protective measures	65
4.4.7 <i>Insulation</i>	67
4.4.8 Compatibility with residual current-operated protective devices (RCD).....	88
4.4.9 Capacitor discharge.....	89
4.4.10 Access conditions for high-voltage sections of <i>BDM/CDM/PDS</i> (<i>interlock</i>)	89
4.5 Protection against electrical energy hazards	91
4.5.1 General	91
4.5.2 Determination of hazardous electrical energy level	92
4.5.3 Limited power sources	92
4.6 Protection against fire and thermal hazards	94
4.6.1 General	94
4.6.2 Circuits and <i>components</i> representing a fire hazard	94
4.6.3 Selection of <i>components</i> to mitigate the risk of a fire hazard	94
4.6.4 Fire protection provided by <i>enclosures</i>	95
4.6.5 Temperature limits.....	96
4.7 Protection against mechanical hazards	98
4.7.1 General	98
4.7.2 Critical torsional speed	99
4.7.3 Transient torque analysis.....	99
4.7.4 Specific requirements for liquid cooled <i>BDM/CDM/PDS</i>	99
4.7.5 Mechanical hazards from rotating parts	101
4.7.6 Sharp edges	102

4.8	<i>BDM/CDM/PDS</i> with multiple sources of supply	102
4.8.1	General	102
4.8.2	<i>Low-voltage</i> DC link sharing	103
4.9	Protection against environmental stresses	103
4.9.1	General	103
4.9.2	Protection against corrosion	105
4.10	Protection against excessive acoustic noise hazards	105
4.10.1	General	105
4.10.2	Acoustic noise level	105
4.11	Wiring and connections	106
4.11.1	General	106
4.11.2	<i>Insulation</i> of conductors	107
4.11.3	Stranded wire	109
4.11.4	Routing and clamping	109
4.11.5	Identification of conductors and terminals of <i>mains supply</i> and <i>non-mains supply</i>	109
4.11.6	Splices and connections	110
4.11.7	Accessible connections	110
4.11.8	Interconnections between parts of the <i>PDS</i>	111
4.11.9	Supply connections for <i>permanently connected BDM/CDM/PDS</i>	111
4.11.10	Supply connections for pluggable <i>BDM/CDM/PDS</i>	111
4.11.11	Terminals	113
4.11.12	Provisions for connecting the shield of shielded wire or cable	116
4.12	Mechanical requirements for <i>enclosures</i>	117
4.12.1	General	117
4.12.2	Handles and manual controls	117
4.12.3	Cast metal <i>enclosure</i>	118
4.12.4	Sheet metal <i>enclosure</i>	118
4.12.5	Stability for floor-standing <i>BDM/CDM/PDS</i>	121
4.12.6	Wiring strain relief	121
4.12.7	Polymeric <i>enclosure</i> stress relief	122
4.12.8	Internal condensation or accumulation of water	122
4.12.9	Polymeric outdoor <i>enclosure</i> ultra-violet (UV) resistance	122
4.13	<i>Components</i>	123
4.13.1	<i>Components</i> general	123
4.13.2	<i>Components</i> representing a fire hazard	123
4.13.3	<i>Components</i> being part of an <i>enclosure</i>	123
4.13.4	<i>Components</i> representing a mechanical hazard	124
4.13.5	Wound <i>components</i>	124
4.13.6	Protective devices	124
4.14	Protection against electromagnetic fields	124
5	Test requirements	124
5.1	General	124
5.1.1	Test objectives and classification	124
5.1.2	Selection of test samples	125
5.1.3	Sequence of tests	125
5.1.4	Earthing conditions	125
5.1.5	General conditions for tests	125
5.1.6	Compliance	125

5.1.7	Test overview	126
5.2	Test specifications	129
5.2.1	<i>Visual inspections (type test, routine test and sample test)</i>	129
5.2.2	Mechanical tests	129
5.2.3	Electrical tests	138
5.2.4	<i>Abnormal operation and simulated faults tests</i>	157
5.2.5	Material tests	170
5.2.6	Environmental tests (<i>type tests</i>)	174
5.2.7	Hydrostatic pressure test (<i>type test, routine test</i>)	180
5.2.8	Electromagnetic fields (EMF) test (<i>type test</i>)	181
6	Information and marking requirements	181
6.1	General	181
6.1.1	Overview	181
6.1.2	Documentation in electronic form	184
6.1.3	Installation Instructions	185
6.2	Information for selection	185
6.2.1	General	185
6.2.2	Instructions and markings pertaining to <i>accessories</i>	187
6.3	Information for installation and commissioning	187
6.3.1	General	187
6.3.2	Mechanical considerations	187
6.3.3	Environment	187
6.3.4	Handling and mounting	188
6.3.5	<i>Enclosure</i> temperature	188
6.3.6	Open type <i>BDM/CDM</i>	188
6.3.7	Connections	189
6.3.8	Commissioning	191
6.3.9	Protection requirements	191
6.3.10	Motor and driven equipment	195
6.3.11	Field installed <i>components</i>	196
6.4	Information for intended use	196
6.4.1	General	196
6.4.2	Adjustment	196
6.4.3	Labels, signs, symbols and signals	196
6.4.4	Hot surface	198
6.4.5	Control and device marking	198
6.4.6	Stability for floor-standing <i>BDM/CDM/PDS</i>	199
6.5	Supplementary information	199
6.5.1	General	199
6.5.2	Capacitor discharge	199
6.5.3	Special operation mode – Auto restart/bypass connection	200
6.5.4	Other hazards	200
6.5.5	<i>BDM/CDM/PDS</i> with multiple sources of supply	200
6.5.6	PT/CT connection	200
6.5.7	Access conditions for <i>high-voltage BDM/CDM/PDS</i> during maintenance	200
Annex A (normative)	Additional information for protection against electric shock	202
A.1	General	202
A.2	Protection by means of <i>DVC As</i>	202
A.3	Protection by means of <i>protective impedance</i>	203

A.4	Protection by using limited voltages	204
A.5	Evaluation of the <i>working voltage</i> of circuits.....	204
A.5.1	General	204
A.5.2	Classification of the <i>working voltage</i>	205
A.5.3	AC <i>working voltage</i>	205
A.5.4	DC <i>working voltage</i>	206
A.5.5	Pulsating <i>working voltage</i>	207
A.6	The concept of protective measures according to 4.4.....	208
A.6.1	General	208
A.6.2	General concept of protection against electric shock	209
A.6.3	Examples of the use of elements of protective measures	210
Annex B (informative)	Considerations for the reduction of the pollution degree	215
B.1	General.....	215
B.2	Factors influencing the pollution degree	215
B.3	Reduction of influencing factors	215
Annex C (informative)	Symbols referred.....	216
C.1	Symbols used	216
C.2	Determination of contrast	218
Annex D (normative)	Evaluation of <i>clearance</i> and <i>creepage distances</i>	219
D.1	Measurement.....	219
D.2	Relationship of measurement to pollution degree	219
D.3	Examples	219
Annex E (normative)	Altitude correction for <i>clearances</i>	226
E.1	Correction factor for <i>clearances</i> at altitudes above 2 000 m	226
E.2	Test voltages for verifying <i>clearances</i> at different altitudes	226
Annex F (normative)	<i>Clearance</i> and <i>creepage distance</i> determination for frequencies greater than 30 kHz	228
F.1	General influence of the frequency on the withstand characteristics.....	228
F.2	<i>Clearance</i>	228
F.2.1	General	228
F.2.2	<i>Clearance</i> for inhomogenous fields	229
F.2.3	<i>Clearance</i> for approximately homogenous fields	230
F.3	<i>Creepage distance</i>	231
F.4	<i>Solid insulation</i>	232
F.4.1	General	232
F.4.2	Approximately uniform field distribution without air gaps or voids.....	232
F.4.3	Other cases	233
Annex G (informative)	Cross-sections of round conductors	234
Annex H (informative)	Guidelines for RCD compatibility	235
H.1	Selection of RCD type.....	235
H.2	Fault current waveforms.....	236
Annex I (informative)	Examples of overvoltage category reduction	240
I.1	General.....	240
I.2	<i>Protection to the surroundings</i> (see 4.4.7.2).....	240
I.2.1	Circuits connected directly to <i>mains supply</i> (see 4.4.7.2.3).....	240
I.2.2	Circuits connected to the <i>non-mains supply</i> (see 4.4.7.2.4)	243
I.2.3	<i>Insulation</i> between circuits (see 4.4.7.2.5)	243
I.3	<i>Functional insulation</i> (see 4.4.7.3)	244

I.4	Further examples	244
Annex J (informative)	Burn thresholds for touchable surfaces	246
J.1	General.....	246
J.2	Burn thresholds	246
Annex K (informative)	Table of electrochemical potentials	249
Annex L (informative)	Measuring instrument for touch current measurements	250
L.1	Measuring test circuit.....	250
L.2	Requirements for measuring instruments	250
Annex M (normative)	Test probes for determining access	251
Annex N (informative)	Guidance regarding short-circuit current	254
Annex O (informative)	Guidance for determination of <i>clearance</i> and <i>creepage distance</i>	255
O.1	Guideline for determination of <i>clearance</i>	255
O.2	Guideline for determination of <i>creepage distance</i>	256
O.3	Minimum <i>clearance</i> and <i>creepage distances</i> for material	257
Annex P (normative)	Protection of persons against electromagnetic fields for frequencies from 0 Hz up to 300 GHz	258
P.1	General influence of electromagnetic fields to persons.....	258
P.1.1	General	258
P.1.2	Low-frequency electric field effects (1 Hz to 100 kHz).....	258
P.1.3	Low-frequency magnetic field effects (1 Hz to 100 kHz).....	258
P.1.4	Low-frequency electric and magnetic field effects	258
P.1.5	High-frequency electromagnetic field effects (100 kHz to 300 GHz)	258
P.1.6	Current knowledge on low-level effects.....	259
P.1.7	Biological effects versus adverse health effects	259
P.1.8	Influence of EMF on passive and active medical implants	259
P.2	Recommendations from ICNIRP Guidelines against exposure to EMF.....	259
P.2.1	Adoption of exposure limits from ICNIRP	259
P.2.2	Limits of EMF exposure for transportation and storage	261
P.3	Protection of persons against exposure of EMF	261
P.3.1	General	261
P.3.2	EMF requirements for general public access areas.....	262
P.3.3	EMF requirements for <i>general-access areas</i> , <i>service-access areas</i> and <i>restricted-access areas</i>	262
P.3.4	EMF requirements for transportation and storage	262
P.4	Electromagnetic fields (EMF) test (<i>type test</i>).....	263
P.4.1	General test set up for EMF	263
P.4.2	EMF test.....	263
P.5	Electromagnetic fields (EMF) marking	263
Annex Q (informative)	Automatic disconnection of supply	264
Q.1	Maximum disconnection times	264
Q.2	Supplementary <i>protective equipotential bonding</i>	265
Annex R (informative)	Risk assessment according to IEC Guide 116	266
R.1	General.....	266
R.2	Risk assessment.....	266
Annex S (informative)	In-some-country requirements – United States of America voltages less than 1,5 kV AC or DC	268
S.0	General.....	268
S.1	Scope	268

S.2	Normative references.....	268
S.3	Terms and definitions.....	268
S.4	Protection against hazards.....	269
S.4.1	General	269
S.4.2	<i>Single-fault conditions</i> and <i>abnormal operating condition</i>	269
S.4.3	Short-circuit and overload protection	269
S.4.4	Protection against electric shock	271
S.4.5	Protection against electrical energy hazards.....	281
S.4.6	Protection against fire and thermal hazards.....	281
S.4.7	Protection against mechanical hazards.....	282
S.4.8	<i>BDM/CDM/PDS</i> with multiple sources of supply	284
S.4.9	Protection against environmental stresses.....	284
S.4.10	Protection against excessive acoustic noise hazards	284
S.4.11	Wiring and connections	284
S.4.12	Mechanical requirements for <i>enclosures</i>	294
S.4.200	Auxiliary device	306
S.4.201	<i>Accessories</i>	306
S.4.202	Provisions for mounting	306
S.4.203	Capacitors	306
S.5	Test requirements.....	307
S.5.1	General	307
S.5.2	Test specifications	308
S.6	Information and marking requirements	328
S.6.1	General	328
S.6.2	Information for selection	328
S.6.3	Information for installation and commissioning.....	329
S.6.4	Information for intended use	333
S.6.5	Supplementary information	333
S.200	Evaluation of clearance and <i>creepage distances</i>	334
S.200.1	<i>Clearance</i> and <i>creepage distances</i>	335
S.201	Normative references and component standards.....	337
S.202	IEC to USA standard references	340
S.203	Isolated secondary circuits and circuits supplied by battery	343
S.203.1	Isolated secondary circuits	343
S.203.2	Secondary circuits test	349
S.203.3	Circuits supplied by a battery.....	351
S.204	Full-load motor-running currents	351
Annex T (informative)	In-some-country requirements – Canada voltages up to 34,5 kV.....	354
T.0	General.....	354
T.1	Scope	354
T.2	Normative references.....	354
T.3	Terms and definitions.....	356
T.4	Protection against hazards.....	357
T.4.1	General	357
T.4.2	<i>Single-fault conditions</i> and <i>abnormal operating condition</i>	357
T.4.3	Short-circuit and overload protection	357
T.4.4	Protection against electric shock	358
T.4.5	Protection against electrical energy hazards.....	367
T.4.6	Protection against fire and thermal hazards	368

T.4.7	Protection against mechanical hazards	369
T.4.8	<i>BDM/CDM/PDS</i> with multiple sources of supply	369
T.4.9	Protection against environmental stresses	369
T.4.10	Protection against excessive acoustic noise hazards	369
T.4.11	Wiring and connections	369
T.4.12	Mechanical requirements for <i>enclosures</i>	382
T.4.13	<i>Components</i>	386
T.4.14	Protection against electromagnetic fields	391
T.5	Test requirements	391
T.5.1	General	391
T.5.2	Test specifications	391
T.6	Information and marking requirements	416
T.6.1	General	416
T.6.2	Information for selection	418
T.6.3	Information for installation and commissioning	419
T.6.4	Information for intended use	421
T.6.5	Supplementary information	423
T.200	IEC normative references replaced by CSA standards	423
	Bibliography	426
	Figure 1 – <i>PDS</i> hardware configuration within an <i>installation</i>	35
	Figure 2 – Time-voltage zones for <i>DVC A</i> s and <i>DVC B</i> circuits – DC	50
	Figure 3 – Time-voltage zones for <i>DVC A</i> s and <i>DVC B</i> circuits – AC peak	51
	Figure 4 – Time-voltage zones for conductive <i>accessible parts</i>	52
	Figure 5 – Example of a <i>protective class I BDM/CDM</i> arrangement and its associated <i>protective equipotential bonding</i>	58
	Figure 6 – Example of a <i>protective class I BDM/CDM</i> arrangement and its associated <i>protective equipotential bonding</i> through direct metallic contact	59
	Figure 7 – Example for interconnections within <i>BDM/CDM</i> and between parts of the <i>PDS</i>	106
	Figure 8 – Example for interconnections between parts of the <i>PDS</i> (<i>BDM/CDM</i> parts separated by field wiring)	107
	Figure 9 – Example arrangement of insulated conductors in a cable	108
	Figure 10 – Detachable <i>mains supply</i> cords and connections	112
	Figure 11 – Wire bending space	116
	Figure 12 – Supported and unsupported <i>enclosure</i> parts	119
	Figure 13 – Impact test using a steel ball	135
	Figure 14 – Voltage test procedures	146
	Figure 15 – Partial discharge test procedure	148
	Figure 16 – Electric strength test instrument	154
	Figure 17 – Mandrel	155
	Figure 18 – Initial position of mandrel	155
	Figure 19 – Final position of mandrel	155
	Figure 20 – Position of metal foil on insulating material	156
	Figure 21 – <i>Protective equipotential bonding</i> test set up	160
	Figure 22 – Example of short-circuit test between <i>BDM/CDM</i> motor power port and <i>protective earth</i> (motor separately earthed)	162

Figure 23 – Example of short-circuit test between <i>BDM/CDM</i> motor power <i>port</i> and <i>protective earth</i> (motor earthed through <i>BDM/CDM</i>).....	162
Figure 24 – Example of short-circuit test between <i>BDM/CDM</i> DC link power <i>port</i> and <i>protective earth</i>	163
Figure 25 – Interpolated values for Table 37	165
Figure 26 – Circuit for high-current arcing test	171
Figure 27 – Test fixture for hot-wire ignition test	172
Figure A.1 – Protection by <i>DVC</i> As with <i>enhanced protection</i>	202
Figure A.2 – Protection by means of <i>protective impedance</i>	203
Figure A.3 – Protection by using limited voltages	204
Figure A.4 – Typical waveform for AC <i>working voltage</i>	205
Figure A.5 – Typical waveform for DC <i>working voltage</i>	206
Figure A.6 – Typical waveform for pulsating <i>working voltage</i>	207
Figure A.7 – Protective measures according to 4.4.1 to 4.4.5 for protection against electric shock considering <i>protective class I</i> and <i>protective class II BDM/CDM/PDS</i>	209
Figure A.8 – Protective measures according to 4.4.1 to 4.4.5 for protection against electric shock considering <i>protective class III BDM/CDM/PDS</i> and <i>DVC</i> As circuits	210
Figure D.1 – Example of measurements including a groove	220
Figure D.2 – Example of measurements including a groove	220
Figure D.3 – Example of measurements including a groove	220
Figure D.4 – Example of measurements including a rib.....	220
Figure D.5 – Example of measurements providing protection of type 2.....	221
Figure D.6 – Example of measurements providing protection of type 1.....	221
Figure D.7 – Example of measurements providing protection of type 1.....	221
Figure D.8 – Example of measurements providing protection of type 1.....	222
Figure D.9 – Example of measurements including a barrier (cemented joint).....	222
Figure D.10 – Example of measurements including a barrier.....	222
Figure D.11 – Example of measurements including a gap	223
Figure D.12 – Example of measurements including a gap	223
Figure D.13 – Example of measurements including an floating conductive part.....	224
Figure D.14 – Example of measurements in inner layer of PWB.....	224
Figure D.15 – Example of measurements in an <i>enclosure</i> of insulating material.....	225
Figure F.1 – Diagram for dimensioning of <i>clearances</i> above 30 kHz	229
Figure F.2 – Diagram for dimensioning of <i>creepage distances</i> above 30 kHz	231
Figure F.3 – Permissible field strength for dimensioning of <i>solid insulation</i> according to Formula (F.1).....	233
Figure H.1 – Flow chart leading to selection of the RCD type upstream of a <i>PDS</i>	235
Figure H.2 – Symbols for marking depending on the type of RCD	236
Figure H.3 – Fault current waveforms in connections with <i>BDM/CDM/PDS</i>	239
Figure I.1 – <i>Basic protection</i> evaluation for circuits connected to the origin of the <i>installation mains supply</i>	240
Figure I.2 – <i>Basic protection</i> evaluation for circuits connected to the <i>mains supply</i>	241
Figure I.3 – <i>Basic protection</i> evaluation for single and three phase <i>BDM/CDM/PDS</i> not permanently connected to the <i>mains supply</i>	241
Figure I.4 – <i>Basic protection</i> evaluation for circuits connected to the origin of the <i>installation mains supply</i> where internal SPDs are used.....	241

Figure I.5 – <i>Basic protection</i> evaluation for circuits connected to the <i>mains supply</i> where internal SPDs are used	242
Figure I.6 – Example of <i>enhanced protection</i> evaluation for circuits connected to the <i>mains supply</i> where internal SPDs are used	242
Figure I.7 – Example of <i>enhanced protection</i> evaluation for circuits connected to the <i>mains supply</i> where internal SPDs are used	242
Figure I.8 – Example of <i>enhanced protection</i> evaluation for circuits connected to the <i>mains supply</i> where internal SPDs are used	243
Figure I.9 – <i>Basic protection</i> evaluation for circuits connected to the <i>non-mains supply</i>	243
Figure I.10 – <i>Basic protection</i> evaluation for circuits connected to the origin of the <i>installation non-mains supply</i>	243
Figure I.11 – <i>Functional insulation</i> evaluation within circuits affected by external transients	244
Figure I.12 – <i>Basic protection</i> evaluation for circuits connected to the <i>mains supply</i> and a non-mains circuit	244
Figure I.13 – <i>Insulation</i> evaluation for <i>accessible circuit</i> of DVC As	245
Figure J.1 – Burn threshold spread when the skin is in contact with a hot smooth surface made of bare (uncoated) metal	246
Figure J.2 – Rise in the burn threshold spread from Figure J.1 for metals which are coated by shellac varnish of a thickness of 50 µm, 100 µm and 150 µm	247
Figure J.3 – Rise in the burn threshold spread from Figure J.1 for metals coated with the specific materials	247
Figure J.4 – Burn threshold spread when the skin is in contact with a hot smooth surface made of ceramics, glass and stone materials	248
Figure J.5 – Burn threshold spread when the skin is in contact with a hot smooth surface made of plastics	248
Figure L.1 – Measuring test circuit	250
Figure M.1 – Sphere 50 mm probe according to IEC 61032:1997, test probe A	251
Figure M.2 – Jointed test finger according to IEC 61032:1997, test probe B	252
Figure M.3 – Test rod 2,5 mm according to IEC 61032:1997, test probe C	253
Figure M.4 – Sphere 12,5 mm test probe according to IEC 61032:1997, test probe 2	253
Figure O.1 – Flowchart <i>clearance</i>	255
Figure O.2 – Flowchart <i>creepage distance</i>	256
Figure S.1 – Articulate probe with web stop	298
Figure S.2 – Determination of current for circuits of 10 000 A and less	318
Figure S.3 – Peak let-through current	322
Figure S.4 – Application of Simpson's rule to fuse current oscillogram to obtain let-through I^2t	323
Figure S.5 – Clamped joint	334
Figure T.1 – Routing conductors through a metal barrier	376
Figure T.2 – Wire bending space	381
Figure T.3 – Test circuit using Formula T.1	400
Figure T.4 – Test circuit using Formula T.2	401
Figure T.5 – Test circuit using Formula T.3	401
Figure T.6 – Test circuit using Formula T.4	402
Figure T.7 – Typical test set sensitivity	403
Figure T.8 – Determination of current and power factor for circuits of 10 000 A and less	412

Table 1 – Alphabetical list of terms	25
Table 2 – Voltage limits for the <i>decisive voltage classes</i>	49
Table 3 – Protection requirements for circuits under consideration	53
Table 4 – <i>PE conductor</i> cross-section	60
Table 5 – Definitions of pollution degrees	68
Table 6 – <i>Impulse withstand voltage</i> and <i>temporary overvoltage</i> versus <i>system voltage</i> for <i>low-voltage</i> circuits	71
Table 7 – <i>Impulse withstand voltage</i> and <i>temporary overvoltage</i> versus <i>system voltage</i> for high-voltage circuits	71
Table 8 – <i>Clearance</i> for <i>functional insulation</i> , <i>basic insulation</i> or <i>supplementary insulation</i>	76
Table 9 – Insulating materials classification	79
Table 10 – <i>Creepage distances</i>	80
Table 11 – <i>Insulation</i> material requirements	83
Table 12 – Distance to uninsulated <i>live parts</i> for consideration of HWI, HAI and CTI	83
Table 13 – Generic materials for <i>insulation</i> material	84
Table 14 – Requirements based on thin sheet material thickness	85
Table 15 – Limits for power sources without an <i>overcurrent</i> protective device	93
Table 16 – Limits for power sources with an <i>overcurrent</i> protective device	93
Table 17 – Maximum measured temperatures for internal materials and <i>components</i>	96
Table 18 – Maximum measured temperatures for <i>accessible parts</i> of <i>BDM/CDM/PDS</i>	98
Table 19 – Minimum tubing wall thickness	100
Table 20 – Environmental service conditions	104
Table 21 – Wire bending space from terminals to <i>enclosure</i>	115
Table 22 – Thickness of sheet metal for <i>enclosures</i> : carbon steel or stainless steel	120
Table 23 – Thickness of sheet metal for <i>enclosures</i> : aluminium, copper or brass	121
Table 24 – Environmental conditions for tests	126
Table 25 – Test overview	127
Table 26 – Pull values for handles and manual control securement	136
Table 27 – Values for physical tests on strain relief of <i>enclosure</i>	137
Table 28 – <i>Impulse withstand voltage</i> test	139
Table 29 – <i>Impulse withstand voltage</i> test voltage for <i>low-voltage BDM/CDM/PDS</i>	140
Table 30 – <i>Impulse withstand voltage</i> test voltage for <i>high-voltage BDM/CDM/PDS</i>	141
Table 31 – AC or DC test voltage for circuits connected directly to <i>low-voltage mains supply</i>	143
Table 32 – AC or DC test voltage for circuits connected directly to <i>high-voltage mains supply</i>	143
Table 33 – AC or DC test voltage for circuits connected to <i>non-mains supply</i> without <i>temporary overvoltages</i>	144
Table 34 – Parameter for <i>BDM/CDM/PDS</i> AC or DC voltage test	147
Table 35 – Partial discharge test	148
Table 36 – <i>Prospective short-circuit current</i> for test vs <i>BDM/CDM</i> rated input current	158
Table 37 – Maximum tripping time for <i>electronic motor overload protection</i> test	164
Table 38 – Environmental tests	164

Table 39 – Preconditioning or recovery procedure for climatic tests (<i>type test</i>)	176
Table 40 – Dry heat test (steady state) (<i>type test</i>)	176
Table 41 – Cold test (<i>type test</i>)	177
Table 42 – Damp heat test (steady state) (<i>type test</i>)	177
Table 43 – Damp heat test (cyclic) (<i>type test</i>)	178
Table 44 – Vibration test	179
Table 45 – Salt mist test	179
Table 46 – Dust test	180
Table 47 – Sand test	180
Table 48 – Marking location	182
Table A.1 – Configurations for protection against electric shock	212
Table C.1 – Symbols used	216
Table D.1 – Width of grooves by pollution degree	219
Table E.1 – Correction factor for <i>clearances</i> at altitudes between 2 000 m and 20 000 m	226
Table E.2 – Test voltages for verifying <i>clearances</i> at different altitudes	227
Table F.1 – Minimum values of <i>clearances</i> in air at atmospheric pressure for inhomogeneous field conditions	230
Table F.2 – Multiplication factors for <i>clearances</i> in air at atmospheric pressure for approximately homogeneous field conditions	230
Table F.3 – Minimum values of <i>creepage distances</i> for different frequency ranges	232
Table G.1 – Standard cross-sections of round conductors	234
Table K.1 – Table of electrochemical potentials	249
Table O.1 – Minimum <i>clearance</i> and <i>creepage distances</i> for material	257
Table P.1 – Limits of EMF for general public exposure	260
Table P.2 – Limits of EMF for occupational exposure	261
Table P.3 – Limits for magnetic flux density of static magnetic fields	261
Table P.4 – EMF test overview	263
Table 41.1 – Maximum disconnection times	264
Table R.1 – Risk assessment	266
Table S.1 – Size of bonding conductor	273
Table S.2 – Duration of current flow for bonding-conductor test	273
Table S.3 – Bonding conductor short-circuit test capacity	273
Table S.4 – Maximum rating of <i>overcurrent</i> device	275
Table S.5 – Dimensions of bushings	277
Table S.6 – <i>BDM/CDM/PDS</i> intended for installation in a feeder circuit	277
Table S.7 – <i>Generic materials for barriers</i>	279
Table S.8 – Tubing wall thickness	283
Table S.9 – Ampacity of flexible cord	286
Table S.10 – Ampacities of insulated conductors	289
Table S.11 – Wire bending space at the terminals of enclosed power conversion equipment	291
Table S.12 – <i>Overcurrent</i> protective device	292
Table S.13 – Branch-circuit <i>short-circuit protective device</i>	293

Table S.14 – Openings in <i>enclosures</i>	299
Table S.15 – Addition to Table 3 of UL 50:2015: Thickness of sheet metal for <i>enclosures</i> – Carbon steel or stainless steel	301
Table S.16 – Addition to Table 4 of UL 50:2015: Thickness of sheet metal for <i>enclosures</i> – Aluminum, copper or brass	301
Table S.17 – Dimensions of knockout	304
Table S.18 – Values of voltage for tests	307
Table S.19 – AC or DC voltage test voltages	310
Table S.20 – Width of copper bus bars	311
Table S.21 – Production-line test conditions	312
Table S.22 – Power factor of test circuits for devices rated 600 V or less	326
Table S.23 – Minimum <i>clearances</i> and <i>creepage distances</i> at <i>field wiring terminals</i> up to 600 V	335
Table S.24 – Minimum <i>clearances</i> and <i>creepage distances</i> for <i>field wiring terminals</i> over 600 V	336
Table S.25 – <i>Clearances</i> and <i>creepage distances</i> at <i>field wiring terminals</i> for pollution degree 2 environments	337
Table S.26 – IEC normative reference standards that do not apply	341
Table S.27 – IEC normative references replaced by USA standards	342
Table S.28 – Secondary circuits, differences in evaluation	344
Table S.29 – Full-load motor-running currents in amperes corresponding to various AC horsepower ratings	352
Table S.30 – Full-load motor-running currents in amperes corresponding to various DC horsepower ratings	353
Table T.1 – Size and number of bonding conductors per termination	359
Table T.2 – Size of bonding conductor	359
Table T.3 – Minimum <i>clearance</i> and <i>creepage distances</i> on <i>field wiring terminals</i>	361
Table T.4 – Dimensions of bushings	362
Table T.5 – Test voltages for verifying <i>clearances</i>	365
Table T.6 – Test voltages for verifying <i>clearances</i> using AC RMS	365
Table T.7 – Generic material acceptable as a barrier	366
Table T.8 – Allowable ampacities of insulated copper conductors inside industrial control equipment <i>enclosures</i> (based on a <i>ambient temperature</i> of 40 °C)	370
Table T.9 – Ampacity correction factors for multiple conductor groupings	370
Table T.10 – Wiring space	371
Table T.11 – Wire-bending space	372
Table T.12 – Full-load motor-running currents in amperes corresponding to AC horsepower ratings	373
Table T.13 – Full-load motor-running currents in amperes corresponding to DC horsepower ratings	374
Table T.14 – Wire-bending space	376
Table T.15 – Test values for <i>BDM/CDM/PDS</i> wiring terminals	378
Table T.16 – Ampacity of conductors based on resistor duty cycle ratings	379
Table T.17 – Thickness of sheet metal for <i>enclosures</i> – Carbon steel or stainless steel	383
Table T.18 – Thickness of sheet metal for <i>enclosures</i> – Aluminum, copper, or brass	384
Table T.19 – Maximum acceptable rating of primary <i>overcurrent</i> device	388

Table T.20 – Minimum acceptable rating of secondary <i>overcurrent</i> device	388
Table T.21 – <i>Overcurrent</i> protective device – Copper conductors	389
Table T.22 – <i>High-Voltage BDM/CDM/PDS</i> dielectric strength test values, kV.....	391
Table T.23 – Tightening torque for testing conduit hubs of polymeric <i>enclosures</i>	394
Table T.24 – Bending moment	394
Table T.25 – Test circuit sensitivity formulas.....	400
Table T.26 – Ampacities of insulated conductors	405
Table T.27 – Size of copper busbar connections for temperature test	406
Table T.28 – Short-circuit test values.....	407
Table T.29 – Short-circuit power factor	411
Table T.30 – Translation of markings	416
Table T.31 – IEC normative references replaced by CSA standards.....	423

INTERNATIONAL ELECTROTECHNICAL COMMISSION

ADJUSTABLE SPEED ELECTRICAL POWER DRIVE SYSTEMS –**Part 5-1: Safety requirements – Electrical, thermal and energy**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

IEC 61800-5-1 has been prepared by subcommittee 22G: Adjustable speed electric power drive systems (PDS), of IEC technical committee 22: Power electronic systems and equipment. It is an International Standard.

This third edition cancels and replaces the second edition published in 2007 and Amendment 1:2016. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) harmonization with IEC 62477-1:2022;
- b) harmonization with UL 61800-5-1 and CSA C22.2 No. 274, including an annex with a list of national deviation which was considered not possible to harmonize within a reasonable timeframe;
- c) more detailed information about the evaluation of components according to this document and relevant safety component standards;
- d) updated requirement for mechanical hazards including multiple IP ratings.

The text of this International Standard is based on the following documents:

Draft	Report on voting
22G/455/FDIS	22G/457/RVD

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/publications.

In this document, terms in *italic* are defined in Clause 3.

The reader's attention is drawn to the fact that

- Annex S and Annex T list all of the "in-some-country" clauses on differing practices of a less permanent nature relating to the subject of this document.
- Due to the rules of ISO/IEC Directives, Part 2, the term "must" instead of the term "shall" is used in Annex S and Annex T.

A list of all parts of the IEC 61800 series, published under the general title *Adjustable speed electrical power drive systems*, is available on the IEC website.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

IMPORTANT – The "colour inside" logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this publication using a colour printer.

The contents of the corrigendum 1 (2023-09) have been included in this copy.

INTRODUCTION

0.1 General

This document contains the revision of IEC 61800-5-1:2007 and IEC 61800-5-1:2007/AMD1:2016.

Several important issues have influenced the scope and the chosen approach of the maintenance of IEC 61800-5-1:2007 in the development of this document.

The most significant changes compared to IEC 61800-5-1:2007 are the following.

a) Structure and content is based on IEC 62477-1 considering modifications and new topics such as the following

- Clause 1: Scope updated to include radio emitting/transmitting *BDM/CDM/PDS*.
- 4.1, 5.1, 6.1: "Intended use" included.
- 4.2: Single fault/abnormal operation analysis (significantly reworked).
- 4.3: Short-circuit and overload protection included as new subclause.
- 4.4 and Annex A: Protection against electric shock updated according to IEC 61140:2016 and IEC 60364-4-41, including insulation coordination according to IEC 60664 (all parts) considering the following:
 - 4.4.2 – Decisive voltage classification (especially DVC As for dry, wet and salt-water wet); Table 2 and Table 3 reworked;
 - 4.4.3 – Basic protection (reworked);
 - 4.4.4 – Fault protection (reworked);
 - 4.4.5 – Enhanced protection (reworked);
 - 4.4.7 – Insulation (reworked):
 - 4.4.7.1.2 – Working voltage (new);
 - 4.4.7.1.8 – Components bridging insulation (new);
 - 4.4.7.7 – *clearance* and *creepage distances* for functional insulation on PWB and component assemblies (reworked);
 - 4.4.7.8 – Solid insulation (new/reworked);
 - 4.4.7.9 – Connection of parts of solid insulation (cemented joints) (new);
 - 4.4.8/Annex H – Compatibility with RCD (reworked);
 - 4.4.10 – Access conditions for *high-voltage PDS* (new).
- 4.5: Protection against energy hazards (new).
- 4.6: Protection against fire and thermal hazards (new).
- 4.7: Protection against mechanical hazards (new).
- 4.8: *BDM/CDM/PDS* with multiple sources of supply (new).
- 4.9: Protection against environmental stresses (new) (in alignment with IEC 61800-2).
- 4.11: Wiring and connections updated (significantly reworked).
- 4.12: Enclosure updated (significantly reworked).
- 4.13 Bibliography: Evaluation of components (new).
- 4.14 Annex P: Protection against electromagnetic fields (new).
- Clause 5: Updated with some additional/modified test requirement:
 - 5.2.2.2 – Non-accessibility test (significantly reworked);
 - 5.2.2.3 – Ingress protection test (IP rating) (significantly reworked);

- 5.2.2.4 – Enclosure integrity tests (new);
- 5.2.2.5 – Wall or ceiling mounted *BDM/CDM/PDS* test (new);
- 5.2.2.6 – Handles and manual control securement test (new);
- 5.2.2.7 – Strain relief test (new);
- 5.2.3.7 – Touch current measurement test (reworked);
- 5.2.3.9 – Limited power source (new);
- 5.2.3.11 – Protective equipotential bonding test (new);
- 5.2.3.12 – Input test (new);
- 5.2.3.13 – Thin sheet material test (new);
- 5.2.3.14 – Test procedure for determination of working voltage (new);
- 5.2.3.16 – Preconditioning of material (reworked);
- 5.2.4.4 – Protective equipotential bonding short-circuit test (new);
- 5.2.4.9 – Output overload test (new);
- 5.2.4.13.5 – Covering of openings for cooling air test (type test) (new);
- 5.2.5.6 – Cemented joints test (new);
- 5.2.7 – Hydrostatic pressure test (new);
- 5.2.8 – Electromagnetic fields (EMF) test (new).
- Clause 6: – Update with more specific marking.
 - Structure aligned with IEC 62477-1 as close as possible;
 - Table 48 simplified.
- Annex A – Additional information for protection against electric shock (reworked).
- Annex C – Symbols referred (reworked).
- Annex E – Altitude correction for *clearances* (reworked).
- Annex F – *Clearance* and *creepage distance* determination for frequencies greater than 30 kHz (reworked).
- Annex H – Guidelines for RCD compatibility (reworked).
- Annex M – Test probes for determining access (new).
- Annex O – Guidance for determination of *clearance* and *creepage distance* (new).
- Annex P – Protection of persons against electromagnetic fields for frequencies from 0 Hz up to 300 GHz (new).
- Annex Q – Automatic disconnection of supply (new).
- Annex R – Guide 116 risk evaluation included (new).
- Bibliography – Relevant component safety standards (new).

b) Harmonization with UL 61800-5-1

Complete document is modified taken into consideration UL 61800-5-1 US National deviations. US National deviations from UL 61800-5-1 not possible to harmonize have been placed in Annex S.

c) Harmonization with CSA C22.2 No. 274

- Due to a short time frame, only some few topics have been harmonized.
- Canadian National deviations from CSA C22.2 No. 274 not possible to harmonize have been placed in Annex T.

d) Harmonization with UL 347A

- Some few relevant topics have been harmonized considering safety aspects related to *high-voltage BDM/CDM/PDS*.

Further harmonization is expected to be adopted in IEC 61800-5-1 considering the content of UL 61800-5-1, CSA C22.2 No 274 and UL 347A in future editions of IEC 61800-5-1.

0.2 Feedback from industry and national committees

The use of IEC 61800-5-1:2007 by manufacturers and test institutes since its release has identified several topics which are considered useful to implement, or topics which need further information for a better understanding of the intent of the specific requirement. These topics are also implemented in this document.

0.3 Requirement covered by other relevant parts of the IEC 61800 series

- general requirements for DC *power drive systems* are covered in IEC 61800-1;
- general requirements for AC *power drive systems* are covered in IEC 61800-2;
- EMC aspects are covered in IEC 61800-3;
- functional safety aspects are covered in IEC 61800-5-2;
- functional safety aspects for encoders are covered in IEC 61800-5-3;
- type of load duty aspects are covered in IEC TR 61800-6;
- communication profiles aspects are covered in IEC 61800-7 (all parts);
- *power interface* voltage aspects are covered in IEC TS 61800-8;
- ecodesign aspects are covered in IEC 61800-9 (all parts);

The following document is not part of the IEC 61800 series, but is used often as part of the BDM:

- active infeed converters in IEC TS 62578.

ADJUSTABLE SPEED ELECTRICAL POWER DRIVE SYSTEMS –

Part 5-1: Safety requirements – Electrical, thermal and energy

1 Scope

This part of IEC 61800 specifies requirements for adjustable speed electrical *power drive systems (PDS)* or their elements, with respect to electrical, thermal, fire, mechanical, energy and other relevant hazards. It does not cover the driven equipment except for interface requirements. It applies to adjustable speed electrical *PDS* which include the power conversion, *basic drive module (BDM)/complete drive module (CDM)* control, and a motor or motors.

Excluded are traction and electric vehicle *BDM/CDM*.

It applies to low-voltage adjustable speed electrical *PDS* intended to feed a motor or motors from a *BDM/CDM* connected to phase-to-phase voltages of up to and including 1,0 kV AC (50 Hz or 60 Hz) and up to and including 1,5 kV DC.

It also applies to high-voltage adjustable speed electrical *PDS* intended to feed a motor or motors from a *BDM/CDM* connected to phase-to-phase voltages of up to and including 35 kV AC (50 Hz or 60 Hz) and up to and including 52 kV DC.

NOTE 1 At the time of publication of this document, the technical upper voltage limit for DC motors is 2,25 kV DC.

NOTE 2 Above voltage and frequency limits reflect the scope of IEC 61800-1 and IEC 61800-2.

NOTE 3 For adjustable speed electrical *PDS* not covered by the scope of this document, applicable requirements of other standards, for example IEC 62477-1 and IEC 62477-2, can be used.

This document also applies to *PDS* which intentionally emit or receive radio waves for the purpose of radio communication.

Motors for driven equipment (see Figure 1) are covered by IEC 60034 (all parts).

NOTE 4 In some cases, safety requirements of the *PDS* (for example, protection against access to hazardous parts) can necessitate the use of special components and/or additional measures.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60034 (all parts), *Rotating electrical machines*

IEC 60034-1:2022, *Rotating electrical machines – Part 1: Rating and performance*

IEC 60034-5:2020, *Rotating electrical machines – Part 5: Degrees of protection provided by the integral design of rotating electrical machines (IP code) – Classification*

IEC 60050-112, *International Electrotechnical Vocabulary (IEV) – Part 112: Quantities and units* (available at www.electropedia.org)

IEC 60050-113, *International Electrotechnical Vocabulary (IEV) – Part 113: Physics for electrotechnology* (available at www.electropedia.org)

IEC 60050-114, *International Electrotechnical Vocabulary (IEV) – Part 114: Electrochemistry* (available at www.electropedia.org)

IEC 60050-131, *International Electrotechnical Vocabulary (IEV) – Part 131: Circuit theory* (available at www.electropedia.org)

IEC 60050-151, *International Electrotechnical Vocabulary (IEV) – Part 151: Electrical and magnetic devices* (available at www.electropedia.org)

IEC 60050-161, *International Electrotechnical Vocabulary (IEV) – Part 161: Electromagnetic compatibility* (available at www.electropedia.org)

IEC 60050-192, *International Electrotechnical Vocabulary (IEV) – Part 192: Dependability* (available at www.electropedia.org)

IEC 60050-426, *International Electrotechnical Vocabulary (IEV) – Part 426: Explosive atmospheres* (available at www.electropedia.org)

IEC 60050-441, *International Electrotechnical Vocabulary (IEV) – Part 441: Switchgear, controlgear and fuses* (available at www.electropedia.org)

IEC 60050-442, *International Electrotechnical Vocabulary (IEV) – Part 442: Electrical accessories* (available at www.electropedia.org)

IEC 60050-551, *International Electrotechnical Vocabulary (IEV) – Part 551: Power electronics* (available at www.electropedia.org)

IEC 60050-601, *International Electrotechnical Vocabulary (IEV) – Part 601: Generation, transmission and distribution of electricity – General* (available at www.electropedia.org)

IEC 60050-826, *International Electrotechnical Vocabulary (IEV) – Part 826: Electrical installations* (available at www.electropedia.org)

IEC 60050-903, *International Electrotechnical Vocabulary (IEV) – Part 903: Risk assessment* (available at www.electropedia.org)

IEC 60068-2-1:2007, *Environmental testing – Part 2-1: Tests – Test A: Cold*

IEC 60068-2-2:2007, *Environmental testing – Part 2-2: Tests – Test B: Dry heat*

IEC 60068-2-6:2007, *Environmental testing – Part 2-6: Tests – Test Fc: Vibration (sinusoidal)*

IEC 60068-2-30:2005, *Environmental testing – Part 2-30: Tests – Test Db: Damp heat, cyclic (12 h + 12 h cycle)*

IEC 60068-2-52:2017, *Environmental testing – Part 2-52: Tests – Test Kb: Salt mist, cyclic (sodium chloride solution)*

IEC 60068-2-68:1994, *Environmental testing – Part 2-68: Tests – Test L: Dust and sand*

IEC 60068-2-78:2012, *Environmental testing – Part 2-78: Tests – Test Cab: Damp heat, steady state*

IEC 60204-11:2018, *Safety of machinery – Electrical equipment of machines – Part 11: Requirements for equipment for voltages above 1 000 V AC or 1 500 V DC and not exceeding 36 kV*

IEC 60320 (all parts), *Appliance couplers for household and similar general purposes*

IEC 60364 (all parts), *Low-voltage electrical installations*

IEC 60364-4-41:2005, *Low-voltage electrical installations – Part 4-41: Protection for safety – Protection against electric shock*
IEC 60364-4-41:2005/AMD1:2017

IEC 60364-5-54:2011, *Low-voltage electrical installations – Part 5-54: Selection and erection of electrical equipment – Earthing arrangements and protective conductors*
IEC 60364-5-54:2011/AMD1:2021

IEC 60417, *Graphical symbols for use on equipment* (available at <https://www.graphical-symbols.info/equipment>)

IEC 60529:1989, *Degrees of protection provided by enclosures (IP Code)*
IEC 60529:1989/AMD1:1999
IEC 60529:1989/AMD2:2013

IEC 60617, *Graphical symbols for diagrams* (available at <http://std.iec.ch/iec60617>)

IEC 60664-1:2020, *Insulation coordination for equipment within low-voltage systems – Part 1: Principles, requirements and tests*

IEC 60664-3:2016, *Insulation coordination for equipment within low-voltage systems – Part 3: Use of coating, potting or moulding for protection against pollution*

IEC 60664-4:2005, *Insulation coordination for equipment within low-voltage systems – Part 4: Consideration of high-frequency voltage stress*

IEC 60695-2-10:2021, *Fire hazard testing – Part 2-10: Glowing/hot-wire based test methods – Glow-wire apparatus and common test procedure*

IEC 60695-2-11:2021, *Fire hazard testing – Part 2-11: Glowing/hot-wire based test methods – Glow-wire flammability test method for end-products (GWEPT)*

IEC 60695-2-13:2021, *Fire hazard testing – Part 2-13: Glowing/hot-wire based test methods – Glow-wire ignition temperature (GWIT) test method for materials*

IEC 60695-10-2:2014, *Fire hazard testing – Part 10-2: Abnormal heat – Ball pressure test method*

IEC 60695-11-10:2013, *Fire hazard testing – Part 11-10: Test flames – 50 W horizontal and vertical flame test methods*

IEC 60695-11-20:2015, *Fire hazard testing – Part 11-20: Test flames – 500 W flame test method*

IEC 60721-3-3:1994, *Classification of environmental conditions – Part 3-3: Classification of groups of environmental parameters and their severities – Stationary use at weatherprotected locations*¹

IEC 60721-3-3:1994/AMD1:1995

IEC 60721-3-3:1994/AMD2:1996

IEC 60721-3-4:2019, *Classification of environmental conditions – Part 3: Classification of groups of environmental parameters and their severities – Stationary use at non-weatherprotected locations*

IEC 60730-1:2013, *Automatic electrical controls – Part 1: General requirements*

IEC 60730-1:2013/AMD1:2015

IEC 60730-1:2013/AMD2:2020

IEC 60755:2017, *General safety requirements for residual current operated protective devices*

IEC 60799:2018, *Electrical accessories – Cord sets and interconnection cord sets*

IEC 60947-4-1:2018, *Low-voltage switchgear and controlgear – Part 4-1: Contactors and motor-starters – Electromechanical contactors and motor-starters*

IEC 60990:2016, *Methods of measurement of touch current and protective conductor current*

IEC 61032:1997, *Protection of persons and equipment by enclosures – Probes for verification*

IEC 61084 (all parts), *Cable trunking systems and cable ducting systems for electrical installations*

IEC 61180:2016, *High-voltage test techniques for low-voltage equipment – Definitions, test and procedure requirements, test equipment*

IEC 61189-3:2007, *Test methods for electrical materials, printed boards and other interconnection structures and assemblies – Part 3: Test methods for interconnection structures (printed boards)*

IEC 61230:2008, *Live working – Portable equipment for earthing or earthing and short-circuiting*

IEC 61386 (all parts), *Conduit systems for cable management*

IEC 61558-1:2017, *Safety of power transformers, reactors, power supply units and combinations thereof – Part 1: General requirements and tests*

IEC 62109-1:2010, *Safety of power converters for use in photovoltaic power systems – Part 1: General requirements*

IEC 62271-102:2018, *High-voltage switchgear and controlgear – Part 102: Alternating current disconnectors and earthing switches*

IEC 62477-1:2022, *Safety requirements for power electronic converter systems and equipment – Part 1: General*

¹ This publication has been withdrawn.

IEC 62477-2:2018, *Safety requirements for power electronic converter systems and equipment – Part 2: Power electronic converters from 1 000 V AC or 1 500 V DC up to 36 kV AC or 54 kV DC*

ISO 3864-1:2011, *Graphical symbols – Safety colours and safety signs – Part 1: Design principles for safety signs and safety markings*

ISO 3746:2010, *Acoustics – Determination of sound power levels and sound energy levels of noise sources using sound pressure – Survey method using an enveloping measurement surface over a reflecting plane*

ISO 7000, *Graphical symbols for use on equipment* (available at <http://www.graphical-symbols.info/equipment>)

ISO 7010, *Graphical symbols – Safety colours and safety signs – Registered safety signs* (available at <https://www.iso.org/obp>)

ISO 9614-1:1993, *Acoustics – Determination of sound power levels of noise sources using sound intensity – Part 1: Measurement at discrete points*

3 Terms and definitions

For the purposes of this document, the terms and definitions given in IEC 60050-112:2010, IEC 60050-113:2011, IEC 60050-114:2014, IEC 60050-131:2002, IEC 60050-426:2020, IEC 60050-151:2001, IEC 60050-161:1990, IEC 60050-192:2015, IEC 60050-441:1984, IEC 60050-442:1998, IEC 60050-551:1998, IEC 60050-601:1985, IEC 60050-826, IEC 60050-903:2013 and IEC 60664-1:2020, and the following apply.

Table 1 provides an alphabetical cross-reference listing of terms.

Table 1 – Alphabetical list of terms

Term	Term no.	Term	Term no.	Term	Term no.
abnormal operating condition (abnormal operation)	3.1	fault protection	3.33	protective class II	3.65
accessible part	3.2	field wiring terminal	3.34	protective class III	3.66
accessory	3.3	fire enclosure	3.35	protective earthing (PE)	3.67
adjacent circuit	3.4	functional insulation	3.36	PE conductor	3.68
ambient temperature	3.5	hand-held BDM/CDM/PDS	3.37	protective impedance	3.69
basic drive module (BDM)	3.6	general-access area	3.38	reinforced insulation	3.70
basic insulation	3.7	hazardous live part	3.39	restricted-access area	3.71
basic protection	3.8	high-voltage BDM/CDM/PDS	3.40	routine test	3.72
bypass	3.9	hinged panel	3.41	sample test	3.73
BDM/CDM rated output current	3.10	installation	3.42	SELV circuit	3.74
clearance	3.11	integrated PDS	3.43	service-access area	3.75
control circuit	3.12	interlock	3.44	short-circuit backup protection	3.76
commissioning test	3.13	live part	3.45	short-circuit protective device (SCPD)	3.77
complete drive module (CDM)	3.14	low-voltage (LV)	3.46	short time withstand current (I_{CW})	3.78
component	3.15	low-voltage BDM/CDM/PDS	3.47	skilled person	3.79
conditional short-circuit current (I_{CC})	3.16	mains supply	3.48	single-fault condition	3.80
cover	3.17	minimum required prospective short-circuit current ($I_{cp,mr}$)	3.49	solid insulation	3.81
creepage distance	3.18	movable	3.50	surrounding air temperature	3.82
decisive voltage class (DVC)	3.19	non-mains supply	3.51	surroundings	3.83
door	3.20	open type	3.52	supplementary insulation	3.84
double insulation	3.21	ordinary person	3.53	surge protective device (SPD)	3.85
direct plug-in BDM/CDM/PDS	3.22	output short-circuit current	3.54	system	3.86
DVC As	3.23	overcurrent	3.55	system voltage	3.87
electrical breakdown	3.24	PELV circuit	3.56	temporary overvoltage	3.88
electrical insulation (insulation)	3.25	permanently connected equipment	3.57	thermal memory	3.89
electrically protective screening (protective screening)	3.26	pluggable equipment type A	3.58	thermal memory retention	3.90
electronic motor overload protection	3.27	pluggable equipment type B	3.59	touch current	3.91
electronic power output short-circuit protection (circuitry)	3.28	port	3.60	trip	3.92
enclosure	3.29	power drive system (PDS)	3.61	type test	3.93
enhanced protection	3.30	prospective short-circuit current (I_{cp})	3.62	visual inspection	3.94
expected lifetime	3.31	protective equipotential bonding	3.63	working voltage	3.95
extra-low voltage (ELV)	3.32	protective class I	3.64	zone of equipotential bonding	3.96

3.1

abnormal operating condition

abnormal operation

temporary operating condition that is not a normal operating condition and is not a *single-fault condition* of the equipment itself

Note 1 to entry: An *abnormal operating condition* may be introduced by the equipment or by a person and may result in a failure of a *component*, a device or *insulation*.

[SOURCE: IEC 62368-1:2018, 3.3.7.1, modified – Note 1 to entry deleted, and Notes 2 and 3 to entry merged.]

3.2

accessible part

part or surface that can be touched by means of test probe B of IEC 61032, and if the part or surface is metal, any conductive part connected to it

Note 1 to entry: Test probe B is found in IEC 61032:1997, Figure 2. See also Figure M.2.

Note 2 to entry: Accessible non-metallic parts with conductive coatings are considered to be accessible metal parts.

[SOURCE: IEC 60335-1:2020, 3.6.3, modified – Note 1 to entry added.]

3.3

accessory

additional part, component or equipment intended to expand capabilities of the BDM/CDM/PDS, but not required for the general function of the BDM/CDM/PDS

Note 1 to entry: Typical examples are:

- external mains coils or RFI filters,
- external motor output filters,
- communication, control or input/output interface kits,
- external SPD for reduction of transient,
- additional *enclosure* parts or kits,
- additional ventilation kits,
- mechanical bonding or cable support kits, or
- additional measuring device, instrument etc.

Note 2 to entry: Expanded capabilities are considered to be electrical, mechanical, thermal or acoustic noise characteristics of the *BDM/CDM/PDS* when installed and operating as intended.

Note 3 to entry: *Accessories* and *accessory* kits might be factory or field installed.

3.4

adjacent circuit

circuit next to the circuit under consideration having a requirement for *functional insulation*, *basic insulation*, *double insulation* or *reinforced insulation* between them for protection

3.5

ambient temperature

average temperature of air or another medium in the vicinity of the equipment

Note 1 to entry: During the measurement of the *ambient temperature* the measuring instrument/probe should be shielded from draughts and radiant heating.

Note 2 to entry: "Equipment" includes *BDM/CDM/PDS* as well as *components*, depending on the application of the term *ambient temperature*.

Note 3 to entry: In general, the *ambient temperature* is measured in vicinity to the equipment (approx. 50 mm to 100 mm distance), shielded from heat radiation and measured at a height of approximately 50 % height of the equipment in case of passively cooled equipment, or air inlet of actively cooled equipment.

[SOURCE: IEC 60050-826:2004, 826-10-03, modified – Notes 2 and 3 to entry added.]

3.6

basic drive module

BDM

electronic power converter and related control, connected between an electric supply and a motor

Note 1 to entry: The *BDM* is capable of transmitting power from the electric supply to the motor and may be capable of transmitting power from the motor to the electric supply.

Note 2 to entry: The *BDM* controls some or all of the following aspects of power transmitted to the motor and motor output: current, frequency, voltage, speed, torque, force.

[SOURCE: IEC 61800-2:2021, 3.4]

3.7

basic insulation

insulation of hazardous live parts which provides *basic protection*

Note 1 to entry: This concept does not apply to *insulation* used exclusively for functional purposes.

[SOURCE: IEC 60050-195:2021, 195-06-06, modified – Words "hazardous live parts" added.]

3.8

basic protection

protection against electric shock under fault-free conditions through the use of *insulation* or distance or a combination of both

[SOURCE: IEC 60050-195:2021, 195-06-01, modified – Word "normal" replaced with "fault-free" and words "through the use of *insulation* or distance or a combination of both" added.]

3.9

bypass

circuit which, when closed, creates an alternative path for current flow in parallel with the circuit being bypassed

Note 1 to entry: The *bypass* circuit typically consists of a switch or contactor.

Note 2 to entry: The *bypass* circuit allows the original circuit to be turned off while maintaining current flow to the load.

3.10**BDM/CDM rated output current**

current at the motor side of the *BDM/CDM* which can be supplied continuously without exceeding established limitations, under rated operating conditions

Note 1 to entry: For AC *BDM/CDM*, this value is expressed in RMS. For DC *BDM/CDM*, this value is expressed in average.

Note 2 to entry: This term is taken from IEC 61800-1:2021, and modified and complies with IEC 61800-2:2021.

3.11**clearance**

shortest distance in air between two conductive parts

Note 1 to entry: This distance can be measured along a string stretched the shortest way between these conductive parts.

[SOURCE: IEC 60050-581:2008, 581-27-76, modified – Note to entry added.]

3.12**control circuit**

circuit that carries signals directing the performance of a *BDM/CDM/PDS*, and that is not the main power circuit

3.13**commissioning test**

test on a device or equipment performed on site, to prove the correctness of *installation* and operation

[SOURCE: IEC 60050-411:1996, 411-53-06, modified – Word "machine" replaced with "device".]

3.14**complete drive module****CDM**

drive module consisting of, but not limited to, the *BDM* and extensions such as protection devices, transformers and auxiliaries, but excluding the motor and the sensors which are mechanically coupled to the motor shaft

[SOURCE: IEC 61800-2:2021, 3.6]

3.15**component**

part of *BDM/CDM/PDS*, which cannot be physically divided into smaller parts without losing its particular function

Note 1 to entry: The term "*component*" as well as the term "sub-assembly" in this document shall be read in their context. A *component* therefore could be a single capacitor, a power supply unit, which is made of several electronic *components* as well as complete drive module inside a cabinet.

Note 2 to entry: An inverter stage (module) can also be seen as sub-assembly of a drive module.

[SOURCE: IEC 60050-151:2001, 151-11-21, modified – Words "constituent part of a device" replaced with "part of *BDM/CDM/PDS*", and notes to entry added.]

3.16 conditional short-circuit current

I_{cc}

RMS value of a *prospective short-circuit current* available from a supply source, declared by the *BDM/CDM/PDS* manufacturer under specified conditions, using a specific type of *short-circuit protective device* (SCPD) protecting the *BDM/CDM/PDS*

Note 1 to entry: The *short-circuit protective device* may form an integral part of the *BDM/CDM/PDS* or may be a separate unit.

3.17 cover

unhinged portion of an *enclosure* that closes an opening

3.18 creepage distance

shortest distance along the surface of a solid insulating material between two conductive parts

[SOURCE: IEC 60050-151:2001, 151-15-50]

3.19 decisive voltage class DVC

classification of voltage range used to determine the protective measures against electric shock and the requirements of *insulation* between circuits

3.20 door

hinged portion of an *enclosure* that covers an opening, which is intended to be opened during routine maintenance, operations and adjustments

3.21 double insulation

insulation comprising both *basic insulation* and *supplementary insulation*

[SOURCE: IEC 60050-195:2021, 195-06-08]

3.22 direct plug-in *BDM/CDM/PDS*

BDM/CDM/PDS in which the mains plug forms an integral part of the equipment *enclosure* so that the equipment is supported by the mains socket-outlet

[SOURCE: IEC 60050-903:2014, 903-04-07, modified – Word "equipment" replaced with "*BDM/CDM/PDS*".]

3.23 DVC As

voltage classification of a circuit providing only safe to touch voltage, under normal operating conditions and *single-fault conditions* and limited overvoltages

Note 1 to entry: For limits refer to Table 2.

[SOURCE: IEC 61204-7:2016, modified – Definition reformulated.]

3.24**electrical breakdown**

failure of *insulation* under electric stress when the discharge completely bridges the *insulation*, thus reducing the voltage across the *insulation* almost to zero

[SOURCE: IEC 60664-1:2020, 3.1.44, modified – Words "between the electrodes" replaced with "across the *insulation*".]

3.25**electrical insulation****insulation**

electrical separation between circuits or conductive parts provided by *clearance* or *creepage distance* or *solid insulation* or combinations of them

Note 1 to entry: The meaning of *clearance* in this document is distance through air.

3.26**electrically protective screening****protective screening**

separation of circuits from *hazardous live parts* by means of an interposed conductive screen, connected to the *PE conductor*, either directly or via *protective equipotential bonding*

Note 1 to entry: If the protective screening is used as a measure for enhanced protection, see 4.4.5.

3.27**electronic motor overload protection**

BDM/CDM circuitry which protects a motor during overload conditions by reducing current to the motor

Note 1 to entry: The protection circuitry is usually a combination of hardware and software.

Note 2 to entry: This protection is typically achieved through an algorithm based on the I^2t of the current to the motor.

3.28**electronic power output short-circuit protection****circuitry**

circuitry integral to *BDM/CDM* that acts to significantly reduce current flow to the power output upon sensing a short-circuit condition

Note 1 to entry: The protection circuitry is usually a combination of hardware and software.

3.29**enclosure**

housing affording the type and degree of protection suitable for the intended application

Note 1 to entry: This document provides requirements for the *enclosure* according to IEC 60529 as well as additional requirements for mechanical and environmental impact. The purpose of the additional requirements is to ensure the *enclosure's* ability to provide *basic protection* under the environmental conditions specified by the manufacturer.

[SOURCE: IEC 60050-151:2001, 151-13-08, modified – Note 1 to entry added.]

3.30**enhanced protection**

protective provision having a reliability of protection not less than that provided by two independent protective provisions through the use of *insulation* or distance or a combination of both

[SOURCE: IEC 61140:2016, 3.19, modified – Word "protective provision" replaced with "protection" in the term, and words "through the use of *insulation* or distance or a combination of both" added to the definition.]

3.31**expected lifetime**

design duration for which the performance characteristics are valid as specified by the manufacturer

3.32**extra-low voltage****ELV**

voltage not exceeding the relevant voltage limit specified in IEC 61140:2016, Table 1

Note 1 to entry: In IEC 61140, *ELV* is defined as not exceeding 50 V AC RMS and 120 V DC. Other product committees may have defined *ELV* with different voltage levels.

Note 2 to entry: In this document, protection against electric shock is dependent on the *decisive voltage class*.

3.33**fault protection**

protection against electric shock under *single-fault conditions*

Note 1 to entry: For *low-voltage installations, systems* and equipment, *fault protection* in IEC 60364-4-41 generally corresponds to the formerly used "protection against indirect contact", mainly with regard to failure of *basic insulation*.

[SOURCE: IEC 60050-195:2021, 195-06-02, modified – Note to entry added.]

3.34**field wiring terminal**

terminal provided for connection of external conductors to the *BDM/CDM/PDS*

Note 1 to entry: See Figure 7 and Figure 8 for examples of connection of internal and external conductors.

3.35**fire enclosure**

part of the equipment intended to minimize the spread of fire or flames from within the *enclosure* to outside the *enclosure*

3.36**functional insulation**

insulation between conductive parts within a circuit that is necessary for the proper function of the circuit, but which does not provide protection against electric shock

Note 1 to entry: *Functional insulation* may, however, reduce the likelihood of ignition and fire.

3.37**hand-held BDM/CDM/PDS**

BDM/CDM/PDS intended to be held in the hand during normal use

[SOURCE: IEC 60050-826:2004, 826-16-05, modified – Word "equipment" replaced with "*BDM/CDM/PDS*" in the term.]

3.38**general-access area**

area of the *BDM/CDM/PDS* to which both *ordinary persons* and *skilled persons* are permitted to access

Note 1 to entry: *General-access areas* do not require the use of a tool or key.

3.39**hazardous live part**

live part which, under certain conditions, can give a harmful electric shock

Note 1 to entry: In this document, a hazardous live part does not meet the requirement of *DVC* As in 4.4.2.2.

[SOURCE: IEC 60050-195:2021, 195-06-05, modified – Hyphens removed from the term and note to entry replaced.]

3.40**high-voltage BDM/CDM/PDS**

BDM/CDM/PDS having a *port* voltage above 1 kV AC 50 Hz or 60 Hz or above 1,5 kV DC

Note 1 to entry: "*Port*" generically applies to both input and output, and the scope of this document addresses only the range of voltages at the input power *port*.

Note 2 to entry: See IEC 61800-2:2021, Table 5.

Note 3 to entry: For *PDS* having series-connected converter sections, a sum of the series-connected phase to phase input voltages is used as the equivalent input voltage of the converter sections (see IEC 61800-2:2021, Annex A).

Note 4 to entry: In the United States of America (USA), the voltage range of this definition is considered medium voltage.

[SOURCE: IEC 61800-2:2021, 3.16, modified – Words "phase to phase" added in Note 3 to entry, "the scope of this document" replaced with "this definition" in Note 4 to entry, and Note 5 to entry deleted.]

3.41**hinged panel**

portion of an *enclosure* that has hinges, but no hand-operable latching *system*, secured in the closed position by multiple bolts or other hardware requiring a tool other than a key to operate

Note 1 to entry: *Hinged panels* are not intended to be opened during normal operating conditions, routine adjustment or simple maintenance operations such as replacement of fuses.

3.42**installation**

apparatus or set of devices and/or apparatuses associated in a given location to fulfil specified purposes, including all means for their satisfactory operation

Note 1 to entry: The word *installation* is also used in this document to denote the process of installing a *PDS*. In these cases, the word does not appear in italics.

[SOURCE: IEC 60050-151:2001, 151-11-26, modified – Note to entry added.]

3.43**integrated PDS**

PDS where motor and *BDM/CDM* are mechanically integrated into a single unit

[SOURCE: IEC 61800-2:2021, 3.28, modified – Word "combined" replaced with "mechanically integrated".]

3.44**interlock**

device(s) that prevent operation of some other device with which it is directly associated under specific conditions

Note 1 to entry: *Interlocks* may be electrical, mechanical, or a combination of both.

3.45**live part**

conductive part intended to be energized under normal operating conditions, including the neutral conductor and mid-point conductor, but excluding the PEN conductor, PEM conductor and PEL conductor

Note 1 to entry: This concept does not necessarily imply a risk of electric shock.

Note 2 to entry: By convention, the PE conductor is not a live part.

[SOURCE: IEC 60050-195:2021, 195-02-19, modified – Notes to entry added.]

3.46**low-voltage****LV**

set of voltage levels used for the distribution of electricity and whose upper limit is generally accepted to be 1 000 V AC or 1 500 V DC

[SOURCE: IEC 60050-601:1985, 601-01-26, modified – Words "or 1 500 V DC" added.]

3.47**low-voltage BDM/CDM/PDS**

BDM/CDM/PDS having a *port* voltage less than or equal to 1 kV AC (50 Hz or 60 Hz) or 1,5 kV DC

Note 1 to entry: For *PDS* having series-connected converter sections, a sum of the series-connected input voltages is used as the equivalent input voltage of the converter sections (see IEC 61800-2:2021, Annex A).

[SOURCE: IEC 61800-2:2021, 3.30, modified – Note 2 to entry deleted.]

3.48**mains supply**

low-voltage or high-voltage power distribution system for supplying power to a *BDM/CDM/PDS*

3.49**minimum required prospective short-circuit current**

$I_{cp,mr}$

RMS value of a minimum *prospective short-circuit current*, which shall be available from the source to ensure operation of the specific type of *short-circuit protective device*

[SOURCE: IEC 62477-1:2022, 3.38]

3.50**movable**

<*BDM/CDM/PDS*> equipment that is either:

- 18 kg or less in mass and not fixed in place, or
- provided with wheels, casters, or other means to facilitate movement by an *ordinary person* as required to perform its intended use

[SOURCE: IEC 60050-903:2014, 903-04-06, modified – Word "limited" replaced with "18 kg or less", and Note to entry deleted.]

3.51**non-mains supply**

electrical source that is not connected directly to the *mains supply*

Note 1 to entry: Examples of *non-mains supplies* are those which are isolated from the *mains supply* by a transformer or supplied by a battery, generator, solar arrays, wind generator, tidal systems, wave, fuel cell or similar sources not directly connected to the AC or DC power distribution system.

3.52**open type**

<BDM/CDM> intended to be incorporated within an *enclosure* or *restricted-access area* that will provide protection against hazards

Note 1 to entry: Hazards are defined in 4.2.

3.53**ordinary person**

person who is not a *skilled person*

EXAMPLE An operator, any person who may have access to the equipment or any person who may be in the vicinity of the equipment, when such equipment is not installed in a *restricted-access area*.

[SOURCE: IEC 60050-826:2004, 826-18-03, modified – Words "nor an instructed person" deleted, and example added.]

3.54**output short-circuit current**

available current that flows at the output power *port* of the *BDM/CDM* when a short-circuit is applied by a conductor of negligible impedance

3.55**overcurrent**

current in excess of the rated current

Note 1 to entry: In this document, the term *overcurrent* covers both short-circuit and overload.

3.56**PELV circuit**

electric *system* in which the voltage cannot exceed the value of *extra-low voltage*:

- under normal operating conditions; and
- under *single-fault conditions*, except earth faults in other electric circuits

Note 1 to entry: *PELV* is the abbreviation for protective *extra-low voltage*.

[SOURCE: IEC 60050-826:2004, 826-12-32, modified – Word "system" replaced with "circuit" in the term, and word "operating" added to the first dash.]

3.57**permanently connected equipment**

equipment that can only be connected to or disconnected from the electric power *system* by the use of a tool

[SOURCE: IEC 60050-151:2014, 151-11-29]

3.58**pluggable equipment type A**

equipment that is intended for connection to the *mains supply* or *non-mains supply* via a non-industrial plug and socket-outlet or via a non-industrial appliance coupler, or both

Note 1 to entry: For non-industrial plug and socket-outlets, see IEC TR 60083 or a national equivalent. For non-industrial appliance couplers, see IEC 60320-1.

[SOURCE: IEC 60050-903:2014, 903-04-08, modified – Word "*mains*" replaced with "*mains supply or non-mains supply*".]

3.59**pluggable equipment type B**

equipment that is intended for connection to the *mains supply* or *non-mains supply* via an industrial plug and socket-outlet or via an industrial appliance coupler, or both

Note 1 to entry: For industrial plug and socket-outlets, see IEC 60309-1 or a national equivalent. For non-industrial appliance couplers, see IEC 60320-1.

[SOURCE: IEC 60050-903:2014, 903-04-09, modified – Word "*mains*" replaced with "*mains supply or non-mains supply*".]

3.60**port**

access to a device or network where electromagnetic energy or signals may be supplied or received or where the device or network variables may be observed or measured


Note 1 to entry: In this document, "input", "output", "power" and "control" are indicated to define usage.

Note 2 to entry: For the evaluation of safety, ports also cover power interfaces as defined in IEC 61800-1:2021, IEC 61800-2:2021 and IEC 61800-3:2017.

[SOURCE: IEC 60050-131:2002, 131-12-60, modified – Note replaced with Note 1 to entry and Note 2 to entry.]

3.61**power drive system****PDS**

system consisting of one or more *complete drive module(s)* (CDM) and a motor or motors



IEC

Figure 1 – PDS hardware configuration within an *installation*

Note 1 to entry: See Figure 1. For more detailed information, see IEC 61800-2:2021, Figure 1.

Note 2 to entry: Any sensors which are mechanically coupled to the motor shaft are also part of the *PDS*; however, the driven equipment is not included.

[SOURCE: IEC 61800-2:2021, 3.52, modified – Note 1 to entry added.]

3.62 prospective short-circuit current

I_{cp}

RMS value of the symmetrical current which would flow if the supply conductors to the circuit are short-circuited by a conductor of negligible impedance located as near as practicable to the supply terminals of the *BDM/CDM/PDS*

[SOURCE: IEC 61439-1:2020, 3.8.7, modified – Word "current" replaced with "RMS value of the symmetrical current", and "assembly" with "*BDM/CDM/PDS*".]

3.63 protective equipotential bonding

provision of electric connections between conductive parts, intended to minimize any difference in potential between those parts, for purposes of safety

EXAMPLE Protection against electric shock.

3.64 protective class I

equipment in which protection against electric shock does not rely on *basic protection* only, but which includes an additional safety precaution in such a way that means are provided for the connection of conductive *accessible parts* to the *PE conductor* in the fixed wiring of the *installation*, in such a way that conductive *accessible parts* cannot become live in the event of a failure of the *basic insulation*

Note 1 to entry: *Protective class I* is defined in IEC 61140:2016, 7.3.

3.65 protective class II

equipment in which protection against electric shock does not rely on *basic protection* only, but in which additional safety precautions such as *supplementary insulation* or *reinforced insulation* are provided, there being no provision for *protective earthing* or reliance upon *installation* conditions

Note 1 to entry: *Protective class II* is defined in IEC 61140:2016, 7.4.

3.66 protective class III

equipment in which protection against electric shock relies on supply at *DVC As* (or *DVC B* under certain conditions) and in which voltages higher than those of *DVC As* (*DVC B*) are not generated and there is no provision for *protective earthing*

Note 1 to entry: *Protective class III* is defined in IEC 61140:2016, 7.5.

Note 2 to entry: Other standards define *protective class III* as supplied by *ELV*.

3.67 protective earthing PE

earthing of a point in a *system*, or equipment, for protection against electric shock in case of a fault

3.68**PE conductor**

conductor in the *installation* wiring or in the power supply cord, connecting a main protective earthing terminal in the equipment to an earthing point in the *installation* for safety purposes

Note 1 to entry: In the USA and Canada, the term "ground" is used instead of "earth".

3.69**protective impedance**

impedance connected between *hazardous live parts* and conductive *accessible parts*, of such value that the current, under normal operating conditions and under *single-fault conditions*, is limited to a safe value, and which is constructed so that its ability is maintained throughout the life of the equipment

[SOURCE: IEC 60050-442:1998, 442-04-24, modified – Definition reformulated.]

3.70**reinforced insulation**

insulation of *hazardous live parts* which provides a degree of protection against electric shock equivalent to *double insulation*

[SOURCE: IEC 60050-826:2004, 826-12-17, modified – Note to entry deleted.]

3.71**restricted-access area**

enclosed electrical area not intended for service, maintenance or commissioning while the *BDM/CDM/PDS* is energized and to which only *skilled persons* are permitted to access

Note 1 to entry: *Restricted-access areas* require the use of a tool or key to get access.

3.72**routine test**

conformity test made on each individual item during or after manufacture

[SOURCE: IEC 60050-151:2001, 151-16-17]

3.73**sample test**

test on a number of devices taken at random from a batch

[SOURCE: IEC 61800-2:2021, 3.85]

3.74**SELV circuit**

electric *system* in which the voltage cannot exceed the value of *extra-low voltage*:

- under normal conditions; and
- under *single-fault conditions*, including earth faults in other electric circuits

Note 1 to entry: *SELV* is the abbreviation for safety *extra-low voltage*.

[SOURCE: IEC 60050-826:2004, 826-12-31, modified – Word "system" replaced with "circuit" in the term.]

3.75**service-access area**

enclosed electrical area intended for service, maintenance and commissioning while the *BDM/CDM/PDS* is energized and to which only *skilled persons* have permitted to access

Note 1 to entry: *Service-access areas* require the use of a tool or key to get access.

Note 2 to entry: *Service-access area* can be a place within a building or a space within an *enclosure*.

3.76**short-circuit backup protection**

protection that is intended to operate when other protective measures within a *system* or equipment fail to clear a fault

[SOURCE: IEC 62477-1:2022, 3.67]

3.77**short-circuit protective device****SCPD**

device intended to protect a circuit or parts of a circuit against short-circuit currents by interrupting them

Note 1 to entry: A *short-circuit protective device* is suitable for protection against short-circuit only, not for protection against overload. An *overcurrent* protective device may also incorporate the function of a *SCPD*.

[SOURCE: IEC 61439-1:2020, 3.1.11, modified – Note to entry added.]

3.78**short time withstand current**

I_{cw}

RMS value of short time current, declared by the *BDM/CDM/PDS* manufacturer, which can be withstood under specified conditions, defined in terms of current and time

3.79**skilled person**

person with relevant education and experience to enable him or her to perceive risks and to avoid hazards which the equipment can create

[SOURCE: IEC 60050-826:2004, 826-18-01, modified – Word "(electrically)" deleted from the term, and "electricity" replaced with "the equipment" in the text.]

3.80**single-fault condition**

condition in which one failure is present which could cause a hazard covered by this document

Note 1 to entry: If a *single-fault condition* results in other subsequent failures, the set of failures is considered as one *single-fault condition*.

Note 2 to entry: Examples of hazards include, but are not limited to, electric shock, fire, energy, mechanical, acoustic noise etc.

Note 3 to entry: IEC Guide 116 provides examples of hazards.

3.81**solid insulation**

solid insulating material, or a combination of solid insulating materials, placed between two conductive parts or between a conductive part and a body part

Note 1 to entry: In this document, *solid insulation* does not cover liquid *insulation*.

[SOURCE: IEC 60050-903:2015, 903-04-14, modified – Example replaced with note to entry 1]

3.82**surrounding air temperature**

<open type> maximum *ambient temperature* of air immediately surrounding *open type* equipment inside of the ultimate *enclosure*

3.83**surroundings**

parts of the *BDM/CDM/PDS* adjacent to the circuit or part under consideration

3.84**supplementary insulation**

independent insulation applied in addition to basic insulation for *fault protection*

Note 1 to entry: *Basic insulation* and *supplementary insulation* are separate, each designed for *basic protection* against electric shock.

[SOURCE: IEC 60664-1:2020, 3.1.31, modified – Note to entry added.]

3.85**surge protective device****SPD**

device that contains at least one non-linear *component* that is intended to limit surge voltages and divert surge currents

Note 1 to entry: An SPD is a complete assembly, having appropriate connecting means.

[SOURCE: IEC 61643-11:2011, 3.1.1]

3.86**system**

set of interrelated and/or interconnected independent elements

Note 1 to entry: A *system* is generally defined with the view of achieving a given objective, for example by performing a definite function, such as grounding *systems*, wiring *systems*, power *systems*, *insulation systems*.

3.87**system voltage**

voltage used to determine *insulation* requirements

Note 1 to entry: See 4.4.7.1.7 for further consideration of *system voltage*.

3.88**temporary overvoltage**

overvoltage at power frequency of relatively long duration

[SOURCE: IEC 60664-1:2020, 3.1.12]

3.89**thermal memory**

ability of an overload protective *system* to approximate the heating and cooling of a protected motor during operation

3.90**thermal memory retention**

ability to retain a representation of the thermal state of a motor prior to tripping or loss of power

Note 1 to entry: Typically, the thermal memory retention will be used by the overload protective *system* to approximate the thermal state of the motor upon restart.

Note 2 to entry: The thermal memory retention may include an ongoing reduction of the thermal representation to reflect cooling of the motor during tripping or loss of power.

3.91**touch current**

electric current passing through a human body or through an animal body when it touches one or more conductive *accessible parts* of an electrical *installation* or electrical equipment

[SOURCE: IEC 60050-826:2004, 826-11-12, modified – Word "conductive" added.]

3.92**trip**

initiate a controlled rapid reduction or elimination of the transfer of energy to any device or process initiated by a detected fault or an *abnormal operating condition*

3.93**type test**

conformity test made on one or more *BDM/CDM/PDS* representative of the production

[SOURCE: IEC 60050-151:2001, 151-16-16, modified – Word "items" replaced with "*BDM/CDM/PDS*".]

3.94**visual inspection**

scrutiny by eye of an item carried out either without dismantling, or with the addition of partial dismantling as required in order to arrive at a reliable conclusion as to the condition of an item

[SOURCE: IEC 60050-426:2020, 426-14-02, modified – Definition reformulated.]

3.95**working voltage**

voltage, at rated supply conditions (without tolerances) and worst case operating conditions, which occurs by design in a circuit or across *insulation*

Note 1 to entry: The *working voltage* can be DC or AC. Both the RMS and recurring peak values are used.

3.96**zone of equipotential bonding**

zone where all simultaneously conductive *accessible parts* are electrically connected to prevent hazardous voltages appearing between them

4 Protection against hazards

4.1 General

Clause 4 defines the minimum requirements for the design and construction of a *BDM/CDM/PDS* and *accessories* for the intended use, to ensure its safety during installation, normal operating conditions and maintenance for the *expected lifetime* of the *BDM/CDM/PDS*. Consideration is also given to minimize hazards resulting from reasonably foreseeable misuse.

Protection against hazards shall be maintained under normal *operating conditions*, *abnormal operating conditions* and *single-fault conditions*, as specified in this document.

Where the *PDS* is intended to be used together with specific equipment or *accessories*, the safety evaluation and testing shall include this, unless it can be shown that it does not affect the safety of either the *PDS* or the specific equipment.

Guidance for risk assessment for electrical equipment and systems is provided in IEC Guide 116 which is transformed for *BDM/CDM/PDS* in Annex R.

4.2 *Single-fault conditions and abnormal operating conditions*

BDM/CDM/PDS and *accessories* shall be designed to avoid operating modes or sequences that can cause a *single-fault condition* or *component* failure leading to a hazard, unless other measures to prevent the hazard are provided by the *installation* and are described in the installation information provided with the *BDM/CDM/PDS*, see Clause 6. The requirements in 4.2 also apply to *abnormal operating conditions* as applicable.

Circuit analysis shall be performed to identify potential hazards.

This circuit analysis shall include situations where a failure of any component, *insulation* system or *port* would result in

- a risk of electromagnetic force and thermal hazards according to 4.3,
- an impact on the decisive voltage determination according to 4.4.2,
- a risk of electric shock due to
 - degradation of the *basic protection* according to 4.4.3, or
 - degradation of the *fault protection* according to 4.4.4,
- a risk of energy hazard according to 4.5,
- a risk of degradation due to emission of flame, burning particles or molten metal of the fire according to 4.6,
- a risk of thermal hazard due to high temperature according to 4.6, and
- a risk of mechanical hazard according to 4.7.

NOTE This document does not provide any requirement to protect against chemical hazard.

The circuit analysis shall include the effect of short-circuit and open-circuit conditions. Testing is necessary unless the circuit analysis conclusively shows that no hazard will result from failure. If testing is required, compliance shall be checked by test of 5.2.4.10.

In addition to this analysis, *components* shall meet the requirements of 4.13.

Clearance, *creepage distances* and *solid insulation* materials designed for *enhanced protection* (see 4.4.5) according to 4.4.7.4, 4.4.7.5 and 4.4.7.8 are considered to meet these requirements and do not need any further investigation.

Functional insulation on printed wiring boards (PWB) and between legs of *components* assembled on PWBs not fulfilling the requirements for *clearance* and *creepage distance* in 4.4.7.4 and 4.4.7.5 shall meet the requirement of 4.4.7.7.

Consideration shall be given to potential safety hazards associated with major *component* parts of the *PDS*, such as motor rotating parts, flammability of transformer and capacitor fluids.

The analysis shall include limited power sourced circuits, only where a failure of the limited power source circuit *component* creates a hazard in a circuit that is not sourced from a limited power source circuit.

The analysis shall also include any other investigation, study, analysis, calculation or test required to address the non-electrical hazards. Testing is necessary unless analysis shows that no hazard will result from the failure of *components* and mechanical parts.

4.3 Short-circuit and overload protection

4.3.1 General

To comply with the requirements defined in 4.2, the *BDM/CDM/PDS* shall not present a hazard under short-circuit or overload conditions (further referred as fault) at any power *port*, including phase to phase, phase to earth and phase to neutral. Adequate information shall be provided in the documentation to allow proper selection of *installation* wiring and protective devices external of the *BDM/CDM/PDS*.

If a protective system or protective device is required for short-circuit or overload protection, it shall be provided or specified.

For marking, see 6.3.9.6.

NOTE 1 Local *installation* codes will still usually require provision of such protection for the purposes of protecting the input wiring in the *installation*. In some cases, it is possible local *installation* codes supersede requirements of this document.

Protection against *overcurrents* shall be provided for all *ports*, except

- for *ports* that comply with the requirements for limited power sources in 4.5.3, or
- if the *BDM/CDM/PDS* complies with all normal operating conditions, *abnormal operating conditions* and *single-fault conditions* in this document without such protection provided.

NOTE 2 In this document, the term *overcurrent* covers both short-circuit and overload.

When protection against *overcurrents* is required, this may be integral to the *BDM/CDM/PDS* or it may be provided in the *installation*, and details of the required *overcurrent* protective device shall be provided in the *BDM/CDM/PDS* installation instructions in accordance with 6.3.9.6.

No protection is required against *overcurrent* to earth on *ports* that have either

- no connection to earth, or
- *enhanced protection* between *live parts* and all conductive parts connected to earth.

NOTE 3 Where *enhanced protection* is provided, a short-circuit to earth would be considered to be two faults.

Testing is not required under a *single-fault condition* to earth in *BDM/CDM/PDS* installed on an IT-system.

NOTE 4 Under a *single-fault condition* in an IT-system, no short-circuit current or a limited short-circuit current will flow. A short-circuit current would flow in an IT-system, when a second fault occurs. Typically, only detection is done after the first fault in an IT-system.

For *pluggable equipment type A*, the protective device is provided in the *installation* and shall not require any specific characteristics other than that required in IEC 60364 (all parts) or other local *installation* codes.

For *pluggable equipment type B* or *permanently connected BDM/CDM/PDS*, this protection may be provided by devices external to the *BDM/CDM/PDS*, in which case the installation instructions shall state the need for the protection to be provided in the *installation* and shall include the specifications for the required short-circuit and/or overload protection (see 6.3.9.6).

NOTE 5 IEC 60364 (all parts) provides requirements for short-circuit and overload protection of the input wiring in the installation. The above requirement ensures that the user is informed about any special characteristics of the protective devices for the protection of the PDS, in addition to the requirements in IEC 60364 (all parts) or other local installation codes.

If a protective device interrupts the neutral conductor, it shall also simultaneously interrupt all other supply conductors of the same circuit. It is permissible for the protective device to interrupt the neutral conductor after the other supply conductors of the same circuit.

Consideration shall be given to compliance with

- different type of earthing system (e.g. TN, TT, IT, star or corner-earthed in 4.4.7.1.5) as the short-circuit current to protective earth depends on the type of earthing system,
- automatic disconnection of supply in 4.4.4.4.1,
- disconnection time in 4.4.4.4.2 as required in IEC 60364-4-41:2005 and IEC 60364-4-41:2005/AMD1:2017, 411.3.2, (see Annex Q), and
- alternative to automatic disconnection of supply in 4.4.4.4.3.

NOTE 6 IEC 60364-4-41:2005 and IEC 60364-4-41:2005/AMD1:2017, 411.3.2, provides more information about protection against indirect contact in case of a short-circuit between *hazardous live parts* and protective earth.

NOTE 7 The short-circuit fault current to earth is expected to be up to the rated short-circuit current of the output power *port* depending on earthing system.

4.3.2 Input short-circuit rating and available *output short-circuit current*

4.3.2.1 General

The interrupting capability of the *overcurrent* protective device shall be equal to or greater than the *prospective short-circuit current* of the *mains supply* or *non-mains supply*.

For *pluggable equipment type A*, either the *PDS* shall be designed such that the *installation* provides *short-circuit backup protection*, or additional *short-circuit backup protection* shall be provided as part of the *BDM/CDM/PDS*.

For *pluggable equipment type B* or *permanently connected BDM/CDM/PDS*, it is permitted for *short-circuit backup protection* to be in the *installation*.

4.3.2.2 Rated *conditional short-circuit current* (I_{cc}) on input power ports

The input *prospective short-circuit current* ratings apply to *ports* intended to be connected to *mains supply* or *non-mains supply* AC or DC sources, and to other *ports* for which *overcurrent* protection is necessary.

The *BDM/CDM/PDS* manufacturer shall specify a *conditional short-circuit current* (I_{cc}) rating for compliance to 4.3.2.2, and in addition the information in either a) or b):

a) information pertaining to the *short-circuit protective device*:

- minimum required prospective short-circuit current ($I_{cp, mr}$); and
 - 1) the protective device rated voltage, current, interrupt rating, I_p and I^2t at I_{cc} ; or
 - 2) the protective device manufacturer and part number;

b) information pertaining to the *short-circuit protective device*:

- the associated duration, and
- if a specific protective device is used to meet this requirement, the manufacturer shall specify the protective device manufacturer and part number.

The associated duration in b) is the time the maximum symmetrical *prospective short-circuit current* was applied during the test of 5.2.4.4, 5.2.4.5 and 5.2.4.10.

Compliance is shown through evaluation according to 4.2 to determine the appropriate combination of testing according to 5.2.4.4, 5.2.4.5 and 5.2.4.10 and in order to evaluate *abnormal operating conditions* and *single-fault condition*, including *insulation* faults.

For topologies where the *BDM/CDM* includes an input transformer, special attention should be made to the fact that the fault current is significantly higher at the primary side of the transformer. This especially applies to HV topologies. See IEC 61800-2:2021, Annex A.

If it is shown by analysis that the result of one test is representative of the worst case, less severe combinations need not be tested.

For marking, see 6.2.1.4 g).

4.3.2.3 Available output short-circuit current

The available *output short-circuit current* ratings apply to each output *port* where overcurrent protection is required to be selected between the output of a *BDM/CDM* and the input of another *BDM/CDM*.

For each output *port*, the short-circuit evaluation to determine the maximum available *output short-circuit current* shall be performed according to 5.2.4.5.

For marking, see 6.2.1.4 g).

4.3.2.4 Combined input and output ports

For *ports* which are both input and output *ports*, the applicable requirements of both 4.3.2.2 and 4.3.2.3 apply.

4.3.3 Short-circuit coordination (upstream protection)

Protective devices provided or specified shall have adequate capability to interrupt the *prospective short-circuit current* specified for the *port* to which they are connected.

If internal protection of the *BDM/CDM/PDS* is not rated for the *prospective short-circuit current*, the installation instructions shall specify the upstream protective device, rated for the *prospective short-circuit current* of that *port*, which shall be used to provide protection, see 6.3.9.6. The combination of these two *overcurrent* protective devices shall be specified by the manufacturer of the protective devices as suitable for use in combination for protection of a circuit having a *prospective short-circuit current* not exceeding the rating of the upstream protective device.

NOTE IEC 60364 (all parts) provides requirements for upstream protective devices in the *installation*. The above requirement ensures that the user is informed about any special characteristics of the upstream protective devices for the protection of the *PDS*, in addition to the requirements in IEC 60364 (all parts) or other local *installation* codes.

Compliance shall be checked by *visual inspection* in 5.2.1 and by the tests of 5.2.4.5.

4.3.4 Protection by several devices

Where protective devices that require manual replacement or resetting are used in more than one pole of a supply to a given load, those devices shall be located together unless this conflicts with another safety based design consideration.

NOTE Phase segregation to prevent or reduce arc fault is a possible reason why the protective devices might not be located together.

It is permitted to combine two or more protective devices in one *component*.

Location of the protective devices shall be defined in the documentation, see 6.2.

Compliance shall be checked by *visual inspection* in 5.2.1.

4.3.5 Motor overload and overtemperature protection

4.3.5.1 Means of protection

A motor of a *PDS* shall be protected against overtemperature. Depending on the application of the motor, one or more of the following means of protection a), b), c), d) or e) for each motor driven shall be selected by the *PDS* manufacturer:

- a) a thermal or electronic overload relay that complies with the applicable requirements in IEC 60947-4-1:2018;
- b) a *BDM/CDM* with *electronic motor overload protection* according to 4.3.5.2, which might include
 - 1) *thermal memory retention* according to 4.3.5.3, and/or
 - 2) speed sensitivity according to 4.3.5.4;
- c) a *BDM/CDM* with monitoring and trip based upon a signal from a thermal sensor mounted in or on the motor according to 4.3.5.5;
- d) an embedded motor thermal protection which disconnects the motor;
- e) information in accordance with 6.3.9.7.1.

NOTE 1 Selection a) and d) are the only possible motor overload protections in the case that several motors in parallel are supplied from the same *BDM/CDM* motor power port.

For information requirements, see 6.3.9.7 and 6.3.10.2.

NOTE 2 In the USA, compliance with US National Electrical Code ANSI/NFPA 70 for:

- overload protection according to 430.32 is achieved by a), b), c) or d); and
- overtemperature protection according to 430.126 is achieved by b) 1) and b) 2), c) or d).

4.3.5.2 *BDM/CDM with electronic motor overload protection*

Electronic motor overload protection shall comply with 5.2.4.6.1 to 5.2.4.6.4 and is subjected to the test requirements in 5.2.4.7.

Adjustable *electronic motor overload protection* shall not be adjustable in such a way that the limits of Table 37 are exceeded.

- a) For *PDS* where motor and *BDM/CDM* are known, limits other than those in Table 37 can be specified and tested in accordance with 5.2.4.6.1 to 5.2.4.6.4.
- b) For information requirements, see 6.3.9.7.2.

4.3.5.3 *BDM/CDM with electronic motor overload protection with thermal memory retention*

Electronic motor overload protection with thermal memory retention shall comply with 5.2.4.6.1 to 5.2.4.6.6 and is subjected to the requirements in 5.2.4.7.

4.3.5.4 *BDM/CDM with electronic motor overload protection which is speed sensitive*

Electronic motor overload protection that is speed sensitive shall comply with 5.2.4.6.1 to 5.2.4.6.7 and is subjected to the requirements in 5.2.4.7.

EXAMPLE Induction motor with fan mounted on the shaft.

4.3.5.5 *BDM/CDM providing monitoring and trip by means of thermal sensors*

BDM/CDM intended to be used with motors that have thermal protection or thermal sensor in or on the motors requiring signal *interface* shall be provided with means to connect to that protection.

Insulation requirements for the connection of the thermal protector or thermal sensor shall be taken into account. See Table 3.

For marking, see 6.3.10.2.

4.3.6 BDM/CDM providing current limiting control

BDM/CDM incorporating a current limiting control, i.e. a circuit that limits the output current to a set value regardless of the load on the motor, shall be tested according to 5.2.4.8.

NOTE Current limiting control can be a fixed or operator-adjustable value.

4.4 Protection against electric shock

4.4.1 General

Protection against electric shock depends on the *decisive voltage class (DVC)* from 4.4.2 and protection requirements from Table 3 and shall be provided by at least one of the following measures a) or b):

- a) *basic protection* from 4.4.3 and *fault protection* from 4.4.4; or
- b) *enhanced protection* from 4.4.5.

Protection under normal operating conditions is provided by *basic protection* 4.4.3, and protection under *single-fault conditions* is provided by *fault protection* 4.4.4.

Enhanced protection (see 4.4.5) provides protection under both normal operating conditions and *single-fault conditions*.

Basic protection, *fault protection* and *enhanced protection* may be achieved by means of *clearance* and *creepage distances* (see 4.4.7.4 and 4.4.7.5), *solid insulation* (see 4.4.7.8) or protection by means of *enclosure* and barriers (see 4.4.3.3) or a combination of those.

Clause A.6 provides an overview about the fundamental concept for protection against electric shock within this document.

NOTE In this document, 4.4.1 to 4.4.6 have been harmonized with the concepts of the horizontal standard IEC 61140 for protection against electric shock. *Basic protection*, *fault protection*, *enhanced protection* and the combination of those measures have been implemented.

Additional protection can be provided by residual current-operated protective devices (RCD). For further information, see 4.4.8.

4.4.2 Decisive voltage class (DVC)

4.4.2.1 General

This document defines four voltage levels with different requirements for the protection against electric shock: *DVC As*, *DVC B*, *DVC C* and *DVC D*.

The determination of a *decisive voltage class* includes the following considerations:

- a) environmental indoor unconditioned or outdoor unconditioned in Table 20;
- b) normal operating conditions, *abnormal operating conditions* and *single-fault conditions*;
- c) maximum *working voltage* V_{ac} RMS, V_{ac} peak and V_{dc} in Table 2, Figure 2, Figure 3 and Figure 4;
- d) protection requirement between circuits and between circuits and surroundings in 4.4.2.7 or Table 3;