

Safety of machinery — Electrical equipment of machines —

Part 1: General requirements

ICS 13.110; 31.020; 29.020

National foreword

This British Standard is the UK implementation of EN 60204-1:2006+A1:2009, incorporating corrigendum February 2010. It is derived from IEC 60204-1:2005, incorporating amendment 1:2008. It supersedes BS EN 60204-1:2006 which is withdrawn.

The start and finish of text introduced or altered by amendment is indicated in the text by tags. Tags indicating changes to IEC text carry the number of the amendment. For example, text altered by IEC amendment 1 is indicated by **A1** **A1**.

The CENELEC common modifications have been implemented at the appropriate places in the text. The start and finish of each common modification is indicated in the text by tags **C** **C**.

The UK participation in its preparation was entrusted to Technical Committee MCE/3, Safeguarding of machinery.

A list of organizations represented on this committee can be obtained on request to its secretary.

This publication does not purport to include all the necessary provisions of a contract. Users are responsible for its correct application.

Compliance with a British Standard cannot confer immunity from legal obligations.

This British Standard was published under the authority of the Standards Policy and Strategy Committee on 30 June 2006

© BSI 2010

ISBN 978 0 580 70975 3

Amendments/corrigenda issued since publication

Date	Comments
30 April 2009	Implementation of IEC amendment 1:2008 with CENELEC endorsement A1:2009
31 May 2010	Implementation of CENELEC corrigendum February 2010. Replacement of Annex ZZ

**Safety of machinery –
Electrical equipment of machines
Part 1: General requirements
(IEC 60204-1:2005, modified)**

Sécurité des machines –
Équipement électrique des machines
Partie 1: Règles générales
(CEI 60204-1:2005, modifiée)

Sicherheit von Maschinen –
Elektrische Ausrüstung von Maschinen
Teil 1: Allgemeine Anforderungen
(IEC 60204-1:2005, modifiziert)

This European Standard was approved by CENELEC on 2006-06-01. CENELEC members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for giving this European Standard the status of a national standard without any alteration.

Up-to-date lists and bibliographical references concerning such national standards may be obtained on application to the Central Secretariat or to any CENELEC member.

This European Standard exists in three official versions (English, French, German). A version in any other language made by translation under the responsibility of a CENELEC member into its own language and notified to the Central Secretariat has the same status as the official versions.

CENELEC members are the national electrotechnical committees of Austria, Belgium, Cyprus, the Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, the Netherlands, Norway, Poland, Portugal, Romania, Slovakia, Slovenia, Spain, Sweden, Switzerland and the United Kingdom.

CENELEC

European Committee for Electrotechnical Standardization
Comité Européen de Normalisation Electrotechnique
Europäisches Komitee für Elektrotechnische Normung

Central Secretariat: rue de Stassart 35, B - 1050 Brussels

Foreword

The text of the International Standard IEC 60204-1:2005, prepared by IEC TC 44, Safety of machinery – Electrotechnical aspects, together with common modifications prepared by the Technical Committee CENELEC TC 44X, Safety of machinery – Electrotechnical aspects, was approved by CENELEC as EN 60204-1 on 2006-06-01.

This European Standard supersedes EN 60204-1:1997.

The following dates were fixed:

- latest date by which the EN has to be implemented
at national level by publication of an identical
national standard or by endorsement (dop) 2007-06-01
- latest date by which the national standards conflicting
with the EN have to be withdrawn (dow) 2009-06-01

NOTE The application of this standard can involve the selection of components and/or parts that are to be integrated with the electrical equipment of a machine in accordance with the instructions and/or specifications of the manufacturers of the components and/or parts.

Also, in the context of legislative duties that are applicable to machinery manufacturers within the European Union it is important to recognise that the safety of electrical equipment can involve the use of equipment and services provided by other parties (see 3.54).

To assist manufacturers in satisfying these duties it can be necessary for the supplier of the equipment to obtain information about its intended use. This can be facilitated by establishing an agreement between the user and supplier on basic conditions and additional user requirements to enable proper design, application and utilization of the electrical equipment of the machine. An enquiry form that can be used for this purpose is provided in Annex B. Such an agreement is not intended to reduce the level of safety of the electrical equipment provided by this standard.

Endorsement notice

The text of the International Standard IEC 60204-1:2005 was approved by CENELEC as a European Standard with agreed common modifications.

Foreword to amendment A1

The text of document 44/575/CDV, future amendment 1 to IEC 60204-1:2005, prepared by IEC TC 44, Safety of machinery - Electrotechnical aspects, was submitted to the IEC-CENELEC parallel vote and was approved by CENELEC as amendment A1 to EN 60204-1:2006 on 2009-02-01.

The following dates were fixed:

- latest date by which the amendment has to be implemented at national level by publication of an identical national standard or by endorsement (dop) 2009-11-01
- latest date by which the national standards conflicting with the amendment have to be withdrawn (dow) 2012-02-01

Annex ZA has been added by CENELEC.

Endorsement notice

The text of amendment 1:2008 to the International Standard IEC 60204-1:2005 was approved by CENELEC as an amendment to the European Standard without any modification.

CONTENTS

INTRODUCTION	8
1 Scope	10
2 Normative references	11
3 Definitions	13
4 General requirements	20
4.1 General considerations	20
4.2 Selection of equipment	21
4.3 Electrical supply	22
4.4 Physical environment and operating conditions	23
4.5 Transportation and storage	25
4.6 Provisions for handling	25
4.7 Installation	25
5 Incoming supply conductor terminations and devices for disconnecting and switching off	25
5.1 Incoming supply conductor terminations	25
5.2 Terminal for connection to the external protective earthing system	26
5.3 Supply disconnecting (isolating) device	26
5.4 Devices for switching off for prevention of unexpected start-up	29
5.5 Devices for disconnecting electrical equipment	29
5.6 Protection against unauthorized, inadvertent and/or mistaken connection	30
6 Protection against electric shock	30
6.1 General	30
6.2 Protection against direct contact	30
6.3 Protection against indirect contact	33
6.4 Protection by the use of PELV	34
7 Protection of equipment	35
7.1 General	35
7.2 Overcurrent protection	35
7.3 Protection of motors against overheating	38
7.4 Abnormal temperature protection	39
7.5 Protection against supply interruption or voltage reduction and subsequent restoration	39
7.6 Motor overspeed protection	40
7.7 Earth fault/residual current protection	40
7.8 Phase sequence protection	40
7.9 Protection against overvoltages due to lightning and to switching surges	40
8 Equipotential bonding	40
8.1 General	40
8.2 Protective bonding circuit	43
8.3 Functional bonding	46
8.4 Measures to limit the effects of high leakage current	46

9	Control circuits and control functions	46
9.1	Control circuits	46
9.2	Control functions	47
9.3	Protective interlocks	52
9.4	Control functions in the event of failure	53
10	Operator interface and machine-mounted control devices	57
10.1	General	57
10.2	Push-buttons	58
10.3	Indicator lights and displays	60
10.4	Illuminated push-buttons	61
10.5	Rotary control devices	61
10.6	Start devices	61
10.7	Emergency stop devices	61
10.8	Emergency switching off devices	62
10.9	Enabling control device	63
11	Controlgear: location, mounting, and enclosures	63
11.1	General requirements	63
11.2	Location and mounting	63
11.3	Degrees of protection	65
11.4	Enclosures, doors and openings	65
11.5	Access to controlgear	66
12	Conductors and cables	67
12.1	General requirements	67
12.2	Conductors	67
12.3	Insulation	68
12.4	Current-carrying capacity in normal service	68
12.5	Conductor and cable voltage drop	69
12.6	Flexible cables	70
12.7	Conductor wires, conductor bars and slip-ring assemblies	71
13	Wiring practices	73
13.1	Connections and routing	73
13.2	Identification of conductors	74
13.3	Wiring inside enclosures	76
13.4	Wiring outside enclosures	76
13.5	Ducts, connection boxes and other boxes	79
14	Electric motors and associated equipment	81
14.1	General requirements	81
14.2	Motor enclosures	82
14.3	Motor dimensions	82
14.4	Motor mounting and compartments	82
14.5	Criteria for motor selection	82
14.6	Protective devices for mechanical brakes	83
15	Accessories and lighting	83
15.1	Accessories	83
15.2	Local lighting of the machine and equipment	83

16	Marking, warning signs and reference designations	84
16.1	General	84
16.2	Warning signs	85
16.3	Functional identification	85
16.4	Marking of equipment	85
16.5	Reference designations	86
17	Technical documentation	86
17.1	General	86
17.2	Information to be provided	86
17.3	Requirements applicable to all documentation	87
17.4	Installation documents	87
17.5	Overview diagrams and function diagrams	88
17.6	Circuit diagrams	88
17.7	Operating manual	89
17.8	Maintenance manual	89
17.9	Parts list	89
18	Verification	89
18.1	General	89
18.2	Verification of conditions for protection by automatic disconnection of supply	90
18.3	Insulation resistance tests	93
18.4	Voltage tests	94
18.5	Protection against residual voltages	94
18.6	Functional tests	94
18.7	Retesting	94
	Annex A (normative) Protection against indirect contact in TN-systems	95
	Annex B (informative) Enquiry form for the electrical equipment of machines	99
	Annex C (informative) Examples of machines covered by this part of IEC 60204	103
	Annex D (informative) Current-carrying capacity and overcurrent protection of conductors and cables in the electrical equipment of machines	105
	Annex E (informative) Explanation of emergency operation functions	111
	Annex F (informative) Guide for the use of this part of IEC 60204	112
	Annex G (informative) Comparison of typical conductor cross-sectional areas	114
	Annex ZA (normative) Normative references to international publications with their corresponding European publications	116
	Annex ZZ (informative) Coverage of Essential Requirements of EC Directives	120
	Bibliography	121
	Index	123
	Figure 1 – Block diagram of a typical machine	9
	Figure 2 – Example of equipotential bonding for electrical equipment of a machine	42
	Figure 3 – Method a)	56
	Figure 4 – Method b)	56
	Figure A.1 – Typical arrangement for fault loop impedance measurement	98

Figure D.1 – Methods of conductor and cable installation independent of number of conductors/cables.....	106
Figure D.2 – Parameters of conductors and protective devices.....	108
Table 1 – Minimum cross-sectional area of the external protective copper conductor.....	26
Table 2 – Colour-coding for push-button actuators and their meanings.....	59
Table 3 – Symbols for push-buttons.....	59
Table 4 – Colours for indicator lights and their meanings with respect to the condition of the machine.....	60
Table 5 – Minimum cross-sectional areas of copper conductors.....	67
Table 6 – Examples of current-carrying capacity (I_Z) of PVC insulated copper conductors or cables under steady-state conditions in an ambient air temperature of +40 °C for different methods of installation.....	69
Table 7 – Derating factors for cables wound on drums.....	71
Table 8 – Minimum permitted bending radii for the forced guiding of flexible cables.....	78
Table 9 – Application of the test methods for TN-systems.....	92
Table 10 – Examples of maximum cable length from each protective device to its load.....	93
Table A.1 – Maximum disconnecting times for TN systems.....	95
Table D.1 – Correction factors.....	105
Table D.2 – Derating factors from I_Z for grouping.....	107
Table D.3 – Derating factors from I_Z for multicore cables up to 10 mm ²	107
Table D.4 – Classification of conductors.....	108
Table D.5 – Maximum allowable conductor temperatures under normal and short-circuit conditions.....	109
Table F.1 – Application options.....	113
Table G.1 – Comparison of conductor sizes.....	114


INTRODUCTION

This part of IEC 60204 provides requirements and recommendations relating to the electrical equipment of machines so as to promote:

- safety of persons and property;
- consistency of control response;
- ease of maintenance.

More guidance on the use of this part of IEC 60204 is given in Annex F.

Figure 1 has been provided as an aid to the understanding of the inter-relationship of the various elements of a machine and its associated equipment. Figure 1 is a block diagram of a typical machine and associated equipment showing the various elements of the electrical equipment addressed in this part of IEC 60204. Numbers in parentheses () refer to Clauses and Subclauses in this part of IEC 60204. It is understood in Figure 1 that all of the elements taken together including the safeguards, tooling/fixtures, software, and the documentation, constitute the machine, and that one or more machines working together with usually at least one level of supervisory control constitute a manufacturing cell or system.



IEC 1388/05

Figure 1 – Block diagram of a typical machine

SAFETY OF MACHINERY – ELECTRICAL EQUIPMENT OF MACHINES –

Part 1: General requirements

1 Scope

This part of IEC 60204 applies to the application of electrical, electronic and programmable electronic equipment and systems to machines not portable by hand while working, including a group of machines working together in a co-ordinated manner.

NOTE 1 This part of IEC 60204 is an application standard and is not intended to limit or inhibit technological advancement.

NOTE 2 In this part of IEC 60204, the term *electrical* includes electrical, electronic and programmable electronic matters (i.e. *electrical equipment* means electrical, electronic and programmable electronic equipment).

NOTE 3 In the context of this part of IEC 60204, the term *person* refers to any individual and includes those persons who are assigned and instructed by the user or his agent(s) in the use and care of the machine in question.

The equipment covered by this part of IEC 60204 commences at the point of connection of the supply to the electrical equipment of the machine (see 5.1).

NOTE 4 The requirements for the electrical supply installation in buildings are given in the IEC 60364 series.

This part of IEC 60204 is applicable to the electrical equipment or parts of the electrical equipment that operate with nominal supply voltages not exceeding 1 000 V for alternating current (a.c.) and not exceeding 1 500 V for direct current (d.c.), and with nominal supply frequencies not exceeding 200 Hz.

NOTE 5 For higher voltages, see IEC 60204-11.

This part of IEC 60204 does not cover all the requirements (for example guarding, interlocking, or control) that are needed or required by other standards or regulations in order to protect persons from hazards other than electrical hazards. Each type of machine has unique requirements to be accommodated to provide adequate safety.

This part specifically includes, but is not limited to, the electrical equipment of machines as defined in 3.35.

NOTE 6 Annex C lists examples of machines whose electrical equipment can be covered by this part of IEC 60204.

Ⓒ This part of EN 60204 does not specify additional and special requirements that can apply to the electrical equipment of machines including those that

- are intended for use in open air (i.e. outside buildings or other protective structures);
- use, process, or produce potentially explosive material (for example paint or sawdust);
- are intended for use in potentially explosive and/or flammable atmospheres;
- have special risks when producing or using certain materials;
- are intended for use in mines;
- are sewing machines, units, and systems;
NOTE 7 For sewing machines, see EN 60204-31.
- are hoisting machines.
NOTE 8 For hoisting machines, see EN 60204-32. Ⓒ

Power circuits where electrical energy is directly used as a working tool are excluded from this part of IEC 60204.

2 Normative references

The following referenced documents are indispensable for the application of this part of IEC 60204. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60034-1, *Rotating electrical machines – Part 1: Rating and performance*

IEC 60034-5, *Rotating electrical machines – Part 5: Degrees of protection provided by the integral design of rotating electrical machines (IP code) – Classification*

IEC 60034-11, *Rotating electrical machines – Part 11: Thermal protection*

IEC 60072-1, *Dimensions and output series for rotating electrical machines – Part 1: Frame numbers 56 to 400 and flange numbers 55 to 1 080*

IEC 60072-2, *Dimensions and output series for rotating electrical machines – Part 2: Frame numbers 355 to 1 000 and flange numbers 1 180 to 2 360*

IEC 60073:2002, *Basic and safety principles for man-machine interface, marking and identification – Coding principles for indicators and actuators*

IEC 60309-1:1999, *Plugs, socket-outlets, and couplers for industrial purposes – Part 1: General requirements*

ⓘ IEC 60364-4-41:2005, *Low-voltage electrical installations – Part 4-41: Protection for safety – Protection against electric shock* ⓘ

IEC 60364-4-43:2001, *Electrical installations of buildings – Part 4-43: Protection for safety – Protection against overcurrent*

IEC 60364-5-52:2001, *Electrical installations of buildings – Part 5-52: Selection and erection of electrical equipment – Wiring systems*

IEC 60364-5-53:2002, *Electrical installations of buildings – Part 5-53: Selection and erection of electrical equipment – Isolation, switching and control*

IEC 60364-5-54:2002, *Electrical installations of buildings – Part 5-54: Selection and erection of electrical equipment – Earthing arrangements, protective conductors and protective bonding conductors*

IEC 60364-6-61:2001, *Electrical installations of buildings – Part 6-61: Verification – Initial verification*

IEC 60417-DB:2002¹, *Graphical symbols for use on equipment*

¹ “DB” refers to the IEC on-line database.

IEC 60439-1:1999, *Low-voltage switchgear and controlgear assemblies – Part 1: Type-tested and partially type-tested assemblies*

IEC 60445:1999, *Basic and safety principles for man-machine interface, marking and identification – Identification of equipment terminals and of terminations of certain designated conductors, including general rules for an alphanumeric system*

IEC 60446:1999, *Basic and safety principles for man-machine interface, marking and identification – Identification of conductors by colours or numerals*

IEC 60447:2004, *Basic and safety principles for man-machine interface, marking and identification – Man-machine interface (MMI) – Actuating principles*

IEC 60529:1999, *Degrees of protection provided by enclosures (IP Code)*
Amendment 1 (2001)

IEC 60617-DB:2001², *Graphical symbols for diagrams*

IEC 60621-3:1979, *Electrical installations for outdoor sites under heavy conditions (including open-cast mines and quarries) – Part 3: General requirements for equipment and ancillaries*

IEC 60664-1:1992, *Insulation co-ordination for equipment within low-voltage systems – Part 1: Principles, requirements and tests*

IEC 60947-1:2004, *Low-voltage switchgear and controlgear – Part 1: General rules*

IEC 60947-2:2003, *Low-voltage switchgear and controlgear – Part 2: Circuit-breakers*

IEC 60947-3:1999, *Low-voltage switchgear and controlgear – Part 3: Switches, disconnectors, switch-disconnectors, and fuse combination units*

IEC 60947-5-1:2003, *Low-voltage switchgear and controlgear – Part 5-1: Control circuit devices and switching elements – Electromechanical control circuit devices*

IEC 60947-7-1:2002, *Low-voltage switchgear and controlgear – Part 7-1: Ancillary equipment – Terminal blocks for copper conductors*

IEC 61082-1:1991, *Preparation of documents used in electrotechnology – Part 1: General requirements*

IEC 61082-2:1993, *Preparation of documents used in electrotechnology – Part 2: Function-oriented diagrams*

IEC 61082-3:1993, *Preparation of documents used in electrotechnology – Part 3: Connection diagrams, tables and lists*

IEC 61082-4:1996, *Preparation of documents used in electrotechnology – Part 4: Location and installation documents*

IEC 61140:2001, *Protection against electric shock – Common aspects for installation and equipment*

IEC 61310 (all parts), *Safety of machinery – Indication, marking and actuation*

IEC 61346 (all parts), *Industrial systems, installations and equipment and industrial products – Structuring principles and reference designations*

² “DB” refers to the IEC on-line database.

IEC 61557-3:1997, *Electrical safety in low voltage distribution systems up to 1000 V a.c. and 1500 V d.c. – Equipment for testing, measuring or monitoring of protective measures –Part 3: Loop impedance*

IEC 61558-1:1997, *Safety of power transformers, power supply units and similar – Part 1: General requirements and tests*
Amendment 1 (1998)

IEC 61558-2-6, *Safety of power transformers, power supply units and similar – Part 2-6: Particular requirements for safety isolating transformers for general use*

IEC 61984:2001, *Connectors – Safety requirements and tests*

IEC 62023:2000, *Structuring of technical information and documentation*

IEC 62027:2000, *Preparation of parts lists*

IEC 62061:2005, *Safety of machinery – Functional safety of safety-related electrical, electronic and programmable electronic control systems*

IEC 62079:2001, *Preparation of instructions – Structuring, content and presentation*

ISO 7000:2004, *Graphical symbols for use on equipment – Index and synopsis*

ISO 12100-1:2003, *Safety of machinery – Basic concepts, general principles for design – Part 1: Basic terminology, methodology*

ISO 12100-2:2003, *Safety of machinery – Basic concepts, general principles for design – Part 2: Technical principles*

ISO 13849-1:2006, *Safety of machinery – Safety-related parts of control systems – Part 1: General principles for design* 

ISO 13849-2:2003, *Safety of machinery – Safety-related parts of control systems – Part 2: Validation*

ISO 13850:2006, *Safety of machinery – Emergency stop – Principles for design* 

3 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

3.1

actuator

part of a device to which an external manual action is to be applied

NOTE 1 The actuator may take the form of a handle, knob, push-button, roller, plunger, etc.

NOTE 2 There are some actuating means that do not require an external actuating force, but only an action.

NOTE 3 See also 3.34.

3.2

ambient temperature

temperature of the air or other medium where the equipment is to be used

3.3

barrier

part providing protection against direct contact from any usual direction of access

3.4

cable tray

cable support consisting of a continuous base and raised edges and no covering

NOTE A cable tray may be perforated or non-perforated.

[IEV 826-15-08]

3.5

cable trunking system

system of closed enclosures comprising a base with a removable cover intended for the complete surrounding of insulated conductors, cables, cords and for the accommodation of other electrical equipment

3.6

concurrent

acting in conjunction; used to describe a situation wherein two or more control devices exist in an actuated condition at the same time (but not necessarily synchronously)

3.7

conduit

part of a closed wiring system of circular or non-circular cross-section for insulated conductors and/or cables in electrical installations, allowing them to be drawn in and/or replaced

NOTE Conduits should be sufficiently close-jointed so that the insulated conductors and/or cables can only be drawn in and not inserted laterally.

[IEV 826-06-03]

3.8

control circuit (of a machine)

circuit used for the control, including monitoring, of a machine and the electrical equipment

3.9

control device

device connected into the control circuit and used for controlling the operation of the machine (for example position sensor, manual control switch, relay, contactor, magnetically operated valve)

3.10

controlgear

switching devices and their combination with associated control, measuring, protective, and regulating equipment, also assemblies of such devices and equipment with associated interconnections, accessories, enclosures, and supporting structures, intended in principle for the control of electrical energy consuming equipment

[IEV 441-11-03, modified]

3.11

controlled stop

stopping of machine motion with electrical power to the machine actuators maintained during the stopping process

3.12

direct contact

contact of persons or livestock with live parts

[IEV 826-12-03]

3.13

direct opening action (of a contact element)

achievement of contact separation as the direct result of a specified movement of the switch actuator through non-resilient members (for example not dependent upon springs)

[IEC 60947-5-1, K.2.2]

3.14

duct

enclosed channel designed expressly for holding and protecting electrical conductors, cables, and busbars

NOTE Conduits (see 3.7), cable trunking systems (see 3.5) and underfloor channels are types of duct.

3.15

electrical operating area

room or location for electrical equipment to which access is intended to be restricted to skilled or instructed persons, by the opening of a door or the removal of a barrier without the use of a key or tool, and which is clearly marked by appropriate warning signs

3.16

electronic equipment

part of the electrical equipment containing circuitry dependent for its operation on electronic devices and components

3.17

emergency stop device

manually actuated control device used to initiate an emergency stop function

[ISO 13850, 3.2]

NOTE See Annex E.

3.18

emergency switching off device

manually actuated control device used to switch off the supply of electrical energy to all or a part of an installation where a risk of electric shock or another risk of electrical origin is involved

NOTE See Annex E.

3.19

enclosed electrical operating area

room or location for electrical equipment to which access is intended to be restricted to skilled or instructed persons by the opening of a door or the removal of a barrier by the use of a key or tool and which is clearly marked by appropriate warning signs

3.20

enclosure

part providing protection of equipment against certain external influences and, in any direction, protection against direct contact

NOTE The definition taken from the existing IEC 60204 needs the following explanations within the scope of this part of IEC 60204:

- a) Enclosures provide protection of persons or livestock against access to hazardous parts.
- b) Barriers, shaped openings, or any other means suitable to prevent or limit the penetration of the specified test probes, whether attached to the enclosure or formed by the enclosed equipment, are considered as part of the enclosure, except where they can be removed without the use of a key or tool.
- c) An enclosure may be:
 - a cabinet or box, either mounted on the machine or separate from the machine;
 - a compartment consisting of an enclosed space within the machine structure.

3.21

equipment

material, fittings, devices, components, appliances, fixtures, apparatus, and the like used as part of, or in connection with, the electrical equipment of machines

3.22

equipotential bonding

provision of electric connections between conductive parts, intended to achieve equipotentiality

[IEV 195-1-10]

3.23

exposed conductive part

conductive part of electrical equipment, which can be touched and which is not live under normal operating conditions, but which can become live under fault conditions

[IEV 826-12-10, modified]

3.24

extraneous conductive part

conductive part not forming part of the electrical installation and liable to introduce a potential, generally the earth potential

[IEV 826-12-11, modified]

3.25

failure

termination of the ability of an item to perform a required function

NOTE 1 After failure, the item has a fault.

NOTE 2 "Failure" is an event, as distinguished from "fault", which is a state.

NOTE 3 This concept as defined does not apply to items consisting of software only.

[IEV 191-04-01]

NOTE 4 In practice, the terms fault and failure are often used synonymously.

3.26

fault

state of an item characterized by inability to perform a required function, excluding the inability during preventive maintenance or other planned actions, or due to lack of external resources

NOTE 1 A fault is often the result of a failure of the item itself, but may exist without prior failure.

NOTE 2 In English, the term "fault" and its definition are identical with those given in IEC 191-05-01. In the field of machinery, the French term "défaut" and the German term "Fehler" are used rather than the terms "panne" and "Fehlzustand" that appear with this definition.

3.27

functional bonding

equipotential bonding necessary for proper functioning of electrical equipment

3.28

hazard

potential source of physical injury or damage to health

NOTE 1 The term hazard can be qualified in order to define its origin (for example, mechanical hazard, electrical hazard) or the nature of the potential harm (for example, electric shock hazard, cutting hazard, toxic hazard, fire hazard).

NOTE 2 The hazard envisaged in this definition:

- either is permanently present during the intended use of the machine (for example motion of hazardous moving elements, electric arc during a welding phase, unhealthy posture, noise emission, high temperature);
- or can appear unexpectedly (for example: explosion, crushing hazard as a consequence of an unintended/unexpected start-up, ejection as a consequence of a breakage, fall as a consequence of acceleration/deceleration).

[ISO 12100-1, 3.6, modified]

3.29

indirect contact

contact of persons or livestock with exposed conductive parts which have become live under fault conditions

[IEV 826-12-04, modified]

3.30

inductive power supply system

system of inductive power transfer, consisting of a track converter and a track conductor, along which one or more pick-up(s) and associated pick-up converter(s) can move, without any galvanic or mechanical contact, in order to transfer electrical power for example to a mobile machine

NOTE The track conductor and the pick-up are analogous to the primary and secondary of a transformer respectively.

3.31

(electrically) instructed person

person adequately advised or supervised by an electrically skilled person to enable him or her to perceive risks and to avoid hazards which electricity can create

[IEV 826-18-02, modified]

3.32

interlock (for safeguarding)

arrangement that interconnects guard(s) or device(s) with the control system and/or all or part of the electrical supply to the machine

3.33

live part

conductor or conductive part intended to be energized in normal use, including a neutral conductor, but, by convention, not a PEN conductor

NOTE This term does not necessarily imply a risk of electric shock.

3.34

machine actuator

power mechanism used to effect motion of the machine

3.35

machinery

machine

assembly of linked parts or components, at least one of which moves, with the appropriate machine actuators, control and power circuits, joined together for a specific application, in particular for the processing, treatment, moving or packaging of a material.

The term "machinery" also covers an assembly of machines which, in order to achieve the same end, are arranged and controlled so that they function as an integral whole

[ISO 12100-1, 3.1, modified]

NOTE The term "component" is used here in a general sense and it does not refer only to electrical components.

3.36

marking

signs or inscriptions primarily for the purpose of identifying equipment, components and/or devices, which can include certain features thereof

3.37

neutral conductor

N

conductor connected to the neutral point of a system and capable of contributing to the transmission of electrical energy

[IEV 826-14-07, modified]

3.38

obstacle

part preventing unintentional direct contact, but not preventing direct contact by deliberate action

3.39

overcurrent

current exceeding the rated value. For conductors, the rated value is the current-carrying capacity

[IEV 826-11-14, modified]

3.40

overload (of a circuit)

time/current relationship in a circuit which is in excess of the rated full load of the circuit when the circuit is not under a fault condition

NOTE *Overload* should not be used as a synonym for *overcurrent*.

3.41

plug/socket combination

component and a suitable mating component, appropriate to terminate conductors, intended for connection or disconnection of two or more conductors

NOTE Examples of plug/socket combination include:

- connectors which fulfil the requirements of IEC 61984;
- a plug and socket-outlet, a cable coupler, or an appliance coupler in accordance with IEC 60309-1;
- a plug and socket-outlet in accordance with IEC 60884-1 or an appliance coupler in accordance with IEC 60320-1.

3.42

power circuit

circuit that supplies power from the supply network to units of equipment used for productive operation and to transformers supplying control circuits

3.43

protective bonding

equipotential bonding for protection against electric shock

NOTE Measures for protection against electric shock can also reduce the risk of burns or fire.

3.44

protective bonding circuit

protective conductors and conductive parts connected together to provide protection against electric shock in the event of an insulation failure

3.45

protective conductor

conductor required for protective bonding by some measures for protection against electric shock for electrically connecting any of the following parts:

- exposed conductive parts;
- extraneous conductive parts;
- main earthing terminal (PE)

[IEV 826-13-22, modified]

3.46

redundancy

application of more than one device or system, or part of a device or system, with the objective of ensuring that in the event of one failing to perform its function, another is available to perform that function

3.47

reference designation

distinctive code which serves to identify an object in the documentation and on the equipment

NOTE ???

3.48

risk

combination of the probability of occurrence of harm (i.e. physical injury or damage to health) and the severity of that harm

[ISO 12100-1, 3.11, modified]

3.49

safeguard

guard or protective device provided as a means to protect persons from a hazard

3.50

safeguarding

protective measure using safeguards to protect persons from the hazards which cannot reasonably be eliminated or from the risks which cannot be sufficiently reduced by inherently safe design measures

[ISO 12100-1, 3.20]

3.51

servicing level

level on which persons stand when operating or maintaining the electrical equipment

3.52

short-circuit current

overcurrent resulting from a short circuit due to a fault or an incorrect connection in an electric circuit

[IEV 441-11-07]

3.53

(electrically) skilled person

person with relevant training, education and experience to enable him or her to perceive risks and to avoid hazards associated with electricity

[IEV 826-18-01, modified]

3.54

supplier

entity (for example manufacturer, contractor, installer, integrator) who provides equipment or services associated with the machine

NOTE The user organization may also act in the capacity of a supplier to itself.

3.55

switching device

device designed to make and/or break the current in one or more electric circuits

[IEV 441-14-01, modified]

NOTE A switching device may perform one or both of these actions.

3.56

uncontrolled stop

stopping of machine motion by removing electrical power to the machine actuators

 NOTE This definition does not imply any particular state of other (for example, non-electrical) stopping devices, for example mechanical or hydraulic brakes that are outside the scope of this standard. 

3.57

user

entity who utilizes the machine and its associated electrical equipment

4 General requirements

4.1 General

This part of IEC 60204 is intended to apply to electrical equipment used with a wide variety of machines and with a group of machines working together in a co-ordinated manner.

The risks associated with the hazards relevant to the electrical equipment shall be assessed as part of the overall requirements for risk assessment of the machine. This will determine the adequate risk reduction, and the necessary protective measures for persons who can be exposed to those hazards, while still maintaining an acceptable level of performance of the machine and its equipment.

Hazardous situations can result from, but are not limited to, the following causes:

- failures or faults in the electrical equipment resulting in the possibility of electric shock or electrical fire;
- failures or faults in control circuits (or components and devices associated with those circuits) resulting in the malfunctioning of the machine;
- disturbances or disruptions in power sources as well as failures or faults in the power circuits resulting in the malfunctioning of the machine;
- loss of continuity of circuits that depend upon sliding or rolling contacts, resulting in a failure of a safety function;
- electrical disturbances for example, electromagnetic, electrostatic either from outside the electrical equipment or internally generated, resulting in the malfunctioning of the machine;
- release of stored energy (either electrical or mechanical) resulting in, for example, electric shock, unexpected movement that can cause injury;
-  Text deleted 
- surface temperatures that can cause injury.

Safety measures are a combination of the measures incorporated at the design stage and those measures required to be implemented by the user.

The design and development process shall identify hazards and the risks arising from them. Where the hazards cannot be removed and/or the risks cannot be sufficiently reduced by inherently safe design measures, protective measures (for example safeguarding,) shall be provided to reduce the risk. Additional means (for example, awareness means) shall be provided where further risk reduction is necessary. In addition, working procedures that reduce risk can be necessary.

The use of the enquiry form as shown in Annex B of this part of IEC 60204 is recommended in order to facilitate an appropriate agreement between the user and the supplier(s) on basic conditions and additional user specifications related to the electrical equipment. Those additional specifications are to:

- provide additional features that are dependent on the type of machine (or group of machines) and the application;
- facilitate maintenance and repair; and
- improve the reliability and ease of operation.

4.2 Selection of equipment

4.2.1 General

Electrical components and devices shall:

- be suitable for their intended use; and
- conform to relevant IEC standards where such exist; and
- be applied in accordance with the supplier's instructions.

4.2.2 Electrical equipment in compliance with the EN 60439 series

The electrical equipment of the machine shall satisfy the safety requirements identified by the risk assessment of the machine. Depending upon the machine, its intended use and its electrical equipment, the designer may select parts of the electrical equipment of the machine that are in compliance with EN 60439-1 and, as necessary, other relevant parts of the EN 60439 series (see also Annex F). 

4.3 Electrical supply

4.3.1 General

The electrical equipment shall be designed to operate correctly with the conditions of the supply:

- as specified in 4.3.2 or 4.3.3, or
- as otherwise specified by the user (see Annex B), or
- as specified by the supplier in the case of a special source of supply such as an on-board generator.

4.3.2 AC supplies

Voltage	Steady state voltage: 0,9 to 1,1 of nominal voltage.
Frequency	0,99 to 1,01 of nominal frequency continuously; 0,98 to 1,02 short time.
Harmonics	Harmonic distortion not exceeding 10 % of the total r.m.s. voltage between live conductors for the sum of the 2 nd through to the 5 th harmonic. An additional 2 % of the total r.m.s. voltage between live conductors for the sum of the 6 th through to the 30 th harmonic is permissible.
Voltage unbalance	Neither the voltage of the negative sequence component nor the voltage of the zero sequence component in three-phase supplies exceeding 2 % of the positive sequence component.
Voltage interruption	Supply interrupted or at zero voltage for not more than 3 ms at any random time in the supply cycle with more than 1 s between successive interruptions.
Voltage dips	Voltage dips not exceeding 20 % of the peak voltage of the supply for more than one cycle with more than 1 s between successive dips.

4.3.3 DC supplies

From batteries:

Voltage	0,85 to 1,15 of nominal voltage; 0,7 to 1,2 of nominal voltage in the case of battery-operated vehicles.
Voltage interruption	Not exceeding 5 ms.

From converting equipment:

Voltage 0,9 to 1,1 of nominal voltage.

Voltage interruption Not exceeding 20 ms with more than 1 s between successive interruptions.

NOTE This is a variation to IEC Guide 106 to ensure proper operation of electronic equipment.

Ripple (peak-to-peak) Not exceeding 0,15 of nominal voltage.

4.3.4 Special supply systems

For special supply systems such as on-board generators, the limits given in 4.3.2 and 4.3.3 may be exceeded provided that the equipment is designed to operate correctly with those conditions.

4.4 Physical environment and operating conditions

4.4.1 General

☐ The electrical equipment shall be suitable for the physical environment and operating conditions of its intended use. The requirements of 4.4.2 to 4.4.8 cover the physical environment and operating conditions of the majority of machines covered by this part of EN 60204. When special conditions apply or the limits specified are exceeded, an agreement between user and supplier (see 4.1) is recommended (see Annex B). ☐

4.4.2 Electromagnetic compatibility (EMC)

The equipment shall not generate electromagnetic disturbances above levels that are appropriate for its intended operating environment. In addition, the equipment shall have a level of immunity to electromagnetic disturbances so that it can function in its intended environment.

NOTE 1 The generic EMC standards IEC 61000-6-1 or IEC 61000-6-2 and CISPR 61000-6-3 or IEC 61000-6-4 give general EMC emission and immunity limits.

NOTE 2 IEC 61000-5-2 gives guidelines for earthing and cabling of electrical and electronic systems aimed at ensuring EMC. If specific product standards exist (for example, IEC 61496-1, IEC 61800-3, IEC 60947-5-2) they take precedence over generic standards.

Measures to limit the generation of electromagnetic disturbances, i.e. conducted and radiated emissions include:

- power supply filtering;
- cable shielding;
- enclosures designed to minimize RF radiation;
- RF suppression techniques.

Measures to enhance the immunity of the equipment against conducted and radiated RF disturbance include:

- design of functional bonding system taking into account the following;
 - connection of sensitive electrical circuits to the chassis. Such terminations should be marked or labelled with the symbol IEC 60417-5020 (DB:2002-10):



- connection of the chassis to earth (PE) using a conductor with low RF impedance and as short as practicable;
- connection of sensitive electrical equipment or circuits directly to the PE circuit or to a functional earthing conductor (FE) (see Figure 2), to minimize common mode disturbance. This latter terminal should be marked or labelled by the symbol IEC 60417-5018 (DB:2002-10):



- separation of sensitive circuits from disturbance sources;
- enclosures designed to minimize RF transmission;
- EMC wiring practices:
 - using twisted conductors to reduce the effect of differential mode disturbances,
 - keeping sufficient distance between conductors emitting disturbances and conductors of sensitive circuits,
 - using cable orientation as close to 90° as possible when cables cross,
 - running the conductors as close as possible to the ground plane,
 - using electrostatic screens and/or electromagnetic shields with a low RF impedance termination.

4.4.3 Ambient air temperature

☐ Electrical equipment shall be capable of operating correctly in the intended ambient air temperature. The minimum requirement for all electrical equipment is correct operation between air temperatures of +5 °C and +40 °C. For very hot environments (for example hot climates, steel mills, paper mills) and for cold environments, additional measures are recommended (see Annex B). ☐

4.4.4 Humidity

The electrical equipment shall be capable of operating correctly when the relative humidity does not exceed 50 % at a maximum temperature of +40 °C. Higher relative humidities are permitted at lower temperatures (for example 90 % at 20 °C).

Harmful effects of occasional condensation shall be avoided by design of the equipment or, where necessary, by additional measures (for example built-in heaters, air conditioners, drain holes).

4.4.5 Altitude

Electrical equipment shall be capable of operating correctly at altitudes up to 1 000 m above mean sea level.

4.4.6 Contaminants

Electrical equipment shall be adequately protected against the ingress of solids and liquids (see 11.3).

The electrical equipment shall be adequately protected against contaminants (for example dust, acids, corrosive gases, salts) that can be present in the physical environment in which the electrical equipment is to be installed (see Annex B).

4.4.7 Ionizing and non-ionizing radiation

ⓘ When equipment is subject to radiation (for example microwave, ultraviolet, lasers, X-rays), additional measures shall be taken to avoid malfunctioning of the equipment and accelerated deterioration of the insulation. A special agreement is recommended between the supplier and the user (see Annex B). ⓘ

4.4.8 Vibration, shock, and bump

ⓘ Undesirable effects of vibration, shock and bump (including those generated by the machine and its associated equipment and those created by the physical environment) shall be avoided by the selection of suitable equipment, by mounting it away from the machine, or by provision of anti-vibration mountings. A special agreement is recommended between the supplier and the user (see Annex B). ⓘ

4.5 Transportation and storage

Electrical equipment shall be designed to withstand, or suitable precautions shall be taken to protect against, the effects of transportation and storage temperatures within a range of -25°C to $+55^{\circ}\text{C}$ and for short periods not exceeding 24 h at up to $+70^{\circ}\text{C}$. Suitable means shall be provided to prevent damage from humidity, vibration, and shock. A special agreement can be necessary between the supplier and the user (see Annex B).

NOTE Electrical equipment susceptible to damage at low temperatures includes PVC insulated cables.

4.6 Provisions for handling

Heavy and bulky electrical equipment that has to be removed from the machine for transport, or that is independent of the machine, shall be provided with suitable means for handling by cranes or similar equipment.

4.7 Installation

Electrical equipment shall be installed in accordance with the electrical equipment supplier's instructions.

5 Incoming supply conductor terminations and devices for disconnecting and switching off

5.1 Incoming supply conductor terminations

It is recommended that, where practicable, the electrical equipment of a machine is connected to a single incoming supply. Where another supply is necessary for certain parts of the equipment (for example, electronic equipment that operates at a different voltage), that supply should be derived, as far as is practicable, from devices (for example, transformers, converters) forming part of the electrical equipment of the machine. For large complex machinery comprising a number of widely-spaced machines working together in a co-ordinated manner, there can be a need for more than one incoming supply depending upon the site supply arrangements (see 5.3.1).

Unless a plug is provided with the machine for the connection to the supply (see 5.3.2 e), it is recommended that the supply conductors are terminated at the supply disconnecting device.

Where a neutral conductor is used it shall be clearly indicated in the technical documentation of the machine, such as in the installation diagram and in the circuit diagram, and a separate insulated terminal, labelled **N** in accordance with 16.1, shall be provided for the neutral conductor (see also Annex B).

There shall be no connection between the neutral conductor and the protective bonding circuit inside the electrical equipment nor shall a combined PEN terminal be provided.

Exception: a connection may be made between the neutral terminal and the PE terminal at the point of the connection of the power supply to the machine for TN-C systems.

All terminals for the incoming supply connection shall be clearly identified in accordance with IEC 60445 and 16.1. For the identification of the external protective conductor terminal, see 5.2.

ⓘ See 17.8 for the provision of instructions for maintenance. ⓘ

5.2 Terminal for connection to the external protective earthing system

For each incoming supply, a terminal shall be provided in the vicinity of the associated phase conductor terminals for connection of the machine to the external protective earthing system or to the external protective conductor, depending upon the supply distribution system.

The terminal shall be of such a size as to enable the connection of an external protective copper conductor with a cross-sectional area in accordance with Table 1.

Table 1 – Minimum cross-sectional area of the external protective copper conductor

Cross-sectional area of copper phase conductors supplying the equipment $S \text{ mm}^2$	Minimum cross-sectional area of the external protective copper conductor $S_p \text{ mm}^2$
$S \leq 16$	S
$16 < S \leq 35$	16
$S > 35$	$S/2$

Where an external protective conductor of a material other than copper is used, the terminal size shall be selected accordingly (see also 8.2.2).

At each incoming supply point, the terminal for connection of the external protective earthing system or the external protective conductor shall be marked or labelled with the letters **PE** (see IEC 60445).

5.3 Supply disconnecting (isolating) device

5.3.1 General

A supply disconnecting device shall be provided:

- for each incoming source of supply to a machine(s);

NOTE The incoming supply can be connected directly to the machine or via a feeder system. Feeder systems of machines can include conductor wires, conductor bars, slip-ring assemblies, flexible cable systems (reeled, festooned) or inductive power supply systems.

- for each on-board power supply.

The supply disconnecting device shall disconnect (isolate) the electrical equipment of the machine from the supply when required (for example for work on the machine, including the electrical equipment).

When two or more supply disconnecting devices are provided, protective interlocks for their correct operation shall also be provided in order to prevent a hazardous situation, including damage to the machine or to the work in progress.

5.3.2 Type

The supply disconnecting device shall be one of the following types:

- a) switch-disconnector, with or without fuses, in accordance with IEC 60947-3, utilization category AC-23B or DC-23B;
- b) disconnector, with or without fuses, in accordance with IEC 60947-3, that has an auxiliary contact that in all cases causes switching devices to break the load circuit before the opening of the main contacts of the disconnector;
- c) a circuit-breaker suitable for isolation in accordance with IEC 60947-2;
- d) any other switching device in accordance with an IEC product standard for that device and which meets the isolation requirements of IEC 60947-1 as well as a utilization category defined in the product standard as appropriate for on-load switching of motors or other inductive loads;
- e) a plug/socket combination for a flexible cable supply.

5.3.3 Requirements

When the supply disconnecting device is one of the types specified in 5.3.2 a) to d) it shall fulfil all of the following requirements:

- isolate the electrical equipment from the supply and have one OFF (isolated) and one ON position marked with "O" and "I" (symbols IEC 60417-5008 (DB:2002-10) and IEC 60417-5007 (DB:2002-10), see 10.2.2);
- have a visible contact gap or a position indicator which cannot indicate OFF (isolated) until all contacts are actually open and the requirements for the isolating function have been satisfied;
- have an external operating means (for example handle), (**exception:** power-operated switchgear need not be operable from outside the enclosure where there are other means to open it). Where the external operating means is not intended for emergency operations, it is recommended that it be coloured BLACK or GREY (see 10.7.4 and 10.8.4);
- be provided with a means permitting it to be locked in the OFF (isolated) position (for example by padlocks). When so locked, remote as well as local closing shall be prevented;
- disconnect all live conductors of its power supply circuit. However, for TN supply systems, the neutral conductor may or may not be disconnected except in countries where disconnection of the neutral conductor (when used) is compulsory;
- have a breaking capacity sufficient to interrupt the current of the largest motor when stalled together with the sum of the normal running currents of all other motors and/or loads. The calculated breaking capacity may be reduced by the use of a proven diversity factor.

When the supply disconnecting device is a plug/socket combination, it shall fulfil the following requirements:

- have the switching capability, or be interlocked with a switching device that has a breaking capacity, sufficient to interrupt the current of the largest motor when stalled together with the sum of the normal running currents of all other motors and/or loads. The calculated breaking capacity may be reduced by the use of a proven diversity factor. When the interlocked switching device is electrically operated (for example a contactor) it shall have an appropriate utilisation category.
- a) to f) of 13.4.5.

NOTE A suitably rated plug and socket-outlet, cable coupler, or appliance coupler, in accordance with IEC 60309-1 can fulfil these requirements.

Where the supply disconnecting device is a plug/socket combination, a switching device with an appropriate utilisation category shall be provided for switching the machine on and off. This can be achieved by the use of the interlocked switching device described above.

5.3.4 Operating means

The operating means (for example, a handle) of the supply disconnecting device shall be easily accessible and located between 0,6 m and 1,9 m above the servicing level. An upper limit of 1,7 m is recommended.

NOTE The direction of operation is given in IEC 61310-3.

5.3.5 Excepted circuits

The following circuits need not be disconnected by the supply disconnecting device:

- lighting circuits for lighting needed during maintenance or repair;
- plug and socket outlets for the exclusive connection of repair or maintenance tools and equipment (for example hand drills, test equipment);
- undervoltage protection circuits that are only provided for automatic tripping in the event of supply failure;
- circuits supplying equipment that should normally remain energized for correct operation (for example temperature controlled measuring devices, product (work in progress) heaters, program storage devices);
- control circuits for interlocking.

It is recommended, however, that such circuits be provided with their own disconnecting device.

Where such a circuit is not disconnected by the supply disconnecting device:

- permanent warning label(s) in accordance with 16.1 shall be appropriately placed in proximity to the supply disconnecting device;
- a corresponding statement shall be included in the maintenance manual, and one or more of the following shall apply;
 - a permanent warning label in accordance with 16.1 is affixed in proximity to each excepted circuit, or
 - the excepted circuit is separated from other circuits, or
 - the conductors are identified by colour taking into account the recommendation of 13.2.4.

5.4 Devices for switching off for prevention of unexpected start-up

Devices for switching off for the prevention of unexpected start-up shall be provided (for example where, during maintenance, a start-up of the machine or part of the machine can create a hazard).

Such devices shall be appropriate and convenient for the intended use, shall be suitably placed, and readily identifiable as to their function and purpose (for example by a durable marking in accordance with 16.1 where necessary).

NOTE 1 This part of IEC 60204 does not address all provisions for prevention of unexpected start up. See ISO 14118 (EN 1037).

Means shall be provided to prevent inadvertent and/or mistaken closure of these devices either at the controller or from other locations (see also 5.6).

 NOTE 2 Further information on the location and actuation of devices such as those used for the prevention of unexpected start-up is provided in EN 60447. 

The following devices that fulfil the isolation function may be provided for this purpose:

- devices described in 5.3.2,
- disconnectors, withdrawable fuse links and withdrawable links only if located in an enclosed electrical operating area (see 3.19).

Devices that do not fulfil the isolation function (for example a contactor switched off by a control circuit) may only be provided where intended to be used for situations that include:

- inspections;
- adjustments;
- work on the electrical equipment where:
 - there is no hazard arising from electric shock (see Clause 6) and burn;
 - the switching off means remains effective throughout the work;
 - the work is of a minor nature (for example replacement of plug-in devices without disturbing existing wiring).

 NOTE 3 The selection of a device should take into account, for example, information derived from the risk assessment, intended use and foreseeable misuse of the device. For example, the use of disconnectors, withdrawable fuse links or withdrawable links located in enclosed electrical operating areas can be inappropriate for use by cleaners (see 17.2 b)12)). 

5.5 Devices for disconnecting electrical equipment

Devices shall be provided for disconnecting (isolating) electrical equipment to enable work to be carried out when it is de-energised and isolated. Such devices shall be:

- appropriate and convenient for the intended use;
- suitably placed;
- readily identifiable as to which part(s) or circuit(s) of the equipment is served (for example by durable marking in accordance with 16.1 where necessary).

Means shall be provided to prevent inadvertent and/or mistaken closure of these devices either at the controller or from other locations (see also 5.6).

The supply disconnecting device (see 5.3) may, in some cases, fulfil that function. However, where it is necessary to work on individual parts of the electrical equipment of a machine, or on one of a number of machines fed by a common conductor bar, conductor wire or inductive power supply system, a disconnecting device shall be provided for each part, or for each machine, requiring separate isolation.

In addition to the supply disconnecting device, the following devices that fulfil the isolation function may be provided for this purpose:

- devices described in 5.3.2;
- disconnectors, withdrawable fuse links and withdrawable links only if located in an electrical operating area (see 3.15) and relevant information is provided with the electrical equipment (see 17.2 b)9) and b)12)).

NOTE Where protection against electric shock is provided in accordance with 6.2.2 c), withdrawable fuse links or withdrawable links for this purpose are intended for use by skilled or instructed persons.

5.6 Protection against unauthorized, inadvertent and/or mistaken connection

The devices described in 5.4 and 5.5 that are located outside an enclosed electrical operating area shall be equipped with means to secure them in the OFF position (disconnected state), (for example by provisions for padlocking, trapped key interlocking). When so secured, remote as well as local reconnection shall be prevented.

Where a non-lockable disconnecting device (for example withdrawable fuse-links, withdrawable links) other means of protection against reconnection (for example warning labels in accordance with 16.1) may be provided.

However, when a plug/socket combination according to 5.3.2 e) is so positioned that it can be kept under the immediate supervision of the person carrying out the work, means for securing in the disconnected state need not be provided.

6 Protection against electric shock

6.1 General

The electrical equipment shall provide protection of persons against electric shock from:

- direct contact (see 6.2 and 6.4);
- indirect contact (see 6.3 and 6.4).

The measures for this protection given in 6.2, 6.3, and, for PELV, in 6.4, are a recommended selection from IEC 60364-4-41. Where those recommended measures are not practicable, for example due to the physical or operational conditions, other measures from IEC 60364-4-41 may be used.

6.2 Protection against direct contact

6.2.1 General

For each circuit or part of the electrical equipment, the measures of either 6.2.2 or 6.2.3 and, where applicable, 6.2.4 shall be applied.

Exception: where those measures are not appropriate, other measures for protection against direct contact (for example by using barriers, by placing out of reach, using obstacles, using construction or installation techniques that prevent access) as defined in IEC 60364-4-41 may be applied (see 6.2.5 and 6.2.6).

When the equipment is located in places open to all persons, which can include children, measures of either 6.2.2 with a minimum degree of protection against direct contact corresponding to IP4X or IPXXD (see IEC 60529), or 6.2.3 shall be applied.

6.2.2 Protection by enclosures

Live parts shall be located inside enclosures that conform to the relevant requirements of Clauses 4, 11, and 14 and that provide protection against direct contact of at least IP2X or IPXXB (see IEC 60529).

Where the top surfaces of the enclosure are readily accessible, the minimum degree of protection against direct contact provided by the top surfaces shall be IP4X or IPXXD.

Opening an enclosure (i.e. opening doors, lids, covers, and the like) shall be possible only under one of the following conditions:

- a) The use of a key or tool is necessary for access. For enclosed electrical operating areas, see IEC 60364-4-41, or IEC 60439-1 as appropriate.

NOTE 1 The use of a key or tool is intended to restrict access to skilled or instructed persons (see 17.2 b)12)).

All live parts, that are likely to be touched when resetting or adjusting devices intended for such operations while the equipment is still connected, shall be protected against direct contact to at least IP2X or IPXXB. Other live parts on the inside of doors shall be protected against direct contact to at least IP1X or IPXXA.

- b) The disconnection of live parts inside the enclosure before the enclosure can be opened.

This may be accomplished by interlocking the door with a disconnecting device (for example, the supply disconnecting device) so that the door can only be opened when the disconnecting device is open and so that the disconnecting device can only be closed when the door is closed.

Exception: a special device or tool as prescribed by the supplier can be used to defeat the interlock provided that:

- it is possible at all times while the interlock is defeated to open the disconnecting device and lock the disconnecting device in the OFF (isolated) position or otherwise prevent unauthorised closure of the disconnecting device;
- upon closing the door, the interlock is automatically restored;
- all live parts, that are likely to be touched when resetting or adjusting devices intended for such operations while the equipment is still connected, are protected against direct contact to at least IP2X or IPXXB and other live parts on the inside of doors are protected against direct contact to at least IP1X or IPXXA;
- relevant information is provided with the electrical equipment (see 17.2 b)9) and b)12)).

NOTE 2 The special device or tool is intended for use only by skilled or instructed persons (see 17.2 b)12)).

Means shall be provided to restrict access to live parts behind doors not directly interlocked with the disconnecting means to skilled or instructed persons. (See 17.2 b)12)).

All parts that are still live after switching off the disconnecting device(s) (see 5.3.5) shall be protected against direct contact to at least IP2X or IPXXB (see IEC 60529). Such parts shall be marked with a warning sign in accordance with 16.2.1 (see also 13.2.4 for identification of conductors by colour).

Excepted from this requirement for marking are:

- parts that can be live only because of connection to interlocking circuits and that are distinguished by colour as potentially live in accordance with 13.2.4;
 - the supply terminals of the supply disconnecting device when the latter is mounted alone in a separate enclosure.
- c) Opening without the use of a key or a tool and without disconnection of live parts shall be possible only when all live parts are protected against direct contact to at least IP2X or IPXXB (see IEC 60529). Where barriers provide this protection, either they shall require a tool for their removal or all live parts protected by them shall be automatically disconnected when the barrier is removed.

NOTE 3 Where protection against direct contact is achieved in accordance with 6.2.2 c), and a hazard can be caused by manual actuation of devices (for example manual closing of contactors or relays), such actuation should be prevented by barriers or obstacles that require a tool for their removal.

6.2.3 Protection by insulation of live parts

Live parts protected by insulation shall be completely covered with insulation that can only be removed by destruction. Such insulation shall be capable of withstanding the mechanical, chemical, electrical, and thermal stresses to which it can be subjected under normal operating conditions.

NOTE Paints, varnishes, lacquers, and similar products alone are generally considered to be inadequate for protection against electric shock under normal operating conditions.

6.2.4 Protection against residual voltages

Live parts having a residual voltage greater than 60 V after the supply has been disconnected shall be discharged to 60 V or less within a time period of 5 s after disconnection of the supply voltage provided that this rate of discharge does not interfere with the proper functioning of the equipment. Exempted from this requirement are components having a stored charge of 60 μC or less. Where this specified rate of discharge would interfere with the proper functioning of the equipment, a durable warning notice drawing attention to the hazard and stating the delay required before the enclosure may be opened shall be displayed at an easily visible location on or immediately adjacent to the enclosure containing the capacitances.

In the case of plugs or similar devices, the withdrawal of which results in the exposure of conductors (for example pins), the discharge time shall not exceed 1 s, otherwise such conductors shall be protected against direct contact to at least IP2X or IPXXB. If neither a discharge time of 1 s nor a protection of at least IP2X or IPXXB can be achieved (for example in the case of removable collectors on conductor wires, conductor bars, or slip-ring assemblies, see 12.7.4), additional switching devices or an appropriate warning device (for example a warning notice in accordance with 16.1) shall be applied.

6.2.5 Protection by barriers

For protection by barriers, 412.2 of IEC 60364-4-41 shall apply.

6.2.6 Protection by placing out of reach or protection by obstacles

For protection by placing out of reach, 412.4 of IEC 60364-4-41 shall apply. For protection by obstacles, 412.3 of IEC 60364-4-41 shall apply.

For conductor wire systems or conductor bar systems with a degree of protection less than IP2X, see 12.7.1.

6.3 Protection against indirect contact

6.3.1 General

Protection against indirect contact (3.29) is intended to prevent hazardous situations due to an insulation fault between live parts and exposed conductive parts.

For each circuit or part of the electrical equipment, at least one of the measures in accordance with 6.3.2 to 6.3.3 shall be applied:

- measures to prevent the occurrence of a touch voltage (6.3.2); or
- automatic disconnection of the supply before the time of contact with a touch voltage can become hazardous (6.3.3).

NOTE 1 The risk of harmful physiological effects from a touch voltage depends on the value of the touch voltage and the duration of possible exposure.

NOTE 2 For classes of equipment and protective provisions, see IEC 61140.

6.3.2 Prevention of the occurrence of a touch voltage

6.3.2.1 General

Measures to prevent the occurrence of a touch voltage include the following:

- provision of class II equipment or by equivalent insulation;
- electrical separation.

6.3.2.2 Protection by provision of class II equipment or by equivalent insulation

This measure is intended to prevent the occurrence of touch voltages on the accessible parts through a fault in the basic insulation.

This protection is provided by one or more of the following:

- class II electrical devices or apparatus (double insulation, reinforced insulation or by equivalent insulation in accordance with IEC 61140);
- switchgear and controlgear assemblies having total insulation in accordance with IEC 60439-1;
- supplementary or reinforced insulation in accordance with 413.2 of IEC 60364-4-41.

6.3.2.3 Protection by electrical separation

Electrical separation of an individual circuit is intended to prevent a touch voltage through contact with exposed conductive parts that can be energized by a fault in the basic insulation of the live parts of that circuit.

For this type of protection, the requirements of 413.5 of IEC 60364-4-41 apply.

6.3.3 Protection by automatic disconnection of supply

This measure consists of the interruption of one or more of the line conductors by the automatic operation of a protective device in case of a fault. This interruption shall occur within a sufficiently short time to limit the duration of a touch voltage to a time within which the touch voltage is not hazardous. Interruption times are given in Annex A.

This measure necessitates co-ordination between:

- the type of supply and earthing system;
- the impedance values of the different elements of the protective bonding system;
- the characteristics of the protective devices that detect insulation fault(s).

Automatic disconnection of the supply of any circuit affected by an insulation fault is intended to prevent a hazardous situation resulting from a touch voltage.

This protective measure comprises both:

- protective bonding of exposed conductive parts (see 8.2.3),
- and either:
 - a) overcurrent protective devices for the automatic disconnection of the supply on detection of an insulation fault in TN systems, or
 - b) residual current protective devices to initiate the automatic disconnection of the supply on detection of an insulation fault from a live part to exposed conductive parts or to earth in TT systems, or
 - c) insulation monitoring or residual current protective devices to initiate automatic disconnection of IT systems. Except where a protective device is provided to interrupt the supply in the case of the first earth fault, an insulation monitoring device shall be provided to indicate the occurrence of a first fault from a live part to exposed conductive parts or to earth. This insulation monitoring device shall initiate an audible and/or visual signal which shall continue as long as the fault persists.

NOTE In large machines, the provision of an earth fault location system can facilitate maintenance.

Where automatic disconnection is provided in accordance with a), and disconnection within the time specified in Clause A.1 cannot be assured, supplementary bonding shall be provided as necessary to meet the requirements of Clause A.3.

6.4 Protection by the use of PELV

6.4.1 General requirements

The use of PELV (Protective Extra-Low Voltage) is to protect persons against electric shock from indirect contact and limited area direct contact (see 8.2.5).

PELV circuits shall satisfy all of the following conditions:

- a) the nominal voltage shall not exceed:
 - 25 V a.c. r.m.s. or 60 V ripple-free d.c. when the equipment is normally used in dry locations and when large area contact of live parts with the human body is not expected; or
 - 6 V a.c. r.m.s. or 15 V ripple-free d.c. in all other cases;

NOTE *Ripple-free* is conventionally defined for a sinusoidal ripple voltage as a ripple content of not more than 10 % r.m.s.

- b) one side of the circuit or one point of the source of the supply of that circuit shall be connected to the protective bonding circuit;
- c) live parts of PELV circuits shall be electrically separated from other live circuits. Electrical separation shall be not less than that required between the primary and secondary circuits of a safety isolating transformer (see IEC 61558-1 and IEC 61558-2-6);
- d) conductors of each PELV circuit shall be physically separated from those of any other circuit. When this requirement is impracticable, the insulation provisions of 13.1.3 shall apply;
- e) plugs and socket-outlets for a PELV circuit shall conform to the following:
 - 1) plugs shall not be able to enter socket-outlets of other voltage systems;
 - 2) socket-outlets shall not admit plugs of other voltage systems.

6.4.2 Sources for PELV

The source for PELV shall be one of the following:

- a safety isolating transformer in accordance with IEC 61558-1 and IEC 61558-2-6;
- a source of current providing a degree of safety equivalent to that of the safety isolating transformer (for example a motor generator with winding providing equivalent isolation);
- an electrochemical source (for example a battery) or another source independent of a higher voltage circuit (for example a diesel-driven generator);
- an electronic power supply conforming to appropriate standards specifying measures to be –taken to ensure that, even in the case of an internal fault, the voltage at the outgoing terminals cannot exceed the values specified in 6.4.1.

7 Protection of equipment

7.1 General

This Clause details the measures to be taken to protect equipment against the effects of:

- overcurrent arising from a short circuit;
- overload and/or loss of cooling of motors;
- abnormal temperature;
- loss of or reduction in the supply voltage;
- overspeed of machines/machine elements;
- earth fault/residual current;
- incorrect phase sequence;
- overvoltage due to lightning and switching surges.

7.2 Overcurrent protection

7.2.1 General

Overcurrent protection shall be provided where the current in a machine circuit can exceed either the rating of any component or the current carrying capacity of the conductors, whichever is the lesser value. The ratings or settings to be selected are detailed in 7.2.10.

7.2.2 Supply conductors

Unless otherwise specified by the user, the supplier of the electrical equipment is not responsible for providing the overcurrent protective device for the supply conductors to the electrical equipment (see Annex B).

The supplier of the electrical equipment shall state on the installation diagram the data necessary for selecting the overcurrent protective device (see 7.2.10 and 17.4).

7.2.3 Power circuits

Devices for detection and interruption of overcurrent, selected in accordance with 7.2.10, shall be applied to each live conductor.

The following conductors, as applicable, shall not be disconnected without disconnecting all associated live conductors:

- the neutral conductor of a.c. power circuits;
- the earthed conductor of d.c. power circuits;
- d.c. power conductors bonded to exposed conductive parts of mobile machines.

Where the cross-sectional area of the neutral conductor is at least equal to or equivalent to that of the phase conductors, it is not necessary to provide overcurrent detection for the neutral conductor nor a disconnecting device for that conductor. For a neutral conductor with a cross-sectional area smaller than that of the associated phase conductors, the measures detailed in 524 of IEC 60364-5-52 shall apply.

In IT systems, it is recommended that the neutral conductor is not used. However, where a neutral conductor is used, the measures detailed in 431.2.2 of IEC 60364-4-43 shall apply.

7.2.4 Control circuits

Conductors of control circuits directly connected to the supply voltage and of circuits supplying control circuit transformers shall be protected against overcurrent in accordance with 7.2.3.

Conductors of control circuits supplied by a control circuit transformer or d.c. supply shall be protected against overcurrent (see also 9.4.3.1):

- in control circuits connected to the protective bonding circuit, by inserting an overcurrent protective device into the switched conductor;
- in control circuits not connected to the protective bonding circuit;
 - where the same cross sectional area conductors are used in all control circuits, by inserting an overcurrent protective device into the switched conductor, and;
 - where different cross sectional areas conductors are used in different sub-circuits, by inserting an overcurrent protective device into both switched and common conductors of each sub-circuit.

7.2.5 Socket outlets and their associated conductors

Overcurrent protection shall be provided for the circuits feeding the general purpose socket outlets intended primarily for supplying power to maintenance equipment. Overcurrent protective devices shall be provided in the unearthed live conductors of each circuit feeding such socket outlets.

7.2.6 Lighting circuits

All unearthed conductors of circuits supplying lighting shall be protected against the effects of short circuits by the provision of overcurrent devices separate from those protecting other circuits.

7.2.7 Transformers

Transformers shall be protected against overcurrent in accordance with the manufacturer's instructions. Such protection shall (see also 7.2.10):

- avoid nuisance tripping due to transformer magnetizing inrush currents;
- avoid a winding temperature rise in excess of the permitted value for the insulation class of transformer when it is subjected to the effects of a short circuit at its secondary terminals.

The type and setting of the overcurrent protective device should be in accordance with the recommendations of the transformer supplier.

7.2.8 Location of overcurrent protective devices

An overcurrent protective device shall be located at the point where a reduction in the cross-sectional area of the conductors or another change reduces the current-carrying capacity of the conductors, except where all the following conditions are satisfied:

- the current carrying capacity of the conductors is at least equal to that of the load;
- the part of the conductor between the point of reduction of current-carrying capacity and the position of the overcurrent protective device is no longer than 3 m;
- the conductor is installed in such a manner as to reduce the possibility of a short-circuit, for example, protected by an enclosure or duct.

7.2.9 Overcurrent protective devices

The rated short-circuit breaking capacity shall be at least equal to the prospective fault current at the point of installation. Where the short-circuit current to an overcurrent protective device can include additional currents other than from the supply (for example from motors, from power factor correction capacitors), those currents shall be taken into consideration.

A lower breaking capacity is permitted where another protective device (for example the overcurrent protective device for the supply conductors (see 7.2.2) having the necessary breaking capacity is installed on the supply side. In that case, the characteristics of the two devices shall be co-ordinated so that the let-through energy (I^2t) of the two devices in series does not exceed that which can be withstood without damage to the overcurrent protective device on the load side and to the conductors protected by that device (see Annex A of IEC 60947-2).

NOTE The use of such a co-ordinated arrangement of overcurrent protective devices can result in the operation of both overcurrent protective devices.

Where fuses are provided as overcurrent protective devices, a type readily available in the country of use shall be selected, or arrangements shall be made for the supply of spare parts.