

Ballasts for tubular fluorescent lamps — Performance requirements

The European Standard EN 60921:2004, with the incorporation of amendment A1:2006, has the status of a British Standard

ICS 29.140.30

National foreword

This British Standard is the official English language version of EN 60921:2004, including amendment A1:2006. It is identical with IEC 60921:2004, including amendment 1:2006. It supersedes BS EN 60921:1991 which will be withdrawn on 1 October 2011.

The start and finish of text introduced or altered by IEC amendment is indicated in the text by tags **A1** **A1**. Tags indicating changes to IEC text carry the number of the IEC amendment. For example, text altered by IEC amendment 1 is indicated by **A1** **A1**.

The UK participation in its preparation was entrusted by Technical Committee CPL/34, Lamps and related equipment, to Subcommittee CPL/34/3, Auxiliaries for lamps, which has the responsibility to:

- aid enquirers to understand the text;
- present to the responsible international/European committee any enquiries on the interpretation, or proposals for change, and keep UK interests informed;
- monitor related international and European developments and promulgate them in the UK.

A list of organizations represented on this subcommittee can be obtained on request to its secretary.

Cross-references

The British Standards which implement international or European publications referred to in this document may be found in the *BSI Catalogue* under the section entitled “International Standards Correspondence Index”, or by using the “Search” facility of the *BSI Electronic Catalogue* or of British Standards Online.

This publication does not purport to include all the necessary provisions of a contract. Users are responsible for its correct application.

Compliance with a British Standard does not of itself confer immunity from legal obligations.

Summary of pages

This document comprises a front cover, an inside front cover, the EN title page, pages 2 to 32, an inside back cover and a back cover.

The BSI copyright notice displayed in this document indicates when the document was last issued.

Amendments issued since publication

Amd. No.	Date	Comments
16527	29 September 2006	See national foreword

This British Standard was published under the authority of the Standards Policy and Strategy Committee on 31 January 2005

© BSI 2006

ISBN 0 580 45346 4

English version

**Ballasts for tubular fluorescent lamps -
Performance requirements
(IEC 60921:2004)**

Ballasts pour lampes tubulaires
à fluorescence -
Exigences de performances
(CEI 60921:2004)

Vorschaltgeräte für röhrenförmige
Leuchtstofflampen -
Anforderungen an die Arbeitsweise
(IEC 60921:2004)

This European Standard was approved by CENELEC on 2004-10-01. CENELEC members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for giving this European Standard the status of a national standard without any alteration.

Up-to-date lists and bibliographical references concerning such national standards may be obtained on application to the Central Secretariat or to any CENELEC member.

This European Standard exists in three official versions (English, French, German). A version in any other language made by translation under the responsibility of a CENELEC member into its own language and notified to the Central Secretariat has the same status as the official versions.

CENELEC members are the national electrotechnical committees of Austria, Belgium, Cyprus, Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, Netherlands, Norway, Poland, Portugal, Slovakia, Slovenia, Spain, Sweden, Switzerland and United Kingdom.

CENELEC

European Committee for Electrotechnical Standardization
Comité Européen de Normalisation Electrotechnique
Europäisches Komitee für Elektrotechnische Normung

Central Secretariat: rue de Stassart 35, B - 1050 Brussels

Foreword

The text of document 34C/642/FDIS, future edition 2 of IEC 60921, prepared by SC 34C, Auxiliaries for lamps, of IEC TC 34, Lamps and related equipment, was submitted to the IEC-CENELEC parallel vote and was approved by CENELEC as EN 60921 on 2004-10-01.

This European Standard supersedes EN 60921:1991 + A1:1992 + A2:1995.

The changes compared to EN 60921:1991 are:

- EMC related requirements have been deleted (marking of 'H' and demands for supply current waveform);
- US requirements have been added;
- references were updated;
- the outlook was modernized.

This standard is to be read in conjunction with EN 61347-2-8.

The following dates were fixed:

- | | | |
|--|-------|------------|
| – latest date by which the EN has to be implemented at national level by publication of an identical national standard or by endorsement | (dop) | 2005-07-01 |
| – latest date by which the national standards conflicting with the EN have to be withdrawn | (dow) | 2011-10-01 |

Annex ZA has been added by CENELEC.

Endorsement notice

The text of the International Standard IEC 60921:2004 was approved by CENELEC as a European Standard without any modification.

Foreword to amendment A1

The text of document 34C/728/FDIS, future amendment 1 to IEC 60921:2004, prepared by SC 34C, Auxiliaries for lamps, of IEC TC 34, Lamps and related equipment, was submitted to the IEC-CENELEC parallel vote and was approved by CENELEC as amendment A1 to EN 60921:2004 on 2006-06-01.

The following dates were fixed:

- | | | |
|---|-------|------------|
| – latest date by which the amendment has to be implemented at national level by publication of an identical national standard or by endorsement | (dop) | 2007-03-01 |
| – latest date by which the national standards conflicting with the amendment have to be withdrawn | (dow) | 2013-06-01 |

Endorsement notice

The text of amendment 1:2006 to the International Standard IEC 60921:2004 was approved by CENELEC as an amendment to the European Standard without any modification.

CONTENTS

INTRODUCTION.....	5
1 Scope.....	6
2 Normative References	6
3 Terms and definitions	6
4 General notes on tests	7
5 Marking	7
6 Voltage at terminations of lamp or starter (if any)	7
6.1 For lamps operated with a starter	7
6.2 For lamps operated without a starter	8
6.3 For lamps operated without a starter (North American practice).....	8
6.4 Maximum (r.m.s.) voltage across starter terminals with lamp operating	9
6.5 For lamps with integral means of starting	9
7 Pre-heating conditions.....	9
7.1 For lamps operated with (integral) starter	9
7.2 For lamps operated without starter	10
7.3 For lamps operated without starter (North American practice)	10
8 Lamp power and current.....	10
8.1 For lamps operated with (integral) starter	10
8.2 For lamps operated without starter	11
9 Circuit power-factor	11
10 Supply current	11
11 Maximum current in any lead to a cathode.....	11
12 Current waveform	12
13 Magnetic screening	12
14 Impedance at audio-frequencies.....	12
 Annex A (normative) Tests.....	13
A.1 General conditions for tests.....	13
A.2 Additional requirements for testing reference ballasts	14
A.3 Selection of reference lamps	15
A.4 Measurement of open-circuit voltage.....	19
A.5 Measurements of pre-heating conditions	19
A.6 Measurement of lamp power and current.....	19
A.7 Measurement of maximum current in any lead to a cathode	22
A.8 Measurement of current waveform (Figure A.9).....	23
A.9 Measurement of impedance at audio-frequencies.....	24
 Annex B (informative) Series operation of two fluorescent lamps	27

Annex C (normative) Reference ballasts	28
C.1 Marking.....	28
C.2 Design characteristics	28
C.3 Operating characteristics	28
 Annex D (normative) Reference lamps.....	30
 Annex ZA (normative) Normative references to international publications with their corresponding European publications	31
 Bibliography.....	32
 Figure A.1 – Circuit for measurement of voltage/current ratio.....	14
Figure A.2 – Circuit for measurement of power factor	14
Figure A.3 – Circuit for selection of reference lamps (without separate cathode heating)	16
Figure A.4 – Circuit for selection of reference lamps (with separate cathode heating)	17
Figure A.5 – Circuit for calibration of cathode transformers.....	18
Figure A.6 – Measurement of power and current output (lamps with starter)	20
Figure A.7 – Measurement of power and current output (lamps without starter)	22
Figure A.8 – Measurement of maximum current in any lead to a cathode	23
Figure A.9 – Measurement of current waveform	24
Figure A.10 – Measurement of impedance at audio-frequencies – Method A.....	25
Figure A.11 – Measurement of impedance at audio frequencies – Method B	26

INTRODUCTION

This standard covers performance requirements for ballasts for tubular fluorescent lamps. It should be read in conjunction with IEC 61347-2-8, with which all ballasts covered by the present standard should comply.

Unless otherwise stated on the lamp data sheet mentioned in IEC 60081 and IEC 60901, it may be expected that ballasts which comply with this standard, when associated with lamps complying with IEC 60081 or IEC 60901, and, where appropriate, operated with a starter complying with IEC 60155 or starting devices complying with IEC 60927, will ensure satisfactory starting of the lamps at an air temperature immediately around the lamps between 10 °C and 35 °C and for voltages between 92 % and 106 % of rated supply voltage, and also proper operation between 10 °C and 50 °C at rated supply voltage.

The compatibility of lamps and ballasts is evaluated with the use of special inductive ballasts called "reference ballasts" having particular characteristics which are stable and reproducible. These ballasts are used when testing commercial ballasts and when selecting reference lamps. Moreover, the testing of ballasts presents particular difficulties, which require a proper definition of testing methods. Such tests will generally be made with reference lamps and, in particular, by comparing the results obtained when such lamps are operated on a reference ballast with the results obtained when the same lamps are operated on the ballast being tested.

NOTE Requirements are also included for all those features of reference ballast construction and performance which are considered necessary to ensure accurate and reproducible results when testing ballasts, particularly with regard to the selection of reference lamps.

For checking the lamp power and current of lamps operated without a starter, this standard specifies a measurement in a reference ballast circuit that makes no provision for separate power sources to heat the cathodes during lamp operation. Although the influence on the ballast specification is small, it has nevertheless been deemed useful for some pre-heated low-voltage cathode lamps, operated without a starter, to include provision for two alternative methods of measurement of lamp power and current:

- a) measurement of lamp power and current without additional cathode heating;
- b) measurement of lamp power and current with additional cathode heating.

The test method to be adopted for appraisal should be stated by the manufacturer.

Two alternative circuits are specified for the measurement of impedance at audio frequencies. The less complex circuit could be used when there is no doubt about the inductive character of the impedance. If there is any doubt, the other circuit should be used.

BALLASTS FOR TUBULAR FLUORESCENT LAMPS – PERFORMANCE REQUIREMENTS

1 Scope

This standard specifies performance requirements for ballasts, excluding resistance types, for use on a.c. supplies up to 1 000 V at 50 Hz or 60 Hz, associated with tubular fluorescent lamps with pre-heated cathodes operated with or without a starter or starting device and having rated wattages, dimensions and characteristics as specified in IEC 60081 and 60901. It applies to complete ballasts and their component parts such as resistors, transformers and capacitors.

A.C. supplied electronic ballasts for tubular fluorescent lamps for high frequency operation specified in IEC 61347-2-3 are excluded from the scope of this standard.

NOTE In some regions there are laws on EMC for luminaires. The controlgear also contributes to this EMC behaviour. See Bibliography for further references.

2 Normative References

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60081, *Double-capped fluorescent lamps – Performance specifications*

IEC 60901, *Single-capped fluorescent lamps – Performance specifications*

IEC 61347-1, *Lamp controlgear – General and safety requirements*

IEC 61347-2-8, *Lamp controlgear – Particular requirements for ballasts for fluorescent lamps*

3 Terms and definitions

For the purposes of the present document, the definitions of IEC 61347-2-8 together with the following apply.

3.1

(peak) lead circuit ballast

ballast having a leading lamp current with respect to the line voltage as a result of a capacitor which is connected in series with the lamp

4 General notes on tests

4.1 Tests according to this specification are type tests.

NOTE The requirements and tolerances permitted by this standard are based on testing of a type test sample submitted by the manufacturer for that purpose. In principle this type test sample should consist of units having characteristics typical of the manufacturer's production and be as close to the production centre point values as possible.

It may be expected with the tolerances given in the standard that products manufactured in accordance with the type test sample will comply with the standard for the majority of the production.

Due to the production spread, it is inevitable, however, that there may sometimes be ballasts outside the specified tolerances.

For guidance of sampling plans and procedures for inspection by attributes, see IEC 60410.

4.2 The tests shall be carried out in the order of the clauses, unless otherwise specified.

4.3 One specimen shall be submitted to all tests.

4.4 In general all tests are made on each type of ballast or, where a range of similar ballasts is involved, for each rated wattage in the range or on a representative selection from the range as agreed with the manufacturer.

4.5 The tests shall be made under the conditions specified in Annex A.

4.6 All ballasts specified in this standard shall comply with the requirements of IEC 61347-2-8.

A1 4.7 Attention is drawn to lamp performance standards which contain "information for ballast design"; this should be followed for proper lamp operation; however, this standard does not require the testing of lamp performance as part of the type test approval for ballasts. **A1**

5 Marking

The following information shall be included either on the ballast or be made available in the manufacturer's catalogue or the like:

5.1 Circuit power-factor, for example λ 0,85.

If the power-factor is less than 0,85 leading, it shall be followed by the letter C, for example λ 0,80 C.

For ballasts intended for the additional application of operated lamps in series, the appropriate power-factors shall be included.

The following additional marking shall be included, if appropriate:

5.2 The symbol $\mathbb{Z}$ which indicates that the ballast is designed to comply with the conditions for audio-frequency impedance (see Clause 14).

6 Voltage at terminations of lamp or starter (if any)

The test shall be carried out in accordance with the measuring conditions of A.4.

6.1 For lamps operated with a starter

A ballast, when operated at any voltage between 92 % and 106 % of its rated voltage, shall provide the following open-circuit voltages:

- a) at terminations of the starter, an r.m.s voltage of at least the value given in IEC 60081 or IEC 60901 on the relevant lamp data sheet;
- b) at lamp terminations, a peak voltage (excluding the surge of the starter) not exceeding the value given in IEC 60081 or IEC 60901 on the relevant lamp data sheet.

When ballasts are designed to operate lamps in parallel circuits, the relevant requirements shall be met for each separate lamp, even in the most adverse load conditions.

6.2 For lamps operated without a starter

A ballast, when operated at any voltage between 92 % and 106 % of its rated voltage, shall provide an open-circuit voltage at lamp terminations such that:

- a) its r.m.s. value is at least the value given in IEC 60081 or IEC 60901 on the relevant lamp data sheet;
- b) its peak value does not exceed the value given in IEC 60081 or IEC 60901 on the relevant lamp data sheet;
- c) its crest factor (ratio of peak value to r.m.s. value) of open circuit voltage does not exceed the value given in IEC 60081 or IEC 60901 on the relevant lamp data sheet.

When ballasts are designed to operate lamps in parallel circuits, the relevant requirements shall be met for each separate lamp, even in the most adverse load conditions.

NOTE 1 For the checking of open-circuit voltage at lamp terminations, the maximum value of the four possible measurements between lamp terminals is taken

NOTE 2 For ballasts with a step-up transformer it is likely that a capacitor is used in series to form lead circuit or peak lead circuit ballasts. A lead circuit ballast typically has an open circuit voltage crest factor of 1,55 to 2,0 and in a peak lead ballast it is 2,0 to 2,3.

6.3 For lamps operated without a starter (North American practice)

A ballast, when operated at any voltage between 90 % and 110 % of its rated voltage, shall provide an open-circuit voltage at lamp terminations such that:

- a) its r.m.s. value is not less than the minimum and not greater than the maximum values given in IEC 60081 or IEC 60901 on the relevant lamp data sheet;
- b) its peak value to starting aid is at least the value given in IEC 60081 or IEC 60901 on the relevant lamp data sheet;
- c) its crest factor (ratio of peak value to r.m.s. value) of open circuit voltage across lamp and to starting aid does not exceed the value given in IEC 60081 or IEC 60901 on the relevant lamp data sheet.

When ballasts are designed to operate lamps in parallel circuits, the relevant requirements shall be met for each separate lamp, even in the most adverse load conditions.

NOTE 1 For the checking of open-circuit voltage at lamp terminations, the maximum value of the four possible measurements between lamp terminals is taken.

NOTE 2 For ballasts with a step-up transformer it is likely that a capacitor is used in series to form lead circuit or peak lead circuit ballasts. A lead circuit ballast typically has an open circuit voltage crest factor of 1,55 to 2,0 and in a peak lead circuit ballast it is 2,0 to 2,3.

Starting aid capacitor sizes are specified not less than the minimum and not greater than the maximum on the relevant lamp data sheet. In two-lamp series ballasts, the capacitor shall shunt the lamp furthest from ground potential. For three-lamp series ballasts, a capacitor shall shunt the two lamps furthest from ground potential. A second capacitor of the same size shall shunt the lamp furthest from ground. If the peak voltage to ground exceeds the minimum by 30 % the second capacitor may shunt either of the two shunted lamps.

6.4 Maximum (r.m.s.) voltage across starter terminals with lamp operating

When a ballast is operating with a reference lamp and is connected to any voltage between 92 % and 106 % of the rated supply voltage at rated frequency, the voltage across the starter terminations shall not exceed the maximum value given in IEC 60081 on the relevant lamp data sheet.

These limits apply both when the lamp is first ignited and after it has warmed up.

When the ballasts are designed to operate lamps in parallel circuits, the relevant requirements shall be met for each separate lamp, under the most adverse load conditions.

6.5 For lamps with integral means of starting

A ballast, when operated at any voltage between 92 % and 106 % of its rated voltage, shall provide an open-circuit voltage at lamp terminations such that:

- a) its r.m.s value is at least the value given in IEC 60901 on the relevant lamp data sheet.
- b) its peak value does not exceed that value given in IEC 60901 on the relevant lamp data sheet.

7 Pre-heating conditions

The test shall be carried out in accordance with the measuring conditions of A.5.

NOTE A marked capacitor tolerance of 10 %, which is typical for shunt connected capacitors, is unsuitable for series capacitors due to the summation of capacitor and ballast tolerances which, when unfavourable tolerances coincide, may lead to poor lamp performance.

Consequently, and in order to satisfy the requirements specified on the relevant lamp data sheets in IEC 60081 or IEC 60901, depending on the tolerances of the series choke component of the ballast either the capacitor tolerances should be narrow or the series connected inductive reactance and capacitor should be selected so that unfavourable tolerances do not coincide.

7.1 For lamps operated with (integral) starter

A ballast, when operated at any voltage between 92 % and 106 % of its rated supply voltage and at rated frequency, shall provide a pre-heating current as specified on the relevant lamp data sheet in IEC 60081 or IEC 60901.

For lamps where such data are not given in IEC 60081 or IEC 60901, the pre-heating current shall be as specified by the lamp manufacturer.