

BS EN 61009-1:2012+A12:2016

Incorporating corrigendum January 2014



BSI Standards Publication

Residual current operated circuit-breakers with integral overcurrent protection for household and similar uses (RCBOs)

Part 1: General rules

bsi.

AVA Documents
Document Sharing Hub

National foreword

This British Standard is the UK implementation of EN 61009-1:2012+A12:2016. It is derived from IEC 61009-1:2010 incorporating amendments 1:2012 and 2:2013 and corrigendum January 2014. It supersedes BS EN 61009-1:2012+A11:2015, which will be withdrawn on 11 February 2019.

The CENELEC common modifications have been implemented at the appropriate places in the text. The start and finish of each common modification is indicated in the text by tags **Ⓒ** **Ⓒ**.

The start and finish of text introduced or altered by amendment is indicated in the text by tags. Tags indicating changes to IEC text carry the number of the IEC amendment. For example, text altered by IEC amendment 1 is indicated by **Ⓐ** **Ⓐ**.

Where a common modification to an IEC amendment has been introduced, the tags carry the number of the amendment. For example, the common modifications introduced by CENELEC to IEC amendment 1 are indicated by **Ⓒ** **Ⓒ**.

The UK participation in its preparation was entrusted by Technical Committee PEL/23, Electrical accessories, to Subcommittee PEL/23/1, Circuit breakers and similar equipment for household use.

A list of organizations represented on this subcommittee can be obtained on request to its secretary.

This publication does not purport to include all the necessary provisions of a contract. Users are responsible for its correct application.

© The British Standards Institution 2016.
Published by BSI Standards Limited 2016

ISBN 978 0 580 94131 3

ICS 29.120.50

Compliance with a British Standard cannot confer immunity from legal obligations.

This British Standard was published under the authority of the Standards Policy and Strategy Committee on 31 August 2013.

Amendments/corrigenda issued since publication

Date	Text affected
31 January 2015	Implementation of IEC amendment 1:2012 with CENELEC modifications
31 January 2015	Implementation of IEC amendment 2:2013 with CENELEC modifications
31 January 2015	Implementation of IEC corrigendum January 2014: Table 26 inserted into subclause 9.9.1.3
30 September 2015	Implementation of CENELEC amendment A11:2015: Annex ZB updated
30 April 2016	Implementation of CENELEC amendment A12:2016: Annex ZB updated

Residual current operated circuit-breakers with integral overcurrent protection for household and similar uses (RCBOs) -

Part 1: General rules
(IEC 61009-1:2010, modified)

Interrupteurs automatiques à courant différentiel résiduel avec dispositif de protection contre les surintensités incorporé pour usages domestiques et analogues (DD) -
Partie 1: Règles générales
(CEI 61009-1:2010, modifiée)

Fehlerstrom-/Differenzstrom-Schutzschalter mit eingebautem Überstromschutz (RCBOs) für Hausinstallationen und für ähnliche Anwendungen -
Teil 1: Allgemeine Anforderungen
(IEC 61009-1:2010, modifiziert)

This European Standard was approved by CENELEC on 2012-06-18. CENELEC members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for giving this European Standard the status of a national standard without any alteration.

Up-to-date lists and bibliographical references concerning such national standards may be obtained on application to the CEN-CENELEC Management Centre or to any CENELEC member.

This European Standard exists in three official versions (English, French, German). A version in any other language made by translation under the responsibility of a CENELEC member into its own language and notified to the CEN-CENELEC Management Centre has the same status as the official versions.

CENELEC members are the national electrotechnical committees of Austria, Belgium, Bulgaria, Croatia, Cyprus, the Czech Republic, Denmark, Estonia, Finland, Former Yugoslav Republic of Macedonia, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, the Netherlands, Norway, Poland, Portugal, Romania, Slovakia, Slovenia, Spain, Sweden, Switzerland, Turkey and the United Kingdom.

CENELEC

European Committee for Electrotechnical Standardization
Comité Européen de Normalisation Electrotechnique
Europäisches Komitee für Elektrotechnische Normung

Management Centre: Avenue Marnix 17, B - 1000 Brussels

Foreword

This document (EN 61009-1:2012) consists of the text of IEC 61009-1:2010 prepared by IEC/TC 23E "Circuit-breakers and similar equipment for household use", together with the common modifications prepared by CLC/TC 23E "Circuit breakers and similar devices for household and similar applications".

The following dates are fixed:

- latest date by which this document has to be implemented (dop) 2013-06-18
at national level by publication of an identical national standard or by endorsement
- latest date by which the national standards conflicting with this document have to be withdrawn (dow) 2017-06-18

This document supersedes EN 61009-1:2004 + corr.Jul.2006 + A11:2008 + A12:2009 + A13:2009 + A14:2012 + AC:2012.

- complete revision of EMC sequences, including the new test T.2.6, already approved in EN 61543;
- clarification of RCDs current/time characteristics reported in Tables 2 and 3;
- revision of test procedure for $I_{\Delta n}$ between 5 A and 200 A;
- tests for the use of RCBOs in IT systems;
- testing procedure regarding the 6mA d.c. current superimposed to the fault current;
- improvement highlighting RCDs with multiple sensitivity;
- some alignments with EN 60898-1.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. CENELEC [and/or CEN] shall not be held responsible for identifying any or all such patent rights.

This document has been prepared under a mandate given to CENELEC by the European Commission and the European Free Trade Association, and supports essential requirements of EU Directive(s).

For the relationship with EU Directive(s) see informative Annex ZZ, which is an integral part of this document.

Clauses, subclauses, notes, tables, figures and annexes which are additional to those in IEC 61009-1:2010 are prefixed "Z".

Endorsement notice

The text of the International Standard IEC 61009-1:2010 was approved by CENELEC as a European Standard with agreed common modifications.

Foreword to amendment A1

This document (EN 61009-1:2012/A1:2014) consists of the text of IEC 61009-1:2010/A1:2012 prepared by SC 23E "Circuit-breakers and similar equipment for household use" of IEC/TC 23 "Electrical accessories", together with the common modifications prepared by CLC/TC 23E "Circuit breakers and similar devices for household and similar applications".

The following dates are fixed:

- latest date by which this document has to be implemented at (dop) 2015-08-04
national level by publication of an identical national standard or
by endorsement
- latest date by which the national standards conflicting with this (dow) 2017-08-04
document have to be withdrawn

Clauses, subclauses, notes, tables, figures and annexes which are additional to those in IEC 61009-1:2010/A1:2012 are prefixed "Z".

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. CENELEC [and/or CEN] shall not be held responsible for identifying any or all such patent rights.

This standard covers the Principle Elements of the Safety Objectives for Electrical Equipment Designed for Use within Certain Voltage Limits (LVD - 2006/95/EC).

This document has been prepared under a mandate given to CENELEC by the European Commission and the European Free Trade Association, and supports essential requirements of EU Directive(s).

Endorsement notice

The text of the International Standard IEC 61009-1:2010/A1:2012 was approved by CENELEC as a European Standard with agreed common modifications.

Foreword to amendment A2

This document (EN 61009-1:2012/A2:2014) consists of the text of IEC 61009-1:2010/A2:2013 prepared by SC 23E "Circuit-breakers and similar equipment for household use" of IEC/TC 23 "Electrical accessories", together with the common modifications prepared by CLC/TC 23E "Circuit breakers and similar devices for household and similar applications".

The following dates are fixed:

- latest date by which this document has to be implemented at (dop) 2015-08-04
national level by publication of an identical national standard or
by endorsement
- latest date by which the national standards conflicting with this (dow) 2017-08-04
document have to be withdrawn

Clauses, subclauses, notes, tables, figures and annexes which are additional to those in IEC 61009-1:2010/A2:2013 are prefixed "Z".

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. CENELEC [and/or CEN] shall not be held responsible for identifying any or all such patent rights.

This standard covers the Principle Elements of the Safety Objectives for Electrical Equipment Designed for Use within Certain Voltage Limits (LVD - 2006/95/EC).

This document has been prepared under a mandate given to CENELEC by the European Commission and the European Free Trade Association, and supports essential requirements of EU Directive(s).

Endorsement notice

The text of the International Standard IEC 61009-1:2010/A2:2013 was approved by CENELEC as a European Standard with agreed common modifications.

Foreword to amendment A11

This document (EN 61009-1:2012/A11:2015) has been prepared by CLC/TC 23E "Circuit breakers and similar devices for household and similar applications".

The following dates are fixed:

- latest date by which the document has to be implemented at (dop) 2016-07-06
national level by publication of an identical national
standard or by endorsement
- latest date by which the national standards conflicting with (dow) 2018-07-06
the document have to be withdrawn

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. CENELEC [and/or CEN] shall not be held responsible for identifying any or all such patent rights.

This document has been prepared under a mandate given to CENELEC by the European Commission and the European Free Trade Association, and supports essential requirements of EU Directive(s).

For the relationship with EU Directive 2004/108/EC, see informative Annex ZZ, mentioned in EN 61009-1:2012.

This standard covers the Principle Elements of the Safety Objectives for Electrical Equipment Designed for Use within Certain Voltage Limits (LVD - 2006/95/EC).

Foreword to amendment A12

This document (EN 61009-1:2012/A12:2016) has been prepared by CLC/TC 23E "Circuit breakers and similar devices for household and similar applications".

The following dates are fixed:

- latest date by which the document has to be implemented at national level by publication of an identical national standard or by endorsement (dop) 2017-02-11
- latest date by which the national standards conflicting with the document have to be withdrawn (dow) 2019-02-11

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. CENELEC [and/or CEN] shall not be held responsible for identifying any or all such patent rights.

This standard covers the Principle Elements of the Safety Objectives for Electrical Equipment Designed for Use within Certain Voltage Limits (LVD - 2006/95/EC).

This document has been prepared under a mandate given to CENELEC by the European Commission and the European Free Trade Association, and supports essential requirements of EU Directive(s).

For the relationship with EU Directive(s) see informative Annex ZZ, included in EN 61009-1:2012.

Annex ZA (normative)

Normative references to international publications with their corresponding European publications

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

NOTE When an international publication has been modified by common modifications, indicated by (mod), the relevant EN/HD applies.

Publication	Year	Title	EN/HD	Year
CISPR 14-1 + corr. January	2005 2009	Electromagnetic compatibility - Requirements for household appliances, electric tools and similar apparatus - Part 1: Emission	EN 55014-1	2006
[C1] Text deleted [C1]				
IEC 60060-1 + corr. March + corr. March	1989 1990 1992	High-voltage test techniques - Part 1: General definitions and test requirements	HD 588.1 S1 ¹⁾	1991
IEC 60060-2	1994	High-voltage test techniques - Part 2: Measuring systems	EN 60060-2 ²⁾	1994
IEC 60068-2-30	2005	Environmental testing - Part 2-30: Tests - Test Db: Damp heat, cyclic (12 h + 12 h cycle)	EN 60068-2-30	2005
IEC 60068-3-4	2001	Environmental testing - Part 3-4: Supporting documentation and guidance - Damp heat tests	EN 60068-3-4	2002
IEC 60112 + corr. October + corr. June	2003 2003 2003	Method for the determination of the proof and the comparative tracking indices of solid insulating materials	EN 60112	2003
[C1] IEC 60228	2004	Conductors of insulated cables	EN 60228 + corr. May	2005 2005 [C1]
IEC 60364	Series	Low-voltage electrical installations	HD 60364	Series
IEC 60417	Data-base	Graphical symbols for use on equipment	-	-
[C1] IEC 60364-4-44 (mod) + corr. May	2007 2010	Low-voltage electrical installations Part 4-44: Protection for safety - Protection against voltage disturbances and electromagnetic disturbances	HD 60364-4-444 + corr. July + AC:2012	2010 2010 2012 [C1]
IEC 60364-5-52	2001	Electrical installations of buildings - Part 5-52: Selection and erection of electrical equipment - Wiring systems	-	-
IEC 60364-5-53	2001	Electrical installations of buildings - Part 5-53: Selection and erection of electrical equipment - Isolation, switching and control	-	-
IEC 60529	-	Degrees of protection provided by enclosures (IP Code)	-	-
IEC 60664-1	2007	Insulation coordination for equipment within low-voltage systems - Part 1: Principles, requirements and tests	EN 60664-1	2007

¹⁾ HD 588.1 S1 is superseded by EN 60060-1:2010, which is based on IEC 60060-1:2010.

²⁾ EN 60060-2 is superseded by EN 60060-2:2011, which is based on IEC 60060-2:2010. [C1]

 Publication	Year	Title	EN/HD	Year
 IEC 60664-3	-	Insulation coordination for equipment within low-voltage systems Part 3: Use of coating, potting or moulding for protection against pollution	EN 60664-3	-
IEC 60695-2-10	-	Fire hazard testing Part 2-10: Glowing/hot-wire based test methods - Glow-wire apparatus and common test procedure	EN 60695-2-10 ¹⁾	-
IEC 60695-2-11 + corr. January	2000 2001	Fire hazard testing Part 2-11: Glowing/hot-wire based test methods - Glow-wire flammability test method for end-products	EN 60695-2-11	2001 
IEC 60898-1 (mod)	2002	Electrical accessories - Circuit breakers for overcurrent protection for household and similar installations - Part 1: Circuit-breakers for a.c. operation	EN 60898-1 + corr. February + A11 + A12	2003 2004 2005 2008
IEC 61009	Series	Residual current operated circuit-breakers with integral overcurrent protection for household and similar uses (RCBO's)	EN 61009	Series
 IEC 61543	1995	Residual current-operated protective devices (RCDs) for household and similar use - Electromagnetic compatibility	EN 61543	1995
-	-		+ corr. December	1997
+ A1 (mod)	2004		+ A11	2003
-	-		+ corr. May	2004
+ A2	2005		+ A2	2006
-	-		+ A12	2005 
ISO 7000	1989	Graphical symbols for use on equipment - Index and synopsis	-	- 

 ¹⁾ EN 60695-2-10 is superseded by EN 60695-2-10:2013, which is based on IEC 60695-2-10:2013. 

Annex ZB (normative)

Special national conditions

Special national condition: National characteristic or practice that cannot be changed even over a long period, e.g. climatic conditions, electrical earthing conditions.

NOTE If it affects harmonization, it forms part of the European Standard / Harmonization Document.

For the countries in which the relevant special national conditions apply these provisions are normative, for other countries they are informative.

<u>Clause</u>	<u>Special national condition</u>
---------------	-----------------------------------

General	Germany
----------------	----------------

In Germany the use of RCBOs of type AC is not permitted. 

General	Ireland
----------------	----------------

EN 61009-1 (referred to as Part 1) is applicable with the modifications given immediately below:

For RCBOs functionally dependant on line voltage IEC 61009-2-2 applies in conjunction with Part 1.

In Ireland, where neutrals are reliably at earth potential, RCBOs with unswitched neutral current paths are permitted for use in accordance with The National Rules For Electrical Installations. The requirements of these types of devices are given in the original text of IEC 61009-1.

Details of the particular clauses are listed below.

3.3.16	Ireland
--------	----------------

The text remains as given in the original IEC text.

3.3.17	Ireland
--------	----------------

The text remains as given in the original IEC text.

4.3	Ireland
-----	----------------

The text remains as given in the original IEC text.

5.3.1	Ireland
-------	----------------

Only the text referring to rated voltages of 120 V is deleted.

9.7.2	Ireland
-------	----------------

The text remains as given in the original IEC text.

9.12.2	Ireland
--------	----------------

The text remains as given in the original IEC text.

9.12.7	Ireland
--------	----------------

The text remains as given in the original IEC text.

9.12.9.1	Ireland
----------	----------------

The text remains as given in the original IEC text.

9.12.11.3	Ireland
-----------	----------------

The text remains as given in the original IEC text.

9.12.11.4	Ireland
-----------	----------------

The text remains as given in the original IEC text.

<u>Clause</u>	<u>Special national condition</u>
9.17.4	Ireland The text remains as given in the original IEC text.
9.20	Ireland In Paragraph 4, the last line after 'neutral pole' neutral path also applies.
Figure 7 and Figure 8	Ireland Retain as given in the original IEC text
Table A.3	Ireland The text remains as given in the original IEC text.
ZE.3.3	Ireland Only universal screwless type terminals are accepted.
ZF.1	Ireland The use of RCBOs with flat quick-connect terminations for rated currents up to and including 20 A is accepted.
ZF.8.2.2	Ireland The use for rated currents up to and including 20 A is accepted.
General	Switzerland In Switzerland, the use of RCBOs of type AC is not permitted.
General	United Kingdom In the United Kingdom, where neutrals are reliably at earth potential, RCBOs with un-switched neutral current paths are permitted. The requirements of these types of devices are given in the original text of IEC 61009-1. Details of the particular clauses are listed below.
3.3.16	United Kingdom The text remains as given in the original IEC text.
3.3.17	United Kingdom The text remains as given in the original IEC text.
4.3	United Kingdom The text remains as given in the original IEC text.
5.3.1	United Kingdom Only the text referring to rated voltages of 120 V is deleted.
9.7.2	United Kingdom The text remains as given in the original IEC text.
9.7.7.2	United Kingdom 4th paragraph, 2nd line – add '(or path)' after 'neutral pole'
9.7.7.2	United Kingdom 5th paragraph, 2nd line – add '(or path)' after 'neutral pole'
9.12.2	United Kingdom The text remains as given in the original IEC text.
9.12.7	United Kingdom The text remains as given in the original IEC text.
9.12.9.1	United Kingdom The text remains as given in the original IEC text.

<u>Clause</u>	<u>Special national condition</u>
9.12.11.3	United Kingdom The text remains as given in the original IEC text.
9.12.11.4	United Kingdom The text remains as given in the original IEC text.
9.17.4	United Kingdom The text remains as given in the original IEC text.
Figure 7 & Figure 8	United Kingdom Retain as given in the original IEC text.
Table A.3	United Kingdom The text remains as given in the original IEC text.

Annex ZC (informative)

A-deviations

A-deviation: National deviation due to regulations, the alteration of which is for the time being outside the competence of the CENELEC member.

This European Standard falls under Directive 2004/108/EC.

NOTE (from CEN/CENELEC IR Part 2:2011 , 2.17) Where standards fall under EC Directives, it is the view of the Commission of the European Communities (OJ No C 59, 1982-03-09) that the effect of the decision of the Court of Justice in case 815/79 Cremonini/Vrankovich (European Court Reports 1980, p. 3583) is that compliance with A-deviations is no longer mandatory and that the free movement of products complying with such a standard should not be restricted except under the safeguard procedure provided for in the relevant Directive.

A-deviations in an EFTA-country are valid instead of the relevant provisions of the European Standard in that country until they have been removed.

<u>Clause</u>	<u>Deviation</u>
---------------	------------------

Austria

Regulations for electrical low voltage installations, statutory order BGBl. II/223/2010, issued 12. July 2010.

- | | |
|------------|--|
| 4.1 | The content of the note of IEC 61009-1 Ed. 3 remains with the adaption to national reference: "The selection of the various types is made according to the requirements of OVE/ONORM E 8001-1:2010." |
| 4.1 | Table Z1 is not valid in Austria.  |

Annex ZD
(normative)

Classification of RCBOs Type B and C up to and including 63A into energy limiting classes

RCBOs of B-type and C-type up to and including 63A, shall be classified into energy limiting classes 1 or 3 in accordance with Tables ZD.1 or ZD.2, as applicable, and be marked with the number of the energy limiting class in a square adjoining the symbol given in t) of Clause 6. This classification shall not be applied to RCBOs type D and to RCBOs with rated current higher than 63A.

Table ZD.1 – Permissible I^2t (let-through) values for RCBOs type B with rated current up to and including 63 A

Type B					
Rated short-circuit capacity(A) I_{cn}	Class 1	class 3			
	$\leq 63A$	$\leq 16A$	20A, 25A, 32A	40A	50A, 63A
3 000	No limits specified	15 000	18 000	21 600	28 000
4 500		25 000	32 000	38 400	48 000
6 000		35 000	45 000	54 000	65 000
10 000		70 000	90 000	108 000	135 000

Table ZD.2 – Permissible I^2t (let-through) values for RCBOs type C with rated current up to and including 63 A

Type C					
Rated short-circuit capacity(A) I_{cn}	Class 1	class 3			
	$\leq 63A$	$\leq 16A$	20A, 25A, 32A	40A	50A, 63A
3 000	No limits specified	17 000	20 000	24 000	30 000
4 500		28 000	37 000	45 000	55 000
6 000		40 000	52 000	63 000	75 000
10 000		80 000	100 000	120 000	145 000

C1 The maximum I^2t values measured during the test sequence F_0 or F_1 as applicable serve as reference values for the classification. **C1**

Compliance with the requirements of Tables ZD.1 and ZD.2 is checked on the RCBOs with the highest rated current available within the range covered by each of these tables.

If these current ratings are not included in the samples submitted to test sequences F_0 or F_1 of Annex A, the appropriate number of samples of these ratings shall be additionally submitted to that test sequence. None of the values measured shall exceed the permissible I^2t value of the proposed energy limiting class in accordance with Tables ZD.1 and ZD.2.

If RCBOs rated 40 A are submitted with the range of RCBOs with rating exceeding 16 A and their measured I^2t values are lower than those indicated in Tables ZD.1 or ZD.2 for rating 32 A, no relevant test is necessary for the RCBOs rated 32 A.

If RCBOs rated 50 A or 63 A are submitted with the range of RCBOs with rating exceeding 32 A and their measured I^2t values are lower than those indicated in Tables ZD.1 or ZD.2 for rating 40 A, no relevant test is necessary for the RCBOs rated 40 A **C**

Annex ZXX
(Informative)

List of clauses that require retesting

Based on EN 61009-1:2012/FprA1:2014, the following tests and/or requirements have been technically modified and may require retesting or inspection as applicable:

- 8.1.3 Clearances and creepage distances (see Annex B)

Annex ZZ (informative)

Coverage of Essential Requirements of EU Directives

This European Standard has been prepared under a mandate given to CENELEC by the European Commission and the European Free Trade Association and within its scope the standard covers all relevant essential requirements as given in Article 1 of Annex I of the EU Directive 2004/108/EC.

Compliance with this standard provides one means of conformity with the specified essential requirements of the Directive(s) concerned.

WARNING: Other requirements and other EU Directives may be applicable to the products falling within the scope of this standard.

_____ 

CONTENTS

FOREWORD.....	8
INTRODUCTION.....	10
1 Scope.....	11
2 Normative references	12
3 Terms and definitions.....	13
3.1 Definitions relating to currents flowing from live parts to earth	13
3.2 Definitions relating to the energization of a residual current circuit-breaker.....	13
3.3 Definitions relating to the operation and functions of residual current circuit-breakers	14
3.4 Definitions relating to values and ranges of energizing quantities	17
3.5 Definitions relating to values and ranges of influencing quantities	21
3.6 Definitions relating to terminals.....	22
3.7 Definitions relating to conditions of operation	23
3.8 Definitions relating to constructional elements.....	24
3.9 Definitions relating to tests	26
3.10 Definitions relating to insulation coordination	26
4 Classification.....	28
4.1 According to the method of operation.....	28
4.1.1 RCBO functionally independent of line voltage (see 3.3.8).....	28
4.1.2 RCBO functionally dependent on line voltage (see 3.3.9).....	28
4.2 According to the type of installation	28
4.3 According to the number of poles and current paths	29
4.4 According to the possibility of adjusting the residual operating current.....	29
4.5 According to resistance to unwanted tripping due to voltage surges	29
4.6 According to behaviour in presence of d.c. components	29
4.7 According to time-delay (in presence of a residual current)	29
4.8 According to the protection against external influences	29
4.9 According to the method of mounting.....	29
4.10 According to the method of connection	30
4.11 According to the instantaneous tripping current (see 3.4.18)	30
4.12 According to the I^2t characteristic	30
4.13 According to the type of terminals.....	30
4.Z.1 According to the range of ambient air temperature	30
5 Characteristics of RCBOs	30
5.1 Summary of characteristics.....	30
5.2 Rated quantities and other characteristics.....	31
5.2.1 Rated voltage	31
5.2.2 Rated current (I_n).....	31
5.2.3 Rated residual operating current ($I_{\Delta n}$).....	32
5.2.4 Rated residual non-operating current ($I_{\Delta no}$).....	32
5.2.5 Rated frequency	32
5.2.6 Rated short-circuit capacity (I_{cn}).....	32
5.2.7 Rated residual making and breaking capacity ($I_{\Delta m}$).....	32
5.2.8 RCBO type S	32

5.2.9	Operating characteristics in case of residual currents with d.c. components	32
5.3	Standard and preferred values.....	32
5.3.1	Preferred values of rated voltage (U_n)	32
5.3.2	Preferred values of rated current (I_n)	33
5.3.3	Standard values of rated residual operating current ($I_{\Delta n}$)	33
5.3.4	Standard value of residual non-operating current ($I_{\Delta no}$).....	33
5.3.5	Standard values of rated frequency	33
5.3.6	Values of rated short-circuit capacity	33
5.3.7	Minimum value of the rated residual making and breaking capacity ($I_{\Delta m}$) ..	34
5.3.8	Limiting values of break time and non-actuating time for RCBO of type AC and A	34
5.3.9	Standard ranges of overcurrent instantaneous tripping	35
5.3.10	Standard values of rated impulse withstand voltage (U_{imp})	36
6	Marking and other product information	36
6.2.1	Standard Marking	36
6.2.2	Additional Marking	37
7	Standard conditions for operation in service and for installation.....	40
7.1	Standard conditions	40
7.2	Conditions of installation.....	40
7.3	Pollution degree	40
8	Requirements for construction and operation	40
8.1	Mechanical design	40
8.1.1	General	40
8.1.2	Mechanism	41
8.1.3	Clearances and creepage distances (see also Annex B)	43
8.1.4	Screws, current-carrying parts and connections.....	45
8.1.5	Terminals for external conductors	46
8.1.6	Non-interchangeability	48
8.1.2.1	Mechanical amounting of plug-in type RCBOs	48
8.2	Protection against electric shock.....	49
8.3	Dielectric properties and isolating capability	49
8.4	Temperature-rise	49
8.4.1	Temperature-rise limits.....	49
8.4.2	Ambient air temperature.....	50
8.5	Operating characteristics	50
8.5.1	Under residual current conditions	50
8.5.2	Under overcurrent conditions	50
8.6	Mechanical and electrical endurance	52
8.7	Performance at short-circuit currents	52
8.8	Resistance to mechanical shock and impact	52
8.9	Resistance to heat.....	52
8.10	Resistance to abnormal heat and to fire	52
8.11	Test device	52
8.12	Requirements for RCBOs functionally dependent on line voltage.....	53
8.13	Void	53

8.14	Behaviour of RCBOs in case of current surges caused by impulse voltages	53
8.15	Behaviour of RCBOs in case of earth fault currents comprising a d.c. component	53
8.16	Reliability	54
8.17	Electromagnetic compatibility (EMC).....	54
8.Z.1	Behaviour of RCBOs at low ambient air temperatures	54
9	Tests	54
9.1	General	54
9.2	Test conditions	55
9.3	Test of indelibility of marking	56
9.4	Test of reliability of screws, current-carrying parts and connections	56
9.5	Test of reliability of screw-type terminals for external copper conductors	57
9.6	Verification of protection against electric shock	59
9.7	Test of dielectric properties and isolating capability	59
9.7.1	Resistance to humidity	59
9.7.2	Insulation resistance of the main circuit.....	60
9.7.3	Dielectric strength of the main circuit.....	61
9.7.4	Insulation resistance and dielectric strength of auxiliary circuits.....	61
9.7.5	Secondary circuit of detection transformers	62
9.7.6	Capability of control circuits connected to the main circuit withstanding high d.c. voltages due to insulation measurements	62
9.7.7	Verification of impulse withstand voltages (across clearances and across solid insulation) and of leakage current across open contacts.....	63
9.8	Test of temperature-rise.....	66
9.8.1	Ambient air temperature.....	66
9.8.2	Test procedure	67
9.8.3	Measurement of the temperature of parts	67
9.8.4	Temperature-rise of a part.....	67
9.9	Verification of the operating characteristic.....	67
9.9.1	Verification of the operating characteristic under residual current conditions	67
9.9.2	Verification of the operating characteristic under overcurrent conditions....	70
9.10	Verification of mechanical and electrical endurance	72
9.10.1	General test conditions	72
9.10.2	Test procedure	72
9.10.3	Condition of the RCBO after test	73
9.11	Verification of the trip-free mechanism	73
9.11.1	General test conditions	73
9.11.2	Test procedure	73
9.12	Short-circuit tests	73
9.12.1	General conditions for test	73
9.12.2	Test circuit for short-circuit performance	74
9.12.3	Values of test quantities	76
9.12.4	Tolerances on test quantities.....	76
9.12.5	Power factor of the test circuit.....	76
9.12.6	Measurement and verification of I^2t and of the peak current (I_p).....	77
9.12.7	Calibration of the test circuit.....	77
9.12.8	Interpretation of records.....	77

9.12.9	Condition of the RCBO for test	77
9.12.10	Behaviour of the RCBO during short-circuit tests	78
9.12.11	Test procedure	78
9.12.12	Verification of the RCBO after short-circuit test	83
	[C] text deleted [C]	
[C] 9.13	Mechanical Stresses	84 [C]
9.13.1	Mechanical shock	84
[C] 9.13.2	Resistance to mechanical stresses and impact	85 [C]
9.14	Test of resistance to heat	88
9.15	Test of resistance to abnormal heat and to fire	89
9.16	Verification of the operation of the test device at the limits of rated voltage	90
9.17	Verification of the behaviour of RCBOs functionally dependent on line voltage, classified under 4.1.2.1, in case of failure of the line voltage	90
9.17.1	Determination of the limiting value of the line voltage (U_x)	90
9.17.2	Verification of the [C] behaviour [C] in case of failure of the line voltage	91
9.17.3	Verification of the correct operation, in presence of a residual current, for RCBOs opening with delay in case of failure of the line voltage	91
9.17.4	Verification of correct operation of RCBOs with three or four [C] poles [C] , in presence of a residual current, the neutral and one line terminal only being energized	91
9.17.5	[C] text deleted [C]	
9.18	[C] Void [C]	91
9.19	Verification of behaviour of RCBOs in case of current surges caused by impulse voltages	92
9.19.1	Current surge test for all RCBOs (0,5 µs/100 kHz ring wave test)	92
9.19.2	Verification of behaviour at surge currents up to 3 000 A (8/20 µs surge current test)	92
9.20	Verification of resistance of the insulation against an impulse voltage	93
9.21	[A2] Void [A2]	93
9.21.1	Type A residual current devices	93
9.22	Verification of reliability	94
9.22.1	Climatic test	94
9.22.2	Test with temperature of 40 °C	96
9.23	Verification of ageing of electronic components	96
9.24	Electromagnetic compatibility (EMC)	97
[A2] 9.24.1	Tests covered by the present standard	97
9.24.2	Additional tests	97
9.25	Test of resistance to rusting	97 [A2]
[C] 9.21	Verification of the correct operation at low ambient temperatures for RCBOs for use at temperatures between -25 °C and +40 °C	98 [C]
Annex A (normative) Test sequence and number of samples to be submitted for certification purposes		
		121
Annex B (normative) Determination of clearances and creepage distances		
		127
Annex C (normative) Arrangement for the detection of the emission of ionized gases during short-circuit tests		
		132
Annex D (normative) Routine tests		
		135
Annex E (normative) Special requirements for auxiliary circuits for safety extra-low voltage ...		
		136

Annex F (normative) Coordination between RCBOs and separate fuses associated in the same circuit	137
Annex G (normative) Additional requirements and tests for RCBOs consisting of a circuit-breaker and a residual current unit designed for assembly on site	138
Annex H (informative) Void	142
Annex IA (informative) Methods for determination of short-circuit power-factor	143
Annex IB (informative) Glossary of symbols	145
Annex IC (informative) Examples of terminals	146
[C] text deleted [C]	
Annex IE (informative) Follow-up testing programme for RCBOs	149
Annex J (normative) Particular requirements for RCBOs with screwless type terminals for external copper conductors	153
Annex K (normative) Particular requirements for RCBOs with flat quick-connect terminations	162
Bibliography	169
Figure 1 – Thread-forming tapping screw (3.6.10)	99
Figure 2 – Thread-cutting tapping screw (3.6.11)	99
Figure 3 – Jointed test finger (9.6)	100
Figure 4 – Test circuit for the verification of	
– operating characteristics (9.9.1)	
– trip-free mechanism (9.11)	
– behaviour in case of failure of line voltage (9.17.3 and 9.17.4) for RCBOs functionally dependent on line voltage	
[C] – behaviour at low ambient air temperature of RCBOs for use in the range of -25 °C to +40 °C (9.Z1)	101 [C]
Figure 5 – Test circuit for the verification of the correct operation of RCBOs, in the case of residual pulsating direct currents	102
Figure 6 – Test circuit for the verification of the correct operation in case of residual pulsating direct currents in presence of a standing smooth direct current of 0,006 A	103
Figure 7 – Test circuit for the verification of the suitability of an RCBO for use in IT systems (9.12.11.2.2)	105
Figure 8 – Typical diagram for short-circuit test according to 9.12.11.2.2	106
Figure 9 – Detail of impedances Z , Z_1 and Z_2	106
Figure 11 – [C] Void [C]	106
[C] Figure Z4 – Example of short-circuit making or breaking test record in the case of a single-pole RCBO on single phase a.c.	107 [C]
[C] text deleted [C]	
Figure 14 – Mechanical shock test apparatus (9.13.1)	108
Figure 15 – Mechanical impact test apparatus (9.13.2.1)	109
Figure 16 – Striking element for pendulum impact test apparatus (9.13.2.1)	110
Figure 17 – Mounting support for sample for mechanical impact test (9.13.2.1)	111
Figure 18 – Example of mounting an unenclosed RCBO for mechanical impact test (9.13.2.1)	112
Figure 19 – Example of mounting of panel mounting type RCBO for the mechanical impact test (9.13.2.1)	113
Figure 20 – Application of force for mechanical impact test of rail mounted RCBO (9.13.2.2)	114
Figure 21 – Ball-pressure test apparatus (9.14.2)	114
Figure 22 – [C] Void [C]	114

Figure 23 – Stabilizing period for reliability test (9.22.1.3).....	115
Figure 24 – Reliability test cycle (9.22.1.3)	116
Figure 25 – Example of a test circuit for verification of ageing  text deleted  (9.23)	117
Figure 26 – Damped oscillator current wave, 0,5 µs/100 kHz	117
Figure 27 – Test circuit for the ring wave test at RCBOs	118
Figure 28 – Surge current impulse 8/20 µs	118
Figure 29 – Test circuit for the surge current test at RCBOs.....	119
 Figure Z5 – Example of application of force for mechanical test on two-pole plug-in RCBO, the holding in position of which depends solely on the plug-in connections (9.13.2.3)	119
Figure Z6 – Test cycle for low temperature test (9.Z.1)	120
Figure Z7 – Diagrammatic representation of a small part	120 
Figure B.1 to B.10 – Illustrations of the application of creepage distances	128
Figure C.1 – Test arrangement	133
Figure C.2 – Grid	134
Figure C.3 – Grid circuit	134
Figure IC.1 – Examples of pillar terminals	146
Figure IC.2 – Example of screw terminals and stud terminals	147
Figure IC.3 – Example of saddle terminals	148
Figure IC.4 – Examples of lug terminals	148
Figure J.1 – Connecting samples	158
Figure J.2 – Examples of screwless-type terminals	160
Figure K.1 – Example of position of the thermocouple for measurement of the temperature-rise	165
Figure K.2 – Dimensions of male tabs	166
Figure K.3 – Dimensions of round dimple detents (see Figure K.2)	167
Figure K.4 – Dimensions of rectangular dimple detents (see Figure K.2).....	167
Figure K.5 – Dimensions of hole detents	167
Figure K.6 – Dimensions of female connectors	168
Table Z1 – Survey of the types of RCBOs according to their method of operation.....	28
 Table 1 – Standard values of rated short-circuit capacity and of the rated residual making and breaking capacity	34 
Table 2 – Limiting values of break time and non-actuating time for alternating residual currents (r.m.s. values) for type AC and A RCBO	34
Table 3 – Maximum values of break time for half-wave residual currents (r.m.s. values) for type A RCBO	35
Table 4 – Ranges of overcurrent instantaneous tripping	36
Table Z3 – Requirements for marking	38
 text deleted 	
Table 6 – Standard conditions for operation in service	40
Table 7 – Minimum clearances and creepage distances	44
Table 8 – Connectable cross-sections of copper conductors for screw-type terminals.....	47
Table 9 – Temperature-rise values	50
Table 10 – Time-current operating characteristics	51
Table 11 – Requirements for RCBOs functionally dependent on line voltage	53
Table 12 – List of type tests.....	54
Table 13 – Test copper conductors corresponding to the rated currents.....	55

Table 14 – Screw thread diameters and applied torques	56
Table 15 – Pulling forces	58
Table 17 – Test voltage of auxiliary circuits	62
A1 Table 19 – Test voltage for verification of impulse withstand voltage	64 A1
Table 28 – Test voltage for verifying the suitability for isolation, referred to the rated impulse withstand voltage of the RCBO and the altitude where the test is carried out.....	65
Table 26 – Tripping current ranges for type A RCBOs	70
Table 20 – List of short-circuit tests	74
Table 21 – Power factor ranges of the test circuit.....	76
Table 22 – Ratio between service short-circuit capacity (I_{cs}) and rated short-circuit capacity (I_{cn}) – (factor k)	81
Table 23 – Test procedure for I_{cs} in the case of single- and two-pole RCBOs	81
Table 24 – Test procedure for I_{cs} in the case of three- and four-pole RCBOs	82
Table 25 – Test procedure for I_{cn}	82
Table 26 – Tripping current ranges for type A RCBOs	93
A2 Table 27 – Tests to be applied for EMC	97
Table 29 – Test to be carried out according to IEC 61543.....	97 A2
Table A.1 – Test sequences.....	121
Table A.2 – Number of samples for full test procedure	123
Table A.3 – Number of samples for simplified test procedure	125
Table A.4 – Test sequences for RCBOs having different instantaneous tripping currents.....	126
Table A.5 – Test sequences for RCBOs of different classification according to 4.6.....	126
Table IE.1 – Test sequences during follow-up inspections	149
Table IE.2 – Number of samples to be tested.....	152
Table J.1 – Connectable conductors	155
Table J.2 – Cross-sections of copper conductors connectable to screwless-type terminals ...	156
Table J.3 – Pull forces.....	157
Table K.1 – Informative table on colour code of female connectors in relationship with the cross section of the conductor	163
Table K.2 – Overload test forces	164
Table K.3 – Dimensions of tabs	165
Table K.4 – Dimensions of female connectors.....	168

INTERNATIONAL ELECTROTECHNICAL COMMISSION

RESIDUAL CURRENT OPERATED CIRCUIT-BREAKERS WITH INTEGRAL OVERCURRENT PROTECTION FOR HOUSEHOLD AND SIMILAR USES (RCBOs) –

Part 1: General rules

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 61009-1 has been prepared by subcommittee 23E: Circuit-breakers and similar equipment for household use, of IEC technical committee 23: Electrical accessories.

This third edition cancels and replaces the second edition, published in 1996, amendment 1 (2002) and amendment 2 (2006). It constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- complete revision of EMC sequences, including the new test T.2.6, already approved in IEC 61543;
- clarification of RCDs current/time characteristics reported in Tables 2 and 3;
- revision of test procedure for $I_{\Delta n}$ between 5 A and 200 A;

- tests for the use of RCBOs in IT systems;
- testing procedure regarding the 6mA d.c. current superimposed to the fault current;
- improvement highlighting RCDs with multiple sensitivity;
- some alignments with IEC 60898-1.

The text of this standard is based on the following documents:

FDIS	Report on voting
23E/682/FDIS	23E/686/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all the parts in the IEC 61009 series, under the general title *Residual current operated circuit-breakers with integral overcurrent protection for household and similar uses (RCBOs)*, can be found on the IEC website.

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

INTRODUCTION

This part includes definitions, requirements and tests covering all types of RCBOs. For applicability to a specific type, this part applies in conjunction with the relevant part, as follows:

Part 2-1: Applicability of the general rules to RCBOs functionally independent of line voltage.

Part 2-2: Applicability of the general rules to RCBOs functionally dependent on line voltage.

RESIDUAL CURRENT OPERATED CIRCUIT-BREAKERS WITH INTEGRAL OVERCURRENT PROTECTION FOR HOUSEHOLD AND SIMILAR USES (RCBOs) –

Part 1: General rules

1 Scope

This International Standard applies to residual current operated circuit-breakers with integral overcurrent protection functionally independent of, or functionally dependent on, line voltage for household and similar uses (hereafter referred to as RCBOs), for rated voltages not exceeding 440 V a.c. ~~text deleted~~ and rated currents not exceeding 125 A for fixed installations and rated short-circuit capacities not exceeding 25 000 A. They are intended for use in an environment with pollution degree 2, and overvoltage category III.

These devices are intended to protect people against indirect contact, the exposed conductive parts of the installation being connected to an appropriate earth electrode and to protect against overcurrents the wiring installations of buildings and similar applications. They may be used to provide protection against fire hazards due to a persistent earth fault current, without the operation of the overcurrent protective device.

RCBOs having a rated residual operating current not exceeding 30 mA are also used as a means for additional protection in the case of failure of the protective means against electric shock.

This standard applies to devices performing simultaneously the function of detection of the residual current, of comparison of the value of this current with the residual operating value and of opening of the protected circuit when the residual current exceeds this value, and also of performing the function of making, carrying and breaking overcurrents under specified conditions.

NOTE 1 The content of the present standard related to operation under residual current conditions is based on IEC 61008-1. The content of the present standard related to protection against overcurrents is based on IEC 60898-1.

NOTE 2 RCBOs are essentially intended to be operated by uninstructed persons and designed not to require maintenance. They may be submitted for certification purposes.

NOTE 3 Installation and application rules of RCBOs are given in the IEC 60364 series.

They are intended for use in an environment with pollution degree 2.

NOTE 4 For more severe overvoltage conditions, circuit-breakers complying with other standards (e.g. IEC 60947-2) should be used.

NOTE 5 For environments with higher pollution degrees, enclosures giving the appropriate degree of protection should be used.

RCBOs of the general type are resistant to unwanted tripping, including the case where surge voltages (as a result of switching transients or induced by lightning) cause loading currents in the installation without occurrence of flashover.

RCBOs of type S are considered to be sufficiently proof against unwanted tripping even if the surge voltage causes a flashover and a follow-on current occurs.

NOTE 6 Surge arresters installed downstream of the general type of RCBOs and connected in common mode may cause unwanted tripping.

RCBOs are suitable for isolation.

RCBOs complying with this standard, ~~text deleted~~ are suitable for use in IT systems.

Special precautions (e.g. lightning arresters) may be necessary when excessive overvoltages are likely to occur on the supply side (for example in the case of supply through overhead lines) (see IEC 60364-4-44).

NOTE 7 For RCBOs having a degree of protection higher than IP20 special constructions may be required.

This standard also applies to RCBOs obtained by the assembly of an adaptable residual current device with a circuit-breaker. The mechanical assembly shall be effected in the factory by the manufacturer, or on site, in which case the requirements of Annex G shall apply.

~~text deleted~~

Supplementary requirements may be necessary for RCBOs of the plug-in type.

~~Particular requirements are necessary for RCBOs :~~

- integrated in one unit with a socket-outlet or designed exclusively for being associated locally with a socket-outlet in the same mounting box;
- if intended to be used at frequencies other than 50 Hz or 60 Hz.

~~For RCBOs incorporated in, or intended only for association with socket-outlets, the requirements of this standard may be used, as far as applicable, in conjunction with the national requirements for socket outlets of the country where the product is placed on the market.~~

NOTE ~~Residual current-operated protective devices (RCDs) incorporated in, or intended only for association with socket-outlets, can either meet IEC 62640 or this standard.~~

~~text deleted~~

This standard does not apply to:

- RCBOs intended to protect motors;
- RCBOs the current setting of which is adjustable by means accessible to the user in normal service.

The requirements of this standard apply for normal environmental conditions (see 7.1). Additional requirements may be necessary for RCBOs used in locations having severe environmental conditions.

RCBOs including batteries are not covered by this standard.

A guide for the coordination of RCBOs with fuses is given in Annex F.

2 Normative references

~~NOTE~~ Normative references to international publications are listed in Annex ZA (normative).

3 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

Where the terms "voltage" or "current" are used, they imply r.m.s. values, unless otherwise specified.

NOTE 1 Reference to IEC definitions is also made when the terms "device" or "mechanical switching device" are replaced by the term "RCBO".

NOTE 2 For a glossary of symbols see Annex IB.

3.1 Definitions relating to currents flowing from live parts to earth

3.1.1

earth fault current

current flowing to earth due to an insulation fault

3.1.2

earth leakage current

current flowing from the live parts of the installation to earth in the absence of an insulation fault

3.1.3

pulsating direct current

current of pulsating wave form which assumes, in each period of the rated power frequency, the value 0 or a value not exceeding 0,006 A d.c. during one single interval of time, expressed in angular measure, of at least 150°

3.1.4

current delay angle α

time, expressed in angular measure, by which the starting instant of current conduction is delayed by phase control

3.2 Definitions relating to the energization of a residual current circuit-breaker

3.2.1

energizing quantity

electrical excitation quantity which, alone or in combination with other such quantities, shall be applied to an RCBO to enable it to accomplish its function under specified conditions

3.2.2

energizing input-quantity

energizing quantity by which the RCBO is activated when it is applied under specified conditions

NOTE These conditions may involve, for example, the energizing of certain auxiliary elements.

3.2.3

residual current

I_{Δ}

vector sum of the instantaneous values of the current flowing in the main circuit of the RCBO (expressed as r.m.s. value)

3.2.4

residual operating current

value of residual current which causes the RCBO to operate under specified conditions

3.2.5

residual non-operating current

value of residual current at and below which the RCBO does not operate under specified conditions

3.2.6

residual current ($I_{\Delta t}$) of an RCBO

value of residual current which is the lower limit of the overcurrent instantaneous tripping range according to type B, C or D (see footnote c of Table 2)

3.3 Definitions relating to the operation and functions of residual current circuit-breakers

3.3.1

switching device

device designed to make or break the current in one or more electric circuits

[IEV 441-14-01:1984]

3.3.2

mechanical switching device

switching device designed to close and open one or more electric circuits by means of separable contacts

[IEV 441-14-02: 1984, modified]

3.3.3

fuse

switching device that, by the melting of one or more of its specially designed and proportioned components, opens the circuit in which it is inserted by breaking the current when it exceeds a given value for a sufficient time. The fuse comprises all the parts that form the complete device

[IEV 441-18-01:1984, modified]

3.3.4

circuit-breaker

mechanical switching device, capable of making, carrying and breaking currents under normal circuit conditions and also making, carrying for a specified time and (automatically) breaking currents under specified abnormal conditions such as those of short-circuit

[IEV 441-14-20:1984, modified]

3.3.5

residual current operated circuit-breaker

mechanical switching device designed to make, carry and break currents under normal service conditions and to cause the opening of the contacts when the residual current attains a given value under specified conditions

3.3.6

residual current operated circuit-breaker without integral overcurrent protection

RCCB

residual current operated circuit-breaker not designed to perform the functions of protection against overloads and/or short-circuits

3.3.7

residual current operated circuit-breaker with integral overcurrent protection

RCBO

residual current operated circuit-breaker designed to perform the functions of protection against overloads and/or short-circuits

3.3.8

RCBOs functionally independent of line voltage

RCBOs for which the functions of detection, evaluation and interruption do not depend on the line voltage

NOTE These devices are defined in 2.3.2 of IEC/TR 60755:1983 as residual current devices without auxiliary source.

3.3.9

RCBOs functionally dependent on line voltage

RCBOs for which the functions of detection, evaluation or interruption depend on the line voltage

NOTE 1 This definition covers partially the definition of residual current devices with auxiliary source of 2.3.3 of IEC 60755:1983.

NOTE 2 It is understood that the line voltage is applied to the RCBO, for detection, evaluation or interruption.

3.3.10

break time of an RCBO

time which elapses between the instant when the residual operating current is suddenly attained and the instant of arc extinction in all poles

3.3.11

limiting non-actuating time

maximum delay during which a value of residual current higher than the residual non-operating current can be applied to the RCBO without causing it to operate

3.3.12

time-delay RCBO

RCBO specially designed to attain a pre-determined value of limiting non-actuating time, corresponding to a given value of residual current

3.3.13

closed position

position in which the predetermined continuity of the main circuit of the RCBO is secured

[IEV 441-16-22]

3.3.14

open position

position in which the predetermined clearance between open contacts in the main circuit of the RCBO is secured

[IEV 441-16-23]

3.3.15

pole

that part of an RCBO associated exclusively with one electrically separated conducting path of its main circuit provided with contacts intended to connect and disconnect the main circuit itself and excluding those portions which provide a means for mounting and operating the poles together

3.3.15.1

overcurrent protected pole

pole provided with an overcurrent release, hereafter referred to as protected pole

3.3.15.2

overcurrent unprotected pole

pole without an overcurrent release, but otherwise generally capable of the same performance as a protected pole of the same RCBO, hereafter referred to as unprotected pole

NOTE 1 To ensure this requirement, the unprotected pole may be of the same construction as the protected pole(s), or of a particular construction.

NOTE 2 If the short-circuit capacity of the unprotected pole is different from that of the protected pole(s), this should be indicated by the manufacturer.

3.3.15.3

switched neutral pole

pole only intended to switch the neutral and not intended to have a short-circuit capacity

3.3.16

⌈C⌋ Void ⌋C⌋

3.3.17

main circuit (of an RCBO)

all the conductive parts of an RCBO included in the ⌈C⌋ poles ⌋C⌋ (see 4.3)

3.3.18

control circuit (of an RCBO)

circuit (other than a path of the main circuit) intended for the closing operation or the opening operation, or both, of the RCBO

NOTE The circuits intended for the test device are included in this definition.

3.3.19

auxiliary circuit (of an RCBO)

all the conductive parts of an RCBO which are intended to be included in a circuit other than the main circuit and the control circuit of the RCBO

[IEV 441-15-04]

3.3.20

RCBO type AC

RCBO for which tripping is ensured for residual sinusoidal alternating currents, whether suddenly applied or slowly rising

3.3.21

RCBO type A

RCBO for which tripping is ensured for residual sinusoidal alternating currents and residual pulsating direct currents, whether suddenly applied or slowly rising

3.3.22

test device

device incorporated in the RCBO simulating the residual current conditions for the operation of the RCBO under specified conditions

3.3.Z1

plug-in RCBO

RCBO having one or more plug-in terminals (see 3.6.Z1) and designed for use with appropriate means for the plug-in connection 

3.4 Definitions relating to values and ranges of energizing quantities

3.4.1

rated value

quantity value assigned by the manufacturer, for a specific operating condition of an RCBO

3.4.2

overcurrent

any current exceeding the rated current

3.4.2.1

overload current

overcurrent occurring in an electrically undamaged circuit

NOTE An overload current may cause damage if sustained for a sufficient time.

3.4.2.2

short-circuit current

overcurrent resulting from a fault of negligible impedance between points intended to be at different potentials in normal service

NOTE A short-circuit current may result from a fault or from an incorrect connection.

3.4.3

prospective current

current that would flow in the circuit, if each main current path of the RCBO and of the overcurrent protective device (if any) were replaced by a conductor of negligible impedance

NOTE The prospective current may be qualified in the same manner as an actual current, for example: prospective breaking current, prospective peak current, prospective residual current, etc.

3.4.4

prospective peak current

peak value of a prospective current during the transient period following initiation

NOTE The definition assumes that the current is made by an ideal RCBO, i.e. with instantaneous transition from infinite to zero impedance. For circuits where the current can follow several different paths, for example polyphase circuits, it further assumes that the current is established simultaneously in all poles, even if the current only in one pole is considered.

3.4.5

maximum prospective peak current (of an a.c. circuit)

prospective peak current, when the initiation of the current takes place at the instant which leads to the highest possible value

NOTE For a multipole circuit-breaker in a polyphase circuit, the maximum prospective peak current refers to a single pole only.

3.4.6

short-circuit (making and breaking) capacity

alternating component of the prospective current, expressed by its r.m.s. value, which the RCBO is designed to make, to carry for its opening time and to break under specified conditions

3.4.6.1

ultimate short-circuit breaking capacity

breaking capacity for which the prescribed conditions according to a specified test sequence do not include the capability of the RCBO to carry 0,85 times its non-tripping current for the conventional time

3.4.6.2

service short-circuit breaking capacity

breaking capacity for which the prescribed conditions according to a specified test sequence include the capability of the RCBO to carry 0,85 times its non-tripping current for the conventional time

3.4.7

breaking current

current in a pole of an RCBO at the instant of initiation of the arc during a breaking process

[IEV 441-17-07:1984, modified]

NOTE For a.c., reference is made to the r.m.s. value.

3.4.8

applied voltage

voltage which exists across the terminals of a pole of an RCBO just before the making of the current

[IEV 441-17-24:1984]

NOTE This definition refers to a single-pole RCBO. For a multipole RCBO, the applied voltage is the voltage across the supply terminals of the RCBO.

3.4.9

recovery voltage

voltage which appears across the terminals of a pole of an RCBO after the breaking of the current

[IEV 441-17-25:1984]

NOTE 1 This voltage may be considered as comprising two successive intervals of time, one during which a transient voltage exists, followed by a second one during which power-frequency voltage alone exists.

NOTE 2 This definition refers to a single-pole RCBO. For a multipole RCBO, the recovery voltage is the voltage across the supply terminals of the RCBO.

3.4.9.1

transient recovery voltage

recovery voltage during the time in which it has a significant transient character

NOTE The transient voltage may be oscillatory or non-oscillatory or a combination of these depending on the characteristics of the circuit and of the RCBO. It includes the voltage shift of the neutral of a polyphase circuit.

[IEV 441-17-26:1984, modified]

3.4.9.2

power-frequency recovery voltage

recovery voltage after the transient voltage phenomena have subsided

[IEV 441-17-27:1984]

3.4.10

opening time

time measured from the instant at which, the RCBO being in the closed position, the current in the main circuit reaches the operating value of the overcurrent release to the instant when the arcing contacts have separated in all poles

NOTE The opening time is commonly referred to as tripping time, although, strictly speaking, tripping time applies to the time between the instant of initiation of the opening time and the instant at which the opening command becomes irreversible.

3.4.11

Definitions relating to arcing time

3.4.11.1

arcing time of a pole

interval of time between the instant of initiation of the arc in a pole and the instant of final arc extinction in that pole

[IEV 441-17-37, modified]

3.4.11.2

arcing time of a multipole RCBO

interval of time between the instant of first initiation of the arc and the instant of final arc extinction in all poles

[IEV 441-17-38]

3.4.12

break time (in case of overcurrent)

interval of time between the beginning of the opening time of an RCBO and the end of the arcing time, in case of overcurrent

[IEV 441-17-39:1984, modified]

3.4.13

I^2t (Joule integral)

integral of the square of the current over a given time interval (t_0 , t_1):

$$I^2t = \int_{t_0}^{t_1} i^2 dt$$

[IEV 441-18-23:1984]

3.4.14

I^2t characteristic of an RCBO

curve giving the maximum value of I^2t as a function of the prospective current under stated conditions of operation

3.4.15

Coordination between overcurrent protective devices in series

3.4.15.1

selectivity-limit current

I_s

current coordinate of the intersection between the maximum break-time current characteristic of the protective device on the load side and the pre-arcing (for fuses) or tripping (for circuit-breakers) time-current characteristic of the other protective device

NOTE 1 The selectivity-limit current is a limiting value of current:

- below which, in the presence of two overcurrent protective devices in series, the protective device on the load side completes its breaking operation in time to prevent the other protective device from starting its operation (i.e. selectivity is ensured);
- above which, in the presence of two overcurrent protective devices in series, the protective device on the load side may not complete its breaking operation in time to prevent the other protective device from starting its operation (i.e. selectivity is not ensured).

NOTE 2 I^2t characteristics may be used instead of time-current characteristics.

3.4.15.2

take-over current

I_B

current coordinate of the intersection between the maximum break time-current characteristics of two overcurrent protective devices

NOTE 1 The take-over current is a limiting value of current above which, in the presence of two overcurrent protective devices in series, the protective device generally, but not necessarily, on the supply side, provides back-up operation for the other protective device.

NOTE 2 I^2t characteristics may be used instead of time-current characteristics.

3.4.16

conventional non-tripping current

I_{nt}

specified value of current which the RCBO can carry for a specified time (conventional time) without operating

[IEV 441-17-22 :1984]

3.4.17

conventional tripping current

I_t

specified value of current which causes the RCBO to operate within a specified time (conventional time)

3.4.18

instantaneous tripping current

minimum value of current which causes the circuit-breaker to operate automatically without intentional time-delay

3.4.19

non-operating overcurrents in the main circuit

NOTE In the case of overcurrent in the main circuit, in the absence of residual current, operation of the detecting device may occur as a consequence of asymmetry existing in the detecting device itself.

3.4.19.1

limiting value of overcurrent in case of a load through an RCBO with two poles

maximum value of overcurrent of a load which, in the absence of any fault to frame or to earth, and in the absence of an earth leakage current, can flow through an RCBO with two poles without causing it to operate

3.4.19.2

limiting value of overcurrent in case of a single phase load through a three-pole or four-pole RCBO

maximum value of a single phase overcurrent which, in the absence of any fault to frame or to earth, and in the absence of an earth leakage current, can flow through a three-pole or a four-pole RCBO without causing it to operate

3.4.20

residual making and breaking capacity

value of the a.c. component of a residual prospective current which an RCBO can make, carry for its opening time and break under specified conditions of use and behaviour

3.4.21

limiting values (U_x and U_y) of the line voltage for RCBOs functionally dependent on line voltage

3.4.21.1

U_x

minimum value of the line voltage at which an RCBO functionally dependent on line voltage still operates under specified conditions in case of decreasing line voltage (see 9.17.1)

3.4.21.2

U_y

minimum value of the line voltage below which an RCBO functionally dependent on line voltage opens automatically in the absence of any residual current (see 9.17.2)

3.5 Definitions relating to values and ranges of influencing quantities

3.5.1

influencing quantity

any quantity likely to modify the specified operation of an RCBO

3.5.2

reference value of an influencing quantity

value of an influencing quantity to which the characteristics stated by the manufacturer are referred

3.5.3

reference conditions of influencing quantities

collectively, the reference values of all influencing quantities

3.5.4

range of an influencing quantity

range of values of an influencing quantity which permits the RCBO to operate under specified conditions, the other influencing quantities having their reference values

3.5.5

extreme range of an influencing quantity

range of values of an influencing quantity within which the RCBO suffers only spontaneously reversible changes, although not necessarily complying with any requirements

3.5.6

ambient air temperature

temperature, determined under prescribed conditions, of the air surrounding the RCBO

NOTE For RCBOs installed inside an enclosure, it is the temperature of the air outside the enclosure.

[IEV 441-11-13]

3.5.7

reference ambient air temperature

ambient air temperature on which the time-overcurrent characteristics are based

3.6 Definitions relating to terminals

3.6.1

terminal

conductive part of an RCBO, provided for re-usable electrical connection to external circuits

3.6.2

screw-type terminal

terminal for the connection and subsequent disconnection of one conductor or the interconnection of two or more conductors capable of being dismantled, the connections being made, directly or indirectly, by means of screws or nuts of any kind

3.6.3

pillar terminal

screw-type terminal in which the conductor is inserted into a hole or cavity, where it is clamped under the shank of the screw(s)

NOTE 1 The clamping pressure may be applied directly by the shank of the screw or by an intermediate clamping element to which pressure is applied by the shank of the screw.

NOTE 2 Examples of pillar terminals are shown in Figure IC.1 of Annex IC.

3.6.4

screw terminal

screw-type terminal in which the conductor is clamped under the head of the screw. The clamping pressure may be applied directly by the head of the screw or through an intermediate part, such as a washer, a clamping plate or an anti-spread device

NOTE Examples of screw terminals are shown in Figure IC.2a of Annex IC.

3.6.5

stud terminal

screw-type terminal in which the conductor is clamped under a nut

NOTE 1 The clamping pressure may be applied directly by a suitably shaped nut or through an intermediate part, such as a washer, a clamping plate or an anti-spread device.

NOTE 2 Examples of stud terminals are shown in Figure IC.2b.

3.6.6

saddle terminal

screw-type terminal in which the conductor is clamped under a saddle by means of two or more screws or nuts

NOTE Examples of saddle terminals are shown in Figure IC.3.

3.6.7

lug terminal

screw terminal or a stud terminal, designed for clamping a cable lug or a bar by means of a screw or nut

NOTE Examples of lug terminals are shown in Figure IC.4.

3.6.8

screwless terminal

connecting terminal for the connection and subsequent disconnection of one conductor or the dismountable interconnection of two or more conductors capable of being dismantled, the connection being made, directly or indirectly, by means of springs, wedges, eccentrics or cones, etc., without special preparation of the conductor other than removal of insulation

3.6.9

tapping screw

screw manufactured from a material having high resistance to deformation, when applied by rotary insertion to a hole in a material having less resistance to deformation than the screw

NOTE The screw is made with a tapered thread, the taper being applied to the core diameter of the thread at the end section of the screw. The thread produced by application of the screw is formed securely only after sufficient revolutions have been made to exceed the number of threads on the tapered section.

3.6.10

thread forming tapping screw

tapping screw having an uninterrupted thread

NOTE 1 It is not a function of this thread to remove material from the hole.

NOTE 2 An example of a thread forming tapping screw is shown in Figure 1.

3.6.11

thread cutting tapping screw

tapping screw having an interrupted thread

NOTE 1 It is a function of this thread to remove material from the hole.

NOTE 2 An example of a thread cutting tapping screw is shown in Figure 2.

3.6.Z1

plug-in terminal

terminal the electrical connection and disconnection of which can be effected without displacing the conductors of the corresponding circuit. The connection is effected without the use of a tool and is provided by the resilience of the fixed and/or moving parts and/or by springs 

3.7 Definitions relating to conditions of operation

3.7.1

operation

transfer of the moving contact(s) from the open position to the closed position or vice versa

NOTE If distinction is necessary, an operation in the electrical sense (i.e. make or break) is referred to as a switching operation and an operation in the mechanical sense (i.e. close or open) is referred to as a mechanical operation.

3.7.2

closing operation

operation by which the RCBO is brought from the open position to the closed position

[IEV 441-16-08:1984]

3.7.3

opening operation

operation by which the RCBO is brought from the closed position to the open position

[IEV 441-16-09:1984]

3.7.4

dependent manual operation

operation solely by means of directly applied manual energy, such that the speed and force of the operation are dependent on the action of the operator

[IEV 441-16-13]

3.7.5

independent manual operation

stored energy operation where the energy originates from manual power, stored and released in one continuous operation, such that the speed and force of the operation are independent of the action of the operator

[IEV 441-16-16]

3.7.6

trip-free RCBO

an RCBO, the moving contacts of which return to and remain in the open position when the (automatic) opening operation is initiated after the initiation of the closing operation, even if the closing command is maintained

NOTE To ensure proper breaking of the current which may have been established, it may be necessary that the contacts momentarily reach the closed position.

[IEV 441-16-31]

3.7.7

operating cycle

succession of operations from one position to another and back to the first position through all other positions, if any

[IEV 441-16-02]

3.7.8

sequence of operations

succession of specified operations with specified time intervals

3.7.9

uninterrupted duty

duty in which the main contacts of an RCBO remain closed whilst carrying a steady current without interruption for long periods (which could be weeks, months, or even years)

3.8 Definitions relating to constructional elements

3.8.1

main contact

contact included in the main circuit of an RCBO, intended to carry, in the closed position, the current of the main circuit

[IEV 441-15-07:1984]

3.8.2

arcing contact

contact on which the arc is intended to be initiated

NOTE An arcing contact may serve as a main contact. It may also be a separate contact so designed that it opens after and closes before another contact which it is intended to protect from damage.

3.8.3

control contact

contact included in a control circuit of an RCBO and mechanically operated by the RCBO

[IEV 441-15-09]

3.8.4

auxiliary contact

contact included in an auxiliary circuit and mechanically operated by the RCBO (e.g. for indicating the position of the contacts)

[IEV 441-15-10:1984, modified]

3.8.5

release

device, mechanically connected to (or integrated into) an RCBO which releases the holding means and permits the automatic opening of the RCBO

[IEV 441-15-17, modified]

NOTE In the IEC definition, reference to closing is also made.

3.8.6

overcurrent release

release which permits an RCBO to open with or without time-delay when the current in the release exceeds a predetermined value

NOTE In some cases, this value may depend upon the rate of rise of current.

[IEV 441-16-33:1984]

3.8.7

inverse time-delay overcurrent release

overcurrent release which operates after a time-delay inversely dependent upon the value of the overcurrent

NOTE Such a release may be designed so that the time-delay approaches a definite minimum for high values of overcurrent.

[IEV 441-16-35:1984]

3.8.8

direct overcurrent release

overcurrent release directly energized by the current in the main circuit of an RCBO

[IEV 441-16-36:1984]

3.8.9

overload release

overcurrent release intended for protection against overloads

[IEV 441-16-38:1984]

3.8.10

conductive part

part which is capable of conducting current, although it may not necessarily be used for carrying service current

[IEV 441-11-09:1984]

3.8.11

exposed conductive part

conductive part which can be readily touched and which normally is not live, but which may become live under fault conditions

[IEV 441-11-10:1984]

3.9 Definitions relating to tests

3.9.1

type test

test of one or more devices made to a certain design to show that the design meets certain requirements

3.9.2

routine test

test to which each individual device is subjected during or after manufacture to ascertain whether it complies with certain criteria

3.10 Definitions relating to insulation coordination

3.10.1

insulation coordination

mutual correlation of insulation characteristics of electrical equipment taking into account the expected micro-environment and other influencing stresses

[IEC 60664-1:2007, definition 3.1]

3.10.2

working voltage

highest r.m.s. value of the a.c. or d.c. voltage across any particular insulation which can occur when the equipment is supplied at rated voltage

NOTE 1 Transients are disregarded.

NOTE 2 Both open-circuit conditions and normal operating conditions are taken into account.

[IEC 60664-1:2007, definition 3.5]

3.10.3

overvoltage

any voltage having a peak value exceeding the corresponding peak value of maximum steady-state voltage at normal operating conditions

[IEC 60664-1:2007, definition 3.7]

3.10.4

impulse withstand voltage

highest peak value of impulse voltage of prescribed form and polarity, which does not cause breakdown of the insulation under specific conditions

[IEC 60664-1:2007, definition 3.8.1]

3.10.5

overvoltage category

numeral defining a transient overvoltage condition

[IEC 60664-1:2007, definition 3.10]

3.10.6

macro-environment

environment of the room or other location, in which the equipment is installed or used

[IEC 60664-1:2007, definition 3.12.1]

3.10.7

micro-environment

immediate environment of the insulation which particularly influences the dimensioning of the creepage distances

[IEC 60664-1:2007, definition 3.12.2]

3.10.8

pollution

any addition of foreign matter, solid, liquid or gaseous that can result in a reduction of electric strength or surface resistivity of the insulation

[IEC 60664-1:2007, definition 3.11]

3.10.9

pollution degree

numeral characterizing the expected pollution of the micro-environment

[IEC 60664-1:2007, definition 3.13]

NOTE The pollution degree to which equipment is exposed may be different from that of the macro-environment where the equipment is located because of protection offered by means such as an enclosure or internal heating to prevent absorption or condensation of moisture.

3.10.10

isolation (isolating function)

function intended to cut off the supply from the whole installation or a discrete section of it by separating it from every source of electrical energy for reasons of safety

[IEC 60947-1:2007, definition 2.1.19, modified]

3.10.11

isolating distance

clearance between open contacts, meeting the safety requirements specified for isolation purposes

[IEV 441-17-35:1984, modified]

3.10.12

clearance

shortest distance in air between two conductive parts along a string stretched the shortest way between these conductive parts

[IEV 441-17-31, modified]

NOTE 1 For the purpose of determining a clearance to accessible parts, the accessible surface of an insulating enclosure should be considered conductive as if it was covered by a metal foil wherever it can be touched by a hand or a standard test finger according to Figure 3.

NOTE 2 See also Annex B.

3.10.13

creepage distance

shortest distance along the surface of an insulating material between two conductive parts

[IEV 604-03-61:1987, modified]

NOTE 1 For the purpose of determining a creepage distance to accessible parts, the accessible surface of an insulating enclosure should be considered conductive as if it was covered by a metal foil wherever it can be touched by a hand or a standard test finger according to Figure 3.

NOTE 2 See also Annex B.

4 Classification

RCBOs are classified in the following **☐** *text deleted* **☐** ways:

4.1 According to the method of operation

☐ NOTE The selection of the various types is made according to HD 60364 and non-conflicting national wiring rules. Table Z1 lists the types of RCBOs according to the various applications but does not exclude the use of RCBOs of any classification for protection over and above that required by the relevant wiring rules. **☐**

☐ Table Z1 – Survey of the types of RCBOs according to their method of operation

Classification	4.1.1	4.1.2.2a)	4.1.2.1 b)	4.1.2.2b)
Marking of use	Without	E1	E2	E3
Protection	Indirect contact and additional protection ^a	Indirect contact and additional protection ^a	Additional protection ^a	Additional protection ^{a b}
Service continuity ^c	Yes	Yes	No	Yes
^a Additional protection, provided only by RCBOs with $I_{\Delta n} \leq 0,03$ A. ^b Only devices integrated in one unit with a socket-outlet or designed exclusively for being associated locally with a socket outlet in a same mounting box. ^c This information is given for guidance only.				

☐

4.1.1 RCBO functionally independent of line voltage (see 3.3.8)

4.1.2 RCBO functionally dependent on line voltage (see 3.3.9)

4.1.2.1 Opening automatically in case of failure of the line voltage, without or with delay (see 8.12):

a) **☐** *text deleted* **☐**

b) not reclosing automatically when the line voltage is restored.

4.1.2.2 Not opening automatically in case of failure of the line voltage:

a) able to trip in case of a hazardous situation (e.g. due to an earth fault), arising on failure of the line voltage **☐** (additional requirements are under consideration); **☐**

b) not able to trip in case of a hazardous situation (e.g. due to an earth fault), arising on failure of line voltage.

☐ *text deleted* **☐**

4.2 According to the type of installation

☐ *text deleted* **☐**

4.3 According to the number of poles and current paths

 text deleted 

- two-pole RCBO with one overcurrent protected pole;
- two-pole RCBO with two overcurrent protected poles;
- three-pole RCBO with three overcurrent protected poles;

 text deleted 

- four-pole RCBO with three overcurrent protected poles;
- four-pole RCBO with four overcurrent protected poles.

NOTE The pole which is not an overcurrent protected pole (see 3.3.15.1) may be:

- "unprotected" (see 3.3.15.2), or
- "switched neutral" (see 3.3.15.3).

4.4 According to the possibility of adjusting the residual operating current

 text deleted 

4.5 According to resistance to unwanted tripping due to voltage surges

- RCBOs with normal resistance to unwanted tripping (general type as in Table 2, and Table 3 if applicable);
- RCBOs with increased resistance to unwanted tripping (S type as in Table 2, and Table 3 if applicable).

4.6 According to behaviour in presence of d.c. components

- RCBOs of type AC;
- RCBOs of type A.

4.7 According to time-delay (in presence of a residual current)

- RCBO without time-delay: type for general use;
- RCBO with time-delay: type S for selectivity.

4.8 According to the protection against external influences

- enclosed-type RCBO (not requiring an appropriate enclosure);
- unenclosed-type RCBO (for use with an appropriate enclosure).

4.9 According to the method of mounting

- surface-type RCBO;
- flush-type RCBO;
- panel board type RCBO, also referred to as distribution board type.

NOTE These types may be intended to be mounted on rails.

4.10 According to the methods of connection

Text deleted

- RCBOs, the electrical connections which are not associated with the mechanical mounting;
- RCBOs, the electrical connections which are associated with the mechanical mounting.

NOTE Examples of this type are:

- plug-in type;
- bolt-on type;
- screw-in type.

Some RCBOs may be of the plug-in type or bolt on type on the line side only, the load terminals being usually suitable for wiring connection.

Text deleted

4.11 According to the instantaneous tripping current (see 3.4.18)

- B-type RCBO;
- C-type RCBO;
- D-type RCBO.

4.12 According to the I^2t characteristic

RCBOs of B-type and C-type, having rated current up to and including 63 A and having short-circuit breaking capacity of 3 000 A, 4 500 A, 6 000 A and 10 000 A, shall be classified according to the limits within which their I^2t characteristics lie, measured according to 9.12.6 (see Annex ZD).

Other ratings and D-type RCBOs cannot be classified according to this Annex ZD.

4.13 According to the type of terminals

- RCBOs with screw-type terminals for external copper conductors;
- RCBOs with screwless type terminals for external copper conductors;

NOTE 1 The requirements for RCBOs equipped with these types of terminals are given in Annex J.

- RCBOs with flat quick-connect terminals for external copper conductors;

NOTE 2 The requirements for RCBOs equipped with these types of terminals are given in Annex K.

Text deleted

4.21 According to the range of ambient air temperature

- RCBOs for use at ambient air temperatures between -5 °C and +40 °C;
- RCBOs for use at ambient air temperatures between -25 °C and +40 °C.

5 Characteristics of RCBOs

5.1 Summary of characteristics

The characteristics of an RCBO shall be stated in the following terms:

text deleted

- number of poles and current paths (see 4.3);
- rated current I_n (see 5.2.2);

- rated residual operating current $I_{\Delta n}$ (see 5.2.3);
- rated residual non-operating current $I_{\Delta no}$ (see 5.2.4);
- rated voltage U_n (see 5.2.1);
- rated frequency (see 5.2.5);
- rated short-circuit capacity I_{cn} (see 5.2.6);
- rated residual making and breaking capacity $I_{\Delta m}$ (see 5.2.7);
- time-delay, if applicable (see 5.2.8);
- operating characteristics in case of residual currents with d.c. components (see 5.2.9);
- method of mounting (see 4.9);
- method of connection (see 4.10);
- range of instantaneous tripping overcurrent (see 4.11);
- I^2t classification (see 4.12);
- degree of protection (see IEC 60529).

☐ – ranges of ambient air temperature (see 5.3.Z1) ☐

For RCBOs functionally dependent on line voltage:

- behaviour of the RCBO in case of failure of line voltage (see 4.1.2).

5.2 Rated quantities and other characteristics

5.2.1 Rated voltage

5.2.1.1 Rated operational voltage (U_e)

The rated operational voltage (hereafter referred to as "rated voltage") of an RCBO is the value of voltage, assigned by the manufacturer, to which its performance is referred.

NOTE The same RCBO may be assigned a number of rated voltages and associated rated short-circuit capacities.

5.2.1.2 Rated insulation voltage (U_i)

The rated insulation voltage of an RCBO is the value of voltage, assigned by the manufacturer, to which dielectric test voltages and creepage distances are referred.

Unless otherwise stated, the rated insulation voltage is the value of the maximum rated voltage of the RCBO. In no case shall the maximum rated voltage exceed the rated insulation voltage.

5.2.1.3 Rated impulse withstand voltage (U_{imp})

The rated impulse withstand voltage of an RCBO shall be equal to or higher than the standard values of rated impulse withstand voltage given in ☐ 5.3.10. ☐

5.2.2 Rated current (I_n)

A current assigned by the manufacturer as the current which the RCBO can carry in uninterrupted duty (see 3.7.9), at a specified reference ambient air temperature.

The standard reference ambient air temperature is 30 °C. If a different reference ambient air temperature for the RCBO is used, the effect on the overload protection of cables shall be taken into account, since this is also based on a reference ambient air temperature of 30 °C, according to installation rules (see Clause 523 of IEC 60364-5-52:2001).

5.2.3 Rated residual operating current ($I_{\Delta n}$)

The value of residual operating current (see 3.2.4), assigned to the RCBO by the manufacturer, at which the RCBO shall operate under specified conditions.

 text deleted 

5.2.4 Rated residual non-operating current ($I_{\Delta no}$)

The value of residual non-operating current (3.2.5), assigned to the RCBO by the manufacturer, at which the RCBO does not operate under specified conditions.

5.2.5 Rated frequency

The rated frequency of an RCBO is the power frequency for which the RCBO is designed and to which the values of the other characteristics correspond.

NOTE The same RCBO may be assigned a number of rated frequencies.

5.2.6 Rated short-circuit capacity (I_{cn})

The rated short-circuit capacity of an RCBO is the value of the ultimate short-circuit breaking capacity (see 3.4.6.1) assigned to that RCBO by the manufacturer.

NOTE An RCBO having a given rated short-circuit capacity I_{cn} has a corresponding service short-circuit capacity (I_{cs}) (see Table 22).

5.2.7 Rated residual making and breaking capacity ($I_{\Delta m}$)

The r.m.s. value of the a.c. component of residual prospective current (3.2.3 and 3.4.3), assigned by the manufacturer, which an RCBO can make, carry and break under specified conditions.

 The conditions are those specified in 9.12.11.4d) 

 NOTE the corresponding rated quantity of circuit-breaker is the rated making and breaking capacity of an individual pole I_{cn1} (see 5.2.5 of EN 60898-1:2002). 

5.2.8 RCBO type S

A time-delay RCBO (see 3.3.12) which complies with the relevant part of Table 2 and Table 3 if applicable.

5.2.9 Operating characteristics in case of residual currents with d.c. components

5.2.9.1 RCBO type AC

An RCBO for which tripping is ensured for residual sinusoidal alternating currents, whether suddenly applied or slowly rising.

5.2.9.2 RCBO type A

An RCBO for which tripping is ensured for residual sinusoidal alternating currents and residual pulsating direct currents, whether suddenly applied or slowly rising.

5.3 Standard and preferred values

5.3.1 Standard values of rated voltage (U_n)

 Standard  values of rated voltage are as follows:

RCBO	Rated voltage of RCBOs for use in systems 230 V, 230 V/400 V, 400V
Two-pole	230 V
	400 V
Three-pole	400 V
Four-pole	400 V

text deleted

5.3.2 Preferred values of rated current (I_n)

Preferred values of rated current are:

6 – text deleted 10 – 13 – 16 – 20 – 25 – 32 – 40 – 50 – 63 – 80 – 100 – 125 A.

5.3.3 Standard values of rated residual operating current ($I_{\Delta n}$)

Standard values of rated residual operating current are:

text deleted 0,01 – 0,03 – 0,1 – 0,3 – 0,5 A.

text deleted

5.3.4 Standard value of residual non-operating current ($I_{\Delta no}$)

The standard value of residual non-operating current is 0,5 $I_{\Delta n}$.

NOTE For residual pulsating direct currents, residual non-operating currents depend on the current delay angle α (see 3.1.4).

5.3.5 Value of rated frequency

The preferred value of rated frequency is 50 Hz

5.3.6 Values of rated short-circuit capacity (I_{cn}) and of rated residual making and breaking capacity ($I_{\Delta m}$)

5.3.6.1 Standard values up to and including 10 000 A

Standard values of rated short-circuit capacity and of rated residual making and breaking capacity are given in Table 1. The values of I_{cn} and $I_{\Delta m}$ may be different on the same product.

Table 1 – Standard values of rated short-circuit capacity

1 500 A
3 000 A
4 500 A
6 000 A
10 000 A

(*) Only for RCBOs integrated in one unit with a socket outlet or designed exclusively for being associated locally with a socket outlet in the same mounting box. **Table 1**

NOTE The values of 1 000 A, 2 000 A, 2 500 A, 7 500 A and 9 000 A are also considered as standard in some countries.

The corresponding ranges of power factor are given in 9.12.5.

5.3.6.2 Values above 10 000 A up to and including 25 000 A

For values above 10 000 A up to and including 25 000 A preferred values are 15 000 A and 20 000 A.

The corresponding range of power factor is given in 9.12.5.

5.3.7

Table 1 Void **Table 1**

5.3.8 Limiting values of break time and non-actuating time for RCBO of type AC and A

5.3.8.1 Limiting values of break time and non-actuating time for alternating residual currents (r.m.s. values) for type AC and A

Table 2 – Limiting values of break time and non-actuating time for alternating residual currents (r.m.s. values) for type AC and A RCBO

Limiting values of break time and Table 1 non-actuating time Table 1 (s) for type AC and A RCBOs in event of alternating residual currents (r.m.s. values) equal to									
Type	I_n A	$I_{\Delta n}$ A	$I_{\Delta n}$	$2 I_{\Delta n}$	$5 I_{\Delta n}$	$5 I_{\Delta n}$ or $0,25 A^a$	$5 A - 200 A, 500 A^b$	$I_{\Delta t}^c$	
General	Any	<0,03	0,3	0,15		0,04	0,04	0,04	Maximum break times
		0,03	0,3	0,15		0,04	0,04	0,04	
		>0,03	0,3	0,15	0,04		0,04	0,04	
S	≥25	>0,03	0,5	0,2	0,15		0,15	0,15	