

Determination of power losses in high-voltage direct current (HVDC) converter stations with line-commutated converters (IEC 61803:1999)

ICS 29.200

National foreword

This British Standard is the UK implementation of EN 61803:1999+A2:2016. It is identical to IEC 61803:1999, incorporating amendment 1:2010, amendment 2:2016 and corrigendum October 1999. It supersedes BS EN 61803:1999+A1:2010, which will be withdrawn on 14 October 2019.

The start and finish of text introduced or altered by amendment is indicated in the text by tags. Tags indicating changes to IEC text carry the number of the IEC amendment. For example, text altered by IEC amendment 1 is indicated by **A1** **A1**.

The UK participation in its preparation was entrusted by Technical Committee PEL/22, Power electronics.

A list of organizations represented on this committee can be obtained on request to its secretary.

This document does not purport to include all the necessary provisions of a contract. Users are responsible for its correct application.

Compliance with a British Standard cannot confer immunity from legal obligations.

This British Standard, having been prepared under the direction of the Electrotechnical Sector Committee, was published under the authority of the Standards Committee and comes into effect on 15 June 1999

© The British Standards Institution 2016.
Published by BSI
Standards Limited 2016

ISBN 978 0 580 81027 5

Amendments/corrigenda issued since publication

Amd. No	Date	Comments
13393 Corr. No. 1	17 May 2002	Change to equation in 5.1.4 .
	31 March 2011	Implementation of IEC amendment 1:2010 with CENELEC endorsement A1:2010.
	30 November 2016	Implementation of IEC amendment 2:2016 with CENELEC endorsement A2:2016.

English version

**Determination of power losses
in high-voltage direct current (HVDC)
converter stations with line-commutated converters**
(IEC 61803:1999)

Détermination des pertes en puissance dans les
postes de conversion en courant continu à haute
tension (CCHT)
(CEI 61803:1999)

Bestimmung der Leistungsverluste in
Hochspannungsgleichstrom (HGÜ)-Stromrichter-
Stationen
(IEC 61803:1999)

This European Standard was approved by CENELEC on 1999-04-01. CENELEC members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for giving this European Standard the status of a national standard without any alteration.

Up-to-date lists and bibliographical references concerning such national standards may be obtained on application to the Central Secretariat or to any CENELEC member.

This European Standard exists in three official versions (English, French, German). A version in any other language made by translation under the responsibility of a CENELEC member into its own language and notified to the Central Secretariat has the same status as the official versions.

CENELEC members are the national electrotechnical committees of Austria, Belgium, Czech Republic, Denmark, Finland, France, Germany, Greece, Iceland, Ireland, Italy, Luxembourg, Netherlands, Norway, Portugal, Spain, Sweden, Switzerland and United Kingdom.

CENELEC

European Committee for Electrotechnical Standardization
Comité Européen de Normalisation Electrotechnique
Europäisches Komitee für Elektrotechnische Normung

Central Secretariat: Avenue Marnix 17, B - 1000 Brussels

Foreword

The text of document 22F/51/FDIS, future edition 1 of IEC 61803, prepared by SC 22F, Power electronics for electrical transmission and distribution systems, of IEC TC 22, Power electronics, was submitted to the IEC-CENELEC parallel vote and was approved by CENELEC as EN 61803 on 1999-04-01.

The following dates were fixed:

- latest date by which the EN has to be implemented at national level by publication of an identical national standard or by endorsement (dow) 2000-01-01
- latest date by which the national standards conflicting with the EN have to be withdrawn (dow) 2002-04-01

Annexes designated “normative” are part of the body of the standard.

Annexes designated “informative” are given for information only.

In this standard, Annex A and Annex ZA are normative and Annex B and Annex C are informative.

Annex ZA has been added by CENELEC.

Endorsement notice

The text of the International Standard IEC 61803:1999 was approved by CENELEC as a European Standard without any modification.

Foreword to Amendment 1

The text of document 22F/214/CDV, future amendment 1 to IEC 61803:1999, prepared by SC 22F, Power electronics for electrical transmission and distribution systems, of IEC TC 22, Power electronic systems and equipment, was submitted to the IEC-CENELEC parallel vote and was approved by CENELEC as amendment A1 to EN 61803:1999 on 2010-12-01.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. CEN and CENELEC shall not be held responsible for identifying any or all such patent rights.

The following dates were fixed:

- latest date by which the amendment has to be implemented at national level by publication of an identical national standard or by endorsement (dow) 2011-09-01

- latest date by which the national standards conflicting with the amendment have to be withdrawn (dow) 2013-12-01

Annex ZA has been added by CENELEC.

Endorsement notice

The text of amendment 1:2010 to the International Standard IEC 61803:1999 was approved by CENELEC as an amendment to the European Standard without any modification.

In the official version, for Bibliography, the following note has to be added for the standard indicated:

IEC 61378-2:2001 NOTE Harmonized as EN 61378-2:2001 (not modified).

Foreword to amendment A2

The text of document 22F/374/CDV, future IEC 61803:1999/A2, prepared by SC 22F “Power electronics for electrical transmission and distribution systems”, of IEC/TC 22 “Power electronic systems and equipment” was submitted to the IEC-CENELEC parallel vote and was approved by CENELEC as EN 61803:1999/A2:2016.

The following dates are fixed:

- latest date by which the document has to be implemented at national level by publication of an identical national standard or by endorsement (dow) 2017-04-14
- latest date by which the national standards conflicting with the document have to be withdrawn (dow) 2019-10-14

Endorsement notice

The text of the International Standard IEC 61803:1999/A2:2016 was approved by CENELEC as a European Standard without any modification.

Contents

	Page		Page
Foreword	2	5.7.2 DC filter capacitor losses	18
1 Scope	5	5.7.3 DC filter reactor losses	18
2 Normative references	5	5.7.4 DC filter resistor losses	18
3 Definitions and symbols	5	5.7.5 Total d.c. filter losses	18
3.1 Definitions	5	5.8 Auxiliaries and station service losses	19
3.2 Letter symbols	6	5.9 $\sqrt{A_2}$ Series filter losses $\sqrt{A_2}$	19
4 General	7	5.10 Other equipment losses	20
4.1 Introduction	7	Annex A (normative) Calculation of harmonic currents and voltages	26
4.2 Ambient conditions	7	A.1 Harmonic currents in converter transformers	26
4.2.1 Outdoor standard reference temperature	7	A.2 Harmonic currents in the a.c. filters	26
4.2.2 Coolant standard reference temperature	7	A.3 Harmonic voltages on the d.c. side	27
4.2.3 Standard reference air pressure	7	A.4 DC side harmonic currents in the smoothing reactor	27
4.3 Operating parameters	8	Annex B (informative) Typical station losses	27
5 Determination of equipment losses	8	Annex C (informative) Bibliography	28
5.1 Thyristor valve losses	8	Annex D (informative) HVDC converter station loss evaluation – An illustration	29
5.1.1 Thyristor conduction loss per valve	9	Annex ZA (normative) Normative references to international publications with their corresponding European publications	32
5.1.2 Thyristor spreading loss per valve	9	Figure 1 — Typical high-voltage direct current (HVDC) equipment for one pole	21
5.1.3 Other conduction losses per valve	10	Figure 2 — Simplified three-phase diagram of an HVDC 12-pulse converter	22
5.1.4 DC voltage-dependent loss per valve	10	Figure 3 — Simplified equivalent circuit of a typical thyristor valve	22
5.1.5 Damping loss per valve (resistor-dependent term)	11	Figure 4 — Current and voltage waveforms of a valve operating in a 12-pulse converter	23
5.1.6 Damping loss per valve (change of capacitor energy term)	11	Figure 5 — Thyristor on-state characteristic	24
5.1.7 Turn-off losses per valve	12	Figure 6 — Conduction current and voltage drop	24
5.1.8 Reactor loss per valve	12	Figure 7 — Distribution of commutating inductance between L_1 and L_2	25
5.1.9 Total valve losses	12	Figure 8 — Thyristor current during reverse recovery	25
5.1.10 Temperature effects	13		
5.1.11 No-load operation loss per valve	13		
5.2 Converter transformer losses	13		
5.2.1 General	13		
5.2.2 No-load operation losses	13		
5.2.3 Operating losses	14		
5.2.4 Auxiliary power losses	15		
5.3 AC filter losses	15		
5.3.1 General	15		
5.3.2 AC filter capacitor losses	15		
5.3.3 AC filter reactor losses	15		
5.3.4 AC filter resistor losses	16		
5.3.5 Total a.c. filter losses	16		
5.4 Shunt capacitor bank losses	16		
5.5 Shunt reactor losses	16		
5.6 DC smoothing reactor losses	16		
5.7 DC filter losses	17		
5.7.1 General	17		

1 Scope

This International Standard applies to all line-commutated high-voltage direct current (HVDC) converter stations used for power exchange in utility systems. This standard presumes the use of 12-pulse thyristor converters but can, with due care, also be used for 6-pulse thyristor converters.

In some applications, synchronous compensators or static var compensators (SVC) may be connected to the a.c. bus of the HVDC converter station. The loss determination procedures for such equipment are not included in this standard.

This standard presents a set of standard procedures for determining the total losses of an HVDC converter station. Typical HVDC equipment is shown in Figure 1. The procedures cover all parts, except as noted above, and address no-load operation and operating losses together with their methods of calculation which use, wherever possible, measured parameters.

Converter station designs employing novel components or circuit configurations compared to the typical design assumed in this standard, or designs equipped with unusual auxiliary circuits that could affect the losses, shall be assessed on their own merits.

2 Normative references

The following normative documents contain provisions which, through reference in this text, constitute provisions of this International Standard. At the time of publication, the editions indicated were valid. All normative documents are subject to revision, and parties to agreements based on this International Standard are encouraged to investigate the possibility of applying the most recent editions of the normative documents indicated below. Members of IEC and ISO maintain registers of currently valid International Standards.

Ⓐ₁ IEC 60076-1, *Power transformers – Part 1: General*

IEC 60076-6, *Power transformers – Part 6: Reactors*

IEC 60633, *Terminology for high-voltage direct current (HVDC) transmission*

IEC 60700-1, *Thyristor valves for high voltage direct current (HVDC) power transmission – Part 1: Electrical testing*

IEC 60747-6, *Semiconductor devices – Part 6: Thyristors*

IEC 60871-1, *Shunt capacitors for a.c. power systems having a rated voltage above 1 000 V – Part 1: General* Ⓐ₁

3 Definitions and symbols

For the purpose of this International Standard, the following definitions apply.

3.1 Definitions

3.1.1

auxiliary losses

Ⓐ₂ electric power required to feed the converter station auxiliary loads

NOTE 1 to entry: The auxiliary losses depend on the number of converter units used and whether the station is in no-load operation or carrying load, in which case the auxiliary losses depend on the load level. Ⓐ₂

3.1.2

Ⓐ₂ **equipment no-load operation losses**

losses produced in an item of equipment with the converter station energised but with the converters blocked and all station service loads and auxiliary equipment connected as required for immediate pick-up of load to specified minimum power Ⓐ₂

3.1.3

load level

this term specifies the direct current, direct voltage, firing angle, a.c. voltage, and converter transformer tap-changer position at which the converter station is operating

3.1.4

Ⓐ₂ **equipment operating losses** Ⓐ₂

the losses produced in an item of equipment at a given load level with the converter station energized and the converters operating

3.1.5 rated load

A2 load related to operation at nominal values of d.c. current, d.c. voltage, a.c. voltage and converter firing angle

Note 1 to entry: The a.c. system shall be assumed to be at nominal frequency and its 3-phase voltages are nominal and balanced. The position of the tap-changer of the converter transformer and the number of a.c. filters and shunt reactive elements connected shall be consistent with operation at rated load, coincident with nominal conditions. **A2**

A2 **3.1.6**
total station operating losses
sum of all equipment operating losses (3.1.4) and corresponding auxiliary losses (3.1.1) at a particular load level

Note 1 to entry: It is recognised that some purchasers evaluate “total station no-load operation losses” (definition 3.1.8) and total station load losses individually instead of the evaluating “total station operating losses” (definition 3.1.6).

Note 2 to entry: “Operating losses” minus “no-load operation losses” may be considered as being quantitatively equivalent to “load losses” as in conventional a.c. substation practice.

Note 3 to entry: An illustrative example to derive “load losses”, “equivalent load losses” and corresponding “loss valuation” is given in Annex D. **A2**

A1 **3.1.7**
station essential auxiliary load
load whose failure will affect the conversion capability of the HVDC converter station (e.g. valve cooling), as well as load that must remain working in case of complete loss of a.c. power supply (e.g. battery chargers, operating mechanisms) **A1**

A2 Text deleted **A2**

A2 **3.1.8**
total station no-load operation losses
sum of all equipment no-load operation losses (3.1.2) and corresponding auxiliary losses (3.1.1) **A2**

3.2 Letter symbols

- A1** α **A2** (trigger/firing) delay angle, in radians (rad) **A2**
- μ overlap angle, in radians (rad) **A1**
- f a.c. system frequency, in hertz (Hz)
- A1** I_d direct current, in amperes (A) **A1**
- I_n harmonic r.m.s. current of order n , in amperes (A)
- L_1 the inductance, in henrys (H), referred to the valve winding, between the commutating voltage source and the point of common coupling between star- and delta-connected windings. L_1 shall include any external inductance between the transformer line-winding terminals and the point of connection of the a.c. harmonic filters
- L_2 the inductance, in henrys (H), referred to the valve winding, between the point of common coupling between star- and delta-connected windings, and the valve. L_2 shall include the saturated inductance of the valve reactors
- m electromagnetic notch coupling factor, $m = L_1/(L_1 + L_2)$
- n harmonic order
- N_t the number of series-connected thyristors per valve
- P power loss in an item of equipment, in watts (W)
- Q_n quality factor at harmonic order n
- A1** R resistance value, in ohms (Ω) **A1**
- U_d direct voltage, in volts (V)
- U_n harmonic r.m.s. voltage of order n , in volts (V)
- A1** U_{v0} r.m.s. value of the phase-to-phase no-load voltage on the valve side of the converter transformer excluding harmonics, in volts (V) **A1**
- X_n inductive reactance at harmonic order n , in ohms (Ω)

4 General

4.1 Introduction

Suppliers need to know in detail how and where losses are generated, since this affects component and equipment ratings. Purchasers are interested in a verifiable loss figure which allows equitable bid comparison and in a procedure after delivery which can objectively verify the guaranteed performance requirements of the supplier.

As a general principle, it would be desirable to determine the efficiency of an HVDC converter station by a direct measurement of its energy losses. However, attempts to determine the station losses by subtracting the measured output power from the measured input power should recognize that such measurements have an inherent inaccuracy, especially if performed at high voltage. The losses of an HVDC converter station at full load are generally less than 1 % of the transmitted power. Therefore, the loss measured as a small difference between two large quantities is not likely to be a sufficiently accurate indication of the actual losses.

In some special circumstances it may be possible, for example, to arrange a temporary test connection in which two converters are operated from the same a.c. source and also connected together via their d.c. terminals. In this connection, the power drawn from the a.c. source equals the losses in the circuit. However, the a.c. source must also provide var support and commutating voltage to the two converters. Once again, there are practical measurement difficulties.

In order to avoid the problems described above, this standard standardizes a method of calculating the HVDC converter station losses by summing the losses calculated for each item of equipment. The standardized calculation method will help the purchaser to meaningfully compare the competing bids. It will also allow an easy generation of performance curves for the wide range of operating conditions in which the performance has to be known. In the absence of an inexpensive experimental method which could be employed for an objective verification of losses during type tests, the calculation method is the next best alternative as it uses, wherever possible, experimental data obtained from measurements on individual equipment and components under conditions equivalent to those encountered in real operation.

It is important to note that the power loss in each item of equipment will depend on the ambient conditions under which it operates, as well as on the operating conditions or duty cycles to which it is subjected. Therefore, the ambient and operating conditions shall be defined for each item of equipment, based on the ambient and operating conditions of the entire HVDC converter station.

4.2 Ambient conditions

A set of standard reference ambient conditions shall be used for determining the power losses in HVDC converter stations.

4.2.1 Outdoor standard reference temperature

- A1** An outdoor ambient dry bulb temperature of 20 °C shall be used as the standard reference temperature for determining the total converter station losses. Corresponding valve hall temperature may be defined by the supplier if necessary. The equivalent wet-bulb temperature (where necessary) shall be defined by the purchaser. **A1**

- A1** NOTE If not defined, the wet-bulb temperature is recommended to be 14 °C which corresponds to approximately 50 % RH at 20 °C dry bulb temperature. **A1**

4.2.2 Coolant standard reference temperature

Where forced cooling is used for equipment, the flow rate and temperature of the coolant can influence the temperature rise and associated losses of that equipment. Therefore, the coolant temperatures and flow rates established by the purchaser and the supplier shall be used as a basis for determining the losses.

4.2.3 Standard reference air pressure

The reference air pressure to be used for the evaluation of total converter station power losses shall be the standard atmospheric pressure (101,3 kPa) corrected to the altitude of the installation in question.

4.3 Operating parameters

The losses of an HVDC converter station depend on its operating parameters.

- A2)** The losses of HVDC converter stations are classified into two categories, referred to as operating losses (3.1.4 and 3.1.6) and no-load operation losses (3.1.2 and 3.1.8). **A2)**

The operating losses and auxiliary losses are affected by the load level of the station because the numbers of certain types of energized equipment (for example harmonic filters and cooling equipment) may depend upon the load level and because losses in individual items of equipment themselves vary with the load level.

- A1)** HVDC converter station losses shall be determined for nominal (balanced) a.c. system voltage and frequency, symmetrical impedances of the converter transformer and symmetrical firing angles. The transformer tap-changer shall be assumed to be in the position corresponding to nominal a.c. system voltage or as decided by the control system for the defined operating condition. **A1)**

The operating losses shall be determined for the load levels specified by the purchaser, or at rated load if no such conditions are specified. For each load level, the valve-winding a.c. voltage, d.c. current, converter firing angle, shunt compensation and harmonic filtering equipment shall be consistent with the respective load level and other specified performance requirements, relating, for example, to harmonic distortion and reactive power. Cooling and other auxiliary equipment, as appropriate to the standard reference temperature (see 4.2.1 and 4.2.2), shall be assumed to be connected to support the respective load level.

For the no-load operation mode, converter transformers shall be energized and the converters blocked. All filters and reactive power compensation equipment shall be assumed to be disconnected except for those which are required to sustain operation at zero load in order, for example, to meet the specified reactive power requirements. Station service loads and auxiliary equipment (e.g. cooling-water pumps) shall be assumed to be connected as required for immediate pick-up of load for the converter station **A2)** (without waiting for tap changer movement) to specified minimum power. **A2)**

5 Determination of equipment losses

5.1 Thyristor valve losses

The loss production mechanisms applicable when the valves are blocked (no-load operation losses) are different from those applicable in normal operation (operating losses). Operating losses are dealt with in subclauses 5.1.1, 5.1.2, 5.1.3, 5.1.4, 5.1.5, 5.1.6, 5.1.7, 5.1.8, 5.1.9 and 5.1.10, and no-load operation losses are dealt with in 5.1.11. Auxiliary losses are dealt with in 5.8.

A simplified three-phase diagram of an HVDC 12-pulse converter is shown in Figure 2. Individual valves are marked in the order of their conduction sequence.

- A1)** A simplified equivalent circuit of a typical valve is shown in Figure 3. Symbol th combines together the effects of N_t thyristors connected in series in the valve. C_{AC} and R_{AC} are the corresponding combined values of R-C damping circuits used for voltage sharing and overvoltage suppression. R_{DC} represents d.c. grading resistors and other resistive components which incur loss when the valve blocks voltage. It also includes the effects of the thyristor leakage current (see 5.1.4 and 5.1.11). C_s includes both stray capacitances and surge distribution capacitors (if used). L_s represents saturable reactors used to limit the di/dt stresses to safe values and to improve the distribution of fast rising voltages. R_s represents the resistances of the current conducting components of the valve such as the busbars, contact resistances, resistance of the windings of the saturable reactors etc. Power losses in the valve surge arrester (not shown) shall be neglected. **A1)**

Figure 4 shows, as an example, current and voltage waveforms of valve 1 (according to Figure 2) operating in rectifier and inverter modes. In the example shown, the firing instants of the valves of the upper bridge are delayed by 30° with respect to the valves of the lower bridge due to the phase shift between the two secondaries. For each valve, the length of the conduction intervals is 130° ($2\pi/3 + \mu$). During commutations the valve current is assumed, for this standard, to be changing linearly whereas in reality the valve currents follow portions of sine waves. This simplification has negligible effect on the resulting losses, while the trapezoidal waveform significantly simplifies the calculations. The voltage blocked by the valve shows notches caused by commutations between individual valves

5.1.1 Thyristor conduction loss per valve

This loss component is the product of the conduction current $i(t)$ and the corresponding ideal on-state voltage as shown in Figure 5 and Figure 6. Formula P_{V1a} shall be used provided that the d.c. bridge current is well smoothed. In the event that the root sum square value of the d.c. side harmonic currents, determined in accordance with clause A.4 (Annex A), exceeds 5 % of the d.c. component, formula P_{V1b} shall be used instead.

$$P_{V1a} = \frac{N_t \times I_d}{3} \left[U_0 + R_0 \times I_d \times \left(\frac{2\pi - \mu}{2\pi} \right) \right]$$

$$P_{V1b} = \frac{N_t \times I_d \times U_0}{3} + \frac{N_t \times R_0}{3} \left(I_d^2 + \sum_{n=12}^{n=48} I_n^2 \right) \left(\frac{2\pi - \mu}{2\pi} \right)$$

where

U_0 is the current-independent component of the on-state voltage of the average thyristor (see note below), in volts;

R_0 is the slope resistance of the on-state characteristic of the average thyristor (see note below), in ohms;

I_n is the calculated r.m.s. value of the n th harmonic current in the bridge d.c. connection according to clause A.4, in amperes.

NOTE U_0 and R_0 (see Figure 5) are determined from the fully spread on-state voltage measured at the appropriate current and junction temperature. The average value of U_0 and R_0 is obtained from production records of the thyristors manufactured for the specific project at 100 % and 50 % of nominal d.c. current. The temperature dependence of U_0 and R_0 is established from type tests or routine tests on a statistically significant number of the thyristors employed, and is used, where necessary, to correct U_0 and R_0 to the appropriate service junction temperature. If parallel connection of p thyristors is employed, the appropriate 100 % current is the nominal d.c. bridge current divided by p . The calculated result is then multiplied by p .

5.1.2 Thyristor spreading loss per valve

This loss component is an additional conduction loss of the thyristors arising from the delay in establishing full conduction of the silicon after the thyristor has been turned on. The additional loss is the product of the current and the voltage by which the thyristor voltage exceeds the ideal thyristor on-state voltage drop (see the hatched area in Figure 6).

$$P_{V2} = N_t \times f \times \int_0^{t_1} [u_B(t) - u_A(t)] \times i(t) dt$$

where

t_1 is the length of the conduction interval, in seconds, which is given by:

$$t_1 = \frac{\frac{2}{3}\pi + \mu}{2\pi f};$$

$u_B(t)$ is the instantaneous on-state voltage, in volts, of a thyristor whose fully spread on-state voltage is typical for the thyristors used. The instantaneous on-state voltage shall be determined for the appropriate junction temperature measured with a trapezoidal current pulse exhibiting the correct amplitude and commutation overlap periods (see Figure 5 and Figure 6);

$u_A(t)$ is the calculated instantaneous on-state voltage of the average thyristor at the same junction temperature for the same current pulse but with the conducting area fully established throughout the conduction, as derived from its on-state characteristic represented by U_0 and R_0 only (see Figure 6);

$i(t)$ is the instantaneous current in the thyristor, in amperes.

NOTE Instantaneous on-state voltage data, including the effects of spreading, are usually not available from production records. Measurements of typical thyristor on-state voltage, including spreading, should therefore be obtained during the valve periodic firing and extinction type test (see IEC 60700-1) or, alternatively, from a separate laboratory test on a statistically significant number of thyristors.