



BSI Standards Publication

High-voltage switchgear and controlgear

Part 107: Alternating current fused circuit-switchers for rated voltages above 1 kV up to and including 52 kV (IEC 62271-107:2019)

National foreword

This British Standard is the UK implementation of EN IEC 62271-107:2019. It is identical to IEC 62271-107:2019. It supersedes BS EN 62271-107:2012, which is withdrawn.

The UK participation in its preparation was entrusted to Technical Committee PEL/17, High voltage switchgear, controlgear and assemblies.

A list of organizations represented on this committee can be obtained on request to its secretary.

This publication does not purport to include all the necessary provisions of a contract. Users are responsible for its correct application.

© The British Standards Institution 2019
Published by BSI Standards Limited 2019

ISBN 978 0 580 51798 3

ICS 29.130.10

Compliance with a British Standard cannot confer immunity from legal obligations.

This British Standard was published under the authority of the Standards Policy and Strategy Committee on 31 July 2019.

Amendments/corrigenda issued since publication

Date	Text affected
------	---------------

English Version

High-voltage switchgear and controlgear - Part 107: Alternating
current fused circuit-switchers for rated voltages above 1 kV up
to and including 52 kV
(IEC 62271-107:2019)

Appareillage à haute tension - Partie 107: Circuits-switchers
à fusibles pour courant alternatif de tension assignée
supérieure à 1 kV et jusqu'à 52 kV inclus
(IEC 62271-107:2019)

Hochspannungs-Schaltgeräte und -Schaltanlagen - Teil
107: Wechselstrom-Leistungsschalter-Sicherungs-
Kombinationen für Bemessungsspannungen über 1 kV bis
einschließlich 52 kV
(IEC 62271-107:2019)

This European Standard was approved by CENELEC on 2019-07-02. CENELEC members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for giving this European Standard the status of a national standard without any alteration.

Up-to-date lists and bibliographical references concerning such national standards may be obtained on application to the CEN-CENELEC Management Centre or to any CENELEC member.

This European Standard exists in three official versions (English, French, German). A version in any other language made by translation under the responsibility of a CENELEC member into its own language and notified to the CEN-CENELEC Management Centre has the same status as the official versions.

CENELEC members are the national electrotechnical committees of Austria, Belgium, Bulgaria, Croatia, Cyprus, the Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, the Netherlands, Norway, Poland, Portugal, Republic of North Macedonia, Romania, Serbia, Slovakia, Slovenia, Spain, Sweden, Switzerland, Turkey and the United Kingdom.



European Committee for Electrotechnical Standardization
Comité Européen de Normalisation Electrotechnique
Europäisches Komitee für Elektrotechnische Normung

CEN-CENELEC Management Centre: Rue de la Science 23, B-1040 Brussels

European foreword

The text of document 17A/1216/FDIS, future edition 3 of IEC 62271-107, prepared by SC 17A "Switching devices" of IEC/TC 17 "High-voltage switchgear and controlgear" was submitted to the IEC-CENELEC parallel vote and approved by CENELEC as EN IEC 62271-107:2019.

The following dates are fixed:

- latest date by which the document has to be implemented at national level by publication of an identical national standard or by endorsement (dop) 2020-04-02
- latest date by which the national standards conflicting with the document have to be withdrawn (dow) 2022-07-02

This document supersedes EN 62271-107:2012 and all of its amendments and corrigenda (if any).

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. CENELEC shall not be held responsible for identifying any or all such patent rights.

Endorsement notice

The text of the International Standard IEC 62271-107:2019 was approved by CENELEC as a European Standard without any modification.

In the official version, for Bibliography, the following notes have to be added for the standards indicated:

IEC 62271-102	NOTE	Harmonized as EN IEC 62271-102
IEC 62271-200	NOTE	Harmonized as EN 62271-200
IEC 62271-201	NOTE	Harmonized as EN 62271-201

Annex ZA

(normative)

Normative references to international publications with their corresponding European publications

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

NOTE 1 Where an International Publication has been modified by common modifications, indicated by (mod), the relevant EN/HD applies.

NOTE 2 Up-to-date information on the latest versions of the European Standards listed in this annex is available here: www.cenelec.eu.

<u>Publication</u>	<u>Year</u>	<u>Title</u>	<u>EN/HD</u>	<u>Year</u>
IEC 60282-1	2009	High-voltage fuses - Part 1: Current-limiting fuses	EN 60282-1	2009
+ A1	2014		+ A1	2014
IEC 62271-1	2017	High-voltage switchgear and controlgear - Part 1: Common specifications for alternating current switchgear and controlgear	EN 62271-1	2017
IEC 62271-100	2008	High-voltage switchgear and controlgear - Part 100: Alternating current circuit-breakers	EN 62271-100	2009
+ A1	2012		+ A1	2012
+ A2	2017		+ A2	2017
IEC 62271-103	2011	High-voltage switchgear and controlgear - Part 103: Switches for rated voltages above 1 kV up to and including 52 kV	EN 62271-103	2011
IEC 62271-105	2012	High-voltage switchgear and controlgear - Part 105: Alternating current switch-fuse combinations for rated voltages above 1 kV up to and including 52 kV	EN 62271-105	2012

This page deliberately left blank

CONTENTS

FOREWORD.....	6
INTRODUCTION.....	8
1 Scope.....	9
2 Normative references	9
3 Terms and definitions	10
3.1 General terms and definitions	10
3.2 Assemblies of switchgear and controlgear	10
3.3 Parts of assemblies	10
3.4 Switching devices	10
3.5 Parts of switchgear and controlgear	10
3.6 Operational characteristics of switchgear and controlgear.....	11
3.7 Characteristic quantities	11
3.101 Fuses	14
4 Normal and special service conditions	14
5 Ratings.....	15
5.1 General.....	15
5.2 Rated voltage (U_r)	15
5.3 Rated insulation level (U_d , U_p , U_s)	15
5.4 Rated frequency (f_r).....	15
5.5 Rated continuous current (I_r)	15
5.6 Rated short-time withstand current (I_k)	15
5.7 Rated peak withstand current (I_p)	15
5.8 Rated duration of short-circuit (t_k).....	16
5.9 Rated supply voltage of auxiliary and control circuits (U_a)	16
5.10 Rated supply frequency of auxiliary and control circuits	16
5.11 Rated pressure of compressed gas supply for controlled pressure systems	16
5.101 Rated short-circuit breaking current (I_{sc})	16
5.102 Rated short-circuit making current (I_{ma})	16
5.103 Rated take-over current (I_{to}).....	17
6 Design and construction	18
6.1 Requirements for liquids in fused circuit-switchers	18
6.2 Requirements for gases in fused circuit-switchers	18
6.3 Earthing of fused circuit-switchers	18
6.4 Auxiliary and control equipment and circuits	18
6.5 Dependent power operation	18
6.6 Stored energy operation.....	18
6.7 Independent unlatched operation (independent manual or power operation)	18
6.8 Manually operated actuators	18
6.9 Operation of releases.....	18
6.10 Pressure/level indication	18
6.11 Nameplates	18
6.12 Locking devices	20
6.13 Position indication.....	20

6.14	Degrees of protection provided by enclosures	20
6.15	Creepage distances for outdoor insulators	20
6.16	Gas and vacuum tightness	20
6.17	Tightness for liquid systems	20
6.18	Fire hazard (flammability)	20
6.19	Electromagnetic compatibility (EMC)	20
6.20	X-ray emission	20
6.21	Corrosion	21
6.22	Filling levels for insulation, switching and/or operation	21
6.101	Basic requirements for fuses	21
6.102	Linkages between the fuse striker(s) and the circuit-switcher release	21
6.103	Low over-current conditions (long fuse-pre-arcing time conditions)	21
6.104	Rated continuous current values	21
7	Type tests	22
7.1	General	22
7.2	Dielectric tests	22
7.3	Radio interference voltage (RIV) test	22
7.4	Resistance measurement	22
7.5	Continuous current tests	22
7.6	Short-time withstand current and peak withstand current tests	22
7.7	Verification of the protection	22
7.8	Tightness tests	23
7.9	Electromagnetic compatibility tests (EMC)	23
7.10	Additional tests on auxiliary and control circuits	23
7.11	X-radiation test for vacuum interrupters	23
7.101	Making and breaking tests	23
7.101.1	General	23
7.101.2	Conditions for performing the tests	23
7.101.3	Test duty procedures	29
7.101.4	Behaviour of the fused circuit-switcher during tests	35
7.101.5	Condition of the apparatus after tests	35
7.102	Mechanical operation tests	36
7.102.1	General	36
7.102.2	Test procedure	36
7.102.3	Condition of fused circuit-switcher during and after mechanical operation tests	37
7.102.4	Condition of the fuses during and after mechanical operation tests	37
7.103	Extension of validity of type tests	37
7.103.1	General	37
7.103.2	Dielectric properties	38
7.103.3	Continuous current tests	38
7.103.4	Making and breaking	38
8	Routine tests	38
8.1	General	38
8.2	Dielectric test on the main circuit	38
8.3	Tests on auxiliary and control circuits	38
8.4	Measurement of the resistance of the main circuit	39
8.5	Tightness test	39
8.6	Design and visual checks	

8.101	Mechanical operating tests	39
9	Guide to the selection of fused circuit-switchers (informative)	40
9.1	General	40
9.2	Selection of rated values	40
9.3	Cable interface consideration	40
9.4	Continuous or temporary overload due to changed service conditions	40
9.5	Environmental aspects	40
9.101	Additional criteria	40
9.102	Rated short-circuit breaking current	41
9.103	Rated continuous current	41
9.104	Currents between rated continuous current and I_3 of the fuses	41
9.105	Transfer current	41
9.106	Take-over current	41
9.107	Extension of the validity of type tests	42
9.108	Operation	42
9.109	Comparison of performances of fused circuit-switchers with performances of switch-fuse combinations and circuit-breakers	43
10	Information to be given with enquiries, tenders and orders (informative)	43
10.1	General	43
10.2	Information with enquiries and orders	43
10.3	Information with tenders	43
11	Transport, storage, installation, operating instructions and maintenance	44
12	Safety	44
13	Influence of the product on the environment	44
Annex A (informative)	Applicability of the rated take-over current test duty	45
A.1	Problem formulation	45
A.2	Background	45
A.3	Terms, definitions and symbols	46
A.4	Assumptions about the fuse melting process	47
A.4.1	General	47
A.4.2	First phase	47
A.4.3	Second phase	47
A.4.4	Modelling of the "application margin"	48
A.5	Mathematical expression of the application requirements	48
A.5.1	General	48
A.5.2	First pole-to-clear	48
A.5.3	Second pole-to-clear	48
A.6	Analysis	50
A.6.1	Applications with fuse strikers	50
A.6.2	Applications with protection relays	51
A.7	Conclusions	52
Annex B (informative)	Particular conditions existing in certain countries	53
Bibliography		54
Figure 1	– Characteristics for determining the take-over current	17
Figure 2	– Arrangement of test circuits for test duties TD_{Ir} , TD_{ISC} , TD_{Ito} and TD_{Ilow}	26

Figure 3 – Representation of a specified TRV by a two-parameter reference line and a delay line	28
Figure 4 – Example of a two parameters envelope for a TRV	29
Figure 5 – Measurement of the power frequency recovery voltage with striker operation.....	31
Figure A.1 – Visualization of the application margin for a given fuse	47
Table 1 – Nameplate information	19
Table 2 – Summary of test parameters for test duties	34
Table 3 – Comparison between switch-fuse combination and fused circuit-switcher	43
Table 4 – Comparison between fused circuit-switcher and circuit breaker	43
Table A.1 – Minimum application margin A_m according to fuse characteristic.....	51
Table A.2 – Minimum protection time delay.....	51
Table A.3 – Examples of possible need for time delay	52
Table B.1 – Voltages used in the Czech Republic	53
Table B.2 – Rated insulation levels for voltage ratings of Table B.1	53

INTERNATIONAL ELECTROTECHNICAL COMMISSION

HIGH-VOLTAGE SWITCHGEAR AND CONTROLGEAR –

**Part 107: Alternating current fused circuit-switchers for
rated voltages above 1 kV up to and including 52 kV**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 62271-107 has been prepared by subcommittee 17A: Switching devices, of IEC technical committee 17: High-voltage switchgear and controlgear

This third edition cancels and replaces the second edition published in 2012. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) technical changes introduced by the second edition of IEC 62271-1 are applied, where relevant;
- b) rated TRV is removed and TRV is now treated as a test parameter, as in IEC 62271-100;
- c) the term "thermal current" is no longer used; the rated continuous current is linked to the installed fuse-links, and values shall be provided by the manufacturer together with the list of the acceptable fuse-links; for tests purpose, the highest rated continuous current listed

is referred, where previously the wording was "rated maximum thermal current", for consistency with IEC 62271-105;

- d) making and breaking test duties are independent type tests (as some may be omitted if the switching device has been validated as a load-break switch). However, TD_{It0} and TD_{low} are kept as a sequence as they are linked to the same rated value (I_{t0});
- e) differentiation has been introduced between requirements expressed for fulfilling the function expected from a fused circuit-switcher, from requirements only relevant when the function is performed by a stand-alone device. The goal is to avoid duplication or conflicts of requirements with a standard dealing with assemblies, when the function is implemented within such an assembly.

The text of this International Standard is based on the following documents:

FDIS	Report on voting
17A/1216/FDIS	17A/1227/RVD

Full information on the voting for the approval of this International Standard can be found in the report on voting indicated in the above table.

This document has been drafted in accordance with the ISO/IEC Directives, Part 2.

This International Standard is to be read in conjunction with IEC 62271-1:2017, to which it refers and which is applicable unless otherwise specified. In order to simplify the indication of corresponding requirements, the same numbering of clauses and subclauses is used as in IEC 62271-1. Amendments to these clauses and subclauses are given under the same numbering, whilst additional subclauses, are numbered from 101.

Particular conditions existing in certain countries are listed in Annex B.

A list of all parts in the IEC 62271 series, published under the general title *High-voltage switchgear and controlgear*, can be found on the IEC website.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under "<http://webstore.iec.ch>" in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

INTRODUCTION

Earthing switches forming an integral part of a circuit-switcher are covered by IEC 62271-102 [1]¹.

Installation in enclosure, if any, is covered either by IEC 62271-200 [2] or by IEC 62271-201 [3].

¹ Numbers in square brackets refer to the Bibliography.

HIGH-VOLTAGE SWITCHGEAR AND CONTROLGEAR –

Part 107: Alternating current fused circuit-switchers for rated voltages above 1 kV up to and including 52 kV

1 Scope

This part of IEC 62271 applies to three-pole-operated fused circuit-switchers designed with rated voltages above 1 kV up to and including 52 kV for use on three-phase alternating current systems of either 50 Hz or 60 Hz.

They can be designed either as stand-alone devices, or be embedded in a switchgear and controlgear assembly.

They are intended to be used for circuits or applications requiring only a normal mechanical and electrical endurance capability. Such applications cover protection of HV/LV transformers for instance, but exclude distribution lines or cables, as well as motor circuits and capacitor bank circuits.

Short-circuit conditions with low currents, up to the fused circuit-switcher rated take-over current, are dealt with by supplementary devices (strickers, relays, etc.), properly arranged, tripping the circuit-switcher. Current-limiting fuses are incorporated in order to ensure that the short-circuit breaking capacity of the device is above that of the circuit-switcher alone.

NOTE 1 In this document, the term "fuse" is used to designate either the fuse or the fuse-link where the general meaning of the text does not result in ambiguity.

NOTE 2 Other circuit-switchers exist; see reference [4].

Devices that require a dependent manual operation are not covered by this document.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60282-1:2009, *High-voltage fuses – Part 1: Current-limiting fuses*
IEC 60282-1:2009/AMD1:2014

IEC 62271-1:2017, *High-voltage switchgear and controlgear – Part 1: Common specifications*

IEC 62271-100:2008, *High-voltage switchgear and controlgear – Part 100: Alternating-current circuit-breakers*
IEC 62271-100:2008/AMD1:2012
IEC 62271-100:2008/AMD2:2017

IEC 62271-103:2011, *High-voltage switchgear and controlgear – Part 103: Switches for rated voltages above 1 kV up to and including 52 kV*

IEC 62271-105:2012, *High-voltage switchgear and controlgear – Part 105: Alternating current switch-fuse combinations for rated voltages above 1 kV up to and including 52 kV*

3 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

ISO and IEC maintain terminological databases for use in standardization at the following addresses:

- IEC Electropedia: available at <http://www.electropedia.org/>
- ISO Online browsing platform: available at <http://www.iso.org/obp>

NOTE IEC Electropedia lists the terms defined in the IEC 60050 [5].

3.1 General terms and definitions

Subclause 3.1 of IEC 62271-1:2017 applies.

3.2 Assemblies of switchgear and controlgear

Subclause 3.2 of IEC 62271-1:2017 applies.

3.3 Parts of assemblies

Subclause 3.3 of IEC 62271-1:2017 applies.

3.4 Switching devices

Subclause 3.4 of IEC 62271-1:2017 applies, with the following additions.

3.4.101

circuit-switcher

mechanical switching device suitable for making, carrying and interrupting currents under normal circuit conditions and for interrupting specified fault currents that are usually smaller than its short-time withstand current

Note 1 to entry: Other circuit-switchers exist; see reference [4].

3.4.102

fused circuit-switcher

combination, in a single device or function, of a circuit-switcher and fuses, one fuse being placed in series with each pole of the circuit-switcher intended to be connected to a phase conductor

Note 1 to entry: the term "one fuse" does not preclude the use of several fuse-links in parallel.

3.4.103

fused circuit-switcher base

fused circuit-switcher without fuse-links mounted

3.5 Parts of switchgear and controlgear

Subclause 3.5 of IEC 62271-1:2017 applies, with the following additions.

3.5.101

release

<of a mechanical switching device> device, mechanically connected to a mechanical switching device, which releases the holding means and permits the opening or the closing of the switching device

[SOURCE: IEC 60050-441:2000, 441-15-17]

3.5.102**shunt release**

release energized by a source of voltage

Note 1 to entry: The source of voltage may be independent of the voltage of the main circuit.

[SOURCE: IEC 60050-441:2000, 441-16-41]

3.6 Operational characteristics of switchgear and controlgear

Subclause 3.6 of IEC 62271-1:2017 applies, with the following additions.

3.6.101**independent manual operation**

<of a mechanical switching device> stored energy operation where the energy originates from manual power, stored and released in one continuous operation, such that the speed and force of the operation are independent of the action of the operator

[SOURCE: IEC 60050-441:2000, 441-16-16]

3.6.102**stored energy operation**

<of a mechanical switching device> operation by means of energy stored in the mechanism itself prior to the completion of the operation and sufficient to complete it under predetermined conditions

Note 1 to entry: This kind of operation may be subdivided according to:

- 1) The manner of storing the energy (spring, weight, etc.);
- 2) The origin of the energy (manual, electric, etc.);
- 3) The manner of releasing the energy (manual, electric, etc.).

[SOURCE: IEC 60050-441: 2000, 441-16-15]

3.7 Characteristic quantities

Subclause 3.7 of IEC 62271-1:2017 applies, with the following additions.

3.7.101**prospective current**

<of a circuit and with respect to a switching device or a fuse> current that would flow in the circuit if each pole of the switching device or the fuse were replaced by a conductor of negligible impedance

Note 1 to entry: The method to be used to evaluate and to express the prospective current is to be specified in the relevant publications.

[SOURCE: IEC 60050-441:2000, 441-17-01]

3.7.102**prospective peak current**

peak value of a prospective current during the transient period following initiation

Note 1 to entry: The definition assumes that the current is made by an ideal switching device, i.e. with instantaneous transition from infinite to zero impedance. For circuits where the current can follow several different paths, e.g. polyphase circuits, it further assumes that the current is made simultaneously in all poles, even if only the current in one pole is considered.

[SOURCE: IEC 60050-441:2000, 441-17-02]

3.7.103

maximum prospective peak current

<of an AC circuit> prospective peak current when initiation of the current takes place at the instant which leads to the highest possible value

Note 1 to entry: For a multiple device in a polyphase circuit, the maximum prospective peak current refers to a single pole only.

[SOURCE: IEC 60050-441:2000, 441-17-04]

3.7.104

prospective breaking current

<for a pole of a switching device or a fuse> prospective current evaluated at a time corresponding to the instant of the initiation of the breaking process

Note 1 to entry: Specifications concerning the instant of the initiation of the breaking process are to be found in the relevant publications. For mechanical switching devices or fuses, it is usually defined as the moment of initiation of the arc during the breaking process.

[SOURCE: IEC 60050-441:2000, 441-17-06]

3.7.105

breaking current

<of a switching device or a fuse> current in a pole of a switching device or in a fuse at the instant of initiation of the arc during a breaking process

[SOURCE: IEC 60050-441:2000, 441-17-07]

3.7.106

minimum breaking current

minimum value of prospective current that a fuse-link is capable of breaking at a stated voltage under prescribed conditions of use and behaviour

[SOURCE: IEC 60050-441:2000, 441-18-29]

3.7.107

short-circuit making capacity

making capacity for which the prescribed conditions include a short circuit at the terminals of the switching device

[SOURCE: IEC 60050-441:2000, 441-17-10]

3.7.108

take-over current

current co-ordinate of the intersection between the time-current characteristics of two over-current protective devices

[SOURCE: IEC 60050-441:2000, 441-17-16]

3.7.109

fused short-circuit current

conditional short-circuit current when the current-limiting device is a fuse

[SOURCE: IEC 60050-441:2000, 441-17-21]

3.7.110**applied voltage**

<for a switching device> voltage which exists across the terminals of a pole of a switching device just before the making of the current

[SOURCE: IEC 60050-441:2000, 441-17-24]

3.7.111**recovery voltage**

voltage which appears across the terminals of a pole of a switching device or a fuse after the breaking of the current

Note 1 to entry: This voltage may be considered in two successive intervals of time, one during which a transient voltage exists, followed by a second one during which the power frequency or the steady-state recovery voltage alone exists.

[SOURCE: IEC 60050-441:2000, 441-17-25]

3.7.112**transient recovery voltage****TRV**

recovery voltage during the time in which it has a significant transient character

Note 1 to entry: The transient recovery voltage may be oscillatory or non-oscillatory or a combination of these depending on the characteristics of the circuit and the switching device. It includes the voltage shift of the neutral of a polyphase circuit.

Note 2 to entry: The transient recovery voltages in three-phase circuits is, unless otherwise stated, that across the first pole to clear, because this voltage is generally higher than that which appears across each of the other two poles.

[SOURCE: IEC 60050-441:2000, 441-17-26]

3.7.113**power frequency recovery voltage**

recovery voltage after the transient voltage phenomena have subsided

[SOURCE: IEC 60050-441:2000, 441-17-27]

3.7.114**prospective transient recovery voltage**

<of a circuit> transient recovery voltage following the breaking of the prospective symmetrical current by an ideal switching device

Note 1 to entry: The definition assumes that the switching device or the fuse, for which the prospective transient recovery voltage is sought, is replaced by an ideal switching device, i.e. having instantaneous transition from zero to infinite impedance at the very instant of zero current, i.e. at the "natural" zero. For circuits where the current can follow several different paths, e.g. a polyphase circuit, the definition further assumes that the breaking of the current by the ideal switching device takes place only in the pole considered.

[SOURCE: IEC 60050-441:2000, 441-17-29]

3.7.115**opening time**

<of a mechanical switching device> interval of time between the specified instant of initiation of the opening operation and the instant when the arcing contacts have separated in all poles

Note 1 to entry: For release operation, instant of initiation is taken as the instant of application of power supply on the release

[SOURCE: IEC 60050-441:2000, 441-17-36, modified – The initial note has been deleted and the current note added.]