



BSI Standards Publication

Assessment of power density of human exposure to radio frequency fields from wireless devices in close proximity to the head and body (frequency range of 6 GHz to 300 GHz)

Part 1: Measurement procedure

National foreword

This British Standard is the UK implementation of EN IEC/IEEE 63195-1:2023. It is identical to IEC/IEEE 63195-1:2022. It supersedes BS IEC/IEEE 63195-1:2022, which is withdrawn.

The UK participation in its preparation was entrusted to Technical Committee GEL/106, Human exposure to low frequency and high frequency electromagnetic radiation.

A list of organizations represented on this committee can be obtained on request to its committee manager.

Contractual and legal considerations

This publication has been prepared in good faith, however no representation, warranty, assurance or undertaking (express or implied) is or will be made, and no responsibility or liability is or will be accepted by BSI in relation to the adequacy, accuracy, completeness or reasonableness of this publication. All and any such responsibility and liability is expressly disclaimed to the full extent permitted by the law.

This publication is provided as is, and is to be used at the recipient's own risk.

The recipient is advised to consider seeking professional guidance with respect to its use of this publication.

This publication is not intended to constitute a contract. Users are responsible for its correct application.

© The British Standards Institution 2023
Published by BSI Standards Limited 2023

ISBN 978 0 539 22705 5

ICS 17.220.20; 33.050.10

Compliance with a British Standard cannot confer immunity from legal obligations.

This British Standard was published under the authority of the Standards Policy and Strategy Committee on 31 August 2022.

Amendments/corrigenda issued since publication

Date	Text affected
31 May 2023	This corrigendum renumbers BS IEC/IEEE 63195-1:2022 as BS EN IEC/IEEE 63195-1:2023

English Version

Assessment of power density of human exposure to radio
frequency fields from wireless devices in close proximity to the
head and body (frequency range of 6 GHz to 300 GHz) - Part 1:
Measurement procedure
(IEC/IEEE 63195-1:2022)

Évaluation de la densité de puissance de l'exposition
humaine aux champs radiofréquences provenant de
dispositifs sans fil à proximité immédiate de la tête et du
corps (plage de fréquences de 6 GHz à 300 GHz) -
Partie 1: Procédure de mesure
(IEC/IEEE 63195-1:2022)

Bewertung der Leistungsdichte der Exposition des
Menschen gegenüber hochfrequenten Feldern von
drahtlosen Geräten in unmittelbarer Nähe des Kopfes und
des Körpers (Frequenzbereich von 6 GHz bis 300 GHz) -
Teil 1: Messverfahren
(IEC/IEEE 63195-1:2022)

This European Standard was approved by CENELEC on 2023-01-09. CENELEC members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for giving this European Standard the status of a national standard without any alteration.

Up-to-date lists and bibliographical references concerning such national standards may be obtained on application to the CEN-CENELEC Management Centre or to any CENELEC member.

This European Standard exists in three official versions (English, French, German). A version in any other language made by translation under the responsibility of a CENELEC member into its own language and notified to the CEN-CENELEC Management Centre has the same status as the official versions.

CENELEC members are the national electrotechnical committees of Austria, Belgium, Bulgaria, Croatia, Cyprus, the Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, the Netherlands, Norway, Poland, Portugal, Republic of North Macedonia, Romania, Serbia, Slovakia, Slovenia, Spain, Sweden, Switzerland, Türkiye and the United Kingdom.



European Committee for Electrotechnical Standardization
Comité Européen de Normalisation Electrotechnique
Europäisches Komitee für Elektrotechnische Normung

CEN-CENELEC Management Centre: Rue de la Science 23, B-1040 Brussels

European foreword

This document (EN IEC/IEEE 63195-1:2023) consists of the text of document IEC/IEEE 63195-1:2022, prepared by IEC/TC 106 "Methods for the assessment of electric, magnetic and electromagnetic fields associated with human exposure".

The following dates are fixed:

- latest date by which this document has to be (dop) 2024-01-09
implemented at national level by publication of an
identical national standard or by endorsement
- latest date by which the national standards (dow) 2026-01-09
conflicting with this document have to be withdrawn

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. CENELEC shall not be held responsible for identifying any or all such patent rights.

This document has been prepared under a Standardization Request given to CENELEC by the European Commission and the European Free Trade Association.

Any feedback and questions on this document should be directed to the users' national committee. A complete listing of these bodies can be found on the CENELEC website.

Endorsement notice

The text of the International Standard IEC/IEEE 63195-1:2022 was approved by CENELEC as a European Standard without any modification.

In the official version, for Bibliography, the following notes have to be added for the standard indicated:

ISO/IEC 17025:2017	NOTE Harmonized as EN ISO/IEC 17025:2017 (not modified)
IEC 62311:2019	NOTE Harmonized as EN IEC 62311:2020 (not modified)
ISO/IEC 17043:2010	NOTE Harmonized as EN ISO/IEC 17043:2010 (not modified)

Annex ZA (normative)

Normative references to international publications with their corresponding European publications

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

NOTE 1 Where an International Publication has been modified by common modifications, indicated by (mod), the relevant EN/HD applies.

NOTE 2 Up-to-date information on the latest versions of the European Standards listed in this annex is available here: www.cenelec.eu.

<u>Publication</u>	<u>Year</u>	<u>Title</u>	<u>EN/HD</u>	<u>Year</u>
IEC/IEEE 62209-1528	2020	Measurement procedure for the assessment of specific absorption rate of human exposure to radio frequency fields from hand-held and body-worn wireless communication devices - Part 1528: Human models, instrumentation and procedures (Frequency range of 4 MHz to 10 GHz)	EN IEC/IEEE 62209-1528	2021
IEC/IEEE 63195-2	2022	Assessment of power density of human exposure to radio frequency fields from wireless devices in close proximity to the head and body (Frequency range of 6 GHz to 300 GHz) – Part 2: Computational procedure	EN IEC/IEEE 63195-2	2023

CONTENTS

FOREWORD.....	9
INTRODUCTION.....	11
1 Scope.....	12
2 Normative references	13
3 Terms and definitions	13
3.1 Exposure metrics and parameters.....	13
3.2 Spatial, physical, and geometrical parameters associated with exposure metrics.....	16
3.3 Measurement instrumentation, field probe, and data-processing parameters.....	17
3.4 RF power parameters	20
3.5 Test device technical operating and antenna parameters	21
3.6 Test device physical configurations.....	23
3.7 Uncertainty parameters.....	24
4 Symbols and abbreviated terms.....	25
4.1 Symbols.....	25
4.1.1 Physical quantities.....	25
4.1.2 Constants	26
4.2 Abbreviated terms.....	26
5 Quick start guide and application of this document	27
5.1 Quick start guide.....	27
5.2 Application of this document	30
5.3 Stipulations.....	30
6 Measurement system and laboratory requirements	30
6.1 General requirements	30
6.2 Laboratory requirements	31
6.3 Field probe requirements	32
6.4 Measurement instrumentation requirements.....	32
6.5 Scanning system requirements	33
6.5.1 Single-probe systems	33
6.5.2 Multiple field-probe systems	33
6.6 Device holder requirements	34
6.7 Post-processing quantities, procedures, and requirements.....	35
6.7.1 Formulas for calculation of sPD	35
6.7.2 Post-processing procedure	37
6.7.3 Requirements	38
7 Protocol for PD assessment	39
7.1 General.....	39
7.2 Measurement preparation	39
7.2.1 Relative system check	39
7.2.2 DUT requirements	39
7.2.3 DUT preparation.....	40
7.2.4 Selecting evaluation surfaces	41
7.3 Tests to be performed.....	44
7.3.1 General	44
7.3.2 Tests to be performed when supported by simulations of the antenna array.....	46
7.3.3 Tests to be performed by measurements of the antenna array.....	48



7.4	Measurement procedure	48
7.4.1	General measurement procedure.....	48
7.4.2	Power density assessment methods	49
7.4.3	Power scaling for operating mode and channel.....	51
7.4.4	Correction for DUT drift	53
7.5	Exposure combining.....	54
7.5.1	General	54
7.5.2	Combining power density and SAR results.....	55
8	Uncertainty estimation	58
8.1	General.....	58
8.2	Requirements for uncertainty evaluations	58
8.3	Description of uncertainty models	58
8.4	Uncertainty terms dependent on the measurement system.....	59
8.4.1	<i>CAL</i> – Calibration of the measurement equipment.....	59
8.4.2	<i>COR</i> – Probe correction	59
8.4.3	<i>FRS</i> – Frequency response	59
8.4.4	<i>SCC</i> – Sensor cross coupling	60
8.4.5	<i>ISO</i> – Isotropy	61
8.4.6	<i>LIN</i> – System linearity error	61
8.4.7	<i>PSC</i> – Probe scattering	61
8.4.8	<i>PPO</i> – Probe positioning offset	62
8.4.9	<i>PPR</i> – Probe positioning repeatability	62
8.4.10	<i>SMO</i> – Sensor mechanical offset.....	63
8.4.11	<i>PSR</i> – Probe spatial resolution	63
8.4.12	<i>FLD</i> – Field impedance dependence (ratio $ E / H $)	63
8.4.13	<i>MED</i> – Measurement drift	63
8.4.14	<i>APN</i> – Amplitude and phase noise	64
8.4.15	<i>TR</i> – Measurement area truncation	64
8.4.16	<i>DAQ</i> – Data acquisition	64
8.4.17	<i>SMP</i> – Sampling.....	64
8.4.18	<i>REC</i> – Field reconstruction.....	64
8.4.19	<i>SNR</i> – Signal-to-noise ratio	65
8.4.20	<i>TRA</i> – Forward transformation and backward transformation	65
8.4.21	<i>SCA</i> – Power density scaling.....	66
8.4.22	<i>SAV</i> – Spatial averaging.....	66
8.4.23	<i>COM</i> – Exposure combining.....	66
8.5	Uncertainty terms dependent on the DUT and environmental factors	66
8.5.1	<i>PC</i> – Probe coupling with DUT	66
8.5.2	<i>MOD</i> – Modulation response.....	67
8.5.3	<i>IT</i> – Integration time	67
8.5.4	<i>RT</i> – Response time.....	68
8.5.5	<i>DH</i> – Device holder influence	68
8.5.6	<i>DA</i> – DUT alignment	68
8.5.7	<i>AC</i> – RF ambient conditions.....	68
8.5.8	<i>TEM</i> – Laboratory temperature.....	68
8.5.9	<i>REF</i> – Reflections in laboratory.....	69
8.5.10	<i>MSI</i> – Measurement system immunity/secondary reception.....	69
8.5.11	<i>DRI</i> – DUT drift.....	69
8.6	Combined and expanded uncertainty	69

9	Measurement report	73
9.1	General.....	73
9.2	Items to be recorded in measurement reports	73
Annex A	(normative) Measurement system check and system validation tests	76
A.1	Overview	76
A.2	Normalization to total radiated power	77
A.2.1	General	77
A.2.2	Option 1: Accepted power measurement.....	77
A.2.3	Option 2: Total radiated power measurement.....	81
A.3	Relative system check	82
A.3.1	Purpose	82
A.3.2	Antenna and test conditions.....	82
A.3.3	Procedure.....	83
A.3.4	Acceptance criteria	83
A.4	Absolute system check	85
A.4.1	Purpose	85
A.4.2	Antenna and test conditions.....	85
A.4.3	Procedure.....	85
A.4.4	Acceptance criteria	85
A.5	System validation.....	86
A.5.1	Purpose	86
A.5.2	Procedure.....	86
A.5.3	Validation of modulation response	87
A.5.4	Acceptance criteria	87
Annex B	(normative) Antennas for system check and system validation tests	89
B.1	General.....	89
B.2	Pyramidal horn antennas for system checks	90
B.3	Cavity-fed dipole arrays for system validation	91
B.3.1	Description	91
B.3.2	Numerical target values for cavity-fed dipole arrays.....	94
B.3.3	Field and power density distribution patterns	94
B.3.4	Far-field radiation patterns.....	99
B.4	Pyramidal horns with slot arrays for system validation	101
B.4.1	Description	101
B.4.2	Numerical target values for pyramidal horns loaded with a slot array	103
B.4.3	Field and power density distribution patterns	104
B.4.4	Far-field radiation patterns.....	109
B.5	Antenna validation procedure.....	110
B.5.1	General	110
B.5.2	Objectives, scope, and usage specifications	111
B.5.3	Antenna design.....	111
B.5.4	Numerical targets	111
B.5.5	Reference antennas calibration	111
B.5.6	Antenna verification and life expectation.....	111
B.5.7	Uncertainty budget considerations	111
B.6	Validation procedure for wideband signals	112
B.6.1	General	112
B.6.2	Validation signals	112
B.6.3	Validation antennas and setup.....	112

B.6.4	Target values for validation antennas transmitting wideband signals	112
B.6.5	Wideband signal uncertainty	112
B.6.6	Validation procedure	113
Annex C (normative)	Calibration and characterization of measurement probes	114
C.1	General	114
C.2	Calibration of waveguide probes	114
C.2.1	General	114
C.2.2	Sensitivity	114
C.2.3	Linearity	114
C.2.4	Lower detection limit	115
C.2.5	Isotropy	115
C.2.6	Response time	115
C.3	Calibration for isotropic scalar E-field or H-field probes	115
C.3.1	General	115
C.3.2	Sensitivity	115
C.3.3	Isotropy	115
C.3.4	Linearity	116
C.3.5	Lower detection limit	116
C.3.6	Response time	116
C.4	Calibration of phasor E-field or H-field probes	116
C.4.1	General	116
C.4.2	Sensitivity	116
C.4.3	Isotropy	117
C.4.4	Linearity	117
C.4.5	Lower detection limit	117
C.5	Calibration uncertainty parameters	117
C.5.1	General	117
C.5.2	Input power to the antenna	117
C.5.3	Mismatch effect (input power measurement)	117
C.5.4	Gain and offset distance	118
C.5.5	Signal spectrum	118
C.5.6	Setup stability	118
C.5.7	Uncertainty for field impedance variations	119
C.6	Uncertainty budget template	119
Annex D (informative)	Information on use of square or circular shapes for power density averaging area in conformity evaluations	121
D.1	General	121
D.2	Method using computational analysis	121
D.3	Areas averaged with square and circular shapes on planar evaluation surface	121
D.4	Areas averaged with square and circular shapes on nonplanar evaluation surface	123
Annex E (informative)	Reconstruction algorithms	125
E.1	General	125
E.2	Methodologies to extract local field components and power densities	125
E.2.1	General	125
E.2.2	Phase-less approaches	126
E.2.3	Approaches using E-field polarization ellipse measurements	126
E.2.4	Direct near-field measurements	126

E.3	Forward transformation (propagation) of the fields	127
E.3.1	General	127
E.3.2	Field expansion methods	128
E.3.3	Field integral equation methods	128
E.4	Backward transformation (propagation) of the fields	129
E.4.1	General	129
E.4.2	Field expansion methods – the plane wave expansion	129
E.4.3	Inverse source methods	130
E.5	Analytical reference functions	131
Annex F (normative)	Interlaboratory comparisons	133
F.1	Purpose	133
F.2	Reference devices	133
F.3	Power setup	133
F.4	Interlaboratory comparison – procedure	133
Annex G (informative)	PD test and verification example	134
G.1	Purpose	134
G.2	DUT overview	134
G.3	Test system verification	134
G.4	Test setup	134
G.5	Power density results	134
G.6	Combined exposure (Total Exposure Ratio)	134
Annex H (informative)	Applicability of plane-wave equivalent approximations	135
H.1	Objective	135
H.2	Method	135
H.3	Results	135
H.4	Discussion	137
Annex I (informative)	Rationales for concepts and methods applied in this document and IEC/IEEE 63195-2	138
I.1	Frequency range	138
I.2	Calculation of sPD	138
I.2.1	Application of the Poynting vector for calculation of incident power density	138
I.2.2	Averaging area	139
Bibliography		140
Figure 1 – Quick Start Guide		29
Figure 2 – Simplified view of a generic measurement setup involving the use of reconstruction algorithms		38
Figure 3 – Cross-sectional view of SAM phantom for SAR evaluations at the reference plane, as described in IEC/IEEE 62209-1528:2020		42
Figure 4 – Cross-sectional view of SAM virtual phantom for PD evaluations at the reference plane (shell thickness is 2 mm everywhere, including at the pinna)		42
Figure 5 – Example reference coordinate system for the left-ear ERP of the SAM phantom		44
Figure 6 – Example reference points and vertical and horizontal lines on a DUT		44
Figure 7 – Flow chart for test procedure in 7.3		46
Figure 8 – Flow chart for general measurement procedure in 7.4.1		49
Figure 9 – Flow chart for power density assessment methods in 7.4.2		50

Figure 10 – SAR and power density evaluation at a point r	57
Figure 11 – Combining SAR (top) and power density (bottom) for the SAM phantom	57
Figure A.1 – Recommended accepted power measurement setup for relative system check, absolute system check and system validation	78
Figure A.2 – Equipment setup for measurement of forward power P_f and forward coupled power P_{fc}	78
Figure A.3 – Equipment setup for measuring the shorted reverse coupled power P_{rcs}	78
Figure A.4 – Equipment setup for measuring the power with the reference antenna	79
Figure A.5 – Port numbering for the S -parameter measurements of the directional coupler	80
Figure B.1 – Main dimensions for the cavity-fed dipole arrays – 30 GHz design	92
Figure B.2 – 10 GHz patterns of $ E_{total} $ and $Re\{S\}_{total}$ for the cavity-fed dipole arrays at distances of a) 2 mm, b) 5 mm, c) 10 mm, and d) 50 mm from the upper surface of the dielectric substrate	95
Figure B.3 – 30 GHz patterns of $ E_{total} $ and $Re\{S\}_{total}$ for the cavity-fed dipole arrays at distances of a) 2 mm, b) 5 mm, c) 10 mm, and d) 50 mm from the upper surface of the dielectric substrate	96
Figure B.4 – 60 GHz patterns of $ E_{total} $ and $Re\{S\}_{total}$ for the cavity-fed dipole arrays at distances of a) 2 mm, b) 5 mm, c) 10 mm, and d) 50 mm from the upper surface of the dielectric substrate	97
Figure B.5 – 90 GHz patterns of $ E_{total} $ and $Re\{S\}_{total}$ for the cavity-fed dipole arrays at distances of a) 2 mm, b) 5 mm, c) 10 mm, and d) 50 mm from the upper surface of the dielectric substrate	98
Figure B.6 – Far-field radiation patterns of a) 10 GHz, b) 30 GHz, c) 60 GHz, and d) 90 GHz cavity-fed dipole arrays	100
Figure B.7 – Main dimensions for the 0,15 mm stainless steel stencil with slot array	101
Figure B.8 – Main dimensions for the pyramidal horn antennas	102
Figure B.9 – 10 GHz patterns of $ E_{total} $ and $Re\{S\}_{total}$ for the pyramidal horn loaded with a slot array at distances of a) 2 mm, b) 5 mm, c) 10 mm, and d) 50 mm from the upper surface of the slot array	105
Figure B.10 – 30 GHz patterns of $ E_{total} $ and $Re\{S\}_{total}$ for the pyramidal horn loaded with a slot array at distances of a) 2 mm, b) 5 mm, c) 10 mm, and d) 50 mm from the upper surface of the slot array	106
Figure B.11 – 60 GHz patterns of $ E_{total} $ and $Re\{S\}_{total}$ for the pyramidal horn loaded with a slot array at distances of a) 2 mm, b) 5 mm, c) 10 mm, and d) 50 mm from the upper surface of the slot array	107
Figure B.12 – 90 GHz patterns of $ E_{total} $ and $Re\{S\}_{total}$ for the pyramidal horn loaded with a slot array at distances of a) 2 mm, b) 5 mm, c) 10 mm, and d) 50 mm from the upper surface of the slot array	108
Figure B.13 – Far-field radiation patterns of a) 10 GHz, b) 30 GHz, c) 60 GHz, and d) 90 GHz pyramidal horn loaded with a slot array	110
Figure D.1 – Schematic view of the assessment of the variation of sPD using square shape by rotating AUT (antenna under test)	121
Figure D.2 – Comparison of $psPD$ averaged using square versus circular shaped areas on planar evaluation surfaces	122
Figure D.3 – Example PD distributions with device next to ear evaluation surface	123
Figure D.4 – Comparison of $psPD$ averaged using cube cross-section (square-like) versus sphere cross-section (circular-like) shaped areas for device next to ear evaluation surface	124

Figure E.1 – Simulation (left) and forward transformation from measurements applying methods described in [29] (right) of power density in the xz -plane (above) and yz -plane (below) at a distance of 2 mm for a cavity-fed dipole array at 30 GHz (see Annex B)	127
Figure H.1 – $psPD_{pwe} / psPD_{tot}$ as function of distance (in units of λ) from cavity-fed dipole array (CDA##G, left-side) and pyramidal horn with slot arrays (SH##G, right-side) operating at 10 GHz, 30 GHz, 60 GHz, and 90 GHz	137
Table 1 – Evaluation plan check-list.....	28
Table 2 – Minimum evaluation distance between the DUT antenna and the evaluation surface for which the plane wave equivalent approximation applies	50
Table 3 – Template of measurement uncertainty for power density measurements	70
Table 4 – Example measurement uncertainty budget for power density measurement results	72
Table A.1 – Example of power measurement uncertainty	81
Table A.2 – Communication signals for modulation response test	87
Table B.1 – Target values for pyramidal horn antennas at different frequencies	90
Table B.2 – Main dimensions for the cavity-fed dipole arrays at each frequency of interest	91
Table B.3 – Geometrical parameters of the cavity-fed dipole arrays at each frequency of interest	93
Table B.4 – Substrate and metallic block parameters for the cavity-fed dipole arrays at each frequency of interest.....	93
Table B.5 – Target values for the cavity-fed dipole arrays at 10 GHz, 30 GHz, 60 GHz, and 90 GHz	94
Table B.6 – Main dimensions for the stencil with slot array for each frequency	102
Table B.7 – Primary dimensions for the corresponding pyramidal horns at each frequency.....	103
Table B.8 – Target values for the pyramidal horns loaded with slot arrays at 10 GHz, 30 GHz, 60 GHz, and 90 GHz	104
Table C.1 – Uncertainty analysis of the probe calibration	119
Table D.1 – Phase shift values for the array antenna	123
Table E.1 – List of analytical reference functions and associated $psPD_{n+}$ target values	131
Table E.2 – List of analytical reference functions and associated $psPD_{tot+}$ target values	132
Table E.3 – List of analytical reference functions and associated $psPD_{mod+}$ target values	132

INTERNATIONAL ELECTROTECHNICAL COMMISSION

**ASSESSMENT OF POWER DENSITY OF HUMAN EXPOSURE TO RADIO
FREQUENCY FIELDS FROM WIRELESS DEVICES IN CLOSE PROXIMITY
TO THE HEAD AND BODY (FREQUENCY RANGE OF 6 GHz TO 300 GHz) –****Part 1: Measurement procedure**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC document(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation.

IEEE Standards documents are developed within IEEE Societies and Standards Coordinating Committees of the IEEE Standards Association (IEEE SA) Standards Board. IEEE develops its standards through a consensus development process, approved by the American National Standards Institute, which brings together volunteers representing varied viewpoints and interests to achieve the final product. Volunteers are not necessarily members of IEEE and serve without compensation. While IEEE administers the process and establishes rules to promote fairness in the consensus development process, IEEE does not independently evaluate, test, or verify the accuracy of any of the information contained in its standards. Use of IEEE Standards documents is wholly voluntary. *IEEE documents are made available for use subject to important notices and legal disclaimers (see <http://standards.ieee.org/ipr/disclaimers.html> for more information).*

IEC collaborates closely with IEEE in accordance with conditions determined by agreement between the two organizations. This Dual Logo International Standard was jointly developed by the IEC and IEEE under the terms of that agreement.

- 2) The formal decisions of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees. The formal decisions of IEEE on technical matters, once consensus within IEEE Societies and Standards Coordinating Committees has been reached, is determined by a balanced ballot of materially interested parties who indicate interest in reviewing the proposed standard. Final approval of the IEEE standards document is given by the IEEE Standards Association (IEEE SA) Standards Board.
- 3) IEC/IEEE Publications have the form of recommendations for international use and are accepted by IEC National Committees/IEEE Societies in that sense. While all reasonable efforts are made to ensure that the technical content of IEC/IEEE Publications is accurate, IEC or IEEE cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications (including IEC/IEEE Publications) transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC/IEEE Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC and IEEE do not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC and IEEE are not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or IEEE or their directors, employees, servants or agents including individual experts and members of technical committees and IEC National Committees, or volunteers of IEEE Societies and the Standards Coordinating Committees of the IEEE Standards Association (IEEE SA) Standards Board, for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC/IEEE Publication or any other IEC or IEEE Publications.
- 8) Attention is drawn to the normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.

- 9) Attention is drawn to the possibility that implementation of this IEC/IEEE Publication may require use of material covered by patent rights. By publication of this standard, no position is taken with respect to the existence or validity of any patent rights in connection therewith. IEC or IEEE shall not be held responsible for identifying Essential Patent Claims for which a license may be required, for conducting inquiries into the legal validity or scope of Patent Claims or determining whether any licensing terms or conditions provided in connection with submission of a Letter of Assurance, if any, or in any licensing agreements are reasonable or non-discriminatory. Users of this standard are expressly advised that determination of the validity of any patent rights, and the risk of infringement of such rights, is entirely their own responsibility.

IEC/IEEE 63195-1 was prepared by IEC technical committee 106: Methods for the assessment of electric, magnetic and electromagnetic fields associated with human exposure, in cooperation with the International Committee on Electromagnetic Safety of the IEEE Standards Association, under the IEC/IEEE Dual Logo Agreement between IEC and IEEE. It is an International Standard.

This document is published as an IEC/IEEE Dual Logo standard.

This publication contains supplemental files in the form of analytical reference functions for validation of the reconstruction algorithms in Annex E. Download links for these files can be found in Clause E.5.

The text of this International Standard is based on the following IEC documents:

Draft	Report on voting
106/565/FDIS	106/570/RVD

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with the rules given in the ISO/IEC Directives, Part 2, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/standardsdev/publications.

A list of all parts in the IEC/IEEE 63195 series, published under the general title *Assessment of power density of human exposure to radio frequency fields from wireless devices in close proximity to the head and body*, can be found on the IEC website.

The IEC Technical Committee and IEEE Technical Committee have decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

IMPORTANT – The "colour inside" logo on the cover page of this document indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION

This document provides methods to evaluate incident power density exposures due to any electromagnetic field (EMF) transmitting device intended to be used at a position near the human head or body, or mounted on the body, combined with other transmitters within a product, or embedded in garments. The device categories covered include but are not limited to mobile telephones, radio transmitters in personal computers, and desktop and laptop devices. This document also addresses multi-band and multi-antenna devices. The overall applicable frequency range is from 6 GHz to 300 GHz. This document specifies:

- measurement system (Clause 6);
- power density measurement protocols (Clause 7);
- uncertainty evaluation (Clause 8);
- measurement report (Clause 9);
- system checks and system validation (Annex B).

To develop this document, IEC Technical Committee 106 (TC 106) and Technical Committee 34 (TC 34) Subcommittee 1 (SC 1) of IEEE International Committee on Electromagnetic Safety (ICES) formed Joint Working Group 12 (JWG 12) on measurement methods to assess the power density of electromagnetic fields from wireless devices in close proximity to the head and body.

This document is partly based on IEC TR 63170:2018.

NOTE System validation tests are specified in Annex B for 10 GHz, 30 GHz, 60 GHz, and 90 GHz to cover the frequency range from 6 GHz to 110 GHz. Additional validation antennas to cover the frequency range up to 300 GHz will be developed in a future revision of this document. Further discussion on rationales is given in Annex I.

ASSESSMENT OF POWER DENSITY OF HUMAN EXPOSURE TO RADIO FREQUENCY FIELDS FROM WIRELESS DEVICES IN CLOSE PROXIMITY TO THE HEAD AND BODY (FREQUENCY RANGE OF 6 GHz TO 300 GHz) –

Part 1: Measurement procedure

1 Scope

This document specifies protocols and test procedures for repeatable and reproducible measurements of power density (PD) that provide conservative estimates of exposure incident to a human head or body due to radio-frequency (RF) electromagnetic field (EMF) transmitting communication devices, with a specified measurement uncertainty. These protocols and procedures apply for exposure evaluations of a significant majority of the population during the use of hand-held and body-worn RF transmitting communication devices. The methods apply for devices that can feature single or multiple transmitters or antennas, and can be operated with their radiating structure(s) at distances up to 200 mm from a human head or body.

The methods of this document can be used to determine conformity with applicable maximum PD requirements of different types of RF transmitting communication devices being used in close proximity to the head and body, including if combined with other RF transmitting or non-transmitting devices or accessories (e.g. belt-clip), or embedded in garments. The overall applicable frequency range of these protocols and procedures is from 6 GHz to 300 GHz.

The RF transmitting communication device categories covered in this document include but are not limited to mobile telephones, radio transmitters in personal computers, desktop and laptop devices, and multi-band and multi-antenna devices.

NOTE 1 System validation tests are specified in Annex B for 10 GHz, 30 GHz, 60 GHz, and 90 GHz to cover the frequency range from 6 GHz to 110 GHz. Additional validation antennas to cover the frequency range up to 300 GHz will be developed in a future revision of this document. Further discussion on rationales is given in Annex I.

NOTE 2 The protocols and test procedures in this document can be adapted to evaluate exposure also due to non-communication types of devices operating in close proximity to the head and body, but these devices are not in the scope of this document.

NOTE 3 For the assessment of the combined exposure from simultaneous transmitters operating on frequencies below 6 GHz, the relevant standards for SAR measurements are IEC/IEEE 62209-1528:2020 and IEC/IEEE 62209-3:2019 [1].

NOTE 4 Between 6 GHz and 10 GHz, the scopes of this document and IEC/IEEE 62209-1528:2020 overlap. According to ICNIRP [2] guidelines and IEEE ICES C95.1 [3] standard, power density is the conformity metric in this frequency range. SAR can be used as conformity metric if local regulatory requirements allow it. (e.g. in case where a single transmit band includes test channels at both below and above 6 GHz).

The procedures of this document do not apply for EMF measurements of devices or objects intended to be implanted in the body.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC/IEEE 62209-1528:2020, *Measurement procedure for the assessment of specific absorption rate of human exposure to radio frequency fields from hand-held and body-mounted wireless communication devices – Part 1528: Human models, instrumentation, and procedures (Frequency range of 4 MHz to 10 GHz)*

IEC/IEEE 63195-2:2021¹, *Assessment of power density of human exposure to radio frequency fields from wireless devices in close proximity to the head and body (Frequency range of 6 GHz to 300 GHz) – Part 2: Computational procedure*

3 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

ISO, IEC, and IEEE maintain terminological databases for use in standardization at the following addresses:

- IEC Electropedia: available at <http://www.electropedia.org/>
- ISO Online browsing platform: available at <http://www.iso.org/obp>
- IEEE Dictionary Online: available at <http://dictionary.ieee.org>

3.1 Exposure metrics and parameters

3.1.1

power density

PD

local power density

function of the complex Poynting vector S at the location r that is integrated over a surface to calculate the sPD

Note 1 to entry: Specifications of power density in terms of the integrands of Formula (4), Formula (5), and Formula (8) are provided in 6.7.1. See also rationales provided in Annex I for the PD specifications of 6.7.1.

Note 2 to entry: The formula used to calculate PD can depend on the applicable exposure guidelines or national regulations.

Note 3 to entry: Power density is also referred to as power flux density.

Note 4 to entry: The associated term incident power density refers to quantity of power per unit area that impinges on the body surface. The incident power density just outside the body surface is used to establish local exposure reference levels, which apply at frequencies above 6 GHz in some jurisdictions.

3.1.2

spatial-average power density

sPD

PD (3.1.1) averaged over a surface of area A_{av}

Note 1 to entry: sPD is a function of the location vector r . It is defined on the evaluation surface, except for the edges where no averaging area can be constructed.

Note 2 to entry: Example averaging area sizes specified in exposure limits are 1 cm² and/or 4 cm².

¹ To be published.

3.1.3

peak spatial-average power density

$psPD$

global maximum value of all sPD (3.1.2) values on the evaluation surface (3.2.3)

Note 1 to entry: $psPD$ is given by Formula (1)

$$psPD = \max_r \{sPD(r)\} \quad (1)$$

where r is a point on the evaluation surface.

Note 2 to entry: Other local maxima (i.e. secondary peak spatial-average power density values) can exist (see 3.1.4).

3.1.4

secondary peak spatial-average power density

other local maxima of the spatial-average power density (sPD) values that are smaller than the peak spatial-average power density ($psPD$)

3.1.5

Poynting vector

S

vector product of the electric field strength E and the magnetic field strength H of the electromagnetic field at a given point

Note 1 to entry: The flux of the Poynting vector through a closed surface is equal to the electromagnetic power passing through this surface.

Note 2 to entry: For a periodic electromagnetic field, the time average of the Poynting vector is a vector the direction of which, with certain reservations, can be considered as being the direction of propagation of electromagnetic energy and the magnitude of which can be considered as being the average power flux density.

Note 3 to entry: For a sinusoidal wave of angular frequency ω , the complex Poynting vector is expressed by Formula (2)

$$S = \frac{1}{2} E \times H^* \quad (2)$$

where E and H are phasors and the asterisk denotes the complex conjugate.

Note 4 to entry: The Poynting vector has units of watt per square metre (W/m²).

[SOURCE: IEC 60050-121:2019, 121-11-66 and IEC 60050-705:1995, 705-02-10, modified – The entries have been combined and rearranged; Note 4 has been added.]

3.1.6

plane wave equivalent approximation

estimation of the power density (PD) under the assumption that the evaluation surface is in the far-field

Note 1 to entry: In accordance with the plane wave equivalent approximation, $PD = 377 \times H^2 = E^2/377$.

Note 2 to entry: This document provides criteria for the validity of the plane wave equivalent approximation using the applied reconstruction algorithm; see 7.4.2.1 and Annex H.

Note 3 to entry: Some documents and national regulations consider the associated term "plane-wave equivalent power density", which for uniform conformity evaluation purposes is applied regardless of whether the evaluation surface is in the far-field. In that case both $377 \times H^2$ and $E^2/377$ must be less than or equal to the applicable power density limit value.

3.1.7**specific absorption rate****SAR**

measure of the rate at which energy is absorbed per unit mass in a human body when exposed to a radio frequency electromagnetic field

Note 1 to entry: The SAR in the tissue-equivalent medium can be determined by the rate of temperature increase or by E-field measurements, according to Formula (3) and Formula (4)

$$SAR = \frac{\sigma E^2}{\rho} \quad (3)$$

$$SAR = c_h \left. \frac{\partial T}{\partial t} \right|_{t=0} \quad (4)$$

where

SAR is the specific absorption rate in watts per kilogram;

E is the RMS value of the electric field strength in the tissue-equivalent medium in volts per metre;

σ is the electrical conductivity of the tissue-equivalent medium in siemens per metre;

ρ is the mass density of the tissue-equivalent medium in kilograms per cubic metre;

c_h is the specific heat capacity of the tissue-equivalent medium in joules per kilogram per kelvin;

$\left. \frac{\partial T}{\partial t} \right|_{t=0}$ is the initial time derivative of temperature in the tissue-equivalent medium in kelvin per second.

Note 2 to entry: A more general definition is that SAR is the time derivative of the incremental energy (dW) absorbed by (dissipated in) an incremental mass (dm) contained in a volume element (dV) of given mass density (ρ), according to Formula (5)

$$SAR = \frac{d}{dt} \left(\frac{dW}{dm} \right) = \frac{d}{dt} \left(\frac{dW}{\rho dV} \right) \quad (5)$$

Note 3 to entry: SAR is expressed in units of watt per kilogram (W/kg).

3.1.8**exposure ratio**

ratio of exposure metric to the relevant exposure limit at a given operating frequency and location

Note 1 to entry: The exposure ratio can be expressed in percent.

3.1.9**total exposure ratio**

sum of all applicable exposure ratios for simultaneous signal transmission at a given location

3.1.10**conservative exposure****conservative estimate**

<of exposure> estimate of the exposure, including uncertainties as specified in this document, representative of and slightly higher than that expected to occur in the head or body of a significant majority of the human population during intended use of a wireless transmitting device

3.2 Spatial, physical, and geometrical parameters associated with exposure metrics

3.2.1

averaging area

A_{av}

nominal size of the area used for calculating sPD (3.1.2)

Note 1 to entry: On a planar evaluation surface, sPD is calculated as the ratio of power density (3.1.1) integrated over the averaging area A_{av} . On a non-planar evaluation surface, the averaging area indicates the dimensions of the projection of the integration area of the power density on a planar surface.

Note 2 to entry: See details on averaging in 8.4 of IEC/IEEE 63195-2:2021.

3.2.2

measurement region

surface or volume over which the field measurements are performed

Note 1 to entry: If the measurement region and the evaluation surface (see 3.2.3) are different, the data at the evaluation surface will then be derived from data taken at the measurement region by means of reconstruction algorithms.

Note 2 to entry: The dimension, shape and orientation of the measurement region is determined by the test equipment manufacturer based on the measurement methodology and test setup conditions required for evaluating the DUT.

3.2.3

evaluation surface

virtual surface for the evaluation of the spatial-average power density (sPD) emitted by a DUT

Note 1 to entry: Typical evaluation surfaces that can be applied in this document are the inner shell of the SAM phantom with an added pinna, or a planar surface with finite or infinite extension.

Note 2 to entry: The evaluation of the $psPD$ (3.1.3) on the evaluation surface should yield a conservative estimate (3.1.10) of the exposure.

Note 3 to entry: In practice, an evaluation surface can be different from a measurement surface or area.

3.2.4

evaluation distance

distance between the DUT and the evaluation surface

Note 1 to entry: For body-worn device evaluations using a virtual flat phantom, the evaluation distance is from the DUT to the inner surface of the virtual phantom (i.e. the separation distance (3.2.5) plus the 2 mm shell thickness of a virtual phantom).

3.2.5

separation distance

distance between the DUT and the outer surface of a virtual phantom

3.2.6

pinna

auricle

cartilaginous projecting portion of the outer ear, consisting of the helix, lobule, and anti-helix

Note 1 to entry: The SAM phantom includes a representative pinna feature.

3.2.7

field impedance

wave impedance

ratio of the magnitude of the electric field (E-field) vector to the magnitude of the magnetic field (H-field) vector at a point in space

Note 1 to entry: In the far-field in air, the field impedance is equal to the characteristic impedance of free space, η_0 . In the reactive near-field, the field impedance can be significantly different from the characteristic impedance of free space and it can vary strongly with location.

3.2.8

near-field

region encompassed by the reactive near-field and the radiative near-field

Note 1 to entry: See also 3.2.10 and 3.2.9 for definitions of reactive near-field and radiative near-field, respectively.

3.2.9

radiative near-field

region of space between the reactive near-field and the far-field, wherein the predominant components of the electromagnetic field are those that represent a propagation of energy, and wherein the angular field distribution is dependent upon the distance from the antenna

Note 1 to entry: In the radiative near-field, the out-of-phase (i.e. evanescent) component of the electromagnetic field decays, and the in-phase (i.e. propagating) component of the electromagnetic field emerges.

[SOURCE: IEC 60050-712:1992, 712-02-04, modified – In the term, "radiating" has been replaced by "radiative". In the definition, "region" has been deleted after "near-field" and "far-field". The note has been replaced by a new note to entry.]

3.2.10

reactive near-field

region of space immediately surrounding an antenna, where the predominant components of the electric field and magnetic field are those that represent an exchange of reactive energy between the antenna and the surrounding medium, and where the electric field and magnetic field components are 90° out of phase

[SOURCE: IEC 60050-712:1992, 712-02-01, modified – In the definition, the electric field and magnetic field component phase difference has been added.]

3.2.11

far-field

region of the electromagnetic field of an antenna wherein the predominant components of the field are those that represent a propagation of energy, the angular field distribution is essentially independent of the distance from the antenna geometrical centre, and the ratio of predominant electric field and magnetic field components is constant and is equal to the wave impedance of 377 Ω

Note 1 to entry: For the purposes of this document, the boundary of the near-field and far-field is as specified in 7.4.2.1.

[SOURCE: IEC 60050-712:1992, 712-02-02, modified – In the definition, the distance to antenna geometrical centre has been clarified, and a phrase on the ratio of the electric field and magnetic field components has been added. The notes have been replaced by a new note to entry.]

3.3 Measurement instrumentation, field probe, and data-processing parameters

3.3.1

power density measurement

assessment of power density (PD) (3.1.1) by the use of a measurement apparatus and possibly the use of reconstruction

3.3.2

reconstruction

use of algorithms to transform the measured fields to the power density at the evaluation surface

Note 1 to entry: Reconstruction algorithms include one or more of the following techniques:

- methodologies to retrieve field components and power densities (i.e. determined using field reconstruction) from the measured data (e.g. to retrieve the phase from the amplitude, or the H-field from the E-field (or vice versa).
- forward transformation and backward transformation to evaluate the field on other surfaces than the surfaces of measurements.

3.3.3

backward transformation

transformation of measured fields toward the source (i.e. against the direction of propagation)

3.3.4

forward transformation

transformation of measured fields away from the source (i.e. in the direction of propagation)

3.3.5

field probe probe

device capable of measuring the electric field, the magnetic field, or both

Note 1 to entry: A field probe consists of one or more probe sensors and a conductive or non-conductive transmission line (e.g. fibre optic) that sends the measured signal to the readout electronics.

Note 2 to entry: A field probe can include a physical housing and electronics components.

3.3.6

probe sensor

element (e.g. small dipole or small loop antenna) that receives an electric field, a magnetic field, or power density at a point in space

Note 1 to entry: One or more probe sensors are contained in a field probe.

3.3.7

scanning system

mechanical, electro-mechanical, or electronic system, or a combination of those, capable of placing the field probe or multiple field-probe at specified positions with known accuracy

3.3.8

multiple field-probe

<system> device comprised of a number of field probes, arranged, oriented and excited to obtain a prescribed electric field, magnetic field or both simultaneously

Note 1 to entry: The multiple field-probes in a system are usually identical and congruent by translation or by rotation about an axis; moreover, in general they are regularly spaced with conductive or non-conductive transmission lines that send the measured signal(s) to the readout electronics.

3.3.9

phasor

complex number expressing the magnitude and phase of a time-varying quantity

Note 1 to entry: Unless otherwise specified, phasor notation is used only within the context of steady state alternating linear systems.

Note 2 to entry: In polar coordinates, a phasor can be written as $Ae^{j\theta}$, where A is the amplitude or magnitude, and θ is the phase angle.

3.3.10**phasor probe**

probe along with readout electronics that enables the measurement of the phasor of a magnetic field vector or an electric field vector

3.3.11**axial isotropy**

maximum deviation of the PD measured when rotating through 360° the source or the probe tip around its major axis, with the propagation vector (k -vector) of the incident plane wave parallel to the probe axis

3.3.12**hemispherical isotropy****probe isotropy**

ratio of the highest to lowest indication from the probe exposed to a constant field strength when the probe orientation is varied through the range of relevant angles that cover the incidence angles that are potentially spanned during DUT testing

Note 1 to entry: For some probe technologies, multiple measurements with different probe orientations followed by an evaluation are required in order to determine the field vector orientation (e.g. see Pfeifer et al. [4]); hemispherical isotropy can be derived from those results.

3.3.13**cross coupling**

signal reading at one sensor port that is due to measurement at another sensor within a field probe

Note 1 to entry: Cross coupling is a result of imperfect isolation of the signals. Cross coupling can occur along the transmission lines from the sensor or in the data acquisition electronics.

3.3.14**linearity error**

maximum deviation of a measured quantity from the expected values specified by a reference line over the measurement range

3.3.15**measurement drift**

continuous or incremental change in measured quantity over time, due to changes in metrological properties of a measuring instrument

Note 1 to entry: This is separate from DUT drift addressed in 7.4.4.

3.3.16**readout electronics**

measurement system component that connects to the electric field or magnetic field probe and provides a conversion of the measured values to the post processor of the measurement system

3.3.17**response time**

time required by the measuring equipment to reach 90 % of its final value after a step variation of the input signal

3.3.18**sensitivity of a measurement system**

ratio of the magnitude of the system response (e.g. voltage) to the magnitude of the quantity being measured (e.g. electric field strength squared)

3.3.19

signal-to-noise ratio

relative magnitude of the desired signal with respect to the total of all undesired signals in a measurement

Note 1 to entry: The signal-to-noise-ratio is often expressed in decibel (dB).

3.3.20

device holder

fixture constructed of low-loss dielectric material that is used to hold the DUT in the required test position during PD measurement

3.3.21

scattering

deflection of electromagnetic fields, causing a change in the local field distribution and the direction of propagation

Note 1 to entry: Scattering can be caused by the measurement equipment or surrounding environment.

3.3.22

validation

verification (3.3.24) where the specified requirements are adequate for an intended use

[SOURCE: ISO/IEC 17025:2017, 3.9 [5]]

3.3.23

system validation

validation (3.3.22) that the accuracy of the measurement system is adequate for use in accordance with the requirements of this document, including validating that the measurement system operates within the stated measurement uncertainty

Note 1 to entry: Although users of systems can perform system validations, generally it is a complex, specialized, and extensive process, and therefore in some cases is performed by the system manufacturer.

3.3.24

verification

provision of objective evidence that a given item fulfils specified requirements

[SOURCE: ISO/IEC 17025:2017, 3.8 [5]]

3.3.25

relative system check

verification (3.3.24) of the repeatability of the measurement system using a source with a reference value before performing conformity testing

3.3.26

absolute system check

verification (3.3.24) of the absolute accuracy of a measurement system using a source with a traceable absolute target value

Note 1 to entry: Absolute system checks are performed at the user's site.

Note 2 to entry: One purpose of the absolute system check is to verify that the shipment and installation at the user site did not affect the performance of the measurement system.

3.4 RF power parameters

3.4.1

output power

power at the output of the RF transmitter when the antenna, or a load with the same input impedance as the antenna, is connected to it

3.4.2**conducted power**

power delivered by the power amplifier of the device to 50 Ω matched load

3.4.3**accepted power****net power**

power delivered to an antenna

Note 1 to entry: The accepted power, P_{acc} , is lower than the forward power, P_f (measured into a 50 Ω load), due to antenna mismatch according to $P_{acc}/P_f = (1 - |S_{11}|^2)$, where S_{11} is the reflection coefficient of the antenna.

3.4.4**equivalent isotropically radiated power****EIRP**

product of the power supplied by a radio transmitter to an antenna and the absolute gain of the antenna in a given direction

Note 1 to entry: Although not indicated in IEC or ITU definitions, some literature synonymously uses the term effective isotropic radiated power.

[SOURCE: IEC 60050-712:2021, 712-02-51]

3.4.5**total radiated power****TRP**

integral of the equivalent isotropically radiated power (EIRP) of an antenna in all directions in the far-field

Note 1 to entry: TRP is given by Formula (6), where ϕ and θ are angles of azimuth and elevation, respectively, in a spherical coordinate system.

$$TRP = \frac{1}{4\pi} \int_{\phi=0}^{2\pi} \int_{\theta=0}^{\pi} EIRP(\theta, \phi) \sin \theta d\theta d\phi \quad (6)$$

Note 2 to entry: If the antenna were enclosed in a perfectly absorbing sphere, the TRP would be the power that would be absorbed by that sphere.

Note 3 to entry: TRP is related to the accepted power, P_{acc} , and the radiation efficiency, η_{eff} , by the formula $TRP = \eta_{eff} \times P_{acc}$.

3.5 Test device technical operating and antenna parameters**3.5.1****operating mode**

wireless protocol or standard used by a device to communicate with another terminal or host network

3.5.2**channel****RF channel****frequency channel**

part of the frequency spectrum intended to be used for the transmission of signals and which may be defined by two specified limits, or by its centre frequency and the associated bandwidth, or by any equivalent indication

Note 1 to entry: The number of RF channels and the corresponding channel bandwidth can vary among individual wireless technologies, and are subject to national frequency allocations. For the purpose of this document, PD measurements are performed at specific channels; for example, the high, middle, and low channels of the transmission band.

[SOURCE: IEC 60050-701:1988, 701-02-05]

3.5.3**frequency band**

transmitting frequency range associated with a specific wireless communication operating mode

Note 1 to entry: Transmitting frequency range depends on (national) spectrum allocations.

Note 2 to entry: Operating mode is also known as "radio access technology (RAT)."

3.5.4**antenna sub-array**

subset of radiating elements in an array that operate collectively

Note 1 to entry: Antenna elements can be used separately by two or more sub-arrays.

3.5.5**array****array antenna****antenna array**

antenna comprised of a number of generally identical radiating elements, arranged, oriented and excited to obtain a prescribed radiation pattern

Note 1 to entry: The IEC also includes phased array antenna (IEV 712-03-20): an array antenna whose beam direction or radiation pattern is controlled primarily by the relative phase of excitation of the different radiating elements of the array.

[SOURCE: IEC 60050-712:1992, 712-01-05]

3.5.6**codebook**

description of all applicable element-feed amplitude and phase combinations supported by antenna array or antenna sub-array in a DUT

Note 1 to entry: IEC/IEEE 63195-2:2021 defines codebook as set of all possible excitation vectors. The excitation vectors correspond to all applicable element-feed amplitude and phase combinations.

3.5.7**correlated signals**

signals yielding non-zero time-domain correlation integral at some time instant

Note 1 to entry: Details on this definition are described in IEC TR 62630:2010 [6].

3.5.8**proximity sensor**

internal sensor or combination of sensors of the DUT utilized for the detection of the user proximity for the purpose of limiting transmitter power to facilitate conformity with RF exposure limits

3.5.9

radiation efficiency

ratio of the total radiated power (TRP) (3.4.5) of an antenna to the accepted power (3.4.3) to the antenna

Note 1 to entry: TRP is related to the accepted power, P_{acc} , and the radiation efficiency, η_{eff} , by the formula

$$TRP = \eta_{eff} \times P_{acc}.$$

3.5.10

time averaging

temporal integration of the measured signal normalized to the integration period

3.6 Test device physical configurations

3.6.1

device under test

DUT

test device

device that is tested according to the procedures described in this document to determine the PD level

Note 1 to entry: A DUT may be further categorized as a body-worn, body-supported, desktop, front-of-face, hand-held, limb-worn, clothing-integrated, or generic device.

3.6.2

multi-band

<wireless communication device> capable of operating in more than one frequency band

3.6.3

generic device

device that does not belong to any of the specific device categories

Note 1 to entry: Specific device categories are defined in 3.6.5, 3.6.6, 3.6.7, 3.6.8, 3.6.9, 3.6.10, and 3.6.11.

3.6.4

intended use

use for which a device is intended, for the full range of available functions, according to the specifications, instructions and information provided by the DUT manufacturer in the user documentation

Note 1 to entry: According to CENELEC [7], [8], conformity evaluations for Europe take into account all intended operating conditions and the reasonably foreseeable conditions of use.

3.6.5

body-worn device

device containing one or more wireless transmitters or transceivers that is positioned in close proximity to a person's torso or limbs (excluding the head) by means of a carrying accessory during its intended use or operation of its radio functions

3.6.6

body-supported device

device containing one or more wireless transmitters or transceivers whose intended use includes transmitting with any portion of the device being placed against a user's body

3.6.7

desktop device

device placed or mounted on a desk, table, or similar supporting structure, with antennas intended to be operated at or closer than 200 mm from the human body

3.6.8**front-of-face device**

hand-held device containing one or more wireless transmitters or transceivers operated in close proximity (within 200 mm) to the face

3.6.9**hand-held device**

portable device which is operated in a user's hand at a distance of over 200 mm from the head or torso during its intended use

3.6.10**laptop device**

device, containing one or more wireless transmitters or transceivers, that can sit on the user's lap and is not intended for hand-held use

Note 1 to entry: Laptop device types include laptop (notebook) computers, typically comprised of separate keyboard and display sections connected through a hinge, and tablet computers that typically have a single-section construction where the display section also serves as input interface using a stylus or virtual keyboard.

3.6.11**limb-mounted device**

device containing one or more wireless transmitters or transceivers whose intended use includes being strapped onto the arm or leg of the user while transmitting

Note 1 to entry: Limb-mounted device types include wrist-mounted, ankle-mounted, and forearm-mounted devices.

3.6.12**accessory**

device supplementing a main device or apparatus, but not forming part of it, that is needed for its operation or to confer on it specific characteristics

EXAMPLE 1 Accessories for holding, affixing, or otherwise carrying, wearing, or attaching the device, as well as providing spacing from the body (e.g. a belt-clip, wrist-strap or any other body strap, or lanyard for wearing the device using a necklace).

EXAMPLE 2 Electronic accessories for performing specialized tasks or which provide additional features (e.g. Global Positioning System (GPS) modules, outboard printers, MPEG-1 Audio Layer 3 (MP3) players, cameras or viewing devices).

EXAMPLE 3 Electronic accessories providing audio or video input or output (e.g. headsets, microphones, cameras).

EXAMPLE 4 Accessories providing enhanced RF capability to the device (e.g. original, replacement, or auxiliary antennas).

EXAMPLE 5 Batteries and related direct current (DC) power components.

EXAMPLE 6 Combinations of accessories, where two or more of the items of the preceding examples are combined within one component (e.g. belt clip with built-in short-range wireless communications technology and "pigtail" audio cable to device).

[SOURCE: IEC 60050-151:2001, 151-11-24]

3.7 Uncertainty parameters**3.7.1****uncertainty**

confidence range of the assessed value

3.7.2**standard uncertainty**

estimated standard deviation of a measurement or simulation result, equal to the positive square root of the estimated variance

3.7.3**combined uncertainty**

estimated standard deviation of the measurement or simulation result obtained by combining the individual standard uncertainties of both Type A and Type B evaluations using the "root-sum-square" method of combining standard deviations that are obtained by taking the positive square root of the estimated variances

3.7.4**expanded uncertainty**

quantity defining an interval about the result of a measurement or simulation that is expected to encompass a distribution of values within a specified confidence interval that can reasonably be attributed to the measurand

3.7.5**uncertainty evaluation**

evaluation of uncertainty by the statistical analysis of series of observations (Type A) or by other means (Type B)

4 Symbols and abbreviated terms**4.1 Symbols****4.1.1 Physical quantities**

The internationally accepted SI units are used throughout the document.

Symbol	Quantity	Unit	Dimensions
α	attenuation coefficient	reciprocal metre	1/m
P	power	watt	W
J	current density	ampere per square metre	A/m ²
σ	electric conductivity	siemens per metre	S/m
E	electric field strength	volt per metre	V/m
f	frequency	hertz	Hz
PD	power density	watt per square metre	W/m ²
S	Poynting vector	watt per square metre	W/m ²
H	magnetic field strength	ampere per metre	A/m
ρ	mass density	kilogram per cubic metre	kg/m ³
δ	penetration depth	metre	m
μ	permeability	henry per metre	H/m
sPD	spatial-average power density	watt per square metre	W/m ²
sPD_{n+}	surface-normal propagation-direction spatial-average power density	watt per square metre	W/m ²
sPD_{tot+}	total propagating spatial-average power density	watt per square metre	W/m ²
sPD_{mod+}	total spatial-average power density considering reactive near-field effects	watt per square metre	W/m ²
$psPD$	peak spatial-average power density	watt per square metre	W/m ²
$psPD_{n+}$	surface-normal propagation-direction peak spatial-average power density	watt per square metre	W/m ²
$psPD_{tot+}$	total propagating peak spatial-average power density	watt per square metre	W/m ²

Symbol	Quantity	Unit	Dimensions
$psPD_{mod+}$	total peak spatial-average power density considering reactive near-field effects	watt per square metre	W/m^2
c_h	specific heat capacity	joule per kilogram per kelvin	$J/(kg\ K)$
ε	permittivity	farad per metre	F/m
SAR	specific absorption rate	watt per kilogram	W/kg
T	temperature	kelvin	K
λ	wavelength	metre	m

NOTE In this document, temperature is quantified in degrees Celsius, as defined by: $T (^{\circ}C) = T (K) - 273,15$.

4.1.2 Constants

Symbol	Physical constant	Magnitude
c	speed of light in vacuum	$2,998 \times 10^8\ m/s$
η_0	characteristic impedance of free space	$376,73\ \Omega$
ε_0	permittivity of free space	$8,854 \times 10^{-12}\ F/m$
μ_0	permeability of free space	$4\pi \times 10^{-8}\ H/m$

4.2 Abbreviated terms

2D	two-dimensional
3D	three-dimensional
B-M	back-to-mouth
CAD	computer aided design
CP	cyclic prefix
CW	continuous wave
DFT-s	discrete Fourier transform spread
DUT	device under test
E-field	electric field
EIRP	equivalent isotropically radiated power
EMC	electromagnetic compatibility
ER	exposure ratio
ERP	ear reference point
FDTD	finite-difference time-domain
GTEM	gigahertz transverse electromagnetic
H-field	magnetic field
ICNIRP	International Commission on Non-Ionizing Radiation Protection
MIMO	multiple input multiple output
N-F	neck-to-front
NR	new radio
OFDM	orthogonal frequency-division multiplexing
PAPR	peak to average power ratio
PD	power density
QAM	quadrature amplitude modulation
QPSK	quadrature phase shift keying

RB	resource block
RF	radio frequency
RMS	root mean square
RSS	root sum square
SAM	specific anthropomorphic mannequin
SAR	specific absorption rate
TER	total exposure ratio
TRP	total radiated power
VNA	vector network analyser

5 Quick start guide and application of this document

5.1 Quick start guide


The quick start guide shown in Figure 1 and the evaluation plan check-list shown in Table 1 provide a high-level overview of the PD measurement procedure. For the details of each step, refer to the relevant clause specified in Figure 1 and Table 1.

NOTE In the far-field of a source at separation distances less than 200 mm, a simpler measurement system and test procedures can be used, such as described in IEC 62311:2019 [9]².

² Numbers in square brackets refer to the Bibliography.

Table 1 – Evaluation plan check-list

Stage	Evaluation steps	Action
Evaluation plan check-list Planning of the measurement configurations	<ul style="list-style-type: none"> – What type of device is being evaluated? – Review of antennas, possible beam-steering options and supported wireless technologies, single antenna or require combinations of exposure from multiple antennas. – What are the applicable evaluation surfaces? – Working under laboratory conditions and following good laboratory practice and documentation, prepare to conduct the necessary evaluation. 	Complete evaluation plan check-list.
Preliminary actions and Relative system check	<ul style="list-style-type: none"> – An environmental measurement shall be performed, and the data recorded (6.2). – Relative system check shall be performed to verify that the system components are working correctly (Clause A.3). 	Shall be performed before starting a project and repeated in accordance with 7.2.1.
DUT setup Preparation of DUT	<p>The protocol for <i>psPD</i> assessment identifies the applicable configurations that shall be tested. The essential steps include:</p> <ul style="list-style-type: none"> – preparing the DUT by establishing a connection to a network simulator; – configuring the DUT to operate on the appropriate test frequencies, wireless modes, and exposure conditions; – configuring the DUT to operate on the appropriate beam-steering options; – positioning the DUT in relation to the measurement region. 	Ensure the DUT is configured in the correct way and radiating appropriately for the test case, and positioned correctly in relation to the measurement region.
PD measurement procedures General <i>psPD</i> procedure	<ul style="list-style-type: none"> – This stage is the actual procedure for the measurement of <i>psPD</i>. – The procedure is iterative to ensure that the highest value of the <i>psPD</i> of a DUT is captured. – This is done by a systematic process looking at all device positions, configurations, and operating modes in all frequency bands accordingly (7.2.3). 	<p>Determining highest <i>psPD</i>.</p> <p>Ensure the rationale for test reduction is recorded and reported if used.</p>
Uncertainty evaluation	<ul style="list-style-type: none"> – Requirements and approximation formulas are provided (Clause 8), enabling the estimation of each individual uncertainty component. – The uncertainty budget shall cover the appropriate frequency range with regards to equipment used in the <i>psPD</i> system. 	Determine uncertainty and complete the uncertainty table.
Reporting <i>psPD</i> results	<ul style="list-style-type: none"> – The final report describes the results of the evaluations, provides sufficient technical details to allow for repeatability of the evaluations performed, and reports the results by comparison with the relevant limit (Clause 9). – The measurement report shall contain sufficient details and information for demonstrating conformity to the requirements of this document. 	Prepare the final measurement report along with addressing the requirements listed in Clause 9.



IEC

Figure 1 – Quick Start Guide

5.2 Application of this document

This document and IEC/IEEE 63195-2:2021 were developed in parallel in two joint working groups of IEC and IEEE to prepare procedures for conformity evaluation to exposure limits on the incident power density under particular consideration of the exposure from wireless devices of the new fifth generation (5G) mobile technology operating in a frequency range from 6 GHz to 300 GHz. This document specifies measurement procedures, and IEC/IEEE 63195-2:2021 specifies computational procedures.

After the fundamental work on the measurement procedures for conformity evaluation at frequencies above 10 GHz had been documented in IEC TR 63170:2018 [10], both this document and IEC/IEEE 63195-2:2021 were developed in a comparatively short time period of two years. In parallel, the ICNIRP [2] and TC95 of the IEEE ICES revised their exposure guidelines and included new basic restrictions and reference levels for the frequency range of 6 GHz and above. These are based on the absorbed/epithelial power density or incident power density, respectively, averaged over a square area of 1 cm² or 4 cm².

This document contains all relevant specifications for the application of measurement procedures for conformity evaluation. While parts of it can be applied independently from the computational standard IEC/IEEE 63195-2:2021, it refers to the post processing methods for power density averaging and maximization of the incident power density that are common to both this document and IEC/IEEE 63195-2, but are specified only in IEC/IEEE 63195-2:2021. Likewise, computational conformity evaluation is described in IEC/IEEE 63195-2:2021. For validations of numerical modelling results by measurements, the methods of this document are required.

5.3 Stipulations

Due to the constraints on the time available for the development of this document and IEC/IEEE 63195-2:2021, practical options needed to be found regarding the interpretation of the new exposure guidelines for the assessment of the conformity with the new limits. These concern the construction of the averaging area and the calculation of the spatial average power density on this averaging area. Regarding the calculation of the spatial average power density, different methods are specified with the objectives to warrant compatibility with exposure evaluations obtained according to IEC TR 63170:2018 [10] and to consider exposure conditions other than perpendicular incidence in the far-field. Annex I discusses the options and their rationales.

These options do not impair the applicability of the methods specified in IEC/IEEE 63195-2 and this document for the conformity evaluation with the reference levels specified in the exposure guidelines.

6 Measurement system and laboratory requirements

6.1 General requirements

A PD measurement system is used to determine the peak spatial-average power density (p_{sPD}) on the evaluation surface in accordance with the methods described in Clause 7. The measurement protocol in this document is based on mechanically positioning field probes in a grid relative to the DUT to scan the electric field or magnetic field distributions, or both. The following are minimum requirements of the measurement system.

- a) Measurements shall be performed in a controlled laboratory (see 6.2).
- b) The measurement system shall consist of the field probe(s) (see 6.3), measurement instrumentation (see 6.4), a scanning system (see 6.5), a DUT holder (see 6.6) and post-processing software (see 6.7). The post-processing software may include field reconstruction algorithms.
- c) The measurement system shall be capable of determining the sPD on the required evaluation surface.

- d) Uncertainties of the measured field components and power density results (i.e. determined using field reconstruction) shall be assessed and provided (see Clause 8).
- e) The measurement system shall determine the *sPD* on the evaluation surface using the measured field components and power densities (i.e. determined using field reconstruction), of which the *psPD* shall be calculated. The uncertainty of the *psPD* calculation shall be provided based on the uncertainty of the measured field components and power densities (i.e. determined using field reconstruction) (see Clause 8).
- f) The dynamic range of the *sPD* for which the uncertainty budget is valid shall be from at most 20 % to at least 200 % (less than –7 dB to more than +3 dB) of the applicable exposure limit.
- g) The noise floor of the measurement system shall be at least 10 dB below the lower end of the dynamic range of the PD, so that the influence of noise on the measurement uncertainty is small.
- h) The maximum expanded uncertainty ($k = 2$) of the *psPD* assessment shall not be larger than ± 2 dB (–37 % to +58 %) over the dynamic range.
- i) The bandwidth of the measurement system shall be valid for the wireless communication signals and systems tested.
- j) The measurement system shall have valid calibration across the frequency range tested.
- k) The manufacturer of the measurement system shall report to the user the limitations of the system relative to this document. This includes the frequency range, the bandwidth, the locations of the evaluation surface relative to the DUT, the dynamic range, and the measurement uncertainty.
- l) The components of the measurement system that directly affect the measurement accuracy (e.g. field probes, measurement instrumentation) shall have calibration traceable to international standards.
- m) The measurement system shall be validated as a complete and calibrated system (see Clause A.5). System validation is required whenever modifications have been made to the system (e.g. software version, or different type or version of measurement components).
- n) Where this document explicitly specifies performance characteristics for the measurement system or a part of the measurement system, the manufacturer of the system or its parts, or the system integrator, shall document conformity with the provisions of this document.

Conformity with the preceding general requirements shall be documented by the system manufacturer or system integrator.

NOTE 1 Simplified measurement systems and test procedures can be applied if the body is always in the far-field of the source (e.g. see IEC 62311:2019 [9]), which can also include separation distances closer than 200 mm.

NOTE 2 The ICNIRP RF EMF Guidelines [2] state that reference levels (incident power density) cannot be used to determine conformity within reactive near-field, basic restrictions (absorbed power density) should be used instead. Based on the ICNIRP definition of reactive near-field, this limitation is applicable to procedures of this document at frequencies below 24 GHz. IEC TC 106 and IEEE ICES are considering to develop an international standard for absorbed or epithelial power density in future.

NOTE 3 System validation methods are currently specified in this document for the frequency range 6 GHz to 100 GHz, which covers all devices currently available. Extension to 300 GHz of the validation procedures will be specified in a future revision.

NOTE 4 To quantify the measurement reproducibility of a system, interlaboratory comparisons (Annex F) using sources that are representative of the radiating characteristics of tested devices can be conducted.

6.2 Laboratory requirements

The tests shall be performed in a laboratory conforming to the following requirements.

- a) The ambient noise for any measurement shall correspond to less than –20 dB (1 %) of either the applicable power density limit or the peak measured field, whichever is higher.

- b) The influence of reflections from objects in the laboratory (including the scanning measurement system, cables, walls, and the DUT holder) on the measurements shall be less than -17 dB (2 %) of the applicable power density limit. See 8.5.9 to determine the influence of reflections. This shall be evaluated at least annually.
- c) The ambient temperature shall be in the range for which the calibration of the system component is valid and the transmission variation of the DUT by temperature due to ambient temperature is less than 5 % (e.g. between 18 °C and 25 °C) (see 8.5.8). It shall also vary by less than ± 2 °C with respect to the ambient temperature during the measurement.
- d) The measurement equipment shall have been powered on and allowed to warm up in the laboratory in accordance with manufacturer's stabilization time.

Conformity with these laboratory requirements shall be documented in the measurement report.

6.3 Field probe requirements

The measurement system includes one or more field probes; multiple field-probe systems can significantly reduce the measurement time. Each field probe shall conform to the following requirements.

- a) The field probe(s) shall measure the electric field or the magnetic field or both.
- b) The cross-coupling level between field components shall be such that the maximum expanded uncertainty requirements in 6.1 are met.
- c) The field probe shall measure the phase of the field unless the evaluation surface is in the far-field (see Table 2 of 7.4.2.1) or unless field reconstruction techniques are applied to estimate the power density correctly.
- d) The field probe dynamic range shall be such that the system dynamic range requirements in 6.1 are met.
- e) The field probe size and construction shall ensure that the effect of scattering from the probe on the fields transmitted by the DUT is within the expanded uncertainty for probe scattering as described in 8.4.7.
- f) The field probe shall be calibrated according to the requirements in Annex C. The probe may be calibrated separately from the rest of the measurement system if the same electrical interface characteristics are used during calibration as during measurements. It is preferable not to calibrate the probe separately from the rest of the measurement system. If the probe is calibrated separately, the calibration uncertainty should include statistical interdependence with a signal reading instrument.
- g) The field probe calibration report shall document at least the uncertainties and the associated validity restrictions of mechanical offset (8.4.10), frequency response (8.4.3), sensitivity, linearity error (8.4.6), isotropy (8.4.5), cross coupling (8.4.4), and field impedance dependence (8.4.12). Any dependence of these quantities on frequency and bandwidth shall also be reported.

Conformity with these field probe requirements shall be documented by the manufacturer of the measurement system.

6.4 Measurement instrumentation requirements

The field probe output is processed by the measurement instrumentation, which conforms to the following requirements.

- a) The measurement instrumentation shall receive the signal measured by the field probe and provide it to a computer for evaluation.

NOTE The computer can be integrated with the measurement instrumentation, separate from it, or both.

- b) The measurement instrumentation shall be calibrated. It may be calibrated separately from the probe if the same input and electrical interface characteristics are used during calibration as during measurements.

The measurement instrumentation may perform amplification, frequency filtering or other signal processing. It may also account for signal compression, amplifier non-linearities and other non-linear effects.

Conformity with these measurement instrumentation requirements shall be documented by the manufacturer of the measurement system.

6.5 Scanning system requirements

6.5.1 Single-probe systems

The scanning system positions the field probe on the measurement region. The requirements of the scanning system are as follows.

- a) The scanning method shall be reported, including whether it performs two-dimensional (2D) or three-dimensional (3D) scans.
- b) The algorithm for determining the measurement grid, if a fixed grid is not used, shall be reported.
- c) The scanning system shall restrict the field probe locations during measurement to the region where the influence of the field impedance on the measurement is within the stated uncertainty (see 8.4.12). This uncertainty shall not be greater than 0,5 dB.
- d) The scanning system shall be capable of positioning the field probe over a large enough measurement region such that the $psPD$ can be determined at any point on the evaluation surface so to meet the stated REC uncertainty (see 8.4.18).
- e) The accuracy and repeatability of the field probe positioning shall be reported, and they shall be sufficient to ensure that the measurement uncertainty of the $psPD$ is within the stated PPO uncertainty (see 8.4.8). The tolerance of field probe positioning shall also be sufficient to combine exposures from multiple antennas or multiple transmitters (see 7.5).
- f) The scanning system shall be capable of rotating the field probe, if necessary, to capture the required field components and power densities (i.e. determined using field reconstruction). The accuracy and repeatability of field probe orientation shall be reported.
- g) The scanning resolution shall be sufficient to maintain the measurement uncertainty of the $psPD$ within the stated uncertainty.
- h) At each field probe location, the scanning system shall be capable of keeping the field probe in place for a sufficiently long time with respect to the integration time, as determined according to 8.5.3.

NOTE Scanning over the measurement region can include a combination of fast scans and full scans to reduce the measurement time, as long as this does not increase the measurement uncertainty. See 7.4.1 for more information.

Conformity with these scanning system requirements shall be documented by the manufacturer of the measurement system.

6.5.2 Multiple field-probe systems

The scanning system with multiple field-probes is in general regularly spaced configuration that manages the relative positioning of the field probes with respect to the DUT, such that the measurement region is covered. The requirements of the scanning system are as follows.

- a) The scanning method shall be documented, including whether it performs 2D or 3D scans.
- b) The algorithm for determining the measurement grid, if it does not measure a fixed grid, shall be documented.
- c) The uncertainty of the relative position of the field probes with respect to the DUT shall be within the uncertainty for probe positioning offset (PPO ; see 8.4.8).
- d) The scanning system shall be capable of covering a large enough measurement region such that the $psPD$ can be determined at any point on the evaluation surface.

- e) The accuracy and repeatability of the positioning shall be reported, and they shall be sufficient to ensure that the measurement uncertainty of the *psPD* is within the stated uncertainty. The tolerance of field probe positioning shall also be sufficient to combine exposures from multiple antennas or multiple transmitters (see 7.5).
- f) The scanning system shall be capable of rotating the field probes and/or the DUT, if necessary, to capture the required field components and power densities (i.e. determined using field reconstruction). The accuracy and repeatability of field probes and/or DUT orientation shall be reported.
- g) Minimal separation distance that ensures sufficiently low uncertainty contribution from the probe mutual coupling, such that the maximum expanded uncertainty requirement in 6.1 is met, shall be specified by the system manufacturer.
- h) The scanning resolution shall be sufficient to maintain the measurement uncertainty of the *psPD* within the stated tolerance.
- i) For each acquisition, the scanning system shall be capable of keeping the field probes or the DUT or both in place for a sufficiently long time with respect to the integration time, as determined according to 8.5.3.

NOTE 1 Scanning over the measurement region can include a combination of fast scans and full scans to reduce the measurement time, as long as this does not increase the measurement uncertainty. See 7.4.1 for more information.

NOTE 2 The scanning system can be employed with combination of a DUT positioning system to reduce the measurement uncertainties such as the phase and amplitude variations due to cable bending.

Conformity with these scanning system requirements shall be documented by the manufacturer of the measurement system.

6.6 Device holder requirements

The device holder maintains the DUT in position during the measurement. The requirements of the device holder are as follows.

- a) The positions and orientations shall enable the measurement of the DUT in all required measurement regions.
- b) The device holder shall enable known and repeatable positioning and orientation of the DUT.
- c) The device holder, including its supporting structure, shall be designed to minimize the perturbation of the fields from the DUT. The parts of the device holder that are in direct contact with the DUT shall be made of materials having a loss tangent $\leq 0,05$ and relative permittivity $\leq 1,2$.

This requirement can be suppressed when the device holder is in direct contact with the DUT sufficiently far away from the radiating antenna. Rationale for use of such materials shall be documented in test report.

- d) The reflections due to the device holder structure shall be less than -20 dB at the location of the DUT.
- e) The device holder uncertainty shall be determined according to 8.5.5.

Conformity with these device holder requirements shall be documented by the manufacturer of the measurement system.

6.7 Post-processing quantities, procedures, and requirements

6.7.1 Formulas for calculation of sPD

6.7.1.1 General

The sPD is evaluated at the location r as a function of the complex Poynting vector S . Depending on the dominant direction of incidence and polarization of the electromagnetic field, or with exposure in the near-field of a DUT, 6.7.1.2, 6.7.1.3, and 6.7.1.4 specify the formulas for calculation of sPD for the different specifications of PD. Annex I provides rationales for the distinct PD specifications. Weighting functions in the integrands of Formula (7), Formula (8), and Formula (11) serve to avoid contributions, by scaling down the integrand at these regions to zero, from regions where the power density is oriented outward from the evaluation surface, or due to numerical inaccuracies for surfaces that are almost parallel to the direction of the Poynting vector.

NOTE 1 The formula used to calculate the PD depends on the applicable exposure guidelines or national regulations.

NOTE 2 The direction of the power density relative to the orientation of the evaluation surface was not considered in IEC TR 63170:2018 [10]. For compatibility with results that were assessed according to [10], weighting functions of Formula (8) and Formula (11) are not applied.

6.7.1.2 Surface-normal propagation-direction power density into the evaluation surface – sPD_{n+}

The surface-normal propagation-direction power density into the evaluation surface, sPD_{n+} , shall be calculated according to Formula (7).

$$sPD(r_0) = \frac{1}{\hat{A}(r_0)} \int_{A(r_0)} \Re\{S(r)\} \cdot n_A(r) \cdot \Theta[\Re\{S(r)\} \cdot n_A(r)] d\hat{A}(r) \quad (7)$$

where

- $\Re\{S(r)\}$ is the real part of the complex Poynting vector S at the location r ;
- $n_A(r)$ is the normal vector of the evaluation surface at the location r pointing into the evaluation surface, with $\|n_A(r)\| = 1$;
- $\Theta(x)$ is the Heaviside (unit step) function of x ;
- $\hat{A}(r_0)$ is the evaluation surface at to the location r ;
- r_0 is the location of the centre point.

NOTE 1 The surface normal propagating power density into the evaluation surface as defined in IEC TR 63170:2018 [10] corresponds to sPD_{n+} with $\Theta(x) = 1$.

NOTE 2 Formula (7) corresponds to power density crossing a surface A , i.e. the energy per unit time and unit area crossing a surface of area A_{av} .

6.7.1.3 Total propagating power density into the evaluation surface – $sPD_{\text{tot+}}$

The total propagating power density into the evaluation surface, $sPD_{\text{tot+}}$, shall be calculated according to Formula (8), along with Formula (9) and Formula (10).

$$sPD(r_0) = \frac{1}{\hat{A}(r_0)} \int_{A(r_0)} \left\| \Re\{\mathbf{S}(r)\} \right\| \cdot \Xi\left\{\cos^{-1}[\mathbf{n}_R(r) \cdot \mathbf{n}_A(r)]\right\} d\hat{A}(r) \quad (8)$$

with

$$\mathbf{n}_R(r) = \Re\{\mathbf{S}(r)\} / \left\| \Re\{\mathbf{S}(r)\} \right\| \quad (9)$$

$$\Xi(\theta) = \begin{cases} 1, & 0 \leq \theta < 85^\circ \\ 1 - (\theta - 85^\circ)/5^\circ, & 85^\circ \leq \theta < 90^\circ \\ 0, & \theta \geq 90^\circ \end{cases} \quad (10)$$

$\left\| \Re\{\mathbf{S}(r)\} \right\|$ is the magnitude of the real part of the complex Poynting vector $\mathbf{S}$ at the location r

and the other terms are as specified in 6.7.1.2.

NOTE 1 The total propagating power density into the evaluation surface as defined in IEC TR 63170:2018 [10] corresponds to $sPD_{\text{tot+}}$ with $\Xi(\theta) = 1$.

NOTE 2 Formula (8) corresponds to magnitude of the real part of the Poynting vector on a surface A , i.e. an overestimation of results using Formula (7).

6.7.1.4 Total power density into the evaluation surface considering reactive near-field effects – $sPD_{\text{mod+}}$

The quantity $sPD_{\text{mod+}}$ is based on the total power density, and considers also the imaginary part of the Poynting vector to account for non-propagating energy transfer in the reactive near-field. It shall be calculated according to Formula (11).

$$sPD(r_0) = \frac{1}{\hat{A}(r_0)} \int_{A(r_0)} \left[\left(\left\| \Re\{\mathbf{S}(r)\} \right\| \cdot \Xi\left\{\cos^{-1}[\mathbf{n}_R(r) \cdot \mathbf{n}_A(r)]\right\} \right)^2 + \left(\left\| \Im\{\mathbf{S}(r)\} \right\| \right)^2 \right]^{1/2} d\hat{A}(r) \quad (11)$$

$\left\| \Im\{\mathbf{S}(r)\} \right\|$ is the magnitude of the imaginary part of the complex Poynting vector $\mathbf{S}$ at the location r

and the other terms are as specified in 6.7.1.3.

NOTE Formula (11) corresponds to magnitude of the Poynting vector (real and imaginary parts) on a surface A , i.e. an overestimation of results using Formula (7) and Formula (8).

6.7.2 Post-processing procedure

Post processing shall include the following steps:

- a) determination of the Poynting vector on the evaluation surface (e.g. using field reconstruction algorithms). Where the plane-wave equivalent approximation is valid (see 7.4.2.1), the power density can be directly computed by measurement of the E-field magnitude or H-field magnitude using the far-field characteristic impedance η_0 ;
- b) determination of the power density from the Poynting vector according to Formula (7), Formula (8), and Formula (11). As example, according to Formula (8), the power density is obtained from the Poynting vector using Formula (12):

$$S_{\text{tot}} = \frac{1}{2} \text{Re} \left\{ (E_y H_z^* - E_z H_y^*) \hat{x} + (E_z H_x^* - E_x H_z^*) \hat{y} + (E_x H_y^* - E_y H_x^*) \hat{z} \right\} \quad (12)$$

where

$$\mathbf{E} = [\text{Re}(E_x) + j\text{Im}(E_x)] \hat{x} + [\text{Re}(E_y) + j\text{Im}(E_y)] \hat{y} + [\text{Re}(E_z) + j\text{Im}(E_z)] \hat{z}$$

$$\mathbf{H} = [\text{Re}(H_x) + j\text{Im}(H_x)] \hat{x} + [\text{Re}(H_y) + j\text{Im}(H_y)] \hat{y} + [\text{Re}(H_z) + j\text{Im}(H_z)] \hat{z}$$

Formula (12) can also be written as shown by Formula (13):

$$S_{\text{tot}} = \sqrt{S_x^2 + S_y^2 + S_z^2} \quad (13)$$

where

$$S_x = \frac{1}{2} \text{Re} (E_y H_z^* - E_z H_y^*)$$

$$S_y = \frac{1}{2} \text{Re} (E_z H_x^* - E_x H_z^*)$$

$$S_z = \frac{1}{2} \text{Re} (E_x H_y^* - E_y H_x^*)$$


- c) spatial averaging of the power density over the required averaging area to determine the *sPD* on the evaluation surface, in accordance with 8.4 of IEC/IEEE 63195-2:2021. The rationale for use of square or circular shapes for power density averaging area in conformity evaluations is provided in Annex D;

NOTE 1 It is possible that applicable national regulations or exposure standards provide a different definition or interpretation for PD.

- d) determination of *psPD*, the peak value of the *sPD*, and any secondary peak spatial-average power density values (secondary peaks).

NOTE 2 Secondary peak measurements are not required if the *sPD* is determined on the entire evaluation surface.

Field reconstruction algorithms may be used to transform the measured fields in the measurement region to the Poynting vector on the evaluation surface (Figure 2) with known uncertainty. This may include intermediate steps such as calculating the H-field from the E-field (or vice versa) or retrieving field components and power densities from the measured data (e.g. the phase from the amplitude). See Annex E for more information on field reconstruction methods.



NOTE The measurement and evaluation surface dimensions, and their orientations and positions, are simplified for illustration purposes (see 7.2.4 for additional information).

Figure 2 – Simplified view of a generic measurement setup involving the use of reconstruction algorithms

6.7.3 Requirements

The following requirements apply to the post-processing.

- The power density on the entire evaluation surface shall be determined from the field measurements on the measurement region (e.g. using field reconstruction) with sufficient resolution to ensure that the *psPD* uncertainty is within the value stated by the system manufacturer.
- The power density shall be determined from the Poynting vector (unless the plane-wave equivalent approximation is valid).
- The power density shall be spatially averaged over the specified averaging area (e.g. 1 cm² and/or 4 cm²) of the relevant exposure standard or national regulations.
- The values and locations of the *psPD* and any secondary peaks shall be recorded. Alternatively, the *sPD* distribution shall be provided.
- The uncertainty of the post-processor shall be determined.
- The limitations for which the uncertainty is valid shall be assessed (e.g. with respect to frequency, measurement region, etc.).
- The post-processing methods shall be documented by the system manufacturer including uncertainty and limitations.

Conformity with these post-processing requirements shall be documented by the manufacturer of the measurement system.

7 Protocol for PD assessment

7.1 General

A high-level flow-chart of the evaluation process for power density assessment is shown in Clause 5. Beginning with an evaluation plan and measurement approach, the process converges to the full power density evaluation and uncertainty analysis. Documentation and reporting complete the evaluation process.

NOTE This document does not contain information needed to configure DUTs for specific wireless technologies, including specific settings such as the operating mode or data rate to ensure that the maximum PD is obtained.

7.2 Measurement preparation

7.2.1 Relative system check

A relative system check according to the procedures of Clause A.3 shall be completed before performing PD assessment for a DUT. The relative system check evaluates field probe function, field probe calibration, scanning system, measurement instrumentation and post-processing. The requirements on relative system check are as follows.

- a) If the relative system check uses a source that does not have a traceable absolute target value, ensure that an absolute system check has been performed according to Clause A.4, or relative system check target value has been determined after the system validation or after the absolute system check at user site.
- b) The relative system check procedure shall be performed on the same PD measurement system used for evaluation of the DUT (see 7.4).
- c) The relative system check shall be performed such that all elements of the measurement system are valid for the DUT to be measured (e.g. if the verification is performed at a different frequency than the test frequency bands of the DUT, then the calibration parameters used in the verification shall be valid for the test frequencies).
- d) The relative system check shall meet the acceptability criteria in A.3.4.

NOTE 1 Because an absolute system check test fulfils all the requirements, an absolute system check test can also be performed instead of a relative system check.

NOTE 2 In case the system is based on a frequency-continuous sensor model valid over the entire frequency range, it is sufficient to perform the system check at the closest frequency of the verification antennas specified in Annex B. In case the system is based on a narrow frequency calibration, the verification is performed within the centre frequency of the measured DUT band $\pm 15\%$.

7.2.2 DUT requirements

The requirements of the DUT are as follows.

- a) The antenna(s), battery and accessories shall be those specified in the user manual. If this information is not available in the user manual, DUT should be equivalent to production line samples to be sold on the market. Accessories that have been approved for use with the DUT by the device manufacturer shall also be considered (e.g. additional accessories that are available on the manufacturer's website that have been approved for use with the DUT). They shall be documented in the measurement report.
- b) All antennas, their location and size, including arrays and sub-arrays, shall be identified.
- c) The battery shall be fully charged before each measurement and no external connections or cables affecting the result shall be used.

A lower battery level, not less than 60 %, is allowed provided it is demonstrated that the power level has not dropped by more than the DUT drift uncertainty.
- d) When national regulatory agencies allow tests to be performed on prototypes, verification shall be undertaken by the device manufacturer to ensure the commercial version has the exact same mechanical, electrical, and operating characteristics as the tested prototype. Where this cannot be guaranteed, testing shall be repeated by sampling of unmodified commercial product versions.

- e) Accessories that can affect the RF output power or RF current distribution of the DUT shall be tested according to the intended use conditions.
- f) Transmitters operating, for example, below 6 GHz can influence the PD of the transmitters due to coupling with the probe, etc., and such influences shall be taken into account. If the coupling from other active transmitters cannot be filtered out (e.g. frequency-selective measurement system), other transmitters shall be inactive during the measurement.

7.2.3 DUT preparation

The following requirements apply when preparing the DUT for testing.

- a) The RF output power and frequency (channel) shall be controlled either by a wireless link or test mode software (active mode). Alternatively, an external generator or a synthesiser and amplifier may be used to replace the transmitter (passive mode), provided that both the measured fields and the power density assessment of the DUT are unaffected, and the impact on power density assessment uncertainty is properly evaluated and remains acceptable. The power chains to all transmitting elements of the antenna array(s) shall be evaluated to accurately determine the input power fed to the antenna.

NOTE 1 National regulations can exist regarding the use of an external generator or a synthesiser and amplifier in place of the transmitter.

NOTE 2 In practice it can be difficult to use external signal generators, etc., to replace a DUT and have the same field distribution.

- b) When beamforming is supported by the device, the beam shall be fixed for the duration of the PD evaluation, to facilitate consistent results.
- c) Record the maximum time-averaged output power of the DUT for each tested frequency band and operating mode. If power scaling is obtained using call handling (see 7.4.3.2), record the time-averaged output powers of N_c channels as specified in 7.4.3.3 for each tested frequency band.

NOTE 2 The maximum time-averaged power of the DUT can be verified, e.g. if applicable, by conducted power measurements with a fully charged battery or, according to radiated power measurements and other operating parameters to support the scaling.

- d) If performing measurement of simultaneous transmission of uncorrelated or Type 2 correlated signals (see 7.5), establish the maximum output power for each transmitter and antenna as described in step a) to ensure the aggregate transmit power from all antennas is also at the maximum.
- e) If the DUT is capable of controlling its transmit power over time to maintain the time-average power density below the applicable limit, the time period averaging procedure in IEC/IEEE 62209-1528:2020 may be applied. If the frequency and relative phase between transmitting elements is kept constant, it is sufficient to measure the amplitude of the E-field, H-field, or Poynting vector at a fixed location. Otherwise the power density shall be measured at the evaluation surfaces. The relevant time-averaging period or periods is/are specified in accordance with international guidelines (e.g. ICNIRP [2]) or national regulations. The time-averaging test procedure in IEC/IEEE 62209-1528:2020 only applies to devices that have network-independent capability to control transmission power over specific durations and intervals.

NOTE 3 Some regulatory authorities can have other or different requirements for PD measurements of devices supporting power control and time averaging.

- f) Record whether proximity sensors are used to lower the output power and the DUT positions and operating modes where proximity sensor activation applies. Verify whether the proximity sensor activation or deactivation is affected by the measurement system. In case the proximity sensor system is affected, either the proximity sensor shall be forced into activation or deactivation mode using test software, as appropriate, or when possible the measurement shall be taken in a separation distance at which the proximity system is not affected. The procedures of 7.7 in IEC/IEEE 62209-1528:2020 may be used to determine the proximity sensor triggering distances. If the proximity sensor performs or triggers time period averaging, the proximity sensor procedure in IEC/IEEE 62209-1528:2020 may be applied with time period averaging deactivated.