

INTERNATIONAL STANDARD

NORME INTERNATIONALE

**Safety of machinery – Electrical equipment of machines –
Part 1: General requirements**

**Sécurité des machines – Equipement électrique des machines –
Partie 1: Règles générales**



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2005 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester.

If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de la CEI ou du Comité national de la CEI du pays du demandeur.

Si vous avez des questions sur le copyright de la CEI ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de la CEI de votre pays de résidence.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland
Email: inmail@iec.ch
Web: www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

- Catalogue of IEC publications: www.iec.ch/searchpub

The IEC on-line Catalogue enables you to search by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, withdrawn and replaced publications.

- IEC Just Published: www.iec.ch/online_news/justpub

Stay up to date on all new IEC publications. Just Published details twice a month all new publications released. Available on-line and also by email.

- Electropedia: www.electropedia.org

The world's leading online dictionary of electronic and electrical terms containing more than 20 000 terms and definitions in English and French, with equivalent terms in additional languages. Also known as the International Electrotechnical Vocabulary online.

- Customer Service Centre: www.iec.ch/webstore/custserv

If you wish to give us your feedback on this publication or need further assistance, please visit the Customer Service Centre FAQ or contact us:

Email: csc@iec.ch
Tel.: +41 22 919 02 11
Fax: +41 22 919 03 00

A propos de la CEI

La Commission Electrotechnique Internationale (CEI) est la première organisation mondiale qui élabore et publie des normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

A propos des publications CEI

Le contenu technique des publications de la CEI est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

- Catalogue des publications de la CEI: www.iec.ch/searchpub/cur_fut-f.htm

Le Catalogue en-ligne de la CEI vous permet d'effectuer des recherches en utilisant différents critères (numéro de référence, texte, comité d'études,...). Il donne aussi des informations sur les projets et les publications retirées ou remplacées.

- Just Published CEI: www.iec.ch/online_news/justpub

Restez informé sur les nouvelles publications de la CEI. Just Published détaille deux fois par mois les nouvelles publications parues. Disponible en-ligne et aussi par email.

- Electropedia: www.electropedia.org

Le premier dictionnaire en ligne au monde de termes électroniques et électriques. Il contient plus de 20 000 termes et définitions en anglais et en français, ainsi que les termes équivalents dans les langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International en ligne.

- Service Clients: www.iec.ch/webstore/custserv/custserv_entry-f.htm

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions, visitez le FAQ du Service clients ou contactez-nous:

Email: csc@iec.ch
Tél.: +41 22 919 02 11
Fax: +41 22 919 03 00



IEC 60204-1

Edition 5.0 2005-10

INTERNATIONAL STANDARD

NORME INTERNATIONALE

**Safety of machinery – Electrical equipment of machines –
Part 1: General requirements**

**Sécurité des machines – Equipement électrique des machines –
Partie 1: Règles générales**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

COMMISSION
ELECTROTECHNIQUE
INTERNATIONALE

PRICE CODE
CODE PRIX

XF

ICS 29.020

ISBN 2-8318-8203-6

CONTENTS

FOREWORD.....	8
INTRODUCTION.....	9
1 Scope.....	11
2 Normative references.....	12
3 Definitions	14
4 General requirements	21
4.1 General considerations	21
4.2 Selection of equipment	22
4.3 Electrical supply	23
4.4 Physical environment and operating conditions	24
4.5 Transportation and storage	26
4.6 Provisions for handling	26
4.7 Installation.....	26
5 Incoming supply conductor terminations and devices for disconnecting and switching off	26
5.1 Incoming supply conductor terminations.....	26
5.2 Terminal for connection to the external protective earthing system	27
5.3 Supply disconnecting (isolating) device	27
5.4 Devices for switching off for prevention of unexpected start-up.....	30
5.5 Devices for disconnecting electrical equipment	30
5.6 Protection against unauthorized, inadvertent and/or mistaken connection.....	31
6 Protection against electric shock.....	31
6.1 General	31
6.2 Protection against direct contact	31
6.3 Protection against indirect contact	34
6.4 Protection by the use of PELV.....	35
7 Protection of equipment	36
7.1 General	36
7.2 Overcurrent protection	36
7.3 Protection of motors against overheating	39
7.4 Abnormal temperature protection	40
7.5 Protection against supply interruption or voltage reduction and subsequent restoration	40
7.6 Motor overspeed protection.....	41
7.7 Earth fault/residual current protection.....	41
7.8 Phase sequence protection.....	41
7.9 Protection against overvoltages due to lightning and to switching surges	41
8 Equipotential bonding	41
8.1 General	41
8.2 Protective bonding circuit.....	44
8.3 Functional bonding	47
8.4 Measures to limit the effects of high leakage current	47

9	Control circuits and control functions.....	47
9.1	Control circuits	47
9.2	Control functions	48
9.3	Protective interlocks	53
9.4	Control functions in the event of failure	54
10	Operator interface and machine-mounted control devices.....	58
10.1	General	58
10.2	Push-buttons	59
10.3	Indicator lights and displays	61
10.4	Illuminated push-buttons	62
10.5	Rotary control devices	62
10.6	Start devices	62
10.7	Emergency stop devices	62
10.8	Emergency switching off devices	63
10.9	Enabling control device	64
11	Controlgear: location, mounting, and enclosures	64
11.1	General requirements	64
11.2	Location and mounting.....	64
11.3	Degrees of protection	66
11.4	Enclosures, doors and openings	66
11.5	Access to controlgear	67
12	Conductors and cables	68
12.1	General requirements	68
12.2	Conductors	68
12.3	Insulation.....	69
12.4	Current-carrying capacity in normal service	69
12.5	Conductor and cable voltage drop	70
12.6	Flexible cables.....	71
12.7	Conductor wires, conductor bars and slip-ring assemblies	72
13	Wiring practices	74
13.1	Connections and routing	74
13.2	Identification of conductors	75
13.3	Wiring inside enclosures	77
13.4	Wiring outside enclosures	77
13.5	Ducts, connection boxes and other boxes	80
14	Electric motors and associated equipment	82
14.1	General requirements	82
14.2	Motor enclosures	83
14.3	Motor dimensions	83
14.4	Motor mounting and compartments	83
14.5	Criteria for motor selection.....	83
14.6	Protective devices for mechanical brakes.....	84
15	Accessories and lighting	84
15.1	Accessories	84
15.2	Local lighting of the machine and equipment	84

16	Marking, warning signs and reference designations	85
16.1	General	85
16.2	Warning signs	86
16.3	Functional identification	86
16.4	Marking of equipment	86
16.5	Reference designations	87
17	Technical documentation	87
17.1	General	87
17.2	Information to be provided	87
17.3	Requirements applicable to all documentation	88
17.4	Installation documents	88
17.5	Overview diagrams and function diagrams	89
17.6	Circuit diagrams	89
17.7	Operating manual	90
17.8	Maintenance manual	90
17.9	Parts list	90
18	Verification	90
18.1	General	90
18.2	Verification of conditions for protection by automatic disconnection of supply	91
18.3	Insulation resistance tests	94
18.4	Voltage tests	95
18.5	Protection against residual voltages	95
18.6	Functional tests	95
18.7	Retesting	95
	Annex A (normative) Protection against indirect contact in TN-systems	96
	Annex B (informative) Enquiry form for the electrical equipment of machines	100
	Annex C (informative) Examples of machines covered by this part of IEC 60204	104
	Annex D (informative) Current-carrying capacity and overcurrent protection of conductors and cables in the electrical equipment of machines	106
	Annex E (informative) Explanation of emergency operation functions	112
	Annex F (informative) Guide for the use of this part of IEC 60204	113
	Annex G (informative) Comparison of typical conductor cross-sectional areas	115
	Bibliography	117
	Index	119
	Figure 1 – Block diagram of a typical machine	10
	Figure 2 – Example of equipotential bonding for electrical equipment of a machine	43
	Figure 3 – Method a)	57
	Figure 4 – Method b)	57
	Figure A.1 – Typical arrangement for fault loop impedance measurement	99
	Figure D.1 – Methods of conductor and cable installation independent of number of conductors/cables	107
	Figure D.2 – Parameters of conductors and protective devices	109

Table 1 – Minimum cross-sectional area of the external protective copper conductor	27
Table 2 – Colour-coding for push-button actuators and their meanings	60
Table 3 – Symbols for push-buttons	60
Table 4 – Colours for indicator lights and their meanings with respect to the condition of the machine	61
Table 5 – Minimum cross-sectional areas of copper conductors	68
Table 6 – Examples of current-carrying capacity (I_Z) of PVC insulated copper conductors or cables under steady-state conditions in an ambient air temperature of +40 °C for different methods of installation	70
Table 7 – Derating factors for cables wound on drums	72
Table 8 – Minimum permitted bending radii for the forced guiding of flexible cables	79
Table 9 – Application of the test methods for TN-systems	93
Table 10 – Examples of maximum cable length from each protective device to its load	94
Table A.1 – Maximum disconnecting times for TN systems	96
Table D.1 – Correction factors	106
Table D.2 – Derating factors from I_Z for grouping	108
Table D.3 – Derating factors from I_Z for multicore cables up to 10 mm ²	108
Table D.4 – Classification of conductors	109
Table D.5 – Maximum allowable conductor temperatures under normal and short-circuit conditions	110
Table F.1 – Application options	114
Table G.1 – Comparison of conductor sizes	115

INTERNATIONAL ELECTROTECHNICAL COMMISSION

SAFETY OF MACHINERY – ELECTRICAL EQUIPMENT OF MACHINES –

Part 1: General requirements

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC provides no marking procedure to indicate its approval and cannot be rendered responsible for any equipment declared to be in conformity with an IEC Publication.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 60204-1 has been prepared by technical committee 44: Safety of machinery – Electrotechnical aspects.

This fifth edition cancels and replaces the fourth edition issued in 1997 and Amendment 1 (1999). This edition constitutes a technical revision. It incorporates material from the fourth edition, amended to provide general requirements for machines, including mobile machines and complex (for example large) machine installations.

The text of this standard is based on the following documents:

FDIS	Report on voting
44/494/FDIS	44/502/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

The following differences exist in some countries:

- 4.3.1: The voltage characteristics of electricity supplied by public distribution systems in Europe are given in EN 50160:1999.
- 5.1: Exception is not allowed (USA).
- 5.1: TN-C systems are not permitted in low-voltage installations in buildings (Norway).
- 5.2: Terminals for the connection of the protective earthing conductors may be identified by the colour green, the letters “G” or “GR” or “GRD” or “GND”, or the word “ground” or “grounding”, or with the graphical symbol IEC 60417-5019 (DB: 2002-10) or any combination (USA).
- 6.3.3 b), 13.4.5 b), 18.2.1: TT power systems are not allowed (USA).
- 7.2.3: Disconnection of the neutral conductor is mandatory in a TN-S system (France and Norway).
- 7.2.3: Third paragraph: distribution of a neutral conductor with an IT system is not allowed (USA and Norway).
- 9.1.2: Maximum nominal a.c. control circuit voltage is 120 V (USA).
- 12.2: Only stranded conductors are allowed on machines, except for 0,2 mm² solid conductors within enclosures (USA).
- 12.2: The smallest power circuit conductor allowed on machines is 0,82 mm² (AWG 18) in multiconductor cables or in enclosures (USA).
- Table 5: Cross-sectional area is specified in ANSI/NFPA 79 using American Wire Gauge (AWG) (USA). See Annex G.
- 13.2.2: For the protective conductor, the colour identification GREEN (with or without YELLOW stripes) is used as equivalent to the bicolour combination GREEN-AND-YELLOW (USA and Canada).
- 13.2.3: The colour identification WHITE or GREY is used for earthed neutral conductors instead of the colour identification BLUE (USA and Canada).
- 15.2.2: First paragraph: Maximum value between conductors 150 V (USA).
- 15.2.2: 2nd paragraph, 5th bullet: The full load current rating of lighting circuits does not exceed 15 A (USA).
- 16.4: Nameplate marking requirements (USA).

IEC 60204 consists of the following parts, under the general title *Safety of machinery – Electrical equipment of machines*:

- Part 1: General requirements
- Part 11: Requirements for HV equipment for voltages above 1 000 V a.c. or 1 500 V d.c. and not exceeding 36 kV
- Part 31: Particular safety and EMC requirements for sewing machines, units and systems
- Part 32: Requirements for hoisting machines
- Part 33: Particular requirements for semiconductor manufacturing equipment¹

The committee has decided that the contents of this publication will remain unchanged until the maintenance result date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed;
- withdrawn;
- replaced by a revised edition, or
- amended.

¹ Under consideration.


INTRODUCTION

This part of IEC 60204 provides requirements and recommendations relating to the electrical equipment of machines so as to promote:

- safety of persons and property;
- consistency of control response;
- ease of maintenance.

More guidance on the use of this part of IEC 60204 is given in Annex F.

Figure 1 has been provided as an aid to the understanding of the inter-relationship of the various elements of a machine and its associated equipment. Figure 1 is a block diagram of a typical machine and associated equipment showing the various elements of the electrical equipment addressed in this part of IEC 60204. Numbers in parentheses () refer to Clauses and Subclauses in this part of IEC 60204. It is understood in Figure 1 that all of the elements taken together including the safeguards, tooling/fixturing, software, and the documentation, constitute the machine, and that one or more machines working together with usually at least one level of supervisory control constitute a manufacturing cell or system.



IEC 1388/05

Figure 1 – Block diagram of a typical machine

SAFETY OF MACHINERY – ELECTRICAL EQUIPMENT OF MACHINES –

Part 1: General requirements

1 Scope

This part of IEC 60204 applies to the application of electrical, electronic and programmable electronic equipment and systems to machines not portable by hand while working, including a group of machines working together in a co-ordinated manner.

NOTE 1 This part of IEC 60204 is an application standard and is not intended to limit or inhibit technological advancement.

NOTE 2 In this part of IEC 60204, the term *electrical* includes electrical, electronic and programmable electronic matters (i.e. *electrical equipment* means electrical, electronic and programmable electronic equipment).

NOTE 3 In the context of this part of IEC 60204, the term *person* refers to any individual and includes those persons who are assigned and instructed by the user or his agent(s) in the use and care of the machine in question.

The equipment covered by this part of IEC 60204 commences at the point of connection of the supply to the electrical equipment of the machine (see 5.1).

NOTE 4 The requirements for the electrical supply installation in buildings are given in the IEC 60364 series.

This part of IEC 60204 is applicable to the electrical equipment or parts of the electrical equipment that operate with nominal supply voltages not exceeding 1 000 V for alternating current (a.c.) and not exceeding 1 500 V for direct current (d.c.), and with nominal supply frequencies not exceeding 200 Hz.

NOTE 5 For higher voltages, see IEC 60204-11.

This part of IEC 60204 does not cover all the requirements (for example guarding, interlocking, or control) that are needed or required by other standards or regulations in order to protect persons from hazards other than electrical hazards. Each type of machine has unique requirements to be accommodated to provide adequate safety.

This part specifically includes, but is not limited to, the electrical equipment of machines as defined in 3.35.

NOTE 6 Annex C lists examples of machines whose electrical equipment can be covered by this part of IEC 60204.

This part of IEC 60204 does not specify additional and special requirements that can apply to the electrical equipment of machines that, for example:

- are intended for use in open air (i.e. outside buildings or other protective structures);
- use, process, or produce potentially explosive material (for example paint or sawdust);
- are intended for use in potentially explosive and/or flammable atmospheres;
- have special risks when producing or using certain materials;
- are intended for use in mines;

- are sewing machines, units, and systems (which are covered by IEC 60204-31);
- are hoisting machines (which are covered by IEC 60204-32).

Power circuits where electrical energy is directly used as a working tool are excluded from this part of IEC 60204.

2 Normative references

The following referenced documents are indispensable for the application of this part of IEC 60204. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60034-1, *Rotating electrical machines – Part 1: Rating and performance*

IEC 60034-5, *Rotating electrical machines – Part 5: Degrees of protection provided by the integral design of rotating electrical machines (IP code) – Classification*

IEC 60034-11, *Rotating electrical machines – Part 11: Thermal protection*

IEC 60072-1, *Dimensions and output series for rotating electrical machines – Part 1: Frame numbers 56 to 400 and flange numbers 55 to 1 080*

IEC 60072-2, *Dimensions and output series for rotating electrical machines – Part 2: Frame numbers 355 to 1 000 and flange numbers 1 180 to 2 360*

IEC 60073:2002, *Basic and safety principles for man-machine interface, marking and identification – Coding principles for indicators and actuators*

IEC 60309-1:1999, *Plugs, socket-outlets, and couplers for industrial purposes – Part 1: General requirements*

IEC 60364-4-41:2001, *Electrical installations of buildings – Part 4-41: Protection for safety – Protection against electric shock*

IEC 60364-4-43:2001, *Electrical installations of buildings – Part 4-43: Protection for safety – Protection against overcurrent*

IEC 60364-5-52:2001, *Electrical installations of buildings – Part 5-52: Selection and erection of electrical equipment – Wiring systems*

IEC 60364-5-53:2002, *Electrical installations of buildings – Part 5-53: Selection and erection of electrical equipment – Isolation, switching and control*

IEC 60364-5-54:2002, *Electrical installations of buildings – Part 5-54: Selection and erection of electrical equipment – Earthing arrangements, protective conductors and protective bonding conductors*

IEC 60364-6-61:2001, *Electrical installations of buildings – Part 6-61: Verification – Initial verification*

IEC 60417-DB:2002², *Graphical symbols for use on equipment*

² “DB” refers to the IEC on-line database.

IEC 60439-1:1999, *Low-voltage switchgear and controlgear assemblies – Part 1: Type-tested and partially type-tested assemblies*

IEC 60445:1999, *Basic and safety principles for man-machine interface, marking and identification – Identification of equipment terminals and of terminations of certain designated conductors, including general rules for an alphanumeric system*

IEC 60446:1999, *Basic and safety principles for man-machine interface, marking and identification – Identification of conductors by colours or numerals*

IEC 60447:2004, *Basic and safety principles for man-machine interface, marking and identification – Man-machine interface (MMI) – Actuating principles*

IEC 60529:1999, *Degrees of protection provided by enclosures (IP Code)*
Amendment 1 (2001)

IEC 60617-DB:2001³, *Graphical symbols for diagrams*

IEC 60621-3:1979, *Electrical installations for outdoor sites under heavy conditions (including open-cast mines and quarries) – Part 3: General requirements for equipment and ancillaries*

IEC 60664-1:1992, *Insulation co-ordination for equipment within low-voltage systems – Part 1: Principles, requirements and tests*

IEC 60947-1:2004, *Low-voltage switchgear and controlgear – Part 1: General rules*

IEC 60947-2:2003, *Low-voltage switchgear and controlgear – Part 2: Circuit-breakers*

IEC 60947-3:1999, *Low-voltage switchgear and controlgear – Part 3: Switches, disconnectors, switch-disconnectors, and fuse combination units*

IEC 60947-5-1:2003, *Low-voltage switchgear and controlgear – Part 5-1: Control circuit devices and switching elements – Electromechanical control circuit devices*

IEC 60947-7-1:2002, *Low-voltage switchgear and controlgear – Part 7-1: Ancillary equipment – Terminal blocks for copper conductors*

IEC 61082-1:1991, *Preparation of documents used in electrotechnology – Part 1: General requirements*

IEC 61082-2:1993, *Preparation of documents used in electrotechnology – Part 2: Function-oriented diagrams*

IEC 61082-3:1993, *Preparation of documents used in electrotechnology – Part 3: Connection diagrams, tables and lists*

IEC 61082-4:1996, *Preparation of documents used in electrotechnology – Part 4: Location and installation documents*

IEC 61140:2001, *Protection against electric shock – Common aspects for installation and equipment*

IEC 61310 (all parts), *Safety of machinery – Indication, marking and actuation*

IEC 61346 (all parts), *Industrial systems, installations and equipment and industrial products – Structuring principles and reference designations*

³ “DB” refers to the IEC on-line database.

IEC 61557-3:1997, *Electrical safety in low voltage distribution systems up to 1000 V a.c. and 1500 V d.c. – Equipment for testing, measuring or monitoring of protective measures – Part 3: Loop impedance*

IEC 61558-1:1997, *Safety of power transformers, power supply units and similar – Part 1: General requirements and tests*
Amendment 1 (1998)

IEC 61558-2-6, *Safety of power transformers, power supply units and similar – Part 2-6: Particular requirements for safety isolating transformers for general use*

IEC 61984:2001, *Connectors – Safety requirements and tests*

IEC 62023:2000, *Structuring of technical information and documentation*

IEC 62027:2000, *Preparation of parts lists*

IEC 62061:2005, *Safety of machinery – Functional safety of safety-related electrical, electronic and programmable electronic control systems*

IEC 62079:2001, *Preparation of instructions – Structuring, content and presentation*

ISO 7000:2004, *Graphical symbols for use on equipment – Index and synopsis*

ISO 12100-1:2003, *Safety of machinery – Basic concepts, general principles for design – Part 1: Basic terminology, methodology*

ISO 12100-2:2003, *Safety of machinery – Basic concepts, general principles for design – Part 2: Technical principles*

ISO 13849-1:1999, *Safety of machinery – Safety-related parts of control systems – Part 1: General principles for design*

ISO 13849-2:2003, *Safety of machinery – Safety-related parts of control systems – Part 2: Validation*

ISO 13850:1996, *Safety of machinery – Emergency stop – Principles for design*

3 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

3.1

actuator

part of a device to which an external manual action is to be applied

NOTE 1 The actuator may take the form of a handle, knob, push-button, roller, plunger, etc.

NOTE 2 There are some actuating means that do not require an external actuating force, but only an action.

NOTE 3 See also 3.34.

3.2

ambient temperature

temperature of the air or other medium where the equipment is to be used

3.3

barrier

part providing protection against direct contact from any usual direction of access

3.4**cable tray**

cable support consisting of a continuous base and raised edges and no covering

NOTE A cable tray may be perforated or non-perforated.

[IEV 826-15-08]

3.5**cable trunking system**

system of closed enclosures comprising a base with a removable cover intended for the complete surrounding of insulated conductors, cables, cords and for the accommodation of other electrical equipment

3.6**concurrent**

acting in conjunction; used to describe a situation wherein two or more control devices exist in an actuated condition at the same time (but not necessarily synchronously)

3.7**conduit**

part of a closed wiring system of circular or non-circular cross-section for insulated conductors and/or cables in electrical installations, allowing them to be drawn in and/or replaced

NOTE Conduits should be sufficiently close-jointed so that the insulated conductors and/or cables can only be drawn in and not inserted laterally.

[IEV 826-06-03]

3.8**control circuit (of a machine)**

circuit used for the control, including monitoring, of a machine and the electrical equipment

3.9**control device**

device connected into the control circuit and used for controlling the operation of the machine (for example position sensor, manual control switch, relay, contactor, magnetically operated valve)

3.10**controlgear**

switching devices and their combination with associated control, measuring, protective, and regulating equipment, also assemblies of such devices and equipment with associated interconnections, accessories, enclosures, and supporting structures, intended in principle for the control of electrical energy consuming equipment

[IEV 441-11-03, modified]

3.11**controlled stop**

stopping of machine motion with electrical power to the machine actuators maintained during the stopping process

3.12**direct contact**

contact of persons or livestock with live parts

[IEV 826-12-03]

3.13

direct opening action (of a contact element)

achievement of contact separation as the direct result of a specified movement of the switch actuator through non-resilient members (for example not dependent upon springs)

[IEC 60947-5-1, K.2.2]

3.14

duct

enclosed channel designed expressly for holding and protecting electrical conductors, cables, and busbars

NOTE Conduits (see 3.7), cable trunking systems (see 3.5) and underfloor channels are types of duct.

3.15

electrical operating area

room or location for electrical equipment to which access is intended to be restricted to skilled or instructed persons, by the opening of a door or the removal of a barrier without the use of a key or tool, and which is clearly marked by appropriate warning signs

3.16

electronic equipment

part of the electrical equipment containing circuitry dependent for its operation on electronic devices and components

3.17

emergency stop device

manually actuated control device used to initiate an emergency stop function

[ISO 13850, 3.2]

NOTE See Annex E.

3.18

emergency switching off device

manually actuated control device used to switch off the supply of electrical energy to all or a part of an installation where a risk of electric shock or another risk of electrical origin is involved

NOTE See Annex E.

3.19

enclosed electrical operating area

room or location for electrical equipment to which access is intended to be restricted to skilled or instructed persons by the opening of a door or the removal of a barrier by the use of a key or tool and which is clearly marked by appropriate warning signs

3.20

enclosure

part providing protection of equipment against certain external influences and, in any direction, protection against direct contact

NOTE The definition taken from the existing IEC 60204-1 needs the following explanations within the scope of this part of IEC 60204:

a) Enclosures provide protection of persons or livestock against access to hazardous parts.

- b) Barriers, shaped openings, or any other means suitable to prevent or limit the penetration of the specified test probes, whether attached to the enclosure or formed by the enclosed equipment, are considered as part of the enclosure, except where they can be removed without the use of a key or tool.
- c) An enclosure may be:
 - a cabinet or box, either mounted on the machine or separate from the machine;
 - a compartment consisting of an enclosed space within the machine structure.

3.21

equipment

material, fittings, devices, components, appliances, fixtures, apparatus, and the like used as part of, or in connection with, the electrical equipment of machines

3.22

equipotential bonding

provision of electric connections between conductive parts, intended to achieve equipotentiality

[IEV 195-1-10]

3.23

exposed conductive part

conductive part of electrical equipment, which can be touched and which is not live under normal operating conditions, but which can become live under fault conditions

[IEV 826-12-10, modified]

3.24

extraneous conductive part

conductive part not forming part of the electrical installation and liable to introduce a potential, generally the earth potential

[IEV 826-12-11, modified]

3.25

failure

termination of the ability of an item to perform a required function

NOTE 1 After failure, the item has a fault.

NOTE 2 "Failure" is an event, as distinguished from "fault", which is a state.

NOTE 3 This concept as defined does not apply to items consisting of software only.

[IEV 191-04-01]

NOTE 4 In practice, the terms fault and failure are often used synonymously.

3.26

fault

state of an item characterized by inability to perform a required function, excluding the inability during preventive maintenance or other planned actions, or due to lack of external resources

NOTE 1 A fault is often the result of a failure of the item itself, but may exist without prior failure.

NOTE 2 In English, the term "fault" and its definition are identical with those given in IEC 191-05-01. In the field of machinery, the French term "défaut" and the German term "Fehler" are used rather than the terms "panne" and "Fehlzustand" that appear with this definition.

3.27

functional bonding

equipotential bonding necessary for proper functioning of electrical equipment

3.28

hazard

potential source of physical injury or damage to health

NOTE 1 The term hazard can be qualified in order to define its origin (for example, mechanical hazard, electrical hazard) or the nature of the potential harm (for example, electric shock hazard, cutting hazard, toxic hazard, fire hazard).

NOTE 2 The hazard envisaged in this definition:

- either is permanently present during the intended use of the machine (for example motion of hazardous moving elements, electric arc during a welding phase, unhealthy posture, noise emission, high temperature);
- or can appear unexpectedly (for example: explosion, crushing hazard as a consequence of an unintended/unexpected start-up, ejection as a consequence of a breakage, fall as a consequence of acceleration/deceleration).

[ISO 12100-1, 3.6, modified]

3.29

indirect contact

contact of persons or livestock with exposed conductive parts which have become live under fault conditions

[IEV 826-12-04, modified]

3.30

inductive power supply system

system of inductive power transfer, consisting of a track converter and a track conductor, along which one or more pick-up(s) and associated pick-up converter(s) can move, without any galvanic or mechanical contact, in order to transfer electrical power for example to a mobile machine

NOTE The track conductor and the pick-up are analogous to the primary and secondary of a transformer respectively.

3.31

(electrically) instructed person

person adequately advised or supervised by an electrically skilled person to enable him or her to perceive risks and to avoid hazards which electricity can create

[IEV 826-18-02, modified]

3.32

interlock (for safeguarding)

arrangement that interconnects guard(s) or device(s) with the control system and/or all or part of the electrical supply to the machine

3.33

live part

conductor or conductive part intended to be energized in normal use, including a neutral conductor, but, by convention, not a PEN conductor

NOTE This term does not necessarily imply a risk of electric shock.

3.34**machine actuator**

power mechanism used to effect motion of the machine

3.35**machinery****machine**

assembly of linked parts or components, at least one of which moves, with the appropriate machine actuators, control and power circuits, joined together for a specific application, in particular for the processing, treatment, moving or packaging of a material.

The term "machinery" also covers an assembly of machines which, in order to achieve the same end, are arranged and controlled so that they function as an integral whole

[ISO 12100-1, 3.1, modified]

NOTE The term "component" is used here in a general sense and it does not refer only to electrical components.

3.36**marking**

signs or inscriptions primarily for the purpose of identifying equipment, components and/or devices, which can include certain features thereof

3.37**neutral conductor****N**

conductor connected to the neutral point of a system and capable of contributing to the transmission of electrical energy

[IEV 826-14-07, modified]

3.38**obstacle**

part preventing unintentional direct contact, but not preventing direct contact by deliberate action

3.39**overcurrent**

current exceeding the rated value. For conductors, the rated value is the current-carrying capacity

[IEV 826-11-14, modified]

3.40**overload (of a circuit)**

time/current relationship in a circuit which is in excess of the rated full load of the circuit when the circuit is not under a fault condition

NOTE *Overload* should not be used as a synonym for *overcurrent*.

3.41**plug/socket combination**

component and a suitable mating component, appropriate to terminate conductors, intended for connection or disconnection of two or more conductors

NOTE Examples of plug/socket combination include:

- connectors which fulfil the requirements of IEC 61984;
- a plug and socket-outlet, a cable coupler, or an appliance coupler in accordance with IEC 60309-1;
- a plug and socket-outlet in accordance with IEC 60884-1 or an appliance coupler in accordance with IEC 60320-1.

3.42

power circuit

circuit that supplies power from the supply network to units of equipment used for productive operation and to transformers supplying control circuits

3.43

protective bonding

equipotential bonding for protection against electric shock

NOTE Measures for protection against electric shock can also reduce the risk of burns or fire.

3.44

protective bonding circuit

protective conductors and conductive parts connected together to provide protection against electric shock in the event of an insulation failure

3.45

protective conductor

conductor required for protective bonding by some measures for protection against electric shock for electrically connecting any of the following parts:

- exposed conductive parts;
- extraneous conductive parts;
- main earthing terminal (PE)

[IEV 826-13-22, modified]

3.46

redundancy

application of more than one device or system, or part of a device or system, with the objective of ensuring that in the event of one failing to perform its function, another is available to perform that function

3.47

reference designation

distinctive code which serves to identify an object in the documentation and on the equipment

3.48

risk

combination of the probability of occurrence of harm (i.e. physical injury or damage to health) and the severity of that harm

[ISO 12100-1, 3.11, modified]

3.49

safeguard

guard or protective device provided as a means to protect persons from a hazard

3.50

safeguarding

protective measure using safeguards to protect persons from the hazards which cannot reasonably be eliminated or from the risks which cannot be sufficiently reduced by inherently safe design measures

[ISO 12100-1, 3.20]

3.51**servicing level**

level on which persons stand when operating or maintaining the electrical equipment

3.52**short-circuit current**

overcurrent resulting from a short circuit due to a fault or an incorrect connection in an electric circuit

[IEV 441-11-07]

3.53**(electrically) skilled person**

person with relevant training, education and experience to enable him or her to perceive risks and to avoid hazards associated with electricity

[IEV 826-18-01, modified]

3.54**supplier**

entity (for example manufacturer, contractor, installer, integrator) who provides equipment or services associated with the machine

NOTE The user organization may also act in the capacity of a supplier to itself.

3.55**switching device**

device designed to make and/or break the current in one or more electric circuits

[IEV 441-14-01, modified]

NOTE A switching device may perform one or both of these actions.

3.56**uncontrolled stop**

stopping of machine motion by removing electrical power to the machine actuators

NOTE This definition does not imply any particular state of other stopping devices, for example mechanical or hydraulic brakes.

3.57**user**

entity who utilizes the machine and its associated electrical equipment

4 General requirements

4.1 General

This part of IEC 60204 is intended to apply to electrical equipment used with a wide variety of machines and with a group of machines working together in a co-ordinated manner.

The risks associated with the hazards relevant to the electrical equipment shall be assessed as part of the overall requirements for risk assessment of the machine. This will determine the adequate risk reduction, and the necessary protective measures for persons who can be exposed to those hazards, while still maintaining an acceptable level of performance of the machine and its equipment.

Hazardous situations can result from, but are not limited to, the following causes:

- failures or faults in the electrical equipment resulting in the possibility of electric shock or electrical fire;
- failures or faults in control circuits (or components and devices associated with those circuits) resulting in the malfunctioning of the machine;
- disturbances or disruptions in power sources as well as failures or faults in the power circuits resulting in the malfunctioning of the machine;
- loss of continuity of circuits that depend upon sliding or rolling contacts, resulting in a failure of a safety function;
- electrical disturbances for example, electromagnetic, electrostatic either from outside the electrical equipment or internally generated, resulting in the malfunctioning of the machine;
- release of stored energy (either electrical or mechanical) resulting in, for example, electric shock, unexpected movement that can cause injury;
- audible noise at levels that cause health problems to persons;
- surface temperatures that can cause injury.

Safety measures are a combination of the measures incorporated at the design stage and those measures required to be implemented by the user.

The design and development process shall identify hazards and the risks arising from them. Where the hazards cannot be removed and/or the risks cannot be sufficiently reduced by inherently safe design measures, protective measures (for example safeguarding,) shall be provided to reduce the risk. Additional means (for example, awareness means) shall be provided where further risk reduction is necessary. In addition, working procedures that reduce risk can be necessary.

The use of the enquiry form as shown in Annex B of this part of IEC 60204 is recommended in order to facilitate an appropriate agreement between the user and the supplier(s) on basic conditions and additional user specifications related to the electrical equipment. Those additional specifications are to:

- provide additional features that are dependent on the type of machine (or group of machines) and the application;
- facilitate maintenance and repair; and
- improve the reliability and ease of operation.

4.2 Selection of equipment

4.2.1 General

Electrical components and devices shall:

- be suitable for their intended use; and
- conform to relevant IEC standards where such exist; and
- be applied in accordance with the supplier's instructions.

4.2.2 Electrical equipment in compliance with the IEC 60439 series

The electrical equipment of the machine shall satisfy the safety requirements identified by the risk assessment of the machine. Depending upon the machine, its intended use and its electrical equipment, the designer may select parts of the electrical equipment of the machine that are in compliance with relevant parts of the IEC 60439 series (see also Annex F).

NOTE The IEC 60439 series specifies requirements for equipment covering a wide range of possible applications of low-voltage switchgear and controlgear assemblies.

4.3 Electrical supply

4.3.1 General

The electrical equipment shall be designed to operate correctly with the conditions of the supply:

- as specified in 4.3.2 or 4.3.3, or
- as otherwise specified by the user (see Annex B), or
- as specified by the supplier in the case of a special source of supply such as an on-board generator.

4.3.2 AC supplies

Voltage	Steady state voltage: 0,9 to 1,1 of nominal voltage.
Frequency	0,99 to 1,01 of nominal frequency continuously; 0,98 to 1,02 short time.
Harmonics	Harmonic distortion not exceeding 10 % of the total r.m.s. voltage between live conductors for the sum of the 2 nd through to the 5 th harmonic. An additional 2 % of the total r.m.s. voltage between live conductors for the sum of the 6 th through to the 30 th harmonic is permissible.
Voltage unbalance	Neither the voltage of the negative sequence component nor the voltage of the zero sequence component in three-phase supplies exceeding 2 % of the positive sequence component.
Voltage interruption	Supply interrupted or at zero voltage for not more than 3 ms at any random time in the supply cycle with more than 1 s between successive interruptions.
Voltage dips	Voltage dips not exceeding 20 % of the peak voltage of the supply for more than one cycle with more than 1 s between successive dips.

4.3.3 DC supplies

From batteries:

Voltage	0,85 to 1,15 of nominal voltage; 0,7 to 1,2 of nominal voltage in the case of battery-operated vehicles.
Voltage interruption	Not exceeding 5 ms.

From converting equipment:

Voltage	0,9 to 1,1 of nominal voltage.
Voltage interruption	Not exceeding 20 ms with more than 1 s between successive interruptions.

NOTE This is a variation to IEC Guide 106 to ensure proper operation of electronic equipment.

Ripple (peak-to-peak) Not exceeding 0,15 of nominal voltage.

4.3.4 Special supply systems

For special supply systems such as on-board generators, the limits given in 4.3.2 and 4.3.3 may be exceeded provided that the equipment is designed to operate correctly with those conditions.

4.4 Physical environment and operating conditions

4.4.1 General

The electrical equipment shall be suitable for the physical environment and operating conditions of its intended use. The requirements of 4.4.2 to 4.4.8 cover the physical environment and operating conditions of the majority of machines covered by this part of IEC 60204. When special conditions apply or the limits specified are exceeded, an agreement between user and supplier (see 4.1) can be necessary.

4.4.2 Electromagnetic compatibility (EMC)

The equipment shall not generate electromagnetic disturbances above levels that are appropriate for its intended operating environment. In addition, the equipment shall have a level of immunity to electromagnetic disturbances so that it can function in its intended environment.

NOTE 1 The generic EMC standards IEC 61000-6-1 or IEC 61000-6-2 and CISPR 61000-6-3 or IEC 61000-6-4 give general EMC emission and immunity limits.

NOTE 2 IEC 61000-5-2 gives guidelines for earthing and cabling of electrical and electronic systems aimed at ensuring EMC. If specific product standards exist (for example, IEC 61496-1, IEC 61800-3, IEC 60947-5-2) they take precedence over generic standards.

Measures to limit the generation of electromagnetic disturbances, i.e. conducted and radiated emissions include:

- power supply filtering;
- cable shielding;
- enclosures designed to minimize RF radiation;
- RF suppression techniques.

Measures to enhance the immunity of the equipment against conducted and radiated RF disturbance include:

- design of functional bonding system taking into account the following;
 - connection of sensitive electrical circuits to the chassis. Such terminations should be marked or labelled with the symbol IEC 60417-5020 (DB:2002-10):



- connection of the chassis to earth (PE) using a conductor with low RF impedance and as short as practicable;
- connection of sensitive electrical equipment or circuits directly to the PE circuit or to a functional earthing conductor (FE) (see Figure 2), to minimize common mode disturbance. This latter terminal should be marked or labelled by the symbol IEC 60417-5018 (DB:2002-10):



- separation of sensitive circuits from disturbance sources;
- enclosures designed to minimize RF transmission;
- EMC wiring practices:
 - using twisted conductors to reduce the effect of differential mode disturbances,
 - keeping sufficient distance between conductors emitting disturbances and conductors of sensitive circuits,
 - using cable orientation as close to 90° as possible when cables cross,
 - running the conductors as close as possible to the ground plane,
 - using electrostatic screens and/or electromagnetic shields with a low RF impedance termination.

4.4.3 Ambient air temperature

Electrical equipment shall be capable of operating correctly in the intended ambient air temperature. The minimum requirement for all electrical equipment is correct operation between air temperatures of +5 °C and +40 °C. For very hot environments (for example hot climates, steel mills, paper mills) and for cold environments, extra requirements can be necessary (see Annex B).

4.4.4 Humidity

The electrical equipment shall be capable of operating correctly when the relative humidity does not exceed 50 % at a maximum temperature of +40 °C. Higher relative humidities are permitted at lower temperatures (for example 90 % at 20 °C).

Harmful effects of occasional condensation shall be avoided by design of the equipment or, where necessary, by additional measures (for example built-in heaters, air conditioners, drain holes).

4.4.5 Altitude

Electrical equipment shall be capable of operating correctly at altitudes up to 1 000 m above mean sea level.

4.4.6 Contaminants

Electrical equipment shall be adequately protected against the ingress of solids and liquids (see 11.3).

The electrical equipment shall be adequately protected against contaminants (for example dust, acids, corrosive gases, salts) that can be present in the physical environment in which the electrical equipment is to be installed (see Annex B).

4.4.7 Ionizing and non-ionizing radiation

When equipment is subject to radiation (for example microwave, ultraviolet, lasers, X-rays), additional measures shall be taken to avoid malfunctioning of the equipment and accelerated deterioration of the insulation. A special agreement can be necessary between the supplier and the user (see Annex B).

4.4.8 Vibration, shock, and bump

Undesirable effects of vibration, shock and bump (including those generated by the machine and its associated equipment and those created by the physical environment) shall be avoided by the selection of suitable equipment, by mounting it away from the machine, or by provision of anti-vibration mountings. A special agreement can be necessary between the supplier and the user (see Annex B).

4.5 Transportation and storage

Electrical equipment shall be designed to withstand, or suitable precautions shall be taken to protect against, the effects of transportation and storage temperatures within a range of $-25\text{ }^{\circ}\text{C}$ to $+55\text{ }^{\circ}\text{C}$ and for short periods not exceeding 24 h at up to $+70\text{ }^{\circ}\text{C}$. Suitable means shall be provided to prevent damage from humidity, vibration, and shock. A special agreement can be necessary between the supplier and the user (see Annex B).

NOTE Electrical equipment susceptible to damage at low temperatures includes PVC insulated cables.

4.6 Provisions for handling

Heavy and bulky electrical equipment that has to be removed from the machine for transport, or that is independent of the machine, shall be provided with suitable means for handling by cranes or similar equipment.

4.7 Installation

Electrical equipment shall be installed in accordance with the electrical equipment supplier's instructions.

5 Incoming supply conductor terminations and devices for disconnecting and switching off

5.1 Incoming supply conductor terminations

It is recommended that, where practicable, the electrical equipment of a machine is connected to a single incoming supply. Where another supply is necessary for certain parts of the equipment (for example, electronic equipment that operates at a different voltage), that supply should be derived, as far as is practicable, from devices (for example, transformers, converters) forming part of the electrical equipment of the machine. For large complex machinery comprising a number of widely-spaced machines working together in a co-ordinated manner, there can be a need for more than one incoming supply depending upon the site supply arrangements (see 5.3.1).

Unless a plug is provided with the machine for the connection to the supply (see 5.3.2 e), it is recommended that the supply conductors are terminated at the supply disconnecting device.

Where a neutral conductor is used it shall be clearly indicated in the technical documentation of the machine, such as in the installation diagram and in the circuit diagram, and a separate insulated terminal, labelled **N** in accordance with 16.1, shall be provided for the neutral conductor (see also Annex B).

There shall be no connection between the neutral conductor and the protective bonding circuit inside the electrical equipment nor shall a combined PEN terminal be provided.

Exception: a connection may be made between the neutral terminal and the PE terminal at the point of the connection of the power supply to the machine for TN-C systems.

All terminals for the incoming supply connection shall be clearly identified in accordance with IEC 60445 and 16.1. For the identification of the external protective conductor terminal, see 5.2.

5.2 Terminal for connection to the external protective earthing system

For each incoming supply, a terminal shall be provided in the vicinity of the associated phase conductor terminals for connection of the machine to the external protective earthing system or to the external protective conductor, depending upon the supply distribution system.

The terminal shall be of such a size as to enable the connection of an external protective copper conductor with a cross-sectional area in accordance with Table 1.

Table 1 – Minimum cross-sectional area of the external protective copper conductor

Cross-sectional area of copper phase conductors supplying the equipment $S \text{ mm}^2$	Minimum cross-sectional area of the external protective copper conductor $S_p \text{ mm}^2$
$S \leq 16$	S
$16 < S \leq 35$	16
$S > 35$	$S/2$

Where an external protective conductor of a material other than copper is used, the terminal size shall be selected accordingly (see also 8.2.2).

At each incoming supply point, the terminal for connection of the external protective earthing system or the external protective conductor shall be marked or labelled with the letters **PE** (see IEC 60445).

5.3 Supply disconnecting (isolating) device

5.3.1 General

A supply disconnecting device shall be provided:

- for each incoming source of supply to a machine(s);

NOTE The incoming supply can be connected directly to the machine or via a feeder system. Feeder systems of machines can include conductor wires, conductor bars, slip-ring assemblies, flexible cable systems (reeled, festooned) or inductive power supply systems.

- for each on-board power supply.

The supply disconnecting device shall disconnect (isolate) the electrical equipment of the machine from the supply when required (for example for work on the machine, including the electrical equipment).

When two or more supply disconnecting devices are provided, protective interlocks for their correct operation shall also be provided in order to prevent a hazardous situation, including damage to the machine or to the work in progress.

5.3.2 Type

The supply disconnecting device shall be one of the following types:

- a) switch-disconnector, with or without fuses, in accordance with IEC 60947-3, utilization category AC-23B or DC-23B;
- b) disconnector, with or without fuses, in accordance with IEC 60947-3, that has an auxiliary contact that in all cases causes switching devices to break the load circuit before the opening of the main contacts of the disconnector;
- c) a circuit-breaker suitable for isolation in accordance with IEC 60947-2;
- d) any other switching device in accordance with an IEC product standard for that device and which meets the isolation requirements of IEC 60947-1 as well as a utilization category defined in the product standard as appropriate for on-load switching of motors or other inductive loads;
- e) a plug/socket combination for a flexible cable supply.

5.3.3 Requirements

When the supply disconnecting device is one of the types specified in 5.3.2 a) to d) it shall fulfil all of the following requirements:

- isolate the electrical equipment from the supply and have one OFF (isolated) and one ON position marked with "O" and "I" (symbols IEC 60417-5008 (DB:2002-10) and IEC 60417-5007 (DB:2002-10), see 10.2.2);
- have a visible contact gap or a position indicator which cannot indicate OFF (isolated) until all contacts are actually open and the requirements for the isolating function have been satisfied;
- have an external operating means (for example handle), (**exception:** power-operated switchgear need not be operable from outside the enclosure where there are other means to open it). Where the external operating means is not intended for emergency operations, it is recommended that it be coloured BLACK or GREY (see 10.7.4 and 10.8.4);
- be provided with a means permitting it to be locked in the OFF (isolated) position (for example by padlocks). When so locked, remote as well as local closing shall be prevented;
- disconnect all live conductors of its power supply circuit. However, for TN supply systems, the neutral conductor may or may not be disconnected except in countries where disconnection of the neutral conductor (when used) is compulsory;
- have a breaking capacity sufficient to interrupt the current of the largest motor when stalled together with the sum of the normal running currents of all other motors and/or loads. The calculated breaking capacity may be reduced by the use of a proven diversity factor.

When the supply disconnecting device is a plug/socket combination, it shall fulfil the following requirements:

- have the switching capability, or be interlocked with a switching device that has a breaking capacity, sufficient to interrupt the current of the largest motor when stalled together with the sum of the normal running currents of all other motors and/or loads. The calculated breaking capacity may be reduced by the use of a proven diversity factor. When the interlocked switching device is electrically operated (for example a contactor) it shall have an appropriate utilisation category.
- a) to f) of 13.4.5.

NOTE A suitably rated plug and socket-outlet, cable coupler, or appliance coupler, in accordance with IEC 60309-1 can fulfil these requirements.

Where the supply disconnecting device is a plug/socket combination, a switching device with an appropriate utilisation category shall be provided for switching the machine on and off. This can be achieved by the use of the interlocked switching device described above.

5.3.4 Operating means

The operating means (for example, a handle) of the supply disconnecting device shall be easily accessible and located between 0,6 m and 1,9 m above the servicing level. An upper limit of 1,7 m is recommended.

NOTE The direction of operation is given in IEC 61310-3.

5.3.5 Excepted circuits

The following circuits need not be disconnected by the supply disconnecting device:

- lighting circuits for lighting needed during maintenance or repair;
- plug and socket outlets for the exclusive connection of repair or maintenance tools and equipment (for example hand drills, test equipment);
- undervoltage protection circuits that are only provided for automatic tripping in the event of supply failure;
- circuits supplying equipment that should normally remain energized for correct operation (for example temperature controlled measuring devices, product (work in progress) heaters, program storage devices);
- control circuits for interlocking.

It is recommended, however, that such circuits be provided with their own disconnecting device.

Where such a circuit is not disconnected by the supply disconnecting device:

- permanent warning label(s) in accordance with 16.1 shall be appropriately placed in proximity to the supply disconnecting device;
- a corresponding statement shall be included in the maintenance manual, and one or more of the following shall apply;
 - a permanent warning label in accordance with 16.1 is affixed in proximity to each excepted circuit, or
 - the excepted circuit is separated from other circuits, or
 - the conductors are identified by colour taking into account the recommendation of 13.2.4.

5.4 Devices for switching off for prevention of unexpected start-up

Devices for switching off for the prevention of unexpected start-up shall be provided (for example where, during maintenance, a start-up of the machine or part of the machine can create a hazard).

Such devices shall be appropriate and convenient for the intended use, shall be suitably placed, and readily identifiable as to their function and purpose (for example by a durable marking in accordance with 16.1 where necessary).

NOTE 1 This part of IEC 60204 does not address all provisions for prevention of unexpected start up. See ISO 14118 (EN 1037).

Means shall be provided to prevent inadvertent and/or mistaken closure of these devices either at the controller or from other locations (see also 5.6).

The following devices that fulfil the isolation function may be provided for this purpose:

- devices described in 5.3.2,
- disconnectors, withdrawable fuse links and withdrawable links only if located in an enclosed electrical operating area (see 3.19).

Devices that do not fulfil the isolation function (for example a contactor switched off by a control circuit) may only be provided where intended to be used for situations that include:

- inspections;
- adjustments;
- work on the electrical equipment where:
 - there is no hazard arising from electric shock (see Clause 6) and burn;
 - the switching off means remains effective throughout the work;
 - the work is of a minor nature (for example replacement of plug-in devices without disturbing existing wiring).

NOTE 2 The selection of a device will be dependent on the risk assessment, taking into account the intended use of the device, for example, the use of disconnectors, withdrawable fuse links or withdrawable links located in enclosed electrical operating areas can be inappropriate for use by cleaners (see 17.2 b)12)).

5.5 Devices for disconnecting electrical equipment

Devices shall be provided for disconnecting (isolating) electrical equipment to enable work to be carried out when it is de-energised and isolated. Such devices shall be:

- appropriate and convenient for the intended use;
- suitably placed;
- readily identifiable as to which part(s) or circuit(s) of the equipment is served (for example by durable marking in accordance with 16.1 where necessary).

Means shall be provided to prevent inadvertent and/or mistaken closure of these devices either at the controller or from other locations (see also 5.6).

The supply disconnecting device (see 5.3) may, in some cases, fulfil that function. However, where it is necessary to work on individual parts of the electrical equipment of a machine, or on one of a number of machines fed by a common conductor bar, conductor wire or inductive power supply system, a disconnecting device shall be provided for each part, or for each machine, requiring separate isolation.

In addition to the supply disconnecting device, the following devices that fulfil the isolation function may be provided for this purpose:

- devices described in 5.3.2;
- disconnectors, withdrawable fuse links and withdrawable links only if located in an electrical operating area (see 3.15) and relevant information is provided with the electrical equipment (see 17.2 b)9) and b)12)).

NOTE Where protection against electric shock is provided in accordance with 6.2.2 c), withdrawable fuse links or withdrawable links for this purpose are intended for use by skilled or instructed persons.

5.6 Protection against unauthorized, inadvertent and/or mistaken connection

The devices described in 5.4 and 5.5 that are located outside an enclosed electrical operating area shall be equipped with means to secure them in the OFF position (disconnected state), (for example by provisions for padlocking, trapped key interlocking). When so secured, remote as well as local reconnection shall be prevented.

Where a non-lockable disconnecting device (for example withdrawable fuse-links, withdrawable links) other means of protection against reconnection (for example warning labels in accordance with 16.1) may be provided.

However, when a plug/socket combination according to 5.3.2 e) is so positioned that it can be kept under the immediate supervision of the person carrying out the work, means for securing in the disconnected state need not be provided.

6 Protection against electric shock

6.1 General

The electrical equipment shall provide protection of persons against electric shock from:

- direct contact (see 6.2 and 6.4);
- indirect contact (see 6.3 and 6.4).

The measures for this protection given in 6.2, 6.3, and, for PELV, in 6.4, are a recommended selection from IEC 60364-4-41. Where those recommended measures are not practicable, for example due to the physical or operational conditions, other measures from IEC 60364-4-41 may be used.

6.2 Protection against direct contact

6.2.1 General

For each circuit or part of the electrical equipment, the measures of either 6.2.2 or 6.2.3 and, where applicable, 6.2.4 shall be applied.

Exception: where those measures are not appropriate, other measures for protection against direct contact (for example by using barriers, by placing out of reach, using obstacles, using construction or installation techniques that prevent access) as defined in IEC 60364-4-41 may be applied (see 6.2.5 and 6.2.6).

When the equipment is located in places open to all persons, which can include children, measures of either 6.2.2 with a minimum degree of protection against direct contact corresponding to IP4X or IPXXD (see IEC 60529), or 6.2.3 shall be applied.

6.2.2 Protection by enclosures

Live parts shall be located inside enclosures that conform to the relevant requirements of Clauses 4, 11, and 14 and that provide protection against direct contact of at least IP2X or IPXXB (see IEC 60529).

Where the top surfaces of the enclosure are readily accessible, the minimum degree of protection against direct contact provided by the top surfaces shall be IP4X or IPXXD.

Opening an enclosure (i.e. opening doors, lids, covers, and the like) shall be possible only under one of the following conditions:

- a) The use of a key or tool is necessary for access. For enclosed electrical operating areas, see IEC 60364-4-41, or IEC 60439-1 as appropriate.

NOTE 1 The use of a key or tool is intended to restrict access to skilled or instructed persons (see 17.2 b)12)).

All live parts, that are likely to be touched when resetting or adjusting devices intended for such operations while the equipment is still connected, shall be protected against direct contact to at least IP2X or IPXXB. Other live parts on the inside of doors shall be protected against direct contact to at least IP1X or IPXXA.

- b) The disconnection of live parts inside the enclosure before the enclosure can be opened.

This may be accomplished by interlocking the door with a disconnecting device (for example, the supply disconnecting device) so that the door can only be opened when the disconnecting device is open and so that the disconnecting device can only be closed when the door is closed.

Exception: a special device or tool as prescribed by the supplier can be used to defeat the interlock provided that:

- it is possible at all times while the interlock is defeated to open the disconnecting device and lock the disconnecting device in the OFF (isolated) position or otherwise prevent unauthorised closure of the disconnecting device;
- upon closing the door, the interlock is automatically restored;
- all live parts, that are likely to be touched when resetting or adjusting devices intended for such operations while the equipment is still connected, are protected against direct contact to at least IP2X or IPXXB and other live parts on the inside of doors are protected against direct contact to at least IP1X or IPXXA;
- relevant information is provided with the electrical equipment (see 17.2 b)9) and b)12)).

NOTE 2 The special device or tool is intended for use only by skilled or instructed persons (see 17.2 b)12)).

Means shall be provided to restrict access to live parts behind doors not directly interlocked with the disconnecting means to skilled or instructed persons. (See 17.2 b)12)).

All parts that are still live after switching off the disconnecting device(s) (see 5.3.5) shall be protected against direct contact to at least IP2X or IPXXB (see IEC 60529). Such parts shall be marked with a warning sign in accordance with 16.2.1 (see also 13.2.4 for identification of conductors by colour).

Excepted from this requirement for marking are:

- parts that can be live only because of connection to interlocking circuits and that are distinguished by colour as potentially live in accordance with 13.2.4;
 - the supply terminals of the supply disconnecting device when the latter is mounted alone in a separate enclosure.
- c) Opening without the use of a key or a tool and without disconnection of live parts shall be possible only when all live parts are protected against direct contact to at least IP2X or IPXXB (see IEC 60529). Where barriers provide this protection, either they shall require a tool for their removal or all live parts protected by them shall be automatically disconnected when the barrier is removed.

NOTE 3 Where protection against direct contact is achieved in accordance with 6.2.2 c), and a hazard can be caused by manual actuation of devices (for example manual closing of contactors or relays), such actuation should be prevented by barriers or obstacles that require a tool for their removal.

6.2.3 Protection by insulation of live parts

Live parts protected by insulation shall be completely covered with insulation that can only be removed by destruction. Such insulation shall be capable of withstanding the mechanical, chemical, electrical, and thermal stresses to which it can be subjected under normal operating conditions.

NOTE Paints, varnishes, lacquers, and similar products alone are generally considered to be inadequate for protection against electric shock under normal operating conditions.

6.2.4 Protection against residual voltages

Live parts having a residual voltage greater than 60 V after the supply has been disconnected shall be discharged to 60 V or less within a time period of 5 s after disconnection of the supply voltage provided that this rate of discharge does not interfere with the proper functioning of the equipment. Exempted from this requirement are components having a stored charge of 60 μC or less. Where this specified rate of discharge would interfere with the proper functioning of the equipment, a durable warning notice drawing attention to the hazard and stating the delay required before the enclosure may be opened shall be displayed at an easily visible location on or immediately adjacent to the enclosure containing the capacitances.

In the case of plugs or similar devices, the withdrawal of which results in the exposure of conductors (for example pins), the discharge time shall not exceed 1 s, otherwise such conductors shall be protected against direct contact to at least IP2X or IPXXB. If neither a discharge time of 1 s nor a protection of at least IP2X or IPXXB can be achieved (for example in the case of removable collectors on conductor wires, conductor bars, or slip-ring assemblies, see 12.7.4), additional switching devices or an appropriate warning device (for example a warning notice in accordance with 16.1) shall be applied.

6.2.5 Protection by barriers

For protection by barriers, 412.2 of IEC 60364-4-41 shall apply.

6.2.6 Protection by placing out of reach or protection by obstacles

For protection by placing out of reach, 412.4 of IEC 60364-4-41 shall apply. For protection by obstacles, 412.3 of IEC 60364-4-41 shall apply.

For conductor wire systems or conductor bar systems with a degree of protection less than IP2X, see 12.7.1.

6.3 Protection against indirect contact

6.3.1 General

Protection against indirect contact (3.29) is intended to prevent hazardous situations due to an insulation fault between live parts and exposed conductive parts.

For each circuit or part of the electrical equipment, at least one of the measures in accordance with 6.3.2 to 6.3.3 shall be applied:

- measures to prevent the occurrence of a touch voltage (6.3.2); or
- automatic disconnection of the supply before the time of contact with a touch voltage can become hazardous (6.3.3).

NOTE 1 The risk of harmful physiological effects from a touch voltage depends on the value of the touch voltage and the duration of possible exposure.

NOTE 2 For classes of equipment and protective provisions, see IEC 61140.

6.3.2 Prevention of the occurrence of a touch voltage

6.3.2.1 General

Measures to prevent the occurrence of a touch voltage include the following:

- provision of class II equipment or by equivalent insulation;
- electrical separation.

6.3.2.2 Protection by provision of class II equipment or by equivalent insulation

This measure is intended to prevent the occurrence of touch voltages on the accessible parts through a fault in the basic insulation.

This protection is provided by one or more of the following:

- class II electrical devices or apparatus (double insulation, reinforced insulation or by equivalent insulation in accordance with IEC 61140);
- switchgear and controlgear assemblies having total insulation in accordance with IEC 60439-1;
- supplementary or reinforced insulation in accordance with 413.2 of IEC 60364-4-41.

6.3.2.3 Protection by electrical separation

Electrical separation of an individual circuit is intended to prevent a touch voltage through contact with exposed conductive parts that can be energized by a fault in the basic insulation of the live parts of that circuit.

For this type of protection, the requirements of 413.5 of IEC 60364-4-41 apply.

6.3.3 Protection by automatic disconnection of supply

This measure consists of the interruption of one or more of the line conductors by the automatic operation of a protective device in case of a fault. This interruption shall occur within a sufficiently short time to limit the duration of a touch voltage to a time within which the touch voltage is not hazardous. Interruption times are given in Annex A.

This measure necessitates co-ordination between:

- the type of supply and earthing system;
- the impedance values of the different elements of the protective bonding system;
- the characteristics of the protective devices that detect insulation fault(s).

Automatic disconnection of the supply of any circuit affected by an insulation fault is intended to prevent a hazardous situation resulting from a touch voltage.

This protective measure comprises both:

- protective bonding of exposed conductive parts (see 8.2.3),
- and either:
 - a) overcurrent protective devices for the automatic disconnection of the supply on detection of an insulation fault in TN systems, or
 - b) residual current protective devices to initiate the automatic disconnection of the supply on detection of an insulation fault from a live part to exposed conductive parts or to earth in TT systems, or
 - c) insulation monitoring or residual current protective devices to initiate automatic disconnection of IT systems. Except where a protective device is provided to interrupt the supply in the case of the first earth fault, an insulation monitoring device shall be provided to indicate the occurrence of a first fault from a live part to exposed conductive parts or to earth. This insulation monitoring device shall initiate an audible and/or visual signal which shall continue as long as the fault persists.

NOTE In large machines, the provision of an earth fault location system can facilitate maintenance.

Where automatic disconnection is provided in accordance with a), and disconnection within the time specified in Clause A.1 cannot be assured, supplementary bonding shall be provided as necessary to meet the requirements of Clause A.3.

6.4 Protection by the use of PELV

6.4.1 General requirements

The use of PELV (Protective Extra-Low Voltage) is to protect persons against electric shock from indirect contact and limited area direct contact (see 8.2.5).

PELV circuits shall satisfy all of the following conditions:

- a) the nominal voltage shall not exceed:
 - 25 V a.c. r.m.s. or 60 V ripple-free d.c. when the equipment is normally used in dry locations and when large area contact of live parts with the human body is not expected; or
 - 6 V a.c. r.m.s. or 15 V ripple-free d.c. in all other cases;

NOTE *Ripple-free* is conventionally defined for a sinusoidal ripple voltage as a ripple content of not more than 10 % r.m.s.

- b) one side of the circuit or one point of the source of the supply of that circuit shall be connected to the protective bonding circuit;
- c) live parts of PELV circuits shall be electrically separated from other live circuits. Electrical separation shall be not less than that required between the primary and secondary circuits of a safety isolating transformer (see IEC 61558-1 and IEC 61558-2-6);
- d) conductors of each PELV circuit shall be physically separated from those of any other circuit. When this requirement is impracticable, the insulation provisions of 13.1.3 shall apply;
- e) plugs and socket-outlets for a PELV circuit shall conform to the following:
 - 1) plugs shall not be able to enter socket-outlets of other voltage systems;
 - 2) socket-outlets shall not admit plugs of other voltage systems.

6.4.2 Sources for PELV

The source for PELV shall be one of the following:

- a safety isolating transformer in accordance with IEC 61558-1 and IEC 61558-2-6;
- a source of current providing a degree of safety equivalent to that of the safety isolating transformer (for example a motor generator with winding providing equivalent isolation);
- an electrochemical source (for example a battery) or another source independent of a higher voltage circuit (for example a diesel-driven generator);
- an electronic power supply conforming to appropriate standards specifying measures to be –taken to ensure that, even in the case of an internal fault, the voltage at the outgoing terminals cannot exceed the values specified in 6.4.1.

7 Protection of equipment

7.1 General

This Clause details the measures to be taken to protect equipment against the effects of:

- overcurrent arising from a short circuit;
- overload and/or loss of cooling of motors;
- abnormal temperature;
- loss of or reduction in the supply voltage;
- overspeed of machines/machine elements;
- earth fault/residual current;
- incorrect phase sequence;
- overvoltage due to lightning and switching surges.

7.2 Overcurrent protection

7.2.1 General

Overcurrent protection shall be provided where the current in a machine circuit can exceed either the rating of any component or the current carrying capacity of the conductors, whichever is the lesser value. The ratings or settings to be selected are detailed in 7.2.10.

7.2.2 Supply conductors

Unless otherwise specified by the user, the supplier of the electrical equipment is not responsible for providing the overcurrent protective device for the supply conductors to the electrical equipment (see Annex B).

The supplier of the electrical equipment shall state on the installation diagram the data necessary for selecting the overcurrent protective device (see 7.2.10 and 17.4).

7.2.3 Power circuits

Devices for detection and interruption of overcurrent, selected in accordance with 7.2.10, shall be applied to each live conductor.

The following conductors, as applicable, shall not be disconnected without disconnecting all associated live conductors:

- the neutral conductor of a.c. power circuits;
- the earthed conductor of d.c. power circuits;
- d.c. power conductors bonded to exposed conductive parts of mobile machines.

Where the cross-sectional area of the neutral conductor is at least equal to or equivalent to that of the phase conductors, it is not necessary to provide overcurrent detection for the neutral conductor nor a disconnecting device for that conductor. For a neutral conductor with a cross-sectional area smaller than that of the associated phase conductors, the measures detailed in 524 of IEC 60364-5-52 shall apply.

In IT systems, it is recommended that the neutral conductor is not used. However, where a neutral conductor is used, the measures detailed in 431.2.2 of IEC 60364-4-43 shall apply.

7.2.4 Control circuits

Conductors of control circuits directly connected to the supply voltage and of circuits supplying control circuit transformers shall be protected against overcurrent in accordance with 7.2.3.

Conductors of control circuits supplied by a control circuit transformer or d.c. supply shall be protected against overcurrent (see also 9.4.3.1):

- in control circuits connected to the protective bonding circuit, by inserting an overcurrent protective device into the switched conductor;
- in control circuits not connected to the protective bonding circuit;
 - where the same cross sectional area conductors are used in all control circuits, by inserting an overcurrent protective device into the switched conductor, and;
 - where different cross sectional areas conductors are used in different sub-circuits, by inserting an overcurrent protective device into both switched and common conductors of each sub-circuit.

7.2.5 Socket outlets and their associated conductors

Overcurrent protection shall be provided for the circuits feeding the general purpose socket outlets intended primarily for supplying power to maintenance equipment. Overcurrent protective devices shall be provided in the unearthed live conductors of each circuit feeding such socket outlets.

7.2.6 Lighting circuits

All unearthed conductors of circuits supplying lighting shall be protected against the effects of short circuits by the provision of overcurrent devices separate from those protecting other circuits.

7.2.7 Transformers

Transformers shall be protected against overcurrent in accordance with the manufacturer's instructions. Such protection shall (see also 7.2.10):

- avoid nuisance tripping due to transformer magnetizing inrush currents;
- avoid a winding temperature rise in excess of the permitted value for the insulation class of transformer when it is subjected to the effects of a short circuit at its secondary terminals.

The type and setting of the overcurrent protective device should be in accordance with the recommendations of the transformer supplier.

7.2.8 Location of overcurrent protective devices

An overcurrent protective device shall be located at the point where a reduction in the cross-sectional area of the conductors or another change reduces the current-carrying capacity of the conductors, except where all the following conditions are satisfied:

- the current carrying capacity of the conductors is at least equal to that of the load;
- the part of the conductor between the point of reduction of current-carrying capacity and the position of the overcurrent protective device is no longer than 3 m;
- the conductor is installed in such a manner as to reduce the possibility of a short-circuit, for example, protected by an enclosure or duct.

7.2.9 Overcurrent protective devices

The rated short-circuit breaking capacity shall be at least equal to the prospective fault current at the point of installation. Where the short-circuit current to an overcurrent protective device can include additional currents other than from the supply (for example from motors, from power factor correction capacitors), those currents shall be taken into consideration.

A lower breaking capacity is permitted where another protective device (for example the overcurrent protective device for the supply conductors (see 7.2.2) having the necessary breaking capacity is installed on the supply side. In that case, the characteristics of the two devices shall be co-ordinated so that the let-through energy (I^2t) of the two devices in series does not exceed that which can be withstood without damage to the overcurrent protective device on the load side and to the conductors protected by that device (see Annex A of IEC 60947-2).

NOTE The use of such a co-ordinated arrangement of overcurrent protective devices can result in the operation of both overcurrent protective devices.

Where fuses are provided as overcurrent protective devices, a type readily available in the country of use shall be selected, or arrangements shall be made for the supply of spare parts.

7.2.10 Rating and setting of overcurrent protective devices

The rated current of fuses or the setting current of other overcurrent protective devices shall be selected as low as possible but adequate for the anticipated overcurrents (for example during starting of motors or energizing of transformers). When selecting those protective devices, consideration shall be given to the protection of switching devices against damage due to overcurrents (for example welding of the switching device contacts).

The rated current or setting of an overcurrent protective device is determined by the current carrying capacity of the conductors to be protected in accordance with 12.4, D.2 and the maximum allowable interrupting time t in accordance with Clause D.3, taking into account the needs of co-ordination with other electrical devices in the protected circuit.

7.3 Protection of motors against overheating

7.3.1 General

Protection of motors against overheating shall be provided for each motor rated at more than 0,5 kW.

Exceptions:

In applications where an automatic interruption of the motor operation is unacceptable (for example fire pumps), the means of detection shall give a warning signal to which the operator can respond.

Protection of motors against overheating can be achieved by:

- overload protection (7.3.2),

NOTE 1 Overload protective devices detect the time and current relationships (I^2t) in a circuit that are in excess of the rated full load of the circuit and initiate appropriate control responses.

- over-temperature protection (7.3.3), or

NOTE 2 Temperature detection devices sense over-temperature and initiate appropriate control responses.

- current-limiting protection (7.3.4).

Automatic restarting of any motor after the operation of protection against overheating shall be prevented where this can cause a hazardous situation or damage to the machine or to the work in progress.

7.3.2 Overload protection

Where overload protection is provided, detection of overload(s) shall be provided in each live conductor except for the neutral conductor. However, where the motor overload detection is not used for cable overload protection (see also Clause D.2), the number of overload detection devices may be reduced at the request of the user (see also Annex B). For motors having single-phase or d.c. power supplies, detection in only one unearthed live conductor is permitted.

Where overload protection is achieved by switching off, the switching device shall switch off all live conductors. The switching of the neutral conductor is not necessary for overload protection.

Where motors with special duty ratings are required to start or to brake frequently (for example, motors for rapid traverse, locking, rapid reversal, sensitive drilling) it can be difficult to provide overload protection with a time constant comparable with that of the winding to be protected. Appropriate protective devices designed to accommodate special duty motors or over-temperature protection (see 7.3.3) can be necessary.

For motors that cannot be overloaded (for example torque motors, motion drives that either are protected by mechanical overload protection devices or are adequately dimensioned), overload protection is not required.

7.3.3 Over-temperature protection

The provision of motors with over-temperature protection (see IEC 60034-11) is recommended in situations where the cooling can be impaired (for example dusty environments). Depending upon the type of motor, protection under stalled rotor or loss of phase conditions is not always ensured by over-temperature protection, and additional protection should then be provided.

Over-temperature protection is also recommended for motors that cannot be overloaded (for example torque motors, motion drives that are either protected by mechanical overload protection devices or are adequately dimensioned), where the possibility of over-temperature exists (for example due to reduced cooling).

7.3.4 Current limiting protection

Where protection against the effects of overheating in three phase motors is achieved by current limitation, the number of current limitation devices may be reduced from 3 to 2 (see 7.3.2). For motors having single phase a.c or d.c. power supplies, current limitation in only one unearthed live conductor is permitted.

7.4 Abnormal temperature protection

Resistance heating or other circuits that are capable of attaining or causing abnormal temperatures (for example, due to short-time rating or loss of cooling medium) and therefore can cause a hazardous situation shall be provided with suitable detection to initiate an appropriate control response.

7.5 Protection against supply interruption or voltage reduction and subsequent restoration

Where a supply interruption or a voltage reduction can cause a hazardous situation, damage to the machine, or to the work in progress, undervoltage protection shall be provided by, for example, switching off the machine at a predetermined voltage level.

Where the operation of the machine can allow for an interruption or a reduction of the voltage for a short time period, delayed undervoltage protection may be provided. The operation of the undervoltage device shall not impair the operation of any stopping control of the machine.

Upon restoration of the voltage or upon switching on the incoming supply, automatic or unexpected restarting of the machine shall be prevented where such a restart can cause a hazardous situation.

Where only a part of the machine or of the group of machines working together in a co-ordinated manner is affected by the voltage reduction or supply interruption, the undervoltage protection shall initiate appropriate control responses to ensure co-ordination.

7.6 Motor overspeed protection

Overspeed protection shall be provided where overspeeding can occur and could possibly cause a hazardous situation taking into account measures in accordance with 9.3.2. Overspeed protection shall initiate appropriate control responses and shall prevent automatic restarting.

The overspeed protection should operate in such a manner that the mechanical speed limit of the motor or its load is not exceeded.

NOTE This protection can consist, for example, of a centrifugal switch or speed limit monitor.

7.7 Earth fault/residual current protection

In addition to providing overcurrent protection for automatic disconnection as described in 6.3, earth fault/residual current protection can be provided to reduce damage to equipment due to earth fault currents less than the detection level of the overcurrent protection.

The setting of the devices shall be as low as possible consistent with correct operation of the equipment.

7.8 Phase sequence protection

Where an incorrect phase sequence of the supply voltage can cause a hazardous situation or damage to the machine, protection shall be provided.

NOTE Conditions of use that can lead to an incorrect phase sequence include:

- a machine transferred from one supply to another;
- a mobile machine with a facility for connection to an external power supply.

7.9 Protection against overvoltages due to lightning and to switching surges

Protective devices can be provided to protect against the effects of overvoltages due to lightning or to switching surges.

Where provided:

- devices for the suppression of overvoltages due to lightning shall be connected to the incoming terminals of the supply disconnecting device.
- devices for the suppression of overvoltages due to switching surges shall be connected across the terminals of all equipment requiring such protection.

8 Equipotential bonding

8.1 General


This Clause provides requirements for both protective bonding and functional bonding. Figure 2 illustrates those concepts.

Protective bonding is a basic provision for fault protection to enable protection of persons against electric shock from indirect contact (see 6.3.3 and 8.2).

The objective of functional bonding (see 8.3) is to minimize:

- the consequence of an insulation failure which could affect the operation of the machine;
- the consequences of electrical disturbances to sensitive electrical equipment which could affect the operation of the machine.

Normally functional bonding is achieved by connection to the protective bonding circuit, but where the level of electrical disturbances on the protective bonding circuit is not sufficiently low for proper functioning of electrical equipment, it may be necessary to connect the functional bonding circuit to a separate functional earthing conductor (see Figure 2).



NOTE The functional earthing conductor was previously referred to as 'noiseless earth conductor' and the 'FE' terminal was previously designated 'TE' (see IEC 60445).

Figure 2 – Example of equipotential bonding for electrical equipment of a machine

8.2 Protective bonding circuit

8.2.1 General

The protective bonding circuit consists of:

- PE terminal(s) (see 5.2);
- the protective conductors in the equipment of the machine including sliding contacts where they are part of the circuit;
- the exposed conductive parts and conductive structural parts of the electrical equipment;
- those extraneous conductive parts which form the structure of the machine.

All parts of the protective bonding circuit shall be so designed that they are capable of withstanding the highest thermal and mechanical stresses that can be caused by earth-fault currents that could flow in that part of the protective bonding circuit.

Where the conductance of structural parts of the electrical equipment or of the machine is less than that of the smallest protective conductor connected to the exposed conductive parts, a supplementary bonding conductor shall be provided. This supplementary bonding conductor shall have a cross-sectional area not less than half that of the corresponding protective conductor.

If an IT distribution system is used, the machine structure shall be part of the protective bonding circuit and insulation monitoring shall be provided. See 6.3.3 c).

Conductive structural parts of equipment in accordance with 6.3.2.2 need not be connected to the protective bonding circuit. Extraneous conductive parts which form the structure of the machine need not be connected to the protective bonding circuit where all the equipment provided is in accordance with 6.3.2.2.

Exposed conductive parts of equipment in accordance with 6.3.2.3 shall not be connected to the protective bonding circuit.

8.2.2 Protective conductors

Protective conductors shall be identified in accordance with 13.2.2.

Copper conductors are preferred. Where a conductor material other than copper is used, its electrical resistance per unit length shall not exceed that of the allowable copper conductor and such conductors shall be not less than 16 mm² in cross-sectional area.

The cross-sectional area of protective conductors shall be determined in accordance with the requirements of:

- 543 of IEC 60364-5-54; or
- 7.4.3.1.7 of IEC 60439-1, as appropriate.

This requirement is met in most cases where the relationship between the cross-sectional area of the phase conductors associated with that part of the equipment and the cross-sectional area of the associated protective conductor is in accordance with Table 1 (see 5.2).

See also 8.2.8.

8.2.3 Continuity of the protective bonding circuit

All exposed conductive parts shall be connected to the protective bonding circuit in accordance with 8.2.1.

Exception: see 8.2.5.

Where a part is removed for any reason (for example routine maintenance), the protective bonding circuit for the remaining parts shall not be interrupted.

Connection and bonding points shall be so designed that their current-carrying capacity is not impaired by mechanical, chemical, or electrochemical influences. Where enclosures and conductors of aluminium or aluminium alloys are used, particular consideration should be given to the possibility of electrolytic corrosion.

Metal ducts of flexible or rigid construction and metallic cable sheaths shall not be used as protective conductors. Nevertheless, such metal ducts and the metal sheathing of all connecting cables (for example cable armouring, lead sheath) shall be connected to the protective bonding circuit.

Where the electrical equipment is mounted on lids, doors, or cover plates, continuity of the protective bonding circuit shall be ensured and a protective conductor (see 8.2.2) is recommended. Otherwise fastenings, hinges or sliding contacts designed to have a low resistance shall be used (see 18.2.2, Test 1).

The continuity of the protective conductor in cables that are exposed to damage (for example flexible trailing cables) shall be ensured by appropriate measures (for example monitoring).

For requirements for the continuity of the protective conductor using conductor wires, conductor bars and slip-ring assemblies, see 12.7.2.

8.2.4 Exclusion of switching devices from the protective bonding circuit

The protective bonding circuit shall not incorporate a switching device or an overcurrent protective device (for example switch, fuse).

No means of interruption of the protective bonding conductor shall be provided.

Exception: links for test or measurement purposes that cannot be opened without the use of a tool and that are located in an enclosed electrical operating area.

Where the continuity of the protective bonding circuit can be interrupted by means of removable current collectors or plug/socket combinations, the protective bonding circuit shall be interrupted by a first make last break contact. This also applies to removable or withdrawable plug-in units (see also 13.4.5).

8.2.5 Parts that need not be connected to the protective bonding circuit

It is not necessary to connect exposed conductive parts to the protective bonding circuit where those parts are mounted so that they do not constitute a hazard because:

- they cannot be touched on large surfaces or grasped with the hand and they are small in size (less than approximately 50 mm × 50 mm); or
- they are located so that either contact with live parts, or an insulation failure, is unlikely.

This applies to small parts such as screws, rivets, and nameplates and to parts inside an enclosure, irrespective of their size (for example electromagnets of contactors or relays and mechanical parts of devices) (see also 410.3.3.5 of IEC 60364-4-41).

8.2.6 Protective conductor connecting points

All protective conductors shall be terminated in accordance with 13.1.1. The protective conductor connecting points shall have no other function and are not intended, for example, to attach or connect appliances or parts.

Each protective conductor connecting point shall be marked or labelled as such using the symbol IEC 60417-5019 (DB:2002-10):



or with the letters **PE**, the graphical symbol being preferred, or by use of the bicolour combination GREEN-AND-YELLOW, or by any combination of these.

8.2.7 Mobile machines

On mobile machines with on-board power supplies, the protective conductors, the conductive structural parts of the electrical equipment, and those extraneous conductive parts which form the structure of the machine shall all be connected to a protective bonding terminal to provide protection against electric shock. Where a mobile machine is also capable of being connected to an external incoming power supply, this protective bonding terminal shall be the connection point for the external protective conductor.

NOTE When the supply of electrical energy is self-contained within stationary, mobile, or movable items of equipment, and when there is no external supply connected (for example when an on-board battery charger is not connected), there is no need to connect such equipment to an external protective conductor.

8.2.8 Additional protective bonding requirements for electrical equipment having earth leakage currents higher than 10 mA a.c. or d.c.

NOTE 1 Earth leakage current is defined as "current flowing from the live parts of an installation to earth, in the absence of an insulation fault" (IEV 442-01-24). This current may have a capacitive component including that resulting from the deliberate use of capacitors.

NOTE 2 Most adjustable speed electrical power drive systems that comply with relevant parts of IEC 61800 will have an earth leakage current greater than 3,5 mA a.c. A touch current measurement method is specified as a type test in IEC 61800-5-1 to determine the earth leakage current of an adjustable speed electrical power drive system.

Where electrical equipment has an earth leakage current (for example adjustable speed electrical power drive systems and information technology equipment) that is greater than 10 mA a.c. or d.c. in any incoming supply, one or more of the following conditions for the associated protective bonding circuit shall be satisfied:

- a) the protective conductor shall have a cross-sectional area of at least 10 mm² Cu or 16 mm² Al, through its total run;
- b) where the protective conductor has a cross-sectional area of less than 10 mm² Cu or 16 mm² Al, a second protective conductor of at least the same cross-sectional area shall be provided up to a point where the protective conductor has a cross-sectional area not less than 10 mm² Cu or 16 mm² Al.

NOTE 3 This can require that the electrical equipment has a separate terminal for a second protective conductor.

- c) automatic disconnection of the supply in case of loss of continuity of the protective conductor.

To prevent difficulties associated with electromagnetic disturbances, the requirements of 4.4.2 also apply to the installation of duplicate protective conductors.

In addition, a warning label shall be provided adjacent to the PE terminal, and where necessary on the nameplate of the electrical equipment. The information provided under 17.2 b)1) shall include information about the leakage current and the minimum cross-sectional area of the external protective conductor.

8.3 Functional bonding

Protection against maloperation as a result of insulation failures can be achieved by connecting to a common conductor in accordance with 9.4.3.1.

For recommendations regarding functional bonding to avoid maloperation due to electromagnetic disturbances, see 4.4.2.

8.4 Measures to limit the effects of high leakage current

The effects of high leakage current can be restricted to the equipment having high leakage current by connection of that equipment to a dedicated supply transformer having separate windings. The protective bonding circuit shall be connected to exposed conductive parts of the equipment and, in addition, to the secondary winding of the transformer. The protective conductor(s) between the equipment and the secondary winding of the transformer shall comply with one or more of the arrangements described in 8.2.8.

9 Control circuits and control functions

9.1 Control circuits

9.1.1 Control circuit supply

Where control circuits are supplied from an a.c. source, control transformers shall be used for supplying the control circuits. Such transformers shall have separate windings. Where several transformers are used, it is recommended that the windings of those transformers be connected in such a manner that the secondary voltages are in phase.

Where d.c. control circuits derived from an a.c. supply are connected to the protective bonding circuit (see 8.2.1), they shall be supplied from a separate winding of the a.c. control circuit transformer or by another control circuit transformer.

NOTE Switch-mode units fitted with transformers having separate windings in accordance with IEC 61558-2-17 meet this requirement.

Transformers are not mandatory for machines with a single motor starter and/or a maximum of two control devices (for example interlock device, start/stop control station).

9.1.2 Control circuit voltages

The nominal value of the control voltage shall be consistent with the correct operation of the control circuit. The nominal voltage shall not exceed 277 V when supplied from a transformer.

9.1.3 Protection

Control circuits shall be provided with overcurrent protection in accordance with 7.2.4 and 7.2.10.

9.2 Control functions

NOTE 1 Information on the safety-related aspects of control functions is given in ISO 13849-1 (1999), ISO 13849-2 (2003), and IEC 62061.

NOTE 2 This subclause does not specify requirements for the equipment used to implement control functions. Examples of such requirements are given in Clause 10.

9.2.1 Start functions

Start functions shall operate by energizing the relevant circuit (see 9.2.5.2).

9.2.2 Stop functions

There are three categories of stop functions as follows:

- stop category 0: stopping by immediate removal of power to the machine actuators (i.e. an uncontrolled stop – see 3.56);
- stop category 1: a controlled stop (see 3.11) with power available to the machine actuators to achieve the stop and then removal of power when the stop is achieved;
- stop category 2: a controlled stop with power left available to the machine actuators.

9.2.3 Operating modes

Each machine can have one or more operating modes determined by the type of machine and its application. When a hazardous situation can result from a mode selection, unauthorised and/or inadvertent selection shall be prevented by suitable means (for example key operated switch, access code).

Mode selection by itself shall not initiate machine operation. A separate actuation of the start control shall be required.

For each specific operating mode, the relevant safety functions and/or protective measures shall be implemented.

Indication of the selected operating mode shall be provided (for example the position of a mode selector, the provision of an indicating light, a visual display indication).

9.2.4 Suspension of safety functions and/or protective measures

Where it is necessary to suspend safety functions and/or protective measures (for example for setting or maintenance purposes), protection shall be ensured by:

- disabling all other operating (control) modes; and
- other relevant means (see 4.11.9 of ISO 12100-2:2003), that can include, for example, one or more of the following:
 - initiation of operation by a hold-to-run device or by a similar control device;
 - a portable control station with an emergency stop device and, where appropriate, an enabling device. Where a portable control station is in use, initiation of motion shall only be possible from that control station;