

INTERNATIONAL STANDARD

NORME INTERNATIONALE



**Low-voltage switchgear and controlgear –
Part 2: Circuit-breakers**

**Appareillage à basse tension –
Partie 2: Disjoncteurs**



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2024 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de l'IEC ou du Comité national de l'IEC du pays du demandeur. Si vous avez des questions sur le copyright de l'IEC ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de l'IEC de votre pays de résidence.

IEC Secretariat
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

IEC publications search - webstore.iec.ch/advsearchform

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee, ...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

IEC Products & Services Portal - products.iec.ch

Discover our powerful search engine and read freely all the publications previews, graphical symbols and the glossary. With a subscription you will always have access to up to date content tailored to your needs.

Electropedia - www.electropedia.org

The world's leading online dictionary on electrotechnology, containing more than 22 500 terminological entries in English and French, with equivalent terms in 25 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

A propos de l'IEC

La Commission Electrotechnique Internationale (IEC) est la première organisation mondiale qui élabore et publie des Normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

A propos des publications IEC

Le contenu technique des publications IEC est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

Recherche de publications IEC -

webstore.iec.ch/advsearchform

La recherche avancée permet de trouver des publications IEC en utilisant différents critères (numéro de référence, texte, comité d'études, ...). Elle donne aussi des informations sur les projets et les publications remplacées ou retirées.

IEC Just Published - webstore.iec.ch/justpublished

Restez informé sur les nouvelles publications IEC. Just Published détaille les nouvelles publications parues. Disponible en ligne et une fois par mois par email.

Service Clients - webstore.iec.ch/csc

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions contactez-nous: sales@iec.ch.

IEC Products & Services Portal - products.iec.ch

Découvrez notre puissant moteur de recherche et consultez gratuitement tous les aperçus des publications, symboles graphiques et le glossaire. Avec un abonnement, vous aurez toujours accès à un contenu à jour adapté à vos besoins.

Electropedia - www.electropedia.org

Le premier dictionnaire d'électrotechnologie en ligne au monde, avec plus de 22 500 articles terminologiques en anglais et en français, ainsi que les termes équivalents dans 25 langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International (IEV) en ligne.



IEC 60947-2

Edition 6.0 2024-09

INTERNATIONAL STANDARD

NORME INTERNATIONALE



**Low-voltage switchgear and controlgear –
Part 2: Circuit-breakers**

**Appareillage à basse tension –
Partie 2: Disjoncteurs**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

COMMISSION
ELECTROTECHNIQUE
INTERNATIONALE

ICS 29.130.20

ISBN 978-2-8322-9521-2

**Warning! Make sure that you obtained this publication from an authorized distributor.
Attention! Veuillez vous assurer que vous avez obtenu cette publication via un distributeur agréé.**

CONTENTS

FOREWORD	15
1 Scope	17
2 Normative references	18
3 Terms and definitions	19
4 Classification	23
4.1 According to the selectivity category, A or B (see 5.4).....	23
4.2 According to the method of controlling the operating mechanism:	23
4.3 According to the provision for maintenance:.....	23
4.4 According to the method of installation:.....	23
4.5 According to the degree of protection provided by the enclosure (see 8.1.12 of IEC 60947-1:2020).....	23
5 Characteristics of circuit-breakers.....	23
5.1 Summary of characteristics	23
5.2 Type of circuit-breaker	23
5.3 Rated and limiting values of the main circuit	23
5.3.1 General	23
5.3.2 Rated voltages	24
5.3.3 Currents	24
5.3.4 Rated frequency	24
5.3.5 Rated duty	24
5.3.6 Short-circuit characteristics	25
5.4 Selectivity categories	27
5.5 Control circuits.....	27
5.5.1 Electrical control circuits.....	27
5.5.2 Air-supply control circuits (pneumatic or electro-pneumatic)	28
5.6 Auxiliary circuits.....	28
5.7 Releases.....	28
5.7.1 Types	28
5.7.2 Characteristics.....	28
5.7.3 Current setting of overcurrent releases	29
5.7.4 Tripping time setting of overcurrent releases	29
5.8 Integral fuses (integrally fused circuit-breakers).....	30
6 Product information	30
6.1 Nature of the information	30
6.2 Marking.....	30
6.3 Instructions for installation, operation and maintenance	32
7 Normal service, mounting and transport conditions.....	32
8 Constructional and performance requirements	32
8.1 Constructional requirements	32
8.1.1 General	32
8.1.2 Withdrawable circuit-breakers.....	33
8.1.3 Isolation.....	33
8.1.4 Clearances and creepage distances	33
8.1.5 Requirements for the safety of the operator	33
8.1.6 List of construction breaks	33
8.1.7 Additional requirements for circuit-breakers provided with a neutral pole	34

8.1.8	Digital inputs and outputs for use with programmable logic controllers (PLCs)	34
8.2	Performance requirements	34
8.2.1	Operating conditions	34
8.2.2	Temperature-rise	37
8.2.3	Dielectric properties	38
8.2.4	Ability to make and break under no load, normal load and overload conditions	39
8.2.5	Ability to make and break under short-circuit conditions	40
8.2.6	Requirements for isolation	40
8.2.7	Specific requirements for integrally fused circuit-breakers	40
8.2.8	Coordination between a circuit-breaker and another short-circuit protective device	41
8.3	Electromagnetic compatibility (EMC)	41
9	Tests	41
9.1	Kind of tests	41
9.1.1	General	41
9.1.2	Type tests	41
9.1.3	Routine tests	41
9.1.4	Special tests	41
9.2	Compliance with constructional requirements	42
9.3	Type tests	42
9.3.1	General	42
9.3.2	Test sequences	43
9.3.3	General test conditions	50
9.3.4	Test sequence I: General performance characteristics	58
9.3.5	Test sequence II: Rated service short-circuit breaking capacity	68
9.3.6	Test sequence III: Rated ultimate short-circuit breaking capacity	69
9.3.7	Test sequence IV: Rated short-time withstand current	71
9.3.8	Test sequence V: Performance of integrally fused circuit-breakers	72
9.3.9	Test sequence VI: Combined test sequence	74
9.3.10	Test sequence VII: Critical DC load current	76
9.3.11	Test sequence VIII: Rated individual pole ultimate short-circuit breaking capacity at phase-to-neutral AC voltage	77
9.4	Routine tests	78
9.4.1	General	78
9.4.2	Mechanical operation tests	78
9.4.3	Verification of the calibration of overcurrent releases	79
9.4.4	Verification of the operation of undervoltage and shunt releases	79
9.4.5	Additional tests for CBRs	80
9.4.6	Dielectric tests	80
9.4.7	Test for the verification of clearances less than those corresponding to case A of Table 13 of IEC 60947-1:2020	81
9.5	Special tests – Damp heat, salt mist, vibration and shock	81
Annex A (normative)	Coordination between a circuit-breaker and another short-circuit protective device associated in the same circuit	84
A.1	General	84
A.2	Object	84
A.3	General requirements for the co-ordination of a circuit-breaker with another SCPD	84

A.4	Type and characteristics of the associated SCPD	84
A.5	Verification of selectivity	84
A.6	Verification of back-up protection	84
Annex B	(normative) Circuit-breakers incorporating residual current protection (CBRs)	86
B.1	General.....	86
B.1.1	Preamble	86
B.1.2	Object.....	86
B.2	Terms and definitions.....	87
B.2.1	Terms and definitions relating to currents flowing from live parts to earth.....	87
B.2.2	Terms and definitions relating to the energization of a CBR	87
B.2.3	Terms and definitions relating to the operation and the functions of a CBR	88
B.2.4	Terms and definitions relating to values and ranges of energizing quantities	89
B.3	Classification	90
B.3.1	Classification according to the method of operation of the residual current function	90
B.3.2	Classification according to the possibility of adjusting the residual operating current	90
B.3.3	Classification according to time delay of the residual current function.....	90
B.3.4	Classification according to behaviour in presence of a DC component	90
B.4	Characteristics of CBRs concerning their residual current function.....	90
B.4.1	Rated values	90
B.4.2	Preferred and limiting values	91
B.4.3	Value of the rated residual short-circuit making and breaking capacity ($I_{\Delta m}$)	92
B.4.4	Operating characteristics in the case of an earth fault current in the presence or absence of a DC component	92
B.5	Marking.....	93
B.6	Normal service, mounting and transport conditions	95
B.7	Design and operating requirements.....	95
B.7.1	Design requirements.....	95
B.7.2	Operating requirements	95
B.7.3	Electromagnetic compatibility	99
B.8	Tests	99
B.8.1	Test sequences	99
B.8.2	Verification of the operating characteristics	102
B.8.3	Verification of dielectric properties.....	104
B.8.4	Verification of the operation of the test device at the limits of rated voltage	104
B.8.5	Verification of the limiting value of the non-operating current under overcurrent conditions	105
B.8.6	Verification of the resistance against unwanted tripping due to surge currents resulting from impulse voltages	105
B.8.7	Additional verifications for CBRs of types A and B	106
B.8.8	Additional verifications for CBRs of type B.....	108
B.8.9	Verification of the behaviour of CBRs functionally dependent on line voltage classified under B.3.1.2.1	113
B.8.10	Verification of the behaviour of CBRs functionally dependent on line voltage classified under B.3.1.2.2	113

B.8.11	Verification of the residual short-circuit making and breaking capacity	114
B.8.12	Verification of the effects of environmental conditions.....	115
B.8.13	Verification of electromagnetic compatibility	116
B.8.14	Test for variations or interruptions of voltage and for voltage dips.....	118
Annex C (normative)	Individual pole short-circuit test sequence.....	130
C.1	General.....	130
C.2	Test of individual pole short-circuit breaking capacity.....	130
C.3	Verification of dielectric withstand and leakage current	130
C.4	Verification of overload releases	130
Annex D (normative)	Additional requirements for circuit-breakers intended for connection of aluminium conductors	131
D.1	General.....	131
D.2	Terms and definitions.....	131
D.3	Classification	132
D.4	Characteristics.....	132
D.5	Product information.....	132
D.5.1	Nature of information	132
D.5.2	Marking	132
D.5.3	Instructions for installation, operation and maintenance.....	132
D.6	Normal service, mounting and transport conditions	132
D.7	Constructional and performance requirements.....	133
D.8	Tests	133
D.8.1	General	133
D.8.2	Current cycling test.....	134
D.8.3	Climatic test.....	138
D.8.4	Mechanical properties of terminals	139
D.8.5	Test for insertability of unprepared round aluminium conductors having the maximum cross-section	139
Annex E (informative)	Items subject to agreement between manufacturer and user	143
Annex F (normative)	Additional tests for circuit-breakers with electronic overcurrent protection	144
F.1	General.....	144
F.2	List of tests	144
F.2.1	General	144
F.2.2	Electromagnetic compatibility (EMC) tests	144
F.2.3	Suitability for multiple frequencies	145
F.2.4	Dry heat test.....	145
F.2.5	Damp heat test	145
F.2.6	Temperature variation cycles at a specified rate of change	145
F.3	General test conditions	145
F.3.1	General	145
F.3.2	Electromagnetic compatibility tests	145
F.4	Immunity tests	146
F.4.1	Harmonic currents	146
F.4.2	Electrostatic discharges.....	147
F.4.3	Radiated RF electromagnetic fields	147
F.4.4	Electrical fast transient/burst (EFT/B)	148
F.4.5	Surges.....	148
F.4.6	Conducted disturbances induced by RF fields (common mode).....	148

F.4.7	Current dips.....	149
F.5	Emission tests	149
F.5.1	Harmonics	149
F.5.2	Voltage fluctuations	149
F.5.3	Conducted RF disturbances (150 kHz to 30 MHz).....	150
F.5.4	Radiated RF disturbances (30 MHz to 6 000 MHz).....	150
F.6	Suitability for multiple frequencies.....	150
F.6.1	General	150
F.6.2	Test conditions	150
F.6.3	Test procedure	150
F.6.4	Test results.....	151
F.7	Dry heat test	151
F.7.1	Test procedure	151
F.7.2	Test results.....	151
F.7.3	Verification of overload releases	151
F.8	Damp heat test	151
F.8.1	Test procedure	151
F.8.2	Verification of overload releases	152
F.9	Temperature variation cycles at a specified rate of change	152
F.9.1	Test conditions	152
F.9.2	Test procedure	152
F.9.3	Test results.....	152
F.9.4	Verification of overload releases	152
Annex G (normative)	Power loss	167
G.1	General.....	167
G.2	Determination method	167
G.2.1	AC circuit-breakers of rated current exceeding 400 A	167
G.2.2	AC circuit-breakers of rated current not exceeding 400 A	168
G.2.3	DC circuit-breakers	168
G.3	Test conditions	168
G.4	Test method.....	169
G.4.1	General	169
G.4.2	Voltage drop measurements	169
G.4.3	Current measurement	169
Annex H (normative)	Test sequence for circuit-breakers for IT systems	172
H.1	General.....	172
H.2	Individual pole short-circuit	172
H.3	Verification of dielectric withstand and leakage current	173
H.4	Verification of overload releases	173
H.5	Marking.....	173
Annex I	Vacant	174
Annex J (normative)	Electromagnetic compatibility (EMC) – Requirements and test methods for circuit-breakers.....	175
J.1	General.....	175
J.2	Immunity	176
J.2.1	General	176
J.2.2	Electrostatic discharges.....	178
J.2.3	Radiated RF electromagnetic fields	179
J.2.4	Electrical fast transients/bursts (EFT/B).....	179

J.2.5	Surges	179
J.2.6	Conducted disturbances induced by RF fields (common mode)	180
J.3	Emission	180
J.3.1	General	180
J.3.2	Conducted RF disturbances (150 kHz to 30 MHz)	181
J.3.3	Radiated RF disturbances (30 MHz to 6 000 MHz)	181
Annex K (informative)	Glossary of symbols and graphical representation of characteristics	187
Annex L (normative)	Circuit-breakers not fulfilling the requirements for overcurrent protection (CBIs)	196
L.1	General	196
L.2	Terms and definitions	196
L.3	Classification	196
L.4	Characteristics	197
L.4.1	Rated current (I_n)	197
L.4.2	Rated conditional short-circuit current (I_{cc})	197
L.4.3	Other characteristics	197
L.5	Product information	197
L.6	Constructional and performance requirements	198
L.7	Tests	198
L.7.1	General	198
L.7.2	Rated conditional short-circuit current tests	200
L.7.3	Routine tests	202
Annex M (normative)	Modular residual current devices (without integral current breaking device)	203
M.1	General	203
M.1.1	Preamble	203
M.1.2	Object	203
M.2	Terms and definitions	203
M.2.1	Terms and definitions relating to the energization of an MRCD	203
M.2.2	Terms and definitions relating to the operation and the functions of an MRCD	204
M.3	Classification	204
M.3.1	Classification according to the configuration of the primary conductors	204
M.3.2	Classification according to the method of operation	204
M.3.3	Classification according to the possibility of adjusting the residual operating current	205
M.3.4	Classification according to time delay of the residual current function	205
M.3.5	Classification according to behaviour in presence of a DC component	205
M.4	Characteristics of MRCDs	205
M.4.1	General characteristics	205
M.4.2	Characteristics of MRCDs concerning their residual current function	206
M.4.3	Behaviour under short-circuit conditions	206
M.4.4	Preferred and limiting values	207
M.5	Product information	207
M.6	Normal service, mounting and transport conditions	209
M.7	Design and operating requirements	209
M.7.1	Design requirements	209
M.7.2	Operating requirements	209

M.8	Tests	212
M.8.1	General	212
M.8.2	Compliance with constructional requirements	213
M.8.3	Verification of the operating characteristics	213
M.8.4	Verification of dielectric properties	215
M.8.5	Verification of the operation of the test device at the limits of the rated voltage	216
M.8.6	Verification of the limiting value of non-operating current under overcurrent conditions, in the case of a single phase load	216
M.8.7	Verification of the resistance against unwanted tripping due to surge currents resulting from impulse voltages	216
M.8.8	Verification of the behaviour in the case of an earth fault current comprising a DC component	217
M.8.9	Verification of the behaviour of MRCDs with separate sensing means in the case of a failure of the sensing means connection	221
M.8.10	Verification of temperature-rise of terminal type MRCDs	221
M.8.11	Verification of mechanical and electrical endurance	222
M.8.12	Verification of the behaviour of MRCDs classified under M.3.2.2.1 in the case of failure of the voltage source	222
M.8.13	Verification of the behaviour of MRCDs classified under M.3.2.2.2 in the case of failure of the voltage source	223
M.8.14	Verification of the behaviour of MRCDs under short-circuit conditions	223
M.8.15	Verification of the effects of environmental conditions	225
M.8.16	Verification of electromagnetic compatibility	226
Annex N (normative)	Electromagnetic compatibility (EMC) – Additional requirements and test methods for devices not covered by Annex B, Annex F and Annex M	250
N.1	General	250
N.1.1	Overview	250
N.1.2	General test conditions	250
N.2	Immunity	250
N.2.1	General	250
N.2.2	Electrostatic discharges	251
N.2.3	Radiated RF electromagnetic fields	251
N.2.4	Electrical fast transients/bursts (EFT/B)	251
N.2.5	Surges	252
N.2.6	Conducted disturbances induced by RF fields (common mode)	252
N.2.7	Voltage dips and interruptions	252
N.3	Emission	252
N.3.1	General	252
N.3.2	Conducted RF disturbances (150 kHz to 30 MHz)	253
N.3.3	Radiated RF disturbances (30 MHz to 6 000 MHz)	253
Annex O (normative)	Instantaneous trip circuit-breakers (ICBs)	254
O.1	General	254
O.2	Terms and definitions	254
O.3	Rated values	254
O.3.1	General	254
O.3.2	Rated current (I_n)	254
O.3.3	Rated short-circuit making capacity	254
O.3.4	Rated short-circuit breaking capacities	255
O.4	Product information	255

O.5	Constructional and performance requirements	255
O.6	Tests	256
O.6.1	Test sequence of the ICB alone	256
O.6.2	ICB associated with a specified protected device (i.e. motor-starter or overload relay).....	256
Annex P	(normative) DC circuit-breakers for use in photovoltaic (PV) applications	257
P.1	Field of application.....	257
P.2	Terms and definitions.....	257
P.3	Classification	257
P.4	Characteristics of PV circuit-breakers	257
P.5	Product information.....	258
P.6	Normal service, mounting and transport conditions	258
P.7	Constructional and performance requirements	258
P.7.1	Constructional requirements	258
P.7.2	Performance requirements.....	258
P.7.3	Electromagnetic compatibility (EMC)	259
P.8	Tests	259
P.8.1	Kind of tests	259
P.8.2	Compliance with constructional requirements	259
P.8.3	Type tests.....	259
P.8.4	Routine tests	261
P.8.5	Special tests.....	261
Annex Q	Vacant.....	262
Annex R	(normative) Circuit-breakers incorporating residual current protection with automatic reclosing functions (CBARs)	263
R.1	General.....	263
R.1.1	Preamble	263
R.1.2	Field of application	263
R.2	Terms and definitions.....	264
R.3	Classification	265
R.3.1	According to the method of construction	265
R.3.2	According to the method of automatic reclosing	265
R.4	Characteristics	265
R.4.1	Rated automatic reclosing operating residual current ($I_{\Delta ar}$).....	265
R.4.2	Maximum number of consecutive reclosing operations.....	265
R.5	Marking and instructions	265
R.6	Normal service, mounting and transport conditions	266
R.7	Design and operating requirements.....	266
R.7.1	Design requirements.....	266
R.7.2	Operating requirements	267
R.8	Tests	268
R.8.1	General conditions.....	268
R.8.2	Verification of the non-reclosing after tripping under overcurrent conditions	268
R.8.3	Verification of the non-reclosing after intentional opening	268
R.8.4	Verification of the automatic reclosing function after tripping on earth fault.....	269
R.8.5	Verification of mechanical endurance	270
R.8.6	Verification of the isolation function	270

R.8.7	Verification of residual short-circuit making and breaking capacity	271
R.8.8	Verification of the automatic reclosing function after the test sequences of Clause B.8.....	271
R.8.9	Test items for external type automatic reclosing devices.....	272
Bibliography.....		274
Figure 1 – Test arrangement (connecting cables not shown) for short-circuit tests		82
Figure 2 – Examples of application of the test force for the verification of the effectiveness of the indication of the main contact position (first criterion, actuator being left free)		83
Figure A.1 – Cable connections for conditional short-circuit breaking capacity tests in the case of a single pole under phase-to-neutral AC voltage (C1)		85
Figure B.1 – Test circuit for the verification of the operating characteristic (see B.8.2).....		118
Figure B.2 – Test circuit for the verification of the limiting value of the non-operating current under overcurrent conditions (see B.8.5).....		119
Figure B.3 – Test circuit for the verification of the behaviour of CBRs classified under B.3.1.2.2 (see B.8.10).....		120
Figure B.4 – Current ring wave 0,5 µs/100 kHz		121
Figure B.5 – Example of a test circuit for the verification of resistance to unwanted tripping		121
Figure B.6 – Surge current wave 8/20 µs		122
Figure B.7 – Test circuit for the verification of resistance to unwanted tripping in the case of flashover without follow-on current		122
Figure B.8 – Test circuit for the verification of the correct operation of CBRs, in the case of residual pulsating direct currents		123
Figure B.9 – Test circuit for residual pulsating direct current superimposed by a smooth direct current		124
Figure B.10 – Test circuit for residual alternating currents superimposed by a smooth direct current		125
Figure B.11 – Test circuit for residual pulsating direct currents which can result from rectifying circuits supplied from two phases		126
Figure B.12 – Test circuit for residual pulsating direct currents which can result from rectifying circuits supplied from three phases.....		127
Figure B.13 – Test circuit for residual smooth direct current.....		128
Figure B.14 – Test circuit for composite residual currents and residual sinusoidal alternating current up to 1 000 Hz		129
Figure D.1 – General test arrangement		135
Figure D.2 – Mounting of terminals for the current cycling test		135
Figure F.1 – Representation of test current produced by back-to-back thyristors in accordance with F.4.1		153
Figure F.2 – Test circuit for immunity and emission tests in accordance with F.4.1.3, F.4.2, F.4.3, F.4.6, F.4.7.1, F.5.4 and F.6.3 – Two phase poles in series		154
Figure F.3 – Test circuit for immunity and emission tests in accordance with F.4.1.3, F.4.2, F.4.3, F.4.6, F.4.7.1, F.5.4 and F.6.3 – Three phase poles in series.....		154
Figure F.4 – Test circuit for immunity and emission tests in accordance with F.4.1.3, F.4.2, F.4.3, F.4.6, F.4.7.1, F.5.4 and F.6.3 – Three-phase connection		155
Figure F.5 – Test current for the verification of the influence of the current dips and interruptions in accordance with F.4.7.1		155
Figure F.6 – Circuit for electrical fast transients/bursts (EFT/B) immunity test in accordance with F.4.4 – Two phase poles in series.....		156

Figure F.7 – Circuit for electrical fast transients/bursts (EFT/B) immunity test in accordance with F.4.4 – Three phase poles in series	156
Figure F.8 – Circuit for electrical fast transients/bursts (EFT/B) immunity test in accordance with F.4.4 – Three-phase connection	157
Figure F.9 – Test circuit for the verification of the influence of surges in the main circuit (line-to-earth) in accordance with F.4.5 – Two phase poles in series.....	157
Figure F.10 – Test circuit for the verification of the influence of surges in the main circuit (line-to-earth) in accordance with F.4.5 – Three phase poles in series.....	158
Figure F.11 – Test circuit for the verification of the influence of surges in the main circuit (line-to-earth) in accordance with F.4.5 – Three-phase connection	158
Figure F.12 – Test circuit for the verification of the influence of current surges in the main circuit in accordance with F.4.5 – Two phase poles in series	159
Figure F.13 – Test circuit for the verification of the influence of current surges in the main circuit in accordance with F.4.5 – Three phase poles in series	159
Figure F.14 – Test circuit for the verification of the influence of current surges in the main circuit in accordance with F.4.5 – Three-phase connection	160
Figure F.15 – Temperature variation cycles at a specified rate of change in accordance with F.9.1	160
Figure F.16 – General test set-up for immunity tests	161
Figure F.17 – Test set-up for the verification of immunity to radiated RF electromagnetic fields	162
Figure F.18 – Test set-up for the verification of immunity to electrical fast transients/bursts (EFT/B) on power lines	163
Figure F.19 – Test set-up for verification of immunity to electrical fast transients/bursts (EFT/B) on signal lines	163
Figure F.20 – General test set-up for the verification of immunity to conducted disturbances induced by RF fields (common mode)	164
Figure F.21 – Arrangement of connections for the verification of immunity to conducted disturbances induced by RF fields – Two phase poles in series configuration	164
Figure F.22 – Arrangement of connections for the verification of immunity to conducted disturbances induced by RF fields – Three phase poles in series configuration.....	165
Figure F.23 – Arrangement of connections for the verification of immunity to conducted disturbances induced by RF fields – Three-phase configuration	166
Figure G.1 – Power loss measurement circuit for AC circuit-breakers	169
Figure G.2 – Power loss measurement circuit for AC circuit-breakers with rated current not exceeding 400 A and DC circuit-breakers.....	170
Figure G.3 – Measurement points for circuit-breakers with a single pole per phase.....	170
Figure G.4 – Measurement points for circuit-breakers with multiple poles per phase	171
Figure J.1 – EUT mounted in a metallic enclosure	182
Figure J.2 – Test set up for the measurement of radiated RF emissions.....	183
Figure J.3 – Test set up for the verification of immunity to electrostatic discharges	184
Figure J.4 – Test set up for the verification of immunity to radiated RF electromagnetic fields.....	185
Figure J.5 – Test set up for the verification of immunity to electrical fast transients/bursts (EFT/B) on power lines	186
Figure J.6 – Test set up for the verification of immunity to electrical fast transients/bursts (EFT/B) on signal lines.....	186
Figure K.1 – Relationship between symbols and tripping characteristics	189

Figure K.2 – Template for characteristics of cut-off current versus prospective current from 1 kA to 200 kA	190
Figure K.3 – Template for characteristics of cut-off current versus prospective current from 0,01 kA to 200 kA	191
Figure K.4 – Template for characteristics of let-through energy versus prospective current from 1 kA to 200 kA	192
Figure K.5 – Template for characteristics of let-through energy versus prospective current from 0,01 kA to 200 kA.....	193
Figure K.6 – Example of the use of template to Figure K.2.....	194
Figure K.7 – Example of the use of template to Figure K.4.....	195
Figure M.1 – Test circuits for the verification of operation in the case of a steady increase of residual current.....	227
Figure M.2 – Test circuits for the verification of operation in the case of a sudden appearance of residual current (with current breaking device).....	228
Figure M.3 – Test circuits for the verification of operation in the case of a sudden appearance of residual current (without current breaking device).....	229
Figure M.4 – Test circuits for the verification of the limiting value of non-operating current under overcurrent conditions.....	230
Figure M.5 – Test circuits for the verification of the resistance to unwanted tripping in the case of loading of the network capacitance	231
Figure M.6 – Test circuit for the verification of the resistance to unwanted tripping in the case of flashover without follow-on current.....	232
Figure M.7 – Test circuits for the verification of operation in the case of a continuous rise of a residual pulsating direct current	233
Figure M.8 – Test circuits for the verification of operation in the case of a sudden appearance of residual pulsating direct current (without current-breaking device).....	234
Figure M.9 – Test circuits for the verification of operation in the case of a sudden appearance of residual pulsating direct current (with current-breaking device).....	235
Figure M.10 – Test circuits for the verification of operation in the case of a residual pulsating direct current superimposed by a smooth direct current	236
Figure M.11 – Test circuits for the verification of operation in the case of a slowly rising residual smooth direct current.....	237
Figure M.12 – Test circuits for the verification of operation in the case of a sudden appearance of residual smooth direct current (without current-breaking device).....	238
Figure M.13 – Test circuits for the verification of operation in the case of a sudden appearance of residual smooth direct current (with current-breaking device)	239
Figure M.14 – Test circuits for the verification of the correct operation in the case of residual direct currents which can result from rectifying circuits supplied from three phases.....	240
Figure M.15 – Test circuits for the verification of the correct operation in the case of residual direct currents which can result from rectifying circuits supplied from two phases.....	241
Figure M.16 – Test circuits for the verification of correct operation in the case of composite residual currents and residual sinusoidal alternating current up to 1 000 Hz.....	242
Figure M.17 – Test circuits for the verification of the correct operation in the case of a residual alternating current superimposed on a smooth direct current	243
Figure M.18 – Test circuit for the verification of the behaviour of MRCDs with separate sensing means in the case of a failure of the connection of the sensing means.....	244
Figure M.19 – Test circuit for the verification of the behaviour of MRCD with separate sensing means under short-circuit conditions	245

Figure M.20 – Test circuit for the verification of the behaviour of MRCD with integral sensing means under short-circuit conditions	246
Figure M.21 – Test circuit for the verification of the behaviour of terminal-type MRCDs under short-circuit conditions	247
Figure M.22 – Verification of immunity to radiated RF electromagnetic fields – Test set-up for MRCDs with separate sensing means (in addition to the test of Annex B)	248
Figure M.23 – Verification of immunity to electrical fast transients/bursts (EFT/B) on the sensing means connection of an MRCD with separate sensing means (in addition to the test of Annex B)	248
Figure M.24 – Verification of immunity to conducted disturbances induced by RF fields – Test setup for MRCD with separate sensing means (in addition to the test of Annex B)	249
Figure R.1 – Test circuit for the verification of the automatic reclosing functions	273
Table 1 – Ratio n between short-circuit making capacity and short-circuit breaking capacities and related power factor for AC circuit-breakers	26
Table 2 – Minimum values of rated short-time withstand current	27
Table 3 – Preferred values of the rated control circuit supply voltage, if different from that of the main circuit	28
Table 4 – Product information	30
Table 5 – Characteristics of the opening operation of inverse time-delay overcurrent opening releases at the reference temperature	36
Table 6 – Temperature-rise limits for terminals and accessible parts	38
Table 7 – Number of operating cycles	40
Table 8 – Type tests	41
Table 9 – Alphabetical index of tests	43
Table 10 – Overall schema of test sequences	44
Table 11 – Applicability of test sequences according to the relationship between I_{CS} , I_{CU} and I_{CW}	46
Table 12 – Alternative test programmes for AC circuit-breakers	47
Table 13 – Applicability of tests or test sequences to 1, 2 and 4-pole circuit-breakers according to the alternative programme 1 of 9.3.2.4	48
Table 14 – Applicability of tests or test sequences to 1, 2 and 3-pole circuit-breakers according to the alternative programme 2 of 9.3.2.4	49
Table 15 – Number of samples for test	52
Table 16 – Values of power factors and time constants corresponding to test currents	54
Table 17 – Tests of test sequence I	58
Table 18 – Test circuit characteristics for overload performance	66
Table 19 – Tests of test sequence II	68
Table 20 – Tests of test sequence III	70
Table 21 – Tests of test sequence IV	71
Table 22 – Tests of test sequence V	72
Table 23 – Tests of test sequence VI	75
Table 24 – Tests of test sequence VIII	77
Table B.1 – Operating characteristic in the case of sinusoidal residual current for non-time-delay type	91

Table B.2 – Operating characteristics in the case of sinusoidal residual currents, for time-delay type having a limiting non-actuating time of 0,06 s	92
Table B.3 – Product information	94
Table B.4 – Requirements for CBRs functionally dependent on line voltage	99
Table B.5 – Additional test sequences	101
Table B.6 – Tripping current range for CBRs in the case of an earth fault comprising a DC component	107
Table B.7 – Composite test current definition and starting current value	108
Table B.8 – Operating current range for composite residual current	109
Table B.9 – Operating limits for residual sinusoidal alternating currents up to 1 000 Hz	110
Table C.1 – Tests of Annex C	130
Table D.1 – List of tests for terminal connections with aluminium cables	133
Table D.2 – Conductor length for the current cycling test as per conductor cross-section	136
Table D.3 – Equalizer dimensions	136
Table D.4 – Starting test current for the current cycling test	139
Table D.5 – Example of stability factor calculation	140
Table D.6 – Test values for flexion and pull-out test for cables	140
Table D.7 – Test aluminium cables for test currents up to 800 A	141
Table D.8 – Test aluminium bars for test currents above 400 A and up to 3 150 A	142
Table E.1 – List of items subject to agreement between manufacturer and user	143
Table F.1 – Test parameters for current dips and interruptions	149
Table H.1 – Tests of Annex H	172
Table H.2 – Product information	173
Table J.1 – EMC – Immunity tests	176
Table J.2 – Reference data for immunity test specifications	178
Table J.3 – EMC – Emission tests	181
Table J.4 – Reference data for emission test specifications	181
Table K.1 – Glossary of symbols and graphical representation of characteristics	187
Table L.1 – Product information	198
Table L.2 – Rated conditional short-circuit tests when the OCPD is specified	201
Table L.3 – Rated conditional short-circuit tests when the OCPD is not specified	201
Table M.1 – Product information	208
Table M.2 – Requirements for MRCDs with voltage source	211
Table M.3 – Test sequences	212
Table O.1 – Product information	255
Table P.1 – Rated impulse withstand levels for PV circuit-breakers	257
Table P.2 – Product information	258
Table P.3 – Number of operating cycles	259
Table R.1 – Product information	266
Table R.2 – Test sequences for external type automatic re-closing devices	272

INTERNATIONAL ELECTROTECHNICAL COMMISSION

LOW-VOLTAGE SWITCHGEAR AND CONTROLGEAR –

Part 2: Circuit-breakers

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) IEC draws attention to the possibility that the implementation of this document may involve the use of (a) patent(s). IEC takes no position concerning the evidence, validity or applicability of any claimed patent rights in respect thereof. As of the date of publication of this document, IEC had not received notice of (a) patent(s), which may be required to implement this document. However, implementers are cautioned that this may not represent the latest information, which may be obtained from the patent database available at <https://patents.iec.ch>. IEC shall not be held responsible for identifying any or all such patent rights.

IEC 60947-2 has been prepared by subcommittee 121A: Low-voltage switchgear and controlgear, of IEC technical committee 121: Switchgear and controlgear and their assemblies for low-voltage. It is an International Standard.

This sixth edition cancels and replaces the fifth edition published in 2016 and its Amendment 1: 2019. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) suitability for isolation (see Clause 1);
- b) removal of the classification according to the interrupting medium, according to the design, according to the suitability for isolation (see Clause 4);
- c) adjustment of current settings with an external device connectable to the release (see 5.7.3);

- d) requirements for circuits with protective separation (see 8.2.3.8);
- e) additional tests for ground-fault overcurrent releases (see 9.3.4.2.5);
- f) additional tests concerning dielectric properties in tripped position (see 9.3.4.3);
- g) use of DC voltage for dielectric tests (see 9.3.4.6.2 and 9.4.6);
- h) tests of individual pole breaking capacity under phase-to-neutral AC voltage (see 9.3.11);
- i) improvement of measurement of power loss in Annex G;
- j) changes in EMC tests (see Annex J);
- k) introduction of CBI class W in Annex L.

The text of this International Standard is based on the following documents:

Draft	Report on voting
121A/608/FDIS	121A/621/RVD

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/publications.

A list of all parts in the IEC 60947 series, published under the general title *Low-voltage switchgear and controlgear*, can be found on the IEC website.

This International Standard is to be used in conjunction with IEC 60947-1:2020.

The provisions of the general rules dealt with in IEC 60947-1 are applicable to this document, where specifically called for. Clauses and subclauses, tables, figures and annexes of the general rules thus applicable are identified by reference to IEC 60947-1:2020.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn, or
- revised.

IMPORTANT – The "colour inside" logo on the cover page of this document indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

LOW-VOLTAGE SWITCHGEAR AND CONTROLGEAR –

Part 2: Circuit-breakers

1 Scope

This document applies to circuit-breakers, intended to be installed and operated by instructed or skilled persons, the main contacts of which are intended to be connected to circuits, the rated voltage of which does not exceed 1 000 V AC or 1 500 V DC; it also contains additional requirements for integrally fused circuit-breakers.

This document also applies to circuit-breakers with ratings at or below 1 000 V AC, additionally having one or more ratings above 1 000 V AC but not exceeding 1 500 V AC.

It applies whatever the rated currents, the method of construction or the proposed applications of the circuit-breakers may be.

Circuit-breakers per this document are suitable for isolation.

The requirements for circuit-breakers which are also intended to provide residual current protection are contained in Annex B.

Additional requirements for circuit-breakers intended for connection of aluminium conductors are contained in Annex D.

The additional requirements for circuit-breakers with electronic overcurrent protection are contained in Annex F.

The additional requirements for circuit-breakers for IT systems are contained in Annex H.

The requirements and test methods for electromagnetic compatibility of circuit-breakers are contained in Annex J.

The requirements for circuit-breakers not fulfilling the requirements for overcurrent protection are contained in Annex L.

The requirements for modular residual current devices (without integral current breaking device) are contained in Annex M.

The requirements and test methods for electromagnetic compatibility of circuit-breaker auxiliaries are contained in Annex N.

The requirements for instantaneous trip circuit-breakers are contained in Annex O.

The requirements and test methods for DC circuit-breakers for use in photovoltaic (PV) applications are contained in Annex P.

The requirements and test methods for circuit-breakers incorporating residual current protection with automatic reclosing functions are contained in Annex R.

Supplementary requirements for circuit-breakers used as direct-on-line starters are given in IEC 60947-4-1, applicable to low-voltage contactors and starters.

The requirements for circuit-breakers for overcurrent protection for household and similar installations, and designed for use by uninstructed persons, are contained in IEC 60898 series.

The requirements for circuit-breakers for equipment (for example electrical appliances) are contained in IEC 60934.

For certain specific applications (for example traction, rolling mills, marine service, downstream of variable frequency drives, use in explosive atmospheres), particular or additional requirements can be applicable.

NOTE 1 Circuit-breakers can have dedicated accessories.

NOTE 2 Circuit-breakers which are dealt with in this document can be provided with devices for automatic opening under predetermined conditions other than those of overcurrent and undervoltage as, for example, reversal of power or current. This document does not deal with the verification of operation under such pre-determined conditions.

The object of this document is to state:

- a) the characteristics of circuit-breakers;
- b) the requirements for circuit-breakers with reference to:
 - 1) operation and behaviour in normal service;
 - 2) operation and behaviour in case of overload, operation and behaviour in case of short-circuit, including co-ordination in service (selectivity and back-up protection), as well as the operation and behaviour in case of ground-fault;
 - 3) dielectric properties;
 - 4) requirements on electromagnetic compatibility, where applicable;
- c) tests intended for confirming that these conditions have been met and the methods to be adopted for these tests;
- d) information to be marked on or given with the circuit-breakers.

NOTE 3 For cybersecurity requirements, see IEC TS 63208.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60068-2-14, *Environmental testing – Part 2-14: Tests – Test N: Change of temperature*

IEC 60068-2-30, *Environmental testing – Part 2-30: Tests – Test Db: Damp heat, cyclic (12 h ± 12 h cycle)*

IEC 60228, *Conductors of insulated cables*

IEC 60664-1:2020, *Insulation coordination for equipment within low-voltage systems – Part 1: Principles, requirements and tests*

IEC 60947-1:2020, *Low-voltage switchgear and controlgear – Part 1: General rules*

IEC 60947-4-1, *Low-voltage switchgear and controlgear – Part 4-1: Contactors and motor-starters – Electromechanical contactors and motor-starters*

IEC 61000-4-2:2008, *Electromagnetic compatibility (EMC) – Part 4-2: Testing and measurement techniques – Electrostatic discharge immunity test*

IEC 61000-4-3:2020, *Electromagnetic compatibility (EMC) – Part 4-3: Testing and measurement techniques – Radiated, radio-frequency, electromagnetic field immunity test*

IEC 61000-4-4:2012, *Electromagnetic compatibility (EMC) – Part 4-4: Testing and measurement techniques – Electrical fast transient/burst immunity test*

IEC 61000-4-5:2014, *Electromagnetic compatibility (EMC) – Part 4-5: Testing and measurement techniques – Surge immunity test*

IEC 61000-4-5:2014/AMD1:2017

IEC 61000-4-6:2023, *Electromagnetic compatibility (EMC) – Part 4-6: Testing and measurement techniques – Immunity to conducted disturbances, induced by radio-frequency fields*

IEC 61000-4-11:2020, *Electromagnetic compatibility (EMC) – Part 4-11: Testing and measurement techniques – Voltage dips, short interruptions and voltage variations immunity tests for equipment with input current up to 16 A per phase*

IEC 61140:2016, *Protection against electric shock – Common aspects for installation and equipment*

IEC 61545:1996, *Connecting devices – Devices for the connection of aluminium conductors in clamping units of any material and copper conductors in aluminium bodied clamping units*

IEC 62475:2010, *High-current test techniques – Definitions and requirements for test currents and measuring systems*

CISPR 11:2015, *Industrial, scientific and medical equipment – Radio-frequency disturbance characteristics – Limits and methods of measurement*

CISPR 11:2015/AMD1:2016

CISPR 11:2015/AMD2:2019

CISPR 32:2015, *Electromagnetic compatibility of multimedia equipment – Emission requirements*

3 Terms and definitions

For the purposes of this document, the terms and definitions given in IEC 60947-1:2020, as well as the following, apply.

NOTE Where these definitions are taken unchanged from the *International Electrotechnical Vocabulary (IEV)*, IEC 60050-441, the reference to this publication is given in brackets.

ISO and IEC maintain terminology databases for use in standardization at the following addresses:

- IEC Electropedia: available at <https://www.electropedia.org/>
- ISO Online browsing platform: available at <https://www.iso.org/obp>

3.1

circuit-breaker

mechanical switching device, capable of making, carrying and breaking currents under normal circuit conditions and also making, carrying for a specified duration and breaking currents under specified abnormal circuit conditions such as those of short-circuit

[SOURCE: IEC 60050-441:1984, 441-14-20]

3.1.1

frame size

term designating a group of circuit-breakers, the external physical dimensions of which are common to a range of current ratings

Note 1 to entry: Frame size is expressed in amperes corresponding to the highest current rating of the group.

Note 2 to entry: Within a frame size, the width can vary according to the number of poles.

Note 3 to entry: This definition does not imply dimensional standardization.

3.1.2

construction break

significant difference in construction between circuit-breakers of a given frame size, requiring additional type testing

3.2

integrally fused circuit-breaker

combination, in a single device, of a circuit-breaker and fuses, one fuse being placed in series with each pole of the circuit-breaker intended to be connected to a line conductor

[SOURCE: IEC 60050-441:1984, 441-14-22, modified – “phase” replaced with “line”.]

3.3

current-limiting circuit-breaker

circuit-breaker that, within a specified range of current, prevents the let-through current reaching the prospective peak value and which limits the let-through energy (I^2t) to a value less than the let-through energy of a half-cycle wave of the symmetrical prospective current

Note 1 to entry: Reference can be made to either the symmetrical or asymmetrical prospective peak value of let-through current.

Note 2 to entry: The let-through current is also referred to as the cut-off current (see IEC 60050-441:1984, 441-17-12).

Note 3 to entry: Templates for the graphical representation of the cut-off current characteristic and the let-through energy characteristic are given from Figure K.2 to Figure K.5 and examples of the use of the templates in Figure K.6 and in Figure K.7.

3.4

plug-in circuit-breaker

circuit-breaker which, in addition to its interrupting contacts, has a set of contacts which enable the circuit-breaker to be removed

Note 1 to entry: Some circuit-breakers can be of the plug-in type on the line side only, the load terminals being usually suitable for wiring connection.

3.5

withdrawable circuit-breaker

circuit-breaker which, in addition to its interrupting contacts, has a set of isolating contacts which enable the circuit-breaker to be withdrawn from the main circuit, and, in the disconnected position, to achieve an isolating distance in accordance with specified requirements

3.6

making-current release

release which permits a circuit-breaker to open, without any intentional time-delay, during a closing operation, if the making current exceeds a predetermined value, and which is rendered inoperative when the circuit-breaker is in the closed position

3.7

short-circuit release

overcurrent release intended for protection against short circuits

3.8**short-time delay short-circuit release**

overcurrent release intended to operate at the end of the short-time delay

3.9**alarm switch**

auxiliary switch which operates only upon the tripping of the circuit-breaker with which it is associated

3.10**circuit-breaker with lock-out device preventing closing**

circuit-breaker in which each of the moving contacts is prevented from closing sufficiently to be capable of passing current if the closing command is initiated while specified conditions remain established

3.11**short-circuit breaking (or making) capacity**

breaking (or making) capacity for which the prescribed conditions include a short circuit

3.11.1**ultimate short-circuit breaking capacity**

breaking capacity for which the prescribed conditions according to a specified test sequence do not include the capability of the circuit-breaker to carry its rated current continuously

3.11.2**individual pole ultimate short-circuit breaking capacity at phase-to-neutral AC voltage**

ultimate short-circuit breaking capacity which is determined for an individual pole at the phase-to-neutral AC voltage

3.11.3**service short-circuit breaking capacity**

breaking capacity for which the prescribed conditions according to a specified test sequence include the capability of the circuit-breaker to carry its rated current continuously

3.12**opening time**

<of a mechanical switching device> interval of time between the specified instant of initiation of the opening operation and the instant when the arcing contacts have separated in all poles

Note 1 to entry:

- in the case of a directly operated circuit-breaker, the instant of initiation of the opening time is the instant of initiation of a current large enough to cause the circuit-breaker to operate;
- in the case of a circuit-breaker operated by any form of auxiliary power, the instant of initiation of the opening time is the instant of application or removal of the auxiliary power to the opening release.

Note 2 to entry: For circuit-breakers "opening time" is commonly referred to as "tripping time", although, strictly speaking, tripping time applies to the time between the instant of initiation of the opening time and the instant when the opening command becomes irreversible.

[SOURCE: IEC 60947-1:2020, 3.7.39, modified – modification of Note 1 to entry and addition of Note 2 to entry.]

3.13 **I^2t characteristic of a circuit-breaker**

information (usually a curve) giving the maximum values of I^2t related to break time as a function of prospective current (RMS symmetrical for AC) up to the maximum prospective current corresponding to the rated short-circuit breaking capacity and associated voltage

3.14**resetting time**

time elapsed between a circuit-breaker tripping due to an overcurrent and subsequently reaching a condition where it can be reclosed

3.15**instantaneous short-circuit current setting** I_i

current setting of a short-circuit release, above which a current causes its operation without any intentional time-delay

Note 1 to entry: I_i can be non-adjustable

3.16**overload current setting** I_r

current setting of an adjustable overload release

Note 1 to entry: In case of a non-adjustable overload release, this value is equal to the rated current I_n .

3.17**short-time pick-up current setting** I_{sd}

current setting of a short-circuit release, above which a current causes its operation with an intentional time-delay (t_{sd})

3.18**programmable logic controller****PLC**

digitally operating electronic system, designed for use in an industrial environment, which uses a programmable memory for the internal storage of user-oriented instructions for implementing specific functions such as logic, sequencing, timing, counting and arithmetic, to control, through digital or analogue inputs and outputs, various types of machines or processes

Note 1 to entry: Both the PLC and its associated peripherals are designed so that they can be easily integrated into an industrial control system and easily used in all their intended functions.

[SOURCE: IEC 61131-1:2003, 3.5, modified – deletion of the note.]

3.19**closing release****closing coil**

release, energized by a source of voltage, which triggers the closing of the circuit-breaker

Note 1 to entry: A closing release is an auxiliary device of the circuit-breaker, and is different from the "closing device" mentioned in the figures of Annex A, and in IEC 60947-1, which is part of the test setup and is intended to establish the short-circuit current.

4 Classification

4.1 According to the selectivity category, A or B (see 5.4)

4.2 According to the method of controlling the operating mechanism:

- dependent manual operation;
- independent manual operation;
- dependent power operation;
- independent power operation;
- stored energy operation.

4.3 According to the provision for maintenance:

- maintainable;
- non-maintainable.

4.4 According to the method of installation:

- fixed;
- plug-in;
- withdrawable.

4.5 According to the degree of protection provided by the enclosure (see 8.1.12 of IEC 60947-1:2020)

5 Characteristics of circuit-breakers

5.1 Summary of characteristics

The characteristics of a circuit-breaker shall be stated in terms of the following, as applicable:

- type of circuit-breaker (5.2);
- rated and limiting values of the main circuit (5.3);
- selectivity categories (5.4);
- control circuits (5.5);
- auxiliary circuits (5.6);
- releases (5.7);
- integral fuses (integrally fused circuit-breakers) (5.8).

5.2 Type of circuit-breaker

The following shall be stated:

- number of poles;
- kind of current (AC or DC) and, in the case of AC, number of phases and rated frequency.

5.3 Rated and limiting values of the main circuit

5.3.1 General

The rated values established of a circuit-breaker shall be stated in accordance with 5.3.2 to 5.4, but it is not necessary to state I_{th} (5.3.3.1), I_{the} (5.3.3.2), rated frequency (5.3.4) in case of a DC only circuit-breaker, rated duty (5.3.5).

5.3.2 Rated voltages

5.3.2.1 Rated operational voltage (U_e)

Subclause 5.3.1.1 of IEC 60947-1:2020 applies with the following amplification:

- circuit-breakers covered by 5.3.1.1 item a) of IEC 60947-1:2020.

U_e is generally stated as the voltage between phases.

NOTE 1 In Canada and the USA, the rated operational voltage U_e is stated as

- a) the voltage between phases and earth, together with the voltage between phases (for example 277 V/480 V) for three-phase four-wire neutral-earthed systems;
- b) the voltage between phases (for example 480 V) for three-phase three-wire unearthened or impedance earthed systems.

Circuit-breakers for unearthened or impedance earthed systems (IT) require additional tests according to Annex H.

- circuit-breakers covered by 5.3.1.1 item b) of IEC 60947-1:2020.

These circuit-breakers require additional tests according to Annex C.

U_e shall be stated as the voltage between phases preceded by the letter C.

NOTE 2 According to present practice in Canada and the USA, circuit-breakers covered by 5.3.1.1 item b) of IEC 60947-1:2020 are identified by the voltage between phases only.

5.3.2.2 Rated insulation voltage (U_i)

Subclause 5.3.1.2 of IEC 60947-1:2020 applies.

5.3.2.3 Rated impulse withstand voltage (U_{imp})

Subclause 5.3.1.3 of IEC 60947-1:2020 applies.

5.3.3 Currents

5.3.3.1 Conventional free air thermal current (I_{th})

Subclause 5.3.2.1 of IEC 60947-1:2020 applies.

5.3.3.2 Conventional enclosed thermal current (I_{the})

Subclause 5.3.2.2 of IEC 60947-1:2020 applies.

5.3.3.3 Rated current (I_n)

For circuit-breakers, the rated current is the rated uninterrupted current (I_u) (see 5.3.2.4 of IEC 60947-1:2020) and is equal to the conventional free-air thermal current (I_{th}).

5.3.4 Rated frequency

Subclause 5.3.3 of IEC 60947-1:2020 applies.

5.3.5 Rated duty

The rated duties considered as normal are:

- the eight-hour duty (see 5.3.4.1 of IEC 60947-1:2020),
- the uninterrupted duty (see 5.3.4.2 of IEC 60947-1:2020).

5.3.6 Short-circuit characteristics

5.3.6.1 Rated short-circuit making capacity (I_{cm})

The rated short-circuit making capacity of a circuit-breaker is the value of short-circuit making capacity assigned to that circuit-breaker by the manufacturer for the rated operational voltage at rated frequency and at a specified power factor for AC, or time constant for DC. It is expressed as the maximum prospective peak current.

For AC, the rated short-circuit making capacity of a circuit-breaker shall be not less than its rated ultimate short-circuit breaking capacity, multiplied by the factor n of Table 1 (see 5.3.6.3).

For DC, the rated short-circuit making capacity of a circuit-breaker shall be not less than its rated ultimate short-circuit breaking capacity.

A rated short-circuit making capacity implies that the circuit-breaker shall be able to make the current corresponding to that rated capacity at the appropriate applied voltage related to the rated operational voltage.

5.3.6.2 Rated short-circuit breaking capacities

5.3.6.2.1 General

The rated short-circuit breaking capacities of a circuit-breaker are the values of short-circuit breaking capacity assigned to that circuit-breaker by the manufacturer for the rated operational voltage, under specified conditions.

NOTE A circuit-breaker in accordance with this document is able to break line-to-line, line-to-earth, line-to-neutral (AC) and line-to-mid-point (DC) short-circuits

A rated short-circuit breaking capacity requires that the circuit-breaker shall be able to break any value of short-circuit current up to and including the value corresponding to the rated capacity at a power-frequency recovery voltage corresponding to the prescribed test voltage values and:

- for AC, at any power factor not less than those required in 9.3.3.2.4;
- for DC, with any time constant not greater than those required in 9.3.3.2.5.

For power-frequency recovery voltages in excess of the prescribed test voltage values (see 9.3.3.2.6), no short-circuit breaking capacity is guaranteed.

For AC, the circuit-breaker shall be capable of breaking a prospective current corresponding to its rated short-circuit breaking capacity and the related power factor given in 9.3.3.2.4, irrespective of the value of the inherent DC component, on the assumption that the RMS value of the AC component of the prospective current is constant.

The rated short-circuit breaking capacities are stated as:

- rated ultimate short-circuit breaking capacity;
- rated service short-circuit breaking capacity.

5.3.6.2.2 Rated ultimate short-circuit breaking capacity (I_{cu})

The rated ultimate short-circuit breaking capacity of a circuit-breaker is the value of ultimate short-circuit breaking capacity (see 3.11.1) assigned to that circuit-breaker by the manufacturer for the corresponding rated operational voltage, under the conditions specified in 9.3.6. It is expressed as the value of the prospective breaking current, in kA (RMS value of the AC component in the case of AC).

5.3.6.2.3 Rated individual pole ultimate short-circuit breaking capacity at phase-to-neutral AC voltage (I_{cu1})

The rated individual pole ultimate short-circuit breaking capacity at phase-to-neutral AC voltage of a circuit-breaker is the value of individual pole breaking capacity at phase-to-neutral voltage assigned to that circuit-breaker by the manufacturer for the corresponding rated operational voltage, under the conditions specified in 9.3.11. It is expressed as a value of the prospective breaking current, in kA (RMS value of the AC component).

5.3.6.2.4 Rated service short-circuit breaking capacity (I_{cs})

The rated service short-circuit breaking capacity of a circuit-breaker is the value of service short-circuit breaking capacity (see 3.11.3) assigned to that circuit-breaker by the manufacturer for the corresponding rated operational voltage, under the conditions specified in 9.3.5. It is expressed as a value of prospective breaking current, in kA, or as a % of I_{cu} (for example $I_{cs} = 25 \% I_{cu}$).

I_{cs} shall be at least equal to 25 % of I_{cu} .

5.3.6.3 Standard relationship between short-circuit making and breaking capacities and related power factor for AC circuit-breakers

The standard relationship between short-circuit breaking capacity and short-circuit making capacity is given in Table 1.

Table 1 – Ratio n between short-circuit making capacity and short-circuit breaking capacities and related power factor for AC circuit-breakers

Short-circuit breaking capacity kA RMS I	Power factor	Minimum value required for n $n = \frac{\text{short-circuit making capacity}}{\text{short-circuit breaking capacity}}$
$I \leq 1,5$	0,95	1,41
$1,5 < I \leq 3$	0,9	1,42
$3 < I \leq 4,5$	0,8	1,47
$4,5 < I \leq 6$	0,7	1,53
$6 < I \leq 10$	0,5	1,7
$10 < I \leq 20$	0,3	2,0
$20 < I \leq 50$	0,25	2,1
$50 < I$	0,2	2,2

The rated short-circuit making and breaking capacities are only valid when the circuit-breaker is operated in accordance with the requirements of 8.2.1.1 and 8.2.1.2.

For special requirements, the manufacturer may assign a value of rated short-circuit making capacity higher than that required by Table 1. Tests to verify these rated values shall be the subject of agreement between manufacturer and user.

5.3.6.4 Rated short-time withstand current (I_{cw})

The rated short-time withstand current of a circuit-breaker is the value of short-time withstand current assigned to that circuit-breaker by the manufacturer under the test conditions specified in 9.3.7.3.

NOTE 1 The rated short-time withstand current is not influenced by a change of a trip unit.

NOTE 2 The attainable time selectivity in an application depends on the actual short-time pick-up current setting (I_{sd}) and the intentional time delay (t_{sd}) of the trip unit.

For AC, the value of this current is the RMS value of the AC component of the prospective short-circuit current, assumed constant during the short-time delay.

The short-time delay associated with the rated short-time withstand current shall be at least 0,05 s, preferred values being as follows:

$$0,05 \text{ s} - 0,1 \text{ s} - 0,25 \text{ s} - 0,5 \text{ s} - 1 \text{ s}$$

The rated short-time withstand current shall be not less than the appropriate values shown in Table 2.

Table 2 – Minimum values of rated short-time withstand current

Rated current I_n A	Rated short-time withstand current I_{cw} – Minimum values kA
$I_n \leq 2\,500$	12 I_n or 5 kA, whichever is the greater
$I_n > 2\,500$	30 kA

5.4 Selectivity categories

Circuit-breakers according to this document are divided into two selectivity categories:

- **Selectivity category B** comprises circuit-breakers providing selectivity by having a short-time withstand current rating and an associated short-time delay according to 5.3.6.4.

Selectivity of circuit-breakers of selectivity category B is not necessarily ensured up to the ultimate short-circuit breaking capacity (e.g. in the case of operation of an instantaneous release) but at least up to the value specified in Table 2.

- **Selectivity category A** comprises all other circuit-breakers.

These circuit-breakers may provide selectivity under short-circuit conditions by other means.

A circuit-breaker of selectivity category A may have an intentional short-time delay with a short-time withstand current less than that according to 5.3.6.4. In that case, the tests shall include test sequence IV (see 9.3.7) at the assigned short-time withstand current.

Attention is drawn to the differences of the tests applying to the two selectivity categories (see Table 10 and 9.3.5, 9.3.6, 9.3.7 and 9.3.9).

5.5 Control circuits

5.5.1 Electrical control circuits

Subclause 5.5.1 of IEC 60947-1:2020 applies, with the following addition:

If the rated control circuit supply voltage is different from that of the main circuit, it is recommended that its value be chosen from Table 3.

Table 3 – Preferred values of the rated control circuit supply voltage, if different from that of the main circuit

Direct current V	Single-phase alternating current V
24 – 48 – 110 – 125 – 220 – 250	24 – 48 – 110 – 127 – 220 – 230

5.5.2 Air-supply control circuits (pneumatic or electro-pneumatic)

Subclause 5.5.2 of IEC 60947-1:2020 applies.

5.6 Auxiliary circuits

Subclause 5.6 of IEC 60947-1:2020 applies.

5.7 Releases

5.7.1 Types

For the purpose of this document, the following types of releases are considered:

- 1) shunt release;
- 2) overcurrent release:
 - a) instantaneous;
 - b) definite time delay;
 - c) inverse time delay:
 - independent of previous load;
 - dependent on previous load (for example thermal type release);
 - d) ground-fault.

NOTE 1 The term "overload release" is used to identify overcurrent releases intended for protection against overloads (see 3.6.31 of IEC 60947-1:2020). The term "short-circuit release" is used to identify overcurrent releases intended for protection against short circuits (see 3.7); it includes the short-time delay short-circuit release (see 3.8).

NOTE 2 The term "adjustable release" used in this document also includes interchangeable releases.

- 3) undervoltage release (for opening);
- 4) closing release;
- 5) other releases.

5.7.2 Characteristics

The following characteristics shall be considered:

- 1) shunt release and undervoltage release (for opening), and closing release:
 - rated control circuit voltage (U_c);
 - kind of current;
 - rated frequency, if AC
- 2) overcurrent release:
 - rated current (I_n);
 - kind of current;
 - rated frequency, if AC;
 - current setting (or range of settings);
 - time setting (or range of settings) if applicable.

The rated current of an overcurrent release is the value of current (RMS if AC) corresponding to the maximum current setting which it shall be capable of carrying under the test conditions specified in 9.3.3.5, without the temperature-rise exceeding the values specified in Table 6.

5.7.3 Current setting of overcurrent releases

For circuit-breakers fitted with adjustable releases (see Note 2 to 5.7.1, item 2), the current settings shall be marked on the release, or displayed on the release's display, or displayed on an external device's display connectable to the release. The settings may be either directly in amperes or as a multiple of the current value. Means shall be provided by the manufacturer to read the display regardless of the status of the circuit-breaker. When applicable, the manufacturer shall specify the characteristics of the external device.

For circuit-breakers fitted with non-adjustable releases, the marking may be on the circuit-breaker. If the operating characteristics of the overload release comply with the requirements of Table 5, it will be sufficient to mark the circuit-breaker with its rated current (I_n).

The current settings may be adjusted through an external (local or remote) device connectable to the release, in which case either local setting indications shall not be exceeded, or a local indication shall show that the settings are controlled remotely. The manufacturer shall provide means to the testing laboratory to ensure settings do not change during type tests.

In the case of indirect releases operated by current transformers, the marking may refer either to the primary current of the current transformer through which they are supplied, or to the current setting of the overload release. In either case, the ratio of the current transformer shall be stated.

Unless otherwise specified:

- the operating value of overload releases other than those of the thermal type is independent of the ambient air temperature within the limits of -5 °C to $+40\text{ °C}$;
- for releases of the thermal type, the values stated are for a reference temperature of $+30\text{ °C} \pm 2\text{ °C}$. The manufacturer shall state the influence of ambient temperature in the literature (see 8.2.1.2.4, item b)).

5.7.4 Tripping time setting of overcurrent releases

The tripping time shall be stated as follows, depending on the type of overcurrent release:

1) Definite time-delay overcurrent releases

The time-delay of such releases is independent of the overcurrent. The tripping time setting shall be stated as the duration in seconds of the opening time of the circuit-breaker, if the time-delay is not adjustable, or the extreme values of the opening time, if the time-delay is adjustable.

2) Inverse time-delay overcurrent releases

The time-delay of such releases is dependent on the overcurrent.

The time/current characteristics shall be given in the form of curves supplied by the manufacturer. These shall indicate how the opening time, starting from the cold state, varies with current within the range of operation of the release. The manufacturer shall indicate, by suitable means, the tolerances applicable to these curves.

These curves shall be given for each extreme value of the current setting and, if the time setting for a given current setting is adjustable, it is recommended that they be given in addition for each extreme value of the time setting.

It is recommended that the current be plotted as abscissa and the time as ordinate, using logarithmic scales. Furthermore, in order to facilitate the study of co-ordination of different types of overcurrent protection, it is recommended that the current be plotted as multiples of the setting current and the time in seconds on the standard graph sheets detailed in 5.6.1 of IEC 60269-1:2006.

5.8 Integral fuses (integrally fused circuit-breakers)

Subclause 5.8 of IEC 60947-1:2020 applies, replacing "SCPD" with "integral fuse".

6 Product information

6.1 Nature of the information

Subclause 6.1 of IEC 60947-1:2020 applies, as far as appropriate for a particular design.

In addition the manufacturer shall make available, upon request, information concerning typical power losses for the various frame sizes (see 3.1.1). See Annex G.

For the glossary of symbols and graphical representation of characteristics, see Annex K.

6.2 Marking

Each circuit-breaker shall be marked in a durable manner; data to be provided and corresponding locations are indicated in Table 4.

Table 4 – Product information

Item	Information	Location
1.1	rated current (I_n)	Visible
1.2	suitability for isolation with the symbol  (IEC 60617-S00287:2001-07 combined with IEC 60617-S00220:2001-07)	Visible
1.3	indication of the open and closed position with O (IEC 60417-5008:2002-10) and I (IEC 60417-5007:2002-10) respectively, if symbols are used (see 8.1.6.1 of IEC 60947-1:2020)	Visible
2.1	manufacturer's name or trade mark	Marked
2.2	type designation or catalogue reference	Marked
2.3	IEC 60947-2, if the manufacturer claims compliance with this document	Marked
2.4	selectivity category A or B	Marked
2.5	rated operational voltage(s) U_e (see 5.3.2.1 and, where applicable, Annex H)	Marked
2.6	Indication that the circuit-breaker is not suitable for IT systems at all rated voltages with the symbol  (IEC 60417-6363:2016-07). For any exception for specific rated voltages, see H.5.	Marked
2.7	rated impulse withstand voltage (U_{imp})	Marked
2.8	value (or range) of the rated frequency, and/or the indication "DC" (or the symbol ) (IEC 60417-5031:2002-10))	Marked
2.9	rated service short-circuit breaking capacity (I_{cs}) at the corresponding rated voltage (U_e)	Marked
2.10	rated ultimate short-circuit breaking capacity (I_{cu}) at the corresponding rated voltage (U_e)	Marked
2.11	rated individual pole ultimate short-circuit breaking capacity at phase-to-neutral AC voltage (I_{cu1}), at the corresponding rated voltage (U_e), if different from I_{cu}	Marked
2.12	rated short-time withstand current (I_{cw}), and associated short-time delay, for selectivity category B	Marked

Item	Information	Location
2.13	range of the current setting (I_r) of the adjustable overload release	Marked ^a
2.14	value or range (when adjustable) of the short-time pick-up current setting (I_{sd}) of the release and its intended time-delay (t_{sd}), when applicable	Marked ^a
2.15	range of the ground-fault current (I_g) of the adjustable release, when applicable	Marked ^a
2.16	range of the instantaneous short-circuit current setting (I_i), for adjustable releases	Marked ^a
2.17	reference temperature for non-compensated thermal releases, if different from 30 °C	Marked
2.18	terminals identification, according to 8.1.8.4 of IEC 60947-1:2020	Marked
2.19	Identification of line and load terminals, if applicable	Marked
2.20	neutral pole terminals, if applicable, by the letter N	Marked
2.21	protective earth terminal, where applicable, by the symbol (IEC 60417-5019:2006-08)  (see 8.1.10.3 of IEC 60947-1:2020)	Marked
3.1	rated short-circuit making capacity (I_{cm}) at the corresponding rated voltage (U_e), if higher than the minimum values specified in 5.3.6.1	Literature
3.2	rated insulation voltage (U_i), if higher than the maximum rated operational voltage	Literature
3.3	pollution degree if other than 3 (see 7.1.3.2 of IEC 60947-1:2020)	Literature
3.4	conventional enclosed thermal current (I_{the}) if different from the rated current	Literature
3.5	IP code, where applicable (see Annex C of IEC 60947-1:2020)	Literature
3.6	when applicable, minimum enclosure size and ventilation data (if any) to which marked ratings apply	Literature
3.7	details of minimum distance between circuit-breaker and earthed metal parts for circuit-breakers intended for use without enclosures	Literature
3.8	suitability for environment A or environment B per Annex J, as applicable	Literature
3.9	RMS sensing, if applicable, in accordance with F.4.1.1	Literature
3.10	minimum cable cross-section, if different from Table 9 of IEC 60947-1:2020, for ratings ≤ 20 A according to rated ultimate short-circuit breaking capacity I_{cu}	Literature
3.11	values of tightening torque for the circuit-breaker terminals	Literature
3.12	current derating, when applicable, for temperatures higher than the reference temperature	Literature
3.13	influence of ambient temperature, if applicable, on the tripping performance of the overcurrent release (see 5.7.3)	Literature
3.14	current derating for terminals and connections, if applicable	Literature
3.15	method and diagram of series connection of poles (as necessary for each rating) for DC circuit-breakers	Literature
3.16	type of ground-fault detection function (see T.4 of IEC 60947-1:2020)	Literature
3.17	value of the instantaneous short-circuit current setting (I_i), for non-adjustable releases	Literature
3.18	number of poles	Literature
3.19	further information concerning aluminum conductors (see D.5.2)	Literature
4.1	for closing releases (see 3.19) and/or motor-operators, rated control circuit voltage, kind of current and rated frequency for AC	Aux

Item	Information	Location
4.2	rated control circuit voltage of the shunt release and/or of the undervoltage release (or of the no-voltage release), kind of current and rated frequency for AC	Aux
4.3	rated current of indirect overcurrent releases (see 5.7.3)	Aux
4.4	number and type of auxiliary contacts, rated operational currents at the rated operational voltages, and rated frequency for AC	Aux
Key Visible: visible from the front when the circuit-breaker is installed as in service and the actuator is accessible Marked: marked on the circuit-breaker Literature: provided in the manufacturer's literature Aux: marked on the auxiliaries or on the circuit-breaker, if marking space is sufficient; additionally, data shall be made available in the manufacturer's literature		
^a Where applicable, settings of I_r , I_i , I_{sd} and I_g may be displayed on the display of the release or of an external device instead of being marked (see 5.7.3).		

6.3 Instructions for installation, operation and maintenance

Subclause 6.3 of IEC 60947-1:2020 applies with the following addition:

Additional information for the decommissioning and dismantling of the circuit-breaker shall be provided to the user in the case of a foreseeable hazardous condition, for example due to stored energy or hazardous substances.

7 Normal service, mounting and transport conditions

Clause 7 of IEC 60947-1:2020 applies with the following addition:

Pollution degree (see 7.1.3.2 of IEC 60947-1:2020).

Unless otherwise stated by the manufacturer, a circuit-breaker is intended for installation under environmental conditions of pollution degree 3.

8 Constructional and performance requirements

8.1 Constructional requirements

8.1.1 General

Subclause 8.1 of IEC 60947-1:2020 applies with the following modifications:

- a) Where, in 8.1.2.2 of IEC 60947-1:2020, the test temperature is to be specified, the value required by this document for the parts necessary to retain in position current-carrying parts is 960 °C for the main circuit and 850 °C for the other circuits.

NOTE 1 "Other circuits" cover control circuits (see 5.5), auxiliary circuits (see 5.6) and releases (see 5.7)

- b) The requirements of 8.1.2 of IEC 60947-1:2020 do not apply to parts with a mass lower than 2 g (insignificant mass, in accordance with 3.14 of IEC 60695-2-11:2021). For products containing more than one small part, the total mass of non-tested parts located within 3 mm of each other shall not exceed 10 g.

NOTE 2 This distance of 3 mm is defined in 30.2 of IEC 60335-1:2020.

When aluminium conductors are to be used, Annex D applies.

NOTE 3 Guidance for the development of embedded software is offered in IEC TR 63201.

8.1.2 Withdrawable circuit-breakers

In the disconnected position, the isolating contacts of the main circuit and, where applicable, auxiliary circuits of withdrawable circuit-breakers shall have isolating distances which comply with the requirements specified for the isolating function, taking account of manufacturing tolerances and changes in dimensions due to wear.

The withdrawable mechanism shall be fitted with a reliable indicating device which indicates unambiguously the positions of the isolating contacts.

The withdrawable mechanism shall be fitted with interlocks which only permit the isolating contacts to be separated or reclosed when the main contacts of the circuit-breaker are open.

In addition, the withdrawable mechanism shall be fitted with interlocks which only permit the main contacts to be closed

- when the isolating contacts are fully closed, or
- when the specified isolating distance is achieved between the fixed and moving parts of the isolating contacts (disconnected position).

When the circuit-breaker is in the disconnected position, means shall be provided to ensure that the specified isolating distances between the isolating contacts cannot be inadvertently reduced.

8.1.3 Isolation

Subclause 8.1.7 of IEC 60947-1:2020 applies.

For additional requirements concerning performance, see 8.2.6.

NOTE In the UK, for circuit-breakers with plug-in line and load connections, isolation is achieved by complete removal of the circuit-breaker from the fixed connecting contacts.

8.1.4 Clearances and creepage distances

Minimum values are given in Table 13 of IEC 60947-1:2020 and in Table 15 of IEC 60947-1:2020.

For U_{imp} values exceeding the values given in Table 13 of IEC 60947-1:2020, clearances shall be obtained from Table F.2 of IEC 60664-1:2020.

8.1.5 Requirements for the safety of the operator

There shall be no path or opening which allows incandescent particles to be discharged from the area of the manual operating means.

Compliance is checked by the provisions of 9.3.3.6.1, item b).

8.1.6 List of construction breaks

Circuit-breakers of a given frame size are considered to have a construction break (see 3.1.2) if any one of the following features are not the same:

- material, finish and dimensions of internal current-carrying parts, admitting, however, the variations listed in a), b), c), f) and g) below;
- size, material, configuration and method of attachment of the main contacts;
- any integral manual operating mechanism, its materials and physical characteristics;
- moulding and insulating materials;

- the principle of operation, materials and construction of the arc extinction device;
- the basic design of the overcurrent tripping devices, admitting, however, the variations detailed in a), b) and c) below.

Variations in the following do not constitute a construction break:

- a) dimensions of terminals, provided that creepage and clearance distances are not reduced;
- b) in the case of thermal and magnetic releases those dimensions and materials of the release components, including flexible connections, which determine the current rating;
- c) secondary windings of current transformer operated releases;
- d) external operating means, additional to the integral operating means;
- e) type designation and/or purely aesthetic features (e.g. labels);
- f) in the case of the 2-pole and 4-pole variants, replacement of the trip unit in one pole by a link, to provide an unprotected neutral;
- g) creating a 2-pole breaker from a 3-pole breaker by removing the centre current path, or rendering the central pole inaccessible;
- h) difference in embedded software (firmware) in electronic trip units, which has no impact on the required performance, in particular the tripping function;
- i) electronic trip unit hardware, due to omitted components on identical printed circuit board layout (e.g. rotary knobs, display, etc.).

8.1.7 Additional requirements for circuit-breakers provided with a neutral pole

Subclause 8.1.9 of IEC 60947-1:2020 applies.

8.1.8 Digital inputs and outputs for use with programmable logic controllers (PLCs)

Annex S of IEC 60947-1:2020 applies. For the purposes of this document, this requirement does not apply to digital inputs and outputs dedicated to devices other than PLCs.

8.2 Performance requirements

8.2.1 Operating conditions

8.2.1.1 Closing

8.2.1.1.1 General

For a circuit-breaker to be closed safely on to the making current corresponding to its rated short-circuit making capacity, it is essential that it should be operated with the same speed and the same firmness as during the type test for proving the short-circuit making capacity.

8.2.1.1.2 Dependent manual closing

For a circuit-breaker having a dependent manual closing mechanism, it is not possible to assign a short-circuit making capacity rating irrespective of the conditions of mechanical operation.

Such a circuit-breaker should not be used in circuits having a prospective peak making current exceeding 10 kA.

However, this does not apply in the case of a circuit-breaker having a dependent manual closing mechanism and incorporating an integral fast-acting opening release which causes the circuit-breaker to break safely, irrespective of the speed and firmness with which it is closed on to prospective peak currents exceeding 10 kA; in this case, a rated short-circuit making capacity can be assigned.

8.2.1.1.3 Independent manual closing

A circuit-breaker having an independent manual closing mechanism can be assigned a short-circuit making capacity rating irrespective of the conditions of mechanical operation.

8.2.1.1.4 Dependent power closing

The power-operated closing mechanism, including intermediate control relays where necessary, shall be capable of securing the closing of the circuit-breaker in any condition between no-load and its rated making capacity, when the supply voltage, measured during the closing operation, remains between the limits of 110 % and 85 % of the rated control circuit supply voltage, and, when AC, at the rated frequency.

At 110 % of the rated control circuit supply voltage, the closing operation performed on no-load shall not cause any damage to the circuit-breaker.

At 85 % of the rated control circuit supply voltage, the closing operation shall be performed to establish a current through the circuit-breaker equal to its rated making capacity within the limits allowed by the operation of its relays or releases and, if a maximum time limit is stated for the closing operation, in a time not exceeding this maximum time limit.

8.2.1.1.5 Independent power closing

A circuit-breaker having an independent power closing operation can be assigned a rated short-circuit making capacity irrespective of the conditions of power closing.

Means for charging the operating mechanism, as well as the closing control components, shall be capable of operating in accordance with the manufacturer's specification.

8.2.1.1.6 Stored energy closing

This type of closing mechanism shall be capable of ensuring closing of the circuit-breaker in any condition between no-load and its rated making capacity.

When the stored energy is retained within the circuit-breaker, a device shall be provided which indicates when the storing mechanism is fully charged.

Means for charging the operating mechanism, as well as the closing control components, shall be capable of operating when the auxiliary supply voltage is between 85 % and 110 % of the rated control circuit supply voltage.

It shall not be possible for the moving contacts to move from the open position unless the charge is sufficient for satisfactory completion of the closing operation.

When the energy storing mechanism is manually operated, the direction of operation shall be indicated.

This last requirement does not apply to circuit-breakers with an independent manual closing operation.

8.2.1.2 Opening

8.2.1.2.1 General

Circuit-breakers which open automatically shall be trip-free (see 3.6.24 of IEC 60947-1:2020) and shall have their energy for the tripping operation stored automatically prior to the completion of the closing operation.

8.2.1.2.2 Opening by undervoltage releases

Subclause 8.2.1.3 of IEC 60947-1:2020 applies.

8.2.1.2.3 Opening by shunt releases

Subclause 8.2.1.4 of IEC 60947-1:2020 applies.

8.2.1.2.4 Opening by overcurrent releases

a) Opening under short-circuit conditions

The short-circuit release shall cause tripping of the circuit-breaker within a tolerance of $\pm 20\%$ of the tripping current value of the current setting for all values of the current setting of the short-circuit current release.

Where necessary for overcurrent coordination, the manufacturer shall provide information (usually curves) showing:

- maximum cut-off (let-through) peak current (see 3.7.21 of IEC 60947-1:2020) as a function of prospective current (RMS symmetrical for AC currents);
- I^2t characteristics (see 3.13) for circuit-breakers of selectivity category A and, if applicable, category B for circuit-breakers with instantaneous override (see note to 9.3.6.1).

When applicable, the conformity with this information shall be checked during the relevant type tests in test sequences II and III (see 9.3.5 and 9.3.6).

NOTE 1 It is possible to provide other forms of data to verify coordination characteristics of circuit-breakers, for example, tests on combinations of short-circuit protective devices.

b) Opening under overload conditions

1) Instantaneous or definite time-delay operation

The release shall cause tripping of the circuit-breaker within a tolerance of $\pm 10\%$ of the tripping current value of the current setting for all values of current setting of the overload release.

2) Inverse time-delay operation

Conventional values for inverse time-delay operation are given in Table 5.

At the reference temperature (see 5.7.3) and at 1,05 times the current setting (see 3.6.38 of IEC 60947-1:2020), i.e. with the conventional non-tripping current (see 3.7.30 of IEC 60947-1:2020), the overload release being energized on all phase poles, tripping shall not occur in less than the conventional time (see 3.7.30 of IEC 60947-1:2020) from the cold state, i.e. with the circuit-breaker at the reference temperature.

Moreover, when at the end of the conventional time the value of current is immediately raised to 1,30 times the current setting, i.e. with the conventional tripping current (see 3.7.31 of IEC 60947-1:2020), tripping shall then occur in less than the conventional time later.

NOTE 2 The reference temperature is the ambient air temperature on which the time-current characteristic of the circuit-breaker is based.

Table 5 – Characteristics of the opening operation of inverse time-delay overcurrent opening releases at the reference temperature

All poles loaded		Conventional time h
Conventional non-tripping current	Conventional tripping current	
1,05 times current setting	1,30 times current setting	2 ^a
^a 1 h when $I_n \leq 63$ A		

If a release is declared by the manufacturer as substantially independent of ambient temperature, the current values of Table 5 shall apply within the temperature band declared by the manufacturer, within a tolerance of 0,3 %/K.

The width of the temperature band shall be at least 10 K on either side of the reference temperature.

c) Opening under ground-fault conditions

The ground-fault overcurrent release shall cause tripping of the circuit-breaker within the tolerance corresponding to the type of detection function (CI-A or CI-B) according to T.4 of IEC 60947-1:2020, for all values of the current setting of the ground-fault overcurrent release.

Ground-fault overcurrent releases may have an intentional time-delay, but the break time shall not exceed the tripping time values indicated in Table T.1 of IEC 60947-1:2020.

NOTE 3 Ground-fault overcurrent releases can have sensors internal or external to the circuit-breaker.

8.2.2 Temperature-rise

8.2.2.1 Temperature-rise limits

The temperature-rises of the several parts of a circuit-breaker, measured under the conditions specified in 9.3.3.5, shall not exceed the limiting values stated in Table 6 during the tests made in accordance with 9.3.4.7. The temperature-rises of the terminals shall not exceed the limiting values stated in Table 6 during the tests made in accordance with 9.3.5.5 and 9.3.7.4.

8.2.2.2 Ambient air temperature

The temperature-rise limits given in Table 6 are applicable only if the ambient air temperature remains within the limits given in 7.1.1 of IEC 60947-1:2020.

8.2.2.3 Main circuit

The main circuit of a circuit-breaker, including the overcurrent releases that may be associated with it, shall be capable of carrying its rated current I_n , under the conditions of Clause 9, without the temperature-rises exceeding the limits specified in Table 6.

8.2.2.4 Control circuits

The control circuits, including control circuit devices, used for the closing and opening operations of a circuit-breaker, shall permit the rated duty, as specified in 5.3.5, and also the temperature-rise tests under the test conditions specified in 9.3.3.5, to be made without the temperature-rises exceeding the limits specified in Table 6.

The requirements of this subclause shall be verified on a new sample. Alternatively, at the discretion of the manufacturer, the verification may be made during the temperature-rise test of 9.3.4.7.

8.2.2.5 Auxiliary circuits

Auxiliary circuits, including auxiliary devices, shall be capable of carrying their conventional thermal current without the temperature-rises exceeding the limits specified in Table 6 when tested in accordance with 9.3.3.5.

Table 6 – Temperature-rise limits for terminals and accessible parts

Description of part ^a	Temperature-rise limits ^b K
– Terminals for external connections	80
– Manual operating means: Metallic non-metallic	25 35
– Parts intended to be touched but not hand-held: Metallic non-metallic	40 50
– Parts which shall not be touched for normal operation: Metallic non-metallic	50 60
^a No value is specified for parts other than those listed but no damage should be caused to adjacent parts of insulating materials. ^b The temperature-rise limits specified are not intended to apply to a new sample, but are those applicable to the temperature-rise verifications during the appropriate test sequences specified in Clause 9.	

8.2.3 Dielectric properties

8.2.3.1 General

Subclauses 8.2.3.1 a) and 8.2.3.1 b) of IEC 60947-1:2020 apply.

Type tests shall be made in accordance with 9.3.4.3.

The verification of dielectric withstand during all test sequences shall be made in accordance with 9.3.4.6.

Routine tests shall be made in accordance with 9.4.6.

8.2.3.2 Impulse withstand voltage

Subclause 8.2.3.2 of IEC 60947-1:2020 applies.

For circuit-breakers rated above 1 000 V AC, the impulse withstand voltage shall be agreed between the manufacturer and the user but shall not be less than the corresponding values for 1 000 V AC.

NOTE Table 1 of IEC TS 62993:2017 provides rated impulse voltage values above 1 000 V AC.

8.2.3.3 Power-frequency or DC withstand voltage of the main, auxiliary and control circuits

Power-frequency tests are used in the following cases:

- dielectric tests as type tests for the verification of solid insulation;
- dielectric withstand verification, as a criterion of failure, after switching or short-circuit type tests;
- routine tests.

8.2.3.4 Clearances

Subclause 8.2.3.4 of IEC 60947-1:2020 applies.

8.2.3.5 Creepage distances

Subclause 8.2.3.5 of IEC 60947-1:2020 applies.

8.2.3.6 Solid insulation

Solid insulation shall be verified by either power-frequency tests, in accordance with 9.3.3.4.1, item 3) of IEC 60947-1:2020, or DC tests (test voltages for DC tests are under consideration).

For the purposes of this document, circuits incorporating solid-state devices shall be disconnected for the tests.

8.2.3.7 Spacing between separate circuits

Subclause 8.2.3.7 of IEC 60947-1:2020 applies.

8.2.3.8 Requirements for circuits with protective separation

Annex N of IEC 60947-1:2020 applies.

8.2.4 Ability to make and break under no load, normal load and overload conditions

8.2.4.1 Overload performance

This requirement applies to circuit-breakers of rated current up to and including 630 A.

The circuit-breaker shall be capable of carrying out the number of operating cycles with current in the main circuit exceeding its rated current, under the test conditions according to 9.3.4.5.

Each operating cycle consists of a making operation followed by a breaking operation.

8.2.4.2 Operational performance capability

Subclause 8.2.4.2 of IEC 60947-1:2020 applies with the following additions:

The circuit-breaker shall be capable of meeting the requirements of Table 7:

- for the test of operational performance without current in the main circuit under the test conditions specified in 9.3.4.4.3;
- for the test of operational performance with current in the main circuit under the test conditions specified in 9.3.4.4.4.

Each operating cycle consists of, either a closing operation followed by an opening operation (test of operational performance without current), or a making operation followed by a breaking operation (test of operational performance with current).

Table 7 – Number of operating cycles

1	2	3	4	5
Rated current ^a	Number of operating cycles per hour ^b	Number of operating cycles		
A		Without current	With current ^c	Total
$I_n \leq 100$	120	8 500	1 500	10 000
$100 < I_n \leq 315$	120	7 000	1 000	8 000
$315 < I_n \leq 630$	60	4 000	1 000	5 000
$630 < I_n \leq 2 500$	20	2 500	500	3 000
$2 500 < I_n$	10	1 500	500	2 000
^a This means the maximum rated current for a given frame size. ^b Column 2 gives the minimum operating rate. This rate may be increased with the consent of the manufacturer; in this case the rate used shall be stated in the test report. ^c During each operating cycle, the circuit-breaker shall remain closed for a sufficient time to ensure that the full current is established, but not exceeding 2 s.				

8.2.5 Ability to make and break under short-circuit conditions

Subclause 8.2.5 of IEC 60947-1:2020 applies with the following amplifications:

The rated short-circuit making capacity shall be in accordance with 5.3.6.1 and 5.3.6.3.

The rated short-circuit breaking capacity shall be in accordance with 5.3.6.2.

The rated short-time withstand current shall be in accordance with 5.3.6.4.

NOTE It is the manufacturer's responsibility to ensure that the tripping characteristic of the circuit-breaker is compatible with the capability of the circuit-breaker to withstand the inherent thermal and electrodynamic stresses.

8.2.6 Requirements for isolation

Subclause 8.2.7 of IEC 60947-1:2020 applies and tests shall be made in accordance with 9.3.4.3, 9.3.4.6, 9.3.4.10, 9.3.5.4, 9.3.6.4 and 9.3.8.8, as applicable.

8.2.7 Specific requirements for integrally fused circuit-breakers

NOTE For the coordination between circuit-breakers and separate fuses associated in the same circuit, see 8.2.8.

An integrally fused circuit-breaker shall comply with this document in all respects up to the rated ultimate short-circuit breaking capacity. In particular, it shall meet the requirements of test sequence V (see 9.3.8).

The circuit-breaker shall function, without causing the fuses to operate, at the occurrence of overcurrents not exceeding the selectivity limit current I_s declared by the manufacturer.

For all overcurrents up to and including the rated ultimate short-circuit breaking capacity assigned to the composite unit, the circuit-breaker shall open when one or more fuses operate (in order to prevent single-phasing). If the circuit-breaker is stated by the manufacturer to be a circuit-breaker with lock-out device preventing closing (see 3.10), it shall not be possible to reclose the circuit-breaker until either the melted fuse-links or any missing fuse-links have been replaced or the lock-out means has been reset.

8.2.8 Coordination between a circuit-breaker and another short-circuit protective device

For the coordination between a circuit-breaker and another short-circuit protective device, see Annex A.

8.3 Electromagnetic compatibility (EMC)

Requirements and test methods are given in Annex J.

9 Tests

9.1 Kind of tests

9.1.1 General

Subclause 9.1 of IEC 60947-1:2020 applies, with the following additions:

The tests to verify the characteristics of circuit-breakers are:

- type tests (see 9.3);
- routine tests (see 9.4);
- special tests (see 9.5).

For items subject to agreement between manufacturer and user, see Annex E.

9.1.2 Type tests

Type tests include the tests listed in Table 8.

Table 8 – Type tests

Test	Subclause
Temperature-rise	9.3.3.5
Tripping limits and characteristics	9.3.4.2
Dielectric properties	9.3.4.3
Operational performance capability	9.3.4.4
Overload performance (where applicable)	9.3.4.5
Short-circuit breaking capacities	9.3.5 and 9.3.6
Short-time withstand current (where applicable)	9.3.7
Performance of integrally fused circuit-breakers	9.3.8
Critical DC load current	9.3.10
Individual pole short-circuit breaking capacity at phase-to-neutral AC voltage (where applicable)	9.3.11

Type tests shall be carried out by the manufacturer, in his workshop or at any suitable laboratory of his choice.

9.1.3 Routine tests

Routine tests comprise the tests listed in 9.4.

9.1.4 Special tests

Special tests comprise the tests listed in 9.5.

9.2 Compliance with constructional requirements

Subclause 9.2 of IEC 60947-1:2020 applies.

9.3 Type tests

9.3.1 General

In order to avoid repetition of identical tests applicable to the various test sequences, the general test conditions have been grouped together at the beginning of this subclause under three headings:

- test conditions applicable to all sequences (9.3.4 to 9.3.9);
- test conditions applicable to temperature-rise tests (9.3.3.5);
- test conditions applicable to short-circuit tests (9.3.3.6).

Wherever appropriate, these general test conditions refer back to, or are based on, the general rules of IEC 60947-1.

Each test sequence refers back to the general test conditions applicable. This requires the use of cross-references, but enables each test sequence to be presented in a much simplified form.

Throughout this clause the term "test" has been used for every test to be made; "verification" should be interpreted as "test for the verification" and has been used where it is intended to verify the condition of the circuit-breaker following an earlier test in a test sequence whereby it may have been adversely affected.

In order to facilitate locating a particular test condition or test, an alphabetical index is given in Table 9, using the terms most likely to be used (not necessarily the exact terms appearing in the relevant subclause heading).

Table 9 – Alphabetical index of tests

General test conditions	Subclause
Arrangement of circuit-breakers, general	9.3.3.1
Arrangement of circuit-breakers for short-circuit tests	9.3.3.6.1
Frequency	9.3.3.2.3
Power factor	9.3.3.2.4
Records (interpretation of)	9.3.3.6.6
Recovery voltage	9.3.3.2.6
Short-circuit test circuits	9.3.3.6.2
Short-circuit test procedure	9.3.3.6.4
Temperature-rise test	9.3.3.5
Time constant	9.3.3.2.5
Tolerances	9.3.3.2.2
Tests (for overall schema of test sequences, see Table 10)	Subclause
Critical DC load current	9.3.10
Dielectric properties	9.3.4.3
Dielectric withstand (verification)	9.3.4.6 – 9.3.5.4 – 9.3.6.4 – 9.3.7.6 – 9.3.8.4 – 9.3.8.8 – 9.3.9.6
Individual pole short-circuit test (for phase-earthed systems)	Annex C
Individual pole short-circuit test (for IT systems)	Annex H – see H.2
Indication of main contact position	9.3.4.10
Integrally fused circuit-breakers (short-circuit tests)	9.3.8.2 – 9.3.8.6 – 9.3.8.7
Operational performance capability	9.3.4.4 – 9.3.5.3 – 9.3.5.5
Overload performance	9.3.4.5
Overload releases (verification)	9.3.4.8 – 9.3.5.6 – 9.3.6.2 – 9.3.6.5 – 9.3.7.2 – 9.3.7.7 – 9.3.8.5 – 9.3.8.9 – 9.3.9.2 – 9.3.9.8
Rated individual pole ultimate short-circuit breaking capacity at phase-to-neutral AC voltage	9.3.11
Service short-circuit breaking capacity	9.3.5.2 – 9.3.9.4
Short-circuit breaking capacity test at maximum short-time withstand current	9.3.7.5
Short-time withstand current	9.3.7.3 – 9.3.9.3
Temperature-rise (verification)	9.3.4.7 – 9.3.5.5 – 9.3.7.4 – 9.3.8.3 – 9.3.9.7
Tripping limits and characteristics	9.3.4.2
Ultimate short-circuit breaking capacity	9.3.6.3
Withdrawable circuit-breakers (additional tests)	9.3.4.4.5

9.3.2 Test sequences

9.3.2.1 General

Type tests are grouped together in a number of sequences, as shown in Table 10.

For each sequence, tests shall be made in the order listed unless otherwise specified in this document.

9.3.2.2 Tests omitted from sequence I and made separately

With reference to 9.1.1 of IEC 60947-1:2020, the following tests of test sequence I (see 9.3.4) may be omitted from the sequence and made on separate samples:

- tripping limits and characteristics (9.3.4.2); in which case the sample(s) tested in the sequence shall be subjected to the tests of 9.3.4.2.3 only on the phase poles at the maximum setting, at room temperature and without the additional test of item b) to verify the time-current characteristic;
- test of dielectric properties (9.3.4.3);
- test of under-voltage releases of 9.3.4.4.2.3 and 9.3.4.4.3 to verify the requirements of 8.2.1.3 of IEC 60947-1:2020, and tests of under-voltage releases at alternative frequencies (see 9.3.3.1);
- test of shunt releases of 9.3.4.4.2.4 and 9.3.4.4.3 to verify the requirements of 8.2.1.4 of IEC 60947-1:2020, and tests of shunt releases at alternative frequencies (see 9.3.3.1);
- additional tests for operational performance capability without current for withdrawable circuit-breakers (9.3.4.4.5).

9.3.2.3 Applicability of sequences according to the relationship between short-circuit ratings

The applicability of test sequences according to the relationship between I_{CS} , I_{CU} and I_{CW} is given in Table 11.

Table 10 – Overall schema of test sequences^a

Test sequence	Applicable to	Tests
I General performance characteristics (9.3.4)	All circuit-breakers	Tripping limits and characteristics Dielectric properties Mechanical operation and operational performance capability Overload performance (where applicable) Verification of dielectric withstand Verification of temperature-rise Verification of overload releases Verification of undervoltage and shunt releases (where applicable) Verification of main contact position
II Rated service short-circuit breaking capacity (9.3.5)	All circuit-breakers ^b	Rated service short-circuit breaking capacity Verification of operational performance capability Verification of dielectric withstand Verification of temperature-rise Verification of overload releases
III Rated ultimate short-circuit breaking capacity (9.3.6)	All circuit-breakers ^c of selectivity category A and circuit-breakers of selectivity category B with instantaneous override ^d	Verification of overload releases Rated ultimate short-circuit breaking capacity Verification of dielectric withstand Verification of overload releases

Test sequence	Applicable to	Tests
IV Rated short-time withstand current (9.3.7)	Circuit-breakers of selectivity category B ^b and circuit-breakers of selectivity category A with an assigned short-time withstand current (see 5.4)	Verification of overload releases Rated short-time withstand current Verification of temperature-rise Short-circuit breaking capacity at maximum short-time withstand current Verification of dielectric withstand Verification of overload releases
V Performance of integrally fused circuit-breakers (9.3.8)	Stage 1 Integrally fused circuit-breakers Stage 2	Short-circuit at the selectivity limit current Verification of temperature-rise Verification of dielectric withstand Verification of overload releases Short-circuit at 1,1 times the take-over current Short-circuit at rated ultimate short-circuit breaking capacity Verification of dielectric withstand Verification of overload releases
VI Combined test sequence (9.3.9)	Circuit-breakers of selectivity category B: when $I_{cw} = I_{cs}$ (replaces test sequences II and IV) when $I_{cw} = I_{cs} = I_{cu}$ (replaces test sequences II, III and IV)	Verification of overload releases Rated short-time withstand current Rated service short-circuit breaking capacity Operational performance capability Verification of dielectric withstand Verification of temperature-rise Verification of overload releases
VII Critical DC load current (9.3.10)	Circuit-breakers with DC ratings	Critical DC load current tests
VIII Rated individual pole ultimate short-circuit breaking capacity at phase-to-neutral AC voltage (9.3.11)	AC circuit-breakers, when applicable (see 9.3.11.1)	Verification of overload releases Rated individual pole ultimate short-circuit breaking capacity at phase-to-neutral AC voltage (I_{cu1}) Verification of dielectric withstand Verification of overload releases
Individual pole short-circuit test sequence (Annex C)	Circuit-breakers for use on phase-earthed systems	Individual pole short-circuit breaking capacity (I_{su}) Verification of dielectric withstand Verification of overload releases
Test sequence for circuit-breakers for IT systems (Annex H)	Circuit-breakers for use in IT systems	Individual pole short-circuit breaking capacity (I_{IT}) Verification of dielectric withstand Verification of overload releases
^a For the selection of circuit-breakers for tests and the applicability of the various test sequences according to the relationship between I_{cs}, I_{cu} and I_{cw}, see Table 11. ^b Except where Sequence VI is applied. ^c Except – where $I_{cs} = I_{cu}$ (but see 9.3.6), – where sequence VI is applied, – for integrally fused circuit-breakers. ^d See note to 9.3.6.1		

Table 11 – Applicability of test sequences according to the relationship between I_{cs} , I_{cu} and I_{cw} ^a

I_{cs} , I_{cu} and I_{cw} relationship	Test sequence	Selectivity category			
		A	A Integrally fused	B	B Integrally fused
CASE 1 $I_{cs} \neq I_{cu}$ for selectivity category A $I_{cs} \neq I_{cu} \neq I_{cw}$ for selectivity category B	I	X	X	X	X
	II	X	X	X	X
	III	X		X ^b	
	IV	X ^d		X	X
	V		X		X
CASE 2 $I_{cs} = I_{cw} \neq I_{cu}$ for selectivity category B	I			X	X
	II			X	X
	III			X ^b	
	IV			X	X
	V				X
	VI (combined)			X ^c	X ^c
CASE 3 $I_{cs} = I_{cu}$ for selectivity category A $I_{cs} = I_{cu} \neq I_{cw}$ for selectivity category B	I	X	X	X	X
	II	X	X	X	X
	III				
	IV	X ^d		X	X
	V		X		X
CASE 4 $I_{cs} = I_{cu} = I_{cw}$ for selectivity category B	I			X	
	II			X	
	III				
	IV			X	
	V				
	VI (combined)			X ^c	
^a This table applies to any one value of U_e . For multiple U_e ratings, the table applies to each U_e rating. The applicability of a test sequence is indicated by X in the relevant space. ^b Test applicable only if $I_{cu} > I_{cw}$. ^c At the discretion of, or in agreement with the manufacturer, this sequence may be applied to circuit-breakers of selectivity category B, in which case it replaces test sequences II and IV. ^d Test sequence IV applies only to circuit-breakers with a rated short-time withstand current (see 5.4).					

9.3.2.4 Alternative test programmes for AC circuit-breakers having a different number of poles

These alternative test programmes may only be applied to AC ratings and when all the ratings are the same or lower than the variant submitted to the full programme of Table 10, and construction breaks are the same for all variants. In the case of 1-pole circuit-breakers the voltage ratings shall be equal to or lower than the line-to neutral voltage of the variant tested to Table 10. A 2-pole circuit-breaker produced by removing the centre current path from a 3-pole circuit-breaker tested to programme 1 or programme 2 of this subclause need not be tested as it is considered to be covered by the tests on the 3-pole variant.

Compliance with the test requirements is met by carrying out one of the alternative programmes 1 or 2 below.

- Programme 1: The applicable test sequences according to Table 10 shall be carried out on the three-pole variant. In addition, where applicable, the tests or test sequences listed in Table 13 shall be carried out on the other variants.
- Programme 2: The applicable test sequences according to Table 10 shall be carried out on the four-pole variant. In addition, where applicable, the tests or test sequences listed in Table 14 shall be carried out on the other variants.

The principle for the application of the alternative test programmes is illustrated in Table 12.

Table 12 – Alternative test programmes for AC circuit-breakers

	Programme 1					Programme 2			
	1-pole	2-poles	3-poles	4-poles		1-pole	2-poles	3-poles	4-poles
Construction 1 ^a	□	□	■	□		○	○	○	■
Construction 2	–	–	■	□		–	–	–	■
Construction 3	–	–	■	□		–	–	–	■
...	–	–	■	□		–	–	–	■
Construction <i>n</i>	–	–	■	□		–	–	–	■
Key	■ fully tested per Table 10 □ tested per Table 13 ○ tested per Table 14 – no test required								
^a Construction 1 is the construction which covers the max rating.									

Table 13 – Applicability of tests or test sequences to 1, 2 and 4-pole circuit-breakers according to the alternative programme 1 of 9.3.2.4

Test sequence	Test subclause	Test	Applicability to 4-pole variant ^{f, h}	Applicability to 1-pole or 2-pole variants ^g
I	9.3.4.2	Test of tripping limits and characteristics		
	9.3.4.2.1	General	X	X
	9.3.4.2.2	Short-circuit releases	X ^a	X ^e
	9.3.4.2.3 a) ⁱ or 9.3.4.2.3 b) ⁱ (as applicable)	Overload releases: – instantaneous/definite time-delay – inverse time-delay	X	X ^e
	9.3.4.2.4	Additional test for definite time-delay releases:		
	9.3.4.3	Dielectric properties	X	X
	9.3.4.4	Mechanical operation and operational performance capability		
	9.3.4.4.1	General	X	X
	9.3.4.4.2	Construction and mechanical operation	X ^d	X ^{d, e}
	9.3.4.4.3	Operational performance capability without current	X	X
	9.3.4.4.4	Operational performance capability with current	X	X
	9.3.4.4.5	Withdrawable circuit-breakers	X	
	9.3.4.5	Overload performance	X	X
	9.3.4.6	Verification of dielectric withstand	X	X
	9.3.4.7	Verification of temperature-rise	X	X
	9.3.4.8	Verification of overload releases		
	9.3.4.9	Verification of undervoltage and shunt releases	X	X
	9.3.4.10	Verification of the main contact position	X	X
II	9.3.5	Rated service short-circuit breaking capacity		
III	9.3.6 ^{b, c}	Rated ultimate short-circuit breaking capacity	X	X
IV	9.3.7	Rated short-time withstand current	X 4 th pole and adjacent pole only (see 9.3.3.6.4)	
V	9.3.8	Performance of integrally fused circuit-breakers	X	X
VI	9.3.9	Combined test sequence		
Annex C		Individual pole short-circuit test sequence		
Annex H		Test sequence for circuit-breakers for IT systems		

NOTE The applicability of a test or test sequence is indicated by X in the relevant space.

^a One test on one pair of phase poles chosen at random. In the case of an electronic trip unit, this test may be made on one pole chosen at random.

^b This test sequence also applies when, for the 3-pole testing, Sequence III on the 3-poles variant is replaced by Sequence II or Sequence VI (see Table 10).

^c Test at maximum kVA rating ($I_{cu} \times$ corresponding U_e).

^d Without verification tests of undervoltage releases (9.3.4.4.2.3) and shunt releases (9.3.4.4.2.4).

^e Applicable only to 1-pole variant; not required for 2-poles variants.

^f In case of 4-poles devices with different levels of neutral protection (e.g. 60 % or 100 %), only the variant with the highest level shall be tested according to Table 13.

^g One sample of maximum current rating only, for each test sequence.

^h One sample of maximum current rating for each test sequence; in the case of one or more construction breaks (see 3.1.2 and 8.1.6) within the frame size, a further sample is tested at the maximum rated current corresponding to each construction.

ⁱ This test is not required for electronic trip units.