



INTERNATIONAL TELECOMMUNICATION UNION

ITU-T

TELECOMMUNICATION
STANDARDIZATION SECTOR
OF ITU

U.101

(03/93)

TELEGRAPH SWITCHING INTEX SERVICE

SIGNALLING SYSTEMS FOR THE INTEX SERVICE (TYPES E AND F SIGNALLING)

ITU-T Recommendation U.101

(Previously "CCITT Recommendation")

FOREWORD

The ITU Telecommunication Standardization Sector (ITU-T) is a permanent organ of the International Telecommunication Union. The ITU-T is responsible for studying technical, operating and tariff questions and issuing Recommendations on them with a view to standardizing telecommunications on a worldwide basis.

The World Telecommunication Standardization Conference (WTSC), which meets every four years, established the topics for study by the ITU-T Study Groups which, in their turn, produce Recommendations on these topics.

ITU-T Recommendation U.101 was prepared by the ITU-T Study Group IX (1988-1993) and was approved by the WTSC (Helsinki, March 1-12, 1993).

NOTES

1 As a consequence of a reform process within the International Telecommunication Union (ITU), the CCITT ceased to exist as of 28 February 1993. In its place, the ITU Telecommunication Standardization Sector (ITU-T) was created as of 1 March 1993. Similarly, in this reform process, the CCIR and the IFRB have been replaced by the Radiocommunication Sector.

In order not to delay publication of this Recommendation, no change has been made in the text to references containing the acronyms "CCITT, CCIR or IFRB" or their associated entities such as Plenary Assembly, Secretariat, etc. Future editions of this Recommendation will contain the proper terminology related to the new ITU structure.

2 In this Recommendation, the expression "Administration" is used for conciseness to indicate both a telecommunication administration and a recognized operating agency.

© ITU 1994

All rights reserved. No part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from the ITU.

CONTENTS

	<i>Page</i>
1 Type E signalling	1
2 Type F signalling.....	25
3 Interworking between Types E and F signalling.....	27

.....

Recommendation U.101**SIGNALLING SYSTEMS FOR THE INTEX SERVICE
TYPES E AND F SIGNALLING)***(Helsinki, 1993)*

The CCITT,

considering

- (a) that new networks are being introduced based upon stored program control techniques;
- (b) that these networks as well as being able to carry the International Telex Service, can also carry the Intex service using alphabets other than the International Telegraph Alphabet No. 2 and that interworking between these services is essential;
- (c) that the equipment provided for these networks supports an enhanced range of facilities but that for speed and ease of introduction of the Intex service some Administrations may wish not to offer these enhanced facilities at the outset;
- (d) that the Intex service requires the establishment of new types of signalling, and these signalling types shall permit interworking between Intex terminals, between telex terminals and Intex terminals, and between telex terminals and terminals capable of operating both telex and Intex dual service terminals;
- (e) that Recommendation S.33 defines the alphabet and presentation characteristics for Intex;
- (f) that Recommendation U.210 defines the network interworking requirements between the International Telex Service and the Intex service;
- (g) that Recommendation S.34 describes Intex terminal requirements to effect interworking with the International Telex Service;
- (h) that Recommendation S.35 defines the composition of answerbacks for the Intex service;
- (i) that Recommendation F.150 defines the operational and service requirements of the Intex service;
- (j) that Recommendation F.82 defines the operational and service requirements for interworking between the Intex service and the International Telex Service;

NOTE – The development in the future of services similar to Intex may occur. It may be possible that some of the provisions of this Recommendation should be applied to such services.

unanimously declares the view

- (1) that to support a full range of enhanced customer facilities, Type E signalling as described in clause 1, shall be adopted on trunks between switching centres,
- (2) that where an Administration does not wish to offer a full range of enhanced customer facilities Type F signalling as described in clause 2 may be adopted on trunks between switching centres,
- (3) interworking between Types E and F signalling is for further study (see clause 3).

1 Type E signalling**1.1 General switching and signalling principles**

1.1.1 Type E signalling is independent of the speed and code conversion method and may be used over synchronous or asynchronous channels. Decentralized signalling shall apply with the same channel being used for control signalling and information transfer.

1.1.2 Both terminal and transit operation shall be supported. Due to the inclusion of transit operation, link-by-link signalling control of calls shall be adopted.

1.1.3 Onward selection from transit and incoming terminal centres shall be arranged to overlap the reception of selection signals in order to minimize call set-up times. Selection signals shall be transmitted by the originating centre at automatic speed in a single block that includes an end of selection signal.

1.1.4 The schedule of telex destination codes detailed in Recommendation F.69 shall apply. The same numerical codes shall be used for network identification purposes.

1.1.5 Alternative routing shall be permitted but shall be restricted in order to prevent repeated alternative routing causing traffic to circulate. Alternative routing shall therefore be allowed only once in the originating network, once during international routing between the originating and terminal networks, and once in the terminal network.

1.1.6 Both-way operation shall be assumed. In order to minimize head-on collisions inverse order testing of circuits shall be used. Also allowed is a close approximation to inverse order testing whereby the route is tested in small groups in fixed order always starting the search from the same position.

1.1.7 Normally the originating network shall be responsible for recording accounting information. The recording of accounting information by other than the originating network is for further study.

1.1.8 The Grade of Service for the provision of circuits shall not be worse than one lost call in 500.

1.1.9 Operation of switching equipment shall be such that congestion shall not be signalled on more than 0.2% of calls in the busy hour, and only when congestion has been positively identified.

1.2 Specific signalling characteristics

Notes applicable to 1.2

NOTES

1 X denotes the international centre that originates the call under consideration on the international link concerned. Y denotes the international centre that receives the call under consideration on the international link.

Centre X and centre Y shall provide any necessary signalling conversion (including speed/code conversion) to the type of signalling employed on the preceding and succeeding links if these do not use Type E signalling.

2 Timings shown are within the centre concerned with no allowance being made for propagation and other delays.

3 The times for permanent start polarity (A) and stop polarity (Z) are generally indicated in the following signal descriptions as integral multiples of the duration of a character.

4 The control signalling code (CSC) used in this signalling system is described in Table 8.

1.2.1 The signalling system for higher baud rate services between two anisochronous networks using Type E signalling is detailed in Table 1.

1.2.2 On incoming calls, if the duration of the calling signal exceeds two character periods (or four character periods in exceptional cases where extension of call signals has been requested by centre Y) start polarity shall be maintained on the backward signalling path from centre Y to centre X. This will cause the connection to be released by centre X.

1.2.3 The first forward path signal following the calling signal (class-of-traffic signal) is distinctive from the first backward path signal to provide positive detection of head-on collisions on bothway circuits. A head-on collision is indicated by the reception of a first class-of-traffic character instead of the reception confirmation or reception congestion signal.

When a head-on collision is detected, the switching centres at each end of the circuit shall make another attempt to select a free circuit, either on the same group of circuits or on an alternative route if one exists and alternative routing is permitted. If no free circuit is found, or if a further head-on collision is detected, the call shall be cleared. At transit centres call progress signal 20 shall be transmitted immediately before the clearing signal but after the reception confirmation signal and the network identification signal (if any).

1.2.4 If no reception confirmation or reception congestion signal is received within four seconds from the start of the calling signal, and no head-on collision has been detected, the call shall be cleared, the circuit shall be marked unavailable for outgoing traffic and the automatic retest procedure shall be applied to the circuit concerned.

1.2.5 Selection signals are divided into two parts. The first part, designated as network selection signals, contains information regarding network and customer requirements and may comprise one or more characters (see Tables 2, 3, 3a, 4, 4a and 5). The second part comprises address signals (the called customer number, preceded by the telex destination code on transit calls). The network selection signals are subdivided and assembled as described in 1.2.5.1 to 1.2.5.4 below for signalling purposes.

1.2.5.1 First class-of-traffic character (see Table 2)

The calling signal shall always be followed by at least one class-of-traffic character. The bit functions of this character are chosen so that no further network selection characters are required on the majority of calls. Whether a second class-of-traffic character or a user-class character follows is indicated by bits b3 and b4 of the first class-of-traffic character.

Bit b1 of the first class-of-traffic indicates whether or not the address selection signals include a telex destination code.

Bit b2 of the first class-of-traffic is used to indicate whether or not the call may be subjected to alternative routing, see 1.1.5.

1.2.5.2 User-class characters (see Tables 3 and 3a)

These characters, if used, shall follow the first class-of-traffic character and will be required when, for example, the information needed to be signalled cannot be derived from the incoming circuit.

Bit b4 of the first user-class character is used to indicate whether or not a second class-of-traffic signal follows.

1.2.5.3 Second and third class-of-traffic characters (see Tables 4 and 4a)

These characters, when used, shall follow either any user-class characters required, or when no user-class character is transmitted, the first class-of-traffic character.

The number of class-of-traffic characters depends on the number of facilities available. Bit b4 of the second and subsequent class-of-traffic characters shall indicate whether a further class-of-traffic character follows.

Bit b1 of the second class-of-traffic character shall indicate whether a call originates on a Type 1 or Type 2 network as defined in Recommendation U.201.

1.2.5.4 User group sequence

A user group sequence, if required, shall follow after all class-of-traffic and user-class characters. Bit b3 of the second class-of-traffic character shall indicate whether or not a user group sequence is included in the network selection.

The user group sequence shall comprise a start of user group character (see Table 5) followed by 1 to 8 hexadecimally coded user group characters.

NOTE – The significance of the user group sequence is for further study.

1.2.5.5 Address selection characters

The numerical characters used for the address selection signals are detailed in Table 6. The first class-of-traffic character shall indicate whether or not this address selection includes a telex destination code.

1.2.5.6 End of selection character

The address selection signals shall be terminated by an end of selection character comprising IA5 character 2/11.



Documents

Document Sharing Hub

Recommendation U.101 (03/93)

3

1.2.6 Invalid selection signals received

If the first character received after detection of a calling signal is not a valid first class-of-traffic character, or has parity error, the incoming switching centre shall maintain start polarity on the backward signalling path.

If any network selection signal after the first class-of-traffic character is not valid or has incorrect parity, or if any address selection character is received with incorrect parity, the incoming switching centre shall transmit call progress signal 20 followed immediately by a clearing signal.

If the end of selection signal is not received within 15 seconds from reception of the first class-of-traffic character, or if more than ten seconds elapses between consecutive selection characters, the incoming switching centre shall transmit call progress signal 20 followed immediately by a clearing signal.

The call progress signal shall be transmitted after the reception confirmation signal and network identification signal (if any).

1.2.7 The maximum number of address selection characters to be expected is 18.

1.2.8 If the reception congestion signal is received at a transit centre, that transit centre shall transmit call progress signal 61 followed immediately by a clearing signal to the preceding centre.

The call progress signal shall be transmitted after the reception confirmation signal and network identification signal (if any).

1.2.9 Network identification signals

On calls incoming from international circuits the network identification signal shall be transmitted after the reception confirmation signal.

Network identification signals may be omitted by switching centres within a single network.

NOTE – The nature of network identification signals to be transmitted from switching centres within a network is for further study.

If several international centres are involved in the establishment of a call, the originating network will receive network identification signals one after another.

If, at an international transit centre, the first character of a network identification signal is not received within two seconds of the reception confirmation signal, the incoming switching centre shall transmit call progress signal 20 followed immediately by a clearing signal to the preceding centre.

It is possible for a transit centre to receive backward path signals such as network identification signals, a call connected signal or a call progress signals from subsequent centres whilst the backward path signals originated locally are still being sent. A transit centre shall ensure that the received signals are retransmitted without mutilation or loss. This can be ensured if seizure of an outgoing circuit is delayed until after complete transmission of the reception confirmation signal.

1.2.10 The backward path signals indicating effective and ineffective call conditions are scheduled in Tables 7, 7a and 7b.

1.2.11 If a call connected signal or start of transit through connect signal is not received within 125 seconds from transmission of the end of selection signal the call shall be cleared after transmission of service signal NC or call progress signal 20 as appropriate to the signalling on the calling circuit.

1.2.12 Connect through procedure

1.2.12.1 Connect through procedure at the terminating Type E centre

When no non-clearing call progress signals are to be transmitted the terminating Type E centre shall transmit a call connected signal to the calling circuit after reception of a call connected signal.

If non-clearing call progress signal(s) are required to be transmitted the terminating Type E centre shall transmit a start of transit through connect signal (STTC) followed by a transit through connect signal (TTC), (see Tables 7 and 7a) to the calling circuit after reception of a call connected signal from the called circuit. Upon detection of a transit centre through connected (TTD) signal (see Table 6) on the forward signalling path the terminating centre shall transmit the non-clearing call progress signal(s), followed by a call connected signal, to the calling circuit.

After transmission of the call connected signal the terminating Type E centre shall establish the call by connecting through the forward and backward signalling paths.

1.2.12.2 Connect through procedure at transit Type E centres

1.2.12.2.1 When no non-clearing call progress signals are required to be generated by the transit centre, all CSC signals received from the called circuit shall be transferred to the calling circuit and vice-versa. Upon detection and transfer of a call connected signal the transit Type E centre shall establish the call by connecting through the forward and backward signalling paths.

1.2.12.2.2 On calls where the transit Type E centre is required to generate one or more non-clearing call progress signals the transit Type E centre shall monitor the backward signalling path for a start of transit through connect/transit through connect (STTC/TTC) and call connected signals.

1.2.12.2.2.1 If a call connected signal but no STTC/TTC signal is received, the transit Type E centre shall transmit a STTC/TTC signal on the backward signalling path of the calling circuit, and then monitor the forward signalling path from the calling circuit for a transit centre through connected signal (TTD).

When the TTD signal is received it shall be absorbed by the transit Type E centre. Upon detection of the TTD signal the transit centre shall transmit the non-clearing call progress signal(s) on the backward signalling path of the calling circuit. After transmission of the call progress signals the transit centre shall transmit a call connected signal to the calling circuit and establish the call by connecting through the forward and backward signalling paths. The call connected signal transmitted shall correspond to that received and absorbed from the called circuit.

1.2.12.2.2.2 If a STTC/TTC signal is received from the called circuit the transit Type E centre shall forward this signal to the calling circuit. After the STTC/TTC signal has been forwarded any CSC characters received from the calling circuit shall be transferred to the called circuit.

The transit Type E centre shall then operate in one of the two ways described below:

- a) After transfer to the calling circuit of the STTC/TTC signals any subsequent backward path signals, except a call connected signal, shall be transferred to the calling circuit. The call connected signal received from the called circuit shall be absorbed by the transit Type E centre.

Upon detection of a call connected signal from the called circuit the transit Type E centre shall transmit its non-clearing call progress signal(s) on the backward signalling path of the calling circuit.

After transmission of the call progress signals the transit Type E centre shall transmit a call connected signal to the calling circuit and establish the call by connecting through the forward and backward signalling paths. The call connected signal transmitted shall correspond to that received and absorbed from the called circuit.

- b) After transfer to the calling circuit of the STTC/TTC signals any subsequent backward path signals, shall be absorbed and stored by the transit Type E centre.

Upon detection of a transit through connected signal from the calling circuit (and transfer of this signal to the called circuit) the transit Type E centre shall transmit its non-clearing call progress signal(s) on the backward signalling path of the calling circuit.

After transmission of the call progress signals the transit Type E centre shall retransmit from store (on the backward signalling path of the calling circuit) any characters which have been received and absorbed from the called circuit.

After completion of transmission of these stored characters the transit Type E centre shall establish the call by connecting through the forward and backward signalling paths.

1.2.12.2.3 Connect through procedure at originating Type E centres

If a STTC/TTC signal is received from the called circuit the originating Type E centre shall transmit a TTD signal on the forward signalling path. Any non-clearing call progress signals received shall be absorbed.

1.2.12.2.3.1 Originating centre in a Type 1 network (see Recommendation U.210)

Upon reception of a call connected signal the originating Type E centre shall transmit an ENQ character (WRU signal) on the forward signalling path.

After reception of the called customers answerback and transfer to the calling circuit the originating Type E centre shall transmit a Speed Indicator character sequence to both the calling and called circuits. Transmission of the Speed Indicator sequence shall commence two character periods from the end of the called customer answerback.

The Speed Indicator sequence transmitted shall be that appropriate to the speed of the calling terminal unless, on mixed speed calls, the called terminal operates at a lower speed (as determined from the outgoing circuit or by reception of the appropriate non-clearing call progress signal). In such cases the Speed Indicator sequence transmitted shall be that appropriate to the speed of the called terminal.

No Speed Indicator sequence shall be transmitted on calls which have been routed to the International Telex Service as determined by either the outgoing circuit seized or reception of non-clearing call progress signal 91.

The format of Speed Indicator sequences is shown in Table 9.

1.2.12.2.3.2 Originating centre in a Type 2 network (see Recommendation U.210)

Upon reception of a call connected signal the originating centre shall transmit an ENQ character (WRU signal) on the forward signalling path unless non-clearing call progress signal 91 has been received indicating connection to the International Telex Service.

If non-clearing service signal 91 is received the originating centre shall transmit a Telex Indicator signal (IA5 character 5/1) to the calling customer line.

Within 33 milliseconds of transmission of the Telex Indicator signal the switching centre shall be able to transmit and receive ITA2 characters at a nominal modulation rate 50 baud on both the calling and called circuits as detailed in Recommendation U.210, clause 2.

The originating switching centre shall transmit the ITA2 character sequence 30, 4 (WRU signal) to the called circuit commencing between 100 and 150 milliseconds after the end of transmission of the Telex Indicator signal.

1.2.13 The reception of a call connected signal confirms that the call is extended to the called customer's line.

1.2.14 Complete network through connection is assured when the called terminal's answerback is received by the calling terminal.

1.2.15 The guard delays on clearing are measured from the moment when start polarity has been established on both signalling paths by

- either recognizing or transmitting the clearing signal on one signalling path; and
- either transmitting or recognizing the clear confirmation signal on the other signalling path.

The guard delay for incoming calls shall be 150-600 milliseconds. A new call shall not be accepted until this guard delay has elapsed.

The guard delay for outgoing calls shall be 450-1000 milliseconds greater than the guard delay for incoming calls.

After expiry of the guard delay the circuit shall be restored to the free line condition.