



BSI Standards Publication

Open Data Communication in Building Automation, Controls and Building Management — Control Network Protocol

Part 6: Application elements

National foreword

This British Standard is the UK implementation of EN 14908-6:2022. It supersedes BS EN 14908-6:2014, which is withdrawn.

The UK participation in its preparation was entrusted to Technical Committee RHE/16, Performance requirements for control systems.

A list of organizations represented on this committee can be obtained on request to its committee manager.

Contractual and legal considerations

This publication has been prepared in good faith, however no representation, warranty, assurance or undertaking (express or implied) is or will be made, and no responsibility or liability is or will be accepted by BSI in relation to the adequacy, accuracy, completeness or reasonableness of this publication. All and any such responsibility and liability is expressly disclaimed to the full extent permitted by the law.

This publication is provided as is, and is to be used at the recipient's own risk.

The recipient is advised to consider seeking professional guidance with respect to its use of this publication.

This publication is not intended to constitute a contract. Users are responsible for its correct application.

© The British Standards Institution 2023
Published by BSI Standards Limited 2023

ISBN 978 0 539 17142 6

ICS 91.140.01; 97.120; 35.240.67; 91.040.01

Compliance with a British Standard cannot confer immunity from legal obligations.

This British Standard was published under the authority of the Standards Policy and Strategy Committee on 31 October 2023.

Amendments/corrigenda issued since publication

Date	Text affected
------	---------------

English Version

Open Data Communication in Building Automation,
Controls and Building Management - Control Network
Protocol - Part 6: Application elements

Réseau ouvert de communication de données pour
l'automatisation, la régulation et la gestion technique
du bâtiment - Protocole de réseau pour le bâtiment -
Partie 6 : Eléments pour l'application

Firmenneutrale Datenkommunikation für die
Gebäudeautomation und Gebäudemanagement -
Gebäude Netzwerk Protokoll - Teil 6:
Anwendungselemente

This European Standard was approved by CEN on 9 October 2022.

CEN members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for giving this European Standard the status of a national standard without any alteration. Up-to-date lists and bibliographical references concerning such national standards may be obtained on application to the CEN-CENELEC Management Centre or to any CEN member.

This European Standard exists in three official versions (English, French, German). A version in any other language made by translation under the responsibility of a CEN member into its own language and notified to the CEN-CENELEC Management Centre has the same status as the official versions.

CEN members are the national standards bodies of Austria, Belgium, Bulgaria, Croatia, Cyprus, Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, Netherlands, Norway, Poland, Portugal, Republic of North Macedonia, Romania, Serbia, Slovakia, Slovenia, Spain, Sweden, Switzerland, Türkiye and United Kingdom.



EUROPEAN COMMITTEE FOR STANDARDIZATION
COMITÉ EUROPÉEN DE NORMALISATION
EUROPÄISCHES KOMITEE FÜR NORMUNG

CEN-CENELEC Management Centre: Rue de la Science 23, B-1040 Brussels

Contents

Page

European foreword	20
Introduction	22
1 Scope.....	23
2 Normative references.....	23
3 Terms and definitions	24
4 Standard network-variable type — SNVT	32
4.1 Introduction.....	32
4.2 SNVT_amp	33
4.3 SNVT_amp_mil.....	33
4.4 SNVT_angle	33
4.5 SNVT_angle_vel	33
4.6 SNVT_btu_kilo.....	33
4.7 SNVT_btu_mega.....	33
4.8 SNVT_char_ascii	33
4.9 SNVT_count.....	34
4.10 SNVT_count_inc.....	34
4.11 SNVT_date_day	34
4.12 SNVT_elec_kwh.....	34
4.13 SNVT_elec_whr	34
4.14 SNVT_flow	34
4.15 SNVT_flow_mil.....	34
4.16 SNVT_length	35
4.17 SNVT_length_kilo.....	35
4.18 SNVT_length_micr	35
4.19 SNVT_length_mil.....	35
4.20 SNVT_lev_cont.....	35
4.21 SNVT_mass.....	35
4.22 SNVT_mass_kilo	35
4.23 SNVT_mass_mega	36
4.24 SNVT_mass_mil.....	36
4.25 SNVT_power	36
4.26 SNVT_power_kilo.....	36
4.27 SNVT_ppm.....	36
4.28 SNVT_press	36
4.29 SNVT_res.....	36
4.30 SNVT_res_kilo	37
4.31 SNVT_sound_db.....	37
4.32 SNVT_speed.....	37
4.33 SNVT_speed_mil.....	37
4.34 SNVT_str_asc	37
4.35 SNVT_str_int	37
4.36 SNVT_telcom	38
4.37 SNVT_temp.....	38
4.38 SNVT_vol.....	38
4.39 SNVT_vol_kilo	38

4.40	SNVT_vol_mil	38
4.41	SNVT_volt.....	38
4.42	SNVT_volt_dbmv	38
4.43	SNVT_volt_kilo.....	39
4.44	SNVT_volt_mil.....	39
4.45	SNVT_amp_f.....	39
4.46	SNVT_angle_f.....	39
4.47	SNVT_angle_vel_f.....	39
4.48	SNVT_count_f.....	39
4.49	SNVT_count_inc_f.....	40
4.50	SNVT_flow_f.....	40
4.51	SNVT_length_f.....	40
4.52	SNVT_lev_cont_f.....	40
4.53	SNVT_mass_f	40
4.54	SNVT_power_f.....	40
4.55	SNVT_ppm_f.....	41
4.56	SNVT_press_f.....	41
4.57	SNVT_res_f	41
4.58	SNVT_sound_db_f.....	41
4.59	SNVT_speed_f.....	41
4.60	SNVT_temp_f	41
4.61	SNVT_time_f.....	42
4.62	SNVT_vol_f.....	42
4.63	SNVT_volt_f.....	42
4.64	SNVT_btu_f.....	42
4.65	SNVT_elec_whr_f.....	42
4.66	SNVT_config_src.....	42
4.67	SNVT_color	43
4.68	SNVT_grammage	43
4.69	SNVT_grammage_f	43
4.70	SNVT_file_req.....	43
4.71	SNVT_file_status	45
4.72	SNVT_freq_f	46
4.73	SNVT_freq_hz.....	46
4.74	SNVT_freq_kilohz	46
4.75	SNVT_freq_milhz	46
4.76	SNVT_lux	47
4.77	SNVT_lev_percent.....	47
4.78	SNVT_multiplier	47
4.79	SNVT_state.....	47
4.80	SNVT_time_stamp	48
4.81	SNVT_zerospans	49
4.82	SNVT_magcard	49
4.83	SNVT_elapsed_tm	52
4.84	SNVT_alarm.....	52
4.85	SNVT_currency.....	53
4.86	SNVT_file_pos.....	54
4.87	SNVT_muldiv.....	54
4.88	SNVT_obj_request	54
4.89	SNVT_obj_status.....	55
4.90	SNVT_preset.....	56
4.91	SNVT_switch.....	57
4.92	SNVT_trans_table	58

4.93	SNVT_override.....	58
4.94	SNVT_pwr_fact.....	58
4.95	SNVT_pwr_fact_f.....	59
4.96	SNVT_density.....	59
4.97	SNVT_density_f.....	59
4.98	SNVT_rpm.....	59
4.99	SNVT_hvac_emerg.....	59
4.100	SNVT_angle_deg.....	59
4.101	SNVT_temp_p.....	59
4.102	SNVT_temp_setpt.....	60
4.103	SNVT_time_sec.....	60
4.104	SNVT_hvac_mode.....	60
4.105	SNVT_occupancy.....	60
4.106	SNVT_area.....	61
4.107	SNVT_hvac_overid.....	61
4.108	SNVT_hvac_status.....	61
4.109	SNVT_press_p.....	62
4.110	SNVT_address.....	62
4.111	SNVT_scene.....	62
4.112	SNVT_scene_cfg.....	63
4.113	SNVT_setting.....	63
4.114	SNVT_evap_state.....	64
4.115	SNVT_therm_mode.....	64
4.116	SNVT_defr_mode.....	64
4.117	SNVT_defr_term.....	64
4.118	SNVT_defr_state.....	64
4.119	SNVT_time_min.....	64
4.120	SNVT_time_hour.....	64
4.121	SNVT_ph.....	65
4.122	SNVT_ph_f.....	65
4.123	SNVT_chlr_status.....	65
4.124	SNVT_tod_event.....	66
4.125	SNVT_smo_obscur.....	66
4.126	SNVT_fire_test.....	66
4.127	SNVT_temp_ror.....	66
4.128	SNVT_fire_init.....	66
4.129	SNVT_fire_indcte.....	66
4.130	SNVT_time_zone.....	67
4.131	SNVT_earth_pos.....	68
4.132	SNVT_reg_val.....	69
4.133	SNVT_reg_val_ts.....	69
4.134	SNVT_volt_ac.....	70
4.135	SNVT_amp_ac.....	70
4.136	SNVT_turbidity.....	70
4.137	SNVT_turbidity_f.....	71
4.138	SNVT_hvac_type.....	71
4.139	SNVT_elec_kwh_l.....	71
4.140	SNVT_temp_diff_p.....	71
4.141	SNVT_ctrl_req.....	71
4.142	SNVT_ctrl_resp.....	72
4.143	SNVT_ptz.....	72
4.144	SNVT_privacyzone.....	73
4.145	SNVT_pos_ctrl.....	73

4.146	SNVT_enthalpy	74
4.147	SNVT_gfci_status	74
4.148	SNVT_motor_state	74
4.149	SNVT_pumpset_mn	75
4.150	SNVT_ex_control	75
4.151	SNVT_pumpset_sn	76
4.152	SNVT_pump_sensor	77
4.153	SNVT_abs_humid	78
4.154	SNVT_flow_p	78
4.155	SNVT_dev_c_mode	78
4.156	SNVT_valve_mode	78
4.157	SNVT_alarm_2	79
4.158	SNVT_state_64	79
4.159	SNVT_nv_type	84
4.160	SNVT_ent_opmode	84
4.161	SNVT_ent_state	84
4.162	SNVT_ent_status	85
4.163	SNVT_flow_dir	86
4.164	SNVT_hvac_satsts	87
4.165	SNVT_dev_status	87
4.166	SNVT_dev_fault	90
4.167	SNVT_dev_maint	92
4.168	SNVT_date_event	94
4.169	SNVT_sched_val	94
4.170	SNVT_sec_state	95
4.171	SNVT_sec_status	95
4.172	SNVT_sbldn_state	95
4.173	SNVT_rac_ctrl	96
4.174	SNVT_rac_req	98
4.175	SNVT_count_32	99
4.176	SNVT_clothes_w_c	99
4.177	SNVT_clothes_w_m	101
4.178	SNVT_clothes_w_s	102
4.179	SNVT_clothes_w_a	104
4.180	SNVT_multiplier_s	106
4.181	SNVT_switch_2	107
4.182	SNVT_color_2	108
4.183	SNVT_log_status	109
4.184	SNVT_time_stamp_p	109
4.185	SNVT_log_fx_request	110
4.186	SNVT_log_fx_status	110
4.187	SNVT_log_request	110
4.188	SNVT_enthalpy_d	111
4.189	SNVT_amp_ac_mil	111
4.190	SNVT_time_hour_p	111
4.191	SNVT_lamp_status	111
4.192	SNVT_environment	117
4.193	SNVT_geo_loc	117
4.194	SNVT_program_status	118
4.195	SNVT_load_offsets	118
4.196	SNVT_Wm2_p	119
4.197	SNVT_safe_1	119
4.198	SNVT_safe_2	121

4.199	SNVT_safe_4.....	122
4.200	SNVT_safe_8.....	124
4.201	SNVT_time_val_2.....	125
4.202	SNVT_time_offset.....	126
4.203	SNVT_sched_exc.....	126
4.204	SNVT_sched_status.....	127
4.205	SNVT_mass_flow.....	127
4.206	SNVT_mass_flow_f.....	127
4.207	SNVT_time_min_p.....	128
4.208	SNVT_stat_control.....	128
4.209	SNVT_faults.....	128
4.210	SNVT_control_data.....	130
4.211	SNVT_power_profile.....	131
4.212	SNVT_version.....	131
4.213	SNVT_control_cfg.....	131
4.214	SNVT_fault_limits.....	132
4.215	SNVT_scene_def.....	133
4.216	SNVT_lux_2.....	133
4.217	SNVT_temp_setpt_2.....	134
5	Standard configuration-property type — SCPT.....	135
5.1	Introduction.....	135
5.2	SCPTactFbDly.....	135
5.3	SCPTalrmClrT1.....	135
5.4	SCPTalrmClrT2.....	135
5.5	SCPTalrmIhbt.....	136
5.6	SCPTalrmSetT1.....	136
5.7	SCPTalrmSetT2.....	136
5.8	SCPTdefOutput.....	136
5.9	SCPTdriveT.....	136
5.10	SCPThighLimit1.....	136
5.11	SCPThighLimit2.....	136
5.12	SCPTthystHigh1.....	137
5.13	SCPTthystHigh2.....	137
5.14	SCPTthystLow1.....	137
5.15	SCPTthystLow2.....	137
5.16	SCPTinFbDly.....	137
5.17	SCPTinvrtOut.....	137
5.18	SCPTlocation.....	137
5.19	SCPTlowLimit1.....	138
5.20	SCPTlowLimit2.....	138
5.21	SCPTmaxRnge.....	138
5.22	SCPTmaxRcvT.....	138
5.23	SCPTmaxSndT.....	138
5.24	SCPTminRnge.....	138
5.25	SCPTminSndT.....	138
5.26	SCPTnwrkCnfg.....	139
5.27	SCPToffset.....	139
5.28	SCPTsndDelta.....	139
5.29	SCPTtrnsTblX.....	139
5.30	SCPTtrnsTblY.....	139
5.31	SCPToffDely.....	139
5.32	SCPTgain.....	139

5.33	SCPTovrBehave	140
5.34	SCPTovrValue.....	140
5.35	SCPTbypassTime.....	140
5.36	SCPTmanOvrTime	140
5.37	SCPTHumSetpt	140
5.38	SCPTmaxFlowHeat	140
5.39	SCPTfireInitType.....	141
5.40	SCPTsmokeNomSens	141
5.41	SCPTsmokeDayAlrmLim	141
5.42	SCPTactuatorType.....	141
5.43	SCPTlimitCO2	141
5.44	SCPTminDeltaAngl	141
5.45	SCPTdirection	142
5.46	SCPTdriveTime	142
5.47	SCPTductArea.....	142
5.48	SCPTminDeltaFlow.....	142
5.49	SCPTmaxRcvTime.....	142
5.50	SCPTmaxSendTime	142
5.51	SCPTmaxSetpoint.....	143
5.52	SCPTmaxFlow.....	143
5.53	SCPTminSendTime	143
5.54	SCPTminSetpoint	143
5.55	SCPTminFlow	143
5.56	SCPTminFlowHeat.....	143
5.57	SCPTminFlowStby.....	143
5.58	SCPTnomAirFlow	144
5.59	SCPTnomAngle	144
5.60	SCPTnumValves.....	144
5.61	SCPTsetPnts.....	144
5.62	SCPToemType	144
5.63	SCPTminDeltaRH	144
5.64	SCPTminDeltaCO2	144
5.65	SCPTminDeltaTemp.....	145
5.66	SCPTsensConstTmp	145
5.67	SCPTgainVAV.....	145
5.68	SCPTsensConstVAV	145
5.69	SCPToffsetCO2.....	145
5.70	SCPToffsetRH.....	145
5.71	SCPToffsetTemp	145
5.72	SCPTdefltBehave.....	146
5.73	SCPTpwrUpDelay	146
5.74	SCPTpwrUpState	146
5.75	SCPTHvacMode	146
5.76	SCPTcoolSetpt	146
5.77	SCPTcoolLowerSP	146
5.78	SCPTcoolUpperSP	147
5.79	SCPTheatSetpt.....	147
5.80	SCPTheatLowerSP	147
5.81	SCPTheatUpperSP	147
5.82	SCPTlimitChlrCap	147
5.83	SCPTluxSetpoint.....	147
5.84	SCPTstep	148
5.85	SCPTonOffHysteresis.....	148

5.86	SCPTclOffDelay	148
5.87	SCPTclOnDelay	148
5.88	SCPTpowerupState	148
5.89	SCPTminDeltaLevel	148
5.90	SCPTreflection	148
5.91	SCPTfieldCalib	149
5.92	SCPTholdTime	149
5.93	SCPTstepValue	149
5.94	SCPTmaxOut	149
5.95	SCPTsceneNmbr	149
5.96	SCPTfadeTime	149
5.97	SCPTdelayTime	149
5.98	SCPTmainReplica	150
5.99	SCPTupdateRate	150
5.100	SCPTsummerTime	150
5.101	SCPTwinterTime	150
5.102	SCPTmanualAllowed	150
5.103	SCPTdefWeekMask	150
5.104	SCPTdayDateIndex	151
5.105	SCPTtimeEvent	151
5.106	SCPTmodeHrtBt	151
5.107	SCPTdefrostMode	152
5.108	SCPTmaxDefrstTime	152
5.109	SCPTdrainDelay	152
5.110	SCPTinjDelay	152
5.111	SCPTmaxDefrstTemp	152
5.112	SCPTstrutDelay	152
5.113	SCPTtermTimeTemp	152
5.114	SCPTpumpDownDelay	153
5.115	SCPTsuperHtRefInit	153
5.116	SCPTstrutOpen	153
5.117	SCPTsuperHtRefMin	153
5.118	SCPTrefrigGlide	153
5.119	SCPTsuperHtRefMax	153
5.120	SCPTrefrigType	154
5.121	SCPTthermMode	154
5.122	SCPTdayNightCntrl	154
5.123	SCPTdiffNight	154
5.124	SCPThighLimTemp	154
5.125	SCPThighLimDly	155
5.126	SCPTcutOutValue	155
5.127	SCPTairTemp1Day	155
5.128	SCPTsmokeNightAlrmLim	155
5.129	SCPTlowLimTemp	155
5.130	SCPTlowLimDly	155
5.131	SCPTdiffValue	155
5.132	SCPTairTemp1Night	156
5.133	SCPTairTemp1Alrm	156
5.134	SCPThighLimDefrDly	156
5.135	SCPTdeltaNight	156
5.136	SCPTrunHrInit	156
5.137	SCPTrunHrAlarm	156
5.138	SCPTenergyCntInit	156

5.139	SCPTsmokeDayPreAlrmLim	157
5.140	SCPTdebounce	157
5.141	SCPTsmokeNightPreAlrmLim	157
5.142	SCPTzoneNum	157
5.143	SCPTthermAlrmROR	157
5.144	SCPTvisOutput	157
5.145	SCPTaudOutput	157
5.146	SCPTflashFreq	158
5.147	SCPTinstallDate	158
5.148	SCPTmaintDate	158
5.149	SCPTmanfDate	158
5.150	SCPTfireTxt1	158
5.151	SCPTfireTxt2	158
5.152	SCPTfireTxt3	158
5.153	SCPTthermThreshold	159
5.154	SCPTfireIndicate	159
5.155	SCPTtimeZone	159
5.156	SCPTprimeVal	159
5.157	SCPTsecondVal	159
5.158	SCPTsceneOffset	159
5.159	SCPTnomRPM	159
5.160	SCPTnomFreq	160
5.161	SCPTrampUpTm	160
5.162	SCPTrampDownTm	160
5.163	SCPTdefScale	160
5.164	SCPTregName	160
5.165	SCPTbaseValue	160
5.166	SCPTdevMajVer	160
5.167	SCPTdevMinVer	161
5.168	SCPTobjMajVer	161
5.169	SCPTobjMinVer	161
5.170	SCPT HVAC Type	161
5.171	SCPTtimeout	161
5.172	SCPTcontrolPriority	161
5.173	SCPTdeviceGroupID	161
5.174	SCPTmaxPrivacyZones	162
5.175	SCPTmaxCameraPrepositions	162
5.176	SCPTdefaultPanTiltZoomSpeeds	162
5.177	SCPTdefaultAutoPanSpeed	162
5.178	SCPTautoAnswer	162
5.179	SCPTdialString	162
5.180	SCPTserialNumber	162
5.181	SCPTnormalRotationalSpeed	163
5.182	SCPTstandbyRotationalSpeed	163
5.183	SCPTpartNumber	163
5.184	SCPTdischargeAirCoolingSetpoint	163
5.185	SCPTdischargeAirHeatingSetpoint	163
5.186	SCPTmaxSupplyFanCapacity	163
5.187	SCPTminSupplyFanCapacity	163
5.188	SCPTmaxReturnExhaustFanCapacity	164
5.189	SCPTminReturnExhaustFanCapacity	164
5.190	SCPTductStaticPressureSetpoint	164
5.191	SCPTmaxDuctStaticPressureSetpoint	164

5.192	SCPTminDuctStaticPressureSetpoint.....	164
5.193	SCPTductStaticPressureLimit.....	164
5.194	SCPTbuildingStaticPressureSetpoint	164
5.195	SCPTreturnFanStaticPressureSetpoint.....	165
5.196	SCPTfanDifferentialSetpoint.....	165
5.197	SCPTmixedAirLowLimitSetpoint.....	165
5.198	SCPTmixedAirTempSetpoint.....	165
5.199	SCPTminOutdoorAirFlowSetpoint.....	165
5.200	SCPToutdoorAirTempSetpoint	165
5.201	SCPToutdoorAirEnthalpySetpoint.....	165
5.202	SCPTdiffTempSetpoint.....	166
5.203	SCPTexhaustEnablePosition	166
5.204	SCPTspaceHumSetpoint	166
5.205	SCPTdischargeAirDewpointSetpoint.....	166
5.206	SCPTmaxDischargeAirCoolingSetpoint	166
5.207	SCPTminDischargeAirCoolingSetpoint.....	166
5.208	SCPTmaxDischargeAirHeatingSetpoint.....	166
5.209	SCPTminDischargeAirHeatingSetpoint	167
5.210	SCPTcoolingLockout	167
5.211	SCPTheatingLockout.....	167
5.212	SCPTcoolingResetEnable.....	167
5.213	SCPTheatingResetEnable	167
5.214	SCPTsetpoint.....	167
5.215	SCPTtemperatureHysteresis	167
5.216	SCPTcontrolTemperatureWeighting	168
5.217	SCPTpwmPeriod.....	168
5.218	SCPTdefrostInternalSchedule	168
5.219	SCPTdefrostStart.....	168
5.220	SCPTdefrostCycles	168
5.221	SCPTminDefrostTime	168
5.222	SCPTmaxDefrostTime	168
5.223	SCPTdefrostFanDelay.....	169
5.224	SCPTdefrostRecoveryTime.....	169
5.225	SCPTdefrostHold	169
5.226	SCPTdefrostDetect.....	169
5.227	SCPTscheduleInternal.....	169
5.228	SCPTtempOffset.....	169
5.229	SCPTaudibleLevel	169
5.230	SCPTscrollSpeed.....	170
5.231	SCPTbrightness.....	170
5.232	SCPTorientation	170
5.233	SCPTinstalledLevel.....	170
5.234	SCPTpumpCharacteristic	170
5.235	SCPTminPressureSetpoint	170
5.236	SCPTmaxPressureSetpoint.....	171
5.237	SCPTminFlowSetpoint.....	171
5.238	SCPTmaxFlowSetpoint.....	171
5.239	SCPTdeviceControlMode	171
5.240	SCPTminRemotePressureSetpoint.....	171
5.241	SCPTmaxRemotePressureSetpoint	171
5.242	SCPTminRemoteFlowSetpoint	171
5.243	SCPTmaxRemoteFlowSetpoint.....	172
5.244	SCPTminRemoteTempSetpoint	172

5.245	SCPTmaxRemoteTempSetpoint	172
5.246	SCPTcontrolSignal	172
5.247	SCPTnightPurgePosition	172
5.248	SCPTfreeCoolPosition	173
5.249	SCPTvalveFlowCharacteristic	173
5.250	SCPTvalveOperatingMode	173
5.251	SCPTemergencyPosition	173
5.252	SCPTblockProtectionTime	173
5.253	SCPTminStroke	173
5.254	SCPTmaxStroke	173
5.255	SCPTnvType	174
5.256	SCPTmaxNVLength	174
5.257	SCPTnvDynamicAssignment	174
5.258	SCPTsafExtCnfg	174
5.259	SCPTemergCnfg	174
5.260	SCPTsluiceCnfg	175
5.261	SCPTfanOperation	175
5.262	SCPTminFlowUnit	175
5.263	SCPTmaxFlowUnit	175
5.264	SCPTminFlowHeatStby	175
5.265	SCPTminFlowUnitStby	175
5.266	SCPToffsetFlow	176
5.267	SCPTareaDuctHeat	176
5.268	SCPTnomAirFlowHeat	176
5.269	SCPTgainVAVHeat	176
5.270	SCPTnumDampers	176
5.271	SCPTminFlowUnitHeat	176
5.272	SCPTsaturationDelay	176
5.273	SCPTeffectivePeriod	177
5.274	SCPTscheduleDates	177
5.275	SCPTschedule	178
5.276	SCPTscheduleTimeValue	179
5.277	SCPTvalueDefinition	179
5.278	SCPTvalueName	179
5.279	SCPTweeklySchedule	180
5.280	SCPTscheduleName	180
5.281	SCPTvalveStroke	180
5.282	SCPTvalveNominalSize	180
5.283	SCPTvalveKvs	180
5.284	SCPTvalveType	181
5.285	SCPTactuatorCharacteristic	181
5.286	SCPTtrnsTbIX2	181
5.287	SCPTtrnsTbIY2	181
5.288	SCPTcombFlowCharacteristic	181
5.289	SCPTtrnsTbIX3	181
5.290	SCPTtrnsTbIY3	182
5.291	SCPTrunTimeAlarm	182
5.292	SCPTtimePeriod	182
5.293	SCPTpulseValue	183
5.294	SCPTnumDigits	183
5.295	SCPTnvPriority	183
5.296	SCPTdefaultSetting	183
5.297	SCPTlowLimit1Enable	183

5.298	SCPTlowLimit2Enable	183
5.299	SCPTclockCalibration	184
5.300	SCPTneuronId	184
5.301	SCPThighLimit1Enable	184
5.302	SCPThighLimit2Enable	184
5.303	SCPTahamApplianceModel	184
5.304	SCPTdefInput	184
5.305	SCPTname1	185
5.306	SCPTscene	185
5.307	SCPTsceneTiming	186
5.308	SCPTname2	186
5.309	SCPTname3	186
5.310	SCPTbuttonPressAction	187
5.311	SCPTbuttonColor	187
5.312	SCPTbuttonRepeatInterval	188
5.313	SCPTbuttonHoldAction	188
5.314	SCPTpwrSendOnDelta	189
5.315	SCPTsceneName	189
5.316	SCPTmaxPower	189
5.317	SCPTifaceDesc	189
5.318	SCPTmonInterval	189
5.319	SCPTlinkPowerDetectEnable	190
5.320	SCPTscanTime	190
5.321	SCPTdevListDesc	190
5.322	SCPTdevListEntry	190
5.323	SCPTlogCapacity	191
5.324	SCPTlogNotificationThreshold	191
5.325	SCPTlogSize	191
5.326	SCPTlogType	191
5.327	SCPTfanInEnable	191
5.328	SCPTlogTimestampEnable	192
5.329	SCPTlogHighLimit	192
5.330	SCPTlogLowLimit	192
5.331	SCPTmaxFanIn	192
5.332	SCPTlogMinDeltaTime	192
5.333	SCPTlogMinDeltaValue	193
5.334	SCPTpollRate	193
5.335	SCPTsourceAddress	193
5.336	SCPTlogRecord	194
5.337	SCPTlogFileHeader	195
5.338	SCPTlogAlarmThreshold	195
5.339	SCPTlogRequest	196
5.340	SCPTlogResponse	196
5.341	SCPTlightingGroupEnable	197
5.342	SCPTsceneColor	197
5.343	SCPTbkupSchedule	197
5.344	SCPTOLCLimits	198
5.345	SCPTlampPower	198
5.346	SCPTdeviceOutSelection	199
5.347	SCPTenableStatusMsg	199
5.348	SCPTmaxLevelVolt	201
5.349	SCPTgeoLocation	201
5.350	SCPTprogName	202

5.351	SCPTprogRevision	202
5.352	SCPTprogSelect.....	202
5.353	SCPTprogSourceLocation	202
5.354	SCPTprogFileIndexes	203
5.355	SCPTprogCmdHistory.....	203
5.356	SCPTprogStateHistory	203
5.357	SCPTnsdsFbIndex	204
5.358	SCPTcurrentSenseEnable	204
5.359	SCPTmeasurementInterval.....	204
5.360	SCPTlightingGroupMembership	204
5.361	SCPTloadControlOffset	204
5.362	SCPTprogErrorHistory.....	205
5.363	SCPTnvUsage	205
5.364	SCPTscheduleSunday	205
5.365	SCPTscheduleMonday	206
5.366	SCPTscheduleTuesday	206
5.367	SCPTscheduleWednesday.....	206
5.368	SCPTscheduleThursday.....	206
5.369	SCPTscheduleFriday	207
5.370	SCPTscheduleSaturday.....	207
5.371	SCPToccupancyBehavior	207
5.372	SCPTtimeSource	208
5.373	SCPTscheduleException	208
5.374	SCPTscheduleHoliday	208
5.375	SCPTrandomizationInterval.....	208
5.376	SCPTsunriseTime.....	208
5.377	SCPTsunsetTime	209
5.378	SCPTschedulerOptions	209
5.379	SCPToccupancyThresholds	209
5.380	SCPTpowerProfile	210
5.381	SCPTcontrolCfg	210
5.382	SCPTlimits	210
5.383	SCPTsceneDef.....	210
5.384	SCPTactuatorFeedbackDisplayMode.....	210
5.385	SCPTcontactType	210
5.386	SCPTcompensation	211
5.387	SCPTpiCoefficients	211
5.388	SCPTsensorCal	211
5.389	SCPTstartOptimize	212
5.390	SCPTslatType.....	212
5.391	SCPTpositionSetting	212
5.392	SCPTwindSpeedLimit	212
5.393	SCPTminSupplyAirTemp	212
5.394	SCPTmaxSupplyAirTemp	213
5.395	SCPTfanEnable.....	213
5.396	SCPTfanControl	213
5.397	SCPTstartEndDrivePos	213
5.398	SCPTminMaxDrivePos	214
5.399	SCPTsetPnts2	214
5.400	SCPTlearnEnable.....	214
5.401	SCPTminOut.....	214
5.402	SCPTstepTime	214
5.403	SCPThumanEyeAdapt.....	214

5.404	SCPTpositionSettingDeAct.....	215
5.405	SCPTthermoSetting	215
5.406	SCPTairQualControlMode.....	215
5.407	SCPToutRoomTempDiff.....	215
5.408	SCPTsignalPresenceMode.....	215
6	Standard Enumeration Type.....	216
6.1	Introduction.....	216
6.2	days_of_week_t.....	216
6.3	discrete_levels_t.....	216
6.4	telcom_states_t.....	216
6.5	config_source_t.....	217
6.6	file_request_t.....	217
6.7	file_status_t.....	217
6.8	alarm_type_t.....	218
6.9	priority_level_t.....	219
6.10	currency_t.....	219
6.11	object_request_t.....	221
6.12	learn_mode_t.....	222
6.13	override_t.....	222
6.14	emerg_t.....	222
6.15	hvac_t.....	222
6.16	occup_t.....	223
6.17	hvac_overid_t.....	223
6.18	scene_t.....	225
6.19	scene_config_t.....	226
6.20	setting_t.....	226
6.21	evap_t.....	226
6.22	therm_mode_t.....	226
6.23	defrost_mode_t.....	226
6.24	defrost_term_t.....	227
6.25	defrost_state_t.....	227
6.26	chiller_t.....	227
6.27	fire_test_t.....	227
6.28	fire_initiator_t.....	228
6.29	fire_indicator_t.....	228
6.30	calendar_type_t.....	228
6.31	reg_val_unit_t.....	229
6.32	hvac_hvt_t.....	230
6.33	control_resp_t.....	230
6.34	pan_dir_t.....	230
6.35	tilt_dir_t.....	231
6.36	zoom_t.....	231
6.37	privacyzone_t.....	231
6.38	cam_func_t.....	231
6.39	cam_act_t.....	231
6.40	gfc_i_status_t.....	232
6.41	motor_state_t.....	232
6.42	boolean_t.....	232
6.43	ex_control_t.....	232
6.44	unit_temp_t.....	233
6.45	device_c_mode_t.....	233
6.46	valve_mode_t.....	233

6.47	nv_type_category_t	234
6.48	ent_opmode_cmd_t	234
6.49	ent_cmd_t	235
6.50	flow_direction_t	235
6.51	device_select_t	236
6.52	event_mode_type_t	236
6.53	manager_subordinate_t	236
6.54	fan_operation_t	236
6.55	days_of_month_t	236
6.56	months_t	240
6.57	sec_status_t	240
6.58	sec_state_t	241
6.59	interval_of_month_t	242
6.60	sblnd_cmd_source_t	242
6.61	sblnd_error_t	243
6.62	rail_audio_sensor_type_t	243
6.63	rail_audio_type_t	244
6.64	appl_cwc_t	245
6.65	appl_cws_t	245
6.66	appl_cwp_t	245
6.67	appl_rin_t	246
6.68	aham_appl_t	246
6.69	button_action_t	246
6.70	char_encoding_t	248
6.71	switch_state_t	248
6.72	color_encoding_t	249
6.73	log_status_t	250
6.74	log_type_t	250
6.75	timestamp_t	250
6.76	log_record_t	250
6.77	point_status_t	250
6.78	message_code_t	251
6.79	log_access_req_t	251
6.80	log_response_code_t	251
6.81	address_type_t	251
6.82	olc_select_t	251
6.83	program_state_t	252
6.84	file_type_t	252
6.85	program_status_error_t	252
6.86	time_source_t	253
6.87	scheduler_status_t	253
6.88	stat_manage_t	253
6.89	olc_state_t	254
6.90	contact_type_t	254
6.91	fb_display_mode_t	254
6.92	presence_mode_t	254
7	Standard functional profiles	255
7.1	General	255
7.2	Functional Profile List	255
7.3	SFPTnodeObject (0)	255
7.4	SFPTopenLoopSensor (1)	257
7.5	SFPTclosedLoopSensor (2)	259

7.6	SFPTopenLoopActuator (3).....	261
7.7	SFPTclosedLoopActuator (4).....	263
7.8	SFPTcalendar (6)	265
7.9	SFPTscheduler (7)	266
7.10	SFPTisiMonitorPoint (8)	267
7.11	SFPTdataLogger (9)	268
7.12	SFPTschedulerSimple (17)	271
7.13	SFPTchannelMonitor (132).....	271
7.14	SFPTdeviceMonitor (136).....	275
7.15	SFPTchannelContinuityMonitor (137).....	276
7.16	SFPTstaticProgrammable (410).....	277
7.17	SFPTanalogInput (520).....	278
7.18	SFPTanalogOutput (521).....	278
7.19	SFPTlightSensor (1010)	278
7.20	SFPTglobalSolarRadiation (1015).....	279
7.21	SFPTpressureSensor (1030).....	279
7.22	SFPTthvacTempSensor (1040).....	281
7.23	SFPTfrostSensor (1042)	281
7.24	SFPTthvacRelativeHumiditySensor (1050).....	282
7.25	SFPTtrainSensor (1051)	282
7.26	SFPToccupancySensor (1060).....	283
7.27	SFPTisiOccupancySensor (1061)	283
7.28	SFPTco2Sensor (1070).....	285
7.29	SFPTairVelocitySensor (1083).....	285
7.30	SFPTutilityDataLoggerRegister (2110)	287
7.31	SFPTutilityMeter (2201)	288
7.32	SFPTlampActuator (3040).....	289
7.33	SFPTisiLampActuator (3041).....	290
7.34	SFPTconstantLightController (3050)	293
7.35	SFPToccupancyController (3071)	294
7.36	SFPTswitch (3200)	295
7.37	SFPTscenePanel (3250).....	296
7.38	SFPTsceneController (3251)	296
7.39	SFPTpartitionWallController (3252)	297
7.40	SFPTisiKeypad (3253)	298
7.41	SFPTrealTimeKeeper (3300)	300
7.42	SFPTrealTimeBasedScheduler (3301).....	301
7.43	SFPTlightingPanelController (3401).....	301
7.44	SFPToutdoorLuminairController (3512).....	302
7.45	SFPTsmartLuminaireController (3514).....	303
7.46	SFPThardwiredGasDetectionShutdown (4310).....	304
7.47	SFPThardwiredFireAlarmShutdown (4311)	305
7.48	SFPThardwiredRecirculation (4312)	306
7.49	SFPThardwiredFullVentilation (4313).....	306
7.50	SFPThardwiredSafetyInstrumentedSystemSIS (4314).....	307
7.51	SFPTidentifierSensor (5035).....	307
7.52	SFPTentryExit (5051).....	308
7.53	SFPTmodemController (5091)	310
7.54	SFPTtelephoneDirectory (5092).....	311
7.55	SFPTvariableSpeedMotorDrive (6010)	311
7.56	SFPTsunblindActuator (6110)	312
7.57	SFPTsunblindController (6111).....	313
7.58	SFPTisiSunblindActuator (6112)	317

7.59	SFPTvariableAirVolume (8010).....	319
7.60	SFPTfanCoilUnit (8020)	323
7.61	SFPTroofTopUnit (8030)	325
7.62	SFPTchiller (8040)	328
7.63	SFPTheatPump (8051)	330
7.64	SFPTthermostat (8060).....	332
7.65	SFPTchilledCeilingController (8070)	335
7.66	SFPTunitVentilatorController (8080).....	341
7.67	SFPTsccCommandModule (8090).....	348
7.68	SFPTdamperActuator (8110).....	352
7.69	SFPTpumpController (8120).....	355
7.70	SFPTthvacValvePositioner (8131).....	358
7.71	SFPTboilerController (8301)	364
7.72	SFPTspaceComfortController (8500).....	366
7.73	SFPTsccFanCoil (8501).....	374
7.74	SFPTsccVAV (8502).....	381
7.75	SFPTsccHeatPump (8503).....	389
7.76	SFPTsccRooftop (8504)	397
7.77	SFPTsccUnitVentilator (8505)	404
7.78	SFPTsccChilledCeiling (8506)	412
7.79	SFPTsccRadiator (8507)	420
7.80	SFPTsccAHU (8508)	428
7.81	SFPTsccSelfContained (8509)	435
7.82	SFPTwallUnit (8540)	443
7.83	SFPTunitHeater (8550)	448
7.84	SFPTdischargeAirController (8610).....	451
7.85	SFPTrailcarAudioController (9111)	461
7.86	SFPTrailcarAudioSensor (9112)	462
7.87	SFPTrefrigDisplayCaseControllerDefrost (10010)	463
7.88	SFPTrefrigDisplayCaseControllerEvaporator (10011)	464
7.89	SFPTrefrigDisplayCaseControllerThermostat (10012).....	467
7.90	SFPTfireSmokeDamperActuator (11001)	469
7.91	SFPTsmokeFireInitiatorIntelli (11002)	470
7.92	SFPTsmokeFireInitiatorConvent (11003).....	472
7.93	SFPTthermalFireInitiator (11004)	473
7.94	SFPTpullStationFireInitiator (11005)	474
7.95	SFPTaudibleFireIndicator (11006).....	475
7.96	SFPTvisibleFireIndicator (11007)	477
7.97	SFPTuniversalFireInitiator (11010).....	478
7.98	SFPTuniversalFireIndicator (11011)	479
7.99	SFPTgeneratorSet (13110)	480
7.100	SFPTautomaticTransferSwitch (13120)	482
7.101	SFPTelevatorPositionIndicator (14011).....	485
7.102	SFPTelevatorHallLantern (14012).....	486
7.103	SFPTelevatorArrivalGong (14013)	487
7.104	SFPTelevatorDirectionLantern (14014).....	488
7.105	SFPTelevatorFireSystemsPort (14041).....	489
7.106	SFPTelevatorVoiceAnnouncer (14061).....	490
7.107	SFPTclothesWasherDomestic (15011)	490
7.108	SFPTpresenceDetection (16101).....	492
7.109	SFPTwindowMonitoring (16102).....	492
7.110	SFPTdewpointMonitoring (16103).....	492
7.111	SFPTairTemperatureSensor (16104)	493

7.112	SFPToutdoorBrightnessMeasurement (16105)	493
7.113	SFPTroomBrightnessMeasurement (16106)	494
7.114	SFPTairQualityMeasurement (16107)	494
7.115	SFPTwindVelocityMeasurement (16108)	495
7.116	SFPTprecipitationDetection (16109)	495
7.117	SFPTlightActuator (16201)	495
7.118	SFPTsunshadeActuator (16202)	496
7.119	SFPTcontrolDriveActuator (16203)	497
7.120	SFPTcontrolDriveActuatorFan (16204)	497
7.121	SFPTactuateLight (16401)	498
7.122	SFPTactuateSunshade (16402)	499
7.123	SFPTactuateDrive (16403)	499
7.124	SFPTactuateDriveFan (16404)	500
7.125	SFPTactuateTemperatureSetpoint (16405)	500
7.126	SFPTselectRoomUtilisationType (16406)	501
7.127	SFPTsignalPresence (16407)	501
7.128	SFPToccupancyEvaluator (16501)	502
7.129	SFPTcontrolRoomUtilisationTypes (16502)	502
7.130	SFPTtimeProgram (16503)	503
7.131	SFPTpartitionWallControl (16504)	503
7.132	SFPTlightControl (16505)	504
7.133	SFPTstairwellLightControl (16506)	505
7.134	SFPTautomaticLightController (16507)	505
7.135	SFPTdaylightDependentLighting (16508)	505
7.136	SFPTconstantLightControl (16509)	506
7.137	SFPTtwilightControl (16510)	507
7.138	SFPTpriorityControl (16511)	508
7.139	SFPTautomaticTwilightControl (16512)	509
7.140	SFPTautomaticSolarControl (16513)	510
7.141	SFPTslatTracking (16514)	511
7.142	SFPTshadowCorrection (16515)	512
7.143	SFPTautomaticThermalControl (16516)	512
7.144	SFPTweatherProtection (16517)	513
7.145	SFPTenergyModeSelection (16518)	514
7.146	SFPTenergyModeSelectionWithStartOpt (16519)	515
7.147	SFPTsetpointCalculation (16520)	516
7.148	SFPTfunctionSelection (16521)	517
7.149	SFPTtemperatureControl (16522)	518
7.150	SFPTroomSupplyAirTemperatureMC (16523)	519
7.151	SFPTroomSupplyAirTemperatureSC (16524)	520
7.152	SFPTfanControl (16525)	521
7.153	SFPTsequenceControl (16526)	522
7.154	SFPTmanipulatedValueLimiting (16527)	522
7.155	SFPTairQualityControl (16528)	523
7.156	SFPTnightTimeCooling (16529)	524
7.157	SFPTvolumeFlowControl (16530)	525
8	Device-interface files	526
8.1	Introduction	526
8.2	Text Device-Interface File Format	526
8.2.1	General	526
8.2.2	Header Section	527
9	Standard method of file transfer between devices	541

9.1	Introduction	541
9.2	Windowed Transfer Protocol.....	541
9.3	Setting-Up a File Transfer.....	542
9.4	Random Access	543
9.5	Delayed Responses.....	543
9.6	Completing a Data Exchange	543
9.7	Completing a File Transfer.....	544
9.8	Multicast File Transfers.....	544
9.9	Concurrency	544
9.10	SNVT_file_req Data Structure	544
9.11	SNVT_file_status Data Structure	546
9.12	SNVT_file_pos Data Structure	546
9.13	Application Protocol Data Unit Structure.....	547
Annex A (informative) Protocol Processor Types.....		548
Annex B (normative) Standard Program Identifier (SPID) List.....		549
B.1	General	549
B.2	Manufacturer Field	549
B.3	Device Class Field	549
B.4	Usage Field	561
B.4.1	General	561
B.4.2	Usage ID.....	561
B.5	Channel Type Field.....	562
Annex C (informative) Standard Transceiver-Type Identifiers		563
Bibliography		564

European foreword

This document (EN 14908-6:2022) has been prepared by Technical Committee CEN/TC 247 “Building Automation, Controls and Building Management”, the secretariat of which is held by SNV.

This European Standard shall be given the status of a national standard, either by publication of an identical text or by endorsement, at the latest by June 2023 and conflicting national standards shall be withdrawn at the latest by June 2023.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. CEN shall not be held responsible for identifying any or all such patent rights.

This document supersedes EN 14908-6:2014.

The main changes compared to EN 14908-6:2014 are as follows:

- Adding 11 Standard Network Variables Types – SNVTs;
- Adding 29 Standard Configuration Property Types – SCPTs;
- Adding 5 Standard Enumerations – ENUM;
- Adding 57 Standard Functional Profile Types – SFPTs;
- The wording Master/Slave is replaced with appropriate language.

This document is part of the EN 14908 series, which consists of the following parts:

- EN 14908-1, *Open Data Communication in Building Automation, Controls and Building Management — Control Network Protocol — Part 1: Protocol Stack*
- EN 14908-2, *Open Data Communication in Building Automation, Controls and Building Management — Control Network Protocol — Part 2: Twisted Pair Communication*
- EN 14908-3, *Open Data Communication in Building Automation, Controls and Building Management — Control Network Protocol — Part 3: Power Line Channel Specification*
- EN 14908-4, *Open Data Communication in Building Automation, Controls and Building Management — Control Network Protocol — Part 4: IP Communication*
- EN 14908-5, *Open Data Communication in Building Automation, Controls and Building Management Implementation Guideline — Control Network Protocol — Part 5: Implementation*
- EN 14908-6, *Open Data Communication in Building Automation, Controls and Building Management — Control Network Protocol — Part 6: Application Elements*
- EN 14908-7, *Open communication in building automation, controls and building management — Control Network Protocol — Part 7: Communication via internet protocols*
- EN 14908-8, *Open Data Communication in Building Automation, Controls and Building Management - Control Network Protocol - Part 8: Communication using Broadband over Power Line Networks - with internet protocols*
- EN 14908-9, *Open Data Communication in Building Automation, Controls and Building Management - Control Network Protocol - Part 9: Wireless Communication in ISM bands*

The content of this European Standard covers the data communications used for management, automation/control and field functions.

Any feedback and questions on this document should be directed to the users' national standards body. A complete listing of these bodies can be found on the CEN website.

According to the CEN-CENELEC Internal Regulations, the national standards organizations of the following countries are bound to implement this European Standard: Austria, Belgium, Bulgaria, Croatia, Cyprus, Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, Netherlands, Norway, Poland, Portugal, Republic of North Macedonia, Romania, Serbia, Slovakia, Slovenia, Spain, Sweden, Switzerland, Türkiye and the United Kingdom.

Introduction

This document is intended to be used by all involved in design, manufacture, engineering, installation and commissioning activities.

This document specifies the definition of various types of data-transfer containers for carrying temperature, pressure, state, and other forms of data over the protocol defined by EN 14908-1 from any number of devices to any other number of devices, as defined by the limits in EN 14908-1. It also specifies the data types for configuration information, used to define timing, default values, and other data. This document describes a data-file transfer method that may be used for transferring configuration information to and from devices, and specifies the device-interface format that describes the interconnection points of a device.

NOTE The file-transfer mechanism is not exclusively used for loading configuration information into a device and can therefore have other purposes.

This document contributes to the general European policy for energy savings, particularly in the field of the “Energy Performance of Building Directive” and the Construction Products Directive (ER No. 6 “Energy Economy and Heat Retention”).

1 Scope

This document provides mechanisms through which various vendors of building automation, control, and building management systems may exchange information in a standardized way.

This document provides specifications for the Application Elements of Control Network Protocol packets as follows:

- definitions of standardized packet (network-variable) data types;
- definitions of device-interface files;
- definitions of standardized configuration-property types;
- definitions of standardized enumeration types;
- definitions of standardized functional profiles;
- definition of the standardized method of file transfer between devices.

The purpose of this document is to ensure interoperability between various CNP implementations. This document contains all the information necessary to read and interpret the format of data and control information that is used by EN 14908-5. It also defines the device interface for a device as specified, which is necessary to exchange data between various devices from different manufacturers.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

EN 14908-1, *Open Data Communication in Building Automation, Controls and Building Management — Building Network Protocol — Part 1: Protocol Stack*

EN 14908-2, *Open Data Communication in Building Automation, Controls and Building Management — Control Network Protocol — Part 2: Twisted Pair Communication*

EN 14908-3, *Open Data Communication in Building Automation, Controls and Building Management — Control Network Protocol — Part 3: Power Line Channel Specification*

EN 14908-4, *Open Data Communication in Building Automation, Controls and Building Management — Control Network Protocol — Part 4: IP Communication*

EN 14908-5, *Open Data Communication in Building Automation, Controls and Building Management Implementation Guideline — Control Network Protocol — Part 5: Implementation*

3 Terms and definitions

For the purposes of this document, the terms and definitions given in EN 14908-1 and the following apply.

ISO and IEC maintain terminology databases for use in standardization at the following addresses:

- IEC Electropedia: available at <https://www.electropedia.org/>
- ISO Online browsing platform: available at <https://www.iso.org/obp>

3.1

application set

functional block or functional blocks to which a configuration property applies

EXAMPLE A network variable, a series or compilation of network variables, a functional block, a series or compilation of functional blocks, or the entire device.

3.2

base type

fundamental type that can be used as the basis of a network-variable type or configuration-property type

Note 1 to entry: The available base types are defined in EN 14908-5.

3.3

changeable-type network variable

network variable whose type can be changed during installation

3.4

CNP device

hardware and software that runs an application and communicates with other devices using the EN 14908-1 protocol

Note 1 to entry: It may optionally interface with input/output hardware. A CNP device includes at least one processor and a CNP transceiver also called a CNP node, or simply a node.

3.5

CNP network

collection of intelligent devices that communicate with each other using the EN 14908-1 protocol over one or more communications channels

3.6

configuration property

CP

data value used to configure the application program in a device

Note 1 to entry: Configuration properties are used to set parameters such as maximum, minimum, default, and override values. CPs are implemented using configuration network variables or as data items within configuration files. Configuration-property data are kept in a device's non-volatile memory.

3.7

configuration-property member

part of a functional profile

Note 1 to entry: See 3.24.

3.8**configuration-property member number**

part of a functional profile

Note 1 to entry: See 3.25.

3.9**configuration-property type index**

16-bit number that uniquely identifies a configuration-property type within the scope defined by the scope number and program-ID template of the resource file that contains the configuration-property type definition

3.10**device**

logical and physical entity of the network containing an application that is designed to communicate with other logical and physical entities

3.11**device channel Identifier**

number that optionally specifies the channel to which a device is attached

3.12**device class**

two-byte field identifying the primary function of a device and part of the SPID of the device

3.13**device interface**

network-visible interface to a device consisting of the unique node ID, program ID, channel ID, location field, device self-documentation string, device configuration properties, and functional blocks

3.14**device-location field**

string or number that optionally specifies the location of a device

3.15**device self-documentation string****DSDS**

string that specifies the structure of the contents of the self-documentation strings, the functional blocks, and optionally describes the function of a device

3.16**device subclass**

two-byte field specifying the usage in the first byte and the channel type in the second byte and is part of the SPID of a device

Note 1 to entry: See the usage and channel-type definitions.

3.17**dynamic functional block**

functional block that is added to a device by a network tool after the device is installed

3.18

dynamic network variable

network variable that is added to a device by a network tool after the device is installed

3.19

format

<program ID> four-bit value defining the structure of the program ID as being a Standard Program Identifier (SPID) and device self-documentation string (DSDS) in the device

<resource file> string that provides formatting instructions for a network-variable or configuration-property type

3.20

functional block

fblock

portion of a device's application that performs a task by receiving configuration and operational data inputs, processing the data, and sending operational data outputs

Note 1 to entry: A functional block may receive inputs from the network, from hardware attached to the device, and/or from other functional blocks on a device. A functional block may send outputs to the network, to hardware attached to the device, and/or to other functional blocks on the device. A functional block is an implementation of a functional profile. A "standard" functional block is one based on a standard functional profile template (SFPT).

3.21

functional-block index

sequentially assigned number identifying a functional-block implementation on a device

3.22

functional profile

FP

template that describes common units of functional behaviour, also known as profiles, or FPs, which can be represented with a machine-readable functional-profile template (FPT)

Note 1 to entry: Each functional profile consists of a profile description and a specified set of network variables and configuration properties designed to perform a single function on a device. The network variables and configuration properties specified by the functional profile are called the functional-profile members. A functional profile specifies whether the implementation of each functional-profile member is mandatory or optional. A profile is uniquely identified by a program-ID template, scope, and functional-profile number.

3.23

functional-profile key

functional-profile number

Note 1 to entry: See 3.26.

3.24

functional-profile member

network-variable or configuration-property member of a functional profile

Note 1 to entry: Each functional-profile member is identified as mandatory or optional by the functional profile. Each member also includes a text description of the member for the functional profile.

3.25**functional-profile member number**

two-byte number that uniquely identifies a network-variable or configuration-property member of a functional profile

Note 1 to entry: This member number is used to associate a network variable or configuration property on a device with the corresponding network-variable or configuration-property member of the functional profile. Member numbers should be in the range of 1 to 4 095, and need not be contiguous. Member numbers shall be unique, with the exception that network-variable and configuration-property members may use the same number (therefore, network-variable members' numbers should be unique, and configuration-property members' numbers should be unique, but they need not be unique between network-variable members and configuration-property members). There may be a maximum of 255 mandatory members and 255 optional members of each type (scope 0 NV, inheriting NV, scope 0 CP, and inheriting CP).

3.26**functional-profile number**

two-byte number that uniquely identifies a functional profile within the scope defined by the scope number and program-ID template of the resource file that contains the functional-profile definition

Note 1 to entry: The functional profile number is also called the "functional-profile key", or the "FPT key".

3.27**functional-profile selector**

ASCII vertical bar ("|") or ASCII number sign ("#") to denote the association of a network variable or configuration property with a scope-0 profile or a profile of a higher-numbered scope, respectively, where a higher-numbered scope would denote the NV or CP was added to enhance a scope-0 profile or that it applies to a non-standard profile

EXAMPLE The "|1" member of a functional profile is not the same as the "#1" member of the same profile. This prevents conflicts if new members are added to a standard functional profile that has already been used as the basis for inheriting profiles.

Note 1 to entry: If the functional profile selector is a vertical bar, the member number identifies a member of a scope-0 profile. If the functional profile selector is a number sign, the member number identifies a member of the inheriting profile. The number-sign functional profile selector is always used for members of user functional profiles, including profiles that do not use inheritance. The vertical-bar functional profile selector is always used for members of standard functional profiles. Two different functional profile members may have the same member number as long as they use different functional profile selectors.

3.28**functional-profile template**

functional profile in human- and machine-readable form

Note 1 to entry: See 3.22.

3.29**global index**

functional-block index

Note 1 to entry: See 3.21.

3.30**inheriting profile**

functional profile that inherits members from a scope-0 profile

3.31

interoperability

conditions that ensure multiple devices – from the same or different manufacturers – can be integrated into a single network without requiring custom device or tool development

3.32

manufacturer Identifier

MID

20-bit number that uniquely identifies the device manufacturer of a device and is part of the device's SPID

3.33

network-interface selection

form of network-variable selection that occurs on the network interface

3.34

network variable

NV

data item that a particular device application program expects to get from other devices on a network (an input network variable) or expects to make available to other devices on a network (an output network variable)

EXAMPLE A temperature, switch value, and actuator-position setting.

Note 1 to entry: Network variable data are typically stored in a device's volatile memory.

3.35

network-variable declaration

establishment of an instance of a network variable type within the code of an application

3.36

network-variable index

sequentially assigned number identifying a network variable implementation on a device

Note 1 to entry: For Neuron C applications, the index is assigned by the Neuron C compiler in the order of declaration. The first network variable on a device has index 0, the second index 1, etc.

3.37

network-variable member

functional-profile member that is a network variable

Note 1 to entry: See 3.24.

3.38

network-variable member number

number of a functional-profile member that is a network variable

Note 1 to entry: See 3.25.

3.39**network-variable programmatic name**

name assigned to a network-variable implementation by the device application developer

Note 1 to entry: The programmatic name is limited to 16 characters, including any optional prefixes. The programmatic name is not significant for interoperability, but conventions are suggested in EN 14908-5 to make programmatic names easier to use for integrators.

3.40**network-variable selection**

process of associating a network-variable selector with a network variable on a device

3.41**network-variable type**

specification of the length, units, valid range, and resolution of the data contained within a network variable

Note 1 to entry: A network variable type may be a simple, one, two, or four-byte scalar type; or a more complex structure or union of up to 31 bytes.

3.42**network-variable type index**

16-bit number that uniquely identifies a network-variable type within the scope defined by the scope number and program-ID template of the resource file that contains the network-variable type definition

3.43**unique node Identifier****UID**

unique 48-bit identifier within the read-only data structure of a device as defined by the EN 14908-1 protocol

Note 1 to entry: It is also called the “unique_node_ID”.

3.44**node**

<common> device

<precise> physical and logical presence on a CNP network with a unique node ID and network address

Note 1 to entry: The unique node ID relates to the identification of a single instance of an implemented EN 14908-1 protocol stack. A device is also a network presence with an application processor and one or more nodes. A device with multiple unique node IDs would consist of multiple nodes. Some infrastructure devices, such as routers, also consist of more than one unique node ID and thus consist of multiple nodes.

3.45**passive configuration tool****PCT**

network tool that can be used on a device to assist in the successful commissioning of the device without disrupting the operation of other network tools

Note 1 to entry: It may be a plug-in, standalone software, hardware attachment, or other tool. A passive configuration tool has attributes and capabilities as defined in EN 14908-5.

3.46

primary functional block

functional block on a device that implements the most important function for the device

3.47

primary functional profile

functional profile that defines the primary functional block on a device

3.48

proprietary data

data and message definitions in the device interface that are known only to the manufacturer and the manufacturer's agents

3.49

self-documentation string

SD string

text string associated with a device, network variable, or configuration property that is stored within a device and within the device interface (XIF) file for a device

Note 1 to entry: Network tools can read the self-documentation strings from the device itself or from the device interface file.

3.50

self-documentation text

optional text within a device, network variable, or configuration property self-documentation string that provides documentation of the intended use of the device, network variable, or configuration property respectively for use by integrators

3.51

shared-media channel

communications channel where messages can leak between tools and devices belonging to different systems

3.52

SNVT_xxx

placeholder for SNVT chosen by the manufacturer – at the time of the device's development – for a network variable that is defined by a functional profile, but where the type for the network variable is not defined by the profile

Note 1 to entry: See definition of SNVT in 4.1.

3.53

standard configuration-property type

SCPT

configuration-property type that has been standardized by this document in Clause 4

Note 1 to entry: A SCPT is a standardized definition of the units, scaling, encoding, valid range, and meaning of the contents of configuration properties.

3.54

standard network-variable type

SNVT

network-variable type that has been standardized by this document in 4.1

3.55**standard program Identifier****SPID**

eight-byte number that uniquely identifies the device interface for a device

Note 1 to entry: Encoded according to rules specified in Annex B.

3.56**static functional block**

functional block that is statically defined for a device; that is, a functional block that is not a dynamic functional block

3.57**static network variable**

network variable that is statically defined for a device; that is, a network variable that is not a dynamic network variable

3.58**subsystem**

two or more devices working together to perform a function and bearing fixed, pre-defined relationships to one another

Note 1 to entry: A subsystem may use one or more EN 14908-1 domains.

3.59**successful commissioning**

<noun> process of taking a device and integrating it into a network

<adjective> device can be physically installed in a network and made to perform its application function with the exclusive use of its device interface and a choice of third-party tools

3.60**system**

one or more independently managed subsystems working together to perform a function

Note 1 to entry: A system may use one or more EN 14908-1 domains.

3.61**unconfigured device**

device without a valid network configuration

3.62**usage**

one-byte value describing the intended usage of the device and is part of the SPID of a device

Note 1 to entry: The usage field consists of a one-bit changeable-interface flag, a one-bit functional-profile-specific flag, and a 6-bit usage ID.

3.63**usage Identifier**

six-bit value in the least-significant portion of the usage field that identifies the primary intended usage of a device

3.64

user data

non-standardized user functional blocks, user network variables, and user configuration properties used by a device manufacturer to augment the device interface

3.65

wink function

function provided by a device that allows a network integrator to physically identify the device

EXAMPLE A wink function may blink an LED on the device.

4 Standard network-variable type — SNVT

4.1 Introduction

CNP devices typically exchange data using network variables. Network variables greatly simplify the tasks of designing CNP application programs for interoperability with multiple vendors' products. A network variable is any data item (temperature, a switch value, or an actuator position setting) that a particular device application program expects to get from other devices on the network (an *input network variable*) or expects to make available to other devices on the network (an *output network variable*).

When the application program has a changed value for an output network variable, it simply passes the new value to the device firmware. Via a process that takes place during network design and installation called *binding*, the protocol stack is configured to know the logical address of the other devices or group of devices in the network expecting that network variable, and it assembles and sends the appropriate packets to these devices. Similarly, when the protocol stack receives an updated value for an input network variable required by its application program, it passes the data to the application program. The binding process thus creates logical *connections* between an output network variable in one device and an input network variable in another device or group of devices. Connections may be thought of as "virtual wires".

Every network variable has a type that defines the units, scaling, and structure of the data contained within the network variable. Network variables shall be the same type to be connected. This prevents common installation errors from occurring such as a pressure output being connected to a temperature input. Type translators are available to convert network variables of one type to another type. This document specifies standard network-variable types (SNVTs) that define commonly used types. Alternatively, manufacturers may define their own user network-variable types (UNVTs). UNVTs shall be documented in manufacturer-specific resource files.

Basic data types (e.g. signed long) and their sizes are specified in EN 14908-5.

4.2 SNVT_amp

Overview: Electric current in Amperes.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
1	2	signed long	-32 768	32 767	$1 \times 10^{-1} \times (Raw+0)$	0,1 Amperes

4.3 SNVT_amp_mil

Overview: Electric current in milliAmperes.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
2	2	signed long	-32 768	32 767	$1 \times 10^{-1} \times (Raw+0)$	0,1 milliAmperes

4.4 SNVT_angle

Overview: Angular distance in radians.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
3	2	unsigned long	0	65 535	$1 \times 10^{-3} \times (Raw+0)$	0,001 radians

4.5 SNVT_angle_vel

Overview: Angular velocity in radians/second.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
4	2	signed long	-32 768	32 767	$1 \times 10^{-1} \times (Raw+0)$	0,1 radians/second

4.6 SNVT_btu_kilo

Overview: Thermal energy in kilo-Btus.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
5	2	unsigned long	0	65 535	$1 \times 10^0 \times (Raw+0)$	1 kilo-Btus

4.7 SNVT_btu_mega

Overview: Thermal energy in mega-Btus.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
6	2	unsigned long	0	65 535	$1 \times 10^0 \times (Raw+0)$	1 mega-Btus

4.8 SNVT_char_ascii

Overview: ASCII character in 8-bit ASCII character.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
7	1	unsigned char	0	255	$1 \times 10^0 \times (Raw+0)$	1 8-bit ASCII character

4.9 SNVT_count

Overview: Absolute count in units.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
8	2	unsigned long	0	65 535	$1 \times 10^0 \times (Raw+0)$	1 units

4.10 SNVT_count_inc

Overview: Increment count in units (delta).

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
9	2	signed long	-32 768	32 767	$1 \times 10^0 \times (Raw+0)$	1 units (delta)

4.11 SNVT_date_day

Overview: Day of week.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
11	1	days_of_week_t	-1	6	none (enumeration)	-1

4.12 SNVT_elec_kwh

Overview: Electrical energy in kiloWatt-hours.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
13	2	unsigned long	0	65 535	$1 \times 10^0 \times (Raw+0)$	1 kW-h

4.13 SNVT_elec_whr

Overview: Electrical energy in Watt-hours.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
14	2	unsigned long	0	65 535	$1 \times 10^{-1} \times (Raw+0)$	0,1 W-h

4.14 SNVT_flow

Overview: Flow volume in liters/second.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
15	2	unsigned long	0	65 535	$1 \times 10^0 \times (Raw+0)$	1 l/s

4.15 SNVT_flow_mil

Overview: Flow volume in milliliters/second.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
16	2	unsigned long	0	65 535	$1 \times 10^0 \times (Raw+0)$	1 ml/s

4.16 SNVT_length

Overview: Length in meters.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
17	2	unsigned long	0	65 535	$1 \times 10^{-1} \times (Raw+0)$	0,1 m

4.17 SNVT_length_kilo

Overview: Length in kilometers.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
18	2	unsigned long	0	65 535	$1 \times 10^{-1} \times (Raw+0)$	0,1 km

4.18 SNVT_length_micr

Overview: Length in micrometers (microns).

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
19	2	unsigned long	0	65 535	$1 \times 10^{-1} \times (Raw+0)$	0,1 μm (microns)

4.19 SNVT_length_mil

Overview: Length in millimeters.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
20	2	unsigned long	0	65 535	$1 \times 10^{-1} \times (Raw+0)$	0,1 mm

4.20 SNVT_lev_cont

Overview: Continuous level in % of full level.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
21	1	unsigned short	0	200	$5 \times 10^{-1} \times (Raw+0)$	0,5 % of full level

4.21 SNVT_mass

Overview: Mass in grams.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
23	2	unsigned long	0	65 535	$1 \times 10^{-1} \times (Raw+0)$	0,1 g

4.22 SNVT_mass_kilo

Overview: Mass in kilograms.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
24	2	unsigned long	0	65 535	$1 \times 10^{-1} \times (Raw+0)$	0,1 kg

4.23 SNVT_mass_mega

Overview: Mass in metric tons.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
25	2	unsigned long	0	65 535	$1 \times 10^{-1} \times (Raw+0)$	0,1 t

4.24 SNVT_mass_mil

Overview: Mass in milligrams.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
26	2	unsigned long	0	65 535	$1 \times 10^{-1} \times (Raw+0)$	0,1 mg

4.25 SNVT_power

Overview: Power in Watts.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
27	2	unsigned long	0	65 535	$1 \times 10^{-1} \times (Raw+0)$	0,1 W

4.26 SNVT_power_kilo

Overview: Power in kiloWatts.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
28	2	unsigned long	0	65 535	$1 \times 10^{-1} \times (Raw+0)$	0,1 kW

4.27 SNVT_ppm

Overview: Concentration in ppm.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
29	2	unsigned long	0	65 535	$1 \times 10^0 \times (Raw+0)$	1 ppm

4.28 SNVT_press

Overview: Pressure (gauge) in kiloPascals.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
30	2	signed long	-32 768	32 767	$1 \times 10^{-1} \times (Raw+0)$	0,1 kP

4.29 SNVT_res

Overview: Electric resistance in Ohms.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
31	2	unsigned long	0	65 535	$1 \times 10^{-1} \times (Raw+0)$	0,1 Ohms

4.30 SNVT_res_kilo

Overview: Electric resistance in kiloOhms.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
32	2	unsigned long	0	65 535	$1 \times 10^{-1} \times (Raw+0)$	0,1 kiloOhms

4.31 SNVT_sound_db

Overview: Sound level in dB.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
33	2	signed long	-32 768	32 767	$1 \times 10^{-2} \times (Raw+0)$	0,01 dB

4.32 SNVT_speed

Overview: Linear velocity in meters/second.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
34	2	unsigned long	0	65 535	$1 \times 10^{-1} \times (Raw+0)$	0,1 m/s

4.33 SNVT_speed_mil

Overview: Linear velocity in meters/second.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
35	2	unsigned long	0	65 535	$1 \times 10^{-3} \times (Raw+0)$	0,001 m/s

4.34 SNVT_str_asc

Overview: Character string (30 characters max).

Index	Size in Bytes	CNP Data Type			
36	31	structure			
Field			CNP Data Type/ Invalid Value	Maximum/ Minimum	Scaled Value/ Resolution
SNVT_str_asc.ascii			unsigned char	255	$1 \times 10^0 \times (Raw+0)$
			(none)	0	1 array of 31 characters

4.35 SNVT_str_int

Overview: Wide character string with locale code (15 characters max).

Index	Size in Bytes	CNP Data Type			
37	31	structure			
Field			CNP Data Type/ Invalid Value	Maximum/ Minimum	Scaled Value/ Resolution
SNVT_str_int.char_set			unsigned short	255	$1 \times 10^0 \times (Raw+0)$
			(none)	0	1 code value
SNVT_str_int.wide_char			unsigned long	65 535	$1 \times 10^0 \times (Raw+0)$
			(none)	0	1 array of 15 wide characters

4.36 SNVT_telcom

Overview: Telecomm states.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
38	1	telcom_states_t	-1	20	none (enumeration)	-1

4.37 SNVT_temp

Overview: Temperature in degrees Celsius.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
39	2	unsigned long	0	65 535	$1 \times 10^{-1} \times (Raw - 2740)$	0,1 °C

4.38 SNVT_vol

Overview: Volume in liters.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
41	2	unsigned long	0	65 535	$1 \times 10^{-1} \times (Raw + 0)$	0,1 l

4.39 SNVT_vol_kilo

Overview: Volume in kiloliters.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
42	2	unsigned long	0	65 535	$1 \times 10^{-1} \times (Raw + 0)$	0,1 kl

4.40 SNVT_vol_mil

Overview: Volume in milliliters.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
43	2	unsigned long	0	65 535	$1 \times 10^{-1} \times (Raw + 0)$	0,1 ml

4.41 SNVT_volt

Overview: Electric potential in Volts.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
44	2	signed long	-32 768	32 767	$1 \times 10^{-1} \times (Raw + 0)$	0,1 V

4.42 SNVT_volt_dbmv

Overview: Electric potential in dB microVolts.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
45	2	signed long	-32 768	32 767	$1 \times 10^{-2} \times (Raw + 0)$	0,01 dB microVolts

4.43 SNVT_volt_kilo

Overview: Electric potential in kiloVolts.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
46	2	signed long	-32 768	32 767	$1 \times 10^{-1} \times (Raw+0)$	0,1 kV

4.44 SNVT_volt_mil

Overview: Electric potential in milliVolts.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
47	2	signed long	-32 768	32 767	$1 \times 10^{-1} \times (Raw+0)$	0,1 mV

4.45 SNVT_amp_f

Overview: Electric current in Amperes.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
48	4	floating-point	-3,402 823 466 385 3E + 038	3,402 823 466 385 3E + 038	floating	NAN and Out of Range

4.46 SNVT_angle_f

Overview: Angular distance in radians.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
49	4	floating-point	-3,402 823 466 385 3E + 038	3,402 823 466 385 3E + 038	floating	NAN and Out of Range

4.47 SNVT_angle_vel_f

Overview: Angular velocity in radians/second.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
50	4	floating-point	-3,402 823 466 385 3E + 038	3,402 823 466 385 3E + 038	floating	NAN and Out of Range

4.48 SNVT_count_f

Overview: Absolute count in units.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
51	4	floating-point	0	3,402 823 466 385 3E + 038	floating	NAN and Out of Range

4.49 SNVT_count_inc_f**Overview:** Increment count in units (delta).

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
52	4	floating-point	-3,402 823 466 385 3E + 038	3,402 823 466 385 3E + 038	floating	NAN and Out of Range

4.50 SNVT_flow_f**Overview:** Flow volume in liters/second.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
53	4	floating-point	-3,402 823 466 385 3E + 038	3,402 823 466 385 3E + 038	floating	NAN and Out of Range

4.51 SNVT_length_f**Overview:** Length in meters.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
54	4	floating-point	0	3,402 823 466 385 3E + 038	floating	NAN and Out of Range

4.52 SNVT_lev_cont_f**Overview:** Continuous level in % of full scale.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
55	4	floating-point	0	100	floating	NAN and Out of Range

4.53 SNVT_mass_f**Overview:** Mass in grams.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
56	4	floating-point	0	3,402 823 466 385 3E + 038	floating	NAN and Out of Range

4.54 SNVT_power_f**Overview:** Power in Watts.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
57	4	floating-point	-3,402 823 466 385 3E + 038	3,402 823 466 385 3E + 038	floating	NAN and Out of Range

4.55 SNVT_ppm_f

Overview: Concentration in ppm.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
58	4	floating-point	0	3,402 823 466 385 3E + 038	floating	NAN and Out of Range

4.56 SNVT_press_f

Overview: Pressure (gauge) in Pascals.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
59	4	floating-point	-3,402 823 466 385 3E + 038	3,402 823 466 385 3E + 038	floating	NAN and Out of Range

4.57 SNVT_res_f

Overview: Electric resistance in Ohms.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
60	4	floating-point	0	3,402 823 466 385 3E+038	floating	NAN and Out of Range

4.58 SNVT_sound_db_f

Overview: Sound level in dBSpl.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
61	4	floating-point	-3,402 823 466 385 3E + 038	3,402 823 466 385 3E + 038	floating	NAN and Out of Range

4.59 SNVT_speed_f

Overview: Linear velocity in meters/second.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
62	4	floating-point	-3,402 823 466 385 3E + 038	3,402 823 466 385 3E + 038	floating	NAN and Out of Range

4.60 SNVT_temp_f

Overview: Temperature in degrees Celsius.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
63	4	floating-point	-273,170 013 427 73	3,402 823 466 385 3E + 038	floating	NAN and Out of Range

4.61 SNVT_time_f**Overview:** Elapsed time in seconds.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
64	4	floating-point	0	3,402 823 466 385 3E + 038	floating	NAN and Out of Range

4.62 SNVT_vol_f**Overview:** Volume in liters.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
65	4	floating-point	0	3,402 823 466 385 3E + 038	floating	NAN and Out of Range

4.63 SNVT_volt_f**Overview:** Electric potential in Volts.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
66	4	floating-point	-3,402 823 466 385 3E + 038	3,402 823 466 385 3E + 038	floating	NAN and Out of Range

4.64 SNVT_btu_f**Overview:** Thermal energy in Btus.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
67	4	floating-point	0	3,402 823 466 385 3E + 038	floating	NAN and Out of Range

4.65 SNVT_elec_whr_f**Overview:** Electrical energy in Watt-hours.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
68	4	floating-point	0	3,402 823 466 385 3E + 038	floating	NAN and Out of Range

4.66 SNVT_config_src**Overview:** Network configuration source.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
69	1	config_source_t	-1	1	none (enumeration)	-1

4.67 SNVT_color

Overview: CIELAB color.

Index	Size in Bytes	CNP Data Type			
70	6	structure			
Field			CNP Data Type/ Invalid Value	Maximum/ Minimum	Scaled Value/ Resolution
SNVT_color.L_star			unsigned long	1 000	$1 \times 10^{-1} \times (Raw+0)$
			(none)	0	0,1
SNVT_color.a_star			signed long	2 000	$1 \times 10^{-1} \times (Raw+0)$
			(none)	-2 000	0,1
SNVT_color.b_star			signed long	2 000	$1 \times 10^{-1} \times (Raw+0)$
			(none)	-2 000	0,1

4.68 SNVT_grammage

Overview: Density in grams/sq meter.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
71	2	unsigned long	0	65 535	$1 \times 10^{-1} \times (Raw+0)$	0,1 g/m ²

4.69 SNVT_grammage_f

Overview: Density in grams/sq meter.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
72	4	floating-point	0	3,402 823 466 385 3E + 038	floating	NAN and Out of Range

4.70 SNVT_file_req

Overview: File request.

Index	Size in Bytes	CNP Data Type			
73	12	structure			
Field			CNP Data Type/ Invalid Value	Maximum/ Minimum	Scaled Value/ Resolution
SNVT_file_req.request			file_request_t	6	none (enumeration)
			-1	-1	1
SNVT_file_req.index			unsigned long	65 535	$1 \times 10^0 \times (Raw+0)$
			(none)	0	1 file index
SNVT_file_req.receive_timeout			unsigned long	65 535	$1 \times 10^0 \times (Raw+0)$
			(none)	0	1 ms
SNVT_file_req.dest_address			union		

Index	Size in Bytes	CNP Data Type			
73	12	structure			
Field			CNP Data Type/ Invalid Value	Maximum/ Minimum	Scaled Value/ Resolution
SNVT_file_req.dest_address.addrt			structure		
			EN 14908-1 address in device's internal address table entry		
SNVT_file_req.dest_address.addrt.type			unsigned short	33	1×10 ⁰ ×(Raw+0)
			(none)	33	1 8-bit unsigned value
SNVT_file_req.dest_address.addrt.index			unsigned long	65 535	1×10 ⁰ ×(Raw+0)
			(none)	0	1 16-bit unsigned value
SNVT_file_req.dest_address.sn			structure		
SNVT_file_req.dest_address.sn.type			unsigned short	1	1×10 ⁰ ×(Raw+0)
			(none)	1	1 8-bit unsigned value
SNVT_file_req.dest_address.sn.domain			bitfield	1	1×10 ⁰ ×(Raw+0)
				0	1 (bits: 1) (offset: 0)
SNVT_file_req.dest_address.sn.node			bitfield	127	1×10 ⁰ ×(Raw+0)
				0	1 (bits: 7) (offset: 1)
SNVT_file_req.dest_address.sn.retry			bitfield	15	1×10 ⁰ ×(Raw+0)
				0	1 (bits: 4) (offset: 4)
SNVT_file_req.dest_address.sn.tx_timer			bitfield	15	1×10 ⁰ ×(Raw+0)
				0	1 (bits: 4) (offset: 4)
SNVT_file_req.dest_address.sn.subnet			unsigned short	255	1×10 ⁰ ×(Raw+0)
			0	0	1 subnet number
SNVT_file_req.dest_address.gp			structure		
SNVT_file_req.dest_address.gp.type			bitfield	1	1×10 ⁰ ×(Raw+0)
				0	1 (bits: 1) (offset: 0)
SNVT_file_req.dest_address.gp.size			bitfield	65	1×10 ⁰ ×(Raw+0)
				0	1 (bits: 7) (offset: 1)
SNVT_file_req.dest_address.gp.domain			bitfield	1	1×10 ⁰ ×(Raw+0)
				0	1 (bits: 1) (offset: 0)
SNVT_file_req.dest_address.gp.unused			bitfield	0	1×10 ⁰ ×(Raw+0)
				0	1 (bits: 7) (offset: 1)
SNVT_file_req.dest_address.gp.retry			bitfield	15	1×10 ⁰ ×(Raw+0)
				0	1 (bits: 4) (offset: 4)

Index	Size in Bytes	CNP Data Type			
73	12	structure			
Field		CNP Data Type/ Invalid Value	Maximum/ Minimum	Scaled Value/ Resolution	
SNVT_file_req.dest_address.gp.tx_timer		bitfield	15	$1 \times 10^0 \times (Raw+0)$	
			0	1 (bits: 4) (offset: 4)	
SNVT_file_req.dest_address.gp.group		unsigned short	255	$1 \times 10^0 \times (Raw+0)$	
		(none)	0	1	
SNVT_file_req.auth_on		unsigned short	1	$1 \times 10^0 \times (Raw+0)$	
		(none)	0	1 boolean	
SNVT_file_req.prio_on		unsigned short	1	$1 \times 10^0 \times (Raw+0)$	
		(none)	0	1 boolean	

4.71 SNVT_file_status

Overview: File status.

Index	Size in Bytes	CNP Data Type			
74	27	structure			
Field			CNP Data Type/ Invalid Value	Maximum/ Minimum	Scaled Value/ Resolution
SNVT_file_status.status			file_status_t	11	none (enumeration)
			-1	-1	1
SNVT_file_status.number_of_files			unsigned long	65 535	$1 \times 10^0 \times (Raw+0)$
			(none)	0	1 count
SNVT_file_status.selected_file			unsigned long	65 535	$1 \times 10^0 \times (Raw+0)$
			(none)	0	1 file index
SNVT_file_status.adr			union		
SNVT_file_status.adr.descriptor			structure		
SNVT_file_status.adr.descriptor.file_info			signed char	127	$1 \times 10^0 \times (Raw+0)$
			(none)	-128	1 array of 16 characters
SNVT_file_status.adr.descriptor.size			s32_type (signed 32-bit type)	2 147 483 647	$1 \times 10^0 \times (Raw+0)$
			(none)	0	1 bytes
SNVT_file_status.adr.descriptor.type			unsigned long	65 535	$1 \times 10^0 \times (Raw+0)$
			(none)	0	1
SNVT_file_status.adr.address			structure		

Index	Size in Bytes	CNP Data Type			
74	27	structure			
Field			CNP Data Type/ Invalid Value	Maximum/ Minimum	Scaled Value/ Resolution
SNVT_file_status.adr.address.domain_id			unsigned short	255	$1 \times 10^0 \times (Raw+0)$
			(none)	0	1 array of 6 bytes
SNVT_file_status.adr.address.domain_length			unsigned short	6	$1 \times 10^0 \times (Raw+0)$
			(none)	0	1
SNVT_file_status.adr.address.subnet			unsigned short	255	$1 \times 10^0 \times (Raw+0)$
			0	0	1 subnet number
SNVT_file_status.adr.address.node			unsigned short	127	$1 \times 10^0 \times (Raw+0)$
			0	0	1 node number

4.72 SNVT_freq_f

Overview: Frequency in Hertz.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaled Value	Invalid
75	4	floating-point	0	3,402 823 466 385 3E + 038	floating	NAN and Out of Range

4.73 SNVT_freq_hz

Overview: Frequency in Hertz.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
76	2	unsigned long	0	65 535	$1 \times 10^{-1} \times (Raw+0)$	0,1 Hz

4.74 SNVT_freq_kilohz

Overview: Frequency in kiloHertz.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
77	2	unsigned long	0	65 535	$1 \times 10^{-1} \times (Raw+0)$	0,1 kHz

4.75 SNVT_freq_milhz

Overview: Frequency in miliHertz.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
78	2	unsigned long	0	65 535	$1 \times 10^{-4} \times (Raw+0)$	0,000 1 Hz

4.76 SNVT_lux

Overview: Illumination in lux.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
79	2	unsigned long	0	65 535	$1 \times 10^0 \times (Raw+0)$	1 lx

4.77 SNVT_lev_percent

Overview: Percentage level in % of full level. Level percent. SNVT_switch should be used instead of SNVT_lev_percent, with the exception of network variables that are used to communicate a percentage value and that require the additional resolution provided by SNVT_lev_percent; or for network variable members of functional profiles that are designed primarily for interfacing with SNVT_lev_percent members of other profiles.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
81	2	signed long	-32 768	32 767	$5 \times 10^{-3} \times (Raw+0)$	0,005 % of full level

4.78 SNVT_multiplier

Overview: Multiplier.

Index	Size in Bytes	CNP Data Type	Minimum	Maximum	Scaling	Resolution
82	2	unsigned long	0	65 535	$5 \times 10^{-4} \times (Raw+0)$	0,000 5 16-bit unsigned value

4.79 SNVT_state

Overview: State vector. Each state is a boolean single bit value. SNVT_state_64 is preferred.

Index	Size in Bytes	CNP Data Type				
83	2	structure				
Field			CNP Data Type/ Invalid Value	Maximum/ Minimum	Scaled Value/ Resolution	
SNVT_state.bit0			bitfield	1	$1 \times 10^0 \times (Raw+0)$	
				0	1 (bits: 1) (offset: 0)	
SNVT_state.bit1			bitfield	1	$1 \times 10^0 \times (Raw+0)$	
				0	1 (bits: 1) (offset: 1)	
SNVT_state.bit2			bitfield	1	$1 \times 10^0 \times (Raw+0)$	
				0	1 (bits: 1) (offset: 2)	
SNVT_state.bit3			bitfield	1	$1 \times 10^0 \times (Raw+0)$	
				0	1 (bits: 1) (offset: 3)	
SNVT_state.bit4			bitfield	1	$1 \times 10^0 \times (Raw+0)$	
				0	1 (bits: 1) (offset: 4)	
SNVT_state.bit5			bitfield	1	$1 \times 10^0 \times (Raw+0)$	
				0	1 (bits: 1) (offset: 5)	
SNVT_state.bit6			bitfield	1	$1 \times 10^0 \times (Raw+0)$	

Index	Size in Bytes	CNP Data Type			
83	2	structure			
Field			CNP Data Type/ Invalid Value	Maximum/ Minimum	Scaled Value/ Resolution
				0	1 (bits: 1) (offset: 6)
SNVT_state.bit7			bitfield	1	$1 \times 10^0 \times (Raw+0)$
				0	1 (bits: 1) (offset: 7)
SNVT_state.bit8			bitfield	1	$1 \times 10^0 \times (Raw+0)$
				0	1 (bits: 1) (offset: 0)
SNVT_state.bit9			bitfield	1	$1 \times 10^0 \times (Raw+0)$
				0	1 (bits: 1) (offset: 1)
SNVT_state.bit10			bitfield	1	$1 \times 10^0 \times (Raw+0)$
				0	1 (bits: 1) (offset: 2)
SNVT_state.bit11			bitfield	1	$1 \times 10^0 \times (Raw+0)$
				0	1 (bits: 1) (offset: 3)
SNVT_state.bit12			bitfield	1	$1 \times 10^0 \times (Raw+0)$
				0	1 (bits: 1) (offset: 4)
SNVT_state.bit13			bitfield	1	$1 \times 10^0 \times (Raw+0)$
				0	1 (bits: 1) (offset: 5)
SNVT_state.bit14			bitfield	1	$1 \times 10^0 \times (Raw+0)$
				0	1 (bits: 1) (offset: 6)
SNVT_state.bit15			bitfield	1	$1 \times 10^0 \times (Raw+0)$
				0	1 (bits: 1) (offset: 7)

4.80 SNVT_time_stamp

Overview: Time stamp.

Index	Size in Bytes	CNP Data Type			
84	7	structure			
Field			CNP Data Type/ Invalid Value	Maximum/ Minimum	Scaled Value/ Resolution
SNVT_time_stamp.year			signed long	3 000	$1 \times 10^0 \times (Raw+0)$
			-1	-1	1 year
SNVT_time_stamp.month			unsigned short	12	$1 \times 10^0 \times (Raw+0)$
			(none)	0	1 month
SNVT_time_stamp.day			unsigned short	31	$1 \times 10^0 \times (Raw+0)$
			(none)	0	1 day
SNVT_time_stamp.hour			unsigned short	23	$1 \times 10^0 \times (Raw+0)$