BS EN 60195:2016

BSI Standards Publication

Method of measurement of current noise generated in fixed resistors

Documents
Document Sharing Hub

Full document details: BS EN 60195:2016

National foreword

This British Standard is the UK implementation of EN 60195:2016. It is identical to IEC 60195:2016. It supersedes BS 4119:1967 which is withdrawn.

The UK participation in its preparation was entrusted to Technical Committee EPL/40X, Capacitors and resistors for electronic equipment.

A list of organizations represented on this committee can be obtained on request to its secretary.

This publication does not purport to include all the necessary provisions of a contract. Users are responsible for its correct application.

© The British Standards Institution 2016.
Published by BSI Standards Limited 2016

ISBN 978 0 580 86205 2
ICS 31.040.10

Compliance with a British Standard cannot confer immunity from legal obligations.

This British Standard was published under the authority of the Standards Policy and Strategy Committee on 31 July 2016.

Amendments/corrigenda issued since publication

Date	Text affected

Documents
Document Sharing Hub

Full document details: BS EN 60195:2016

EUROPEAN STANDARD

NORME EUROPÉENNE

EUROPÄISCHE NORM

EN 60195

July 2016

ICS 31.040.10

English Version

Method of measurement of current noise generated in fixed resistors (IEC 60195:2016)

Méthode pour la mesure du bruit produit en charge par les résistances fixes (IEC 60195:2016)

Messverfahren für das Stromrauschen in Festwiderständen (IEC 60195:2016)

This European Standard was approved by CENELEC on 2016-05-12. CENELEC members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for giving this European Standard the status of a national standard without any alteration.

Up-to-date lists and bibliographical references concerning such national standards may be obtained on application to the CEN-CENELEC Management Centre or to any CENELEC member.

This European Standard exists in three official versions (English, French, German). A version in any other language made by translation under the responsibility of a CENELEC member into its own language and notified to the CEN-CENELEC Management Centre has the same status as the official versions.

CENELEC members are the national electrotechnical committees of Austria, Belgium, Bulgaria, Croatia, Cyprus, the Czech Republic, Denmark, Estonia, Finland, Former Yugoslav Republic of Macedonia, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, the Netherlands, Norway, Poland, Portugal, Romania, Slovakia, Slovenia, Spain, Sweden, Switzerland, Turkey and the United Kingdom.

European Committee for Electrotechnical Standardization
Comité Européen de Normalisation Electrotechnique
Europäisches Komitee für Elektrotechnische Normung

CEN-CENELEC Management Centre: Avenue Marnix 17, B-1000 Brussels

© 2016 CENELEC All rights of exploitation in any form and by any means reserved worldwide for CENELEC Members.

Ref. No. EN 60195:2016 E

Documents Document Sharing Hub

Full document details: BS EN 60195:2016

European foreword

The text of document 40/2431/FDIS, future edition 2 of IEC 60195, prepared by IEC/TC 40 “Capacitors and resistors for electronic equipment" was submitted to the IEC-CENELEC parallel vote and approved by CENELEC as EN 60195:2016.

The following dates are fixed:

• latest date by which the document has to be implemented at national level by publication of an identical national standard or by endorsement	(dop)	2017-02-12
• latest date by which the national standards conflicting with the document have to be withdrawn	(dow)	2019-05-12

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. CENELEC [and/or CEN] shall not be held responsible for identifying any or all such patent rights.

Endorsement notice

The text of the International Standard IEC 60195:2016 was approved by CENELEC as a European Standard without any modification.

In the official version, for Bibliography, the following notes have to be added for the standards indicated:

IEC 60027 (series)	NOTE	Harmonized as EN 60027 (series).

Documents
Document Sharing Hub
Full document details: BS EN 60195:2016

Annex ZA
(normative)
Normative references to international publications with their corresponding European publications

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

NOTE 1 When an International Publication has been modified by common modifications, indicated by (mod), the relevant EN/HD applies.

NOTE 2 Up-to-date information on the latest versions of the European Standards listed in this annex is available here: www.cenelec.eu.

Publication	Year	Title	EN/HD	Year
IEC 60068-1	2013	Environmental testing -- Part 1: General and guidance	EN 60068-1	2014

Documents
Document Sharing Hub
Full document details: BS EN 60195:2016

CONTENTS

FOREWORD 4
1 Scope 6
2 Normative references 6
3 Terms and definitions 6
4 Method of measurement 7
4.1 Noise basics 7
4.1.1 Noise 7
4.1.2 Thermal noise 8
4.1.3 Current noise 8
4.2 Measurement principle 9
4.3 Measurement system 10
4.3.1 Proposal of a suitable measuring system 10
4.3.2 Alternative measuring systems 11
4.4 Measurement system requirements 11
4.4.1 Input circuit 11
4.4.2 Isolation resistor R_M 12
4.4.3 DC voltage source 12
4.4.4 DC electronic voltmeter 12
4.4.5 Calibration resistor R_{Cal} 12
4.4.6 Calibration source 13
4.4.7 Determination of the calibration voltage 13
4.4.8 AC band-pass amplifier 15
4.4.9 AC r.m.s. meter 16
4.4.10 Test fixture 16
4.5 Verification of the measuring system 17
4.5.1 Performance check by measurement of instrument and thermal noise 17
4.5.2 Performance check by comparison of repeated measurements 17
5 Measurement procedure 18
5.1 Ambient conditions 18
5.2 Preparation of specimen 18
5.3 Procedure 18
5.3.1 General 18
5.3.2 Calibration 18
5.3.3 Measurement of system noise S 18
5.3.4 Measurement of total noise T 19
5.4 Precautions 22
6 Evaluation of measurement results 22
6.1 Term for the contribution of system noise 22
6.2 Determination of the current-noise index A_1 24
6.3 Determination of the current-noise voltage ratio CNR_U 25
6.4 Accuracy 26
6.5 Requirements 26
7 Information to be given in the relevant component specification 26
Annex A (informative) Letter symbols and abbreviations 27
A.1 Letter symbols 27

AVA Documents
Document Sharing Hub
Full document details: BS EN 60195:2016

A.2 Abbreviations 27
Annex X (informative) Cross-reference for references to the prior revision of this standard 28
Bibliography 29

Figure 1 – Block schematic of a suitable measuring system 11
Figure 2 – Typical transfer function of the band-pass amplifier 16
Figure 3 – Contribution of system noise, $f(T - S)$ 23

Table 1 – Permissible limits of system noise 17
Table 2 – Recommended operating conditions *(1 of 2)* 20
Table 3 – Numeric values of the contribution of system noise, $f(T - S)$ 24
Table X.1 – Cross reference for references to the 1st edition of this standard 28

Documents
Document Sharing Hub
Full document details: BS EN 60195:2016

INTERNATIONAL ELECTROTECHNICAL COMMISSION

METHOD OF MEASUREMENT OF CURRENT NOISE GENERATED IN FIXED RESISTORS

FOREWORD

1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
6) All users should ensure that they have the latest edition of this publication.
7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 60195 has been prepared by IEC technical committee 40: Capacitors and resistors for electronic equipment.

This second edition cancels and replaces the first edition published in 1965 and constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- harmonization of the allocation of isolation resistors R_M in the recommended operating conditions given in Table 2;
- correction of erroneous numeric values of the contribution of system noise, $f(T - S)$ in Table 3;
- addition of advice on the prescription of requirements in a relevant component specification;
- addition of a set of recommended measuring conditions for specimens with a rated dissipation of less than 100 mW;

AVA Documents
Document Sharing Hub

- complete editorial revision.

The text of this standard is based on the following documents:

FDIS	Report on voting
40/2431/FDIS	40/2458/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC website under "http://webstore.iec.ch" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

Documents
Document Sharing Hub
Full document details: BS EN 60195:2016

METHOD OF MEASUREMENT OF CURRENT NOISE GENERATED IN FIXED RESISTORS

1 Scope

This International Standard specifies a method of measurement and associated test conditions to assess the "noisiness", or magnitude of current noise, generated in fixed resistors of any given type. The method applies to all classes of fixed resistors. The aim is to provide comparable results for the determination of the suitability of resistors for use in electronic circuits having critical noise requirements.

The current noise in resistive materials reflects the granular structure of the resistive material. For some resistor technologies utilizing homogenous layers it is regarded as providing an indication of defects, which are considered as a root cause for abnormal ageing of the component under the influence of temperature and time.

The method described in this International Standard is not a general specification requirement and therefore is applied if prescribed by a relevant component specification, or, if agreed between a customer and a manufacturer.

2 Normative references

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60068-1:2013, *Environmental testing – Part 1: General and guidance*

3 Terms and definitions

For the purposes of this document the following terms and definitions apply.

3.1
current-noise
combination of all random fluctuations of current flow in a resistor which are not attributed to thermal agitation of the charge carriers (thermal noise) and which depend on the applied direct current

3.2
current-noise index
A_1
logarithmic index of the ratio of the open circuit r.m.s. current-noise voltage in a frequency decade, in μV, over the d.c. voltage applied under test, in V, used to express the “noisiness” of an individual resistor

Note 1 to entry: The current-noise index is expressed in dB. The ratio between μV and V is not considered in this index, leading to its value being 120 dB less than the mathematical current-noise index A_1'. This practical index follows the history of prior revisions of this method.

Documents
Document Sharing Hub
Full document details: BS EN 60195:2016

3.3
mathematical current-noise index
A_1'
logarithmic index of the ratio of the open circuit r.m.s. current-noise voltage in a frequency decade over the d.c. voltage applied under test, established in consistent units and their multiples

Note 1 to entry: The mathematical current-noise index is expressed in dB. This index has been introduced for the mathematical derivation of the considered parameters.

3.4
current-noise voltage ratio
CNR_U
ratio of the open circuit r.m.s. current-noise voltage in a frequency decade over the d.c. voltage applied under test, established in μV/V, used to express the "noisiness" of an individual resistor

3.5
flicker noise
pink noise
random fluctuation present in most electronic devices and typically related to internal properties of the respective device, which depends on direct current and has a power spectral density inversely proportional to the frequency

3.6
noise
random fluctuation in an electrical signal having instantaneous amplitude values which, due to their distribution in a random manner, can only be predicted in terms of probability statements

3.7
shot noise
random fluctuation in electric current due to the flowing current consisting of discrete charges, which is independent of temperature and has nearly constant power spectral density throughout the frequency spectrum

3.8
thermal noise
random fluctuation generated by the thermal agitation of the charge carriers (usually the electrons) inside an electrical conductor at equilibrium, which is independent of any applied voltage and has nearly constant power spectral density throughout the frequency spectrum

Note 1 to entry: Thermal noise is also referred to as Johnson noise or as Nyquist noise.

4 Method of measurement

4.1 Noise basics

4.1.1 Noise

Noise appears as a spontaneous fluctuating voltage $e_n(t)$ with instantaneous amplitude values.

Noise voltage is a statistically independent random variable, where for most kinds of noise the frequency distribution of amplitudes follows a Gaussian distribution curve. Therefore noise voltage cannot be predicted except in terms of probability statements.

Usually the characteristic of principal interest is not the instantaneous amplitude value but the "time-averaged" value.

Documents
Document Sharing Hub
Full document details: BS EN 60195:2016