

BS EN 60688:2013

Incorporating corrigendum December 2013



BSI Standards Publication

Electrical measuring transducers for converting A.C. and D.C. electrical quantities to analogue or digital signals

bsi.

...making excellence a habit.
AVA **Documents**
Document Sharing Hub

National foreword

This British Standard is the UK implementation of EN 60688:2013. It is identical to IEC 60688:2012, incorporating corrigendum December 2013. It supersedes BS EN 60688:1992 which is withdrawn.

The UK participation in its preparation was entrusted to Technical Committee PEL/85, Measuring equipment for electrical and electromagnetic quantities.

A list of organizations represented on this committee can be obtained on request to its secretary.

This publication does not purport to include all the necessary provisions of a contract. Users are responsible for its correct application.

© The British Standards Institution 2014.
Published by BSI Standards Limited 2014

ISBN 978 0 580 85439 2

ICS 17.220.20

Compliance with a British Standard cannot confer immunity from legal obligations.

This British Standard was published under the authority of the Standards Policy and Strategy Committee on 28 February 2013.

Amendments/corrigenda issued since publication

Date	Text affected
30 April 2014	Implementation of IEC corrigendum December 2013: F-33 in Table 7 amended

EUROPEAN STANDARD
NORME EUROPÉENNE
EUROPÄISCHE NORM

EN 60688

January 2013

ICS 17.220.20

English version

Electrical measuring transducers for converting A.C. and D.C. electrical quantities to analogue or digital signals (IEC 60688:2012)

Transducteurs électriques de mesure
convertissant les grandeurs électriques
alternatives ou continues en signaux
analogiques ou numériques
(CEI 60688:2012)

Elektrische Messumformer
zur Umwandlung von elektrischen
Wechselstromgrößen
und Gleichstromgrößen in analoge
oder digitale Signale
(IEC 60688:2012)

This European Standard was approved by CENELEC on 2012-11-23. CENELEC members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for giving this European Standard the status of a national standard without any alteration.

Up-to-date lists and bibliographical references concerning such national standards may be obtained on application to the CEN-CENELEC Management Centre or to any CENELEC member.

This European Standard exists in three official versions (English, French, German). A version in any other language made by translation under the responsibility of a CENELEC member into its own language and notified to the CEN-CENELEC Management Centre has the same status as the official versions.

CENELEC members are the national electrotechnical committees of Austria, Belgium, Bulgaria, Croatia, Cyprus, the Czech Republic, Denmark, Estonia, Finland, Former Yugoslav Republic of Macedonia, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, the Netherlands, Norway, Poland, Portugal, Romania, Slovakia, Slovenia, Spain, Sweden, Switzerland, Turkey and the United Kingdom.

CENELEC

European Committee for Electrotechnical Standardization
Comité Européen de Normalisation Electrotechnique
Europäisches Komitee für Elektrotechnische Normung

Management Centre: Avenue Marnix 17, B - 1000 Brussels

© 2013 CENELEC - All rights of exploitation in any form and by any means reserved worldwide for CENELEC members.

Ref. No. EN 60688:2013 E



Documents
Document Sharing Hub

Foreword

The text of document 85/421/FDIS, future edition 3 of IEC 60688, prepared by IEC/TC 85 "Measuring equipment for electrical and electromagnetic quantities" was submitted to the IEC-CENELEC parallel vote and approved by CENELEC as EN 60688:2013.

The following dates are fixed:

- latest date by which the document has to be implemented at national level by publication of an identical national standard or by endorsement (dop) 2013-08-23
- latest date by which the national standards conflicting with the document have to be withdrawn (dow) 2015-11-23

This document supersedes EN 60688:1992 + A1:1999 + A2:2001.

EN 60688:2013 includes the following significant technical changes with respect to EN 60688:1992 + A1:1999 + A2:2001:

- extending the scope to DC quantities;
- extending the scope to harmonics, total harmonic distortion and apparent power;
- adaptation of the requirements for digital transducers;
- updating normative references;
- updating safety requirements with the EN 61010 series;
- updating EMC requirements with EN 61326-1.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. CENELEC [and/or CEN] shall not be held responsible for identifying any or all such patent rights.

This standard covers the Principle Elements of the Safety Objectives for Electrical Equipment Designed for Use within Certain Voltage Limits (LVD - 2006/95/EC).

Endorsement notice

The text of the International Standard IEC 60688:2012 was approved by CENELEC as a European Standard without any modification.

In the official version, for Bibliography, the following notes have to be added for the standards indicated:

IEC 60044-7	NOTE	Harmonised as EN 60044-7.
IEC 60044-8	NOTE	Harmonised as EN 60044-8.
IEC 60051 Series	NOTE	Harmonised as EN 60051 Series (not modified).
IEC 60068-2-30	NOTE	Harmonised as EN 60068-2-30.
IEC 60359	NOTE	Harmonised as EN 60359.
IEC 60770-1	NOTE	Harmonised as EN 60770-1.
IEC 60770-2	NOTE	Harmonised as EN 60770-2.
IEC 60770-3	NOTE	Harmonised as EN 60770-3.

Annex ZA (normative)

Normative references to international publications with their corresponding European publications

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

NOTE When an international publication has been modified by common modifications, indicated by (mod), the relevant EN/HD applies.

<u>Publication</u>	<u>Year</u>	<u>Title</u>	<u>EN/HD</u>	<u>Year</u>
IEC 60051-1	1997	Direct acting indicating analogue electrical measuring instruments and their accessories - Part 1: Definitions and general requirements common to all parts	EN 60051-1	1998
IEC 60068-2-6	-	Environmental testing - Part 2-6: Tests - Test Fc: Vibration (sinusoidal)	EN 60068-2-6	-
IEC 60068-2-27	-	Environmental testing - Part 2-27: Tests - Test Ea and guidance: Shock	EN 60068-2-27	-
IEC 60255-151	-	Measuring relays and protection equipment - Part 151: Functional requirements for over/under current protection	EN 60255-151	-
IEC 61010	Series	Safety requirements for electrical equipment for measurement, control, and laboratory use	EN 61010	Series
IEC 61010-1	-	Safety requirements for electrical equipment for measurement, control and laboratory use - Part 1: General requirements	EN 61010-1	-
IEC 61010-2-030	-	Safety requirements for electrical equipment for measurement, control and laboratory use - Part 2-030: Particular requirements for testing and measuring circuits	EN 61010-2-030	-
IEC 61326	Series	Electrical equipment for measurement, control and laboratory use - EMC requirements	EN 61326	Series
IEC 61326-1	-	Electrical equipment for measurement, control and laboratory use - EMC requirements - Part 1: General requirements	EN 61326-1	-
IEC 61557-12	-	Electrical safety in low voltage distribution systems up to 1 000 V a.c. and 1 500 V d.c. - Equipment for testing, measuring or monitoring of protective measures - Part 12: Performance measuring and monitoring devices (PMD)	EN 61557-12	-
IEC 60417-DB		Graphical symbols for use on equipment	-	-

CONTENTS

INTRODUCTION	6
1 Scope	7
2 Normative references	8
3 Terms and definitions	8
3.1 General terms	8
3.2 Description of transducers according to the measurand	11
3.3 Description of transducers according to their output load	12
3.4 Nominal values	12
3.5 User adjustment	13
3.6 Influence quantities and reference conditions	14
3.7 Errors and variations	14
3.8 Accuracy, accuracy class, class index	14
4 Class index, permissible limits of intrinsic error, auxiliary supply and reference conditions	15
4.1 Transducer general architecture	15
4.2 Class index	15
4.3 Class index for transducer used with sensors	16
4.4 Intrinsic error	16
4.5 Conditions for the determination of intrinsic error	16
4.6 Auxiliary supply	18
4.7 Safety requirements: Clearances and creepage distances	19
5 Requirements	19
5.1 Input values	19
5.2 Analogue output signals	19
5.3 Output transfer function	20
5.4 Digital output signals	23
5.5 Ripple (for analogue outputs)	23
5.6 Response time	23
5.7 Variation due to over-range of the measurand	23
5.8 Limiting value of the output signal	23
5.9 Limiting conditions of operation	23
5.10 Limits of the measuring range	24
5.11 Limiting conditions for storage and transport	24
5.12 Sealing	24
5.13 Stability	24
6 Tests	24
6.1 General	24
6.2 Variations due to auxiliary supply voltage	25
6.3 Variations due to auxiliary supply frequency	26
6.4 Variations due to ambient temperature	27
6.5 Variations due to the frequency of the input quantity(ies)	27
6.6 Variations due to the input voltage	28
6.7 Variations due to the input current	29
6.8 Variations due to power factor	29
6.9 Variation due to output load	30

6.10	Variations due to distortion of the input quantity(ies)	30
6.11	Variation due to magnetic field of external origin	31
6.12	Variation due to unbalanced currents	32
6.13	Variation due to interaction between measuring elements	32
6.14	Variation due to self-heating	33
6.15	Variation due to continuous operation	33
6.16	Variation due to common mode interference	34
6.17	Variation due to series mode interference	34
6.18	Voltage test, insulation tests and other safety requirements	35
6.19	Impulse voltage tests	35
6.20	High frequency disturbance test	36
6.21	Test for temperature rise	36
6.22	Other tests	36
7	Marking and information	36
7.1	Marking on the case	36
7.2	Markings relating to the reference conditions and nominal ranges of use for transducers	37
7.3	Identification of connections and terminals	38
7.4	Information to be given in a separate document	38
	Bibliography	40
	Figure 1 – Transducer architecture	15
	Figure 2 – Transfer function curves	22
	Table 1 – Relationship between the limits of intrinsic error, expressed as a percentage of the fiducial value, and the class index	16
	Table 2 – Pre-conditioning	16
	Table 3 – Reference conditions of the influence quantities and tolerances or testing purposes	17
	Table 4 – Reference conditions relative to the measurand	18
	Table 5 – Usage groups	25
	Table 6 – Examples of marking relating to the reference conditions and nominal range of use for temperature	37
	Table 7 – Symbols for marking transducers	38

INTRODUCTION

New transducers can now be equipped with micro-processors that utilize digital data processing, communication methods and auxiliary sensors. This makes them more complex than conventional analogue transducers and gives them considerable added value.

The class index system of classification used in this standard is based upon the IEC 60051 series: *Direct acting indicating analogue electrical measuring instruments and their accessories*. Under this system, the permitted variations of the output signal due to varying influence quantities – ambient temperature, voltage, frequency, etc., – are implicit in the classification.

For those unfamiliar with the class index system, a word of warning is necessary. If, for example, a transducer is classified as Class 1, it does not mean that the error under practical conditions of use will be within ± 1 % of the actual value of the output or ± 1 % of the full output value. It means that the error should not exceed ± 1 % of the fiducial value under closely specified conditions. If the influence quantities are varied between the limits specified by the nominal ranges of use, a variation of amount comparable with the value of the class index may be incurred for each influence quantity.

The permissible error of a transducer under working conditions is the sum of the permissible intrinsic error and of the permissible variations due to each of the influence quantities. However, the actual error is likely to be much smaller because not all of the influence quantities are likely to be simultaneously at their most unfavourable values and some of the variations may cancel one another. It is important that these facts be taken into consideration when specifying transducers for a particular purpose.

Furthermore, some of the terms used in this standard are different from those used in IEC 60051 due to the fundamental differences between indicating instruments and measuring transducers.

All statements of performance are related to the output which is governed by two basic terms:

- "the nominal value", which may have a positive or a negative sign or both;
- "the span", which is the range of values of the output signal from maximum positive to maximum negative, if appropriate.

ELECTRICAL MEASURING TRANSDUCERS FOR CONVERTING A.C. AND D.C. ELECTRICAL QUANTITIES TO ANALOGUE OR DIGITAL SIGNALS

1 Scope

This International Standard applies to transducers with electrical inputs and outputs for making measurements of a.c. or d.c. electrical quantities. The output signal may be in the form of an analogue direct current, an analogue direct voltage or in digital form. In this case, that part of the transducer utilized for communication purposes will need to be compatible with the external system.

This standard applies to measuring transducers used for converting electrical quantities such as the following:

- current,
- voltage,
- active power,
- reactive power,
- power factor,
- phase angle,
- frequency,
- harmonics or total harmonic distortion,
- apparent power

to an output signal.

This standard is not applicable for:

- instrument transformers that comply with IEC 60044 series;
- transmitters for use in industrial process applications that comply with the IEC 60770 series;
- performance measuring and monitoring devices (PMD) that comply with IEC 61557-12.

Within the measuring range, the output signal is a function of the measurand. An auxiliary supply may be needed.

This standard applies:

- a) if the nominal frequency of the input(s) lies between 0 Hz and 1 500 Hz;
- b) if a measuring transducer is part of a system for the measurement of a non-electrical quantity, this standard may be applied to the electrical measuring transducer, if it otherwise falls within the scope of this standard;
- c) to transducers for use in a variety of applications such as telemetry and process control and in one of a number of defined environments.

This International Standard is intended:

- to specify the terminology and definitions relating to transducers whose main application is in industry;
- to unify the test methods used in evaluating transducer performance;

- to specify accuracy limits and output values for transducers.

2 Normative references

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60051-1:1997, *Direct acting indicating analogue electrical measuring instruments and their accessories – Part 1: Definitions and general requirements common to all parts*

IEC 60068-2-6, *Environmental testing – Part 2-6: Tests – Test Fc: Vibration (sinusoidal)*

IEC 60068-2-27, *Environmental testing – Part 2-27: Tests – Test Ea and guidance: Shock*

IEC 60255-151, *Measuring relays and protection equipment – Part 151: Functional requirements for over/under current protection*

IEC 61010 (all parts), *Safety requirements for electrical equipment for measurement, control and laboratory use*

IEC 61010-1, *Safety requirements for electrical equipment for measurement, control and laboratory use – Part 1: General requirements*

IEC 61010-2-030, *Safety requirements for electrical equipment for measurement, control, and laboratory use – Part 30 Special requirements for testing and measuring circuits*

IEC 61326 (all parts), *Electrical equipment for measurement, control and laboratory use – EMC requirements*

IEC 61326-1, *Electrical equipment for measurement, control and laboratory use – EMC requirements – Part 1: General requirements*

IEC 61557-12, *Electrical safety in low voltage distribution systems up to 1 000 V a.c. and 1 500 V d.c. – Equipment for testing, measuring or monitoring of protective measures – Part 12: Performance measuring and monitoring devices (PMD)*

IEC 60417, *Graphical symbols for use on equipment*

NOTE Please refer to the Bibliography for the list of informative references.

3 Terms and definitions

For the purpose of this document the following terms and definitions apply:

3.1 General terms

3.1.1

electrical measuring transducer **transducer**

device for converting an a.c or d.c.. measurand to a direct current, a direct voltage or a digital signal for measurement purposes

3.1.2

analogue transducer

device for converting an a.c or d.c.. measurand to a direct current, direct voltage for measurement purposes

3.1.3

digital transducer

device for converting an a.c or d.c.. measurand to a digital signal for measurement purposes

3.1.4

auxiliary supply

a.c. or d.c. electrical supply, other than the measurand, which is necessary for the correct operation of the transducer

3.1.5

auxiliary circuit

circuit which is usually energized by the auxiliary supply.

Note 1 to entry: The auxiliary circuit is sometimes energized by one of the input quantities.

3.1.6

transducer with offset zero

transducer that gives a predetermined output signal other than zero when the measurand is zero

3.1.7

transducer with suppressed zero

transducer for which zero output signal corresponds to a measurand greater than zero

3.1.8

total distortion factor

ratio of the r.m.s. value of the total distortion content to the the r.m.s. value of an alternating quantity

Note 1 to entry: The total distortion factor depends on the choice of the fundamental component. If it is not clear from the context which one is used, an indication should be given.

3.1.9

output load

for analogue signals, the total resistance of the circuits and apparatus connected externally across the output terminals of the transducer

3.1.10

ripple content of an analogue output signal

with steady-state input conditions, the ratio of the peak-to-peak value of the fluctuating component of an analogue output signal, expressed in percentage, to the fiducial value

3.1.11

output signal

an analogue or digital representation of the measurand

3.1.12

output power

power at the transducer output terminals

3.1.13

output current

output voltage

for analogue signals, the current (voltage) produced by the transducer which is an analogue function of the measurand

3.1.14

reversible output current

reversible output voltage

for analogue signals, the output current (voltage) that reverses polarity in response to a change of sign or direction of the measurand

3.1.15

measuring element of a transducer

unit or module of a transducer that converts the measurand, or part of the measurand, into a corresponding signal

3.1.16

single element transducer

transducer having one measuring element

3.1.17

multi-element transducer

transducer having two or more measuring elements, the signals from the individual elements being combined to produce an output signal corresponding to the measurand

3.1.18

combined transducer

transducer having two or more measuring circuits for one or more functions

3.1.19

response time

time from the instant of application of a specified change of the measurand until the output signal reaches and remains at its final steady value or within a specified interval centred on this value

3.1.20

compliance voltage

accuracy limiting output voltage

for variable output load transducers having a current output, the value of the voltage appearing across the output terminals up to which the transducer complies with the requirements of this standard

3.1.21

output series mode interference voltage

unwanted alternating voltage appearing in series between the output terminals and the load

3.1.22

output common mode interference voltage

unwanted alternating voltage that exists between each of the output terminals and a reference point

3.1.23

storage conditions

conditions, defined by means of the ranges of the influence quantities, such as temperature or any other special condition, within which the transducer may be stored (non-operating) without damage

3.1.24

stability

ability of a transducer to keep its performance characteristics unchanged during a specified time, all influence quantities remaining within their specified ranges

3.1.22.1

short-term stability

stability over a period of 24 h

3.1.22.2

long-term stability

stability over a period of one year

3.1.23

usage group

group of transducers capable of operating under a specified set of environmental conditions

3.2 Description of transducers according to the measurand

3.2.1

voltage transducer

transducer used for the measurement of a.c. or d.c. voltage

3.2.2

current transducer

transducer used for the measurement of a.c. or d.c. current

3.2.3

apparent power transducer

transducer that is used for the measurement of the apparent power

3.2.4

active power transducer

transducer used for the measurement of active electrical power

3.2.5

reactive power transducer

transducer used for the measurement of reactive electrical power

3.2.6

frequency transducer

transducer used for the measurement of the frequency of an a.c. electrical quantity

3.2.7

phase angle transducer

transducer for the measurement of the phase angle between two a.c. electrical quantities having the same frequency

3.2.8

power factor transducer

transducer used for the measurement of the power factor of an a.c. circuit

3.2.9

harmonics transducer

transducer that is used for the measurement of the harmonics or the total harmonic distortion of an a.c. circuit

3.3 Description of transducers according to their output load

3.3.1

fixed output load transducer

transducer that complies with this standard only when the output load is at its nominal value, within specified limits

3.3.2

variable output load transducer

transducer that complies with this standard when the output load has any value within a given range

3.4 Nominal values

3.4.1

nominal value

value, or one of the values, indicating the intended use of a transducer

Note 1 to entry: The lower and upper nominal values of the measurand are those which correspond to the lower and upper nominal values of the output signal.

3.4.2

output span

span

algebraic difference between the upper and lower nominal values of the output signal

3.4.3

fiducial value

value to which reference is made in order to specify the accuracy of a transducer

Note 1 to entry: The fiducial value is the span, except for transducers having a reversible and symmetrical output signal when the fiducial value may be half the span if specified by the manufacturer.

3.4.4

circuit insulation voltage

highest circuit voltage to earth of a transducer that determines its voltage test

3.4.5

nominal power factor

factor by which it is necessary to multiply the product of the nominal voltage and nominal current to obtain the nominal power

$$\text{Nominal power factor} = \frac{\text{nominal power}}{\text{nominal voltage} \times \text{nominal current}}$$

Note 1 to entry: When the current and voltage are sinusoidal quantities, the nominal power factor is $\cos \varphi$ where φ is the phase difference between the current and the voltage. For reactive power transducers, the nominal power factor is $\sin \varphi$.

3.4.6

maximum permissible values of input current and voltage

values of current and voltage assigned by the manufacturer as those which the transducer will withstand indefinitely without damage

3.4.7

limiting value of the output current signal

limiting value of the output voltage signal

upper limit of output (current or voltage) signal which cannot, by design, be exceeded under any conditions