

BS EN 61810-2:2011



BSI Standards Publication

Electromechanical elementary relays

Part 2: Reliability

bsi.

...making excellence a habit.
AVA Documents™
Document Sharing Hub

National foreword

This British Standard is the UK implementation of EN 61810-2:2011. It is identical to IEC 61810-2:2011. It supersedes BS EN 61810-2:2005 which is withdrawn.

The UK participation in its preparation was entrusted to Technical Committee EPL/94, General purpose relays and reed contact units.

A list of organizations represented on this committee can be obtained on request to its secretary.

This publication does not purport to include all the necessary provisions of a contract. Users are responsible for its correct application.

© BSI 2011

ISBN 978 0 580 61894 9

ICS 29.120.70

Compliance with a British Standard cannot confer immunity from legal obligations.

This British Standard was published under the authority of the Standards Policy and Strategy Committee on 30 June 2011.

Amendments issued since publication

Amd. No.	Date	Text affected
----------	------	---------------

EUROPEAN STANDARD
NORME EUROPÉENNE
EUROPÄISCHE NORM

EN 61810-2

April 2011

ICS 29.120.70

Supersedes EN 61810-2:2005

English version

Electromechanical elementary relays - Part 2: Reliability (IEC 61810-2:2011)

Relais électromécaniques élémentaires -
Partie 2: Fiabilité
(CEI 61810-2:2011)

Elektromechanische Elementarrelais -
Teil 2: Funktionsfähigkeit (Zuverlässigkeit)
(IEC 61810-2:2011)

This European Standard was approved by CENELEC on 2011-04-01. CENELEC members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for giving this European Standard the status of a national standard without any alteration.

Up-to-date lists and bibliographical references concerning such national standards may be obtained on application to the Central Secretariat or to any CENELEC member.

This European Standard exists in three official versions (English, French, German). A version in any other language made by translation under the responsibility of a CENELEC member into its own language and notified to the Central Secretariat has the same status as the official versions.

CENELEC members are the national electrotechnical committees of Austria, Belgium, Bulgaria, Croatia, Cyprus, the Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, the Netherlands, Norway, Poland, Portugal, Romania, Slovakia, Slovenia, Spain, Sweden, Switzerland and the United Kingdom.

CENELEC

European Committee for Electrotechnical Standardization
Comité Européen de Normalisation Electrotechnique
Europäisches Komitee für Elektrotechnische Normung

Management Centre: Avenue Marnix 17, B - 1000 Brussels

© 2011 CENELEC - All rights of exploitation in any form and by any means reserved worldwide for CENELEC members.

Ref. No. EN 61810-2:2011 E

 **Documents**
Document Sharing Hub

Foreword

The text of document 94/316/FDIS, future edition 2 of IEC 61810-2, prepared by IEC TC 94, All-or-nothing electrical relays, was submitted to the IEC-CENELEC parallel vote and was approved by CENELEC as EN 61810-2 on 2011-04-01.

This European Standard supersedes EN 61810-2:2005.

The main changes with respect to EN 61810-2:2005 are listed below:

- inclusion of both numerical and graphical methods for Weibull evaluation;
- establishment of full coherence with the second edition of the basic reliability standard EN 61649;
- deletion of previous Annex A and Annex D since both annexes are contained in EN 61810-1.

This standard is to be used in conjunction with EN 61649:2008.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. CEN and CENELEC shall not be held responsible for identifying any or all such patent rights.

The following dates were fixed:

- | | | |
|--|-------|------------|
| – latest date by which the EN has to be implemented
at national level by publication of an identical
national standard or by endorsement | (dop) | 2012-01-01 |
| – latest date by which the national standards conflicting
with the EN have to be withdrawn | (dow) | 2014-04-01 |

Annex ZA has been added by CENELEC.

Endorsement notice

The text of the International Standard IEC 61810-2:2011 was approved by CENELEC as a European Standard without any modification.

Annex ZA (normative)

Normative references to international publications with their corresponding European publications

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

NOTE When an international publication has been modified by common modifications, indicated by (mod), the relevant EN/HD applies.

<u>Publication</u>	<u>Year</u>	<u>Title</u>	<u>EN/HD</u>	<u>Year</u>
IEC 60050-191	1990	International Electrotechnical Vocabulary (IEV) - Chapter 191: Dependability and quality of service	-	-
IEC 60050-444	2002	International Electrotechnical Vocabulary - Part 444: Elementary relays	-	-
IEC 60300-3-5	2001	Dependability management - Part 3-5: Application guide - Reliability test conditions and statistical test principles	-	-
IEC 61649	2008	Weibull analysis	EN 61649	2008
IEC 61810-1	2008	Electromechanical elementary relays - Part 1: General requirements	EN 61810-1	2008

CONTENTS

INTRODUCTION	5
1 Scope	6
2 Normative references	6
3 Terms and definitions	7
4 General considerations	9
5 Test conditions	10
5.1 Test items	10
5.2 Environmental conditions	10
5.3 Operating conditions	10
5.4 Test equipment	11
6 Failure criteria	11
7 Output data	11
8 Analysis of output data	11
9 Presentation of reliability measures	12
Annex A (normative) Data analysis	13
Annex B (informative) Example of numerical and graphical Weibull analysis	22
Annex C (informative) Example of cumulative hazard plot	26
Annex D (informative) Gamma function	32
Bibliography	33
Figure A.1 – An example of Weibull probability paper	16
Figure A.2 – An example of cumulative hazard plotting paper	18
Figure A.3 – Plotting of data points and drawing of a straight line	18
Figure A.4 – Estimation of distribution parameters	19
Figure B.1 – Weibull probability chart for the example	24
Figure C.1 – Estimation of distribution parameters	28
Figure C.2 – Cumulative hazard plots	30
Table B.1 – Ranked failure data	23
Table C.1 – Work sheet for cumulative hazard analysis	26
Table C.2 – Example work sheet	29
Table D.1 – Values of the gamma function	32

INTRODUCTION

Within the IEC 61810 series of basic standards covering elementary electromechanical relays, IEC 61810-2 is intended to give requirements and tests permitting the assessment of relay reliability. All information concerning endurance tests for type testing have been included in IEC 61810-1.

NOTE According to IEC 61810-1, a specified value for the electrical endurance under specific conditions (e.g. contact load) is verified by testing 3 relays. None is allowed to fail. Within this IEC 61810-2, a prediction of the reliability of a relay is performed using statistical evaluation of the measured cycles to failure of a larger number of relays (generally 10 or more relays).

Recently the technical committee responsible for dependability (TC 56) has developed a new edition of IEC 61649 dealing with Weibull distributed test data. This second edition contains both numerical and graphical methods for the evaluation of Weibull-distributed data.

On the basis of this basic reliability standard, IEC 61810-2 was developed. It comprises test conditions and an evaluation method to obtain relevant reliability measures for electromechanical elementary relays. The life of relays as non-repairable items is primarily determined by the number of operations. For this reason, the reliability is expressed in terms of mean cycles to failure (MCTF).

Commonly, equipment reliability is calculated from mean time to failure (MTTF) figures. With the knowledge of the frequency of operation (cycling rate) of the relay within an equipment, it is possible to calculate an effective MTTF value for the relay in that application.

Such calculated MTTF values for relays can be used to calculate respective reliability, probability of failure, and availability (e.g. MTBF (mean time between failures)) values for equipment into which these relays are incorporated.

Generally it is not appropriate to state that a specific MCTF value is “high” or “low”. The MCTF figures are used to make comparative evaluations between relays with different styles of design or construction, and as an indication of product reliability under specific conditions.

ELECTROMECHANICAL ELEMENTARY RELAYS –

Part 2: Reliability

1 Scope

This part of IEC 61810 covers test conditions and provisions for the evaluation of endurance tests using appropriate statistical methods to obtain reliability characteristics for relays. It should be used in conjunction with IEC 61649.

This International Standard applies to electromechanical elementary relays considered as non-repaired items (i.e. items which are not repaired after failure), whenever a random sample of items is subjected to a test of cycles to failure (CTF).

The lifetime of a relay is usually expressed in number of cycles. Therefore, whenever the terms “time” or “duration” are used in IEC 61649, this term should be understood to mean “cycles”. However, with a given frequency of operation, the number of cycles can be transformed into respective times (e.g. times to failure (TTF)).

The failure criteria and the resulting characteristics of elementary relays describing their reliability in normal use are specified in this standard. A relay failure occurs when the specified failure criteria are met.

As the failure rate for elementary relays cannot be considered as constant, particularly due to wear-out mechanisms, the times to failure of tested items typically show a Weibull distribution. This standard provides both numerical and graphical methods to calculate approximate values for the two-parameter Weibull distribution, as well as lower confidence limits.

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60050-191:1990, *International Electrotechnical Vocabulary (IEV) – Chapter 191: Dependability and quality of service*

IEC 60050-444:2002, *International Electrotechnical Vocabulary (IEV) – Part 444: Elementary relays*

IEC 60300-3-5:2001, *Dependability management – Part 3-5: Application guide – Reliability test conditions and statistical test principles*

IEC 61649:2008, *Weibull analysis*

IEC 61810-1:2008, *Electromechanical elementary relays – Part 1: General requirements*

3 Terms and definitions

For the purposes of this document, the terms and definitions given in IEC 60050-191 and IEC 60050-444, some of which are reproduced below, as well as the following, apply.

3.1

item

any component that can be individually considered

[IEC 60050-191:1990, 191-01-01, modified]

NOTE For the purpose of this standard, items are elementary relays.

3.2

non-repaired item

item which is not repaired after a failure

[IEC 60050-191:1990, 191-01-03, modified]

3.3

cycle

operation and subsequent release/reset

[IEC 60050-444:2002, 444-02-11]

3.4

frequency of operation

number of cycles per unit of time

[IEC 60050-444:2002, 444-02-12]

3.5

reliability

ability of an item to perform a required function under given conditions for a given number of cycles or time interval

[IEC 60050-191:1990, 191-02-06, modified]

NOTE 1 It is generally assumed that the item is in a state to perform this required function at the beginning of the time interval.

NOTE 2 The term “reliability” is also used as a measure of reliability performance (see IEC 60050-191:1990, 191-12-01).

3.6

reliability test

experiment carried out in order to measure, quantify or classify a reliability measure or property of an item

[IEC 60300-3-5:2001, 3.1.27]

3.7

life test

test with the purpose of estimating, verifying or comparing the lifetime of the class of items being tested

[IEC 60300-3-5:2001, 3.1.17, modified]

3.8
cycles to failure
CTF

total number of cycles of an item, from the instant it is first put in an operating state until failure

3.9
mean cycles to failure
MCTF

expectation of the number of cycles to failure

3.10
time to failure
TTF

total time duration of operating time of an item, from the instant it is first put in an operating state until failure

[IEC 60050-191:1990, 191-10-02, modified]

3.11
mean time to failure
MTTF

expectation of the time to failure

[IEC 60050-191:1990, 191-12-07]

3.12
useful life

number of cycles or time duration until a certain percentage of items have failed

NOTE In this standard, this percentage is defined as 10 %.

3.13
failure

termination of the ability of an item to perform a required function

[IEC 60050-191:1990, 191-04-01, modified]

3.14
malfunction

single event when an item does not perform a required function

3.15
contact failure

occurrence of break and/or make malfunctions of a contact under test, exceeding a specified number

3.16
failure criteria

set of rules used to decide whether an observed event constitutes a failure

[IEC 60300-3-5:2001, 3.1.10]

3.17
contact load category

classification of relay contacts dependent on wear-out mechanisms

NOTE Various contact load categories are defined in IEC 61810-1.

4 General considerations

The provisions of this part of IEC 61810 are based on the relevant publications on dependability. In particular, the following documents have been taken into account: IEC 60050-191, IEC 60300-3-5 and IEC 61649.

The aim of reliability testing as given in this standard is to obtain objective and reproducible data on reliability performance of elementary relays representative of standard production quality. The tests described and the related statistical tools to gain reliability measures based on the test results can be used for the estimation of such reliability measures, as well as for the verification of stated measures.

NOTE 1 Examples for the application of reliability measurements are:

- establishment of reliability measures for a new relay type;
- comparison of relays with similar characteristics, but produced by different manufacturers;
- evaluation of the influence, on a relay, of different materials or different manufacturing solutions;
- comparison of a new relay with a relay which has already worked for a specific period of time;
- calculation of the reliability of an equipment or system incorporating one or more relays.

According to Clauses 8 and 9 of IEC 60300-3-5, for non-repaired items showing a non-constant failure rate the Weibull model is the most appropriate statistical tool for evaluation of reliability measures. This analysis procedure is described in IEC 61649.

Elementary relays within the scope of this standard are considered as non-repaired items. They generally do not exhibit a constant failure rate but a failure rate increasing with time, being tested until wear-out mechanisms become predominant. The cycles to failure of a random sample of tested items typically show the Weibull distribution.

NOTE 2 In cases where no wear-out mechanisms prevail, random failures with constant failure rate can be assumed. Then the shape parameter β of the Weibull distribution equals 1 and the reliability function becomes the well-known exponential law. For relay tests where only very few failures (or even no failures at all) occur, the WeiBayes approach of IEC 61649 might be appropriate. Another option may be the application of the sudden death method described in Clause 13 of IEC 61649.

The statistical procedures of this standard are valid only when at least 10 relevant failures are recorded.

Upon special agreement between manufacturer and user, the test may be performed with even less than 10 relays, provided the uncertainty of the estimated Weibull parameters is acceptable to them. In such a case the minimum number of tested relays shall be specified; this number then replaces the minimum number of 10 relays wherever prescribed in this standard. However, it shall be noted that this reduction of relay specimens is only acceptable where the graphical methods of A.5.1 are applied. For the numerical method of A.5.2 at least 10 failures are required, since the maximum likelihood estimation (MLE) is a computational method for larger sample sizes, i.e. when at least 10 relevant failures are recorded (see 9.3 of IEC 61649).

The first step in the analysis of the recorded cycles to failure (CTF) of the tested relays is the determination of the two distribution parameters of the Weibull distribution. In a second step, the mean cycles to failure (MCTF) is calculated as a point estimate. In a third step, the useful life is determined as the lower confidence limit of the number of cycles by which 10 % of the relay population will have failed (B_{10}).

With a given frequency of operation these reliability measures expressed in number of cycles (MCTF) can be transformed into respective times (MTTF), see Annex B for an example.

The statistical procedures require some appropriate computing facility. Software for evaluation of Weibull distributed data is commercially available on the market. Such software

may be used for the purpose of this standard provided it shows equivalent results when the data given in Annex B are used.

Since the number of cycles to failure highly depends on the specific set of test conditions (particularly the electrical loading of the relay contacts), values for MCTF and useful life derived from test data apply only to this set of test conditions, which have to be stated by the manufacturer together with the reliability measures.

5 Test conditions

5.1 Test items

As a minimum of 10 failures need to be recorded to perform the analysis described in this standard, 10 or more items (relays) should be submitted to the test. This allows the test to be truncated when at least 10 relays have failed. When the test is truncated at a specific number of cycles, all relays that have not yet failed may be considered to fail at that number of cycles (worst case assumption). However, at least 70 % of the tested relays shall fail physically. This allows the test to be carried out with 10 relays only, even when the test is truncated before all relays have physically failed (with a minimum of 7 physical failures recorded).

The items shall be selected at random from the same production lot and shall be of identical type and construction. No action is allowed on the test items from the time of sampling until the test starts.

Where any particular burn-in procedure or reliability stress screening is employed by the manufacturer prior to sampling, this shall apply to all production. The manufacturer shall describe and declare such procedures, together with the test results.

Unless otherwise specified by the manufacturer, all contacts of each relay under test shall be loaded as stated and monitored continuously during the test.

The test starts with all items and is stopped at some number of cycles. At that instant a certain number of items (minimum: 10 items) have failed. The number of cycles to failure of each of the failed items is recorded.

Items failed during the test are not replaced once they fail.

5.2 Environmental conditions

The testing environment shall be the same for all items.

- The items shall be mounted in the manner intended for normal service; in particular, relays for mounting onto printed circuit-boards are tested in the horizontal position, unless otherwise specified.
- The ambient temperature shall be as specified by the manufacturer.
- All other influence quantities shall comply with the values and tolerance ranges given in Table 1 of IEC 61810-1, unless otherwise specified.

5.3 Operating conditions

The set of operating conditions

- rated coil voltage(s);
- coil suppression (if any);
- frequency of operation;
- duty factor;