DD IEC/TS 61934:2011

BSI Standards Publication

Electrical insulating materials and systems — Electrical measurement of partial discharges (PD) under short rise time and repetitive voltage impulses

NO COPYING WITHOUT BSI PERMISSION EXCEPT AS PERMITTED BY COPYRIGHT LAW

raising standards worldwide™

Full document details: DD IEC/TS 61934:2011

National foreword

This Draft for Development is the UK implementation of IEC/TS 61934:2011. It supersedes DD IEC/TS 61934:2006 which is withdrawn.

The UK participation in its preparation was entrusted to Technical Committee GEL/112, Evaluation and qualification of electrical insulating materials and systems.

A list of organizations represented on this committee can be obtained on request to its secretary.

This publication does not purport to include all the necessary provisions of a contract. Users are responsible for its correct application.

© BSI 2011

ISBN 978 0 580 71782 6

ICS 17.220.99; 29.035.01; 29.080.30

Compliance with a British Standard cannot confer immunity from legal obligations.

This Draft for Development was published under the authority of the Standards Policy and Strategy Committee on 30 June 2011.

Amendments issued since publication

Amd. No.	Date	Text affected

Documents
Document Sharing Hub

Full document details: DD IEC/TS 61934:2011

IEC/TS 61934

Edition 2.0 2011-04

TECHNICAL SPECIFICATION

colour inside

Electrical insulating materials and systems – Electrical measurement of partial discharges (PD) under short rise time and repetitive voltage impulses

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

PRICE CODE U

ICS 17.220.99; 29.035.01; 29.080.30

ISBN 978-2-88912-479-4

® Registered trademark of the International Electrotechnical Commission

Documents
Document Sharing Hub

Full document details: DD IEC/TS 61934:2011

CONTENTS

FOREWORD 4
INTRODUCTION 6
1 Scope 7
2 Normative references 7
3 Terms and definitions 7
4 Measurement of partial discharge pulses during repetitive, short rise-time voltage impulses and comparison with power frequency 9
4.1 Measurement frequency 9
4.2 Measurement quantities 9
4.3 Test objects 10
4.3.1 General 10
4.3.2 Inductive test objects 10
4.3.3 Capacitive test objects 10
4.3.4 Distributed impedance test objects 10
4.4 Impulse generators 10
4.4.1 General 10
4.4.2 Impulse waveforms 11
4.5 Effect of testing conditions 11
4.5.1 General 11
4.5.2 Effect of environmental factors 12
4.5.3 Effect of testing conditions and ageing 12
5 PD detection methods 12
5.1 General 12
5.2 PD pulse coupling and detection devices 12
5.2.1 Introductory remarks 12
5.2.2 Coupling capacitor with multipole filter 13
5.2.3 HFCT with multipole filter 14
5.2.4 Electromagnetic couplers 15
5.2.5 Charge measurements 16
5.3 Source-controlled gating techniques 17
6 Measuring instruments 17
7 Sensitivity check of the PD measuring equipment 17
7.1 General 17
7.2 Test diagram for sensitivity check 18
7.3 PD detection sensitivity check 18
7.4 Background noise check 19
7.5 Detection system noise check 19
7.6 Sensitivity report 19
8 Test procedure for increasing and decreasing the repetitive impulse voltage magnitude 19
9 Test report 20
Annex A (informative) Voltage impulse suppression required by the coupling device 22
Annex B (informative) PD pulses extracted from a supply voltage impulse through filtering techniques 24
Annex C (informative) Result of round-robin tests of RPDIV measurement 26
Annex D (informative) Examples of noise levels of practical PD detectors 28

AVA Documents
Document Sharing Hub
Full document details: DD IEC/TS 61934:2011

Bibliography 29

Figure 1 – Coupling capacitor with multipole filter 13
Figure 2 – Example of voltage impulse and PD pulse frequency spectra before and after filtering 14
Figure 3 – HFCT between supply and test object with multipole filter 14
Figure 4 – HFCT between test object and earth with multipole filter 15
Figure 5 – Circuit using an electromagnetic coupler (for example an antenna) to suppress impulses from the test supply 15
Figure 6 – Circuit using an electromagnetic UHF antenna 15
Figure 7 – Example of waveforms of repetitive bipolar impulse voltage and charge accumulation for a twisted-pair sample 16
Figure 8 – Charge measurements 16
Figure 9 – Example of PD detection using electronic source-controlled gating (other PD coupling devices can be used) 17
Figure 10 – Test diagram for sensitivity check 18
Figure 11 – Example of relation between the outputs of LVPG and PD detector 19
Figure 12 – Example of increasing and decreasing the impulse voltage magnitude 20
Figure A.1 – Example of overlap between voltage impulse and PD pulse spectra (dotted area) 22
Figure A.2 – Example of voltage impulse and PD pulse spectra after filtering 22
Figure A.3 – Example of impulse voltage damping as a function of impulse voltage magnitude and rise time 23
Figure B.1 – Power supply waveform and recorded signal using an antenna during supply voltage commutation 24
Figure B.2 – Signal detected by an antenna from the record of Figure B.1, using a filtering technique (400 MHz high-pass filter) 25
Figure B.3 – Characteristic of the filter used to pass from Figure B.1 to Figure B.2 25
Figure C.1 – The sequence of negative voltage impulses used for RRT 26
Figure C.2 – PD pulses (under) corresponding to voltage impulses (above) 26
Figure C.3 – Dependence of normalized RPDIV on 100 data (NRPIV/100) on relative humidity (A-F indicates the participants of RRT) 27

Table 1 – Example of parameter values of impulse voltage waveform without load 11
Table D.1 – Examples of bandwidths and noise levels for practical PD sensors 28

Documents
Document Sharing Hub
Full document details: DD IEC/TS 61934:2011

INTERNATIONAL ELECTROTECHNICAL COMMISSION

ELECTRICAL INSULATING MATERIALS AND SYSTEMS – ELECTRICAL MEASUREMENT OF PARTIAL DISCHARGES (PD) UNDER SHORT RISE TIME AND REPETITIVE VOLTAGE IMPULSES

FOREWORD

1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
6) All users should ensure that they have the latest edition of this publication.
7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

The main task of IEC technical committees is to prepare International Standards. In exceptional circumstances, a technical committee may propose the publication of a technical specification when

- the required support cannot be obtained for the publication of an International Standard, despite repeated efforts, or
- the subject is still under technical development or where, for any other reason, there is the future but no immediate possibility of an agreement on an International Standard.

Technical specifications are subject to review within three years of publication to decide whether they can be transformed into International Standards.

IEC/TS 61934, which is a technical specification, has been prepared by IEC technical committee 112: Evaluation and qualification of electrical insulating materials and systems.

This second edition cancels and replaces the first edition, published in 2006, and constitutes a technical revision.

Documents
Document Sharing Hub
Full document details: DD IEC/TS 61934:2011

The principal changes with regard to the previous edition concern the addition of

- an Introduction that provides some background information on the progress being made in the field of power electronics;
- impulse generators;
- PD detection methods;
- a new informative Annex C covering practical experience obtained from round-robin testing (RRT);
- example of noise levels, as shown in new informative Annex D.

The text of this technical specification is based on the following documents:

Enquiry draft	Report on voting
112/163/DTS	112/175/RVC

Full information on the voting for the approval of this technical specification can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC web site under "http://webstore.iec.ch" in the data related to the specific publication. At this date, the publication will be

- transformed into an International standard,
- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

Documents
Document Sharing Hub

Full document details: DD IEC/TS 61934:2011

INTRODUCTION

Power electronics has developed along with both control theory and semiconductor technology. Switching is one of the essential features of power electronics control. For higher efficiency and smoother operation, switching times of the latest devices such as insulated-gate bipolar transistor (IGBT) tend to be shorter than microseconds. Such a short rise time may cause transient overvoltage impulses or surges in the systems. When the voltage impulses reach the breakdown strength of an air gap, partial discharge (PD) may occur. In addition, the impulses are repetitive from power electronics modulation such as pulse width modulation (PWM). Since PD may cause degradation of electrical insulation parts in the system, it is one of the most important parameters to be measured.

The first edition of IEC/TS 61934 was issued in April 2006. Because of rapid development in this field, the revision activity for the latest information was approved in TC112 at the Berlin meeting in September 2006. In addition to technical and editorial changes, practical experience obtained through round-robin test (RRT) is also presented in Annex C.

Documents
Document Sharing Hub
Full document details: DD IEC/TS 61934:2011

ELECTRICAL INSULATING MATERIALS AND SYSTEMS – ELECTRICAL MEASUREMENT OF PARTIAL DISCHARGES (PD) UNDER SHORT RISE TIME AND REPETITIVE VOLTAGE IMPULSES

1 Scope

IEC/TS 61934, which is a technical specification, is applicable to the off-line electrical measurement of partial discharges (PD) that occur in electrical insulation systems (EIS) when stressed by repetitive voltage impulses generated from electronic power devices.

Typical applications are EIS belonging to apparatus driven by power electronics, such as motors, inductive reactors and windmill generators.

NOTE 1 Use of this technical specification with specific products may require the application of additional procedures.

NOTE 2 The procedures described in this technical specification are emerging technologies. Experience and caution, as well as certain preconditions, are needed to apply it.

Excluded from the scope of this technical specification are

– methods based on optical or ultrasonic PD detection,
– fields of application for PD measurements when stressed by non-repetitive impulse voltages such as lightning impulse or switching impulses from switchgear.

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60034 (all parts), *Rotating electrical machines*

IEC 60270:2000, *High-voltage test techniques – Partial discharge measurements*

3 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

3.1
repetitive voltage impulses
voltage impulses which are used as test voltage for the evaluation of switching surges from power electronic devices with a carrier or driven frequency

3.2
partial discharge
PD
electric discharge that only partially bridges the insulation between conductors

[IEC 60270:2000, 3.1, modified]

Documents
Document Sharing Hub
Full document details: DD IEC/TS 61934:2011

3.3
partial discharge pulse
current pulse in an object under test that results from a partial discharge occurring within the object under test

NOTE 1 The pulse is measured using suitable detector circuits, which have been introduced into the test circuit for the purpose of the test.

NOTE 2 A detector in accordance with the provisions of this technical specification produces a current or a voltage signal at its output related to the PD pulse at its input.

[IEC 60270:2000, 3.2, modified]

3.4
repetitive partial discharge inception voltage
RPDIV
minimum peak-to-peak impulse voltage at which more than five PD pulses occur on ten voltage impulses of the same polarity

NOTE This is a mean value for the specified test time and a test arrangement where the voltage applied to the test object is gradually increased from a value at which no partial discharges can be detected.

3.5
repetitive partial discharge extinction voltage
RPDEV
maximum peak-to-peak impulse voltage at which less than five PD pulses occur on ten voltage impulses of the same polarity

NOTE This is a mean value for a specified test time and a test arrangement where the voltage applied to the test object gradually decreases from a voltage at which PD have been detected.

3.6
impulse voltage polarity
polarity of the applied impulse voltage with respect to earth

[IEC 62068-1:2003, 3.10]

3.7
unipolar impulse
repetitive voltage impulse, the polarity of which is either positive or negative

[IEC 62068-1:2003, 3.8, modified]

NOTE The magnitude of the oscillation of the opposite polarity has to be less than 20 %.

3.8
bipolar impulse
repetitive voltage impulse, the polarity of which changes

[IEC 62068-1:2003, 3.9, modified]

3.9
impulse voltage repetition rate
inverse of the average time between successive impulses of the same polarity, whether unipolar or bipolar

[IEC 62068-1:2003, 3.11, modified]

3.10
impulse rise time
time for the voltage impulse to go from 0 % to 100 %

NOTE Unless otherwise stated, this is estimated as 1,25 times the time for the voltage to rise from 10 % to 90 %.

Documents
Document Sharing Hub
Full document details: DD IEC/TS 61934:2011

[IEC 62068-1:2003, 3.12, modified]

3.11
impulse decay time
time interval between the instants at which the instantaneous value of an impulse decreases from a specified upper value to a specified lower value

NOTE Unless otherwise specified, the upper and lower values are fixed at 90 % and 10 % of the impulse magnitude.

3.12
impulse width
interval of time between the first and last instants at which the instantaneous value of an impulse reaches a specified fraction of impulse magnitude or a specified threshold

3.13
impulse duty cycle
ratio, for a given time interval, of the impulse width to the total time

3.14
peak partial discharge magnitude
largest magnitude of any quantity related to PD pulses observed in a test object at a specified voltage following a specified conditioning and test

[IEC 60270:2000, 3.4 modified]

NOTE For impulse voltage tests, the peak magnitude of the PD pulse is the largest repeatedly occurring PD magnitude.

4 Measurement of partial discharge pulses during repetitive, short rise-time voltage impulses and comparison with power frequency

4.1 Measurement frequency

IEC 60270 describes the methods employed to measure the electrical pulses associated with PD in test objects excited by DC and alternating voltages up to 400 Hz. The methods used to measure PD pulses when the test object is subjected to supply voltage impulses have to be modified from the standard narrow-band and wide-band frequency methods described in IEC 60270.

To measure the PD during repetitive short rise time voltage impulses, it is necessary to avoid the induced current of the excited impulse voltage. One technique is current or electromagnetic wave measurement at ultra-high frequency, that is, higher than that of the impulse. Ultra-wide band (UWB) detection is often used with a high-pass filter for the suppression of relatively lower frequency components of impulse voltage. In principle, narrow-band measurement in the ultra-high frequency (UHF: 300 MHz to 3 GHz) region is also effective for the suppression of the impulse voltage. The other method is the integration of PD current at a very low frequency compared to that of the impulse voltage.

4.2 Measurement quantities

Measured quantities concern the RPDIV, the RPDEV, the peak partial discharge magnitude and partial discharge pulse repetition rate.

RPDIV and RPDEV may depend on PD measurement sensitivity and measurement circuit noise, so that normalization, as indicated in Clause 7, is needed. Moreover, they depend on the test object and the pulse deformation from the discharge to the measurement point.

Documents
Document Sharing Hub
Full document details: DD IEC/TS 61934:2011