

DIN EN ISO 16484-6

ICS 35.240.67; 91.140.01

Ersatz für
DIN EN ISO 16484-6:2014-09

**Systeme der Gebäudeautomation –
Teil 6: Datenübertragungsprotokoll –
Konformitätsprüfung (ISO 16484-6:2020);
Englische Fassung EN ISO 16484-6:2020, nur auf CD-ROM**

Building automation and control systems (BACS) –
Part 6: Data communication conformance testing (ISO 16484-6:2020);
English version EN ISO 16484-6:2020, only on CD-ROM

Systèmes d'automatisation et de gestion technique du bâtiment –
Partie 6: Essais de conformité de la communication de données (ISO 16484-6:2020);
Version anglaise EN ISO 16484-6:2020, seulement en CD-ROM

Gesamtumfang 736 Seiten

DIN-Normenausschuss Heiz- und Raumluftechnik sowie deren Sicherheit (NHRS)

Nationales Vorwort

Dieses Dokument (EN ISO 16484-6:2020) wurde vom Technischen Komitee ISO/TC 205 „Building environment design“ in Zusammenarbeit mit dem Technischen Komitee CEN/TC 247 „Gebäudeautomation und Gebäudemanagement“ erarbeitet, dessen Sekretariat von SNV (Schweiz) gehalten wird.

Das zuständige deutsche Normungsgremium ist der Arbeitsausschuss NA 041-03-65 AA „Gebäudeautomation: Produkte, Systeme und Kommunikation (SpA CEN/TC 247 und ISO/TC 205/WG 3)“ des DIN-Normenausschusses Heiz- und Raumlufttechnik sowie deren Sicherheit (NHRS).

Dieses Dokument enthält unter Berücksichtigung des Präsidialbeschlusses 1/2004 nur die englische Originalfassung von EN ISO 16484-6:2020.

Aktuelle Informationen zu diesem Dokument können über die Internetseiten von DIN (www.din.de) durch eine Suche nach der Dokumentennummer aufgerufen werden.

Änderungen

Gegenüber DIN EN ISO 16484-6:2014-09 wurden folgende Änderungen vorgenommen:

- a) eine konsolidierte Version der Norm, die die Addenda o, p, q und r nach ANSI/ASHRAE 135.1-2013 und alle bekannten Errata enthält.

Frühere Ausgaben

DIN EN ISO 16484-6: 2006-04, 2009-11, 2014-09

Nationaler Anhang NA (informativ)

Begriffe

Die Benummerung der folgenden Begriffe ist identisch mit der Benummerung in der englischen Fassung.

3 Begriffe

Alle Definitionen nach ANSI/ASHRAE 135-2016 gelten auch für diesen Zusatz.

3.1

lokales Netzwerk

en **local network**

Netzwerk, mit dem ein BACnet-Gerät direkt verbunden ist

3.2

Remote-Netzwerk

en **remote network**

Netzwerk, das von einem BACnet-Gerät nur über einen oder mehrere Router zugänglich ist

3.3

Testdatenbank

en **test database**

Datenbank von BACnet-Funktionalitäten und Objekten, erstellt durch das Auslesen des Inhaltes eines EPICS

3.4 In der Norm verwendete Abkürzungen und Akronyme

BNF	Backus-Naur-Form-Syntax
EPICS	elektronische Konformitätserklärung der Protokoll-Implementierung (en: electronic protocol implementation conformance statement)
IUT	Implementierung im Test
TCSL	Prüfungs- und Konformitätsskriptsprache
TD	Testgerät
TPI	Text-Protokoll-Information

— Leerseite —

English Version

**Building automation and control systems (BACS) - Part 6:
Data communication conformance testing (ISO 16484-
6:2020)**

Systèmes d'automatisation et de gestion technique du
bâtiment - Partie 6: Essais de conformité de la
communication de données (ISO 16484-6:2020)

Systeme der Gebäudeautomation - Teil 6:
Datenübertragungsprotokoll - Konformitätsprüfung
(ISO 16484-6:2020)

This European Standard was approved by CEN on 4 April 2020.

CEN members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for giving this European Standard the status of a national standard without any alteration. Up-to-date lists and bibliographical references concerning such national standards may be obtained on application to the CEN-CENELEC Management Centre or to any CEN member.

This European Standard exists in three official versions (English, French, German). A version in any other language made by translation under the responsibility of a CEN member into its own language and notified to the CEN-CENELEC Management Centre has the same status as the official versions.

CEN members are the national standards bodies of Austria, Belgium, Bulgaria, Croatia, Cyprus, Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, Netherlands, Norway, Poland, Portugal, Republic of North Macedonia, Romania, Serbia, Slovakia, Slovenia, Spain, Sweden, Switzerland, Turkey and United Kingdom.



EUROPEAN COMMITTEE FOR STANDARDIZATION
COMITÉ EUROPÉEN DE NORMALISATION
EUROPÄISCHES KOMITEE FÜR NORMUNG

CEN-CENELEC Management Centre: Rue de la Science 23, B-1040 Brussels

European foreword

This document (EN ISO 16484-6:2020) has been prepared by Technical Committee ISO/TC 205 "Building environment design" in collaboration with Technical Committee CEN/TC 247 "Building Automation, Controls and Building Management" the secretariat of which is held by SNV.

This European Standard shall be given the status of a national standard, either by publication of an identical text or by endorsement, at the latest by October 2020, and conflicting national standards shall be withdrawn at the latest by October 2020.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. CEN shall not be held responsible for identifying any or all such patent rights.

This document supersedes EN ISO 16484-6:2014.

According to the CEN-CENELEC Internal Regulations, the national standards organizations of the following countries are bound to implement this European Standard: Austria, Belgium, Bulgaria, Croatia, Cyprus, Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, Netherlands, Norway, Poland, Portugal, Republic of North Macedonia, Romania, Serbia, Slovakia, Slovenia, Spain, Sweden, Switzerland, Turkey and the United Kingdom.

Endorsement notice

The text of ISO 16484-6:2020 has been approved by CEN as EN ISO 16484-6:2020 without any modification.

Foreword

ISO (the International Organization for Standardization) is a worldwide federation of national standards bodies (ISO member bodies). The work of preparing International Standards is normally carried out through ISO technical committees. Each member body interested in a subject for which a technical committee has been established has the right to be represented on that committee. International organizations, governmental and non-governmental, in liaison with ISO, also take part in the work. ISO collaborates closely with the International Electrotechnical Commission (IEC) on all matters of electrotechnical standardization.

The procedures used to develop this document and those intended for its further maintenance are described in the ISO/IEC Directives, Part 1. In particular, the different approval criteria needed for the different types of ISO documents should be noted. International Standards are drafted in accordance with the editorial rules of the ISO/IEC Directives, Part 2 (see www.iso.org/directives).

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO shall not be held responsible for identifying any or all such patent rights. Details of any patent rights identified during the development of the document will be in the Introduction and/or on the ISO list of patent declarations received (see www.iso.org/patents).

Any trade name used in this document is information given for the convenience of users and does not constitute an endorsement.

For an explanation of the voluntary nature of standards, the meaning of ISO specific terms and expressions related to conformity assessment, as well as information about ISO's adherence to the World Trade Organization (WTO) principles in the Technical Barriers to Trade (TBT) see www.iso.org/iso/foreword.html.

This document was prepared by Technical Committee ISO/TC 205, *Building environmental design*, in collaboration with the European Committee for Standardization (CEN) Technical Committee CEN/TC 247, *Building Automation, Controls and Building Management*, in accordance with the Agreement on technical cooperation between ISO and CEN (Vienna Agreement).

This fourth edition cancels and replaces the third edition (ISO 16484-6:2014), which has been technically revised. See the detailed list of changes in pages 724 to 728.

A list of all parts in the ISO 16484 series can be found on the ISO website.

Any feedback or questions on this document should be directed to the user's national standards body. A complete listing of these bodies can be found at www.iso.org/members.html.

CONTENTS

CLAUSE	PAGE
Foreword.....	iii
1. PURPOSE.....	1
2. SCOPE.....	1
3. DEFINITIONS	1
4. ELECTRONIC PICS FILE FORMAT	1
4.1 Character Encoding.....	1
4.2 Structure of EPICS Files	2
4.3 Character Strings.....	3
4.4 Notational Rules for Parameter Values.....	3
4.5 Sections of the EPICS File.....	4
5. EPICS CONSISTENCY TESTS.....	10
6. CONVENTIONS FOR SPECIFYING BACnet CONFORMANCE TESTS.....	12
6.1 TCSL Components	12
6.2 TCSL Statements	13
6.3 Time Dependencies	18
6.4 BACnet References.....	19
6.5 TD Requirements.....	19
7. OBJECT SUPPORT TESTS	20
7.1 Read Support for Properties in the Test Database.....	20
7.2 Write Support for Properties in the Test Database.....	22
7.3 Object Functionality Tests.....	24
8. APPLICATION SERVICE INITIATION TESTS.....	186
8.1 AcknowledgeAlarm Service Initiation Tests	186
8.2 ConfirmedCOVNotification Service Initiation Tests.....	187
8.3 UnconfirmedCOVNotification Service Initiation Tests	196
8.4 ConfirmedEventNotification Service Initiation Tests	199
8.5 UnconfirmedEventNotification Service Initiation Tests	241
8.6 GetAlarmSummary Service Initiation Tests.....	261
8.7 GetEnrollmentSummary Service Initiation Tests	262
8.8 GetEventInformation Service Initiation Tests.....	263
8.9 LifeSafetyOperation Service Initiation Tests	265
8.10 SubscribeCOV Service Initiation Tests	266
8.11 SubscribeCOVProperty Service Initiation Tests	267
8.12 AtomicReadFile Service Initiation Tests	268
8.13 AtomicWriteFile Service Initiation Tests	268
8.14 AddListElement Service Initiation Tests	269
8.15 RemoveListElement Service Initiation Tests	270
8.16 CreateObject Service Initiation Tests.....	270
8.17 DeleteObject Service Initiation Tests.....	271
8.18 ReadProperty Service Initiation Tests.....	271
8.19 ReadPropertyConditional Service Initiation Tests.....	273
8.20 ReadPropertyMultiple Service Initiation Tests.....	274
8.21 ReadRange Service Initiation Tests	276
8.22 WriteProperty Service Initiation Tests	280
8.23 WritePropertyMultiple Service Initiation Tests.....	282
8.24 DeviceCommunicationControl Service Initiation Tests.....	284
8.25 ConfirmedPrivateTransfer Service Initiation Test.....	286
8.26 UnconfirmedPrivateTransfer Service Initiation Test.....	286

8.27	ReinitializeDevice Service Initiation Tests.....	286
8.28	ConfirmedTextMessage Service Initiation Tests.....	287
8.29	UnconfirmedTextMessage Service Initiation Tests.....	288
8.30	TimeSynchronization Service Initiation Tests.....	289
8.31	UTCTimeSynchronization Service Initiation Tests.....	290
8.32	Who-Has Service Initiation Tests.....	290
8.33	I-Have Service Initiation Tests.....	291
8.34	Who-Is Service Initiation Tests.....	291
8.35	I-Am Service Initiation Tests.....	292
8.36	VT-Open Service Initiation Tests.....	292
8.37	VT-Close Service Initiation Tests.....	293
8.38	VT-Data Service Initiation Tests.....	294
8.39	RequestKey Service Initiation Tests.....	296
8.40	Authenticate Service Initiation Tests.....	297
9.	APPLICATION SERVICE EXECUTION TESTS.....	301
9.1	AcknowledgeAlarm Service Execution Tests.....	301
9.2	ConfirmedCOVNotification Service Execution Tests.....	327
9.3	UnconfirmedCOVNotification Service Execution Tests.....	332
9.4	ConfirmedEventNotification Service Execution Tests.....	334
9.5	UnconfirmedEventNotification Service Execution Tests.....	337
9.6	GetAlarmSummary Service Execution Tests.....	337
9.7	GetEnrollmentSummary Service Execution Tests.....	338
9.8	GetEventInformation Service Execution Tests.....	342
9.9	LifeSafetyOperation Service Execution Test.....	345
9.10	SubscribeCOV Service Execution Tests.....	346
9.11	SubscribeCOVProperty Service Execution Tests.....	354
9.12	AtomicReadFile Service Execution Tests.....	361
9.13	AtomicWriteFile Service Execution Tests.....	368
9.14	AddListElement Service Execution Tests.....	379
9.15	RemoveListElement Service Execution Tests.....	381
9.16	CreateObject Service Execution Tests.....	383
9.17	DeleteObject Service Execution Tests.....	388
9.18	ReadProperty Service Execution Tests.....	389
9.19	ReadPropertyConditional Service Execution Tests.....	391
9.20	ReadPropertyMultiple Service Execution Tests.....	392
9.21	ReadRange Service Execution Tests.....	400
9.22	WriteProperty Service Execution Tests.....	410
9.23	WritePropertyMultiple Service Execution Tests.....	415
9.24	DeviceCommunicationControl Service Execution Test.....	424
9.25	ConfirmedPrivateTransfer Service Execution Tests.....	430
9.26	UnconfirmedPrivateTransfer Service Execution Tests.....	431
9.27	ReinitializeDevice Service Execution Tests.....	431
9.28	ConfirmedTextMessage Service Execution Tests.....	434
9.29	UnconfirmedTextMessage Service Execution Tests.....	435
9.30	TimeSynchronization Service Execution Tests.....	435
9.31	UTCTimeSynchronization Service Execution Tests.....	437
9.32	Who-Has Service Execution Tests.....	437
9.33	Who-Is Service Execution Tests.....	444
9.34	VT-Open Service Execution Tests.....	447
9.35	VT-Close Service Execution Tests.....	449

9.36	VT-Data Service Execution Tests	450
9.37	RequestKey Service Execution Test.....	450
9.38	Authenticate Service Execution Tests.....	452
9.39	General Testing of Service Execution.....	456
10.	NETWORK LAYER PROTOCOL TESTS.....	458
10.1	General Network Layer Tests.....	458
10.2	Router Functionality Tests	459
10.3	Half-Router Functionality Tests	483
10.4	B/IP PAD Tests	490
10.5	Initiating Network Layer Messages	492
10.6	Non-Router Functionality Tests	494
10.7	Route Binding Tests	496
10.8	Virtual Routing Functionality Tests.....	501
11.	LOGICAL LINK LAYER PROTOCOL TESTS.....	520
11.1	UI Command and Response	520
11.2	XID Command and Response.....	520
11.3	TEST Command and Response	521
12.	DATA LINK LAYER PROTOCOLS TESTS	523
12.1	MS/TP State Machine Tests.....	523
12.2	PTP State Machine Tests	587
13.	SPECIAL FUNCTIONALITY TESTS.....	626
13.1	Segmentation	626
13.2	Time Master	635
13.3	Character Sets	640
13.4	Malformed PDUs	640
13.5	Slave Proxy Tests.....	642
13.6	Automatic Network Mapping.....	644
13.7	Automatic Device Mapping.....	645
13.8	Backup and Restore Procedure Tests	645
13.9	Application State Machine Tests	657
13.10	Workstation Scheduling Tests.....	658
14.	BACnet/IP Functionality Tests.....	676
14.1	Non-BBMD B/IP Device	676
14.2	BBMD B/IP Device with a Server Application	678
14.3	Broadcast Distribution Table Operations	682
14.4	Foreign Device Table Operations (Negative Tests).....	686
14.5	BACnet Broadcast Management (No Foreign Device Table, No Applications)	687
14.6	Foreign Device Management	689
14.7	Broadcast Management (BBMD, Foreign Devices, Local Application).....	693
14.8	Registering as a Foreign Device.....	701
14.9	Initiating BVLL Service Requests Conveying an NPDU.....	702
15.	Reporting Test Results	704
ANNEX A – EXAMPLE EPICS (INFORMATIVE).....		705
HISTORY OF REVISIONS.....		722

1. PURPOSE

To define a standard method for verifying that an implementation of the BACnet protocol provides each capability claimed in its Protocol Implementation Conformance Statement (PICS) in conformance with the BACnet standard.

2. SCOPE

This standard provides a comprehensive set of procedures for verifying the correct implementation of each capability claimed on a BACnet PICS including:

- (a) support of each claimed BACnet service, either as an initiator, executor, or both,
- (b) support of each claimed BACnet object-type, including both required properties and each claimed optional property,
- (c) support of the BACnet network layer protocol,
- (d) support of each claimed data link option, and
- (e) support of all claimed special functionality.

3. DEFINITIONS

All definitions from ANSI/ASHRAE Standard 135-2016 also apply to this addendum.

3.1 local network: the network to which a BACnet device is directly connected.

3.2 remote network: a network that is accessible from a BACnet device only by passing through one or more routers.

3.3 test database: a database of BACnet functionality and objects created by reading the contents of an EPICS.

3.4 Abbreviations and Acronyms Used in the Standard

BNF	Backus-Naur Form syntax
EPICS	electronic protocol implementation conformance statement
IUT	implementation under test
TCSL	testing and conformance scripting language
TD	testing device
TPI	text protocol information

4. ELECTRONIC PICS FILE FORMAT

An electronic protocol implementation conformance statement (EPICS) file contains a BACnet protocol implementation conformance statement expressed in a standardized text form. EPICS files are machine and human readable representations of the implementation of BACnet objects and services within a given device. EPICS files shall use the extension ".TPI" (text protocol information) and contain normal editable text lines consisting of text character codes ending in carriage return/linefeed pairs (X'0D', X'0A').

EPICS files are used by software testing tools to conduct and interpret the results of tests defined in this standard. An EPICS file shall accompany any device tested according to the procedures of this standard.

4.1 Character Encoding

BACnet provides for a variety of possible character encodings. The character encodings in BACnet fall into three groups: octet streams, double octet streams and quad octet streams. Octet streams represent characters as single octet values. In some cases, such as Microsoft DBCS and JIS C 6226, certain octet values signal that the second octet which follows should be viewed along with the leading octet as a single value, thus extending the range to greater than 256 possible characters. In contrast, double octet streams view pairs of octets as representing single characters. The ISO 10646 UCS-2 encoding is an example. The first or leading octet of the pair is the most significant part of the value. Quad octet streams, such as ISO 10646 UCS-4, treat tuples of four octets at a time as single characters with the first or leading octet being the most significant.

To accommodate the various encodings that may be used with BACnet device descriptions, EPICS files begin with a header that serves both to identify the file as an EPICS file, and to identify the particular encoding used. The header begins with the string "PICS #" where # is replaced by a numeral representing the character set as shown in Table 4-1.

Table 4-1. Character Set Codes

code	character set
0	ANSI X3.4
1	Microsoft DBCS
2	JIS C 6226
3	ISO 10646 (UCS-4)
4	ISO 10646 (UCS-2)
5	ISO 8859-1

An octet stream format can be recognized by examining the first eight octets of the EPICS file. Using ANSI X3.4 encoding as an example these eight octets will contain: X'50' X'49' X'43' X'53' X'20' X'30' X'0D' X'0A'. This represents the text "PICS 0" followed by carriage return and linefeed.

A double octet stream format can be recognized by examining the first 16 octets of the EPICS file. Using ISO 10646 UCS-2 encoding as an example these 16 octets will contain:

X'00' X'50' X'00' X'49' X'00' X'43' X'00' X'53'
X'00' X'20' X'00' X'34' X'00' X'0D' X'00' X'0A'

This represents the text "PICS 4" followed by carriage return and linefeed.

A quad octet stream format can be recognized by examining the first 32 octets of the EPICS file. Using ISO 10646 UCS-4 as an example these 32 octets will contain:

X'00' X'00' X'00' X'50' X'00' X'00' X'00' X'49'
X'00' X'00' X'00' X'43' X'00' X'00' X'00' X'53'
X'00' X'00' X'00' X'20' X'00' X'00' X'00' X'33'
X'00' X'00' X'00' X'0D' X'00' X'00' X'00' X'0A'

This represents the text "PICS 3" followed by carriage return and linefeed.

4.2 Structure of EPICS Files

EPICS files consist of text lines ending in carriage return/linefeed pairs (X'0D', X'0A') encoded as octet, double octet or quad octet streams as defined in 4.1. In the rest of this standard, the term "character" will be used to mean one symbol encoded as one, two, or four octets based on the character encoding used in the EPICS file header. For example, the character space may be encoded as X'20' or X'0020' or X'00000020'. In this standard all characters will be shown in their single octet form.

The special symbol ¶ is used in this Clause to signify the presence of a carriage return/linefeed pair (X'0D0A'). Except within character strings, the character codes tab (X'09'), space (X'20'), carriage return (X'0D') and linefeed (X'0A') shall be considered to be white space. Any sequence of 1 or more white space characters shall be equivalent to a single white space character. Except within a character string, a sequence of two dashes (X'2D') shall signify the beginning of a comment which shall end with the next carriage return/linefeed pair, i.e., the end of the line upon which the -- appears. Comments shall be considered to be white space, and may thus be inserted freely.

EPICS files shall have, as their first line following the header, the literal text:

BACnet Protocol Implementation Conformance Statement ¶

This text serves as a signature identifying the EPICS file format.

Lines that define the sections of the EPICS (see 4.5) and the particular implementation data for a given device follow the signature line.

The EPICS file ends with a line containing the following literal text:

End of BACnet Protocol Implementation Conformance Statement ↵

4.3 Character Strings

The occurrence of a double quote (X'22'), single quote (X'27') or accent grave (X'60') shall signify character strings. For double quotes, the end of the string shall be signified by the next occurrence of a double quote, or the end of the line. For single quote or accent grave, the end of the string shall be signified by the next occurrence of a single quote (X'27'), or the end of the line. Thus strings which need to include a single quote or accent grave as a literal character in the string shall use the double quote quoting method, while strings which need to include double quote shall use the single quote or accent grave quoting method.

4.4 Notational Rules for Parameter Values

Within each section, parameters may need to be expressed in one of several forms. The following rules govern the format for parameters:

- (a) key words are case insensitive so that X'41' through X'5A' are equivalent to X'61' through X'7A';
- (b) null values are shown by the string "NULL";
- (c) Boolean values are shown by the strings "T" or "TRUE" if the value is true, or "F" or "FALSE" if the value is false;
- (d) integer values are shown as strings of digits, possibly with a leading minus (-): 12345 or -111;
- (e) real values are shown with a decimal point, which may not be the first or last character: 1.23, 0.02, 1.0 but not .02;
- (f) octet strings are shown as pairs of hex digits enclosed in either single quotes (X'2D') or accent graves (X'60'), and preceded by the letter "X": X'001122';
- (g) character strings are represented as one or more characters enclosed in double, single or accent grave quotes as defined in 4.3: 'text' or 'text' or "text";
- (h) bitstrings are shown as a list, enclosed by curly brackets ({} or X'7B' and X'7D'), of true and false values: {T,T,F} or {TRUE, TRUE, FALSE}. When the actual value of a bit does not matter, a question mark is used: {T,T,?};
- (i) enumerated values are represented as named, rather than numeric, values. Enumeration names are case insensitive so that X'41' through X'5A' are equivalent to X'61' through X'7A'. The underscore (X'5F') and dash (X'2D') are considered equivalent in enumeration names. Proprietary values are shown as a named text with no whitespace and ending in a non-negative decimal numeric. Each must start with the word "proprietary": Object_Type, proprietary-object-type-653;
- (j) dates are represented enclosed in parenthesis: (Monday, 24-January-1998). Any "wild card" or unspecified field is shown by an asterisk (X'2A'): (Monday, *-January-1998). The omission of day of week implies that the day is unspecified: (24-January-1998);
- (k) times are represented as hours, minutes, seconds, hundredths in the format hh:mm:ss.xx: 2:05:44.00, 16:54:59.99. Any "wild card" field is shown by an asterisk (X'2A'): 16:54:*.;*;
- (l) object identifiers are shown enclosed by parentheses, with commas separating the object type and the instance number: (analog-input, 56). Proprietary object types replace the object type enumeration with the word "proprietary" followed by the numeric value of the object type: (proprietary 700,1);
- (m) constructed data items are represented enclosed by curly brackets ({} or X'7B' and X'7D'), with elements separated by commas. If an element is itself a constructed value, then that element shall be enclosed in curly brackets.

4.4.1 Complex Parameter Values

Some parameter values, notably property values for constructed or CHOICE types of encoded values, need to use a more complex notation to represent their values. This notation is tied to the ASN.1 encoding for those property values and may appear obscure out of context. These additional rules govern the presentation of those types of parameter values:

- (a) values which are a CHOICE of application-tagged values are represented by the value of the chosen item encoded as described in 4.4;
- (b) values which are a CHOICE of context-tagged values are represented by the context tag number enclosed in square brackets, followed by the representation of the value of the chosen item;
- (c) list values (ASN.1 "SEQUENCE OF") are represented enclosed in parenthesis, with the elements of the list separated by commas. If an element is itself a constructed value, then that element shall be enclosed in curly brackets;

- (d) array values are represented enclosed in curly brackets, with the elements of the array separated by commas. If an element is itself a constructed value, then that element shall be enclosed in curly brackets.

4.4.2 Specifying Limits on Parameter Values

Some properties may have restrictions on the range or resolution of their values. In order to correctly interpret the results of tests in which the value of a property is changed using WriteProperty, WritePropertyMultiple, or AddListElement then read back using ReadProperty or ReadPropertyMultiple, it is necessary to know what these restrictions are. The test database may contain restriction statements that define these constraints. The permissible restrictions and the datatypes they apply to are:

- (a) **minimum** - the minimum value for Unsigned, Integer, Real, or Double datatypes. The earliest date for the Date datatype;
- (b) **maximum** - the maximum value for Unsigned, Integer, Real, or Double datatypes. The latest date for the Date datatype;
- (c) **resolution** - the minimum guaranteed resolution for Real and Double datatypes. The minimum time resolution in seconds for the Time datatype;
- (d) **maximum length string** - the maximum length of a CharacterString or OctetString;
- (e) **maximum length list** - the maximum number of elements guaranteed to fit in a list;
- (f) **maximum length array** - the maximum number of elements in an array;
- (g) **allowed values** - a comma-delimited list of supported enumerations for an Enumerated datatype. A comma-delimited list of object types for properties that reference an external object identifier.

Restriction statements shall be listed within pointed brackets (< and >) following the default value. If there are multiple restrictions within a single set of angle brackets, then the restrictions shall be separated by a semicolon (;). A restriction statement consists of the restriction name followed by a colon (:) followed by the restriction value or, where appropriate, a comma-delimited list of possible values.

Here are some examples of property values with restriction statements as they could appear in the test database.

```
present-value: 13.4 <minimum: 0.0; maximum: 20.0; resolution: 0.1>
description: "this is a description" <maximum length string: 30>
units: milliamperes <allowed values: milliamperes, amperes>
object-property-reference: (analog input, 12) <allowed values: analog input, analog value>
```

The Units property is a special case, because changing the units can change the value of the Present_Value property as well as any restrictions on its value. Therefore, minimum, maximum, and resolution restrictions are only valid for the default value of the Units property.

It is possible to specify default restrictions for most datatypes as described in 4.5.8. Restriction statements in the test database override the default restrictions for the individual property that contains the restriction statement.

4.5 Sections of the EPICS File

Each section of the EPICS file begins with a section name followed by a colon (: or X'3A'). After the colon is a set of one or more parameters delimited by a set of curly braces ({ } or X'7B' X'7D').

The following symbols are used as placeholders to indicate the presence of parameter information:

- (a) the open box symbol inside quotation marks, "□", is used to indicate that a character string parameter shall be present;
- (b) the open box symbol with no quotation marks, □, is used to indicate that a parameter with a datatype other than a character string shall be present;
- (c) a question mark, ?, is used in the test database to indicate that the property is present but the value is unknown because it depends on hardware input or is being changed by an internal algorithm.

An example EPICS file may be found in Annex A.

4.5.1 General Information Sections

These sections provide general information about the BACnet device. The syntax for these sections is shown below.

```
Vendor Name: "□"↵
Product Name: "□"↵
Product Model Number: "□"↵
Product Description: "□"↵
```

4.5.2 Conformance Sections

These sections provide information about the BACnet functionality that the device claims to support.

4.5.2.1 BIBBs Supported

This section indicates which BIBBs are supported. The syntax is shown below. Each BIBB shall be listed, one per line between the curly braces. An empty list indicates that no BIBBs are supported.

```
BIBBs Supported: ↵
{↵
  □↵
}↵
```

The BIBBs may be any of those BIBBs described in Annex K. The format in the EPICS shall be to use the short acronym described in the title for each BIBB. For example: A device which supports 'Data Sharing - ReadProperty - B' should include 'DS-RP-B' in this section.

For example:

```
BIBBS Supported: ↵
{↵
  DS-RP-B↵
  DS-WP-B↵
  DS-RPM-B↵
  DM-DOB-B↵
  DM-DDB-B↵
  DM-DDB-A↵
}↵
```

4.5.3 Application Services Supported

This section indicates which standard application services are supported. The syntax is shown below. Each supported service shall be listed between curly braces one service per line, followed by the words "Initiate" or "Execute" to indicate whether the service can be initiated, executed, or both.

```
BACnet Standard Application Services Supported: ↵
{↵
  □ Initiate↵
  □ Execute↵
  □ Initiate Execute↵
}
```

The standard services may be any of the services listed in the Clause 21 production BACnetServicesSupported.

The format should match the title of each corresponding services section in the standard minus the text 'Service'. For example, if the device supports the AcknowledgeAlarm service, the text 'AcknowledgeAlarm' should be included in this section of the EPICS.

For example:

```
BACnet Standard Application Services Supported: ↵
{↵
  Who-Is                Initiate Execute↵
  I-Am                  Initiate Execute↵
  Who-Has                Execute↵
  I-Have                 Initiate ↵
  ReadProperty           Execute↵
  ReadPropertyMultiple   Execute↵
  WriteProperty          Execute↵
}
```

4.5.4 Object Types Supported

This section indicates which standard object types are supported. The syntax is shown below. Each supported object type shall be listed between curly braces one object type per line, optionally followed by the words "Createable", "Deleteable", or both to indicate that dynamic creation or deletion is supported.

```
Standard Object Types Supported: ↵
{↵
  □↵
  □ Createable↵
  □ Deleteable↵
  □ Createable Deleteable↵
}↵
```

The standard objects may be any of the objects listed in the Clause 21 production, BACnetObjectTypesSupported.

The format should be the title of each corresponding object section in the standard minus the text Object Type. For example, if the device supports the object access door, the text 'Access Door' should be included in this section.

For example:

```
BACnet Standard Application Services Supported: ↵
{↵
  Analog Value Createable Deleteable↵
  Analog Input↵
  Device↵
}
```

4.5.5 Data Link Layer Options

This section indicates which standard data link layer options are supported. The syntax is shown below. Each supported data link layer type shall be listed between the curly braces one per line. MS/TP and Point-To-Point data links shall also specify supported baud rate(s).

```
Data Link Layer Option: ↵
{↵
  ISO 8802-3, 10BASE5↵
  ISO 8802-3, 10BASE2↵
  ISO 8802-3, 10BASET↵
  ISO 8802-3, fiber↵
  ARCNET, coax star↵
  ARCNET, coax bus↵
}
```

```

ARCNET, twisted pair star.
ARCNET, twisted pair bus.
ARCNET, fiber star.
ARCNET, twisted pair, EIA-485, Baud rate(s): .
MS/TP master. Baud rate(s): 9600, .
MS/TP slave. Baud rate(s): 9600, .
Point-To-Point. EIA 232, Baud rate(s): .
Point-To-Point. Modem, Baud rate(s): .
Point-To-Point. Modem, Autobaud range: to .
BACnet/IP, 'DIX' Ethernet.
BACnet/IP, Other.
Other.
}

```

4.5.6 Character Sets

This section indicates which BACnet character sets are supported. The syntax is shown below. Each supported character set shall be listed one per line between the curly braces.

```

Character Sets Supported:
{
ANSI X3.4
IBM/Microsoft DBCS.
JIS C 6226.
ISO 8859-1
ISO 10646 (UCS-4)
ISO 10646 (UCS2)
}

```

4.5.7 Special Functionality

This section indicates which BACnet special functionalities are supported. The syntax is shown below. Each special functionality supported shall be listed one per line between the curly braces. The maximum APDU size and window sizes shall be specified as integers.

```

Special Functionality:
{
Maximum APDU size in octets: .
Segmented Requests Supported, window size: .
Segmented Responses Supported, window size: .
Router.
BACnet/IP BBMD.
}

```

4.5.8 Property Value Restrictions

This section defines default restrictions on the values of writable properties. Restrictions listed for a particular datatype apply to every writable property or component of a writable property of that datatype. The restriction may be overridden for a particular property by adding a new restriction specifically for that property in the test database section of the EPICS. See 4.4.2. Only those datatypes for which default restrictions are being defined should be listed, one datatype per line. An empty list indicates that no default restrictions apply.

```

Default Property Value Restrictions:
{
unsigned-integer:    <minimum: .; maximum: .>
signed-integer:     <minimum: .; maximum: .>
real:               <minimum: .; maximum: .; resolution: .>
}

```

```

double:          <minimum: □; maximum: □; resolution: □>↵
date:            <minimum: □; maximum: □>↵
octet-string:    <maximum length string: □>↵
character-string: <maximum length string: □>↵
list:            <maximum length list: □>↵
variable-length-array: <maximum length array: □>↵
}↵

```

4.5.9 Timers

This section defines timer values that are used to determine when a test has failed because an appropriate response has not been observed by the TD. A Real value in seconds must be provided for each timer. See 6.3.

```

Fail Times: ↵
{↵
  Notification Fail Time: □↵
  Internal Processing Fail Time: □↵
  Minimum ON/OFF Time: □↵
  Schedule Evaluation Fail Time: □↵
  External Command Fail Time: □↵
  Program Object State Change Fail Time: □↵
  Acknowledgement Fail Time: □↵
  Slave Proxy Confirm Interval: □↵
  Unconfirmed Response Fail Time: □↵
}↵

```

4.5.10 Test Database

The last section of the EPICS file defines the contents of the device's test database of objects and their properties. The syntax for this section is described below.

```

List of Objects in Test Device: ↵
{↵
  object1↵
  object2↵
  ...
  objectN↵
}↵

```

Each of the objects is defined by a collection of object property values contained within curly braces. The first property to appear within the curly braces shall always be the Object_Identifier which specifies the tuple of (object type, instance). The second property shall always be Object_Name and the third property shall always be Object_Type with a value matching the object type portion of the object-identifier tuple:

```

{
  object-identifier: (object-type, instance)
  object-name: "□"
  object-type: object-type
  other properties...
}

```

Definitions of nonstandard objects shall contain only the three properties required by the BACnet standard, as shown below:

```

{
  object-identifier: (proprietary □, instance)
  object-name: "□"
  object-type: proprietary □
}

```

Properties in the test database that are writable shall have a "W" following the property value, as shown in the example below:

```
{  
  object-identifier: (analog-value, 6)  
  object-name: "□"  
  object-type: analog-value  
  present-value: 23.4 W  
  other properties...  
}
```

Properties in the test database that are conditionally writable shall have a "C" following the property value, as shown in the example below. It is recommended that the governing mechanism be identified in a comment:

```
{  
  object-identifier: (analog-input, 6)  
  object-name: "□"  
  object-type: analog-input  
  present-value: 12.3 C          -- Writable when Out_Of_Service is TRUE  
  other properties...  
}
```

5. EPICS CONSISTENCY TESTS

These tests are static tests of the EPICS and do not involve interrogating the IUT. There are no Test Configuration or Test Step sections with TCSL in these tests because the tests are static tests of the EPICS and not tests of the IUT itself.

Each implementation shall be tested to ensure consistency among interrelated data elements. These tests shall include:

- (a) All object types required by the specified BIBBs shall be indicated as supported in the Standard Object Types Supported section of the EPICS.
- (b) A minimum of one instance of each object type required by the specified BIBBs shall be included in the test database.
- (c) The Protocol_Object_Types_Supported property of the Device object in the test database shall indicate support for each object type required by the supported BIBBs.
- (d) All application services required by the supported BIBBs shall be indicated as supported in the BACnet Standard Application Services Supported section of the EPICS with Initiate and Execute indicated as required by the supported BIBBs.
- (e) The Protocol_Services_Supported property of the Device object in the test database shall indicate support for each application service for which the supported BIBBs requires support for execution of the service.
- (f) The object types listed in the Standard Object Types Supported section of the EPICS shall have a one-to-one correspondence with object types listed in the Protocol_Object_Types_Supported property of the Device object contained in the test database. An object type is supported if it can be made to exist in the IUT's database.
- (g) For each object type listed in the Standard Object Types Supported there shall be at least one object of that type in the test database. It is permissible for there to be no instance of the File object type if File objects are dynamically creatable and come into existence only temporarily during Backup and Restore.
- (h) There shall be a one-to-one correspondence between the objects listed in the Object_List property of the Device object and the objects included in the test database. The Object_List property and the test database shall both include all proprietary objects. Properties of proprietary objects that are not required by BACnet Clause 23.4.3 need not be included in the test database.
- (i) For each object included in the test database, all required properties for that object as defined in Clause 12 of BACnet shall be present. Standard properties which are not defined for the implemented Protocol_Revision shall not be present. In addition, if any of the properties supported for an object require the conditional presence of other properties, their presence shall be verified.
- (j) For each property that is required to be writable, or conditionally writable, that property shall be marked as writable or conditionally writable, in the EPICS.
- (k) The length of the Protocol_Services_Supported bitstring shall have the number of bits defined for BACnetProtocolServicesSupported for the IUT's declared protocol revision.
- (l) The length of the Protocol_Object_Types_Supported bitstring shall have the number of bits defined for BACnetObjectTypesSupported for the IUT's declared protocol revision.
- (m) For each object included in the test database, any properties that are deprecated or removed shall not appear after the Protocol_Revision in which the property was deprecated or removed.
- (n) If the Protocol_Revision property is present in the Device object and its value is greater than or equal to 14, for each object included in the test database, the Property_List property shall have one entry for each property present, including non-standard properties, but excluding Object_Type, Object_Identifier, Object_Name, and Property_List.

- (o) If the Segmentation_Supported property in the Device object is SEGMENTED_BOTH or SEGMENTED_RECEIVE, then the value of the Max_Segments_Accepted property of the Device object shall be greater than 1.

6. CONVENTIONS FOR SPECIFYING BACnet CONFORMANCE TESTS

In order to shorten and clarify test descriptions a simple Testing and Conformance Scripting Language (TCSL) is used. Following the Backus-Naur Form (BNF) syntax for programming language grammars, the following symbols will be used:

<part>	language component names are enclosed in pointed brackets
::=	is defined as
<a> <c>	implicit concatenation
	pattern selection
()	required component
[]	optional component
()...	one required, may be repeated
[]...	optional, may be repeated
<d>...	component appears once, may be repeated
'?'	symbols are in single quotes
WOW	reserved words are upper case
--	indicates that the remaining characters in this line are a comment

Because TCSL is pseudo language that is not intended to be an implementation language for a TD, the rigorous forms of BNF are relaxed in some places and an English statement or phrase is used in their place.

In the tests defined using TCSL an exchange of messages exactly as prescribed constitutes a passing result unless some additional constraint is explicitly noted.

6.1 TCSL Components

6.1.1 Common Symbols and Characters

The following definitions are used to represent common symbols and characters.

<binary digit> ::=	'0' '1'
<decimal digit> ::=	'0' '1' '2' '3' '4' '5' '6' '7' '8' '9'
<hex digit> ::=	<decimal digit> 'A' 'B' 'C' 'D' 'E' 'F'
<single quote> ::=	(the single quote character)
<double quote> ::=	(the double quote character)
<conditional> ::=	'=' '<' '>' '<=' '>=' '~=' '<>'

The conditional '~=' is approximately equal to. The definition of approximate is dependant on the context of its use.

6.1.2 Integers

The following definitions are used to represent integers. These definitions match the syntax used in the BACnet standard.

<integer> ::=	<binary int> <decimal int> <hex int>
<binary int> ::=	B <single quote> <binary digit>... <single quote>
<decimal int> ::=	['-'] <unsigned> D <single quote> <decimal digit>... <single quote>
<hex int> ::=	X <single quote> <hex digit>... <single quote>
<unsigned> ::=	<decimal digit>...

6.1.3 Text Strings

Text strings representing the value of a property or service parameter may be upper, lower or mixed case and are enclosed in double quotes (").

Examples: Object_Name = "CW_STEMP", Description = "AC1 Supply Temperature".

6.1.4 Enumerations

The value of a property or parameter that is an enumerated type is represented in all UPPER CASE letters without quotation.

Examples: TRUE, FALSE, RELIABLE, UNRELIABLE.

6.1.5 Property Identifiers

Property identifiers are represented by mixed case letters with each component word capitalized and joined with other component words, if present, by an underscore (_).

Examples: Present_Value, Reliability, Object_Identifier, Object_Type, and Vendor_Name.

6.1.6 Service Parameters

The names of service parameters are enclosed in single quotes.

Examples: 'Return Read Access Specifications with Result', 'List of Read Access Results'.

6.1.7 Object Identifiers

The representation of object identifiers is defined as follows:

`<object identifier> ::= '(' <object type> ',' <instance number> ')'`

Where:

<object type> ::= (one of the object types defined in BACnet Clause 12)
<instance number> ::= <unsigned>

Examples: (Analog Input, 1), (Device, 150)

6.2 TCSL Statements

Statements in TCSL fall into two categories, those that control the flow and order of tests and those that tell the TD to send data, receive data, or both.

```

<statement> ::= <simple statement> | <compound statement>
<compound statement> ::= '{' <statement>... '}'

```

A <compound statement> can be used anywhere a <simple statement> can be used.

$$\begin{aligned} \langle \text{simple statement} \rangle ::= & \langle \text{if statement} \rangle \mid \langle \text{repeat statement} \rangle \mid \langle \text{error statement} \rangle \\ & \mid \langle \text{check statement} \rangle \mid \langle \text{make statement} \rangle \\ & \mid \langle \text{transmit statement} \rangle \mid \langle \text{receive statement} \rangle \\ & \mid \langle \text{write statement} \rangle \mid \langle \text{verify statement} \rangle \mid \langle \text{before statement} \rangle \\ & \mid \langle \text{read statement} \rangle \end{aligned}$$

6.2.1 IF Statement

The IF statement is used to test for a condition and take an alternate flow of control based on the result of the test.

$$\langle \text{if statement} \rangle ::= \text{IF '}' \langle \text{condition} \rangle \text{'}' THEN } \langle \text{statement} \rangle \text{ [ELSE } \langle \text{statement} \rangle \text{]}$$

The <condition> is a simple English phrase describing a decision the TD must make. If the <condition> is true, the statement after the THEN keyword will execute. If the <condition> is false and the ELSE clause has been specified, the statement following the ELSE will execute. For example:

```
IF (it is raining outside) THEN
    VERIFY Present_Value = 1
ELSE
    VERIFY Present_Value = 2
```

6.2.2 REPEAT Statement

The REPEAT statement is used to iterate through a list of similar objects or values.

`<repeat statement> ::= REPEAT <var> '=' '(' <list description> ')' DO <statement>`

The <var> is some unique identifier that will take on each of the values in the <list description>. By convention it is usually the letter 'X', 'Y', or 'Z' and is specified as an uppercase character. The <list description> is a simple English phrase that describes the elements to iterate through. For example:

```
REPEAT X = (values specified by 6.3 appropriate to the object type) DO {
    WRITE Present_Value = X
    VERIFY Present_Value = X
}
```

6.2.3 ERROR Statement

Some TCSL steps may result in an error condition that is made visible by the ERROR statement.

`<error statement> ::= ERROR [ <explanation string> ]`

The optional <explanation string> is a text string provided to the operator of the TD for diagnostic purposes. For example:

```
ERROR "Retry count exceeded"
```

6.2.4 CHECK Statement

The CHECK statement is used when the operator must verify that some action by the TD has resulted in a change to the IUT that is not network visible.

`<check statement> ::= CHECK '(' <condition> ')'`

The operator is given an opportunity to notify the TD that an operation was or was not successful, the <condition> is a simple English phrase that describes what to check. If the operation was not successful, the test will fail. For example:

```
CHECK (Did the IUT reboot?)
```

6.2.5 MAKE Statement

The MAKE statement is used when the operator must perform some action to create a change in the IUT.

`<make statement> ::= MAKE '(' <action> ')'`

Where <action> is a text string describing the action that is to take place. For example:

```
MAKE (Out_Of_Service TRUE)
```

6.2.6 TRANSMIT Statement

The TRANSMIT statement is used to transmit a packet.

`<transmit statement> ::= TRANSMIT <packet desc>`

Where:

`<packet desc> ::= [ <port> ',' ] [ <addressing> ',' ] ( <service specification> | <pdu specification> | <string> )`

`<port> ::= PORT <port identifier>`

`<port identifier> ::= 'A' | 'B' ... 'Z'`

`<addressing> ::= ( <dst> | <src> | <dst> ',' <src> )`

<src> ::=	(SOURCE '=' <src parm value>) <src parm list>
<src parm value> ::=	TD IUT <device>
<src parm list> ::=	(any src addr parameter name) '=' (<src parm value> <addr parm value>) [',' <src parm list>]
<dst> ::=	(DESTINATION '=' <dst parm value>) <dst parm list>
<dst parm value> ::=	LOCAL BROADCAST GLOBAL BROADCAST REMOTE BROADCAST <net> IUT TD <device>
<dst parm list> ::=	(any dst addr parameter name) '=' (<dst parm value> <addr parm value>) [',' <dst parm list>]
<addr parm value> ::=	(any media specific address description)
<device> ::=	'(device ' (device instance) ')' (a valid device description or variable)
<net> ::=	(a valid BACnet network number, description or variable)
<service specification> ::=	<BACnet service> [',' <pdu parm list>] [',' <service parm list>]
<BACnet service> ::=	(any BACnet service choice)
<service parm list> ::=	<service parameter> '=' <parameter value> [',' <service parm list>]
<service parameter> ::=	(parameter name specific to the BACnet service)
<pdu specification> ::=	<pdu type> [',' <pdu parm list>]
<pdu type> ::=	(any BACnet application, network, link, or MAC layer PDU type)
<pdu parm list> ::=	<pdu parameter> '=' <parameter value> [',' <pdu parm list>]
<pdu parameter> ::=	(any BACnet application, network, data link, or MAC layer PDU parameter)
<parameter value> ::=	(<atomic value> <parameter value list> <parameter cond value>)
<parameter value list> ::=	'(' <parameter value> [' ' <parameter value>]... ')'
<parameter cond value> ::=	'(' IF <condition> THEN <parameter value> ELSE <parameter value> ')'
<string> ::=	<"> <ASCII Char> <">
<ASCII Char> ::=	(ANSI X3.4 character)

The SOURCE and DESTINATION parameters are used to briefly specify common combinations of NPDU, LPDU and MPDU parameter values. If no source addressing information is provided, then the source address shall be TD. If no destination addressing information is provided, then the destination address shall be IUT.

A list of <pdu parameter> = <parameter value> pairs indicate that the specified parameters shall convey the indicated values. The parameter values may be specified in any order.

A list of <service parameter> = <parameter value> pairs indicate that the specified parameters shall convey the indicated values. The parameter values may be specified in any order.

Example 1:

TRANSMIT DESTINATION = GLOBAL BROADCAST, Who-Is

In this simple case, the Who-Is service does not have any mandatory parameters and the <pdu type> is known to be a BACnet-Unconfirmed-Request-PDU by definition. The DESTINATION implies parameter values in the NPDU, LPDU and MPDU layers. The following statement is identical, but more completely specified:

TRANSMIT
DA = LOCAL BROADCAST,
SA = TD,
DNET = GLOBAL BROADCAST,
BACnet-Unconfirmed-Request-PDU,

'Service Choice' = Who-Is

Example 2:

```
TRANSMIT ReadProperty-Request,
  'Object Identifier' = (Analog Input,1),
  'Property Identifier' = Present_Value
```

In this case a ReadProperty service request will be sent from the TD to the IUT with the specified service parameter values.

6.2.7 RECEIVE Statement

The RECEIVE procedure is used to define a message from the IUT.

<receive statement> ::= RECEIVE (<packet desc> | '(' <packet desc> ')' ['(' <packet desc> ')'] ...)

The <pdu specification> parameter is the same as used in the TRANSMIT statement. If unspecified the source addressing information defaults to IUT and destination addressing information defaults to TD. Note: When the destination addressing information refers to a device on a remote network, DA is allowed to be a local MAC broadcast.

Example: TRANSMIT SubscribeCOV-Request,

```
'Subscriber Process Identifier' = any value selected by the TD,
'Monitored Object Identifier' = any object supporting COV notification,
'Issue Confirmed Notifications' = TRUE,
'Lifetime' = 300
```

RECEIVE ConfirmedCOVNotification-Request,

```
'Subscriber Process Identifier' = the value from the previous subscription,
'Monitored Object' = the value from the previous subscription,
'Initiating Device Identifier' = IUT,
'Lifetime' = 300,
'List of Values' = values appropriate to the object type of the
                    monitored object
```

6.2.8 WAIT Statement

The WAIT statement is used to pause the execution of the TD for some specified amount of time.

<wait statement> ::= WAIT <timer value>

Test Steps: The TD shall pause the amount of time specified by the <timer value> before proceeding to the next test step. The <timer value> shall be one of the timers specified in 6.3 of this standard, in ANSI/ASHRAE 135-2008, or as otherwise specified.

Example: WAIT **Internal Processing Fail Time**

6.2.9 WRITE Statement

The WRITE statement is used to modify the value of a specific property of an object.

<write statement> ::= WRITE [<object identifier> ','] <property identifier> '=' <property value>
 [',' ARRAY INDEX '=' <index value>]
 [',' PRIORITY '=' <write priority>]

This is a shortcut of the following statements:

1. TRANSMIT WriteProperty-Request,
 'Object Identifier' = <object identifier>,
 'Property Identifier' = <property identifier>,
 'Property Value' = <property value>,

'Priority Array Index' = <array index>,
'Priority' = <write priority>

2. RECEIVE BACnet-SimpleACK-PDU

Note: In some tests <object identifier> is omitted from the description because it is clear from the context what object type should be written to and any instance of that object type would be acceptable. In cases where there may be some ambiguity this parameter will be explicitly specified.

If <index value> or <write priority> are omitted then the corresponding service parameter shall be omitted in the WriteProperty service request.

Example: WRITE (Analog Output, 1), Present_Value = 6.5, PRIORITY = 8

6.2.10 VERIFY Statement

<verify statement> ::= VERIFY [<object identifier> ','] <property identifier> <conditional> <property value>
[',' ARRAY INDEX '=' <array index>]

The verify procedure consists of the following steps:

1. WAIT Internal Processing Fail Time

2. TRANSMIT ReadProperty-Request,

'Object Identifier' = <object identifier>,
'Property Identifier' = <property identifier>,
'Property Array Index' = <array index>

3. RECEIVE BACnet-ComplexACK-PDU,

'Object Identifier' = <object identifier>,
'Property Identifier' = <property identifier>,
'Property Array Index' = <array index>,
'Property Value' = (any valid value x, where x <conditional> <property value> is TRUE subject to the resolution constraints of 4.4.2)

Example: WRITE (Analog Output, 1), Present_Value = 6.5, PRIORITY = 8

VERIFY (Analog Output, 1), Present_Value = 6.5

6.2.11 BEFORE Statement

The BEFORE statement is used to test for the occurrence of an expected action before a timer expires.

<before statement> ::= BEFORE <timer> <statement>

The <timer value> shall be one of the timers specified in 6.3 of this standard, in ANSI/ASHRAE 135-2008, or as otherwise specified. If the action indicated by <statement> has not yet occurred when the timer expires the test fails. Otherwise this test step passes and the test continues. For example:

Example: BEFORE **Acknowledgment Fail Time** RECEIVE BACnet-SimpleACK-PDU

6.2.12 WHILE Statement

The WHILE statement is used to repeatedly perform a step or series of steps until some condition becomes FALSE.

<while statement> ::= WHILE '(' <condition> ')' DO <statement>

Example:

```
WHILE (IUT not initialized) DO {
    TRANSMIT Poll For Master
}
```

6.2.13 READ Statement

`<read statement> ::= READ <variable> '=' [<object identifier> ','] <property identifier>
[',' ARRAY INDEX '=' <array index>]`

The read procedure consists of the following steps:

1. WAIT **Internal Processing Fail Time**
2. TRANSMIT ReadProperty-Request,
 - 'Object Identifier' = <object identifier> ,
 - 'Property Identifier' = <property identifier> ,
 - 'Property Array Index' = <array index>
3. RECEIVE BACnet-ComplexACK-PDU,
 - 'Object Identifier' = <object identifier> ,
 - 'Property Identifier' = <property identifier> ,
 - 'Property Array Index' = <array index> ,
 - 'Property Value' = (any valid value, <variable>)

Example: READ X = Priority_Array, ARRAY INDEX=10

6.3 Time Dependencies

The BACnet standard does not define how long it should take for actions that result from service requests to become network visible. These time delays can reasonably be expected to vary from implementation to implementation. In a testing environment it is necessary to place a bound on these times in order to decide if a test has passed or failed. The timers defined in this clause are used for this purpose. The vendor shall provide the actual value of the timers for a particular implementation in the EPICS. See 4.5.9. The data type for these timers shall be Real.

6.3.1 Notification Fail Time

The **Notification Fail Time** is the elapsed time, in seconds, between when the conditions that constitute an event or change of value become externally observable and when a test is considered to have failed because the expected notification message has not been transmitted.

6.3.2 Internal Processing Fail Time

The **Internal Processing Fail Time** is the elapsed time, in seconds, between the receipt of a write to a BACnet property or some other event that changes the value of the property and when a test is considered to have failed because the property value has not been updated.

6.3.3 Minimum ON/OFF Fail Time

The **Minimum ON/OFF Fail Time** is the maximum elapsed time, in seconds, between the expiration of a minimum on or minimum off timer and when the test is considered to have failed because the value at command priority level 6 is not as expected.

6.3.4 Schedule Evaluation Fail Time

The **Schedule Evaluation Fail Time** is the elapsed time, in seconds, between a change to a property defining a Calendar or a Schedule, or a change in the device's Local_Time, and when a test is considered to have failed because the Present_Value of the Calendar or Schedule does not reflect the correct state.

6.3.5 External Command Fail Time

The **External Command Fail Time** is the elapsed time, in seconds, between a change to the Present_Value of a Command object and when a test is considered to have failed because the first message associated with the newly commanded state has not been transmitted.

6.3.6 Program Object State Change Fail Time

The **Program Object State Change Fail Time** is the time, in seconds, between a write to the Program_Change property and when a test is considered to have failed because the expected program result was not observed.

6.3.7 Acknowledgment Fail Time

The **Acknowledgment Fail Time** is the elapsed time, in seconds, between when a BACnet confirmed service request is transmitted and the corresponding acknowledgment shall have been received.

6.3.8 Default Time Delay in Test Descriptions

For the test cases defined in this standard it is acceptable to have a time delay of up to **Internal Processing Fail Time** before a message specified by a RECEIVE statement is actually received unless a different timing constraint is explicitly stated.

6.3.9 Unconfirmed Response Fail Time

The **Unconfirmed Response Fail Time** is the elapsed time, in seconds, between when the IUT receives an unconfirmed request and when a test is considered to have failed because the expected unconfirmed request from the IUT has not been received. For example, this is the maximum amount of time that the IUT would take to initiate an I-Am request in response to a Who-Is request.

6.4 BACnet References

All references to BACnet clauses in this standard refer to ANSI/ASHRAE 135-2008, except as otherwise noted ("BACnet-2001" refers to ANSI/ASHRAE 135-2001).

6.5 TD Requirements

The tests defined in this test standard describe specific conversations between the TD and the IUT. While these test conversations take place, the IUT may initiate other conversations related to or unrelated to the current test. Unless otherwise noted in the test, for conversations initiated by the IUT that are not reflected in the test steps of the test, the TD shall generate a correct response consistent with the device capabilities and state that the TD is emulating.

7. OBJECT SUPPORT TESTS

The IUT shall be tested to ensure that each property of each object contained in the test database is supported. This support shall be verified by reading each property and verifying the correctness of the value returned and, where appropriate, by writing to the property and verifying an appropriate response. The read support tests are defined in 7.1 and the write support tests are defined in 7.2. Some BACnet objects are also required to provide certain functionality based on the values of their properties. Tests for the purpose of verifying this functionality are defined in 7.3.

7.1 Read Support for Properties in the Test Database

7.1.1 Read Support Test Procedure

Dependencies: ReadProperty Service Execution Tests, 9.18.

Purpose: Verifies that a correct response is returned when each property of each object is read using BACnet ReadProperty and ReadPropertyMultiple services. The test is performed once using ReadProperty and once using ReadPropertyMultiple, if supported. When verifying array properties, whole arrays shall be read without using an ARRAY INDEX, where possible.

Test Steps:

```

1. REPEAT X = (all objects in the IUT's database) DO {
    REPEAT Y = (all properties in object X) DO {
        IF (Y is defined by the standard as not accessible via the ReadProperty service) THEN
            TRANSMIT ReadProperty-Request,
                'Object Identifier' = X,
                'Property Identifier' = Y
            IF (Protocol_Revision >= 7) THEN
                RECEIVE BACnet-Error-PDU,
                    Error Class = PROPERTY,
                    Error Code = READ_ACCESS_DENIED
            ELSE
                RECEIVE BACnet-Error-PDU,
                    Error Class = PROPERTY,
                    Error Code = READ_ACCESS_DENIED | OTHER
                | (BACnet-Error-PDU,
                    Error Class = OBJECT,
                    Error Code = OTHER)
                | (BACnet-Error-PDU,
                    Error Class = SERVICES,
                    Error Code = SERVICE_REQUEST_DENIED | OTHER)
            ELSE IF (Y is an array and its value is too large to return given the IUT's APDU and segmentation
                limitations) THEN
                TRANSMIT ReadProperty-Request,
                    'Object Identifier' = X,
                    'Property Identifier' = Y
                RECEIVE BACnet-Abort-PDU,
                    'Abort Reason' = SEGMENTATION_NOT_SUPPORTED | BUFFER_OVERFLOW
                TRANSMIT ReadProperty-Request,
                    'Object Identifier' = X,
                    'Property Identifier' = Y,
                    'Property Array Index' = 0
                RECEIVE ReadProperty-ACK,
                    'Object Identifier' = X,
                    'PropertyIdentifier' = Y,
                    'Priority Array Index' = 0,
                    'Property Value' = (N: the number of array elements in Y as indicated in the EPICS)
    }
}

```

```

        REPEAT Z = (1 .. N) DO {
            VERIFY (X), Y = (the value for element Z as indicated in the EPICS), ARRAY INDEX = Z
        }
    ELSE
        VERIFY (X), Y = (the value for this property specified in the EPICS)
    }
}

```

Notes to Tester: For cases where the EPICS indicates that the value of a property is unspecified using the "?" symbol, any value that is of the correct datatype shall be considered to be a match.

7.1.2 Non-documented Property Test

Purpose: To verify that all properties contained in every standard object are documented in the EPICS.

Test Concept: For each standard object in the EPICS database, attempt to read each standard property that the EPICS does not document as being part of the object.

Test Steps:

```

1. REPEAT X = (a tester selected set of standard objects) DO {
    REPEAT Y = (0 through 511) DO {
        IF (the property Y is not in the EPICS for object X) THEN
            TRANSMIT ReadProperty-Request,
                'Object Identifier' = X,
                'Property Identifier' = Y
            RECEIVE BACnet-Error-PDU,
                Error Class = PROPERTY,
                Error Code = UNKNOWN_PROPERTY
        }
    }
}

```

Notes to Tester: The objects selected by the tester should include one instance of each supported standard object type. Where some instances of an object type differ in the set of supported properties, the allowable value ranges for a property, or the writability of a property, then one instance of each variant of that object type should be selected.

7.1.3 Verifying Property_List against the EPICS

Purpose: To verify the correct content of the Property_List using the properties in each object as claimed in the EPICS.

Test Concept: Match the properties in each object as claimed in the EPICS, against the content of each object's Property_List.

Test Conditionality: If Protocol_Revision is not present, or Protocol_Revision < 14, then this test shall be skipped.

Test Steps:

```

1. READ OL = Object_List
2. REPEAT O1 = (each object in the content of OL) DO {
    READ PL = O1, Property_List
    CHECK (that the property identifiers in the EPICS for O1 and those in PL match, except as specified in Notes to
Tester)
}

```

Notes to Tester: Object_Name (77), Object_Type (79), Object_Identifier (75), and Property_List (371) will appear in the EPICS, but shall not appear in the Property_List value. Any proprietary properties that are supported for the object-type shall be in the Property_List, but are not required to appear in the EPICS. The order in which property identifiers appear in the EPICS is not required to match the order that they appear in the Property_List value.

7.2 Write Support for Properties in the Test Database

7.2.1 Functional Range Requirements for Property Values

For each writable property, multiple values will be selected by the tester as defined in this clause to verify the range of supported values.

7.2.1.1 Enumerated and Boolean Values

For enumerated and Boolean values a set of the defined enumerations, including, at a minimum, the lowest, highest, and a mid-range value, shall be tested after taking into consideration any permitted restrictions as defined in 4.4.2.

7.2.1.2 Unsigned Integer, Signed Integer, Real, and Double Values

Properties with a continuous datatype shall be tested at the upper limit, lower limit, and two intermediate points selected by the tester. The vendor shall provide the actual value of the limits for a particular implementation in the EPICS. See 4.4.2.

7.2.1.3 Octetstrings and Characterstrings,

Properties with an octetstring or characterstring datatype shall be tested with a string of the minimum supported length, a string with the maximum supported length, and a string with some length between the two. The vendor shall provide the values of the minimum and maximum string lengths in the EPICS. For string properties that do not have a fixed maximum length, the vendor shall provide a maximum length that is acceptable under normal operating conditions for use in these tests. In such cases, no statement is made as to whether or not a longer string value would or would not be accepted by the property. See Clause 4.4.2.

7.2.1.4 Bitstring

Properties with a Bitstring datatype shall be tested with a single value that differs from the current value.

7.2.1.5 Date

Properties with a Date datatype shall be tested using a single date that differs from the current value.

7.2.1.6 Time

Properties with a Time datatype shall be tested by writing a time value with all fields explicitly specified. This time shall differ from the previous value by an amount greater than the resolution of the IUT's clock. When the property is read back, the time shall match the written value within the resolution of the IUT's clock.

One time value with an unspecified field shall also be tested. The unspecified field shall be a time value that is within the IUT's clock resolution. For all properties except the Local_Time property of the Device object, when this value is read back the time shall match the written value within the resolution of the IUT's clock and the unspecified field shall remain unspecified. For the special case of the Local_Time property, which is coupled to the system clock, the value returned for the unspecified portion of the time is a local matter.

7.2.1.7 Constructed Datatypes

For constructed datatypes the tester shall select one or more values to write that is consistent with the datatype.

7.2.2 Write Support Test Procedure

Purpose: To verify that all writable properties of all objects can be written to using BACnet WriteProperty and WritePropertyMultiple services. The test is performed once using WriteProperty and once using WritePropertyMultiple. When writing to array properties, the whole array shall be written without using an ARRAY INDEX, where possible.

Dependencies: ReadProperty Service Execution Tests, 9.18; WriteProperty Service Execution Tests, 9.22.

Test Steps:

1. REPEAT X = (all objects in the IUT's database) DO {
 REPEAT Y = (all writable properties in object X) DO {
 REPEAT Z = (a set of values meeting the range requirements of 7.2.1 and

```

        any additional restrictions placed on the allowable property values as specified by the vendor) DO {
        WRITE (X), Y = Z,
        VERIFY (X), Y = Z
        }
    }
}

```

7.2.3 Read-only Property Test

Purpose: To verify that properties marked as read-only in the EPICS are in fact read-only.

Test Concept: To each read-only (not writable and not conditionally writable) property in the EPICS, write the value of the property as read from the device and verify that an error is returned. Write another value that is within the acceptable range for the datatype and verify that an error is returned. If the property is a list and the IUT supports AddListElement, attempt to modify the property with AddListElement and verify that an error is returned. If the IUT does not support the WriteProperty service, then this test shall be skipped.

Test Steps:

```

1. REPEAT X = (a tester selected set of objects) DO {
    REPEAT Y = (all read-only properties in object X) DO {
        IF (the property is not an array) THEN
            READ Z = X
            TRANSMIT WriteProperty-Request,
                'Object Identifier' = X,
                'Property Identifier' = Y,
                'Property Value' = Z
            RECEIVE BACnet-Error-PDU,
                Error Class = PROPERTY,
                Error Code = WRITE_ACCESS_DENIED

            TRANSMIT WriteProperty-Request,
                'Object Identifier' = X,
                'Property Identifier' = Y,
                'Property Value' = (any value meeting the range requirements of 7.2.1 except Z)
            RECEIVE BACnet-Error-PDU,
                Error Class = PROPERTY,
                Error Code = WRITE_ACCESS_DENIED

            IF (the IUT supports AddListElement and the property is a list) THEN
                TRANSMIT AddListElement-Request,
                    'Object Identifier' = X,
                    'Property Identifier' = Y,
                    List of Elements' = (any element value meeting the range requirements of 7.2.1
excluding
                                those in Z)
                RECEIVE BACnet-Error-PDU,
                    Error Class = PROPERTY,
                    Error Code = WRITE_ACCESS_DENIED
            ELSE
                READ LEN = X, Array_Index = 0
                IF (LEN > 0) THEN
                    READ Z = X, Array Index = 1
                    TRANSMIT WriteProperty-Request,
                        'Object Identifier' = X,
                        'Property Identifier' = Y,
                        'Property Value' = Z

```

```

        'Priority Array Index' =      1
    RECEIVE BACnet-Error-PDU,
        Error Class =                PROPERTY,
        Error Code =                WRITE_ACCESS_DENIED

    TRANSMIT WriteProperty-Request,
        'Object Identifier' =        X,
        'Property Identifier' =      Y,
        'Property Value' =            (any value meeting the range requirements of 7.2.1 except Z)
        'Priority Array Index' =      1
    RECEIVE BACnet-Error-PDU,
        Error Class =                PROPERTY,
        Error Code =                WRITE_ACCESS_DENIED

    IF (the IUT supports AddListElement and the property is an array of lists) THEN
        TRANSMIT AddListElement-Request,
            'Object Identifier' =      X,
            'Property Identifier' =    Y,
            'Priority Array Index' =    1
            List of Elements' =        (any elements value meeting the range requirements of
                                        7.2.1excluding those in Z)

        RECEIVE BACnet-Error-PDU,
            Error Class =              PROPERTY,
            Error Code =              WRITE_ACCESS_DENIED
    ELSE
        TRANSMIT WriteProperty-Request,
            'Object Identifier' =      X,
            'Property Identifier' =    Y,
            'Property Value' =        (any value meeting the range requirements of 7.2.1)
        RECEIVE BACnet-Error-PDU,
            Error Class =              PROPERTY,
            Error Code =              WRITE_ACCESS_DENIED
    }
}

```

Notes to Tester: The objects selected by the tester should include one instance of each supported object type. Where some instances of an object type differ in the set of supported properties, the allowable value ranges for a property, or the writability of a property, then one instance of each variant of that object type should be selected.

Notes to Tester: When modifying a property, it is expected that an error class of PROPERTY with an error code of WRITE_ACCESS_DENIED will be returned, but the IUT may instead return an error_class of PROPERTY with an error_code of VALUE_OUT_OF_RANGE, or an error_class of RESOURCES with an error_code of NO_SPACE_TO_WRITE_PROPERTY.

7.3 Object Functionality Tests

The tests defined in this clause are used to verify that the required functionality for various BACnet objects is supported. The tests are object type specific and in some cases also dependent of the value of particular properties. For each object type supported, all of the tests in this clause that apply shall be executed. It is sufficient to demonstrate the correct functionality for a single instance of each object type.

7.3.1 Property Tests

The tests in this clause apply to properties that appear in multiple object types. The functionality associated with the property shall be tested once for each object type that supports the property.

7.3.1.1 Out_Of_Service, Status_Flags, and Reliability Tests

Dependencies: ReadProperty Service Execution Tests, 9.18; WriteProperty Service Execution Tests, 9.22.

BACnet Reference Clauses: 12.1.7, 12.1.9, 12.1.10, 12.2.7, 12.2.9, 12.2.10, 12.3.7, 12.3.9, 12.3.10, 12.4.6, 12.4.8, 12.4.9, 12.6.7, 12.6.9, 12.6.10, 12.7.7, 12.7.9, 12.7.10, 12.8.6, 12.8.8, 12.8.9, 12.15.8, 12.15.10, 12.15.11, 12.16.8, 12.16.10, 12.16.11, 12.17.6, 12.17.8, 12.17.9, 12.18.7, 12.18.9, 12.18.10, 12.19.7, 12.19.9, 12.19.10, 12.20.6, 12.20.8, 12.20.9, 12.23.7, 12.23.9, and 12.23.10.

Purpose: This test case verifies that `Present_Value` is writable when `Out_Of_Service` is `TRUE`. It also verifies the interrelationship between the `Out_Of_Service`, `Status_Flags`, and `Reliability` properties. If the PICS indicates that the `Out_Of_Service` property of the object under test is not writable, and if the value of the property cannot be changed by other means, then this test shall be omitted. This test applies to Accumulator, Analog Input, Analog Output, Analog Value, Binary Input, Binary Output, Binary Value, Life Safety Point, Life Safety Zone, Multi-state Input, Multi-state Output, Multi-state Value, Loop and Pulse Converter objects.

Test Concept: The IUT will select one instance of each appropriate object type and test it as described. If the `Reliability` property is not supported then step 4 shall be omitted.

Test Steps:

1. IF (Out_Of_Service is writable) THEN
 WRITE Out_Of_Service = TRUE
ELSE
 MAKE (Out_Of_Service TRUE)
2. VERIFY Out_Of_Service = TRUE
3. VERIFY Status_Flags = (?, FALSE, ?, TRUE)
4. REPEAT X = (all values meeting the functional range requirements of 7.2.1) DO {
 WRITE Present_Value = X
 VERIFY Present_Value = X
}
5. IF (Reliability is present and writable) THEN
 REPEAT X = (all values of the Reliability enumeration appropriate to the object type except
 NO_FAULT_DETECTED) DO {
 WRITE Reliability = X
 VERIFY Reliability = X
 VERIFY Status_Flags = (?, TRUE, ?, TRUE)
 WRITE Reliability = NO_FAULT_DETECTED
 VERIFY Reliability = NO_FAULT_DETECTED
 VERIFY Status_Flags = (?, FALSE, ?, TRUE)
 }
ELSE
 MAKE (Out_Of_Service FALSE)
7. VERIFY Out_Of_Service = FALSE
8. VERIFY Status_Flags = (?, ?, ?, FALSE)

Notes to Tester: If the object being tested is commandable and there is an internal process writing to the Present_Value property, then each WriteProperty request shall contain a priority sufficient to override the internal process. After step 4 the priority array slot shall be relinquished.

7.3.1.2 Relinquish Default Test

Dependencies: ReadProperty Service Execution Tests, 9.18; WriteProperty Service Execution Tests, 9.22.

BACnet Reference Clauses: 12.3.16, 12.4.12, 12.7.22, 12.8.20, 12.19.14, and 12.20.13.

Purpose: To verify that the Present_Value property takes on the value of Relinquish_Default when all prioritized commands have been relinquished. This test applies to Analog Output, Analog Value, Binary Output, Binary Value, Multi-state Output, and Multi-state Value objects that are commandable.

Test Concept: A pre-requisite to this test is that an object has been provided for which all prioritized commands have been relinquished and any minimum on/off time has been accounted for. The Present_Value is compared to the value of Relinquish_Default to ensure that they are the same. If possible, the value of Relinquish_Default is changed to verify that Present_Value tracks the changes.

Configuration Requirements: The object to be tested shall be configured such that all slots in the Priority_Array have a value of NULL and no internal algorithms are issuing prioritized commands to this object.

Test Steps:

1. VERIFY Priority_Array = (NULL, NULL, NULL, NULL, NULL, NULL, NULL, NULL, NULL, NULL, NULL, NULL, NULL, NULL, NULL, NULL)
2. TRANSMIT ReadProperty-Request,
 'Object Identifier' = (the object being tested),

- 'Property Identifier' = Present_Value
3. RECEIVE ReadProperty-ACK,
 'Object Identifier' = (the object being tested),
 'Property Identifier' = Present_Value
 'Property Value' = (any valid value, X)
 4. VERIFY Relinquish_Default = X
 5. IF (Relinquish_Default is writable) THEN
 WRITE Relinquish_Default = (any valid value, Y, other than the one returned in step 3)
 VERIFY Present_Value = Y

7.3.1.3 Command Prioritization Test

Dependencies: ReadProperty Service Execution Tests, 9.18; WriteProperty Service Execution Tests, 9.22.

BACnet Reference Clause: 19.2.

Purpose: To verify that the command prioritization algorithm is properly implemented. This test applies to all commandable objects.

Test Concept: The TD selects three different values V_{low} , V_{med} , and V_{high} chosen from the valid values specified in 4.4.2. For objects that are limited to two values, V_{low} and V_{high} shall be the same, and V_{med} shall be different. The TD also selects three priorities P_{low} , P_{med} , and P_{high} , all between 1 and 5, such that numerically $P_{low} > P_{med} > P_{high}$. The selected values are written one at a time to Present_Value at the corresponding priority. The Present_Value and Priority_Array are checked to verify correct operation. Priorities numerically smaller than 6 (higher priority) are used to eliminate minimum on/off time considerations

Configuration Requirements: The object to be tested shall be configured such that all slots in the Priority_Array with a priority higher than 6 have a value of NULL.

Test Steps:

1. WRITE Present_Value = V_{low} , PRIORITY = P_{low}
2. VERIFY Present_Value = V_{low}
3. VERIFY Priority_Array = V_{low} , ARRAY INDEX = P_{low}
4. REPEAT Z = (each index 1 through 5 not equal to P_{low}) DO {
 VERIFY Priority_Array = NULL, ARRAY INDEX = Z
 }
5. WRITE Present_Value = V_{high} , PRIORITY = P_{high}
6. VERIFY Present_Value = V_{high}
7. VERIFY Priority_Array = V_{high} , ARRAY INDEX = P_{high}
8. REPEAT Z = (each index 1 through 5 not equal to P_{low} or P_{high}) DO {
 VERIFY Priority_Array = NULL, ARRAY INDEX = Z
 }
9. WRITE Present_Value = V_{med} , PRIORITY = P_{med}
10. VERIFY Present_Value = V_{high}
11. VERIFY Priority_Array = V_{med} , ARRAY INDEX = P_{med}
12. REPEAT Z = (each index 1 through 5 not equal to P_{low} , P_{med} or P_{high}) DO {
 VERIFY Priority_Array = NULL, ARRAY INDEX = Z
 }
13. WRITE Present_Value = NULL, PRIORITY = P_{high}
14. VERIFY Present_Value = V_{med}
15. REPEAT Z = (each index 1 through 5 not equal to P_{low} or P_{med}) DO {
 VERIFY Priority_Array = NULL, ARRAY INDEX = Z
 }
16. WRITE Present_Value = NULL, PRIORITY = P_{med}
17. VERIFY Present_Value = V_{low}
18. REPEAT Z = (each index 1 through 5 not equal to P_{low}) DO {

```

    VERIFY Priority_Array = NULL, ARRAY INDEX = Z
  }
19. WRITE Present_Value = NULL, PRIORITY = Plow
20. REPEAT Z = (each index 1 through 5) DO {
    VERIFY Priority_Array = NULL, ARRAY INDEX = Z
  }

```

7.3.1.4 Minimum_Off_Time

Dependencies: ReadProperty Service Execution Tests, 9.18; WriteProperty Service Execution Tests, 9.22.

BACnet Reference Clauses: 12.7.19, 12.8.17, 19.2.3, and Annex I.

Purpose: To verify that the minimum off time algorithm is properly implemented. If minimum off time is not supported this test shall be omitted. This test applies to Binary Output and Binary Value objects.

Test Concept: The initial Present_Value of the object tested is set to ACTIVE and it is controlled at a priority numerically greater (lower priority) than 6. The object has been in this state long enough for any minimum on time to have expired. The Present_Value is written to with a value of INACTIVE at priority 7. The value of slot 6 of the Priority_Array is monitored to verify that it contains the value INACTIVE for the duration of the minimum off time.

Configuration Requirements: The object to be tested shall be configured such that all slots in the Priority_Array numerically less than 7 have a value of NULL, the Present_Value is ACTIVE, and no internal algorithms are issuing commands to this object at a priority numerically lower (higher priority) than the priority that is currently controlling Present_Value.

Test Steps:

1. WRITE Present_Value = INACTIVE, PRIORITY = 7
2. VERIFY Present_Value = INACTIVE
3. VERIFY Priority_Array = INACTIVE, ARRAY INDEX = 6
4. WAIT (approximately 90% of Minimum_Off_Time from step 1)
5. VERIFY Priority_Array = INACTIVE, ARRAY INDEX = 6
6. WAIT (**Minimum ON/OFF Fail Time** + Minimum_Off_Time from step 1)
7. VERIFY Priority_Array = NULL, ARRAY INDEX = 6

7.3.1.5 Minimum_On_Time

Dependencies: ReadProperty Service Execution Tests, 9.18; WriteProperty Service Execution Tests, 9.22.

BACnet Reference Clauses: 12.7.20, 12.8.18, 19.2.3, and Annex I.

Purpose: To verify that the minimum on time algorithm is properly implemented. If minimum on time is not supported this test shall be omitted. This test applies to Binary Output and Binary Value objects.

Test Concept: The initial Present_Value of the object tested is set to INACTIVE and it is controlled at a priority numerically greater (lower priority) than 6. The object has been in this state long enough for any minimum on time to have expired. The Present_Value is written to with a value of ACTIVE at priority 7. The value of slot 6 of the Priority_Array is monitored to verify that it contains the value ACTIVE for the duration of the minimum on time.

Configuration Requirements: The object to be tested shall be configured such that all slots in the Priority_Array numerically less than 7 have a value of NULL, the Present_Value is INACTIVE, and no internal algorithms are issuing commands to this object at a priority numerically lower (higher priority) than the priority that is currently controlling Present_Value.

Test Steps:

1. WRITE Present_Value = ACTIVE, PRIORITY = 7
2. VERIFY Present_Value = ACTIVE
3. VERIFY Priority_Array = ACTIVE, ARRAY INDEX = 6

4. WAIT (approximately 90% of Minimum_On_Time from step 1)
5. VERIFY Priority_Array = ACTIVE, ARRAY INDEX = 6
6. WAIT (**Minimum ON/OFF Fail Time** + Minimum_On_Time from step 1)
7. VERIFY Priority_Array = NULL, ARRAY INDEX = 6

7.3.1.6 Override of Minimum Time

Dependencies: ReadProperty Service Execution Tests, 9.18; WriteProperty Service Execution Tests, 9.22.

BACnet Reference Clause: 12.7.19, 12.7.20, 12.8.17, 12.8.18, 19.2.

Purpose: To verify that higher priority commands override minimum on or off times. If neither minimum on time or minimum off time is supported this test shall be omitted. This test applies to Binary Output and Binary Value objects.

Test Concept: The initial Present_Value of the object tested is set to INACTIVE and it is controlled at a priority numerically greater (lower priority) than 6. The object has been in this state long enough for any minimum on time to have expired. The Present_Value is written to with a value of ACTIVE at priority 7. The value of slot 6 of the Priority_Array is monitored to verify that it contains the value ACTIVE. Before the minimum on time expires the Present_Value is written to with a value of INACTIVE and a priority numerically lower (higher priority) than 6. This overrides the minimum on time and immediately initiates the minimum off time algorithm.

Configuration Requirements: The object to be tested shall be configured such that all slots in the Priority_Array numerically less than 7 have a value of NULL and no internal algorithms are issuing commands to this object at a priority numerically lower (higher priority) than the priority that is currently controlling Present_Value.

Test Steps:

1. WRITE Present_Value = ACTIVE, PRIORITY = 7
2. VERIFY Present_Value = ACTIVE
3. VERIFY Priority_Array = ACTIVE, ARRAY INDEX = 6
4. BEFORE Minimum_On_Time
WRITE Present_Value = INACTIVE, PRIORITY = (any value numerically lower than 6 (higher priority))
5. VERIFY Present_Value = INACTIVE
6. VERIFY Priority_Array = INACTIVE, PRIORITY = 6

Notes to Tester: If minimum on time is not supported but minimum off time is supported, this test should be conducted by using INACTIVE in steps 1 through 3 and ACTIVE in steps 4 through 6, and by using Minimum_Off_Time in step 4.

7.3.1.7 COV Tests

Tests to demonstrate COV functionality are covered in 8.2 and 9.6.

7.3.1.8 Binary Object Change of State Tests

Dependencies: ReadProperty Service Execution Tests, 9.18; WriteProperty Service Execution Tests, 9.22.

BACnet Reference Clauses: 12.6.14, 12.6.15, 12.6.16, 12.7.14, 12.7.15, 12.7.16, 12.8.12, 12.8.13, and 12.8.14.

Purpose: To verify that the properties of binary objects that collectively track state changes (changes in Present_Value) function as required. If the Change_Of_State_Count, Change_Of_State_Time, and Time_Of_State_Count_Reset properties are not supported this test shall be omitted. This test applies to Binary Input, Binary Output, and Binary Value objects.

Test Concept: The Present_Value of the binary object under test is changed. The Change_Of_State_Count property is checked to verify that it has been incremented and the Change_Of_State_Time property is checked to verify that it has been updated. The Change_Of_State_Count is reset and Time_Of_State_Count_Reset is checked to verify that it has been updated appropriately.

Configuration Requirements: The object being tested shall be configured such that the Present_Value and Change_Of_State_Count properties are writable or another means of changing these properties shall be provided.

Test Steps:

1. TRANSMIT ReadProperty-Request,
 'Object Identifier' = (the object being tested),
 'Property Identifier' = Present_Value
2. RECEIVE ReadProperty-ACK,
 'Object Identifier' = (the object being tested),
 'Property Identifier' = Present_Value,
 'Property Value' = ACTIVE | INACTIVE
3. TRANSMIT ReadProperty-Request,
 'Object Identifier' = (the object being tested),
 'Property Identifier' = Change_Of_State_Count
4. RECEIVE ReadProperty-ACK,
 'Object Identifier' = (the object being tested),
 'Property Identifier' = Change_Of_State_Count,
 'Property Value' = (any valid value, N)
5. IF (Present_Value is writable) THEN
 IF (the value returned in step 2 was ACTIVE) THEN
 WRITE Present_Value = INACTIVE
 VERIFY Present_Value = INACTIVE
 ELSE
 WRITE Present_Value = ACTIVE
 VERIFY Present_Value = ACTIVE
 ELSE
 MAKE (Present_Value change to the opposite state)
6. TRANSMIT ReadProperty-Request,
 'Object Identifier' = (the IUT's Device object),
 'Property Identifier' = Local_Date
7. RECEIVE ReadProperty-ACK,
 'Object Identifier' = (the IUT's Device object),
 'Property Identifier' = Local Date,
 'Property Value' = (the current local date, D)
8. TRANSMIT ReadProperty-Request,
 'Object Identifier' = (the IUT's Device object),
 'Property Identifier' = Local_Time
9. RECEIVE ReadProperty-ACK,
 'Object Identifier' = (the IUT's Device object),
 'Property Identifier' = Local_Time,
 'Property Value' = (any valid time stamp, T_{Loc})
10. WAIT **Internal Processing Fail Time**
11. TRANSMIT ReadProperty-Request,
 'Object Identifier' = (the object being tested),
 'Property Identifier' = Change_Of_State_Time
12. RECEIVE ReadProperty-ACK,
 'Object Identifier' = (the object being tested),
 'Property Identifier' = Change_Of_State_Time,
 'Property Value' = (a date and time such that the date = D and the time is approximately T_{Loc})
13. TRANSMIT ReadProperty-Request,
 'Object Identifier' = (the object being tested),
 'Property Identifier' = Change_Of_State_Count
14. RECEIVE ReadProperty-ACK,
 'Object Identifier' = (the object being tested),
 'Property Identifier' = Change_Of_State_Count,

- 'Property Value' = N + 1
15. IF (Change_Of_State_Count is writable) THEN
 WRITE Change_Of_State_Count = 0
 VERIFY Change_Of_State_Count = 0
 ELSE
 MAKE (Change_Of_State_Count = 0)
 16. TRANSMIT ReadProperty-Request,
 'Object Identifier' = (the IUT's Device object),
 'Property Identifier' = Local_Time
 17. RECEIVE ReadProperty-ACK,
 'Object Identifier' = (the IUT's Device object),
 'Property Identifier' = Local_Time,
 'Property Value' = (any valid time stamp, T_{LOC})
 18. TRANSMIT ReadProperty-Request,
 'Object Identifier' = (the object being tested),
 'Property Identifier' = Time_Of_State_Count_Reset
 19. RECEIVE ReadProperty-ACK,
 'Object Identifier' = (the object being tested),
 'Property Identifier' = Time_Of_State_Count_Reset,
 'Property Value' = (a date and time such that the date = D and the time is approximately T_{LOC})

7.3.1.9 Binary Object Elapsed Active Time Tests

Dependencies: ReadProperty Service Execution Tests, 9.18; WriteProperty Service Execution Tests, 9.22.

BACnet Reference Clauses: 12.6.17, 12.6.18, 12.7.17, 12.7.18, 12.8.15, and 12.8.16.

Purpose: To verify that the properties of binary objects that collectively track active time function properly. If the Elapsed_Active_Time and Time_Of_Active_Time_Reset properties are not supported then this test shall be omitted. This test applies to Binary Input, Binary Output, and Binary Value objects.

Test Concept: The Present_Value of the binary object being tested is set to INACTIVE. The Elapsed_Active_Time property is checked to verify that it does not accumulate time while the object is in an INACTIVE state. The Present_Value is then set to ACTIVE. The Elapsed_Active_Time property is checked to verify that it is accumulating time while the object is in an ACTIVE state. The Present_Value is then set to INACTIVE and the Elapsed_Active_Time is reset. The Time_Of_Active_Time_Reset property is checked to verify that it has been updated.

Configuration Requirements: The object being tested shall be configured such that the Present_Value and Elapsed_Active_Time properties are writable or another means of changing these properties shall be provided.

Test Steps:

1. IF (Present_Value is writable) THEN
 WRITE Present_Value = INACTIVE
 VERIFY Present_Value = INACTIVE
 ELSE
 MAKE (Present_Value = INACTIVE)
2. TRANSMIT ReadProperty-Request,
 'Object Identifier' = (the object being tested),
 'Property Identifier' = Elapsed_Active_Time
3. RECEIVE ReadProperty-ACK,
 'Object Identifier' = (the object being tested),
 'Property Identifier' = Elapsed_Active_Time,
 'Property Value' = (the elapsed active time, T_{ELAPSED} in seconds)
4. WAIT (1 minute)
5. TRANSMIT ReadProperty-Request,
 'Object Identifier' = (the object being tested),

- 'Property Identifier' = Elapsed_Active_Time
6. RECEIVE ReadProperty-ACK,
 'Object Identifier' = (the object being tested),
 'Property Identifier' = Elapsed_Active_Time,
 'Property Value' = (the same $T_{ELAPSED}$ as step 3)
 7. IF (Present_Value is writable) THEN
 WRITE Present_Value = ACTIVE
 VERIFY Present_Value = ACTIVE
 ELSE
 MAKE (Present_Value = ACTIVE)
 8. WAIT (**Internal Processing Fail Time** + 30 seconds)
 9. TRANSMIT ReadProperty-Request,
 'Object Identifier' = (the object being tested),
 'Property Identifier' = Elapsed_Active_Time
 10. RECEIVE ReadProperty-ACK,
 'Object Identifier' = (the object being tested),
 'Property Identifier' = Elapsed_Active_Time,
 'Property Value' = ($T: (T_{ELAPSED} + 30) \leq T \leq (T_{ELAPSED} + 30 + \text{Internal Processing Fail Time})$)
 11. IF (Present_Value is writable) THEN
 WRITE Present_Value = INACTIVE
 VERIFY Present_Value = INACTIVE
 ELSE
 MAKE (Present_Value = INACTIVE)
 12. IF (Elapsed_Active_Time is writable) THEN
 WRITE Elapsed_Active_Time = 0
 VERIFY Elapsed_Active_Time = 0
 ELSE
 MAKE (Elapsed_Active_Time = 0)
 13. TRANSMIT ReadProperty-Request,
 'Object Identifier' = (the IUT's Device object),
 'Property Identifier' = Local_Date
 14. RECEIVE ReadProperty-ACK,
 'Object Identifier' = (the IUT's Device object),
 'Property Identifier' = Local Date,
 'Property Value' = (the current local date, D)
 15. TRANSMIT ReadProperty-Request,
 'Object Identifier' = (the IUT's Device object),
 'Property Identifier' = Local_Time
 16. RECEIVE ReadProperty-ACK,
 'Object Identifier' = (the IUT's Device object),
 'Property Identifier' = Local_Time,
 'Property Value' = (any valid time stamp, T_{LOC})
 17. TRANSMIT ReadProperty-Request,
 'Object Identifier' = (the object being tested),
 'Property Identifier' = Time_Of_Active_Time_Reset
 18. RECEIVE ReadProperty-ACK,
 'Object Identifier' = (the object being tested),
 'Property Identifier' = Present_Value,
 'Property Value' = (a date and time such that the date = D and the time is approximately T_{LOC})

7.3.1.10 Event_Enable Tests

7.3.1.10.1 Event_Enable Test for TO_OFFNORMAL, TO_NORMAL, and TO_FAULT

Purpose: To verify that notification messages are transmitted only if the bit in Event_Enable corresponding to the event transition has a value of TRUE.

Test Concept: The IUT is configured with an event-generating object, O1, such that the Event_Enable property is tested in all supported states. Each event transition is triggered and the IUT is monitored to verify that notification messages are transmitted only for those transitions for which the Event_Enable property has a value of TRUE.

Configuration Requirements: If the Event_Enable property is configurable, repeat the test with Event_Enable = (T, F, F), (F, T, F), (F, F, T). If the Event_Enable property is not configurable, then follow the test steps as written and verify correct behavior for the value of the Event_Enable property. All other properties in O1, and any supporting objects, shall be configured to allow these events to be generated. The event-generating object shall be in a NORMAL state at the start of the test. D1 is either the pTimeDelay parameter or, in case of the EXTENDED and proprietary algorithms, a vendor specific delay (may be zero).

D2 is either the pTimeDelayNormal parameter or, in case of the EXTENDED and proprietary algorithms, a vendor specific delay (may be zero).

Test Steps:

1. VERIFY pCurrentState = NORMAL
2. WAIT (pTimeDelay + **Notification Fail Time**)
3. IF (O1 contains pFeedbackValue) THEN
 - MAKE (pFeedbackValue differ from pMonitoredValue)
 - ELSE IF (pMonitoredValue is writable) THEN
 - WRITE pMonitoredValue = (a value that is OFFNORMAL)
 - ELSE
 - MAKE (pMonitoredValue have a value that is OFFNORMAL)
4. WAIT (D1)
5. BEFORE **Notification Fail Time**
 - IF (the Transitions bit corresponding to the TO-OFFNORMAL transition is TRUE) THEN {
 - RECEIVE ConfirmedEventNotification-Request,
 - 'Process Identifier' = (any valid process ID),
 - 'Initiating Device Identifier' = IUT,
 - 'Event Object Identifier' = O1,
 - 'Time Stamp' = (any valid time stamp),
 - 'Notification Class' = (the class corresponding to the object being tested),
 - 'Priority' = (the value configured to correspond to a TO-OFFNORMAL transition),
 - 'Event Type' = (any valid event type),
 - 'Message Text' = (optional, any valid message text),
 - 'Notify Type' = EVENT | ALARM,
 - 'AckRequired' = TRUE | FALSE,
 - 'From State' = NORMAL,
 - 'To State' = OFFNORMAL,
 - 'Event Values' = (values appropriate to the event type)
 - TRANSMIT BACnet-SimpleACK-PDU
 - }
 - ELSE
 - CHECK (verify that the IUT did not transmit an event notification message)
6. VERIFY pCurrentState = OFFNORMAL
7. IF (O1 contains pFeedbackValue) THEN
 - MAKE (pFeedbackValue equal to pMonitoredValue)
 - ELSE IF (pMonitoredValue is writable) THEN
 - WRITE pMonitoredValue = (a value that is NORMAL)
 - ELSE
 - MAKE (pMonitoredValue have a value that is NORMAL)
8. WAIT (D2)
9. BEFORE **Notification Fail Time**
 - IF (the Transitions bit corresponding to the TO-NORMAL transition is TRUE) THEN {
 - RECEIVE ConfirmedEventNotification-Request,

```

        'Process Identifier' =      (any valid process ID),
        'Initiating Device Identifier' = IUT,
        'Event Object Identifier' = O1,
        'Time Stamp' =             (any valid time stamp),
        'Notification Class' =      (the class corresponding to the object being tested),
        'Priority' =                (the value configured to correspond to a TO-NORMAL transition),
        'Event Type' =             (any valid event type),
        'Message Text' =           (optional, any valid message text),
        'Notify Type' =            EVENT | ALARM,
        'AckRequired' =            TRUE | FALSE,
        'From State' =             OFFNORMAL,
        'To State' =               NORMAL,
        'Event Values' =           (values appropriate to the event type)
    TRANSMIT BACnet-SimpleACK-PDU
}
ELSE
    CHECK (verify that the IUT did not transmit an event notification message)
10. VERIFY pCurrentState = NORMAL
11. IF (O1 can be placed into a fault condition) THEN {
    MAKE (a condition exist that will cause O1 to generate a TO-FAULT transition)
    BEFORE Notification Fail Time
    IF (the Transitions bit corresponding to the TO-FAULT transition is TRUE) THEN {
        RECEIVE ConfirmedEventNotification-Request,
        'Process Identifier' =      (any valid process ID),
        'Initiating Device Identifier' = IUT,
        'Event Object Identifier' =  (the event-generating object configured for this test),
        'Time Stamp' =             (any valid time stamp),
        'Notification Class' =      (the class corresponding to the object being tested),
        'Priority' =                (the value configured to correspond to a TO-FAULT transition),
        'Event Type' =             (any valid event type),
        'Message Text' =           (optional, any valid message text),
        'Notify Type' =            EVENT | ALARM,
        'AckRequired' =            TRUE | FALSE,
        'From State' =             NORMAL,
        'To State' =               FAULT,
        'Event Values' =           (values appropriate to the event type)
    TRANSMIT BACnet-SimpleACK-PDU
    }
    ELSE
        CHECK (verify that the IUT did not transmit an event notification message)
        VERIFY pCurrentState = FAULT
    }
}

```

Notes to Tester: The UnconfirmedEventNotification service may be substituted for the ConfirmedEventNotification service, in which case the TD shall skip all of the steps in which a BACnet-SimpleACK-PDU is sent.

7.3.1.10.2 Event_Enable Tests for TO_NORMAL only Algorithms

Purpose: To verify that notification messages are transmitted only if the bit in Event_Enable corresponding to the event transition has a value of TRUE. This test applies to objects that only support generation of TO_NORMAL transitions.

Test Concept: The IUT is configured such that the Event_Enable property indicates that some event transitions are to trigger an event notification. Each event transition is triggered, and the IUT is monitored to verify that notification messages are transmitted only for those transitions for which the Event_Enable property has a value of TRUE.

Configuration Requirements: In the Notification Class object providing recipient information, the value of the Transitions parameter for all recipients shall be (TRUE, TRUE, TRUE). The event-generating object shall be in a NORMAL state at the

start of the test. D1 is either the pTimeDelayNormal parameter or, in case of the EXTENDED and proprietary algorithms, a vendor specific delay (may be zero).

Test Steps:

1. VERIFY pCurrentState = NORMAL
2. MAKE (the TO-NORMAL bit of the Event_Enable property equal to TRUE)
3. MAKE (a condition exist that will cause the object to generate a TO_NORMAL transition)
4. WAIT D1
5. **BEFORE Notification Fail Time**
 RECEIVE ConfirmedEventNotification-Request,
 'Process Identifier' = (any valid process ID),
 'Initiating Device Identifier' = IUT,
 'Event Object Identifier' = (the event-generating object configured for this test),
 'Time Stamp' = (any valid time stamp),
 'Notification Class' = (the class corresponding to the object being tested),
 'Priority' = (the value configured to correspond to a TO-NORMAL transition),
 'Event Type' = (any valid event type),
 'Message Text' = (optional, any valid message text),
 'Notify Type' = EVENT | ALARM,
 'AckRequired' = TRUE | FALSE,
 'From State' = NORMAL,
 'To State' = NORMAL,
 'Event Values' = (values appropriate to the event type)
6. TRANSMIT SimpleACK-PDU
7. VERIFY pCurrentState = NORMAL
8. IF (Event_Enable can be changed such that the TO-NORMAL transition is FALSE) THEN {
 MAKE (the TO-NORMAL bit of the Event_Enable property equal to FALSE)
 MAKE (a condition exist that would cause the object to generate a TO_NORMAL transition)
 WAIT (D1 + **Notification Fail Time**)
 CHECK (verify that the IUT did not transmit an event notification message)
 MAKE (the TO_NORMAL bit of the Event_Enable property equal to TRUE)
 }
9. IF (the event-generating object can be placed into a fault condition) THEN {
 IF (Event_Enable can be modified) THEN
 MAKE (Event_Enable TO-FAULT transition equal TRUE)
 IF (Event_Enable TO-FAULT transition = TRUE) THEN {
 MAKE (the event-triggering object change to a fault condition)
 BEFORE Notification Fail Time
 RECEIVE ConfirmedEventNotification-Request,
 'Process Identifier' = (any valid process ID),
 'Initiating Device Identifier' = IUT,
 'Event Object Identifier' = (the event-generating object configured for this test),
 'Time Stamp' = (any valid time stamp),
 'Notification Class' = (the class corresponding to the object being tested),
 'Priority' = (the value configured to correspond to a TO-FAULT transition),
 'Event Type' = (IF (Protocol_Revision < 13) THEN
 (any valid event type),
 ELSE
 CHANGE_OF_RELIABILITY),
 'Message Text' = (optional, any valid message text),
 'Notify Type' = EVENT | ALARM,
 'AckRequired' = TRUE | FALSE,
 'From State' = NORMAL,
 'To State' = FAULT,
 'Event Values' = (values appropriate to the event type)
 }

```

TRANSMIT BACnet-SimpleACK-PDU
VERIFY pCurrentState = FAULT
MAKE (the event-generating object change to a normal condition)
BEFORE Notification Fail Time
  RECEIVE ConfirmedEventNotification-Request,
    'Process Identifier' =      (any valid process ID),
    'Initiating Device Identifier' = IUT,
    'Event Object Identifier' = (the event-generating object configured for this test),
    'Time Stamp' =             (any valid time stamp),
    'Notification Class' =      (the class corresponding to the object being tested),
    'Priority' =                (the value configured to correspond to a TO-NORMAL transition),
    'Event Type' =             (IF (Protocol_Revision < 13) THEN
                                (any valid event type),
                                ELSE
                                  CHANGE_OF_RELIABILITY),
    'Message Text' =           (optional, any valid message text),
    'Notify Type' =            EVENT | ALARM,
    'AckRequired' =            TRUE | FALSE,
    'From State' =             FAULT,
    'To State' =               NORMAL,
    'Event Values' =           (values appropriate to the event type)
  TRANSMIT BACnet-SimpleACK-PDU
  VERIFY pCurrentState = NORMAL
}
}
10. IF (Event_Enable can be modified) THEN
  MAKE (Event_Enable TO-FAULT transition equal FALSE)
11. IF (Event_Enable TO-FAULT transition = FALSE) THEN {
  MAKE (the event-triggering object change to a fault condition)
  VERIFY pCurrentState = FAULT
  CHECK (verify that the IUT did not transmit an event notification message)
  MAKE (the event-triggering object change to a normal condition)
}

```

Notes to Tester: The UnconfirmedEventNotification service may be substituted for the ConfirmedEventNotification service, in which case the TD shall skip all of the steps in which a BACnet-SimpleACK-PDU is sent.

7.3.1.11 Acked_Transitions Tests

Purpose: To verify that the Acked_Transitions property tracks whether or not an acknowledgment has been received for a previously issued event notification. It also verifies the interrelationship between Status_Flags and Event_State.

Test Concept: The IUT is configured such that the Event_Enable property indicates that all event transitions are to trigger an event notification. The Acked_Transitions property shall have the value (TRUE, TRUE, TRUE) indicating that all previous transitions have been acknowledged. Each event transition is triggered and the Acked_Transitions property is monitored to verify that the appropriate bit is cleared when a notification message is transmitted and reset if an acknowledgment is received.

Configuration Requirements: The Event_Enable and Acked_Transitions properties shall be configured with a value of (TRUE, TRUE, TRUE). For analog objects the Limit_Enable property shall be configured with the value (TRUE, TRUE). The referenced event-triggering property shall be set to a value that results in a NORMAL condition. The value of the Transitions parameter for all recipients shall be (TRUE, TRUE, TRUE).

Test Steps:

1. VERIFY pCurrentState = NORMAL
2. VERIFY Acked_Transitions = (TRUE, TRUE, TRUE)

3. IF (Protocol_Revision is present AND Protocol_Revision $\geq$ 13) THEN
 VERIFY pStatusFlags = (FALSE, FALSE, ?, ?)
4. IF (pMonitoredValue is writable) THEN
 WRITE pMonitoredValue = (a value that is OFFNORMAL)
 ELSE
 MAKE (pMonitoredValue have a value that is OFFNORMAL)
5. WAIT (pTimeDelay)
6. BEFORE **Notification Fail Time**
 RECEIVE ConfirmedEventNotification-Request,
 'Process Identifier' = (PI1: any valid process ID),
 'Initiating Device Identifier' = IUT,
 'Event Object Identifier' = (the event-generating object configured for this test),
 'Time Stamp' = (Toffnormal: any valid time stamp),
 'Notification Class' = (the class corresponding to the object being tested),
 'Priority' = (Poffnormal: the value configured to correspond to a TO-OFFNORMAL transition),
 'Event Type' = (any valid event type),
 'Message Text' = (optional, any valid message text),
 'Notify Type' = (the notify type configured for this event),
 'AckRequired' = TRUE,
 'From State' = NORMAL,
 'To State' = OFFNORMAL,
 'Event Values' = (values appropriate to the event type)
7. TRANSMIT BACnet-SimpleACK-PDU
8. VERIFY pCurrentState = OFFNORMAL
9. VERIFY Acked_Transitions = (FALSE, TRUE, TRUE)
10. IF (Protocol_Revision is present AND Protocol_Revision $\geq$ 13) THEN
 VERIFY pStatusFlags = (TRUE, FALSE, ?, ?)
11. IF (pMonitoredValue is writable) THEN
 WRITE pMonitoredValue = (a value that is NORMAL)
 ELSE
 MAKE (pMonitoredValue have a value that is NORMAL)
12. WAIT (pTimeDelayNormal)
13. BEFORE **Notification Fail Time**
 RECEIVE ConfirmedEventNotification-Request,
 'Process Identifier' = (PI2: any valid process ID),
 'Initiating Device Identifier' = IUT,
 'Event Object Identifier' = (the event-generating object configured for this test),
 'Time Stamp' = (Tnormal: any valid time stamp),
 'Notification Class' = (the class corresponding to the object being tested),
 'Priority' = (Pnormal: the value configured to correspond to a TO-NORMAL transition),
 'Event Type' = (any valid event type),
 'Message Text' = (optional, any valid message text),
 'Notify Type' = (the notify type configured for this event),
 'AckRequired' = TRUE,
 'From State' = OFFNORMAL,
 'To State' = NORMAL,
 'Event Values' = (values appropriate to the event type)
14. TRANSMIT BACnet-SimpleACK-PDU
15. VERIFY pCurrentState = NORMAL
16. VERIFY Acked_Transitions = (FALSE, TRUE, FALSE)
17. IF (Protocol_Revision is present AND Protocol_Revision $\geq$ 13) THEN
 VERIFY pStatusFlags = (FALSE, FALSE, ?, ?)
18. IF (the event-triggering object can be placed into a fault condition) THEN {
 MAKE (a condition exist that will cause the object to generate a TO_FAULT transition)

BEFORE Notification Fail Time

RECEIVE ConfirmedEventNotification-Request,

'Process Identifier' = (PI3: any valid process ID),
 'Initiating Device Identifier' = IUT,
 'Event Object Identifier' = (the event-generating object configured for this test),
 'Time Stamp' = (Tfault: any valid time stamp),
 'Notification Class' = (the class corresponding to the object being tested),
 'Priority' = (Pfault: the value configured to correspond to a TO-FAULT transition),
 'Event Type' = IF (Protocol_Revision < 13) THEN
 (any valid event type)
 ELSE
 CHANGE_OF_RELIABILITY),
 'Message Text' = (optional, any valid message text),
 'Notify Type' = (the notify type configured for this event),
 'AckRequired' = TRUE,
 'From State' = NORMAL,
 'To State' = FAULT,
 'Event Values' = (values appropriate to the event type)

TRANSMIT BACnet-SimpleACK-PDU

VERIFY pCurrentState = FAULT

VERIFY Acked_Transitions = (FALSE, FALSE, FALSE)

TRANSMIT AcknowledgeAlarm-Request,

'Acknowledging Process Identifier' = (PI3),
 'Event Object Identifier' = (the event-generating object configured for this test),
 'Event State Acknowledged' = FAULT,
 'Acknowledgement Source' = (a character string),
 'Time Stamp' = (Tfault),
 'Time of Acknowledgment' = (the TD's current time)

RECEIVE BACnet-SimpleACK-PDU

IF (Protocol_Revision is present AND Protocol_Revision ≥ 1) THEN

BEFORE Notification Fail Time

RECEIVE ConfirmedEventNotification-Request,

'Process Identifier' = (PI3),
 'Initiating Device Identifier' = IUT,
 'Event Object Identifier' = (the event-generating object configured for this test),
 'Time Stamp' = (Tfault),
 'Notification Class' = (the class corresponding to the object being tested),
 'Priority' = (Pfault),
 'Event Type' = IF (Protocol_Revision < 13)
 (any valid event type)
 ELSE
 CHANGE_OF_RELIABILITY,
 'Message Text' = (optional, any valid message text),
 'Notify Type' = ACK_NOTIFICATION,
 'To State' = FAULT

ELSE

BEFORE Notification Fail Time

RECEIVE ConfirmedEventNotification-Request,

'Process Identifier' = (PI3),
 'Initiating Device Identifier' = IUT,
 'Event Object Identifier' = (the event-generating object configured for this test),
 'Time Stamp' = (Tfault),
 'Notification Class' = (the class corresponding to the object being tested),
 'Priority' = (Pfault),
 'Event Type' = (any valid event type),
 'Message Text' = (optional, any valid message text),

```

        'Notify Type' =                ACK_NOTIFICATION
        TRANSMIT BACnet-SimpleACK-PDU
        VERIFY Acked_Transitions = (FALSE, TRUE, FALSE)
    }
19. TRANSMIT AcknowledgeAlarm-Request,
    'Acknowledging Process Identifier' =    (PI2),
    'Event Object Identifier' =            (the event-generating object configured for this test),
    'Event State Acknowledged' =          NORMAL,
    'Time Stamp' =                        (Tnormal),
    'Acknowledgement Source' =            (a character string),
    'Time of Acknowledgment' =            (the TD's current time)
20. RECEIVE BACnet-SimpleACK-PDU
21. IF (Protocol_Revision is present AND Protocol_Revision ≥ 1) THEN
    BEFORE Notification Fail Time
        RECEIVE ConfirmedEventNotification-Request,
        'Process Identifier' =            (PI2),
        'Initiating Device Identifier' =    IUT,
        'Event Object Identifier' =        (the event-generating object configured for this test),
        'Time Stamp' =                    (Tnormal),
        'Notification Class' =            (the class corresponding to the object being tested),
        'Priority' =                      (Pnormal),
        'Event Type' =                    (any valid event type),
        'Message Text' =                  (optional, any valid message text),
        'Notify Type' =                  ACK_NOTIFICATION,
        'To State' =                      NORMAL
    ELSE
        BEFORE Notification Fail Time
            RECEIVE ConfirmedEventNotification-Request,
            'Process Identifier' =          (PI2),
            'Initiating Device Identifier' = IUT,
            'Event Object Identifier' =    (the event-generating object configured for this test),
            'Time Stamp' =                (Tnormal),
            'Notification Class' =        (the class corresponding to the object being tested),
            'Priority' =                  (Pnormal),
            'Event Type' =                (any valid event type),
            'Message Text' =              (optional, any valid message text),
            'Notify Type' =              ACK_NOTIFICATION
22. TRANSMIT BACnet-SimpleACK-PDU
23. VERIFY Acked_Transitions = (FALSE, TRUE, TRUE)
24. TRANSMIT AcknowledgeAlarm-Request,
    'Acknowledging Process Identifier' =    (PI1),
    'Event Object Identifier' =            (the event-generating object configured for this test),
    'Event State Acknowledged' =          OFFNORMAL,
    'Time Stamp' =                        (Toffnormal),
    'Acknowledgement Source' =            (a character string),
    'Time of Acknowledgment' =            (the TD's current time)
25. RECEIVE BACnet-SimpleACK-PDU
26. IF (Protocol_Revision is present AND Protocol_Revision ≥ 1) THEN
    BEFORE Notification Fail Time
        RECEIVE ConfirmedEventNotification-Request,
        'Process Identifier' =            (PI1),
        'Initiating Device Identifier' =    IUT,
        'Event Object Identifier' =        (the event-generating object configured for this test),
        'Time Stamp' =                    (Toffnormal),
        'Notification Class' =            (the class corresponding to the object being tested),
        'Priority' =                      (Poffnormal),

```

'Event Type' =	(any valid event type),
'Message Text' =	(optional, any valid message text),
'Notify Type' =	ACK_NOTIFICATION,
'To State' =	OFFNORMAL

ELSE

BEFORE Notification Fail Time

RECEIVE ConfirmedEventNotification-Request,

'Process Identifier' =	(PII),
'Initiating Device Identifier' =	IUT,
'Event Object Identifier' =	(the event-generating object configured for this test),
'Time Stamp' =	(Toffnormal),
'Notification Class' =	(the class corresponding to the object being tested),
'Priority' =	(Poffnormal),
'Event Type' =	(any valid event type),
'Message Text' =	(optional, any valid message text),
'Notify Type' =	ACK_NOTIFICATION

27. TRANSMIT BACnet-SimpleACK-PDU

28. VERIFY Acked_Transitions = (TRUE, TRUE, TRUE)

Notes to Tester: The UnconfirmedEventNotification service may be substituted for the ConfirmedEventNotification service, in which case the TD shall skip all of the steps in which a BACnet-SimpleACK-PDU is sent.

7.3.1.12 Notify_Type Test

Purpose: To verify that the value of the Notify_Type property determines whether an event notification is transmitted as an alarm or as an event.

Configuration Requirements: The IUT shall be configured with two event-generation objects, E1 and E2. Object E1 shall be configured with a Notify_Type of ALARM and E2 shall be configured with a Notify_Type of EVENT. The value of the Transitions parameter for all recipients shall be (TRUE, TRUE, TRUE)

In the test description below X1 and X2 are used to designate the pMonitoredValue algorithm parameter linked to E1 and E2 respectively. X1 and X2 shall be set to a value that results in a NORMAL condition of E1 and E2, respectively.

Test Steps:

1. VERIFY (E1), pCurrentState = NORMAL
2. VERIFY (E2), pCurrentState = NORMAL
3. WAIT (pTimeDelay + **Notification Fail Time**)
4. IF (X1 is writable) THEN
 - WRITE X1 = (a value that will cause a transition in E1)
- ELSE
 - MAKE (X1 a value that will cause a transition in E1)
5. IF (the transition is not a FAULT transition) THEN
 - IF (the transition is a TO-OFFNORMAL transition) THEN
 - WAIT (pTimeDelay)
 - ELSE
 - WAIT (pTimeDelayNormal)
6. **BEFORE Notification Fail Time**
 - RECEIVE ConfirmedEventNotification-Request,

'Process Identifier' =	(any valid process ID),
'Initiating Device Identifier' =	IUT,
'Event Object Identifier' =	(E1),
'Time Stamp' =	(any valid time stamp),
'Notification Class' =	(the class corresponding to the object being tested),
'Priority' =	(any valid value),
'Event Type' =	(any valid event type),