

DIN EN IEC 61757-2-1



ICS 33.180.99

Einsprüche bis 2021-08-04

Entwurf

**Lichtwellenleistersensoren –
Teil 2-1: Temperaturmessung –
Temperatursensoren auf der Basis von Faser-Bragg-Gittern
(IEC 86C/1702/CDV:2021);
Englische Fassung prEN IEC 61757-2-1:2021**

Fibre Optic Sensors –
Part 2-1: Temperature measurement –
Temperature sensors based on fibre Bragg gratings
(IEC 86C/1702/CDV:2021);
English version prEN IEC 61757-2-1:2021

Capteurs fibroniques –
Partie 2-1: Mesure de la température –
Capteurs de température basés sur des réseaux de Bragg à fibres
(IEC 86C/1702/CDV:2021);
Version anglaise prEN IEC 61757-2-1:2021

Anwendungswarnvermerk

Dieser Norm-Entwurf mit Erscheinungsdatum 2021-06-04 wird der Öffentlichkeit zur Prüfung und Stellungnahme vorgelegt.

Weil die beabsichtigte Norm von der vorliegenden Fassung abweichen kann, ist die Anwendung dieses Entwurfs besonders zu vereinbaren.

Stellungnahmen werden erbeten

- vorzugsweise online im Norm-Entwurfs-Portal von DIN unter www.din.de/go/entwuerfe bzw. für Norm-Entwürfe der DKE auch im Norm-Entwurfs-Portal der DKE unter www.entwuerfe.normenbibliothek.de, sofern dort wiedergegeben;
- oder als Datei per E-Mail an dke@vde.com möglichst in Form einer Tabelle. Die Vorlage dieser Tabelle kann im Internet unter www.din.de/go/stellungnahmen-norm-entwuerfe oder für Stellungnahmen zu Norm-Entwürfen der DKE unter www.dke.de/stellungnahme abgerufen werden;
- oder in Papierform an die DKE Deutsche Kommission Elektrotechnik Elektronik Informationstechnik in DIN und VDE oder Stresemannallee 15, 60596 Frankfurt am Main.

Die Empfänger dieses Norm-Entwurfs werden gebeten, mit ihren Kommentaren jegliche relevanten Patentrechte, die sie kennen, mitzuteilen und unterstützende Dokumentationen zur Verfügung zu stellen.

Gesamtumfang 37 Seiten

DKE Deutsche Kommission Elektrotechnik Elektronik Informationstechnik in DIN und VDE

Nationales Vorwort

Die Englische Fassung des europäischen Dokuments prEN IEC 61757-2-1:2021-01 „Lichtwellenleitersensoren – Teil 2-1: Temperaturmessung – Temperatursensoren auf der Basis von Faser-Bragg-Gittern“ (Entwurf in der Umfrage) ist unverändert in diesen Norm-Entwurf übernommen worden.

Die Internationale Elektrotechnische Kommission (IEC) und das Europäische Komitee für Elektrotechnische Normung (CENELEC) haben vereinbart, dass ein auf IEC-Ebene erarbeiteter Entwurf für eine Internationale Norm zeitgleich (parallel) bei IEC und CENELEC zur Umfrage (CDV-Stadium) und Abstimmung als FDIS (en: Final Draft International Standard) bzw. Schluss-Entwurf für eine Europäische Norm gestellt wird, um eine Beschleunigung und Straffung der Normungsarbeit zu erreichen. Dem entsprechend ist das internationale Dokument IEC 86C/1702/CDV:2021-01 „Fibre Optic Sensors – Part 2-1: Temperature measurement – Temperature sensors based on fibre Bragg gratings“ unverändert in den Entwurf prEN IEC 61757-2-1:2021-01 übernommen worden.

Das internationale Dokument wurde vom IEC/SC 86C „Fibre optic systems and active devices“ der Internationalen Elektrotechnischen Kommission (IEC) erarbeitet und unterliegt dem Copyright der IEC . Das Dokument wurde den nationalen Komitees zur Stellungnahme vorgelegt.

Bei der Abstimmung zu dem Europäischen Schluss-Entwurf bei CENELEC und dem Internationalen Schluss-Entwurf bei IEC [Final Draft International Standard (FDIS)] sind jeweils nur „JA/NEIN“-Entscheidungen möglich, wobei „NEIN“-Entscheidungen fundiert begründet werden müssen. Dokumente, die bei CENELEC als Europäische Norm angenommen und ratifiziert werden, sind unverändert als Deutsche Normen zu übernehmen.

Für dieses Dokument ist das nationale Arbeitsgremium DKE/UK 412.2 „Komponenten für Kommunikationskabelanlagen“ der DKE Deutsche Kommission Elektrotechnik Elektronik Informationstechnik in DIN und VDE (www.dke.de) zuständig.

Aktuelle Informationen zu diesem Dokument können über die Internetseiten von DKE (www.dke.de) und DIN (www.din.de) durch eine Suche nach der Dokumentennummer aufgerufen werden.

Dieses Dokument enthält unter Berücksichtigung des Beschlusses des Technischen Beirats Internationale und Nationale Koordinierung (TBINK) der DKE vom 17.09.2020 nur die englische Fassung von IEC 86C/1702/CDV:2021.

Für den Fall einer undatierten Verweisung im normativen Text (Verweisung auf ein Dokument ohne Angabe des Ausgabedatums und ohne Hinweis auf eine Abschnittsnummer, eine Tabelle, ein Bild usw.) bezieht sich die Verweisung auf die jeweils aktuellste Ausgabe des in Bezug genommenen Dokuments.

Für den Fall einer datierten Verweisung im normativen Text bezieht sich die Verweisung immer auf die in Bezug genommene Ausgabe des Dokuments.

Der Zusammenhang der zitierten Dokumente mit den entsprechenden deutschen Dokumenten ergibt sich, soweit ein Zusammenhang besteht, grundsätzlich über die Nummer der entsprechenden IEC-Publikation. Beispiel: IEC 60068 ist als EN 60068 als Europäische Norm durch CENELEC übernommen und als DIN EN 60068 ins Deutsche Normenwerk aufgenommen.

Es wird auf die Möglichkeit hingewiesen, dass einige Elemente dieses Dokuments Patentrechte berühren können. IEC ist nicht dafür verantwortlich, einige oder alle diesbezüglichen Patentrechte zu identifizieren.

Das Original-Dokument enthält Bilder in Farbe, die in der Papierversion in einer Graustufen-Darstellung wiedergegeben werden. Elektronische Versionen dieses Dokuments enthalten die Bilder in der originalen Farbdarstellung.

Content

	Page
INTRODUCTION	6
1 Scope	7
2 Normative references	7
3 Terms, definitions and abbreviated terms	7
3.1 Terms and definitions	7
3.2 Abbreviated terms	11
3.3 Quantity symbols	11
4 Design and characteristics of a FBG temperature sensor	12
4.1 Fibre Bragg grating (FBG)	12
4.2 Dependence of Bragg wavelength on temperature	12
4.3 Design features	13
5 Performance parameters	14
6 Test apparatuses for performance parameter determination	14
6.1 Temperature calibration equipment	14
6.2 Optical spectrum analyser and interrogator	15
6.3 Broadband light source	15
7 Test procedures of performance parameters	15
7.1 Sample preparation and test set-up	15
7.2 Bragg wavelength λ_{Bref}	16
7.2.1 Measuring procedure	16
7.2.2 Evaluation	17
7.2.3 Reporting	17
7.3 FBG peak spectral width	17
7.3.1 Measuring procedure	17
7.3.2 Evaluation	17
7.3.3 Reporting	17
7.4 FBG reflectivity	17
7.4.1 Measuring procedure	17
7.4.2 Evaluation	17
7.4.3 Reporting	18
7.5 Side-lobe suppression ratio	18
7.5.1 Measuring procedure	18
7.5.2 Evaluation	18
7.5.3 Reporting	19
7.6 Signal-to-noise ratio	19
7.6.1 Measuring procedure	19
7.6.2 Evaluation	19
7.6.3 Reporting	20

7.7	Characteristic curve	20
7.7.1	Measuring procedure.....	20
7.7.2	Evaluation	21
7.7.3	Reporting	26
7.8	Thermal time constant	26
7.8.1	Measuring procedure.....	26
7.8.2	Evaluation	27
7.8.3	Reporting	27
7.9	Sensor stability	27
7.9.1	Measuring procedure.....	27
7.9.2	Evaluation	28
7.9.3	Reporting	28
Anhang A (informative) Blank detail specification		29
A.1	General	29
A.2	Mechanical and optical set-up	29
A.3	Operational characteristics	29
A.4	Limiting parameters	29
A.5	Further information given upon request	30
Annex B (informative) Examples of specific temperature calibration equipment		31
B.1	Simple liquid bath	31
B.2	Liquid tube-thermostat.....	31
B.3	Solid state calibration equipment	33
Annex C (informative) Contributions to measurement uncertainty		36
Bibliography		37

Tables

Table 1 – Calibration bath fluids	15
---	----

Figures

Figure 1 – Principal test set-up for FBG sensor	16
Figure 2 – Determination of the FBG reflectivity from the reflection spectrum (left) and transmission spectrum (right)	18
Figure 3 – Side-lobes in the case of a single FBG temperature sensor	19
Figure 4 – Signal-to-noise ratio determination.....	20
Figure 5 – Example of a polynomial fit of calibration points $\lambda_{B,i}(T_{N,i})$	22
Figure 6 – Example of a third-order polynomial fit.....	24
Figure 7 – Example of a fourth-order polynomial fit.....	25
Figure 8 – Example of a polynomial fit of the sensitivity	26
Figure 9 – Typical response time curve.....	27
Figure B.1 – Schematic representation of a simple liquid bath	31

Figure B.2 – Schematic representation of liquid calibration device for connection to laboratory liquid thermostats.....	32
Figure B.3 – Schematic representation of a long-tube fluid calibration device	33
Figure B.4 – Schematic representation of a solid-state calibration device for higher temperatures	34
Figure B.5 – Schematic representation of a block calibrator for calibrating an FBG temperature sensor at higher temperatures	35

INTRODUCTION

This document is based on guideline VDI/VDE 2660 Blatt 2:2020-04 „Technical temperature measurement – Optical temperature sensor based on fibre Bragg gratings – Recommendation on temperature measurement and statement of measurement uncertainty” [1]. It was prepared in cooperation with VDI/VDE-GMA Technical Committee 2.17 „Fibre optic measurement techniques”. Unless otherwise stated, all figures in this standard have been taken from the aforementioned document in original or modified form.

Fibre Optic Sensors – Part 2-1: Temperature measurement – Temperature sensors based on fibre Bragg gratings

1 Scope

This part of the IEC 61757 series specifies terminology, characteristic performance parameters and related test methods of optical temperature sensors based on fibre Bragg gratings (FBG) carrying out temperature measurements in the temperature range between -260 °C and 600 °C.

Generic specifications for fibre optic sensors are defined in IEC 61757.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60050 (all parts), *International Electrotechnical Vocabulary*

IEC 61757:2018, *Fibre optic sensors – Generic specification*

IEC 61757-1-1:2020, *Fibre optic sensors – Part 1-1: Strain measurement – Strain sensors based on fibre Bragg gratings*

ISO/IEC GUIDE 98-3, *Uncertainty of measurement – Part 3: Guide to the expression of uncertainty in measurement (GUM:1995)*

3 Terms, definitions and abbreviated terms

For the purposes of this document, terms and definitions given in IEC 61757:2018, IEC 61757-1-1:2020, IEC 60050 (all parts), and the following apply.

ISO and IEC maintain terminological databases for use in standardization at the following addresses:

- IEC Electropedia: available at <http://www.electropedia.org/>
- ISO Online browsing platform: available at <http://www.iso.org/obp>

3.1 Terms and definitions

3.1.1

Bragg wavelength under reference conditions

λ_{Bref}

wavelength of maximal reflectance or minimal transmittance of a mechanically stress-free fibre Bragg grating at reference or standard temperature conditions, without the effect of a temperature change

Note 1 to entry: The term Bragg wavelength λ_{B} specified in the data sheet of the manufacturer of a fibre Bragg grating normally describes the Bragg wavelength without further details on reference or standard temperature conditions.

[SOURCE: IEC 61757-1-1:2020, modified — transformed to temperature sensing]

3.1.2

birefringence

optical property of the directional dependence of the index of refraction of an optically anisotropic material having orientation-dependent refractive indices that leads to different propagation velocities of light in different propagation and polarization directions

Note 1 to entry: In fibre optic sensors terminology, the term "birefringence" is mainly applied when optical waveguides with birefringence properties, such as panda or bow-tie fibres, are used. Birefringence in fibre Bragg gratings becomes important only when polarized light is used for the measurement. Because of the properties of fibre Bragg gratings, this can lead to an additional systematic increase in the measurement uncertainty.

[SOURCE: IEC 61757-1-1:2020, clarified and Note modified]

3.1.3

drift

shift of the characteristic curve (rarely also change of the characteristic curve parameters) under the same measuring and operating conditions or reference conditions due to material aging or/and mechanical and/or thermal continuous or alternating stress

3.1.4

dynamic measurement deviation

$\Delta T(t)$

time-dependent thermal measurement deviation resulting from time-varying differences between sensor temperature $T_S(t)$ and temperature of the medium $T_M(t)$ with

$$\Delta T(t) = T_S(t) - T_M(t) \quad (1)$$

3.1.5

FBG peak

reflection peak or transmission minimum in the Bragg grating reflectance or transmittance spectrum

Note 1 to entry: Maximum peak value is typically at the Bragg wavelength λ_B .

3.1.6

FBG peak spectral width

full width at half maximum (FWHM) of the FBG peak

Note 1 to entry: Full width at half maximum of the FBG peak is the wavelength range of the spectrum for which the amplitude is greater than 50 % (3 dB).

[SOURCE: IEC 61757-1-1:2020, modified – transformed for temperature sensor]

3.1.7

FBG period

Λ

distance between the periodically changing refractive index zones (grating planes) in an optical waveguide having effective refractive index n_{eff}

Note 1 to entry: The FBG period defines the Bragg wavelength λ_B through the equation

$$\Lambda = \frac{k \cdot \lambda_B}{2 \cdot n_{\text{eff}}} \quad \text{for } k = \text{positive integer} \quad (2)$$

[SOURCE: IEC 61757-1-1:2020, definition extended]

3.1.8

FBG temperature sensor

fibre optic sensor that uses a fibre Bragg grating as a sensitive element for temperature measurements

Note 1 to entry: FBG temperature sensors can be used in series configuration with multiple gratings allowing to perform distributed measurements.

3.1.9

FBG temperature sensing system

measurement set-up consisting of one or more serial arranged FBG temperature sensors connected to an interrogation unit consisting of light source, detector module, processor, data archive, and user interface

Note 1 to entry: A FBG temperature sensing system works in principal like follows: After light from the light source is sent into the fibre and partially reflected or transmitted by the FBG temperature sensor, it is guided to the detector module of the interrogator, which determines the FBG peak wavelength. From a shift of the FBG peak wavelength caused by temperature change, the temperature change can be quantitatively determined in measuring units.

3.1.10

maximum operating temperature

highest value of temperature at which the FBG temperature sensor meets specified performance

3.1.11

minimum operating temperature

lowest value of temperature at which the FBG temperature sensor meets specified performance

3.1.12

minimum bending radius

minimum radius at which a FBG temperature sensor is bent without change of the specified performance parameters

Note 1 to entry: This value may differ from the minimum bending radius given for transport and storage.

[SOURCE: IEC 61757-1-1:2020, modified – transformed for temperature sensor]

3.1.13

parasitic strain effect

non-thermally induced deformation of the fibre Bragg grating during temperature measurement resulting in a change in the wavelength response of the FBG

Note 1 to entry: A non-rateable deformation of the FBG during temperature measurement occurs as an apparent temperature change in the response signal and shall therefore be excluded or assessable.

3.1.14

reference wavelength

λ_{ref}

wavelength response of a fibre Bragg grating to which a specific temperature T_{ref} value is referred

Note 1 to entry: Depending on the evaluation method, the interrogator devices of the sensor often emit different wavelengths to determine the filter function of the Bragg grating. The reference wavelength is not necessarily equal to the Bragg wavelength λ_B . However, because of the small difference between reference wavelength and Bragg wavelength, both wavelengths can be used in Equations (6) to (8) and in Equations (16) to (20) without relevant errors occurring.

[SOURCE: IEC 61757-1-1:2020, modified – transformed to temperature sensing]

3.1.15

reference wavelength at reference temperature

$\lambda_{T_{\text{ref}}}$

Bragg wavelength of the fibre Bragg grating for a specified reference temperature T_{ref} not equal to 0 °C

3.1.16

reference wavelength at 0 °C

$\lambda_{T_{\text{ref}},0}$

Bragg wavelength of the fibre Bragg grating at reference temperature $T_0 = 0$ °C

3.1.17

response time

t_R

time after which the difference between the sensor temperature $T_S(t)$ and the temperature of the medium T_M is smaller than a meaningful defined fraction δ of the initial temperature difference $T_S(0) - T_M$, as described by Equation (3)

$$T_S(t_R) - T_M = \delta [T_S(0) - T_M] \quad (3)$$

3.1.18

sensitive area of FBG temperature sensor

length of the fibre Bragg grating that is sensitive to the temperature to be measured and thereby changes the wavelength response of the fibre Bragg grating

3.1.19

side-lobe suppression ratio

R_{SLS}

ratio of the intensity of the FBG peak to the nearest largest side-lobe expressed in dB

3.1.20

sensor stability

ability of the FBG temperature sensor to keep its performance characteristics under specified limits within in a specified time interval, all other conditions being the same

[SOURCE: VIM 5.14, modified – transformed for temperature sensor]

3.1.21

static thermal measurement deviation

ΔT_{th}

time-invariant temperature difference in steady state between sensor temperature $T_S(t)$ and the temperature of the medium T_M

$$\Delta T_{\text{th}} = T_S(t) - T_M \text{ for } t \rightarrow \infty \quad (4)$$

3.1.22

temperature sensitivity

$S(T)$

ratio of the wavelength change $\Delta \lambda_T$ of a FBG temperature sensor caused by a temperature change ΔT in steady state, which is the temperature-dependent slope of the characteristic curve $\lambda_T(T)$ expressed in m/K

$$S(T) = \frac{\Delta \lambda_T}{\Delta T} \quad (5)$$

Note 1 to entry: The unit can also be pm/K or nm/K.

3.1.23

operating temperature range

interval for which the FBG temperature sensor under specified conditions is able to perform temperature measurements in accordance with specified performance

3.1.24

thermal time constant

τ

t_{63}

time it takes a FBG temperature sensor to reach 63,2 % of the total difference between the initial and the final medium or body temperature when subjected to a step-like change in temperature under defined conditions

Note 1 to entry: In many industrial applications, the thermal time constant is also provided for 50 % of the total temperature difference and for 90 % of the total temperature difference, so as to characterize the dynamic behaviour of the temperature sensor. The dynamic response of some surface temperature sensors, like jacketed thermocouples with measuring point at the temperature sensor bottom and similar approaches, does not follow an exponential function but is rather characterized by an initial rapid rise in temperature and a subsequent slow creep to the final value. For these temperature sensors, the thermal time constant is also specified for 95 % and 99 % of the total temperature difference.

3.1.25

thermal measurement deviation

time-dependent difference between the sensor temperature $T_S(t)$ and the originally to be measured temperature of the measuring medium or body $T_M(t)$

Note 1 to entry: For $t \rightarrow \infty$, the thermal measurement deviation is equal to static thermal measurement deviation.

3.2 Abbreviated terms

ASE	amplified spontaneous emission
FBG	fibre Bragg grating
ITS-90	international temperature scale of 1990
OSA	optical spectrum analyser

3.3 Quantity symbols

k	number of order (mathematical description)
ΔL	length change of the Bragg grating due to external load in fibre direction
n	index of refraction
n_{eff}	effective index of refraction (of the Bragg grating)
P_0	incident optical power
P_{SL}	optical power of the nearest side-lobe
P_{λ_B}	optical power of the FBG at λ_B
R_{FBG}	FBG reflectivity
R_{SLS}	side-lobe suppression ratio expressed in dB
SNR_{FBG}	FBG signal-to-noise ratio
$S(T)$	temperature sensitivity in m/K
T	temperature in °C
T_0	reference temperature for $T = 0$ °C, at which the FBG has the reference wavelength λ_0 in °C
T_B	reference temperature (freely selectable) in °C
T_M	actual temperature of the medium/measuring object to be measured in °C
T_N	actual temperature provided by the standard thermometer
T_{ref}	defined reference temperature at which the FBG has the reference wavelength λ_{ref} in °C
T_s	output signal of the temperature sensor (measured temperature) in °C

$T_s(0)$	output signal of the temperature sensor at an abrupt change of the temperature of the measuring body or medium in °C
ΔT_{th}	static thermal measurement deviation in K
x_i	i -th measured value
α	coefficient of thermal expansion in 1/K
δ	part of the initial temperature difference, which has appropriately to be determined according to the uncertainty of measurement in K
σ	mechanical stress
ε	strain applied to the temperature sensor (always considered in direction of the fibre axis)
p_ε	effective photo-elastic (stress-optical) constant
λ_0	reference wavelength for $T = 0$ °C in m
λ_B	Bragg wavelength in m
λ_{FBG0}	reference wavelength of the FBG of a temperature sensor at $T = 0$ °C in m
λ_{Bref}	Bragg wavelength under reference conditions, mechanically stress-free operated at a specified reference temperature in m
λ_{ref}	reference wavelength in m
$\lambda_{Tref,0}$	Bragg wavelength of the FBG at reference temperature $T_0 = 0$ °C
λ_{Tref}	Bragg wavelength of the FBG at reference specified temperature $T_{ref} \neq 0$ °C
Λ	FBG period
τ, t_{63}	thermal time constant
ζ	thermo-optic coefficient

4 Design and characteristics of a FBG temperature sensor

4.1 Fibre Bragg grating (FBG)

A detailed description of the structure, function, principle characteristics and manufacturing process of a FBG is provided in IEC 61757-1-1.

4.2 Dependence of Bragg wavelength on temperature

As explained in IEC 61757-1-1, the change of the Bragg wavelength caused by a change in grating temperature can be described by Equation (6).

$$\Delta\lambda_B = 2 \cdot \left(\Lambda \frac{\partial n_{eff}}{\partial L} + n_{eff} \frac{\partial \Lambda}{\partial L} \right) \cdot \Delta L + 2 \cdot \left(\Lambda \frac{\partial n_{eff}}{\partial T} + n_{eff} \frac{\partial \Lambda}{\partial T} \right) \cdot \Delta T \quad (6)$$

where

$\Delta\lambda_B$	is the Bragg wavelength shift;
T	is the temperature;
ΔT	is the temperature difference
n_{eff}	is the effective index of refraction (of the Bragg grating);
ΔL	is the change of length of the Bragg grating due to external load in fibre direction;
Λ	is the FBG period.