

INTERNATIONAL STANDARD

NORME INTERNATIONALE



**Industrial communication networks – Fieldbus specifications –
Part 4-2: Data-link layer protocol specification – Type 2 elements**

**Réseaux de communication industriels – Spécifications de bus de terrain –
Partie 4-2: Spécification du protocole de la couche de liaison de données –
Éléments de Type 2**



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2010 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester.

If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de la CEI ou du Comité national de la CEI du pays du demandeur.

Si vous avez des questions sur le copyright de la CEI ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de la CEI de votre pays de résidence.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
Fax: +41 22 919 03 00
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

Useful links:

IEC publications search - www.iec.ch/searchpub

The advanced search enables you to find IEC publications by a variety of criteria (reference number, text, technical committee,...).

It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available on-line and also once a month by email.

Electropedia - www.electropedia.org

The world's leading online dictionary of electronic and electrical terms containing more than 30 000 terms and definitions in English and French, with equivalent terms in additional languages. Also known as the International Electrotechnical Vocabulary (IEV) on-line.

Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: csc@iec.ch.

A propos de la CEI

La Commission Electrotechnique Internationale (CEI) est la première organisation mondiale qui élabore et publie des Normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

A propos des publications CEI

Le contenu technique des publications de la CEI est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

Liens utiles:

Recherche de publications CEI - www.iec.ch/searchpub

La recherche avancée vous permet de trouver des publications CEI en utilisant différents critères (numéro de référence, texte, comité d'études,...).

Elle donne aussi des informations sur les projets et les publications remplacées ou retirées.

Just Published CEI - webstore.iec.ch/justpublished

Restez informé sur les nouvelles publications de la CEI. Just Published détaille les nouvelles publications parues. Disponible en ligne et aussi une fois par mois par email.

Electropedia - www.electropedia.org

Le premier dictionnaire en ligne au monde de termes électroniques et électriques. Il contient plus de 30 000 termes et définitions en anglais et en français, ainsi que les termes équivalents dans les langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International (VEI) en ligne.

Service Clients - webstore.iec.ch/csc

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions contactez-nous: csc@iec.ch.

INTERNATIONAL STANDARD

NORME INTERNATIONALE



**Industrial communication networks – Fieldbus specifications –
Part 4-2: Application layer protocol specification – Type 2 elements**

**Réseaux de communication industriels – Spécifications des bus de terrain –
Partie 4-2: Spécification de protocole de la couche application – Éléments de
Type 2**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

COMMISSION
ELECTROTECHNIQUE
INTERNATIONALE

PRICE CODE
CODE PRIX

XH

ICS 25.040.40; 35.100.20; 35.110

ISBN 978-2-83220-126-8

Warning! Make sure that you obtained this publication from an authorized distributor.

Attention! Veuillez vous assurer que vous avez obtenu cette publication via un distributeur agréé.

CONTENTS

FOREWORD.....	9
INTRODUCTION.....	11
1 Scope.....	13
1.1 General.....	13
1.2 Specifications.....	13
1.3 Procedures.....	13
1.4 Applicability.....	14
1.5 Conformance.....	14
2 Normative references.....	14
3 Terms, definitions, symbols and abbreviations.....	15
3.1 Reference model terms and definitions.....	15
3.2 Service convention terms and definitions.....	17
3.3 Common terms and definitions.....	18
3.4 Additional Type 2 definitions.....	20
3.5 Type 2 symbols and abbreviations.....	27
4 Overview of the data-link protocol.....	28
4.1 General.....	28
4.2 Services provided by the DL.....	30
4.3 Structure and definition of DL-addresses.....	31
4.4 Services assumed from the PhL.....	33
4.5 Functional classes.....	36
5 General structure and encoding of PhIDUs and DLPDUs and related elements of procedure.....	36
5.1 Overview.....	36
5.2 Media access procedure.....	36
5.3 DLPDU structure and encoding.....	40
5.4 Lpacket components.....	44
5.5 DLPDU procedures.....	46
5.6 Summary of DLL support services and objects.....	47
6 Specific DLPDU structure, encoding and procedures.....	49
6.1 Modeling language.....	49
6.2 DLS user services.....	51
6.3 Generic tag Lpacket.....	57
6.4 Moderator Lpacket.....	58
6.5 Time distribution Lpacket.....	59
6.6 UCMM Lpacket.....	61
6.7 Keeper UCMM Lpacket.....	62
6.8 TUI Lpacket.....	62
6.9 Link parameters Lpacket and tMinus Lpacket.....	63
6.10 I'm-alive Lpacket.....	65
6.11 Ping Lpackets.....	66
6.12 WAMI Lpacket.....	68
6.13 Debug Lpacket.....	68
6.14 IP Lpacket.....	69
6.15 Ethernet Lpacket.....	69
7 Objects for station management.....	71

7.1	General	69
7.2	ControlNet object	70
7.3	Keeper object	80
7.4	Scheduling object	102
7.5	TCP/IP Interface object	113
7.6	Ethernet link object	122
7.7	DeviceNet object	130
7.8	Connection configuration object (CCO)	139
7.9	DLR object	159
7.10	QoS object	168
8	Other DLE elements of procedure	170
8.1	Network attachment monitor (NAM)	170
8.2	Calculating link parameters	177
9	Detailed specification of DL components	185
9.1	General	185
9.2	Access control machine (ACM)	185
9.3	TxLLC	202
9.4	RxLLC	206
9.5	Transmit machine (TxM)	209
9.6	Receive machine (RxM)	212
9.7	Serializer	218
9.8	Deserializer	219
9.9	DLL management	220
10	Device Level Ring (DLR) protocol	222
10.1	General	222
10.2	Supported topologies	222
10.3	Overview of DLR operation	224
10.4	Classes of DLR implementation	226
10.5	DLR behavior	227
10.6	Implementation requirements	232
10.7	Using non-DLR nodes in the ring network	234
10.8	DLR messages	237
10.9	State diagrams and state-event-action matrices	241
10.10	Performance analysis	262
Annex A	(normative) Indicators and switches	267
Bibliography		280
Figure 1	– Relationships of DLSAPs, DLSAP-addresses and group DL-addresses	19
Figure 2	– Data-link layer internal architecture	29
Figure 3	– Basic structure of a MAC ID address	31
Figure 4	– Basic structure of a generic tag address	32
Figure 5	– Basic structure of a fixed tag address	32
Figure 6	– M_symbols and Manchester encoding at 5 MHz	34
Figure 7	– NUT structure	37
Figure 8	– Media access during scheduled time	38
Figure 9	– Media access during unscheduled time	39
Figure 10	– DLPDU format	41

Figure 11 – Aborting a DLPDU during transmission	43
Figure 12 – Lpacket format	44
Figure 13 – Generic tag Lpacket format	45
Figure 14 – Fixed tag Lpacket format	45
Figure 15 – Goodness parameter of TimeDist_Lpacket	60
Figure 16 – Example I'm alive processing algorithm	66
Figure 17 – Keeper CRC algorithm	87
Figure 18 – Keeper object power-up state diagram	98
Figure 19 – Keeper object operating state diagram	99
Figure 20 – Synchronized network change processing	102
Figure 21 – State transition diagram for TCP/IP Interface object	122
Figure 22 – Connection configuration object edit flowchart	159
Figure 23 – NAM state machine	171
Figure 24 – DLR rings connected to switches	223
Figure 25 – Normal operation of a DLR network	224
Figure 26 – Beacon and Announce frames	224
Figure 27 – Link failure	225
Figure 28 – Network reconfiguration after link failure	226
Figure 29 – Neighbor Check process	232
Figure 30 – Unsupported topology – example 1	236
Figure 31 – Unsupported topology – example 2	236
Figure 32 – State transition diagram for Beacon frame based non-supervisor ring node	242
Figure 33 – State transition diagram for Announce frame based non-supervisor ring node	247
Figure 34 – State transition diagram for ring supervisor	250
Figure A.1 – Non redundant network status indicator labeling	271
Figure A.2 – Redundant network status indicator labeling	272
Table 1 – Data-link layer components	29
Table 2 – MAC ID addresses allocation	32
Table 3 – Fixed tag service definitions	33
Table 4 – Data encoding rules	34
Table 5 – M Data symbols	35
Table 6 – Truth table for ph_status_indication	35
Table 7 – FCS length, polynomials and constants	41
Table 8 – DLL support services and objects	48
Table 9 – Elementary data types	51
Table 10 – DLL events	55
Table 11 – Time distribution priority	60
Table 12 – Format of the TUI Lpacket	63
Table 13 – ControlNet object class attributes	71
Table 14 – ControlNet object instance attributes	71
Table 15 – TUI status flag bits	75

Table 16 – Channel state bits	76
Table 17 – ControlNet object common services.....	78
Table 18 – ControlNet object class specific services	79
Table 19 – Keeper object revision history	81
Table 20 – Keeper object class attributes	81
Table 21 – Keeper object instance attributes	82
Table 22 – Keeper operating state definitions	84
Table 23 – Port status flag bit definitions	85
Table 24 – TUI status flag bits	86
Table 25 – Keeper attributes.....	88
Table 26 – Memory requirements (in octets) for the Keeper attributes.....	89
Table 27 – Keeper object common services	89
Table 28 – Keeper object class specific services	90
Table 29 – Service error codes	91
Table 30 – Wire order format of the TUI Lpacket.....	95
Table 31 – Service error codes	96
Table 32 – Keeper object operating states	96
Table 33 – Keeper object state event matrix	100
Table 34 – Scheduling object class attributes	103
Table 35 – Scheduling object instance attributes	104
Table 36 – Scheduling object common services	104
Table 37 – Status error descriptions for Create.....	105
Table 38 – Status error descriptions for Delete and Kick_Timer	106
Table 39 – Scheduling object class specific services	106
Table 40 – Status error descriptions for Read	108
Table 41 – Status error descriptions for Conditional_Write	109
Table 42 – Status error descriptions for Forced_Write	109
Table 43 – Status error descriptions for Change_Start.....	110
Table 44 – Status error descriptions for Break_Connections	110
Table 45 – Status error descriptions for Change_Complete.....	111
Table 46 – Status error descriptions for Restart_Connections	112
Table 47 – TCP/IP Interface object class attributes.....	113
Table 48 – TCP/IP Interface object instance attributes.....	114
Table 49 – Status bits	116
Table 50 – Configuration capability bits	116
Table 51 – Configuration control bits.....	117
Table 52 – Example path	117
Table 53 – Interface configuration components	118
Table 54 – Alloc control values	119
Table 55 – TCP/IP Interface object common services	120
Table 56 – Get_Attribute_All reply format	120
Table 57 – Ethernet link object revision history	122
Table 58 – Ethernet link object class attributes	123

Table 59 – Ethernet link object instance attributes	124
Table 60 – Interface flags bits	127
Table 61 – Control bits	128
Table 62 – Interface type	128
Table 63 – Interface state	129
Table 64 – Admin state	129
Table 65 – Ethernet Link object common services	129
Table 66 – Ethernet Link object class specific services	130
Table 67 – DeviceNet object revision history	131
Table 68 – DeviceNet object class attributes	131
Table 69 – DeviceNet object instance attributes	132
Table 70 – Bit rate attribute values	134
Table 71 – BOI attribute values	135
Table 72 – Diagnostic counters bit description	136
Table 73 – DeviceNet object common services	137
Table 74 – Reset service parameter	138
Table 75 – Reset service parameter values	138
Table 76 – DeviceNet object class specific services	138
Table 77 – Connection configuration object revision history	139
Table 78 – Connection configuration object class attributes	140
Table 79 – Format number values	141
Table 80 – Connection configuration object instance attributes	142
Table 81 – Originator connection status values	144
Table 82 – Target connection status values	145
Table 83 – Connection flags	145
Table 84 – I/O mapping formats	147
Table 85 – Connection configuration object common services	148
Table 86 – Get_Attribute_All error codes	148
Table 87 – Get_Attribute_All response	149
Table 88 – Set_Attribute_All error codes	150
Table 89 – Set_Attribute_All request	151
Table 90 – Create request parameters	152
Table 91 – Create error codes	153
Table 92 – Delete error codes	153
Table 93 – Restore error codes	153
Table 94 – Connection configuration object class specific services	154
Table 95 – Kick_Timer error codes	154
Table 96 – Open_Connection error codes	155
Table 97 – Close_Connection error codes	155
Table 98 – Stop_Connection error codes	155
Table 99 – Change_Start error codes	156
Table 100 – Get_Status service parameter	156
Table 101 – Get_Status service response	156

Table 102 – Get_Status service error codes	157
Table 103 – Change_Complete service parameter	157
Table 104 – Change_Complete service error codes	157
Table 105 – Audit_Changes service parameter	158
Table 106 – Audit_Changes service error codes	158
Table 107 – Class attributes	160
Table 108 – Instance attributes	160
Table 109 – Network Status values	162
Table 110 – Ring Supervisor Status values	163
Table 111 – DLR object common services	166
Table 112 – Get_Attributes_All Response – non supervisor device	166
Table 113 – Get_Attributes_All Response – supervisor-capable device	166
Table 114 – DLR object class specific services	167
Table 115 – QoS object revision history	168
Table 116 – QoS object class attributes	168
Table 117 – QoS object instance attributes	169
Table 118 – Default DCSP values and usages	170
Table 119 – Common services	170
Table 120 – NAM states	171
Table 121 – Default link parameters	172
Table 122 – PhL timing characteristics	178
Table 123 – DLR variables	227
Table 124 – MAC addresses for DLR messages	238
Table 125 – IEEE 802.1Q frame format	238
Table 126 – Common fields in DLR messages	238
Table 127 – Format of the Beacon frame	239
Table 128 – Ring State values	239
Table 129 – Format of the Neighbor_Check request	239
Table 130 – Format of the Neighbor_Check response	240
Table 131 – Format of the Link_Status/Neighbor_Status frame	240
Table 132 – Link/Neighbor status values	240
Table 133 – Format of the Announce frame	241
Table 134 – Format of the Sign_On frame	241
Table 135 – Parameter values for Beacon frame based non-supervisor ring node	242
Table 136 – State-event-action matrix for Beacon frame based non-supervisor ring node	243
Table 137 – Parameter values for Announce frame based non-supervisor ring node	247
Table 138 – State-event-action matrix for Announce frame based non-supervisor ring node	248
Table 139 – Parameter values for ring supervisor node	251
Table 140 – State-event-action matrix for ring supervisor node	252
Table 141 – Parameters/assumptions for example performance calculations	263
Table 142 – Example ring configuration parameters and performance	266

Table A.1 – Module status indicator	268
Table A.2 – Network status indicators	269
Table A.3 – Network status indicator	273
Table A.4 – Network status indicator	275
Table A.5 – Combined module/network status indicator	276
Table A.6 – I/O status indicator	277
Table A.7 – Bit rate switch encoding	279

Withdrawn

INTERNATIONAL ELECTROTECHNICAL COMMISSION

**INDUSTRIAL COMMUNICATION NETWORKS –
FIELDBUS SPECIFICATIONS –****Part 4-2: Data-link layer protocol specification –
Type 2 elements**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.

International Standard IEC 61158-4-2 has been prepared by subcommittee 65C: Industrial networks, of IEC technical committee 65: Industrial process measurement, control and automation.

This second edition cancels and replaces the first edition published in 2007. This edition constitutes a technical revision.

The main changes with respect to the previous edition are listed below.

- Clause 2 and Bibliography: update of normative and bibliographic references;
- subclause 3.5: update of abbreviations;
- subclause 7.6: updates of the Ethernet Link object;
- subclause 7.7: minor update of the Devicenet object (additional attribute);
- new subclauses 7.9 and 7.10: new DLR and QoS objects;
- new Clause 10: new DLR protocol.

This bilingual version (2012-07) corresponds to the monolingual English version, published in 2010-08.

The text of this standard is based on the following documents:

FDIS	Report on voting
65C/605/FDIS	65C/619/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

The French version has not been voted upon.

This publication has been drafted in accordance with ISO/IEC Directives, Part 2.

A list of all parts of the IEC 61158 series, published under the general title *Industrial communication networks – Fieldbus specifications*, can be found on the IEC web site.

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed;
- withdrawn;
- replaced by a revised edition, or
- amended.

NOTE The revision of this standard will be synchronized with the other parts of the IEC 61158 series.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION

This part of IEC 61158 is one of a series produced to facilitate the interconnection of automation system components. It is related to other standards in the set as defined by the “three-layer” fieldbus reference model described in IEC/TR 61158-1:2010.

The data-link protocol provides the data-link service by making use of the services available from the physical layer. The primary aim of this standard is to provide a set of rules for communication expressed in terms of the procedures to be carried out by peer data-link entities (DLEs) at the time of communication. These rules for communication are intended to provide a sound basis for development in order to serve a variety of purposes:

- a) as a guide for implementers and designers;
- b) for use in the testing and procurement of equipment;
- c) as part of an agreement for the admittance of systems into the open systems environment;
- d) as a refinement to the understanding of time-critical communications within OSI.

This standard is concerned, in particular, with the communication and interworking of sensors, effectors and other automation devices. By using this standard together with other standards positioned within the OSI or fieldbus reference models, otherwise incompatible systems may work together in any combination.

NOTE Use of some of the associated protocol types is restricted by their intellectual-property-right holders. In all cases, the commitment to limited release of intellectual-property-rights made by the holders of those rights permits a particular data-link layer protocol type to be used with physical layer and application layer protocols in Type combinations as specified explicitly in the IEC 61784 series. Use of the various protocol types in other combinations may require permission from their respective intellectual-property-right holders.

The International Electrotechnical Commission (IEC) draws attention to the fact that it is claimed that compliance with this document may involve the use of patents given in several subclauses as indicated in the table below. These patents are held by their respective inventors under license to ODVA, Inc:

US 5,400,331	[ODVA]	Communication network interface with screeners for incoming messages	Subclause 3.4, Clauses 4 to 9
US 5,471,461	[ODVA]	Digital communication network with a moderator station election process	
US 5,491,531	[ODVA]	Media access controller with a shared class message delivery capability	
US 5,493,571	[ODVA]	Apparatus and method for digital communications with improved delimiter detection	
US 5,537,549	[ODVA]	Communication network with time coordinated station activity by time slot and periodic interval number	
US 5,553,095	[ODVA]	Method and apparatus for exchanging different classes of data during different time intervals	
US 12/493,838	[ODVA]	Industrial controller employing the network ring topology	Clause 10

IEC takes no position concerning the evidence, validity and scope of these patent rights.

ODVA and the holders of these patent rights have assured the IEC that ODVA is willing to negotiate licences under reasonable and non-discriminatory terms and conditions with applicants throughout the world. In this respect, the statement of ODVA and the holders of these patent rights is registered with IEC. Information may be obtained from:

[ODVA] ODVA, Inc.
2370 East Stadium Boulevard #1000
Ann Arbor, Michigan 48104
USA
Attention: Office of the Executive Director
e-mail: odva@odva.org

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights other than those identified above. IEC shall not be held responsible for identifying any or all such patent rights.

ISO (www.iso.org/patents) and IEC (http://www.iec.ch/tctools/patent_decl.htm) maintain on-line data bases of patents relevant to their standards. Users are encouraged to consult the data bases for the most up to date information concerning patents.

Withdrawal

INDUSTRIAL COMMUNICATION NETWORKS – FIELDBUS SPECIFICATIONS –

Part 4-2: Data-link layer protocol specification – Type 2 elements

1 Scope

1.1 General

The data-link layer provides basic time-critical messaging communications between devices in an automation environment.

This protocol provides communication opportunities to all participating data-link entities, sequentially and in a cyclic synchronous manner. Foreground scheduled access is available for time-critical activities together with background unscheduled access for less critical activities.

Deterministic and synchronized transfers can be provided at cyclic intervals up to 1 ms and device separations of 25 km. This performance is adjustable dynamically and on-line by re-configuring the parameters of the local link whilst normal operation continues. By similar means, DL connections and new devices may be added or removed during normal operation.

This protocol provides means to maintain clock synchronization across an extended link with a precision better than 10 μ s.

This protocol optimizes each access opportunity by concatenating multiple DLSDUs and associated DLPCI into a single DLPDU, thereby improving data transfer efficiency for data-link entities that actively source multiple streams of data.

The maximum system size is an unlimited number of links of 99 nodes, each with 255 DLSAP-addresses. Each link has a maximum of 2^{24} related peer and publisher DLCEPs.

1.2 Specifications

This standard specifies

- a) procedures for the timely transfer of data and control information from one data-link user entity to a peer user entity, and among the data-link entities forming the distributed data-link service provider;
- b) the structure of the fieldbus DLPDUs used for the transfer of data and control information by the protocol of this standard, and their representation as physical interface data units.

1.3 Procedures

The procedures are defined in terms of

- a) the interactions between peer DL-entities (DLEs) through the exchange of fieldbus DLPDUs;
- b) the interactions between a DL-service (DLS) provider and a DLS-user in the same system through the exchange of DLS primitives;
- c) the interactions between a DLS-provider and a Ph-service provider in the same system through the exchange of Ph-service primitives.

1.4 Applicability

These procedures are applicable to instances of communication between systems which support time-critical communications services within the data-link layer of the OSI or fieldbus reference models, and which require the ability to interconnect in an open systems interconnection environment.

Profiles provide a simple multi-attribute means of summarizing an implementation's capabilities, and thus its applicability to various time-critical communications needs.

1.5 Conformance

This standard also specifies conformance requirements for systems implementing these procedures. This standard does not contain tests to demonstrate compliance with such requirements.

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 61131-3, *Programmable controllers – Part 3: Programming languages*

IEC 61158-3-2:2007, *Industrial communication networks – Fieldbus specifications – Part 3-2: Data-link layer service definition – Type 2 elements*

IEC 61158-5-2:2010¹, *Industrial communication networks – Fieldbus specifications – Part 5-2: Application layer service definition – Type 2 elements*

IEC 61158-6-2:2010¹, *Industrial communication networks – Fieldbus specifications – Part 6-2: Application layer protocol specification – Type 2 elements*

IEC 61588:2009, *Precision clock synchronization protocol for networked measurement and control systems*

IEC 61784-3-2, *Industrial communication networks – Profiles – Part 3-2: Functional safety fieldbuses – Additional specifications for CPF 2*

IEC 62026-3:2008, *Low-voltage switchgear and controlgear – Controller-device interfaces (CDIs) – Part 3: DeviceNet*

ISO/IEC 3309, *Information technology – Telecommunications and information exchange between systems – High-level data link control (HDLC) procedures – Frame structure*

ISO/IEC 7498-1, *Information technology – Open Systems Interconnection – Basic Reference Model: The Basic Model*

ISO/IEC 7498-3, *Information technology – Open Systems Interconnection – Basic Reference Model: Naming and addressing*

¹ To be published.

ISO/IEC 8802-3, *Information technology – Telecommunications and information exchange between systems – Local and metropolitan area networks – Specific requirements – Part 3: Carrier sense multiple access with collision detection (CSMA/CD) access method and physical layer specifications*

ISO 11898:1993², *Road vehicles – Interchange of digital information – Controller area network (CAN) for high-speed communication*

IEEE 802.1D, *IEEE standard for local and metropolitan area networks – Media Access Control (MAC) bridges*, available at <<http://www.ieee.org>>

IEEE 802.1Q, *IEEE standard for local and metropolitan area networks – Virtual bridged local area networks*, available at <<http://www.ieee.org>>

IETF RFC 1213, *Management Information Base for Network Management of TCP/IP-based internets : MIB-I*, available at <<http://www.ietf.org>>

IETF RFC 1643, *Definitions of Managed Objects for the Ethernet-like Interface Types*, available at <<http://www.ietf.org>>

3 Terms, definitions, symbols and abbreviations

For the purposes of this document, the following terms, definitions, symbols and abbreviations apply.

3.1 Reference model terms and definitions

This standard is based in part on the concepts developed in ISO/IEC 7498-1 and ISO/IEC 7498-3, and makes use of the following terms defined therein.

3.1.1	called-DL-address	[ISO/IEC 7498-3]
3.1.2	calling-DL-address	[ISO/IEC 7498-3]
3.1.3	centralized multi-end-point-connection	[ISO/IEC 7498-1]
3.1.4	correspondent (N)-entities correspondent DL-entities (N=2) correspondent Ph-entities (N=1)	[ISO/IEC 7498-1]
3.1.5	demultiplexing	[ISO/IEC 7498-1]
3.1.6	DL-address	[ISO/IEC 7498-3]
3.1.7	DL-address-mapping	[ISO/IEC 7498-1]
3.1.8	DL-connection	[ISO/IEC 7498-1]
3.1.9	DL-connection-end-point	[ISO/IEC 7498-1]
3.1.10	DL-connection-end-point-identifier	[ISO/IEC 7498-1]
3.1.11	DL-connection-mode transmission	[ISO/IEC 7498-1]
3.1.12	DL-connectionless-mode transmission	[ISO/IEC 7498-1]

² A newer edition of this standard has been published, but only the cited edition applies.

3.1.13	DL-data-sink	[ISO/IEC 7498-1]
3.1.14	DL-data-source	[ISO/IEC 7498-1]
3.1.15	DL-duplex-transmission	[ISO/IEC 7498-1]
3.1.16	DL-facility	[ISO/IEC 7498-1]
3.1.17	DL-local-view	[ISO/IEC 7498-3]
3.1.18	DL-name	[ISO/IEC 7498-3]
3.1.19	DL-protocol	[ISO/IEC 7498-1]
3.1.20	DL-protocol-connection-identifier	[ISO/IEC 7498-1]
3.1.21	DL-protocol-control-information	[ISO/IEC 7498-1]
3.1.22	DL-protocol-data-unit	[ISO/IEC 7498-1]
3.1.23	DL-protocol-version-identifier	[ISO/IEC 7498-1]
3.1.24	DL-relay	[ISO/IEC 7498-1]
3.1.25	DL-service-connection-identifier	[ISO/IEC 7498-1]
3.1.26	DL-service-data-unit	[ISO/IEC 7498-1]
3.1.27	DL-simplex-transmission	[ISO/IEC 7498-1]
3.1.28	DL-subsystem	[ISO/IEC 7498-1]
3.1.29	DL-user-data	[ISO/IEC 7498-1]
3.1.30	flow control	[ISO/IEC 7498-1]
3.1.31	layer-management	[ISO/IEC 7498-1]
3.1.32	multiplexing	[ISO/IEC 7498-3]
3.1.33	naming-(addressing)-authority	[ISO/IEC 7498-3]
3.1.34	naming-(addressing)-domain	[ISO/IEC 7498-3]
3.1.35	naming-(addressing)-subdomain	[ISO/IEC 7498-3]
3.1.36	(N)-entity DL-entity Ph-entity	[ISO/IEC 7498-1]
3.1.37	(N)-interface-data-unit DL-service-data-unit (N=2) Ph-interface-data-unit (N=1)	[ISO/IEC 7498-1]
3.1.38	(N)-layer DL-layer (N=2) Ph-layer (N=1)	[ISO/IEC 7498-1]
3.1.39	(N)-service DL-service (N=2) Ph-service (N=1)	[ISO/IEC 7498-1]

3.1.40	(N)-service-access-point DL-service-access-point (N=2) Ph-service-access-point (N=1)	[ISO/IEC 7498-1]
3.1.41	(N)-service-access-point-address DL-service-access-point-address (N=2) Ph-service-access-point-address (N=1)	[ISO/IEC 7498-1]
3.1.42	peer-entities	[ISO/IEC 7498-1]
3.1.43	Ph-interface-control-information	[ISO/IEC 7498-1]
3.1.44	Ph-interface-data	[ISO/IEC 7498-1]
3.1.45	primitive name	[ISO/IEC 7498-3]
3.1.46	reassembling	[ISO/IEC 7498-1]
3.1.47	recombining	[ISO/IEC 7498-1]
3.1.48	reset	[ISO/IEC 7498-1]
3.1.49	responding-DL-address	[ISO/IEC 7498-3]
3.1.50	routing	[ISO/IEC 7498-1]
3.1.51	segmenting	[ISO/IEC 7498-1]
3.1.52	sequencing	[ISO/IEC 7498-1]
3.1.53	splitting	[ISO/IEC 7498-1]
3.1.54	synonymous name	[ISO/IEC 7498-3]
3.1.55	systems-management	[ISO/IEC 7498-1]

3.2 Service convention terms and definitions

This standard also makes use of the following terms defined in ISO/IEC 10731 as they apply to the data-link layer:

3.2.1	acceptor
3.2.2	asymmetrical service
3.2.3	confirm (primitive); requestor.deliver (primitive)
3.2.4	deliver (primitive)
3.2.5	DL-confirmed-facility
3.2.6	DL-facility
3.2.7	DL-local-view
3.2.8	DL-mandatory-facility
3.2.9	DL-non-confirmed-facility
3.2.10	DL-provider-initiated-facility
3.2.11	DL-provider-optional-facility

- 3.2.12 DL-service-primitive;
primitive**
- 3.2.13 DL-service-provider**
- 3.2.14 DL-service-user**
- 3.2.15 DL-user-optional-facility**
- 3.2.16 indication (primitive)
acceptor.deliver (primitive)**
- 3.2.17 multi-peer**
- 3.2.18 request (primitive);
requestor.submit (primitive)**
- 3.2.19 requestor**
- 3.2.20 response (primitive);
acceptor.submit (primitive)**
- 3.2.21 submit (primitive)**
- 3.2.22 symmetrical service**


3.3 Common terms and definitions

NOTE Many definitions are common to more than one protocol Type; they are not necessarily used by all protocol Types.

3.3.1

DL-segment, link, local link

single DL-subnetwork in which any of the connected DLEs may communicate directly, without any intervening DL-relaying, whenever all of those DLEs that are participating in an instance of communication are simultaneously attentive to the DL-subnetwork during the period(s) of attempted communication



NOTE 1 DLSAPs and PhSAPs are depicted as ovals spanning the boundary between two adjacent layers.

NOTE 2 DL-addresses are depicted as designating small gaps (points of access) in the DLL portion of a DLSAP.

NOTE 3 A single DL-entity may have multiple DLSAP-addresses and group DL-addresses associated with a single DLSAP.

Figure 1 – Relationships of DLSAPs, DLSAP-addresses and group DL-addresses

3.3.2 DLSAP

distinctive point at which DL-services are provided by a single DL-entity to a single higher-layer entity.

NOTE This definition, derived from ISO/IEC 7498-1, is repeated here to facilitate understanding of the critical distinction between DLSAPs and their DL-addresses. (See Figure 1.)

3.3.3 DL(SAP)-address

either an individual DLSAP-address, designating a single DLSAP of a single DLS-user, or a group DL-address potentially designating multiple DLSAPs, each of a single DLS-user.

NOTE This terminology is chosen because ISO/IEC 7498-3 does not permit the use of the term DLSAP-address to designate more than a single DLSAP at a single DLS-user

3.3.4 (individual) DLSAP-address

DL-address that designates only one DLSAP within the extended link

NOTE A single DL-entity may have multiple DLSAP-addresses associated with a single DLSAP.

3.3.5 extended link

DL-subnetwork, consisting of the maximal set of links interconnected by DL-relays, sharing a single DL-name (DL-address) space, in which any of the connected DL-entities may communicate, one with another, either directly or with the assistance of one or more of those intervening DL-relay entities

NOTE An extended link may be composed of just a single link.

3.3.6

frame

denigrated synonym for DLPDU

3.3.7

group DL-address

DL-address that potentially designates more than one DLSAP within the extended link. A single DL-entity may have multiple group DL-addresses associated with a single DLSAP. A single DL-entity also may have a single group DL-address associated with more than one DLSAP

3.3.8

node

single DL-entity as it appears on one local link

3.3.9

receiving DLS-user

DL-service user that acts as a recipient of DL-user-data

NOTE A DL-service user can be concurrently both a sending and receiving DLS-user.

3.3.10

sending DLS-user

DL-service user that acts as a source of DL-user-data

3.4 Additional Type 2 definitions

3.4.1

actual packet interval

API

measure of how frequently a specific connection produces its Lpacket data

3.4.2

allocate

take a resource from a common area and assign that resource for the exclusive use of a specific entity

3.4.3

application

function or data structure for which data is consumed or produced

3.4.4

application objects

multiple object classes that manage and provide the run time exchange of messages across the network and within the device

3.4.5

attribute

description of an externally visible characteristic or feature of an object

NOTE The attributes of an object contain information about variable portions of an object. Typically, they provide status information or govern the operation of an object. Attributes may also affect the behavior of an object. Attributes are divided into class attributes and instance attributes.

3.4.6

behavior

indication of how the object responds to particular events. Its description includes the relationship between attribute values and services

3.4.7**bit**

unit of information consisting of a 1 or a 0. This is the smallest data unit that can be transmitted

3.4.8**blanking or blanking time**

length of time required after transmitting before the node is allowed to receive

3.4.9**client**

- 1) An object which uses the services of another (server) object to perform a task
- 2) An initiator of a message to which a server reacts

3.4.10**communication objects**

components that manage and provide run time exchange of messages across the network such as the ControlNet object, the Unconnected Message Manager (UCMM)

3.4.11**connection**

logical binding between two application objects within the same or different devices

3.4.12**connection ID****CID**

identifier assigned to a transmission, associated with a particular connection between producers and consumers, that identifies a specific piece of application information

NOTE Within the data link, this is a generic tag.

3.4.13**cyclic redundancy check****CRC**

residual value computed from an array of data and used as a representative signature for the array

3.4.14**cyclic**

term used to describe events which repeat in a regular and repetitive manner

3.4.15**deafness**

situation where the node can not hear the moderator DLPDU but can hear other link traffic

3.4.16**device**

physical hardware connection to the link

NOTE A device may contain more than one node.

3.4.17**DLPDU**

data-link protocol data unit

NOTE A DLPDU consists of a source MAC ID, zero or more Lpackets and an FCS as transmitted or received by an associated PhE.

3.4.18

end delimiter

unique set of M_symbols that identifies the end of a DLPDU

3.4.19

error

discrepancy between a computed, observed or measured value or condition and the specified or theoretically correct value or condition

3.4.20

extended link

links connected by DL-routers (sometimes called a local area network)

3.4.21

FCS error

error that occurs when the computed frame check sequence value after reception of all the octets in a DLPDU does not match the expected residual

3.4.22

fixed tag

two octet identifier (tag) which identifies a specific service to be performed by either

- a) that receiving node on the local link which has a specified MAC ID, or
- b) all receiving nodes on the local link

NOTE Identification of the target node(s) is included in the two octet tag

3.4.23

frame

denigrated synonym for DLPDU

3.4.24

Frame Check Sequence

FCS

redundant data derived from a block of data within a DLPDU (frame), using a hash function, and stored or transmitted together with the block of data, in order to detect data corruption

3.4.25

generic tag

three octet identifier (tag) which identifies a specific piece of application information

3.4.26

guardband

time slot allocated for the transmission of the moderator DLPDU

3.4.27

implicit token

mechanism that governs the right to transmit

NOTE No actual token message is transmitted on the medium. Each node keeps track of the MAC ID of the node that it believes currently holds the right to transmit. The right to transmit is passed from node to node by keeping a record of the node that last transmitted. A slot time is used to allow a missing node to be skipped in the rotation

3.4.28

implicit token register

register that contains the MAC ID of the node that holds the right to transmit

3.4.29**instance**

actual physical occurrence of an object within a class, identifying one of many objects within the same object class

EXAMPLE California is an instance of the object class state.

NOTE The terms object, instance, and object instance are used to refer to a specific instance.

3.4.30**instance attribute**

attribute that is unique to an object instance and not shared by the object class

3.4.31**instantiated**

object that has been created in a device

3.4.32**Keeper**

object responsible for distributing link configuration data to all nodes on the link

3.4.33**link**

collection of nodes with unique MAC IDs, attached to Ph-segments connected by Ph-repeaters

3.4.34**little endian**

model of memory organization which stores the least significant octet at the lowest address, and of transmission organization which transfers the least significant octet first on the medium

3.4.35**Lpacket**

well-defined sub-portion of a DLPDU consisting of

- a) size and control information
- b) a fixed tag or a generic tag, and
- c) DLS-user data or, when the tag has DL-significance, DL-data

3.4.36**M_symbol(s)**

symbols that represent the data bits and related information encoded and transmitted by the PhL

3.4.37**maximum scheduled node**

node with highest MAC ID that can use scheduled time on a link

3.4.38**maximum unscheduled node**

node with highest MAC ID that can use unscheduled time on a link

3.4.39**Message Router**

object within a node that distributes messaging requests to the appropriate application objects

3.4.40**moderator**

node with the lowest MAC ID that is responsible for transmitting the moderator DLPDU

3.4.41

moderator DLPDU

DLPDU transmitted by the node with the lowest MAC ID for the purpose of synchronizing the nodes and distributing the link configuration parameters

3.4.42

multipoint connection

connection from one node to many

NOTE Multipoint connections allow messages from a single producer (publisher) to be received by many consumer (subscriber) nodes.

3.4.43

network

series of nodes connected by some type of communication medium. The connection paths between any pair of nodes can include repeaters, routers and gateways

3.4.44

network access monitor

NAM

component within a node that manages communication with a temporary node connected to the nodes local NAP

3.4.45

network access port

NAP

PhL variant that allows a temporary node to be connected to the link by connection to the NAP of a permanent node

3.4.46

network address or node address

node's address on the link (also called MAC ID)

3.4.47

network status indicators

indicators on a node indicating the status of the Physical and Data Link Layers

3.4.48

network update time

NUT

repetitive time interval in which data can be sent on the link

3.4.49

node

logical connection to a local link, requiring a single MAC ID

NOTE A single physical device may appear as many nodes on the same local link. For the purposes of this protocol, each node is considered to be a separate DLE.

3.4.50

non-concurrence

situation where a transmission is received from an unexpected MAC ID, which appears to violate the time based access protocol

NOTE This may occur when a connection is made between two working links that are not synchronized with each other but who have the same configuration information.

3.4.51

non-data symbol

PhL symbol which violates the requirements of Manchester biphase L encoding

3.4.52**object**

abstract representation of a particular component within a device

NOTE An object can be

- 1) an abstract representation of a computer's capabilities. Objects can be composed of any or all of the following components:
 - a) data (information which changes with time);
 - b) configuration (parameters for behavior);
 - c) methods (things that can be done using data and configuration).
- 2) a collection of related data (in the form of variables) and methods (procedures) for operating on that data that have clearly defined interface and behavior.

3.4.53**object specific service**

service defined by a particular object class to perform a required function which is not performed by a common service

NOTE An object specific service is unique to the object class which defines it.

3.4.54**originator**

client responsible for establishing a connection path to the target

3.4.55**permanent node**

node whose connection to the network does not utilize the network access port (NAP) PhL variant

NOTE This node may optionally support a NAP PhL variant to allow temporary nodes to connect to the network

3.4.56**produce**

act of sending data to be received by a consumer

3.4.57**producer**

node that is responsible for sending data

3.4.58**redundant media**

system using more than one medium to help prevent communication failures

3.4.59**requested packet interval****RPI**

measure of how frequently the originating application requires the transmission of Lpackets or data packets from the target application

3.4.60**rogue**

node that has received a moderator DLPDU that disagrees with the link configuration currently used by this node

3.4.61**scheduled**

data transfers that occur in a deterministic and repeatable manner on predefined NUTs

3.4.62

server

object which provides services to another (client) object

3.4.63

service

operation or function than an object and/or object class performs upon request from another object and/or object class

NOTE A set of common services is defined and provisions for the definition of object-specific services are provided. Object-specific services are those which are defined by a particular object class to perform a required function which is not performed by a common service.

3.4.64

slot time

maximum time required for detecting an expected transmission

NOTE Each node waits a slot time for each missing node during the implied token pass

3.4.65

start delimiter

unique set of M_symbols that identifies the beginning of a DLPDU

3.4.66

supernode

DLE with a MAC ID of zero

NOTE This DLE DL-address is reserved for special DLL functions

3.4.67

table unique identifier

TUI

unique reference code used by ControlNet and Keeper objects to reference a consistent set of link configuration attribute

3.4.68

tag

shorthand name for a specific piece of application information, two or three octets in length

3.4.69

target

end-node to which a connection is established

3.4.70

temporary node

same as transient node

3.4.71

tMinus

number of NUTs before a new set of link configuration parameters are to be used

3.4.72

tone

instant of time which marks the boundary between two NUTs

3.4.73

tool

executable software program which interacts with the user to perform some function

EXAMPLE Link scheduling software (LSS).

3.4.74**transaction id**

field within a UCMM header that matches a response with the associated request, which a server echoes in the response message

3.4.75**transient node**

node that is only intended to be connected to the network on a temporary basis using the NAP PhL medium connected to the NAP of a permanent node

3.4.76**Unconnected Message Manager****UCMM**

component within a node that transmits and receives unconnected explicit messages and sends them directly to the Message Router object

3.4.77**unconnected service**

messaging service which does not rely on the set up of a connection between devices before allowing information exchanges

3.4.78**unscheduled**

data transfers that use the remaining allocated time in the NUT after the scheduled transfers have been completed

3.4.79**vendor ID**

identification of each product manufacturer/vendor by a unique number

NOTE Vendor IDs are assigned by ODVA, Inc.

3.5 Type 2 symbols and abbreviations

ACM	Access control machine	
CA	Clock accuracy	
CAN	Controller area network	[ISO 11898:1993]
COP	Connection originator password	
DLR	Device level ring	
DSCP	DiffServ code point	
FCS	Frame Check Sequence	
IP	Internet Protocol	[IETF RFC 791]
LED	Light emitting diode.	
LSS	Link scheduling software	
MAC ID	MAC address of a node	
MSTP	Multiple spanning tree protocol	[IEEE 802.1Q]
NAM	Network attachment monitor	
NAP	Network access port	
ND	Non-data symbol	
NUT	Network update time	
PT	Programming terminal (a temporary network connection)	
QoS	Quality of service	
Rcv	Receive	
RPI	Requested Lpacket interval	

RSTP	Rapid spanning tree protocol	[IEEE 802.1D]
Rx	Receive	
RxLLC	Receive logical link control	
RxM	Receive machine	
SEM	State event matrix	
SMAX	MAC ID of the maximum scheduled node	
STD	State transition diagram, used to describe object behavior	
STP	Spanning tree protocol	[IEEE 802.1D]
TCP	Terminal Control Protocol	[IETF RFC 793]
TUI	Table unique identifier	
Tx	Transmit	
TxLLC	Transmit logical link control	
TxM	Transmit machine	
UCCM	Unconnected Message Manager	
UMAX	MAC ID of maximum unscheduled node	
USR	Unscheduled start register	

4 Overview of the data-link protocol

4.1 General

4.1.1 DLL architecture

The Type 2 DLL is modeled as an integrated Access Control Machine (ACM), with scheduling support functions, designed for reliable and efficient support of higher-level connection-mode and connectionless data transfer services. Interoperating with these higher level functions are DLL management functions.

PhL framing and delimiters are managed by DLL functions for serializing and deserializing M_symbol requests and indications.

Within the Data Link Layer, the Access Control Machine (ACM) has the primary responsibility for detecting and recovering from network disruptions. The major objectives of the ACM are


- to make sure that the local node detects and fully utilizes its assigned access slots in the schedule;
- to make sure that the local node does not interfere with the transmissions of other nodes, especially the moderator node;
- to start the next NUT (see 4.1.2) on schedule, whether the moderator DLPDU is heard or not;
- if the local node is the moderator, to transmit each moderator DLPDU strictly on schedule.

The Data Link Layer is comprised of the components listed in Table 1 :

Table 1 – Data-link layer components

Components	Description
Access Control Machine (ACM)	receives and transmits control DLPDUs and header information, and determines the timing and duration of transmissions.
Transmit LLC (TxLLC)	buffers DLSDUs received from Station Management and the DLS-user, and determines which should be transmitted next.
Receive LLC (RxLLC)	performs the task of quarantining received link units until they are validated by a good FCS.
Transmit Machine (TxM)	receives requests to send DLPDU headers and trailers, and Lpackets from the ACM, and breaks them down into octet symbol requests that are sent to the Serializer.
Receive Machine (RxM)	assembles received Lpackets from octet symbols received from the Deserializer, and submits them to the RxLLC.
Serializer	receives octet symbols, encodes and serializes them, and sends them as M_symbols to the PhL. It is also responsible for generating the FCS.
Deserializer	receives M_symbols from the PhL, converts M_symbols into octets and sends them to the receive machine. It is also responsible for checking the FCS.
DLL Management Interface	holds the Station Management variables that belong to the DLL, and helps manage synchronized changes of the link parameters.

The internal arrangement of these components, and their interfaces, are shown in Figure 2. The arrowheads illustrate the primary direction of flow of data and control.

**Figure 2 – Data-link layer internal architecture**

4.1.2 Access control machine (ACM) and scheduling support functions

The ACM functions schedule all communication from one DLE to another. The timing of this communication are regulated at two levels,

- 1) to provide an accurate time based distribution of scheduled opportunities for designated communications in accord with, and with a pre-established schedule for, the local link and any extended network of links.
- 2) to provide a democratic distribution of unscheduled opportunities for arbitrary communications, generally in a cyclic but asynchronous manner.

Accurate schedule timing as provided by 1) is very important to support many control and data collection tasks in the applications domain of this protocol. The schedule is based on a fixed, repetitive time cycle called network update time (NUT). The NUT is maintained in close synchronism among all nodes participating in the DLL and used to provide two types of access opportunity;

- 1) One opportunity for each active station to transfer one scheduled DLPDU containing multiple scheduled DLSDUs.

NOTE 1 Only DLSDUs with scheduled as their QoS parameter may be included in a scheduled DLPDU.

NOTE 2 DLSDUs with scheduled as their QoS parameter are usually connection mode transfers with generic as their tag parameter.

- 2) One opportunity for at least one active station to send one background (unscheduled) DLPDU containing multiple DLSDUs of any QoS type. If time is available within a NUT, one background MAC opportunity is offered to each other active station in order of their MAC ID address. The station MAC ID for the first background opportunity in each NUT, is incremented (+1 modulo the set of background addresses) for each successive NUT to democratically share the available time among active stations.

Support procedures are included for automatic transfer to backup scheduling services and to manage the use of redundant Ph media.

4.1.3 Connection-mode, connectionless-mode data transfer and DL service

The connection mode, connectionless mode and DL services provide the necessary functionality for

- managing DL provider interactions with the DL user by converting request and response primitives into necessary DLE operations and generating indications and confirm primitives where appropriate,
- determination of the DL address and control information to be added to each DLSDU,
- local confirmation of status for each outgoing DLSDU,
- DLPDU formation by concatenation of multiple DL user DLSDUs for efficient transfer as single PhPDUs, subject to DLPDU size limitations, QoS parameters and the type of access opportunity.

4.2 Services provided by the DL

4.2.1 Overview

The DLL provides connectionless data transfer services and connection-mode data transfer services for limited-size DLSDUs, an internally synchronized time service, scheduling services to control the time allocation of the underlying shared PhL service, a DL(SAP)-address and queue management service, and a packing/unpacking service that combines multiple DLSDUs into a single data transfer DLPDU for efficient use of each access opportunity.

4.2.2 QoS

4.2.2.1 Definition

The QoS parameter specifies priority options for DLSDUs and access opportunities. The available values are as follows:

4.2.2.2 DLL scheduled priority

The scheduled priority QoS provides accurate time based cyclic and acyclic sending of DLSDUs. The execution timing for this fieldbus scheduled service can be accurate and repeatable to better than 1 ms. Scheduled priority is normally used with connected mode services.

NOTE The master Keeper is responsible for regular publication of a unique table identifier (TUI) which ensures all nodes have a reference for the current set of link operating parameters. This TUI publication uses a fixed tag and is sent with QoS priority set to scheduled.

4.2.2.3 DLL high priority (unscheduled)

The high priority QoS provides acyclic sending of DLSDUs with a bounded upper time for the sending delay. Data on this priority is sent only when all scheduled data has been sent and a non-scheduled sending opportunity is available.

4.2.2.4 DLL low priority (unscheduled)

The low priority QoS provides for sending of DLSDUs only on an as-available basis. Data on this priority is sent only when all other data priorities have been sent and a non-scheduled sending opportunity is available.

NOTE High and Low priority are used only in a local sense to set the order of servicing among locally submitted, unscheduled DLS-user-data.

4.3 Structure and definition of DL-addresses

4.3.1 General

DL-addresses are used as MAC ID addresses (Link node designators), Fixed tag addresses (DLSAP-addresses and group DL-addresses), and Generic tag addresses (DLCEP-addresses).

This subclause defines the form and structure of DL-addresses and includes specific definitions for some standard DL-addresses.

All addresses are formed of octets. Each octet shall be transferred to the Ph layer low-bit first and multiple octets shall be transferred low-order octet first (little endian format).

Three types of DL addresses are used.

4.3.2 MAC ID address

MAC ID addresses identify physical nodes on the local link as shown in Figure 3.

Permitted values are within the range 0–99, values from 100–254 are reserved.

MAC ID
1 octet

Figure 3 – Basic structure of a MAC ID address

Table 2 specifies the use of MAC ID addresses.

Table 2 – MAC ID addresses allocation

MAC ID	Meaning and purpose
0x0	temporary address used for maintenance
SMAX	current maximum address value for Scheduled access opportunities. SMAX ≤ UMAX
UMAX	current maximum address value for Unscheduled access opportunities SMAX. ≤ UMAX ≤ 0x63
0x64 to 0xFE	reserved
0xFF	broadcast address to all MAC ID nodes on this link

4.3.3 Generic tag address

Generic tag addresses types identify all data transfers for connected mode services. The available capacity in the DLL is 3 octets, see Figure 4.

Generic tag
3 octets

Figure 4 – Basic structure of a generic tag address

NOTE 1 Generic tags are used to send connected DLSDUs and may be associated with any of the available QoS priorities (Scheduled, High, Low).

NOTE 2 Negotiation and management of generic tags and connected mode services are the responsibility of the DL user.

4.3.4 Fixed tag address

Fixed tag addresses types identify DLSDUs within a designated station MAC ID. They are used with all data transfers for connectionless mode services.

NOTE Fixed tags are used to send connectionless DLSDUs and are usually associated with unscheduled QoS priorities (High, Low). Typical uses of fixed tags are for station management and to establish connections.

Each fixed tag address shall consist of two octets as shown in Figure 5.

Fixed tag service	Destination MAC ID
1 octet	1 octet

Figure 5 – Basic structure of a fixed tag address

The first octet shall specify the service access point in the destination node as specified in Table 3. The second octet shall be the address of the destination node. The destination address shall be either a MAC ID or 0xFF, which indicates the broadcast address to all MAC IDs on the local link.

Table 3 – Fixed tag service definitions

Fixed tag service	Meaning
0x00	moderator
0x01 - 0x08	vendor specific
0x09	ping request
0x0A – 0x14	vendor specific
0x15	tMinus
0x16 - 0x28	vendor specific
0x29	ping reply
0x2A - 0x3F	vendor specific
0x40 - 0x6F	reserved
0x70 – 0x7F	vendor-specific
0x80	I'm alive
0x81	link parameters
0x82	reserved
0x83	UCMM
0x84	TUI
0x85	IP (reserved for Internet Protocol)
0x86	WAMI
0x87	reserved
0x88	Keeper UCMM
0x89	Ethernet (used for address resolution protocol)
0x8A - 0x8B	reserved
0x8C	Time distribution
0x8D - 0x8F	reserved for time distribution
0x90	debug
0x91 - 0xCF	reserved
0xD0 - 0xEF	group addresses
0xF0 - 0xFF	vendor specific

Fixed tags in the range 0xD0 to 0xEF shall be reserved to permit group screening of connection identifiers.

4.4 Services assumed from the PhL

4.4.1 General requirements

The following subclauses include requirements for interface to a Type 2 PhL that are not required for other Types.

- Transmit Machine.
- Receive Machine.
- Serializer.
- Deserializer.

This is necessary because the Ph-Interface Data Units (PhIDUs) that Type 2 passes across the DLL–PhL interface are individual serial data and non-data symbols, designated on the DLE side as M_Symbols (see Table 4), whereas PhIDUs for other Types are not conceptualized in this way. As a consequence, a Type 2 Data Link Layer requires a Type 2 PhL.

4.4.2 Data encoding rules

The M_Symbols transferred at the DLL to PhL interface are of four types designated 0, 1, +, -. They will be encoded inside the PhL into appropriate Ph_Symbols as shown in Table 4. The M_0 and M_1 will be encoded into Ph_Symbols that represent Manchester biphas L data encoding rules. The M_ND symbols are non-data symbols to allow for the creation of unique data patterns used for start and end delimiters. The example of signal voltage waveform as it might be applied to an electrically-conductive medium is shown in an idealized form in Figure 6 to provide an example of the data encoding rules shown in Table 4.

Table 4 – Data encoding rules

Data bits (common name)	M_Symbol representation	Ph_Symbol encoding	Manchester encoded
data “zero”	M_0 or {0}	{L,H}	0
data “one”	M_1 or {1}	{H,L}	1
“non_data+”	M_ND+ or {+}	{H,H}	no data
“non_data-”	M_ND- or {-}	{L,L}	no data




Figure 6 – M_symbols and Manchester encoding at 5 MHz

4.4.3 DLL to PhL interface

4.4.3.1 General

The DLL to PhL interface need not be exposed in the implementation of any PhL variant. This interface may be internal to the node. If conformance to the DLL to PhL interface is claimed, it shall conform to the requirements of this clause.

4.4.3.2 Ph_lock_indication

ph_lock_indication shall provide an indication of either data lock or Ph_Symbol synchronization by the PhL. Valid states for ph_lock_indication shall be true and false. ph_lock_indication shall be true whenever valid Ph_Symbols are present at the PhL interface and the PhL to DLL interface timing of M_Symbols conforms to the PhL requirements. It shall be false between frames (when no Ph_Symbols are present on the medium) or whenever data synchronization is lost or the timing fails to conform to the PhL requirements. ph_lock_indication shall be true prior to the beginning of the start delimiter.

4.4.3.3 Ph_frame_indication

ph_frame_indication shall provide an indication of a valid data frame from the PhL. Valid states for ph_frame_indication shall be true and false. ph_frame_indication shall be true upon ph_lock_indication = true and reception of the first valid start delimiter. ph_frame_indication shall be false at reception of next M_ND symbol (following the start delimiter) or ph_lock_indication = false.

NOTE This signal provides octet synchronization to the DLL.

4.4.3.4 Ph_carrier_indication

ph_carrier_indication shall represent the presence of a signal carrier on the medium. The ph_carrier_indication shall be true if internal PhL identification of signal carrier has been true during any of the last 4 M_symbol times and it shall be false otherwise.

4.4.3.5 Ph_data_indication

ph_data_indication shall represent the M_Symbols that are decoded from the PhL internal representations such as those shown in Table 4. Valid M_symbols shall be M_0 {0}, M_1 {1}, M_ND+ {+}, and M_ND- {-} as shown in Table 5.

Table 5 – M Data symbols

Data bits (common name)	M_Symbol representation
data “zero”	M_0 or {0}
data “one”	M_1 or {1}
“non_data+”	M_ND+ or {+}
“non_data-”	M_ND- or {-}

The ph_data_indication shall represent the M_Symbols as decoded within the PhL whenever ph_lock_indication is true.

4.4.3.6 Ph_status_indication

ph_status_indication shall represent the delimiter status of the frame which was received from the PhL as shown in Table 6. Valid symbols shall be Normal, Abort, and Invalid. ph_status_indication shall indicate Normal after reception of a frame (ph_frame_indication = true) composed of a start delimiter, valid data (no M_ND symbols) and an end delimiter. ph_status_indication shall indicate Abort after reception of a frame (ph_frame_indication = true) composed of a start delimiter, valid data, and a second start delimiter. ph_status_indication shall indicate Invalid after reception of a frame (ph_frame_indication = true) composed of a start delimiter and the detection of any M_ND symbol which was not part of a start or end delimiter.

Table 6 – Truth table for ph_status_indication

Ph_status_indication	Ph_frame_indication	Start delimiters in a single frame	End delimiter detection	Any non-delimiter Manchester violations
Normal	true	1	true	false
Abort	true	2	don't care	false
Invalid	true	1	don't care	true

4.4.3.7 Ph_data_request

ph_data_request shall present the M_Symbols to be transmitted. Valid symbols shall be M_0, M_1, M_ND+ or M_ND– as shown in Table 5. ph_data_request shall indicate M_0 when no data is to be transmitted (and ph_frame_request = false).

4.4.3.8 Ph_frame_request

ph_frame_request shall be true when ph_data_request presents M_Symbols to be encoded into the appropriate Ph_Symbols by the PhL, and shall be false when no valid M_Symbols are to be transferred to the PhL.

4.5 Functional classes

Implementations of this protocol fall into two broad classes:

- connection originators (sometimes called Scanners);
- connection responders or connection targets (sometimes called Adaptors).

Devices with connection origination capability will include functions such as Scheduling object, support for external Configuration Tools and usually a Keeper object.

Connection responders are typically simpler devices which do not need the full set of capabilities.

This specification does not mandate particular groupings of functions for classes of implementation devices.

NOTE Grouping of services and functions into implementation classes may be done by separate specifications for profiles.

5 General structure and encoding of PhPDUs and DLPDUs and related elements of procedure

5.1 Overview

The DLL and its procedures are those necessary to provide the services offered to DLS user by using the services available from the PhL. The main services of this protocol are

- a) provision of timely access opportunities to support scheduled data-transfer DL-services on one link and on an extended multi-link network;
- b) the packing of multiple DLS-user transfers into a single PhL transfer unit (DLPDU) to efficiently use each transfer opportunity;
- c) the efficient distribution of DLS-user data from a publishing DLS-user to a set of subscribing DLS-users;
- d) the provision of a synchronized sense of internal time among the DLEs and available to the DLS-users of the extended link;
- e) the standardized availability of local DL-address, buffer and queue management capabilities.

5.2 Media access procedure

The primary task of the Data Link Layer is to determine, in co-operation with other Data Link Layers on the same link, the granting of permission to transmit on the medium. At its upper interface, the DLL provides services to receive and deliver service data units for the DLS user and Station Management.

The DLL protocol is based on a fixed, repetitive time cycle called a network update time (NUT). The NUT is maintained in close synchronism among all nodes on the link. A node is

not permitted access to transmit on the medium if its NUT does not agree with the NUT currently being used on a link wide basis. Different links may have different NUT duration.

Each node contains its own timer synchronized to the NUT for the local link. Media access is determined by local sub-division of the NUT into access slots. Access to the medium is in sequential order based on the MAC ID of the node. Specific behaviors have been incorporated into the access protocol allowing a node which temporarily assumes a MAC ID of zero to perform link maintenance. The MAC ID numbers of all nodes on a link are unique. Any DLL detecting the presence of a duplicate MAC ID shall immediately stop transmitting.

An implicit token passing mechanism is used to grant access to the medium. Each node monitors the source MAC ID of each DLPDU received. At the end of a DLPDU, each DLL sets an “implicit token register” to the received source MAC ID + 1. If the implicit token register is equal to the local MAC ID, then the node shall transmit one DLPDU containing one or more Lpackets with data or a null DLPDU. In all other cases, the node watches for either a new DLPDU from the node identified by the “implicit token register” or a time-out value if the identified node fails to transmit. In each case, the “implicit token” is automatically advanced to the next MAC ID. All nodes have the same value in their “implicit token register” preventing collisions on the medium.

The time-out period (called the “slot time”) is based on the amount of time required for

- the current node to hear the end of the transmission from the previous node;
- the current node to begin transmitting;
- the next node to hear the beginning of the transmission from the current node.

The slot time is adjusted to compensate for the total length of the medium since the propagation delay of the medium effects the first and last item on the previous list.

NOTE The calculation of slot time is specified in 8.2.

Each NUT is divided into three major parts: scheduled, unscheduled, and guardband as shown in Figure 7. This sequence is repeated in every NUT. The implicit token passing mechanism is used to grant access to the medium during both the unscheduled and scheduled intervals.




Figure 7 – NUT structure

During the scheduled part of the NUT, each node, starting with node 0 and ending with node SMAX, gets a chance to transmit time-critical (scheduled) data. SMAX is the MAC ID of the highest numbered node that has access to the medium during the scheduled part of the NUT. Every node between 0 and SMAX has only one opportunity to send one DLPDU of scheduled data in each NUT. The opportunity to access the medium during the scheduled time is the same for each node in every NUT. This allows data that is transmitted during the scheduled portion of the NUT to be sent in a predictable and deterministic manner. Figure 8 shows how

Time

SCHEDULED

UNSCHEDULED

GUARDBAND

0
1
2
3
n

each node is allowed to transmit exactly once during scheduled time (implied token)

nodes wait one slot time for each missing node (MAC ID) from 0 to SMAX

Example:
node #3 waits one slot time because node #2 was missing

$n = \text{SMAX}$
maximum scheduled network address

This boundary moves from NUT to NUT depending on the utilization of scheduled time

DRAFT

During the unscheduled part of the NUT, each node from 0 to UMAX shares the opportunity to transmit one DLPDU of non-time critical data in a round robin fashion, until the allocated NUT duration is exhausted. UMAX is the MAC ID of the highest numbered node that has access to the medium during the unscheduled part of the NUT. The round robin method of access opportunity enables every node between 0 and UMAX to have zero, one or many opportunities to send unscheduled data depending on how much of the NUT remains after the completion of the scheduled time. Variations in scheduled traffic means the opportunity to access the medium during the unscheduled time may be different for each node in every NUT. Figure 9 shows how the permission to transmit is granted during the unscheduled time. The MAC ID of the node that goes first in the unscheduled part of the NUT is incremented by 1 for each NUT. The unscheduled token begins at the MAC ID specified in the unscheduled start register (USR) of the previous moderator DLPDU. The USR increments by one modulo (UMAX+1) each NUT. If the USR reaches UMAX before the guardband, it returns to zero and the token pass continues.




Figure 9 – Media access during unscheduled time

When the guardband is reached, all nodes stop transmitting. A node is not allowed to start a transmission unless it can be completed before the beginning of the guardband. During the guardband, the node with the lowest MAC ID (called the “moderator”) transmits a maintenance message (called the “moderator DLPDU”) that accomplishes two things:

- it keeps the NUT timers of all nodes synchronized;
- it publishes critical link parameters enabling all members of the local DLL group to share a common version of important DLL values such as NUT, slot time, SMAX, UMAX, etc.

The moderator transmits the moderator DLPDU, which re-synchronizes all nodes and restarts the NUT. Following the receipt of a valid moderator DLPDU, each node compares its internal values with those transmitted in the moderator DLPDU. A node using link parameters that disagree with the moderator disables itself. If the moderator DLPDU is not heard for 2 consecutive NUTs, the node with the lowest MAC ID assumes the moderator role, and begins transmitting the moderator DLPDU in the guardband of the third NUT. A moderator node that notices another node on-line and transmitting with a MAC ID lower than its own immediately cancels its moderator role.

Typical situations that may cause disruption of the DLL access protocol include

- induced noise on the link;
- poor cable or termination quality;
- physically connecting two links together while the network is operating.

One common consequence of such disruption is that nodes may be caused to disagree as to which node should be transmitting; this is called a network “non-concurrence”. Another potential problem occurs when the nodes do not agree to the same link configuration parameters. A node that disagrees with the link parameters as transmitted by the moderator is called a “rogue” and immediately stops transmitting. The DLL access protocol is designed to recover a rogue node and bring it back on-line.

5.3 DLPDU structure and encoding

5.3.1 General

DLPDUs are the DLPDUs passed to the Ph layer for sending on the Ph medium. The DLPDUs are formed by the transmit logical link control (TxLLC) protocol in two stages:

- DLSDUs are formed into Link-units (Lpackets);
- Multiple Lpackets are packed into one DLPDU subject to constraints set by the QoS required, the type of access opportunity available and limits on DLPDU overall length.

5.3.2 DLPDU components

The general DLPDU structure is shown in Figure 10 and managed by the DLL support units TxFramer, RxFramer, Octet Serializer and Octet Deserializer as shown in Figure 2.

The components of the DLPDU shall be transmitted in the following order: preamble, start delimiter, source MAC ID, zero or more Lpackets, FCS and end delimiter.




Figure 10 – DLPDU format

5.3.3 Preamble

The preamble shall be composed of 16 consecutive {1} M_Symbols.

5.3.4 Start and end delimiters

The start delimiter shall consist of these M_Symbols, {+, 0, –, +, –, 1, 0, 1}, transmitted from left to right.

The end delimiter shall consist of these M_Symbols, {1, 0, 0, 1, +, –, +, –}, transmitted from left to right.

The use of non-data M_Symbols shall be reserved for the start and end delimiters.

5.3.5 DLPDU octets and ordering

The source MAC ID, Lpackets, and FCS shall be composed of octets. An octet shall be composed of exactly eight M_Symbols each of which shall be either {0} or {1}. An octet shall be transferred to the PhL low bit first. Multiple octet fields shall be transmitted low order octet first (little endian format).

5.3.6 Source MAC ID

The source MAC ID address shall be a single octet as specified in 4.3.2. A node may also temporarily assume a MAC ID of zero to perform link maintenance.

5.3.7 Lpackets field

Zero or more Lpackets shall be concatenated into a single DLPDU subject to the constraint that the maximum number of octets which compose all Lpackets in a DLPDU shall be 510.

An additional constraint is that DLPDUs sent during a scheduled access opportunity shall only contain Lpackets with a QoS parameter of scheduled.

5.3.8 Frame check sequence (FCS)

5.3.8.1 Frame check sequence requirements

The FCS shall be a modified CCITT checksum using the 16 bit polynomial: $G(X) = X^{16} + X^{12} + X^5 + 1$. A two octet FCS shall be included in each DLPDU.

The formal concepts for its generation and checking on reception are described in 5.3.8.2. The generation and checking of the FCS are further specified in 9.7 and 9.8.

5.3.8.2 Frame check sequence formal concepts

5.3.8.2.1 Frame check sequence field

Within this subclause, any reference to bit K of an octet is a reference to the bit whose weight in a one-octet unsigned integer is 2^K .

NOTE This is sometimes referred to as "little endian" bit numbering.

For this standard, as in other international standards (for example, ISO/IEC 3309, ISO/IEC 8802 and ISO/IEC 9314-2), DLPDU-level error detection is provided by calculating and appending a multi-bit frame check sequence (FCS) to the other DLPDU fields during transmission to form a "systematic code word"³ of length n consisting of k DLPDU message bits followed by $n - k$ (equal to 16) redundant bits, and by calculating during reception that the message and concatenated FCS form a legal (n, k) code word. The mechanism for this checking is as follows, where the generic form of the generator polynomial for this FCS construction is specified in equation (4) and the polynomial for the receiver's expected residue is specified in equation (9). The specific polynomials for this standard are specified in Table 7.

Table 7 – FCS length, polynomials and constants

Item	Value
$n-k$	16
$G(X)$	$X^{16} + X^{12} + X^5 + 1$ (notes 1, 2)
$R(X)$	$X^{12} + X^{11} + X^{10} + X^8 + X^3 + X^2 + X + 1$ (notes 2, 3)
NOTE 1 Code words $D(X)$ constructed from this $G(X)$ polynomial have Hamming distance 4 for lengths $\leq 4\ 095$ octets, and all errors of odd weight are detected.	
NOTE 2 These are the same polynomials and method as specified in ISO/IEC 3309 (HDLC).	
NOTE 3 The remainder $R(x)$ should be 0001 1101 0000 1111 (X^{15} to X^0 , respectively) in the absence of errors.	

³ W. W. Peterson and E. J. Weldon, Jr., *Error Correcting Codes* (2nd edition), MIT Press, Cambridge, 1972.

5.3.8.2.2 At the sending DLE

The original message (that is, the DLPDU without an FCS), the FCS, and the composite message code word (the concatenated DLPDU and FCS) shall be regarded as vectors $M(X)$, $F(X)$, and $D(X)$, of dimension k , $n - k$, and n , respectively, in an extension field over $GF(2)$. If the message bits are $m_1 \dots m_k$ and the FCS bits are $f_{n-k-1} \dots f_0$, where

$m_1 \dots m_8$ form the first octet sent,
 $m_{8N-7} \dots m_{8N}$ form the N th octet sent,
 $f_7 \dots f_0$ form the last octet sent, and
 m_1 is sent by the first PhL symbol(s) of the message and f_0 is sent by the last PhL symbol(s) of the message (not counting PhL framing information),

NOTE 1 This "as transmitted" ordering is critical to the error detection properties of the FCS.

then the message vector $M(X)$ shall be regarded to be

$$M(X) = m_1 X^{k-1} + m_2 X^{k-2} + \dots + m_{k-1} X^1 + m_k \quad (1)$$

and the FCS vector $F(X)$ shall be regarded to be

$$\begin{aligned} F(X) &= f_{n-k-1} X^{n-k-1} + \dots + f_0 \\ &= f_{15} X^{15} + \dots + f_0 \end{aligned} \quad (2)$$

The composite vector $D(X)$, for the complete DLPDU, shall be constructed as the concatenation of the message and FCS vectors

$$\begin{aligned} D(X) &= M(X) X^{n-k} + F(X) \\ &= m_1 X^{n-1} + m_2 X^{n-2} + \dots + m_k X^{n-k} + f_{n-k-1} X^{n-k-1} + \dots + f_0 \\ &= m_1 X^{n-1} + m_2 X^{n-2} + \dots + m_k X^{16} + f_{15} X^{15} + \dots + f_0 \quad (\text{for the case of } k = 15) \end{aligned} \quad (3)$$

The DLPDU presented to the PhL shall consist of an octet sequence in the specified order.

The redundant check bits $f_{n-k-1} \dots f_0$ of the FCS shall be the coefficients of the remainder $F(X)$, after division by $G(X)$, of $L(X)(X^k + 1) + M(X) X^{n-k}$

where $G(X)$ is the degree $n-k$ generator polynomial for the code words

$$G(X) = X^{n-k} + g_{n-k-1} X^{n-k-1} + \dots + 1 \quad (4)$$

and $L(X)$ is the maximal weight (all ones) polynomial of degree $n-k-1$

$$\begin{aligned} L(X) &= (X^{n-k} + 1) / (X + 1) = X^{n-k-1} + X^{n-k-2} + \dots + X + 1 \\ &= X^{15} + X^{14} + X^{13} + X^{12} + \dots + X^2 + X + 1 \quad (\text{for the case of } k = 15) \end{aligned} \quad (5)$$

That is,

$$F(X) = L(X)(X^k + 1) + M(X) X^{n-k} \quad (\text{modulo } G(X)) \quad (6)$$

NOTE 2 The $L(X)$ terms are included in the computation to detect initial or terminal message truncation or extension by adding a length-dependent factor to the FCS.

NOTE 3 As a typical implementation when $n-k = 16$, the initial remainder of the division is preset to all ones. The transmitted message bit stream is multiplied by X^{n-k} and divided (modulo 2) by the generator polynomial $G(X)$, specified in equation (7). The ones complement of the resulting remainder is transmitted as the $(n-k)$ -bit FCS, with the coefficient of X^{n-k-1} transmitted first.

The equation for $D(X)$ does not apply to the Type 8 protocol because that protocol sends the message and check bits in separate DLPDUs. The equation for $F(X)$ as just given does not apply to the Type 8 protocol because that protocol does not complement the check bits before transmission. The equation corresponding to $F(X)$ for the Type 8 protocol is

$$F_{\text{Type 8}}(X) = L(X) X^k + M(X) X^{n-k} \quad (\text{modulo } G(X)) \quad (7)$$

NOTE 4 As a typical implementation for the Type 8 protocol, the initial remainder of the division is preset to all ones. The transmitted message bit stream is multiplied by X^{n-k} and divided (modulo 2) by the generator polynomial

$G(X)$, specified in equation (7). The resulting remainder without ones complementation is transmitted as the $(n-k)$ -bit FCS, with the coefficient of X^0 transmitted first.

5.3.8.2.3 At the receiving DLE

NOTE 1 This subclause does not apply to the Type 8 protocol.

The octet sequence indicated by the PhE shall be concatenated into the received DLPDU and FCS, and regarded as a vector $V(X)$ of dimension u

$$V(X) = v_1X^{u-1} + v_2X^{u-2} + \dots + v_{u-1}X + v_u \quad (8)$$

NOTE 2 Because of errors u can be different than n , the dimension of the transmitted code vector.

A remainder $R(X)$ shall be computed for $V(X)$, the received DLPDU and FCS, by a method similar to that used by the sending DLE (see 5.3.8.2.2) in computing $F(X)$

$$\begin{aligned} R(X) &= L(X) X^u + V(X) X^{n-k} \text{ (modulo } G(X)) \\ &= r_{n-k-1}X^{n-k-1} + \dots + r_0 \end{aligned} \quad (9)$$

Define $E(X)$ to be the error code vector of the additive (modulo-2) differences between the transmitted code vector $D(X)$ and the received vector $V(X)$ resulting from errors encountered (in the PhS provider and in bridges) between sending and receiving DLEs.

$$E(X) = D(X) + V(X) \quad (10)$$

If no error has occurred, so that $E(X) = 0$, then $R(X)$ will equal a non-zero constant remainder polynomial

$$R_{ok}(X) = L(X) X^{n-k} \text{ (modulo } G(X)) \quad (11)$$

whose value is independent of $D(X)$. Unfortunately $R(X)$ will also equal $R_{ok}(X)$ in those cases where $E(X)$ is an exact non-zero multiple of $G(X)$, in which case there are “undetectable” errors. In all other cases, $R(X)$ will not equal $R_{ok}(X)$; such DLPDUs are erroneous and shall be discarded without further analysis.

NOTE 3 As a typical implementation, the initial remainder of the division is preset to all ones. The received bit stream is multiplied by X^{n-k} and divided (modulo 2) by the generator polynomial $G(X)$, specified in equation (8).

5.3.9 Null DLPDU

A DLPDU with an empty Lpacket field, called a null DLPDU, shall be sent by a node to indicate that it has no data to send at the QoS allowed by the access opportunity.

5.3.10 Abort DLPDU

To abort a partially transmitted DLPDU, the Data Link Layer shall transmit the following sequence:

- one 0xFF octet;
- start delimiter;
- end delimiter.




Figure 11 – Aborting a DLPDU during transmission

NOTE 1 Some implementations of this specification may build the DLPDU as it is being transmitted. If a higher layer has provided only a partial DLPDU to the Data Link Layer, and the DLL has begun transmission of the DLPDU

assuming that the rest will be provided shortly, a transmit underflow occurs if the rest of the DLPDU is not provided to the DLL soon enough to complete the transmission.

NOTE 2 Although the DLL assembles the entire DLPDU including delimiters, the PhL performs start and end delimiter detection. The PhL identifies a transmit abort as a DLPDU which includes two start delimiters which are not separated by an end delimiter, as shown in Figure 11.

NOTE 3 The 0xFF octet is inserted before the start delimiter / end delimiter pair to avoid violating PhL constraints governing consecutive physical symbol relationships on the media.

5.4 Lpacket components

5.4.1 General Lpacket structure

The Lpacket (or link unit) is the PDU which is used to carry DLSDUs between peer DLS users. The components of the Lpacket shall be transmitted in the following order: size, control, tag, and link data as shown in Figure 12.




Figure 12 – Lpacket format

5.4.2 Size

The size field shall specify the number of octet pairs (from 3 to 255) contained in an individual Lpacket. The number of octet pairs shall include the size, control, tag, and link data fields counted in accordance with the following rules:

- combined, the size and control shall count as a single octet pair;
- the number of octet pairs from the tag and link data fields shall be counted separately and odd octet counts shall be rounded up;
- although the counting of octet pairs is done independently, the format of an Lpacket as placed into a DLPDU shall not include the extra octets caused by the round up.

NOTE For example, an Lpacket with a 3 octet tag (2 octet pairs) and a 9 octet link data (5 octet pairs) has a size field of $1+2+5 = 8$ octet pairs; however the Lpacket occupies $2+3+9 = 14$ octets in the DLPDU.

5.4.3 Control

5.4.3.1 Bit 0 and Bit 4 (type of Lpacket)

The bits of the control field shall be numbered 0 to 7, where bit 0 shall be the least significant bit of the control field. Bit 0 shall indicate the type of Lpacket.

- When set (bit 0 = 1), the Lpacket shall be a fixed tag Lpacket (see 4.3.4).
- When clear (bit 0 = 0), the Lpacket shall be a generic tag Lpacket (see 4.3.3).

Bit 4 of the control field shall be the inverse of bit 0. If bit 0 is clear, then bit 4 shall be set. If bit 0 is set, then bit 4 shall be clear.

5.4.3.2 Bit 1 (odd tag size)

Bit 1 of the control field shall indicate whether the tag field contains an even or odd number of octets. When clear (bit 1 = 0), this bit shall indicate that the tag contains an even number of octets. When set (bit 1 = 1), it shall indicate that the tag contains an odd number of octets.

5.4.3.3 Bit 2 (odd link data size)

Bit 2 of the control field shall indicate whether the link data contains an even or odd number of octets. When clear (bit 2 = 0), this bit shall indicate that the link data contains an even number of octets. When set (bit 2 = 1), it shall indicate that the link data contains an odd number of octets.

5.4.3.4 Bits 3, 5, 6 and 7 (reserved bits)

Bits 3, 5, 6 and 7 of the control field are reserved and shall be zero.

5.4.4 Generic tag Lpackets

Generic link-units are formed from the DLS-generic-tag and DLS-user-data provided by the DLS user with the addition of size and control field information for generic tags as shown in Figure 13. The 3 octet generic tag address (see 4.3.3) shall identify the connected mode information carried in the link data field




Figure 13 – Generic tag Lpacket format

The minimum length generic tag Lpacket shall be 5 octets (minimum link data size of 0 octets). The maximum size of link data shall be 504 octets.

NOTE Generic Lpackets are usually connection mode transfers with the QoS value of scheduled or low.

5.4.5 Fixed tag Lpackets

Fixed tag link-units are formed from the DLS-fixed-tag and DLS-user-data provided by the DLS user with the addition of size and control field information for fixed tags as shown in Figure 14. The 2 octet fixed tag address (see 4.3.4) shall identify the service access point in the destination node and the address of the destination node.




Figure 14 – Fixed tag Lpacket format

The minimum length fixed tag Lpacket shall be 7 octets (minimum link data size of 3 octets). The maximum size of link data shall be 506 octets.

NOTE Fixed Lpackets are always connectionless mode transfers. They are not usually sent with the QoS parameter value scheduled.

5.5 DLPDU procedures

5.5.1 General

The transmission protocol combines one or more Lpackets into single DLPDUs for sending according to the available transmission opportunity. The DLPDU components are passed to the Ph layer by the transmit machine framer (TxM) and Serializer (see 9.3).

A node shall always send one DLPDU at each valid access opportunity for it to transmit, and no DLPDU shall include Lpackets with a lesser QoS parameter than the QoS value applicable to the access opportunity.

If a node has no Lpackets available at or better than the QoS of the access opportunity, then a Null DLPDU shall be sent.

If for internal reasons a node begins a DLPDU and is unable to complete it, the abort sequence shall be sent, transmission shall stop for that access opportunity and the local DLS user shall be notified.

NOTE Null DLPDUs and abort DLPDUs provide an efficiency improvement as they notify other nodes that use of the transmission slot has ended and enable the next node to begin transmission without waiting for slot time out.

Each Lpacket in the queue awaiting transfer has an associated local identifier. At completion of the transfer to the PhL, or an aborted transfer, the local identifier is returned to the local DLS user with a status confirmation of OK or TXABORT.

The DLS user has additional local services to identify unsent Lpackets and request they are flushed from the queue; this action results in the confirmation status of FLUSHED being returned with the local identifier for Lpackets that have been flushed.

5.5.2 Sending scheduled DLPDUs

Scheduled DLPDUs are normally used for transfer of connected mode operation using Generic Lpackets. They are formed by concatenating multiple Lpackets (subject to a limit of 510 octets), prepending Ph-control information and source station MAC ID, and appending a defined frame check sequence and further Ph-control information.

Lpackets are packed into a Scheduled DLPDU in FIFO order as received from the DLS user, until the queue is empty of packets with Scheduled QoS or the next such Lpacket size exceeds the remaining space.

5.5.3 Sending unscheduled DLPDUs

Unscheduled DLPDUs may contain both Generic Lpackets and Fixed Lpackets. They are formed by concatenating multiple Lpackets (subject to a limit of 510 octets), prepending Ph-control information and source station MAC ID, and appending a defined frame check sequence and further Ph-control information.

Lpackets are packed into an unscheduled DLPDU in QoS priority order (Scheduled, High and Low priorities respectively). Within each QoS, the FIFO order of queuing by the DLS user is followed, until the queue is empty or the next such Lpacket size exceeds the remaining space.

5.5.4 Receiving DLPDUs

5.5.4.1 Unpacking

Received DLPDUs are assembled from the incoming Ph stream of symbols and unpacked by the Octet Deserializer, Receive Machine Framer (RxM) and Receive Logical Link Control (RxLLC) functions in two stages

- a frame check sequence is computed over the stream of received octets, (excluding Ph delimiters) and checked for the proper residual value, if this is correct, then
- each Lpacket contained in the DLPDU is examined to extract its tag. Each extracted tag is then compared with the contents of a local tag filter to determine if the associated Lpacket is of interest to the receiving station. Lpackets whose tags match the tag filter are then processed further and passed to the DL user, DL management or used inside the DLL. Indications passed to the DL user or DL management include Lpacket size, Lpacket tag and Lpacket data. In addition for fixed tag Lpackets, the source ID is also indicated.

5.5.4.2 Tag filtering

Each local DLS provider maintains a list of tags used to identify Lpackets of interest to its DL user or its internal DL management functions. The DL user may access and change this list to specify

- generic tags of interest
- fixed tags of interest

NOTE A generic tag specifies the Lpackets for a single connection-mode object. A fixed tag specifies all connectionless-mode messages in a particular class, for example Time distribution.

5.6 Summary of DLL support services and objects

The operation and coordination of participating DLL providers is governed by variables and attributes held in DL management objects or provided by the DL user services listed in Table 8. Access to these items is via defined fixed tag addresses, DL user services or unspecified local services. Details are given in the listed clauses.

Table 8 – DLL support services and objects

DLL item	Description	Location
DLS user services		see IEC 61158-3-2:2007
connected mode transfer service	a local service for requesting, indicating and confirming generic tag (connected mode) data transfer by Lpackets	see 6.2.2
connectionless mode transfer service	a local service for requesting, indicating and confirming generic tag (connected mode) data transfer by Lpackets	see 6.2.2
queue maintenance service	a local service for flushing unsent Lpacket messages from the internal DL service queue	see 6.2.3
tag filter service	a local service for the DLS user to inform its local DL provider which Lpacket tags and tag types are to be accepted and processed by the DLL or passed to the DL user	see 6.2.4
link synchronization service	a local service for informing the local DLS user of the current NUT number to maintain schedule pointers	see 6.2.5
synchronized parameter change service and tMinus-start-countdown	a local service for loading and changing local lists of current and pending DL configuration data and in conjunction with the tMinus-start-countdown service and moderator DLPDU, to manage an accurately timed change over to new DL link configurations	see 6.2.6
event reports service	local services to report various events for use by management	see 6.2.7
bad FCS service		see 6.2.8
current moderator		see 6.2.9
power-up and on-line		see 6.2.10
enable moderator		see 6.2.11
listen only		see 6.2.12
Generic tag service	an Lpacket service for connected mode communication	see 6.3
Fixed tag services	a range of Lpacket service addresses for various connectionless mode communication	see 5.4.5
moderator	an Lpacket broadcast in every NUT for managing time precision and timing for change of link parameters	see 6.4
time distribution service	an Lpacket for publishing time values and offsets used in coordinating the same time sense in all stations	see 6.5
UCMM	an Lpacket service to transfer DLSDUs from a DLS user to the Unconnected Message Manager in a peer DLS-user	see 6.6
Keeper UCMM	an Lpacket service to transfer DLSDUs from a DLS user to the Keeper objects in other nodes	see 6.7
TUI	an Lpacket broadcast to all stations assisting their synchronization to the current link configuration	see 6.8
link parameters	an Lpacket service for publishing pending link parameters in advance of a synchronized change of link operating conditions	see 6.9
tMinus	an Lpacket service to start a count down leading to a change of link parameters and return the result.	see 6.9
I'm alive	an Lpacket broadcast by new and reset devices to assist their entry into an operating system	see 6.10
ping request and reply	an Lpacket service soliciting identification responses from all other active devices on the link	see 6.11
WAMI	an Lpacket allowing temporary devices to identify a local device MAC ID when they are plugged into its network access port	see 6.12
debug	an Lpacket service to trace object state transitions	see 6.13