



IEC 61196-1-119

Edition 2.0 2020-05
REDLINE VERSION

INTERNATIONAL STANDARD



Coaxial communication cables –
Part 1-119: Electrical test methods – RF **average** power rating





THIS PUBLICATION IS COPYRIGHT PROTECTED
Copyright © 2020 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

IEC publications search - webstore.iec.ch/advsearchform

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

Electropedia - www.electropedia.org

The world's leading online dictionary on electrotechnology, containing more than 22 000 terminological entries in English and French, with equivalent terms in 16 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

IEC Glossary - std.iec.ch/glossary

67 000 electrotechnical terminology entries in English and French extracted from the Terms and Definitions clause of IEC publications issued since 2002. Some entries have been collected from earlier publications of IEC TC 37, 77, 86 and CISPR.



IEC 61196-1-119

Edition 2.0 2020-05
REDLINE VERSION

INTERNATIONAL STANDARD



Coaxial communication cables –
Part 1-119: Electrical test methods – RF **average** power rating

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 33.120.10

ISBN 978-2-8322-8356-1

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

FOREWORD	3
1 Scope	5
2 Normative references	5
3 Terms and definitions	5
4 Symbols	5
5 Methodology	7
5.1 Method A	7
5.2 Method B	7
6 Procedure: Test general considerations	7
6.1 Sample preparation	7
6.2 Surrounding condition	7
6.3 Temperature test	7
6.4 Test equipment	7
7 Procedure	8
7.1 RF test – Method A	8
7.2 Low frequency power AC test – Method B	9
7.3 Adjustment to other frequencies	11
7 Attenuation test	8
7.1 Conduct attenuation test	8
7.2 Calculate A and B coefficients – Method B	9
7.3 Calculate the A_i and A_o coefficients – Method B	11
8 Power calculation	11
8.1 Determined from AC test – Method B	11
8.2 Determined from RF test – Method A	11
8.3 Adjustment to other frequencies	11
8 Test report	11
9 Requirements	11
Annex A (informative) Determination method of thermal time constant	12
A.1 General	12
A.2 Determination method	12
Bibliography	14

INTERNATIONAL ELECTROTECHNICAL COMMISSION

COAXIAL COMMUNICATION CABLES –

Part 1-119: Electrical test methods – RF **average** power rating

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

This redline version of the official IEC Standard allows the user to identify the changes made to the previous edition. A vertical bar appears in the margin wherever a change has been made. Additions are in green text, deletions are in strikethrough red text.

International Standard IEC 61196-1-119 has been prepared by subcommittee 46A: Coaxial cables, of IEC technical committee 46: Cables, wires, waveguides, RF connectors, RF and microwave passive components and accessories.

This second edition cancels and replaces the first edition, published in 2012. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) title was changed from: RF power rating to: RF average power rating;
- b) a test method to determine sufficient duration is included as Annex A;
- c) the equations used for calculating cable coefficients and RF average power rating are corrected;
- d) the clauses and subclauses are rearranged.

The text of this International Standard is based on the following documents:

FDIS	Report on voting
46A/1401/FDIS	46A/1408/RVD

Full information on the voting for the approval of this International Standard can be found in the report on voting indicated in the above table.

This document has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all the parts in the IEC 61196 series published under the general title *Coaxial communication cables* can be found on the IEC website.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under "<http://webstore.iec.ch>" in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

COAXIAL COMMUNICATION CABLES –

Part 1-119: Electrical test methods – RF **average** power rating

1 Scope

This part of IEC 61196 defines the requirements to determine the average power handling capability of a coaxial cable at specified frequencies at ambient temperatures.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 61196-1, *Coaxial communication cables – Part 1: Generic specification – General, definitions and requirements*

IEC 61196-1-113, *Coaxial communication cables – Part 1-113: Electrical test methods – Test for attenuation constant*

3 Terms and definitions

For the purposes of this document, the terms and definitions given in IEC 61196-1 and the following apply.

ISO and IEC maintain terminological databases for use in standardization at the following addresses:

- IEC Electropedia: available at <http://www.electropedia.org/>
- ISO Online browsing platform: available at <http://www.iso.org/obp>

3.1

RF **average power rating**

maximum average input power that a cable can continuously handle when terminated in its characteristic impedance at a reference ambient temperature (**usually 40 °C**) and RF frequency

Note 1 to entry: RF **average** power rating is determined by the power level at which the temperature at any location in the cable does not exceed the allowable maximum temperature rating of the materials used in the cable's construction.

Note 2 to entry: Typically, the inner conductor temperature determines the maximum operating temperature.

Note 3 to entry: The test RF signal is a pure sinusoidal, without any modulation.

4 Symbols

For the purposes of this document, the following symbols apply.

K_i thermal constant of the insulation (W/(°C·m))

K_o thermal constant of outer sheath (W/(°C·m))

A	attenuation constant associated with the conductors $\left(\frac{\text{dB}}{\text{m} \cdot \sqrt{\text{MHz}}} \right)$
A_i	attenuation constant of inner conductor $\left(\frac{\text{dB}}{\text{m} \cdot \sqrt{\text{MHz}}} \right)$
A_o	attenuation constant of outer conductor $\left(\frac{\text{dB}}{\text{m} \cdot \sqrt{\text{MHz}}} \right)$
B	attenuation constant for the dielectric material $\left(\frac{\text{dB}}{\text{m} \cdot \text{MHz}} \right)$
a	mean outer diameter of inner conductor (mm) Sine shape corrugated: Mean = (peak + root)/2 Other shape corrugated: Mean shall be specified by the manufacturer. Smooth wall = (max + min)/2 outer diameter Wire = outer diameter
b	mean inner diameter of outer conductor (mm) Sine shape corrugated: Mean = (peak + root)/2 Other shape corrugated: Mean shall be specified by the manufacturer. Smooth wall = (max + min)/2 inner diameter
C_i	corrugation factor of inner conductor: Ratio of the distance that compares the non-corrugated (conversion of corrugated length to an equivalent smooth wall length) to the cable corrugated length. $C_i > 1$ for corrugated cable $C_i = 1$ for smooth wall or wire
C_o	corrugation factor of outer conductor Ratio of the distance that compares the non-corrugated (conversion of corrugated length to an equivalent smooth wall length) to the cable corrugated length. $C_o > 1$ for corrugated cable $C_o = 1$ for smooth wall
P_{in}	RF input power (W)
P_r	rated RF average power (W) at frequency f
P_{rf1}	rated RF average power (W) at frequency f_1
P_{rf2}	rated RF average power (W) at frequency f_2
P_i	power dissipated in inner conductor (W/m)
P_o	power dissipated in outer conductor (W/m)
σ_i	conductivity of inner conductor (relative to copper)
σ_o	conductivity of outer conductor (relative to copper)
γ_i	temperature coefficient of resistance for inner conductor
γ_o	temperature coefficient of resistance for outer conductor
α_c	attenuation of cable, at frequency f (dB/100 m)
α_{f1}	attenuation of cable, at frequency f_1 (dB/100 m)
α_{f2}	attenuation of cable, at frequency f_2 (dB/100 m)
α_i	attenuation of inner conductor, at frequency f (dB/100 m)
α_o	attenuation of outer conductor, at frequency f (dB/100 m)
T_i	inner conductor temperature (°C)

T_o	outer conductor temperature (°C)
T_a	test ambient temperature (°C)
T_{ri}	inner conductor temperature rise (°C)
T_{ro}	outer conductor temperature rise (°C)
R_T	maximum rated ambient temperature (°C)

5 Methodology

5.1 Method A

If a suitable RF power source is available, it is possible to determine the input power required for a conductor temperature to reach its limiting value (i.e. the RF average power rating), per 7.1. This provides measurements at one frequency and generally needs to be adjusted to other frequencies by knowing the RF cable attenuation.

5.2 Method B

Cables of large diameter, however, have high RF average power ratings, and a suitable RF source may not be available for such direct test. The following methodology allows the RF average power rating to be determined by using low frequency (50 Hz or 60 Hz) AC power to determine the ~~required~~ cable thermal characteristics first (i.e. the thermal constants K_i and K_o). ~~The low~~ As these parameters are independent with frequency ~~AC data needs to~~, it can be combined with RF data for RF average power rating calculation. This is because the relative conductor power dissipations are different. Also, there is no dissipation in the dielectric in the low frequency case, but at RF frequencies it becomes significant.

6 ~~Procedure:~~ Test general considerations

6.1 Sample preparation

A cable of sufficient length shall be used so that the temperatures measured at the centre of the cable are not influenced by heat sinking effects at the ends of the cable.

6.2 Surrounding condition

There shall be sufficient air space around the cable under test to allow natural air circulation.

6.3 Temperature test

Temperature measurements on the inner and outer conductors shall be made at the centre of the cable length and 0,5 m away from both sides of the centre point. For RF test – method A, the temperature should be measured at the cable's current antinode.

~~Sufficient power should be applied for a conductor temperature to reach its maximum value, determined by the materials used in the cable construction.~~

The thermocouples should be chosen and sized to eliminate the possibility of heat sinking effects, particularly with thin walled cables.

The test is conducted for sufficient duration for the conductors to reach constant temperatures. A test method to determine sufficient duration is included as Annex A.

6.4 Test equipment

For method A, the RF power source, power meter, temperature tester, coupler and absorbing load are needed.

For method B, the AC power source, multimeter and temperature tester are needed.

No matter which method is used, the sufficient power should be applied for a conductor temperature to reach its maximum value, and be determined by the materials used in the cable construction.

The measured results and determination of the average power rating are adjusted for an ambient temperature of 40 °C (or other specified ambient temperature).

7 Procedure

7.1 ~~Procedure:~~ RF test – Method A

The input of the cable shall be connected to the RF power source capable of delivering the specified power at the specified test frequency at the load.

The load side of the cable shall be terminated in its characteristic impedance that is capable of handling the power.

The input power, P_{in} , at the test frequency shall be monitored.

It is recommended to drill a small hole into the cable just above the inner conductor. A fibre optic thermocouple should be placed within 1 mm above the surface of the inner conductor to measure the temperature.

The input power, at room temperature (T_a), shall be increased in stages until maximum component temperature ratings are reached. The conductor temperatures are allowed to stabilize at each stage and then recorded.

Each conductor temperature rise (T_{ri} and T_{ro}) at each stage above the room temperature (T_a) is determined for each input power level by subtracting the T_a from the measured conductors (T_i or T_o) temperature.

For each stage, T_i and T_o shall be determined for R_T by adding T_{ri} and T_{ro} to R_T .

Compare the recalculated T_i and T_o at R_T to the maximum temperature ratings of the cable components. The power rating is the level that does not exceed the maximum temperature ratings of the cable components.

The increase in conductor temperature above ambient temperature is determined for each input power level. The average power rating (P_r) is that power which will cause an increase in conductor temperature above ambient equal to the difference between the maximum conductor temperature and the reference ambient (usually 40 °C).

The measurement error of P_r should be taken into account when the load is mismatched.

$$e_{\max} = 100 \times \left[\frac{(1+s)^2}{4} - 1 \right] \quad (1)$$

where

$e_{\max}$ is the measurement error of P_r ;

s is the *SWR* of the DUT.