IEC 62489-2

Edition 2.0 2014-09

INTERNATIONAL STANDARD

NORME INTERNATIONALE

colour inside

Electroacoustics – Audio-frequency induction loop systems for assisted hearing –
Part 2: Methods of calculating and measuring the low-frequency magnetic field emissions from the loop for assessing conformity with guidelines on limits for human exposure

Électroacoustique – Systèmes de boucles d'induction audiofréquences pour améliorer l'audition –
Partie 2: Méthodes de calcul et de mesure des émissions de champ magnétique basse fréquence à partir de la boucle pour l'évaluation de la conformité aux instructions sur les limites d'exposition humaine

IEC 62489-2:2014-09(en-fr)

Documents
Document Sharing Hub
Full document details: IEC 62489-2 2014

THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2014 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de l'IEC ou du Comité national de l'IEC du pays du demandeur. Si vous avez des questions sur le copyright de l'IEC ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de l'IEC de votre pays de résidence.

IEC Central Office
3, rue de Varembé
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
Fax: +41 22 919 03 00
info@iec.ch
www.iec.ch

About the IEC
The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications
The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

IEC Catalogue - webstore.iec.ch/catalogue
The stand-alone application for consulting the entire bibliographical information on IEC International Standards, Technical Specifications, Technical Reports and other documents. Available for PC, Mac OS, Android Tablets and iPad.

IEC publications search - www.iec.ch/searchpub
The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee,…). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished
Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and also once a month by email.

Electropedia - www.electropedia.org
The world's leading online dictionary of electronic and electrical terms containing more than 30 000 terms and definitions in English and French, with equivalent terms in 14 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

IEC Glossary - std.iec.ch/glossary
More than 55 000 electrotechnical terminology entries in English and French extracted from the Terms and Definitions clause of IEC publications issued since 2002. Some entries have been collected from earlier publications of IEC TC 37, 77, 86 and CISPR.

IEC Customer Service Centre - webstore.iec.ch/csc
If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: csc@iec.ch.

A propos de l'IEC
La Commission Electrotechnique Internationale (IEC) est la première organisation mondiale qui élabore et publie des Normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

A propos des publications IEC
Le contenu technique des publications IEC est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

Catalogue IEC - webstore.iec.ch/catalogue
Application autonome pour consulter tous les renseignements bibliographiques sur les Normes internationales, Spécifications techniques, Rapports techniques et autres documents de l'IEC. Disponible pour PC, Mac OS, tablettes Android et iPad.

Recherche de publications IEC - www.iec.ch/searchpub

La recherche avancée permet de trouver des publications IEC en utilisant différents critères (numéro de référence, texte, comité d'études,…). Elle donne aussi des informations sur les projets et les publications remplacées ou retirées.

IEC Just Published - webstore.iec.ch/justpublished

Restez informé sur les nouvelles publications IEC. Just Published détaille les nouvelles publications parues. Disponible en ligne et aussi une fois par mois par email.

Electropedia - www.electropedia.org

Le premier dictionnaire en ligne de termes électroniques et électriques. Il contient plus de 30 000 termes et définitions en anglais et en français, ainsi que les termes équivalents dans 14 langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International (IEV) en ligne.

Glossaire IEC - std.iec.ch/glossary
Plus de 55 000 entrées terminologiques électrotechniques, en anglais et en français, extraites des articles Termes et Définitions des publications IEC parues depuis 2002. Plus certaines entrées antérieures extraites des publications des CE 37, 77, 86 et CISPR de l'IEC.

Service Clients - webstore.iec.ch/csc

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions contactez-nous: csc@iec.ch.

Documents
Document Sharing Hub

Full document details: IEC 62489-2 2014

IEC 62489-2

Edition 2.0 2014-09

INTERNATIONAL STANDARD

NORME INTERNATIONALE

colour inside

Electroacoustics – Audio-frequency induction loop systems for assisted hearing –
Part 2: Methods of calculating and measuring the low-frequency magnetic field emissions from the loop for assessing conformity with guidelines on limits for human exposure

Électroacoustique – Systèmes de boucles d'induction audiofréquences pour améliorer l'audition –
Partie 2: Méthodes de calcul et de mesure des émissions de champ magnétique basse fréquence à partir de la boucle pour l'évaluation de la conformité aux instructions sur les limites d'exposition humaine

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

COMMISSION
ELECTROTECHNIQUE
INTERNATIONALE

PRICE CODE
CODE PRIX P

ICS 17.140.50

ISBN 978-2-8322-1860-0

Warning! Make sure that you obtained this publication from an authorized distributor.
Attention! Veuillez vous assurer que vous avez obtenu cette publication via un distributeur agréé.

AVA Documents
Document Sharing Hub

® Registered trademark of the International Electrotechnical Commission
Marque déposée de la Commission Electrotechnique Internationale

Full document details: IEC 62489-2 2014

CONTENTS

FOREWORD 3
INTRODUCTION 5
1 Scope 6
2 Normative references 6
3 Rated values 6
4 Situation regarding current standards 6
5 Configurations of loops 7
5.1 Main types of configuration 7
5.2 General considerations 7
5.3 Large-area loops 7
5.4 Medium-area loops 7
5.5 Small-area loops 8
5.6 Solenoid antennas 8
6 Calculations 8
6.1 General 8
6.2 Solenoid antennas 9
7 Measurements 9
7.1 General 9
7.2 Input signal 9
7.3 Measuring instrument 9
8 Comparison of calculated or measured results with guidelines or limits 10
9 Meeting limits or guidelines 10
10 Measurement uncertainty 10
Annex A (informative) Rationale for this product-family magnetic field emission standard for audio-frequency induction-loop systems (AFILS) in the context of human exposure to non-ionizing radiation 11
Bibliography 14

Figure 1 – An ear-hook induction transducer, with a BTE (behind the ear) hearing aid body for scale 8
Figure A.1 – ICNIRP magnetic field reference levels 11

Table 1 – Basic restrictions 10
Table A.1 – Application to AFILS of Table 1 of IEC 62311:2007 "Characteristics and parameters of the equipment to be considered" 12

Documents
Document Sharing Hub
Full document details: IEC 62489-2 2014

INTERNATIONAL ELECTROTECHNICAL COMMISSION

ELECTROACOUSTICS – AUDIO-FREQUENCY INDUCTION LOOP SYSTEMS FOR ASSISTED HEARING –

Part 2: Methods of calculating and measuring the low-frequency magnetic field emissions from the loop for assessing conformity with guidelines on limits for human exposure

FOREWORD

1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
6) All users should ensure that they have the latest edition of this publication.
7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 62489-2 has been prepared by IEC technical committee 29: Electroacoustics.

This second edition cancels and replaces the first edition published in 2011. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition: it reflects several updates to the ICNIRP Guide [1][1] to which it makes frequent

[1] Numbers in square brackets refer to the Bibliography.

Documents
Document Sharing Hub
Full document details: IEC 62489-2 2014

reference. The most significant change is that the underlying metric in the Guide has been changed from tissue current density to induced electric field.

The text of this standard is based on the following documents:

FDIS	Report on voting
29/847/FDIS	29/854/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all parts of the IEC 62489 series, published under the general title *Electroacoustics – Audio-frequency induction loop systems for assisted hearing*, can be found on the IEC website.

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC web site under "http://webstore.iec.ch" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

Documents
Document Sharing Hub

Full document details: IEC 62489-2 2014

INTRODUCTION

A revision of IEC 62489-2 is necessary because, while the standard does not call up any particular set of exposure limits, it has numerous references to the ICNIRP Guide, which has profoundly changed between the 1998 and 2010 editions. This has resulted in a change in the physical quantity on which the basic restrictions are established, from tissue current density to induced electric field, resulting in changes to the reference levels and a considerable simplification of the application of the guidelines.

The recommendations of the new Guide have not yet been adopted at the regulatory level in the European Union. However, since the references to the Guide in IEC 62489-2 are purely informative, it does not appear that this revision should be unacceptable in Europe.

Documents
Document Sharing Hub

Full document details: IEC 62489-2 2014

ELECTROACOUSTICS – AUDIO-FREQUENCY INDUCTION LOOP SYSTEMS FOR ASSISTED HEARING –

Part 2: Methods of calculating and measuring the low-frequency magnetic field emissions from the loop for assessing conformity with guidelines on limits for human exposure

1 Scope

This part of IEC 62489 applies to audio-frequency induction-loop systems for assisted hearing. It may also be applied to such systems used for other purposes, as far as it is applicable. The standard is intended for assessment of human exposure to low-frequency magnetic fields produced by the system, by calculation and by in-situ testing.

This standard does not deal with other aspects of safety, for which IEC 60065 applies, or with EMC.

2 Normative references

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60118-4:2006, *Electroacoustics - Hearing aids - Part 4: Induction loop systems for hearing aid purposes - Magnetic field strength*

IEC 60268-1:1985, *Sound system equipment – Part 1: General*

IEC 60268-2:1987, *Sound system equipment – Part 2: Explanation of general terms and calculation methods*

IEC 60268-10:1991, *Sound system equipment – Part 10: Peak programme level meters*

3 Rated values

The term "rated" means "the value stated by the manufacturer". Rated values are of two kinds: rated conditions, which are fundamental values that cannot be verified by measurement, and others that can be so verified. For a full explanation, see IEC 60268-2.

4 Situation regarding current standards

Current published and draft IEC standards on EMF exposure can be ambiguous in their guidance on the approach that should be taken by product committees. The differences between the signals that are of concern and those considered in depth in EMF exposure standards are the following:

- wide relative bandwidth, i.e. the ratio of highest to lowest frequency present, 5 kHz and 100 Hz;
- no predominant frequency within the band;

AVA Documents Document Sharing Hub

Full document details: IEC 62489-2 2014

- rapidly varying amplitude;
- high ratio of peak amplitude to average r.m.s. amplitude (at least 4).

5 Configurations of loops

5.1 Main types of configuration

There are four main types of configuration:

a) large area loops, with the smallest dimension larger than 1 m, usually installed at floor level in a room;

b) medium-area loops, with dimensions of the order of 1 m, often oriented in a vertical plane, installed at service desks and similar positions;

c) small area loops, with the largest dimension less than 1 m;

d) solenoid antennas, including the ear-hook.

NOTE Examples of small-area loops are portable systems, clipboards, neck loops, cushion loops (including those for use in vehicles) and chair loops.

5.2 General considerations

All loops produce strong fields close to the loop conductor(s). This is shown by the relationship between current I in a long, straight wire and the magnetic field strength H produced at a distance R from the centre of the wire, where R is greater than the radius r of the wire:

$$H = I/2\pi R \tag{1}$$

NOTE 1 Within the wire, the field strength decreases linearly from $I/2\pi r$ at the surface to zero at the centre.

NOTE 2 For n parallel conductors very close together (i.e. a multi-turn loop), the magnetic field strength is n times that produced by a single conductor.

For calculations of field strengths in the high field strength regions, very close to the conductor(s), the 'long, straight wire' approximation is almost always sufficiently accurate, except for solenoids, which need a completely different treatment (see 6.2).

5.3 Large-area loops

The occupants of a room are likely to come close to the loop conductor only by stepping on the floor at a point below which the conductor is installed. Such proximity is normally transient. However, in places of worship, devotional postures can bring parts of the body other than the feet into proximity. This can also apply in hospitals, treatment rooms and gymnasia.

Maintenance staff might come into closer contact and for longer periods, but it is unlikely that the system would then be operating.

5.4 Medium-area loops

For these, there are three considerations.

a) The hearing-aid user is normally at a distance from the loop comparable to its dimensions. Thus the loop current required to produce a maximum r.m.s. field strength of 400 mA/m (in compliance with IEC 60118-4) at the hearing-aid is much larger than the current required to produce it at the centre of the plane of the loop.

b) Nevertheless, the separation ensures that the hearing-aid user is not exposed to the high fields strengths near the loop conductor.

AVA Documents
Document Sharing Hub

Full document details: IEC 62489-2 2014

c) However, staff can come into close proximity of the loop conductor while the system is working unless steps are taken to maintain a minimum separation.

NOTE These loops often have more than one turn, so that the loop current can be kept reasonably small.

5.5 Small-area loops

For these, again, there are three considerations.

a) The separation for portable loops is very much greater than the loop dimensions, but for other types, the separation distance can be small or very small unless steps are taken to maintain a minimum separation.

b) The current apparently required is quite large, because of the large separation.

c) Both users and staff can come into close proximity of the loop, even that of a portable system.

NOTE These loops usually have many turns, so that the actual current is not so large.

5.6 Solenoid antennas

One example that is commercially available is the ear-hook. This device is typically as shown in Figure 1. A very small solenoid is incorporated in the stem of the device.

IEC

Figure 1 – An ear-hook induction transducer, with a BTE (behind the ear) hearing aid body for scale

6 Calculations

6.1 General

Calculation of the field strength can be reliably made using Equation (1) in almost all cases, except where the loop is very small or is a solenoid of length which is not very small compared with its plan dimensions, such as for the ear-hook device. It is necessary to calculate the current required in the loop to produce a field strength of 400 mA/m at the hearing-aid position, taking into account the orientation of the pick-up coil in the hearing-aid relative to the plane of the loop. In general, this calculation is not easy, but simple, approximate methods give sufficiently accurate results when used with insight. Proprietary calculation software, based on published mathematical analyses, exists. General-purpose mathematics software can also be used.

Translating the calculated field strengths into a form comparable with exposure guidelines or limits is considered in Clause 8.

AVA Documents
Document Sharing Hub

Full document details: IEC 62489-2 2014

6.2 Solenoid antennas

There is no simple expression for the field strength at a point outside a cylindrical solenoid. A solenoid may be treated as a stack of loops, or as a magnetic dipole, or the field strength can be calculated by means of a rather complex equation (see [2]).

7 Measurements

7.1 General

In the audio-frequency range, exposure time is irrelevant, because the predominant physiological effect, if it occurs, is nerve stimulation, which operates over a time-scale of a few milliseconds. It is therefore appropriate to use a quasi-peak measurement of field strength. Furthermore, exposure limits and guidelines are given in r.m.s. values, so the quasi-peak meter should be scaled to read r.m.s. values with a sinusoidal signal. This type of meter, the peak programme meter (PPM), is further described in IEC 60118-4 and IEC 60268-10 (type II) already.

It is also necessary to consider the type of magnetic field pick-up coil or sensor. Sensors may be single-axis, with just one coil, or three-axis, with three orthogonal coils. For use with a PPM, the single-axis sensor is most convenient, and if it is properly constructed, it is not difficult to orient it for maximum reading, especially as the likely direction of the field can usually be predicted from text-book field patterns.

The first measurement that shall be made is that the field strength is correct at the point or points where it is intended to be 400 mA/m (or the agreed lower value if adjusted to reduce loudness, as specified in IEC 60118-4).

NOTE IEC 60118-4 specifies the use of either a PPM or an r.m.s. meter with a 125 ms integration time for the measurement of magnetic field strength. However, for the purpose of this standard, the 125 ms integration time is incompatible with the requirement to measure field strengths over times of the order of a few milliseconds.

The instrument specified for measurements on other equipment and systems, such as in IEC 62233 [3], has an averaging time specified only as an upper limit of 1 s, which is also too slow for the assessment of fields due to audio-frequency signals.

7.2 Input signal

The input signal for the amplifier shall be the simulated programme signal described in IEC 60268-1, with additional filtering, –3 dB at 100 Hz and 5 kHz relative to the 1 kHz level, with ultimate attenuation slopes of at least 12 dB/octave.

7.3 Measuring instrument

It is unlikely that a suitable complete instrument is commercially available at present, since the application is extremely specialized. However, the design of an adapter for use with widely-available audio test equipment, or that itself provides the PPM function, is not very difficult. The elements are the following.

- The pick-up coil, which, because the field strengths of interest are high, needs few turns and no magnetic core material. Because the fields are highly inhomogeneous, the coil should be of small dimensions to minimize averaging. A coil covering four faces of a 1 cm cube of insulating material is convenient.
- A frequency-response correction circuit, which produces a constant output from a magnetic field that varies with frequency in the same way as the guidelines or limits, with bandwidth control so as to discard out-of band interference signals.
- Amplification of the signal such that the maximum permissible field strength produces an output voltage of 0,775 V for connection to the audio test equipment.
- Optionally, a quasi-peak detector substantially as specified in IEC 60268-10 (type II) and means to display its output with a resolution of 1 dB.

AVA Documents
Document Sharing Hub

Full document details: IEC 62489-2 2014