

INTERNATIONAL STANDARD

NORME INTERNATIONALE

**Alarm systems – Intrusion and hold-up systems –
Part 2-71: Intrusion detectors – Glass break detectors (acoustic)**

**Systèmes d'alarme – Systèmes d'alarme contre l'intrusion et les hold-up –
Partie 2-71: Détecteurs d'intrusion – Détecteurs de bris de glace (acoustiques)**



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2015 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de l'IEC ou du Comité national de l'IEC du pays du demandeur. Si vous avez des questions sur le copyright de l'IEC ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de l'IEC de votre pays de résidence.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
Fax: +41 22 919 03 00
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

IEC Catalogue - webstore.iec.ch/catalogue

The stand-alone application for consulting the entire bibliographical information on IEC International Standards, Technical Specifications, Technical Reports and other documents. Available for PC, Mac OS, Android Tablets and iPad.

IEC publications search - www.iec.ch/searchpub

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and also once a month by email.

Electropedia - www.electropedia.org

The world's leading online dictionary of electronic and electrical terms containing more than 30 000 terms and definitions in English and French, with equivalent terms in 15 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

IEC Glossary - std.iec.ch/glossary

More than 60 000 electrotechnical terminology entries in English and French extracted from the Terms and Definitions clause of IEC publications issued since 2002. Some entries have been collected from earlier publications of IEC TC 37, 77, 86 and CISPR.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: csc@iec.ch.

A propos de l'IEC

La Commission Electrotechnique Internationale (IEC) est la première organisation mondiale qui élabore et publie des Normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

A propos des publications IEC

Le contenu technique des publications IEC est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

Catalogue IEC - webstore.iec.ch/catalogue

Application autonome pour consulter tous les renseignements bibliographiques sur les Normes internationales, Spécifications techniques, Rapports techniques et autres documents de l'IEC. Disponible pour PC, Mac OS, tablettes Android et iPad.

Recherche de publications IEC - www.iec.ch/searchpub

La recherche avancée permet de trouver des publications IEC en utilisant différents critères (numéro de référence, texte, comité d'études,...). Elle donne aussi des informations sur les projets et les publications remplacées ou retirées.

IEC Just Published - webstore.iec.ch/justpublished

Restez informé sur les nouvelles publications IEC. Just Published détaille les nouvelles publications parues. Disponible en ligne et aussi une fois par mois par email.

Electropedia - www.electropedia.org

Le premier dictionnaire en ligne de termes électroniques et électriques. Il contient plus de 30 000 termes et définitions en anglais et en français, ainsi que les termes équivalents dans 15 langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International (IEV) en ligne.

Glossaire IEC - std.iec.ch/glossary

Plus de 60 000 entrées terminologiques électrotechniques, en anglais et en français, extraites des articles Termes et Définitions des publications IEC parues depuis 2002. Plus certaines entrées antérieures extraites des publications des CE 37, 77, 86 et CISPR de l'IEC.

Service Clients - webstore.iec.ch/csc

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions contactez-nous: csc@iec.ch.

INTERNATIONAL STANDARD

NORME INTERNATIONALE

**Alarm systems – Intrusion and hold-up systems –
Part 2-71: Intrusion detectors – Glass break detectors (acoustic)**

**Systèmes d'alarme – Systèmes d'alarme contre l'intrusion et les hold-up –
Partie 2-71: Détecteurs d'intrusion – Détecteurs de bris de glace (acoustiques)**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

COMMISSION
ELECTROTECHNIQUE
INTERNATIONALE

ICS 13.320

ISBN 978-2-8322-2920-0

**Warning! Make sure that you obtained this publication from an authorized distributor.
Attention! Veuillez vous assurer que vous avez obtenu cette publication via un distributeur agréé.**

CONTENTS

FOREWORD.....	5
INTRODUCTION.....	7
1 Scope.....	8
2 Normative references	8
3 Terms, definitions and abbreviations	8
3.1 Terms and definitions.....	8
3.2 Abbreviations	9
4 Functional requirements	9
4.1 Event processing	9
4.2 Operational requirements.....	11
4.2.1 Time interval between intrusion signals or messages.....	11
4.2.2 Switch on delay	11
4.2.3 Self tests	11
4.3 Detection	11
4.3.1 Detection performance.....	11
4.3.2 Indication of detection.....	12
4.4 Immunity to false alarm sources.....	12
4.4.1 General	12
4.4.2 Immunity to small objects hitting the glass	12
4.4.3 Immunity to soft objects hitting the glass	12
4.4.4 Immunity to hard objects hitting the glass	12
4.4.5 Immunity to single frequency sound sources.....	13
4.4.6 Immunity to wide band noise.....	13
4.5 Tamper security	13
4.5.1 General	13
4.5.2 Resistance to and detection of unauthorised access to the inside of the detector through covers and existing holes	13
4.5.3 Detection of removal from the mounting surface	13
4.5.4 Detection of masking	14
4.5.5 Immunity to magnetic field interference.....	14
4.5.6 Resistance to, or detection of, re-orientation.....	14
4.6 Electrical requirements	14
4.6.1 General	14
4.6.2 Detector current consumption	14
4.6.3 Slow input voltage rise and voltage range limits.....	15
4.6.4 Input voltage ripple	15
4.6.5 Input voltage step change.....	15
4.7 Environmental classification and conditions	15
4.7.1 Environmental classification.....	15
4.7.2 Immunity to environmental conditions	15
5 Marking, identification and documentation	15
5.1 Marking and/or identification	15
5.2 Documentation.....	15
6 Testing	16
6.1 General.....	16
6.2 General test conditions	16

6.2.1	Standard laboratory conditions for testing	16
6.2.2	General detection testing environment and procedures	16
6.3	Basic detection test	17
6.3.1	General	17
6.3.2	Basic test source	17
6.3.3	Basic detection test method	18
6.4	Performance tests	18
6.4.1	General	18
6.4.2	Verification of detection performance	18
6.4.3	Hole drilling with a diamond hole saw	19
6.4.4	Glass cutting	19
6.5	Switch-on delay, time interval between signals, and indication of detection	20
6.6	Fault condition signals or messages: self tests	20
6.7	Tests of immunity to false alarm sources	21
6.7.1	General	21
6.7.2	Immunity to small objects hitting the glass	21
6.7.3	Immunity to soft objects hitting the glass	22
6.7.4	Immunity to hard objects hitting the glass	22
6.7.5	Immunity to single frequency sound sources	22
6.7.6	Immunity to wide band noise based using flat steel rulers	23
6.7.7	Immunity to wide band noise based using ICs	23
6.8	Tamper security	24
6.8.1	General	24
6.8.2	Prevention of unauthorised access to the inside of the detector through covers and existing holes	24
6.8.3	Detection of removal from the mounting surface	24
6.8.4	Resistance to or detection of re-orientation of adjustable mountings	24
6.8.5	Resistance to magnetic field interference	24
6.8.6	Detection of masking	25
6.9	Electrical tests	26
6.9.1	General	26
6.9.2	Detector current consumption	26
6.9.3	Slow input voltage change and input voltage range limits	26
6.9.4	Input voltage ripple	27
6.9.5	Input voltage step change	27
6.9.6	Total loss of power supply	27
6.10	Environmental classification and conditions	28
6.11	Marking, identification and documentation	29
6.11.1	Marking and/or identification	29
6.11.2	Documentation	29
Annex A (informative)	Example of the setup of the test room	30
Annex B (normative)	Catalogue of standard glass types	31
Annex C (normative)	List of small tools suitable for testing immunity of casing to attack	32
Annex D (normative)	Dimensions and requirements of a standard test magnet	33
D.1	Reference documents	33
D.2	Requirements	33
Annex E (normative)	Immunity test: small objects hit sensitivity	36
Annex F (normative)	Immunity test: soft objects hit sensitivity	37

Annex G (normative) Immunity test: hard objects hit sensitivity	38
Annex H (normative) General testing matrix	39
Annex I (normative) Immunity test: noise sensitivity	41
Annex J (normative) Performance test setup and alternative performance test setup	42
J.1 Performance test setup	42
J.2 Alternative performance test setup	43
Annex K (informative) Manipulation test: resistance to re-orientation of adjustable mountings	45
Bibliography	46
Figure A.1 – Schematic test room setup	30
Figure D.1 – Test magnet – Magnet type 1	34
Figure D.2 – Test magnet – Magnet type 2	35
Figure E.1 – Immunity test setup for small object hit sensitivity	36
Figure F.1 – Immunity test setup for soft object hit sensitivity	37
Figure G.1 – Immunity test setup for hard object hit sensitivity	38
Figure I.1 – Immunity test setup for noise sensitivity	41
Figure J.1 – Performance test setup	42
Figure J.2 – Alternative performance test setup	44
Table 1 – Events to be processed by grade	10
Table 2 – Generation of indication signals or messages	10
Table 3 – Performance test requirements	11
Table 4 – Tamper security requirements	13
Table 5 – Electrical requirements	14
Table 6 – Wide band noise simulation based on flat steel rulers	23
Table 7 – Range of materials for masking tests	26
Table 8 – Operational tests	28
Table 9 – Endurance tests	29
Table B.1 – Standard glass types	31
Table H.1 – Test and sample matrix	39
Table J.1 – Performance test setup: glass types, maximum thickness and minimum dropping height	43
Table J.2 – Alternative performance test setup: standard glass types, maximum thickness	43

INTERNATIONAL ELECTROTECHNICAL COMMISSION

ALARM SYSTEMS – INTRUSION AND HOLD-UP SYSTEMS –**Part 2-71: Intrusion detectors – Glass break detectors (acoustic)**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 62642-2-71 has been prepared by IEC technical committee 79: Alarm and electronic security systems.

This standard is based on EN 50131-2-7-1 (2012) and its IS1 (2014).

The text of this standard is based on the following documents:

FDIS	Report on voting
79/511/FDIS	79/527/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all parts in the IEC 62642 series, published under the general title *Alarm systems – Intrusion and hold-up systems*, can be found on the IEC website.

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC website under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

INTRODUCTION

This part 2-71 of the IEC 62642 series concerns of intrusion and hold-up alarm systems (I&HAS) installed in buildings. It includes devices that are installed inside or outside of the supervised premises and mounted in indoor or outdoor environments. The other parts of this series of standards are as follows:

Part 1	System requirements
Part 2-2	Intrusion detectors – Passive infrared detectors
Part 2-3	Intrusion detectors – Microwave detectors
Part 2-4	Intrusion detectors – Combined passive infrared / Microwave detectors
Part 2-5	Intrusion detectors – Combined passive infrared / Ultrasonic detectors
Part 2-6	Intrusion detectors – Opening contacts (magnetic)
Part 2-71	Intrusion detectors – Glass break detectors (acoustic)
Part 2-72	Intrusion detectors – Glass break detectors (passive)
Part 2-73	Intrusion detectors – Glass break detectors (active)
Part 3	Control and indicating equipment
Part 4	Warning devices
Part 5-3	Interconnections – Requirements for equipment using radio frequency techniques
Part 6	Power supplies
Part 7	Application guidelines
Part 8	Security fog devices/systems

ALARM SYSTEMS – INTRUSION AND HOLD-UP SYSTEMS –

Part 2-71: Intrusion detectors – Glass break detectors (acoustic)

1 Scope

This part of IEC 62642 defines passive acoustic glass break detectors installed in buildings and provides for security grades 1 to 4 (see IEC 62642-1), specific or non-specific wired or wire-free detectors, and uses environmental classes I to IV (see IEC 62599-1). This International Standard does not include requirements for passive acoustic glass break detectors intended for use outdoors.

A detector complies with all the requirements of the specified grade.

Functions additional to the mandatory functions specified in this standard may be included in the detector, providing they do not adversely influence the correct operation of the mandatory functions.

This International Standard does not apply to system interconnections.

2 Normative references

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60068-2-52:1984, *Basic environmental testing procedures – Part 2: Tests – Test Kb: Salt mist, cyclic (sodium, chloride solution)*¹

IEC 62599-1, *Alarm systems – Part 1: Environmental test methods*

IEC 62599-2, *Alarm systems – Part 2: Electromagnetic compatibility – Immunity requirements for components of fire and security alarm systems*

IEC 62642-1, *Alarm systems – Intrusion and hold-up systems – Part 1: System requirements*

3 Terms, definitions and abbreviations

For the purposes of this document, the terms, definitions and abbreviations given in IEC 62642-1, as well as the following apply.

3.1 Terms and definitions

3.1.1

glass breakage

physical destruction of a glass pane, which allows intrusion to the monitored area, for example in doors, windows or enclosures

¹ First edition. This edition has been replaced in 1996 by IEC 60068-2-52:1996, *Environmental testing – Part 2: Tests – Test Kb: Salt mist, cyclic (sodium, chloride solution)*.

3.1.2**passive acoustic glass break detector**

detector that is mounted in the area to be monitored, which detects an airborne acoustic event created by a glass breakage

3.1.3**basic test source**

signal simulator designed to verify the basic function of the detector

3.1.4**incorrect operation**

physical condition that causes an inappropriate signal or message from a detector

3.1.5**basic detection test**

test whose purpose is to verify the operation of a detector after conditioning

3.1.6**masking**

interference with the detector input capability such as an introduction of a physical barrier (e.g. metal, plastic, paper or sprayed paints or lacquers in close proximity to the detector) or changing the characteristics of the monitored area (e.g. placing wet newspapers on the outside of the monitored glass pane)

3.1.7**standard immunity glass pane**

glass pane to be used for all immunity tests, where a glass pane is needed, according to Annex B

3.1.8**reverberation time 60**

time taken for the volume of a single sound to decrease by 60 dB

Note 1 to entry: Reverberation time (RT60) at a frequency of 4 kHz shall not be less than 0,5 s and no more than 1 s. If required, reverberation time may be adjusted by installing absorbent panels or surfaces in the room.

3.2 Abbreviations

BTS basic test source

EMC electromagnetic compatibility

RT60 reverberation time 60

4 Functional requirements**4.1 Event processing**

Detectors shall process the events shown in Table 1. Detectors shall generate signals or messages as shown in Table 2.

Table 1 – Events to be processed by grade

Event	Grade			
	1	2	3	4
Intrusion	M	M	M	M
No stimulus ^a	M	M	M	M
Masking	Op	Op	M	M
Tamper	Op	M	M	M
Low supply voltage	Op	Op	M	M
Total loss of power supply	Op	M	M	M
Local self test	Op	Op	M	M
Remote self test	Op	Op	Op	M
M = Mandatory Op = Optional ^a 'No Stimulus' is considered to be the quite condition, while no alarm generating stimulus for a detector at that time applies to the detector input capabilities.				

Table 2 – Generation of indication signals or messages

Event	Signals or messages		
	Intrusion	Tamper	Fault
Intrusion	M	NP	NP
No Stimulus	NP	NP	NP
Masking ^a	M	Op	M
Tamper	NP	M	NP
Low supply voltage	Op	Op	M
Total loss of power supply ^b	M	Op	Op
Local self test pass	NP	NP	NP
Local self test fail	NP	NP	M
Remote self test pass	M	NP	NP
Remote self test fail	NP	NP	M
M = Mandatory NP = Not permitted Op = Optional			
^a An independent masking signal or message may be provided instead.			
^b Alternatively total loss of power supply shall be determined by loss of communication with the detector.			
This permits two methods of signalling a masking event: either by the intrusion signal and fault signal, or by a dedicated output. Use of the intrusion signal and fault signal is preferable, as this requires fewer connections between CIE and detector. If multiple events overlap there will be some signal combinations that may be ambiguous. To overcome this ambiguity it is suggested that detectors should not signal 'intrusion' and 'fault' at the same time except to indicate masking. This implies that the detector should prioritise signals, e.g. 1. Intrusion, 2 Fault, 3 Masking.			
When, in Table 1, an event may optionally generate signals or messages, they shall be as shown in Table 2.			

4.2 Operational requirements

4.2.1 Time interval between intrusion signals or messages

Wired detectors shall be able to provide an intrusion signal or message not more than 15 s after the end of the preceding intrusion signal or message.

Wire free detectors shall be able to provide an intrusion signal or message after the end of the preceding intrusion signal or message within the following times:

Grade 1	300 s
Grade 2	180 s
Grade 3	30 s
Grade 4	15 s

4.2.2 Switch on delay

The detector shall meet all functional requirements within 180 s of the power supply reaching its nominal voltage as specified by the manufacturer.

4.2.3 Self tests

4.2.3.1 Local self test

The detector shall automatically test itself at least once every 24 h according to the requirements of Tables 1 and 2. If normal operation of the detector is inhibited during a local self-test, the detector inhibition time shall be limited to a maximum of 30 s in any period of 2 h.

4.2.3.2 Remote self test

A detector shall process remote self tests and generate signals or messages in accordance with Tables 1 and 2 within 10 s of the remote self test signal being received, and shall return to normal operation within 30 s of the remote test signal being received.

4.3 Detection

4.3.1 Detection performance

4.3.1.1 General

The detector shall generate an intrusion signal or message when a simulated or real glass breakage according to the corresponding requirements of Table 3 is performed.

Table 3 – Performance test requirements

Requirement	Grade 1	Grade 2	Grade 3	Grade 4
Verification of detection performance	M	M	M	M
Performance test: hole drilling with diamond hole saw	Op	Op	Op	M
Performance test: glass cutting	Op	Op	Op	M
M = Mandatory				
Op = Optional				

4.3.1.2 Verification of detection performance

This test will verify the detection performance of a glass breakage according to the supported conditions claimed by the manufacturer. It will verify the covering range including the maximum and minimum range as well as the performance of randomly chosen mounting locations of the detector, according to Annex B for different glass types and sizes claimed to be supported (types and dimensions) by the manufacturer. A number of standard glass types and sizes need to be passed by this test according to the corresponding test section.

4.3.1.3 Performance test for hole drilling with a diamond hole saw

This test will verify the detection performance by drilling a hole using a diamond hole saw on different glass types and dimensions according to the supported conditions claimed by the manufacturer and Annex B. It will verify if the detector is able to identify and signal the change of the integrity of the monitored side of the glass pane.

4.3.1.4 Performance test for glass cutting

This test will verify the detection performance by cutting the glass using a standard glass cutter on different glass types and dimensions according to the supported conditions claimed by the manufacturer and Annex B. It will verify if the detector is able to identify and signal the change of the integrity of the monitored side of the glass pane.

4.3.2 Indication of detection

Powered detectors at grades 3 and 4 that include processing capabilities shall provide an indicator at the detector to indicate when an intrusion signal or message has been generated.

At grades 3 and 4 this indicator shall be capable of being enabled and disabled remotely at access level 2.

4.4 Immunity to false alarm sources

4.4.1 General

The detector shall have sufficient immunity to false alarm sources if the following requirements have been met. No intrusion signal or message shall be generated as a result of the false alarm sources according to each individual test clause.

The tests for this clause will be performed on the standard immunity test glass pane as defined in section 3.1.7, wherever a glass pane is required.

4.4.2 Immunity to small objects hitting the glass

The detector shall not generate an intrusion signal or message when small objects such as hail, sand, gravel etc. hit the outside of the monitored glass. The tests are described in 6.7.2.

4.4.3 Immunity to soft objects hitting the glass

The detector shall not generate an intrusion signal or message when soft objects (e.g. a human fist) hit the outside of the monitored glass. The tests are described in 6.7.3.

4.4.4 Immunity to hard objects hitting the glass

The detector shall not generate an intrusion signal or message when hard objects (e.g. handlebars of a bicycle) hit the outside of the monitored glass. The tests are described in 6.7.4.

4.4.5 Immunity to single frequency sound sources

The detector shall not generate an intrusion signal or message when various frequencies and levels of noise (like brakes of a lorry, etc.) are applied to the detector. The tests are described in 6.7.5.

4.4.6 Immunity to wide band noise

The detector shall not generate an intrusion signal or message when a wide band of frequencies at the same time, which are close to the frequency of a glass breakage (e.g. branches of a tree moving against the window) are applied to the detector. The tests are described in 6.7.6 and 6.7.7.

4.5 Tamper security

4.5.1 General

Tamper security requirements for each grade of a detector are shown in Table 4.

Table 4 – Tamper security requirements

Requirement	Grade 1	Grade 2	Grade 3	Grade 4
Resistance to access to the inside of the detector	M	M	M	M
Detection of access to the inside of the detector	Op	M	M	M
Removal from the mounting surface	Op	M ^a	M	M
Detection of masking	Op	Op	M	M
Magnetic field immunity	Op	M	M	M
Magnet type defined in Annex D		Type 1	Type 2	Type 2
Resistance to or detection of re-orientation ^b	Op	M	M	M
Applied torque		2 Nm	5 Nm	10 Nm
M = Mandatory				
Op = Optional				
^a Required for wire free detectors only				
^b Required for detectors mounted on brackets only				

4.5.2 Resistance to and detection of unauthorised access to the inside of the detector through covers and existing holes

All components and means of adjustment and access to mounting screws, which, when interfered with, could adversely affect the operation of the detector, shall be located within the detector housing. Such access shall require the use of an appropriate tool and depending on the grade as specified in Table 4 shall generate a tamper signal or message before access can be gained.

It shall not be possible to gain access without generating a tamper signal or message or causing visible damage.

4.5.3 Detection of removal from the mounting surface

A tamper signal or message shall be generated if the detector is removed from its mounting surface, in accordance with Table 4.

4.5.4 Detection of masking

Means shall be provided to detect inhibition of the operation of the detector by masking according to the requirements of Table 4. Alternatively, the detector shall continue to operate normally.

In an I&HAS any masked detectors shall prevent setting of the system.

The maximum response time for the masking detection device shall be 180 s. Masking shall be signalled according to the requirements of Table 2. The signals or messages shall remain for at least as long as the masking condition is present. A masking signal or message shall not be reset while the masking condition is still present. Alternatively the masking signal or message shall be generated again within 180 s of being reset if the masking condition is still present.

NOTE From a system design point of view it would be preferable for masked detectors to automatically reset after the masking condition is removed.

For detectors where detection of masking may be remotely disabled, the detection of masking shall operate when the I&HAS is unset; it is not required to operate when the I&HAS is set.

4.5.5 Immunity to magnetic field interference

It shall not be possible to inhibit any signals or messages with a magnet of grade dependence according to Table 4. The magnet types shall be as described in Annex D.

4.5.6 Resistance to, or detection of, re-orientation

When the torque given in Table 4 has been applied to the detector and then removed, the detector shall be within 5° of its original orientation. Alternatively, when the torque given in Table 4 is applied, a tamper signal or message shall be generated before the detector has rotated by 5°.

The manufacturer should indicate if the detector is directional sensitive; if this is the case, this requirement applies.

4.6 Electrical requirements

4.6.1 General

These requirements do not apply to detectors having type C power supplies. For these detectors refer to IEC 62642-6. For detectors having an external power supply, the requirements appear in Table 5.

Table 5 – Electrical requirements

Test	Grade 1	Grade 2	Grade 3	Grade 4
Detector current consumption	Required	Required	Required	Required
Input voltage range	Required	Required	Required	Required
Slow input voltage rise	Not required	Required	Required	Required
Input voltage ripple	Not required	Required	Required	Required
Input voltage step change	Not required	Required	Required	Required

4.6.2 Detector current consumption

The detector's quiescent and maximum current consumption shall not exceed the figures claimed by the manufacturer at the nominal input voltage.

4.6.3 Slow input voltage rise and voltage range limits

The detector shall meet all functional requirements when the input voltage lies between $\pm 25\%$ of the nominal value, or between the manufacturers range limits if greater. When the supply voltage is raised slowly, the detector shall function normally at the specified range limits.

4.6.4 Input voltage ripple

The detector shall meet all functional requirements during the sinusoidal variation of the input voltage by $\pm 10\%$ of nominal, at a frequency of 100 Hz.

4.6.5 Input voltage step change

No signals or messages shall be caused by a step in the input voltage between maximum or minimum and nominal values of the input voltage.

4.7 Environmental classification and conditions

4.7.1 Environmental classification

The environmental classification is described in IEC 62642-1 and shall be specified by the manufacturer.

4.7.2 Immunity to environmental conditions

All detectors shall meet the requirements of the relevant environmental class and equipment class as specified by the manufacturer of the environmental tests described in Table 8 and Table 9. These tests shall be performed in accordance with IEC 62599-1 and IEC 62599-2.

Impact tests shall not be carried out on delicate detector components such as LEDs or microphones.

Unless specified otherwise for operational tests, the detector shall not generate unintentional intrusion, tamper, fault or other signals or messages when subjected to the specified range of environmental conditions.

For endurance tests, the detector shall continue to meet the requirements of this standard after being subjected to the specified range of environmental conditions.

5 Marking, identification and documentation

5.1 Marking and/or identification

Marking and/or identification shall be applied to the product in accordance with the requirements of IEC 62642-1.

5.2 Documentation

The product shall be accompanied with clear and concise documentation conforming to the main systems document IEC 62642-1. The documentation shall additionally state:

- a) a list of all options, functions, inputs, signals or messages, indications and their relevant characteristics;
- b) any disallowed field adjustable control settings or combinations of these;
- c) where alignment adjustments are provided, these shall be labelled as to their function;
- d) the manufacturer's quoted nominal operating voltage and the maximum and quiescent current consumption at that voltage;

- e) the detection range (minimum and maximum) and coverage diagram showing top and side elevations. The installation instructions shall be clear and concise that the maximum range will include the farthest point from the sensor input to any point of the monitored glass;
- f) all types, minimum size, minimum and maximum thickness of glass for which the detector is claimed to detect;
- g) any restrictions according to the mounting location of the detector, or any other restrictions which apply to the performance of the detector;
- h) a warning to the user not to obscure partially or completely the detector's field of view with large objects such as furniture, curtains, blinds, if required;
- i) any specific settings needed to meet the requirements of this document at the claimed grade.

6 Testing

6.1 General

The tests are intended to be primarily concerned with verifying the correct operation of the detector to the specification provided by the manufacturer. All the test parameters specified shall carry a general tolerance of $\pm 10\%$ unless otherwise stated, for acoustic measurements a general tolerance of ± 3 dB is applicable. A list of tests appears as a general test matrix in Annex H.

6.2 General test conditions

6.2.1 Standard laboratory conditions for testing

The general atmospheric conditions in the measurement and tests laboratory shall be those specified below, unless stated otherwise.

Temperature	15 °C to 35 °C
Relative humidity	25 % RH to 75 % RH
Air pressure	86 kPa to 106 kPa
Noise level	Shall not exceed 65 dB C-weighted (alternatively 70 dB linear) in the frequency range of 12,5 kHz to 16 kHz; time averaging has to be set to fast (0,125 s) when measuring

6.2.2 General detection testing environment and procedures

6.2.2.1 General

Manufacturer's documented instructions regarding mounting and operation shall be read and applied to all tests.

6.2.2.2 Testing environment

For passive acoustic glass break detectors, the detection tests require an enclosed, unobstructed and draught-free area having a length at least 15 % larger in the long dimension and at least half of long dimension length in the short dimension than the manufacturers claimed range.

NOTE An example of a potential calculation for a detector with a claimed range of 10 m would be:

- min. long dimension = $10\text{ m} + 1,5\text{ m (15 \%)} = 11,5\text{ m}$;
- min. short dimension = $11,5\text{ m} / 2 = 5,75\text{ m}$.

See Annex A for a description of a potential test room. The minimum sized standardized glass types (glass window or door glass pane as defined in Annex B) needs to be in a fixed off centre position in both directions (horizontal and vertical) in a fixed solid wall e.g. brick, block or concrete.

The fixed off centre means the mounting position of the window, whereas the minimum distance of the window centre is between 15 % and 40 % of the length of the mounted wall from either side of the wall.

The detectors shall be mounted in the as-used position on a wall, or ceiling at the height specified by the manufacturer.

Testing the maximum detection range of a passive acoustic glass break detector can be performed by installing a detector in the maximum distance position on a wall or ceiling, whereas the maximum distance will be measured as in the corresponding test section described.

Alternatively to the wall or ceiling, it can be installed on a free standing rig, whereas the installation position has to be in the horizontal centre of a 1,20 m wide, 2,40 m high and 18 mm thick laminated wooden plate. The free standing rig has to be setup in opposite and parallel position to the monitored object.

Testing the minimum detection range of a passive acoustic glass break detector can be performed by installing a detector in the minimum distance position on a wall, ceiling or close by the monitored object, whereas the minimum distance will be measured as in the corresponding test section described.

The test room shall comply with the RT60 definition.

6.2.2.3 Test procedures

The tests will be performed with the types of glass claimed by the manufacturer. These tests will be performed with the sizes and thicknesses of glass specified in Annex B.

Additionally, tests will be performed with the minimum size claimed by the manufacturer, if it is smaller than the minimum size specified in Annex B.

Additionally, tests will be performed with the thinnest glass claimed by the manufacturer, if it is thinner than the minimum thickness specified in Annex B.

The detector shall be connected to the nominal supply voltage and connected to the monitoring system that is appropriate to the test. The detector shall be allowed to stabilise for 180 s. The intrusion signal or message output shall be monitored. If multiple sensitivity modes are available, any non-compliant modes shall be identified by the manufacturer. All compliant modes shall be tested.

6.3 Basic detection test

6.3.1 General

The purpose of the basic detection test is to verify that a detector is still operational after a test or tests has/have been carried out. The basic detection verifies only the qualitative performance of the detector. The basic detection test is performed using the BTS.

6.3.2 Basic test source

For functional verification there shall be a device available which will simulate a glass breakage or destruction, without breaking the glass (BTS), alternatively a pane of standard sized glass (see Annex B) can be broken to verify the detection. The basic test source (BTS) which is specified by the manufacturer simulates the breaking of a standard glass window by the low energy attack test.

The available test device shall be based on recorded glass break sounds, from or recommended by the manufacturer. This device should be a glass break simulator which ensures reliable locating and testing of passive acoustic glass break detectors. The passive acoustic glass break simulator should generate plate or tempered glass sound samples.

6.3.3 Basic detection test method

The detector shall generate an intrusion signal or message when a test device (BTS) is used to simulate a glass breakage. The test will be performed according to the manufacturer's instructions after the first installation, to verify, that all detectors are installed properly. It will be performed again, after or / and during the environmental tests under the same conditions the tests had been performed the first time, to verify that the detectors will still function the way, the manufacturer claims to support (e.g. detection range) and to compare this results with the results of the initial test.

If the test is not compatible with the detector, use the manufacturer's information to generate the correct algorithm.

The detector(s) shall produce an intrusion signal or message when exposed to an alarm stimulus both before and after being subjected to any test that may adversely affect its performance.

6.4 Performance tests

6.4.1 General

The general test conditions of 6.2.2 shall apply to all tests in this series.

Detection performance shall be tested against the manufacturer's documented claims. Any variable controls shall be set to the values recommended by the manufacturer to achieve the claimed performance.

The detectors shall be assessed in the specified test environment.

6.4.2 Verification of detection performance

All performance tests shall use the sound of breakage of the size, thickness and types of glass claimed to be supported by the manufacturer including the standard glass types listed in Annex B, if claimed to be supported by the manufacturer:

- Minimum thickness and minimum size

For each glass type claimed to be supported, two panes of the minimum thickness and minimum size according to the manufacturer will be tested by dropping a steel ball according to the test set up of Annex J. Nine detectors shall be used to measure the detection performance.

Pass/fail criteria: At least 16 out of 18 attempts shall be detected for each glass type. No single detector shall miss more than one time.

- Maximum thickness and minimum size

For each glass type claimed to be supported, two panes of the maximum thickness and minimum size according to the manufacturer will be tested by dropping a steel ball according to the test set up of Annex J. Nine detectors shall be used to measure the detection performance.

Pass/fail criteria: At least 16 out of 18 attempts shall be detected for each glass type. No single detector shall miss more than one time.

- Standard sized glass per glass type as specified in Annex B

For each glass type claimed to be supported according to the manufacturer, two panes within the range between the minimum and maximum standard thickness and standard

size will be tested by dropping a steel ball according to the test set up of Annex J. Nine detectors shall be used to measure the detection performance.

Pass/fail criteria: At least 16 out of 18 attempts shall be detected for each glass type. No single detector shall miss more than one time.

Nine detectors shall be mounted at different positions according to the installation instructions of the manufacturer. If ceiling mounting is supported, one of the 9 detectors shall be mounted on the ceiling according the installation instructions of the manufacturer.

One of the detectors shall be mounted at the maximum distance claimed to be supported. The maximum distance is measured from the farthest point of the monitored glass to the detectors case. The detector shall be installed on any position of a wall or ceiling if claimed to be supported by the manufacturer, alternatively on a free standing rig according to 6.2.2.2. If the room is larger than the supported maximum range of the detector, it is allowed to install one or more detector(s) on an adjacent wall to the window in maximum distance to the monitored glass.

One of the detectors shall be mounted at the minimum distance claimed to be supported. The minimum distance is measured from the nearest point of the monitored glass to the detectors case. The detector shall be installed on any position of a frame, wall or ceiling if claimed to be supported by the manufacturer.

Four detectors shall be mounted along the boundary of the coverage range claimed to be supported by the manufacturer on randomly chosen positions.

All other detectors shall be mounted on randomly chosen positions.

6.4.3 Hole drilling with a diamond hole saw

This test will be performed according to the grading listed in Table 3.

The drilling of a hole using a diamond hole saw will be performed. It will be verified, if the detector is able to identify and signal the change of the integrity of the monitored side of the glass pane. Three detectors will be mounted according to the installation instructions of the manufacturer. A diamond hole saw with a diameter of 20 mm (± 1 mm) will be used to drill a hole into the glass pane opposite to the monitored side. This will be performed once in the most distant position to the detector and four times on randomly chosen positions within the coverage range claimed to be supported by the manufacturer.

Pass/fail criteria: The test is passed successfully, if the detector(s) has indicated the change of the integrity of the glass pane for the most distant position and detected at least three out of the four attempts on the randomly chosen positions. In case the change of integrity for the most distant position was not indicated, it is allowed to carry out three more tests in the most distant position, whereas all of them need to be indicated by the detector.

A change of integrity of a glass pane can be either a successful hole drilling or a destruction of the glass, complete or in parts, which allows access to the side where the detector or the sensor(s) are mounted.

These tests need to be repeated for each glass type with the minimum size and minimum thickness claimed to be supported by the manufacturer.

6.4.4 Glass cutting

This test will be performed according to the grading listed in Table 3.

A standard glass cutter will be used to cut a piece of glass on the opposite side where the detector or its sensor element is mounted and the cut piece will be carefully broken.

be performed once in the most distance position to the detector and four times on randomly chosen positions. At one location there will be a circle created, with a diameter of 100 mm $\pm$ 10 mm and carefully removed out of the glass pane.

Pass/fail criteria: The test is passed successfully, if the detector(s) has indicated the change of the integrity of the glass pane for the most distant position and detected at least three out of the four attempts on the randomly chosen positions. In case the change of integrity for the most distant position was not indicated, it is allowed to carry out three more tests in the most distant position, whereas all of them need to be indicated by the detector.

A change of integrity of a glass pane can be either a successful glass cutting or a destruction of the glass, complete or in parts, which allows access to the side where the detector or the sensor(s) are mounted.

All of the tests need to be repeated for each glass type with the minimum size and minimum thickness claimed to be supported by the manufacturer.

6.5 Switch-on delay, time interval between signals, and indication of detection

The general test conditions of 6.2 shall apply.

Switch on the detector power with the indicator enabled (if provided) and allow 180 s for stabilisation. Carry out the basic detection test. Note the response. After the specified time interval between signals carry out the basic detection test. Note the response. Disable the intrusion indicator (if provided). After the specified time interval between signals carry out the basic detection test. Note the response.

Pass/fail criteria: The detector shall generate an intrusion signal or message in response to each of the three basic detection tests. For the first and second basic detection tests, the intrusion signal or message and the intrusion indicator (if provided) shall both respond. For the third basic detection test there shall be no indication.

6.6 Fault condition signals or messages: self tests

The general test conditions of 6.2 shall apply.

Carry out the basic detection test to verify that the detector is operating.

Pass/fail criteria: The detector shall generate an intrusion signal or message and shall not generate tamper or fault signals or messages.

For grade 3 and 4 detectors, monitor the detector during a local self test.

Pass/fail criteria: The detector shall not generate any intrusion, tamper or fault signals or messages.

For grade 4 detectors, monitor the detector during a remote self test. Note the response.

Pass/fail criteria: The detector shall generate an intrusion signal or message and shall not generate tamper or fault signals or messages.

Short the sensor signal output to ground or carry out an equivalent action as recommended by the manufacturer. For grade 3 and 4 detectors, monitor the detector during a local self test. For grade 4 detectors, also monitor the detector during a remote self test. For detectors with more than one sensor signal output, the test(s) shall be repeated for each output individually.

Pass/fail criteria: (local self test): The detector shall generate a fault signal or message and shall not generate intrusion or tamper signals or messages.

Pass/fail criteria: (remote self test): The detector shall generate a fault signal or message and shall not generate intrusion or tamper signals or messages.

It might be necessary to consult the detector manufacturer regarding the most appropriate method for initiating the specified faults.

6.7 Tests of immunity to false alarm sources

6.7.1 General

The general test conditions of 6.2 shall apply.

The purpose of this test section is to verify that impacts which will not result in a breakage of the monitored glass do not generate any type of signal or message to the CIE.

Before and after each of the following tests a basic functional test (6.3) will be performed, to verify that each detector is still in a valid working and detection condition.

The mounting positions of the detectors shall comply with the manufacturer's instructions. At least one of the detectors shall be mounted in the minimal distance claimed to be supported, if not described different in the corresponding test section.

Pass/fail criteria: There shall be no change of status of the detector during each of the following tests. After each performed test a basic functional test shall generate an alarm signal or message.

6.7.2 Immunity to small objects hitting the glass

This test will simulate hail hitting the window.

Mount six detectors on the opposite ('inner') side of the standard immunity glass pane, 3 kg hail consisting out of Polyoxymethylene according the below specification will be dropped at the other ('out') side of a glass pane running through a plastic tube with a length of 1,80 m, which is mounted at a distance of 50 mm and where at the end the hail will hit the centre of the monitored standard immunity glass pane.

Polyoxymethylene (Delrin®)² ball specification:

Material	Delrin 500 or 100 (or equivalent)
Density	1 390 kg·m ⁻³ to 1 420 kg·m ⁻³ (ISO 1183)
Diameter	12 mm ± 1 mm
Quantity per kg	790 pieces to 800 pieces
Tensile strength	57 MPa to 59 MPa (ISO 527-1/ ISO 527-2)
Rockwell hardness	115 HRR to 122 HRR (ISO 2039-2)

The test set up shall be according to Figure E.1.

The general pass/fail criteria in 6.7.1 shall apply.

² This information is given for the convenience of users of this standard and does not constitute an endorsement by IEC of the product named. Equivalent products may be used if they can be shown to lead to the same results.

6.7.3 Immunity to soft objects hitting the glass

This test will simulate soft objects hitting the centre of the glass pane (e.g. a human fist).

Whereas 6 detectors will be mounted on the opposite ('inner') side of the standard immunity glass pane, a pendulum test with rubber ball with the following characteristics will be performed:

Pendulum object (A)	Rubber ball
Diameter	80 mm $\pm$ 5 mm
Weight	0,38 kg $\pm$ 0,05 kg
Angle α	60° $\pm$ 5°
Number of tests	5
Minimum Pause between each test:	5 s

Each test will consist out of one hit, without repeated bouncing.

The test set up shall be according to Figure F.1.

The general pass/fail criteria in 6.7.1 shall apply.

6.7.4 Immunity to hard objects hitting the glass

This test will simulate hard objects hitting the centre of the glass pane (e.g. handlebars of a bicycle).

Whereas 6 detectors will be mounted on the opposite ('inner') side of the standard immunity glass pane, a pendulum test with a steel ball with the following characteristics will be performed:

Pendulum object (A)	Hardened steel ball
Diameter	40 mm $\pm$ 3 mm
Weight	0,26 kg $\pm$ 0,03 kg
Angle α	27° $\pm$ 1°
Number of tests	5
Minimum pause between each test	5 s

The connection between the steel ball and the upper most point of the pendulum is a cotton string with a diameter of < 3 mm. Each test will consist of one hit, without repeated bouncing.

The test set up shall be according to Figure G.1.

The general pass/fail criteria in 6.7.1 shall apply.

6.7.5 Immunity to single frequency sound sources

This test will simulate noises in different frequency ranges (e.g. brakes of a lorry).

During the following test, a sound at a level of 80 dB will be generated in front of one installed detector. For this test a sounder which supports a frequency range from 20 Hz to 20 kHz, whereas the sinusoidal signal will be changed with a speed of 1 octave per second.

A sounder will be placed 2 m at the same height in front of the detector. The sound level will be measured in immediate vicinity of the detector.

The sound source will be switched on at a pre-selected start sound frequency of 20 Hz; the frequency will be increased with a speed of 1 octave/s until 20 kHz is reached. The sound level of 80 dB at the detector shall be constant. The same test will be repeated, with a pre-selected start frequency of 20 kHz, whereas the frequency will be decreased with a speed of 1 octave per second until 20 Hz is reached.

The test set up shall be according to Figure I.1.

The general pass/fail criteria in 6.7.1 shall apply.

6.7.6 Immunity to wide band noise based using flat steel rulers

This test will simulate a wide band of frequencies, which is close to the sound of a glass breakage.

As a test tool three different types of steel rulers of the following types and characteristics will be used:

- Material: stainless steel with 18 % Cr, 8 % Ni
- 1 short steel ruler: 200 mm total length, cross section 13 by 0,4 mm, app. 0,01 kg
- 1 midsize steel ruler: 300 mm total length, cross section 30 by 1 mm, app. 0,06 kg
- 1 long steel ruler: 500 mm total length, cross section 30 by 1 mm, app. 0,1 kg

Whereas 6 detectors will be mounted on one side ('inner') of the standard immunity glass pane, each steel rule will be placed in different positions on the opposite side ('out') of the glass pane where the detectors are mounted, one end will be held down on the glass, the other end will be bent away and by immediate release snap against the glass according to Table 6:

Table 6 – Wide band noise simulation based on flat steel rulers

Test – Steel ruler type	Description	
	End of ruler hold down distance	Distance the steel ruler is bent from glass
Short steel ruler	3 cm	≤ 12,5 cm
Midsize steel ruler	3,5 cm	≤ 15 cm
Long steel ruler	3,8 cm	≤ 10 cm

This will happen with different intensity and in a different frequency. With each ruler, there should be 5 tests carried out.

The general pass/fail criteria in 6.7.1 shall apply.

6.7.7 Immunity to wide band noise based using ICs

This test will simulate a wide band of frequencies, which is close to the sound of a glass breakage.

As a test tool there will be an Integrated Circuit (IC) with hardened legs / pins DIP40 PIN ICs or equivalent used. The standard immunity glass pane shall be used. The scratching will happen on the opposite side of the glass pane where the detectors are mounted.

Whereas 6 detectors will be mounted on the one ('inner') side of the standard immunity glass pane it will be scratched on the opposite ('outer') side, the maximum test time should last 2 min.

The general pass/fail criteria in 6.7.1 shall apply.

6.8 Tamper security

6.8.1 General

The general test conditions of 6.2.1 shall apply.

6.8.2 Prevention of unauthorised access to the inside of the detector through covers and existing holes

Mount the detector according to the manufacturer's recommendations. Using commonly available small tools such as those specified in Annex C and by attempting to distort the housing attempt to gain access to all components, means of adjustment and mounting screws, which, when interfered with, could adversely affect the operation of the detector.

Pass/fail criteria: Normal access shall require the use of an appropriate tool. For the grades specified in Table 4, it shall not be possible to gain access to any components, means of adjustment and mounting screws, which, when interfered with, could adversely affect the operation of the detector, without generating a tamper signal or message or causing visible damage.

6.8.3 Detection of removal from the mounting surface

Confirm the operation of the back tamper device by removing the detector from the mounting surface. Place the unit on the mounting surface without the fixing screws, unless they form a part of the tamper detection device. Slowly lift the detector away from the mounting surface and attempt to prevent the tamper device from operating by inserting a strip of steel between 100 mm and 200 mm long by 10 mm to 20 mm wide, and 1 mm thick, between the rear of the detector and its mounting surface.

Pass/fail criteria: A tamper signal or message shall be generated before the tamper device can be inhibited.

6.8.4 Resistance to or detection of re-orientation of adjustable mountings

Mount the detector so that it may be turned on the adjustable mount by a measured torque, and the resultant angular displacement assessed both during and after the test, as shown in Annex K.

The levels of grade dependent torque required are given in Table 4.

Connect power to the detector, wait 180 s and place it in the alert/set mode. Apply the required torque. Remove the torque. Measure the angle of twist of the detector relative to the mounting.

Pass/fail criteria: If the angle of re-orientation is less than 5°, the test is passed. Alternatively if a tamper device is provided, it shall generate a tamper signal or message before the angular displacement of 5° is reached, when the required torque is applied.

6.8.5 Resistance to magnetic field interference

Connect power to the detector and wait 180 s. A magnet of nominal remanence in accordance with Annex D and Table 4 shall be placed on each surface of the detector housing in sequence whilst the basic detection test is performed. The magnet shall be applied in a manner that ensures that a single magnetic pole contacts the surface, to maximize flux penetration. Record the response of the detector.

Then interrogate each tamper detection device and record any change of state, including the state of the relay. The magnets shall be as specified in Annex D.

Pass/fail criteria: A tamper signal or message shall be produced, according to Table 4 or the detector shall continue to work normally without a signal or message being generated. The presence of the magnet shall not prevent correct generation of any signal or message.

6.8.6 Detection of masking

For each test, the detector shall be powered, the materials applied as specified in Table 7 and its signals or messages monitored for changes of status.

Material No. 1 shall be applied directly into the microphone hole of the detector.

Material No. 2 shall be applied directly onto the microphone hole of the detector.

Apply the materials Nos. 3 and 4 as specified directly onto the microphone hole of the detector:

Material 3 shall be sprayed using intermittent passes lasting no longer than 2 s each.

Material 4 shall be applied using single passes of the brush.

For materials 3 and 4 repeat the applications until the detector no longer responds or the masking signal is generated

Material No. 5 shall be a box which is large enough to cover the overall detector. The thickness of the foam shall be 5 cm with a tolerance of 10 %.

Material No. 6 (a very liquid glue, which shall harden within in 10 s) shall be injected into the microphone hole, the volume to be injected would be at least 5 ml.

Material No. 7 shall be made flexible and carefully placed into the microphone hole in a way that the hole is completely covered.

After each individual material application for type 1 to 7, wait 180 s for the system to stabilise and carry out a basic detection test.

Material No. 8 shall be placed on the opposite to the monitored side of the standard immunity glass pane, covering the overall surface of the pane. After the material had been applied to the pane wait 180 s for the system to stabilise and perform a breakage of the glass pane according to J.2.

Pass/fail criteria: Either an intrusion or / and a fault signal or message or an independent anti-masking signal or message shall be generated within 180 s of the masking material being applied, and shall continue to be generated as long as the material is in place. Alternatively, the detector shall continue to operate normally.

If an individual test is failed, it shall be repeated twice more. Two passes out of the three tests shall constitute a passed test.

All materials tested shall be passed.

Table 7 – Range of materials for masking tests

Test No.	Material
1	Montage (PUR) foam ^a
2	Self adhesive clear vinyl ^a
3	Plastic skin, spray PU ^a
4	Clear lacquer, brush applied ^a
5	Box with fine granular foamed material covering the detector
6	Inject with a syringe a 10 s glue into the microphone hole ^a
7	Chewing gum ^a
8	Wet Newspaper
^a Applied to the microphone opening.	

All plate/sheet samples shall be large enough to inhibit detection.

6.9 Electrical tests

6.9.1 General

The BTS given in 6.3 shall be used where appropriate for verification. Connect the detector to a variable, stabilised power supply and allow it to stabilise for at least 180 s.

Table 5 specifies grade dependency.

6.9.2 Detector current consumption

This test is not applicable to detectors with Type C power supplies.

Connect the detector to a suitable variable, stabilised power supply with a current measuring meter in series. Connect a voltmeter across the power input terminals of the detector. Set the voltage to the nominal supply voltage and allow the detector to stabilise for at least 180 s.

Place the detector in the mode which draws the maximum current as described by the manufacturer and measure the current drawn.

Place the detector in the mode which draws quiescent current as described by the manufacturer and measure the current drawn.

Pass/fail criteria: The current shall not exceed the manufacturer's stated values by more than 20 % in either mode.

6.9.3 Slow input voltage change and input voltage range limits

Connect the detector to a suitable variable, stabilised power supply.

Raise the supply voltage from zero at a rate of $0,1 \text{ V} \cdot \text{s}^{-1}$ in steps not greater than 10 mV until the nominal supply voltage $V - 25 \%$ is reached, or the minimum supply voltage specified by the manufacturer, whichever is lower. Allow the detector to stabilise for 180 s.

Monitor the intrusion and fault signals or messages and carry out the basic detection test. This test is not applicable to detectors with Type C power supplies.

Pass/fail criteria: The basic detection test shall cause an intrusion signal or message and shall not cause a fault signal or message.

Reset the input voltage to the nominal $V + 25\%$ or the maximum level specified by the manufacturer, whichever is greater. Allow the detector to stabilise for 180 s. Monitor the intrusion and fault signals or messages and carry out the basic detection test. This test is not applicable to detectors with type C power supplies.

Pass/fail criteria: The basic detection test shall cause an intrusion signal or message and shall not cause a fault signal or message.

For grade 3 and 4 detectors, lower the supply voltage at a rate of $0,1 \text{ V} \cdot \text{s}^{-1}$ in steps of not more than 10 mV until a fault signal or message is generated. Carry out the basic detection test.

Pass/fail criteria: For grade 3 and 4 detectors, the detector shall generate a fault signal or message prior to the situation where no intrusion signal or message is generated when the basic detection test is carried out.

6.9.4 Input voltage ripple

This test is not applicable to detectors with Type C power supplies.

Set a signal generator to the nominal voltage V . Allow 180 s for the detector to stabilise. Modulate the detector supply voltage V by $\pm 10\%$ at a frequency of 100 Hz for a further 180 s.

During the application of the ripple carry out a basic detection test. Observe whether any intrusion or fault signals or messages are generated.

Pass/fail criteria: There shall be no unintentional signals or messages generated by the detector during the voltage ripple test. There shall be an intrusion signal or message generated by the BTS.

6.9.5 Input voltage step change

This test is not applicable to detectors with Type C power supplies.

Connect the detector to a square wave generator limited to a maximum current of 1 A, capable of switching from the nominal supply voltage V to the nominal voltage $V \pm 25\%$ in 1 ms.

Set the input voltage to the nominal supply voltage V and allow at least 180 s for the detector to stabilise. Monitor intrusion and fault signals or messages. Apply ten successive square wave pulses from nominal supply voltage V to $V + 25\%$, of duration 5 s at intervals of 10 s. Repeat the step change test for the voltage range V to $V - 25\%$.

Pass/fail criteria: There shall be no unintentional signals or messages generated by the detector during the test.

6.9.6 Total loss of power supply

This test is not applicable to detectors with Type C power supplies.

Connect the detector to a suitable variable, stabilised power supply. Set the voltage to the nominal supply voltage and allow the detector to stabilise for at least 180 s.

Monitor the intrusion and fault signals or messages and disconnect the detector from the power supply.

Pass/fail criteria: The detector shall either generate signals or messages according to the requirements of Table 2. Alternatively for bus based systems total loss of power supply may be determined by loss of communication with the detector.

6.10 Environmental classification and conditions

Unless stated otherwise the general test conditions of 6.2.1 shall apply.

Detectors shall be subjected to the environmental conditioning described in IEC 62599-1 according to the requirements of Tables 7 and 8, and the tests of the EMC product family standard IEC 62599-2.

Detectors subjected to the operational tests are always powered. Detectors subjected to the endurance tests are always un-powered.

Special conditions: During testing ensure that the glass break detector is shielded from rapid changes of surface temperature or air movement within the field of view due to unwanted effects of the tests. This may be achieved by covering the receiving aperture of the detector with a material unable to pass acoustic energy, which shall not interfere with the intended conditioning. Monitor the detector for unintentional intrusion and (where applicable) tamper signals or messages. Furthermore it is necessary to consider potential effects on any anti-masking sensors when selecting a suitable material or method. No functional test is required during the tests.

After the tests and any recovery period prescribed by the environmental test standard carry out the basic detection test, and visually inspect the detector both internally and externally for signs of mechanical damage.

After the water ingress test, wipe any water droplets from the exterior of the enclosure, dry the detector, and carry out the basic detection test. Warm air shall not be used for drying.

After the SO₂ test, detectors shall be washed and dried in accordance with the procedure prescribed in IEC 60068-2-52:1984 (First edition). The basic detection test shall be performed immediately after drying. Carry out the access to interior test and the anti-masking test with chewing gum only, material No. 7 (4.5.4).

Table 8 – Operational tests

Test	Environmental classification		
	Class I	Class II	Class III
Dry heat	Required	Required	Required
Cold	Required	Required	Required
Damp heat (steady state)	Required	Not required	Not required
Damp heat (cyclic)	Not required	Required	Required
Water ingress	Not required	Not required	Required
Mechanical shock	Required	Required	Required
Vibration	Required	Required	Required
Impact	Required	Required	Required
EMC	Required	Required	Required