

INTERNATIONAL STANDARD



This extended version of IEC 62841-2-18:2024 includes the content of the references made to IEC 62841-1:2014

**Electric motor-operated hand-held tools, transportable tools and lawn and garden machinery – Safety –
Part 2-18: Particular requirements for hand-held strapping tools**



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2024 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Secretariat
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

IEC publications search - webstore.iec.ch/advsearchform

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee, ...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

IEC Products & Services Portal - products.iec.ch

Discover our powerful search engine and read freely all the publications previews, graphical symbols and the glossary. With a subscription you will always have access to up to date content tailored to your needs.

Electropedia - www.electropedia.org

The world's leading online dictionary on electrotechnology, containing more than 22 500 terminological entries in English and French, with equivalent terms in 25 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.



IEC 62841-2-18

Edition 1.0 2024-06
EXTENDED VERSION

INTERNATIONAL STANDARD



This extended version of IEC 62841-2-18:2024 includes the content of the references made to IEC 62841-1:2014

**Electric motor-operated hand-held tools, transportable tools and lawn and garden machinery – Safety –
Part 2-18: Particular requirements for hand-held strapping tools**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 25.140.20

ISBN 978-2-8322-9276-1

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

FOREWORD	4
INTRODUCTION	7
1 Scope	8
2 Normative references	9
3 Terms and definitions	14
4 General requirements	20
5 General conditions for the tests	20
6 Radiation, toxicity and similar hazards	22
7 Classification	23
8 Marking and instructions	24
9 Protection against access to live parts	35
10 Starting	36
11 Input and current	36
12 Heating	37
13 Resistance to heat and fire	41
14 Moisture resistance	42
15 Resistance to rusting	45
16 Overload protection of transformers and associated circuits	46
17 Endurance	46
18 Abnormal operation	47
19 Mechanical hazards	55
20 Mechanical strength	56
21 Construction	58
22 Internal wiring	68
23 Components	69
24 Supply connection and external flexible cords	74
25 Terminals for external conductors	80
26 Provision for earthing	82
27 Screws and connections	84
28 Creepage distances, clearances and distances through insulation	86
Annex A (normative) Measurement of creepage distances and clearances	94
Annex B (normative) Motors not isolated from the supply mains and having basic insulation not designed for the rated voltage of the tool	99
Annex C (normative) Leakage current	101
Annex D (normative) Electric strength	105
Annex E (informative) Methods of applying ISO 13849-1 to power tools	107
Annex F (informative) Rules for routine tests	109
Annex G Void	111
Annex H (normative) Determination of a low-power circuit	112
Annex I (informative) Measurement of noise and vibration emissions	113
Annex J Void	128
Annex K (normative) Battery tools and battery packs	129

Annex L (normative) Battery tools and battery packs provided with mains connection or non-isolated sources.....	149
Bibliography.....	168
Figure 1 – Test fingernail.....	91
Figure 2 – Flexing test apparatus.....	92
Figure 3 – Overload test of a class II armature.....	93
Figure A.1 – Clearance gap for parallel sided and V-shaped groove	95
Figure A.2 – Clearance gap for rib and uncemented joint with groove	96
Figure A.3 – Clearance gap for uncemented joint and diverging-sided groove.....	97
Figure A.4 – Clearance gap between wall and screw	98
Figure B.1 – Simulation of fault conditions	100
Figure C.1 – Diagram for leakage current measurement for single-phase connection and three-phase tools suitable for single-phase supply	103
Figure C.2 – Diagram for leakage current measurement for three-phase connection	104
Figure C.3 – Circuit of the leakage current meter	104
Figure H.1 – Example of an electronic circuit with low-power points.....	112
Figure I.1 – Test bench	126
Figure I.2 – Positions of a hand-held power tool and microphones for the hemispherical / cylindrical measurement surface	126
Figure I.3 – Microphone positions on a cubic measurement surface.....	127
Figure I.4 – Directions of vibration measurement	127
Figure K.1 – Measurement of clearances	148
Figure L.1 – Measurement of clearances	167
Table 1 – Maximum normal temperature rises (1 of 2).....	39
Table 2 – Maximum outside surface temperature rises.....	41
Table 3 – Maximum winding temperature	48
Table 4 – Required performance levels.....	54
Table 5 – Impact energies.....	57
Table 6 – Test torques	58
Table 7 – Switch trigger force	63
Table 8 – Minimum cross-sectional area and AWG sizes of supply cords.....	75
Table 9 – Pull and torque value	77
Table 10 – Quick-connect terminals for earthing conductors	82
Table 11 – Torque for testing screws and nuts.....	85
Table 12 – Minimum creepage distances and clearances.....	88
Table D.1 – Test voltages	105
Table F.1 – Test voltages for the electric strength test.....	110
Table I.101 – Operating conditions for strapping tools noise measurement	118
Table I.102 – Operating conditions for strapping tools' vibration measurement	124
Table K.1 – Minimum creepage distances and clearances between parts of opposite polarity	147
Table L.1 – Minimum creepage distances and clearances between parts of opposite polarity	166

INTERNATIONAL ELECTROTECHNICAL COMMISSION

ELECTRIC MOTOR-OPERATED HAND-HELD TOOLS, TRANSPORTABLE TOOLS AND LAWN AND GARDEN MACHINERY – SAFETY –

Part 2-18: Particular requirements for hand-held strapping tools

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) IEC draws attention to the possibility that the implementation of this document may involve the use of (a) patent(s). IEC takes no position concerning the evidence, validity or applicability of any claimed patent rights in respect thereof. As of the date of publication of this document, IEC had not received notice of (a) patent(s), which may be required to implement this document. However, implementers are cautioned that this may not represent the latest information, which may be obtained from the patent database available at <https://patents.iec.ch>. IEC shall not be held responsible for identifying any or all such patent rights.

This extended version (EXV) of the official IEC Standard provides the user with the comprehensive content of the Standard.

IEC 62841-2-18:2024 EXV includes the content of IEC 62841-2-18:2024, and the references made to IEC 62841-1:2014.

The specific content of IEC 62841-2-18:2024 is displayed on a blue background.

IEC 62841-2-18 has been prepared by IEC technical committee 116: Safety of motor-operated electric tools. It is an International Standard.

The text of this International Standard is based on the following documents:

Draft	Report on voting
116/760/FDIS	116/790/RVD

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/publications.

This document is to be used in conjunction with IEC 62841-1:2014.

This document supplements or modifies the corresponding clauses in IEC 62841-1, so as to convert it into the IEC Standard: Particular requirements for hand-held strapping tools.

Where a particular subclause of IEC 62841-1 is not mentioned in this document, that subclause applies as far as reasonable. Where this document states "addition", "modification" or "replacement", the relevant text in IEC 62841-1 is to be adapted accordingly.

The following print types are used:

- requirements: in roman type;
- *test specifications: in italic type;*
- **terms defined in Clause 3: in bold type;**
- notes: in small roman type.

Subclauses, notes, tables and figures which are additional to those in IEC 62841-1 are numbered starting from 101.

Subclauses, notes, tables and figures in Annex K and Annex L which are additional to those in the main body of this document are numbered starting from 301.

A list of all parts in the IEC 62841 series, published under the general title *Electric motor-operated hand-held tools, transportable tools and lawn and garden machinery – Safety*, can be found on the IEC website.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn, or
- revised.

IMPORTANT – The "colour inside" logo on the cover page of this document indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION

Individual countries may wish to consider the application of this Part 1 of IEC 62841, so far as is reasonable, to tools not mentioned in an individual part of IEC 62841-2, IEC 62841-3 or IEC 62841-4 and to tools designed on new principles.

Examples of standards dealing with non-safety aspects of **hand-held tools, transportable tools and lawn and garden machinery** are

- standards dealing with EMC aspects;
- standards dealing with environmental aspects.

ELECTRIC MOTOR-OPERATED HAND-HELD TOOLS, TRANSPORTABLE TOOLS AND LAWN AND GARDEN MACHINERY – SAFETY –

Part 2-18: Particular requirements for hand-held strapping tools

1 Scope

This International Standard deals with the safety of electric motor-operated or magnetically driven:

- **hand-held tools** (IEC 62841-2);
- **transportable tools** (IEC 62841-3);
- **lawn and garden machinery** (IEC 62841-4).

The above listed categories are hereinafter referred to as “tools” or “machines”.

The **rated voltage** is not more than 250 V for single-phase a.c. or d.c. tools, and 480 V for three-phase a.c. tools. The **rated input** is not more than 3 700 W.

The limits for the applicability of this standard for battery tools are given in K.1 and L.1.

This standard deals with the hazards presented by tools which are encountered by all persons in the **normal use** and reasonably foreseeable misuse of the tools.

Tools with electric heating elements are within the scope of this standard.

Requirements for motors not isolated from the supply, and having **basic insulation** not designed for the **rated voltage** of the tools, are given in Annex B. Requirements for rechargeable battery-powered motor-operated or magnetically driven tools and the battery packs for such tools are given in Annex K. Requirements for such tools that are also operated and/or charged directly from the mains or a non-isolated source are given in Annex L.

Hand-held electric tools, which can be mounted on a support or working stand for use as fixed tools without any alteration of the tool itself, are within the scope of this standard and such combination of a **hand-held tool** and a support is considered to be a **transportable tool** and thus covered by the relevant Part 3.

This document applies to hand-held **strapping tools**.

This standard does not apply to:

- tools intended to be used in the presence of explosive atmosphere (dust, vapour or gas);
- tools used for preparing and processing food;
- tools for medical purposes;

NOTE 1 IEC 60601 series covers a variety of tools for medical purposes.

- tools intended to be used with cosmetics or pharmaceutical products;
- heating tools;

NOTE 2 IEC 60335-2-45 covers a variety of heating tools.

- electric motor-operated household and similar electrical appliances;

NOTE 3 IEC 60335 series covers a variety of electric motor-operated household and similar electrical appliances.

- electrical equipment for industrial machine-tools;

NOTE 4 IEC 60204 series deals with electrical safety of machinery.

- small low voltage transformer operated bench tools intended for model making, e.g. the making of radio controlled model aircraft or cars, etc.

NOTE 5 In the United States of America, the following conditions apply:

This standard deals with tools used in non-hazardous locations in accordance with the National Electrical Code, NFPA 70.

NOTE 6 In Canada, the following conditions apply:

This standard deals with tools used in non-hazardous locations in accordance with the Canadian Electric Code, Part 1, CSA C22.1, and General Requirements – Canadian Electrical Code, Part II, CAN/CSA-C22.2 No. 0.

2 Normative references

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60061, *Lamp caps and holders together with gauges for the control of interchangeability and safety*, available at <http://std.iec.ch/iec60061>

IEC 60065:2001, *Audio, video and similar electronic apparatus – Safety requirements*¹
Amendment 2:2010
Amendment 1:2005

IEC 60068-2-75:1997, *Environmental testing – Part 2-75: Tests – Test Eh: Hammer tests*

IEC/TR 60083, *Plugs and socket-outlets for domestic and similar general use standardized in member countries of IEC*

IEC 60085:2007, *Electrical insulation – Thermal evaluation and designation*

IEC 60127 (all parts), *Miniature fuses*

IEC 60227 (all parts), *Polyvinyl chloride insulated cables of rated voltages up to and including 450/750 V*

IEC 60238, *Edison screw lampholders*

IEC 60245 (all parts), *Rubber insulated cables – Rated voltages up to and including 450/750 V*

IEC 60252-1, *AC motor capacitors – Part 1: General – Performance, testing and rating – Safety requirements – Guidance for installation and operation*

IEC 60320 (all parts), *Appliance couplers for household and similar general purposes*

IEC 60320-1, *Appliance couplers for household and similar general purposes – Part 1: General requirements*

¹ There exists a consolidated version (Edition 7.2:2011) which includes IEC 60065:2001 and its Amendment 1 (2005) and Amendment 2 (2010).

IEC 60335-1:2010, *Household and similar electrical appliances – Safety – Part 1: General requirements*

IEC 60384-14, *Fixed capacitors for use in electronic equipment – Part 14: Sectional specification – Fixed capacitors for electromagnetic interference suppression and connection to the supply mains*

IEC 60417, *Graphical symbols for use on equipment*, available at [http://www.graphical-symbols.info/graphical-symbols/equipment/db1.nsf/\\$enHome?OpenForm](http://www.graphical-symbols.info/graphical-symbols/equipment/db1.nsf/$enHome?OpenForm)

IEC 60529:1989, *Degrees of protection provided by enclosures (IP Code)*²

Amendment 1:1999

Amendment 2:2013

IEC 60664-1, *Insulation coordination for equipment within low-voltage systems – Part 1: Principles, requirements and tests*

IEC 60695-2-11:2000, *Fire hazard testing – Part 2-11: Glowing/hot-wire based test methods – Glow-wire flammability test method for end-products*

IEC 60695-2-13:2010, *Fire hazard testing – Part 2-13: Glowing/hot-wire based test methods – Glow-wire ignition temperature (GWIT) test method for materials*

IEC 60695-10-2:2003, *Fire hazard testing – Part 10-2: Abnormal heat – Ball pressure test*

IEC 60695-11-10:2013, *Fire hazard testing – Part 11-10: Test flames – 50 W horizontal and vertical flame test methods*

IEC 60730-1:2010, *Automatic electrical controls for household and similar use – Part 1: General requirements*

IEC 60825-1:2007, *Safety of laser products – Part 1: Equipment classification and requirements*

IEC 60884 (all parts), *Plugs and socket-outlets for household and similar purposes*

IEC 60906-1, *IEC system of plugs and socket-outlets for household and similar purposes – Part 1: Plugs and socket-outlets 16 A 250 V a.c.*

IEC 60990:1999, *Methods of measurement of touch current and protective conductor current*

IEC 60998-2-1, *Connecting devices for low-voltage circuits for household and similar purposes – Part 2-1: Particular requirements for connecting devices as separate entities with screw-type clamping units*

IEC 60998-2-2, *Connecting devices for low-voltage circuits for household and similar purposes – Part 2-2: Particular requirements for connecting devices as separate entities with screwless-type clamping units*

IEC 60999-1:1999, *Connecting devices – Electrical copper conductors – Safety requirements for screw-type and screwless-type clamping units – Part 1: General requirements and particular requirements for clamping units for conductors from 0,2 mm² up to 35 mm² (included)*

² There exists a consolidated version (Edition 2.2:2013) which includes IEC 60529:1989 and its Amendment 1 (1999) and Amendment 2 (2013).

IEC 61000-4-2:2008, *Electromagnetic compatibility (EMC) – Part 4-2: Testing and measurement techniques – Electrostatic discharge immunity test*

IEC 61000-4-3:2006, *Electromagnetic compatibility (EMC) – Part 4-3: Testing and measurement techniques – Radiated, radio-frequency, electromagnetic field immunity test*³
Amendment 1:2007
Amendment 2:2010

IEC 61000-4-4:2012, *Electromagnetic compatibility (EMC) – Part 4-4: Testing and measurement techniques – Electrical fast transient/burst immunity test*

IEC 61000-4-5:2005, *Electromagnetic compatibility (EMC) – Part 4-5: Testing and measurement techniques – Surge immunity test*

IEC 61000-4-6:2008, *Electromagnetic compatibility (EMC) – Part 4-6: Testing and measurement techniques – Immunity to conducted disturbances, induced by radio-frequency fields*

IEC 61000-4-11:2004, *Electromagnetic compatibility (EMC) – Part 4-11: Testing and measurement techniques – Voltage dips, short interruptions and voltage variations immunity tests*

IEC 61032:1997, *Protection of persons and equipment by enclosures – Probes for verification*

IEC 61056-1, *General purpose lead-acid batteries (valve-regulated types) – Part 1: General requirements, functional characteristics – Methods of test*

IEC 61058-1:2000, *Switches for appliances – Part 1: General requirements*⁴
Amendment 1:2001
Amendment 2:2007

IEC 61210, *Connecting devices – Flat quick-connect terminations for electrical copper conductors – Safety requirements*

IEC 61540:1997, *Electrical accessories – Portable residual current devices without integral overcurrent protection for household and similar use (PRCDs)*⁵
Amendment 1:1998

IEC 61558-1, *Safety of power transformers, power supplies, reactors and similar products – Part 1: General requirements and tests*

IEC 61558-2-4, *Safety of transformers, reactors, power supply units and similar products for supply voltages up to 1 100 V – Part 2-4: Particular requirements and tests for isolating transformers and power supply units incorporating isolating transformers*

IEC 61558-2-6, *Safety of transformers, reactors, power supply units and similar products for supply voltages up to 1 100 V – Part 2-6: Particular requirements and tests for safety isolating transformers and power supply units incorporating safety isolating transformers*

³ There exists a consolidated version (Edition 3.2:2010) which includes IEC 61000-4-3:2006 and its Amendment 1 (2007) and Amendment 2 (2010).

⁴ There exists a consolidated version (Edition 3.2:2008) which includes IEC 61058-1:2000 and its Amendment 1 (2001) and Amendment 2 (2007).

⁵ There exists a consolidated version (Edition 1.1:1999) which includes IEC 61540:1997 and its Amendment 1 (2001).

IEC 61558-2-16, *Safety of transformers, reactors, power supply units and similar products for supply voltages up to 1 100 V – Part 2-16: Particular requirements and tests for switch mode power supply units and transformers for switch mode power supply units*

IEC 61951-1, *Secondary cells and batteries containing alkaline or other non-acid electrolytes – Portable sealed rechargeable single cells – Part 1: Nickel-cadmium*

IEC 61951-2, *Secondary cells and batteries containing alkaline or other non-acid electrolytes – Portable sealed rechargeable single cells – Part 2: Nickel-metal hydride*

IEC 61960, *Secondary cells and batteries containing alkaline or other non-acid electrolytes – Secondary lithium cells and batteries for portable applications*

IEC 61984, *Connectors – Safety requirements and tests*

IEC 62133, *Secondary cells and batteries containing alkaline or other non-acid electrolytes – Safety requirements for portable sealed secondary cells, and for batteries made from them, for use in portable applications*

IEC 62233, *Measurement methods for electromagnetic fields of household appliances and similar apparatus with regard to human exposure*

IEC 62471, *Photobiological safety of lamps and lamp systems*

IEC/TR 62471-2:2009, *Photobiological safety of lamps and lamp systems – Part 2: Guidance on manufacturing requirements relating to non-laser optical radiation safety*

IEC 62841-1:2014, *Electric motor-operated hand-held tools, transportable tools and lawn and garden machinery – Safety – Part 1: General requirements*

ISO 1463, *Metallic and oxide coatings – Measurement of coating thickness – Microscopical method*

ISO 2178, *Non-magnetic coatings on magnetic substrates – Measurement of coating thickness – Magnetic method*

ISO 2768-1, *General tolerances – Part 1: Tolerances for linear and angular dimensions without individual tolerance indications*

ISO 3744, *Acoustics – Determination of sound power levels and sound energy levels of noise sources using sound pressure – Engineering methods for an essentially free field over a reflecting plane*

ISO 3864-2, *Graphical symbols – Safety colours and safety signs – Part 2: Design principles for product safety labels*

ISO 3864-3, *Graphical symbols – Safety colours and safety signs – Part 3: Design principles for graphical symbols for use in safety signs*

ISO 4871:1996, *Acoustics – Declaration and verification of noise emission values of machinery and equipment*

ISO 5347 (all parts), *Methods for the calibration of vibration and shock pick-ups*

ISO 5349-1, *Mechanical vibration – Measurement and evaluation of human exposure to hand-transmitted vibration – Part 1: General requirements*

ISO 5349-2, *Mechanical vibration – Measurement and evaluation of human exposure to hand-transmitted vibration – Part 2: Practical guidance for measurement in the workplace*

ISO 7000:2012, *Graphical symbols for use on equipment – Index and synopsis*

ISO 7010, *Graphical symbols – Safety colours and safety signs – Registered safety signs*

ISO 7574-4, *Acoustics – Statistical methods for determining and verifying stated noise emission values of machinery and equipment – Part 4: Methods for stated values for batches of machines*

ISO 8041, *Human response to vibration – Measuring instrumentation*

ISO 9772:2012, *Cellular plastics – Determination of horizontal burning characteristics of small specimens subjected to a small flame*

ISO 11201, *Acoustics – Noise emitted by machinery and equipment – Determination of emission sound pressure levels at a work station and at other specified positions in an essentially free field over a reflecting plane with negligible environmental corrections*

ISO 11203, *Acoustics – Noise emitted by machinery and equipment – Determination of emission sound pressure levels at a work station and at other specified positions from the sound power level*

ISO 12100, *Safety of machinery – General principles for design – Risk assessment and risk reduction*

ISO 13849-1, *Safety of machinery – Safety-related parts of control systems – Part 1: General principles for design*

ISO 13850, *Safety of machinery – Emergency stop – Principles for design*

ISO/TR 11690-3, *Acoustics – Recommended practice for the design of low-noise workplaces containing machinery – Part 3: Sound propagation and noise prediction in workrooms*

ISO 16063-1, *Methods for the calibration of vibration and shock transducers – Part 1: Basic concepts*

EN 12096, *Mechanical vibration – Declaration and verification of vibration emission values*

ASTM B 258, *Standard specification for standard nominal diameters and cross-sectional areas of AWG sizes of solid round wires used as electrical conductors*

UL 969, *Standard for marking and labeling systems*

NOTE 1 In the United States of America, the following normative reference applies:

US, Code of Federal Regulations (CFR) Title 21, *Food and Drugs*.

NOTE 2 In Canada, the following normative reference applies:

C.R.C., c. 1370, *Radiation Emitting Devices Regulations*

NOTE 3 In Europe (EN 62841-1), the following normative references apply:

CR 1030-1, *Hand-arm vibration – Guidelines for vibration hazards reduction – Part 1: Engineering methods by design of machinery*

EN ISO 11688-1, *Acoustics – Recommended practice for the design of low-noise machinery and equipment – Part 1: Planning (ISO/TR 11688-1)*

3 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

Where the terms voltage and current are used, they imply the r.m.s. values, unless otherwise specified.

Where in this standard the expressions “with the aid of a tool”, “without the aid of a tool”, and “requires the use of a tool”, are used, the word “tool” means a hand tool, for example a screwdriver, which may be used to operate a screw or other fixing means.

3.1

accessible part

conductive part or surface of insulating materials that can be touched by means of the test probe B of IEC 61032:1997

3.2

accessory

device that is attached only to the output mechanism of the tool

3.3

adjustable guard

guard which is adjustable as a whole or which incorporates adjustable part(s). For manually adjustable guards, the adjustment remains fixed during a particular operation

3.4

all-pole disconnection

disconnection of all supply conductors except the protective earthing (grounding) conductor by a single initiating action

3.5

attachment

device attached to the housing or other component of the tool and which may or may not be attached to the output mechanism and does not modify the **normal use** of the tool within the scope of this standard

3.6

basic insulation

insulation applied to **live parts** to provide protection against electric shock. Insulation applied to **live parts** not intended to provide electric shock protection is considered to be insulation for functional purposes, such as magnet wire insulation

3.7

battery

assembly of one or more **cells** intended to provide electrical current to the tool

3.8

class I tool

tool in which protection against electric shock does not rely on basic, double or **reinforced insulation** only, but which includes an additional safety precaution in that conductive **accessible parts** are connected to the protective earthing conductor in the fixed wiring of the installation in such a way that conductive **accessible parts** cannot become live in the event of a failure of the **basic insulation**

Note 1 to entry: Also considered as **class I tools** are tools with **double insulation** and/or **reinforced insulation** throughout, but also having an earthing terminal or earthing contact.

3.9**class II tool**

tool in which protection against electric shock does not rely on **basic insulation** only, but in which additional safety precautions, such as **double insulation** or **reinforced insulation**, are provided, there being no provision for protective earthing or reliance upon installation conditions

3.10**class III tool**

tool in which protection against electric shock relies on supply at **safety extra-low voltage**, and in which voltages higher than those of **safety extra-low voltages** are not generated

3.11**class II construction**

part of a tool for which protection against electric shock relies upon **double insulation** or **reinforced insulation**

3.12**class III construction**

part of a tool for which protection against electric shock relies upon **safety extra-low voltage**, and in which voltages higher than those of **safety extra-low voltages** are not generated

3.13**clearance**

shortest distance between two conductive parts, or between a conductive part and the outer surface of the enclosure, considered as though metal foil were pressed into contact with accessible surfaces of insulating material, measured through air

Note 1 to entry: Examples of **clearances** are given in Annex A.

3.14**control device**

device used by the user to adjust and/or regulate an electrical or mechanical function of the tool

3.15**creepage distance**

shortest path between two conductive parts, or between a conductive part and the outer surface of the enclosure, considered as though metal foil were pressed into contact with accessible surfaces of insulating material, measured along the surface of the insulating material

Note 1 to entry: Examples of **creepage distances** are given in Annex A.

3.16**detachable part**

part which can be removed or opened without the aid of a tool, or a part which is removed in accordance with the instruction for use, except externally accessible brush caps, even if removal requires the use of a tool

Note 1 to entry: A non-detachable part is covered by the requirements of 21.22.

3.17**double insulation**

insulation system comprising both **basic insulation** and **supplementary insulation**

3.18**electronic circuit**

circuit incorporating at least one **electronic component**

3.19

electronic component

part in which conduction is achieved principally by electrons moving through a vacuum, gas or semiconductor, with the exclusion of neon indicators

Note 1 to entry: Examples of **electronic components** are diodes, transistors, triacs and monolithic integrated circuits. Resistors, capacitors and inductors are not considered **electronic components**.

3.20

explosion

failure that occurs, when an enclosure opens violently and major components are forcibly expelled in a manner that could result in injury

3.21

extra-low voltage

voltage supplied from a source within the tool and, which, when the tool is supplied at **rated voltage**, does not exceed 50 V between conductors and between conductors and earth

3.22

fixed guard

guard affixed in such a manner (e.g. by screws, nuts, welding) that it can only be opened or removed with the use of tools or by destruction of the affixing means

3.23

guard

physical barrier, designed as part of the tool, to provide protection

3.24

hand-held tool

tool intended to do mechanical work, with or without provisions for mounting on a support, and so designed that the motor and the machine form an assembly which can easily be brought to the place of operation, and which is either held or supported by hand or suspended during operation

Note 1 to entry: **Hand-held tools** include tools provided with a flexible shaft, the motor being either fixed or portable.

3.25

inherent operating cycle

repetitive operation of a tool designed in such a way that the complete cycle duration cannot be altered by the operator

3.26

interconnection cord

external flexible cord provided for electrical connections between two parts of a tool

3.27

lawn and garden machinery

tool for garden maintenance

3.28

liquid system

system that employs water or a water-based liquid from an external or integral supply that is used to perform the intended function of the tool

3.29

live part

any conductor or conductive part intended to be energized in **normal use**, including a neutral conductor

3.30

mean time to dangerous failure

MTTF_d

expectation of the mean time to dangerous failure

3.31

momentary power switch

power switch that does not remain in the “on” position when the actuating device is released

3.32

non-self-resetting thermal cut-out

thermal cut-out which requires a manual operation for resetting, or replacement of a part, in order to restore the current

Note 1 to entry: Manual operation also includes operation of the **power switch**.

3.33

non-isolated source

voltage source in which the output is not isolated from the mains supply by means of a **safety isolating transformer**

3.34

normal operation

conditions under which the tool is operated in **normal use** when it is connected to the power supply

3.35

normal use

use of a tool for which it is designed, taking into account the manufacturer's instructions

3.36

power switch

device that electrically activates the primary function of the tool in the “on” position and deactivates the same function of the tool in its “off” position

3.37

protective device

device, the operation of which prevents a hazardous situation under abnormal operation conditions

3.38

protective impedance

impedance connected between **live parts** and accessible conductive parts, and of value so that the current is limited to a safe value

3.39

rated current

current assigned to the tool by the manufacturer

3.40

rated frequency

frequency assigned to the tool by the manufacturer

3.41

rated frequency range

frequency range assigned to the tool by the manufacturer, expressed by its lower and upper limits

3.42

rated input

input in watts assigned to the tool by the manufacturer

3.43

rated no-load speed

no-load speed assigned to the tool by the manufacturer

3.44

rated voltage

voltage assigned to the tool by the manufacturer. For three-phase supply, it is the voltage between phases

3.45

rated voltage range

voltage range assigned to the tools by the manufacturer, expressed by its lower and upper limits

3.46

reinforced insulation

insulation of **live parts** which provides a degree of protection against electric shock equivalent to **double insulation**

Note 1 to entry: Examples of **reinforced insulation** are a single layer or several layers which cannot be tested singly as **basic insulation** or **supplementary insulation**.

3.47

residual current device

RCD

device intended to detect a diversion of current from a circuit in a way that may expose the user to an electric shock; in such conditions the device opens the circuit

Note 1 to entry: Such a device is also known as portable **residual current device** (PRCD), ground fault circuit interrupter (GFCI) or earth leakage circuit breaker (ELCB).

3.48

safety critical function

SCF

function(s) required by this standard, the loss of which would cause the tool to function in such a manner as to expose the user to a risk that is in excess of the risk that is permitted by this standard under abnormal conditions

3.49

safety extra-low voltage

voltage not exceeding a peak value of 42,4 V between conductors and between conductors and earth, the no-load voltage not exceeding a peak value of 50 V, in an electric circuit which has galvanic separation from the supplying electric power system by such means as a **safety isolating transformer** or a converter with separate windings, the insulation of which complies with **double insulation** or **reinforced insulation** requirements

3.50

safety isolating transformer

transformer, the input winding of which is electrically separated from the output winding by an insulation at least equivalent to **double insulation** or **reinforced insulation**, and which is intended to supply a distribution circuit, a tool or other equipment at **safety extra-low voltage**

3.51

self-resetting thermal cut-out

thermal cut-out which automatically restores the current after the relevant part of the tool has cooled down to a given value

3.52**supplementary insulation**

independent insulation applied in addition to the **basic insulation**, in order to provide protection against electric shock in the event of a failure of the **basic insulation**

3.53**supply cord**

flexible cord, for supply purposes, which is fixed to the tool

3.54**temperature limiter**

temperature-sensing device, the operating temperature of which may be either fixed or adjustable, and which, during **normal operation**, operates by opening or closing a circuit when the temperature of the controlled part reaches a predetermined value

Note 1 to entry: This does not reverse this operation of opening or closing a circuit during the **normal operation** of the tool.

3.55**thermal cut-out**

device which, during abnormal operation, limits the temperature of the controlled part by automatically opening the circuit, or by reducing the current, the setting of which cannot be altered by the user

3.56**thermal link**

thermal cut-out which operates only once, and then requires partial or complete replacement

3.57**thermostat**

temperature-sensing device, the operating temperature of which may be either fixed or adjustable; and which, during **normal operation**, keeps the temperature of the controlled part between certain limits by automatically opening and closing a circuit

3.58**transportable tool**

tool that has the following characteristics:

- a) intended to be taken to various designated working areas. The tool performs work on the material that is either brought to the tool, the tool is mounted to the workpiece or the tool is placed in proximity of the workpiece;
- b) intended to be moved by one or two people, with or without simple devices to facilitate transportation, e.g. handles, wheels and the like;
- c) used in a stationary position set up on a bench, table, floor or incorporating a device that performs the function of a bench or table, with or without fixing, e.g. fast clamping devices, bolting and the like, or mounted to the workpiece;
- d) used under the control of an operator;
- e) either the workpiece or the tool is fed or introduced manually;
- f) not intended for continuous production or production line use;
- g) if mains operated, supplied with a flexible **supply cord** and plug

3.59**type X attachment**

method of attachment of the **supply cord** specified by the manufacturer so that it can easily be replaced

3.60

type Y attachment

method of attachment of the **supply cord** such that any replacement is intended to be made by the manufacturer, its service agent or similar qualified person

3.61

type Z attachment

method of attachment of the **supply cord** so that it cannot be replaced without breaking or destroying the tool

3.62

user maintenance

maintenance operation(s) which are intended to be carried out by the user in accordance with the instruction manual

3.63

working voltage

maximum voltage, without the effect of transient voltages, to which the part under consideration is subjected when the tool is supplied at its **rated voltage** and operating with **rated input** or **rated current**

3.101

strapping tool

hand-held tool for clinching straps on boxes

4 General requirements

Tools shall be so constructed that they operate safely so as to cause no danger to persons or surroundings.

Tools that have clearly separate modes of operation shall comply separately with the requirements applicable to each specific mode of operation.

Multifunction tools shall comply separately with the applicable part of IEC 62841-2, IEC 62841-3 or IEC 62841-4 and shall take into account any other hazards due to the combination of functions.

NOTE In Europe (EN 62841-1), the above paragraph is not applicable.

Compliance is checked by fulfilling the relevant requirements and carrying out the relevant tests of this standard.

5 General conditions for the tests

5.1 *Tests according to this standard are type tests. General test conditions in Clause 5 apply unless otherwise specified in this standard.*

NOTE Annex F shows an example of routine tests.

5.2 *The tests are made on separate samples. However, at the manufacturer's discretion, fewer samples may be used.*

*The cumulative stress resulting from successive tests on **electronic circuits** is to be avoided. It may be necessary to replace components or to use additional samples.*

If several tests are conducted on a single sample, then the results shall not be affected by previous tests.

5.3 *If it is evident from the construction of the tool that a particular test is not applicable, the test is not made.*

5.4 *The tests are carried out with the tool, and/or any movable part of it, placed in the most unfavourable position that may occur in **normal use**.*

5.5 *Tools provided with controls or switching devices are tested with these controls or devices adjusted to their most unfavourable settings, if the setting can be altered by the user. Electronic speed **control devices** are set for the highest speed.*

If the adjusting means of the control is accessible without the aid of a tool, 5.5 applies whether the setting can be altered by hand or with the aid of a tool. If the adjusting means is not accessible without the aid of a tool, and if the setting is not intended to be altered by the user, 5.5 does not apply.

Adequate sealing is regarded as preventing alteration of the setting by the user.

5.6 *The tests are made in a draught-free location and at an ambient temperature of $(20 \pm 5) ^\circ\text{C}$.*

If the temperature attained by any part is limited by a temperature sensitive device, the ambient temperature is, in case of doubt, maintained at $(23 \pm 2) ^\circ\text{C}$.

5.7 *The test conditions related to frequency and voltage are specified in 5.7.1 to 5.7.3.*

5.7.1 *Tools for a.c. only are tested with a.c. at **rated frequency**, if marked, and those for a.c./d.c. are tested with the most unfavourable supply.*

*Tools for a.c. which are not marked with **rated frequency**, or marked with a **rated frequency range** of 50 Hz to 60 Hz or with 50/60 Hz, are tested with either 50 Hz or 60 Hz, whichever is the most unfavourable, unless the tool employs only series motors, in which case either frequency may be used.*

5.7.2 *Tools having more than one **rated voltage** or having a **rated voltage range** are tested at the highest voltage.*

5.7.3 *For tests that require a value for **rated current** and with tools where there is no marked **rated current**, the value of the **rated current** is substituted by the current measured when the tool is operated at **rated input** at the lowest **rated voltage** or the lower value of the **rated voltage range**.*

5.8 *When alternative heating elements or **attachments** are made available for the tool by its manufacturer, the tool is tested with those heating elements or **attachments** which give the most unfavourable results.*

5.9 *Tools are tested with the specified flexible **supply cord** connected to the tool.*

5.10 *If **class I tools** have **accessible parts** which are not connected to an earthing terminal or earthing contact, and are not separated from **live parts** by an intermediate metal part which is connected to an earthing terminal or earthing contact, such parts are checked for compliance with the appropriate requirements specified for **class II construction**.*

5.11 *If **class I tools** or **class II tools** have parts operating at **safety extra-low voltage**, such parts are checked for compliance with the appropriate requirements specified for **class III tools**.*

5.12 When testing **electronic circuits**, the supply is to be free from those perturbations from external sources that can influence the results of the tests.

5.13 If, in **normal use**, a heating element, if any, cannot be operated unless the motor is running, the element is tested with the motor running. If the heating element can be operated without the motor running, the element is tested with or without the motor running, whichever is the more unfavourable. Heating elements incorporated in the tool are connected to a separate supply unless otherwise specified.

5.14 For **attachments** performing a function which is within the scope of one of the relevant parts of IEC 62841-2, IEC 62841-3 or IEC 62841-4, the tests are made in accordance with that part of IEC 62841-2, IEC 62841-3 or IEC 62841-4.

5.15 If a torque is to be applied, the method of loading is chosen so as to avoid additional stresses, such as those caused by side thrust. Additional loads necessary for the correct operation of the tool are, however, taken into consideration.

If a brake is used for applying a load, it must be applied gradually to assure that the starting current does not affect the test. Modification of output means for purpose of loading is permitted for the connection to a brake.

5.16 Tools intended to be operated at **safety extra-low voltage** are tested using a supply transformer intended to be used with the tool.

5.17 If a requirement is based upon the mass of the tool, the mass shall be determined without **supply cord**, if any, and without tool bits or **accessories**, but with all equipment and **attachments** needed for **normal use**. Details of the required **accessories**, equipment and **attachments** are given in the relevant part of IEC 62841-2, IEC 62841-3 or IEC 62841-4.

If the tool is supplied with more than one **accessory**, equipment or **attachment**, the heaviest configuration shall be used to determine the mass.

The mass of a **strapping tool** does not include any additional **accessories**, equipment or **attachments**.

5.18 If linear and angular dimensions are specified without a tolerance, ISO 2768-1, class “c” is applicable.

5.19 All electrical measurements shall be made with a maximum measurement error of 5 %.

Instruments for measuring voltage shall have an input resistance of at least 1 M Ω with a maximum parallel capacitance of 150 pF.

5.20 Thermal equilibrium is considered achieved when the total deviation of three successive temperature rise readings, taken at 3 min intervals, does not exceed 4 K. For induction motors, a measurement time of 1 h is considered sufficient.

For motors, thermal equilibrium may be evaluated by measuring the temperature of the stator laminations.

6 Radiation, toxicity and similar hazards

6.1 Tools shall not emit harmful radiation, or present a toxic or similar hazard.

Compliance is checked by the test, given in the relevant part of IEC 62841-2, IEC 62841-3 or IEC 62841-4, where necessary.

NOTE Previous studies have shown that the level of electromagnetic fields (EMF) emitted by power tools and garden machinery, measured in accordance with IEC 62233, is far below the applicable limits, provided the sole significant source of EMF is the motor, which is typically a universal, DC (with or without brushes), induction or solenoid motor. Therefore, a general measurement in accordance with IEC 62233 was regarded as not necessary.

6.2 If the tool is fitted with a laser to indicate a cutting line or the like, the laser class shall be 2M or lower, according to IEC 60825-1:2007.

In addition, the tool shall be marked with the symbol(s) as required by IEC 60825-1:2007 for the relevant laser class.

Compliance is checked by inspection.

6.3 If a tool is fitted with non-coherent light sources, users of tools shall be cautioned as to the risk of potential photo-biological harm, if such harm exists.

Depending on the type of light source, the requirements of 6.3.1, 6.3.2 or 6.3.3 apply.

6.3.1 Visible light indicators (pilot lamps) and Infrared sources used for signalling and communication are considered to have no risk of photo-biological harm and require no marking.

Compliance is checked by inspection.

6.3.2 Tools emitting visible light from electroluminescent, incandescent or LED sources are considered to be for short term, non-general light services use where exposure is both incidental and intermittent.

Tools emitting light from these sources shall be marked with one of the following:

- “**CAUTION** Do not stare at operating lamp”, or
- symbol IEC 60417-6041 (2010-08).

The marking may be omitted, if it can be demonstrated that the emitted light presents no reasonable risk of harm.

The emitted light is considered to present no reasonable risk or harm, if either

- the light emission at a distance of 200 mm along any direction of the tool is below 500 Lux; or
- the luminance light emission is less than 10 000 cd/m² in the range of visible light; or
- the light source (if not focused by external optics) is in Risk Group 1 or lower evaluated by the methods of IEC 62471; or
- the tool itself is evaluated by the methods of IEC 62471 and found to be in Risk Group 1 or lower.

Compliance is checked by measurement and by the methods specified in IEC 62471.

6.3.3 For light derived by sources other than those mentioned in 6.3.2, the product shall be evaluated by the methods of IEC 62471 and the markings shall be guided by 5.4 of IEC/TR 62471-2:2009.

Compliance is checked by inspection and by the methods specified in IEC 62471.

7 Classification

7.1 Tools shall be of one of the following classes with respect to protection against electric shock:

class I, class II, class III.

Compliance is checked by inspection and by the relevant tests.

7.2 Tools shall have the appropriate degree of protection against harmful ingress of water according to IEC 60529:2013. If a degree other than IPX0 is required this shall be specified in the relevant part of IEC 62841-2, IEC 62841-3 or IEC 62841-4.

Compliance is checked by inspection and by the relevant tests.

8 Marking and instructions

8.1 Tools shall be marked with rating information as follows:

- **rated voltage(s)** or **rated voltage range**, in volts. Tools for star-delta connection shall be clearly marked with the two **rated voltages** (for example 230 Δ / 400 Y). A tool that complies with this standard for a voltage range, may also be marked with any single voltage or smaller voltage range within that range;
- symbol for nature of supply, unless the **rated frequency(ies)** or **rated frequency range** is marked. The symbol for nature of supply shall be placed next to the marking for **rated voltage**;
- **rated input**, in watts or **rated current**, in amperes. The **rated input** or **rated current** to be marked on the tool is the total maximum input or current that can be drawn from external circuit at the same time. If a tool has alternative components which can be selected by a **control device**, the **rated input** or **rated current** is that corresponding to the highest loading possible;
- symbol for **class II construction**, for **class II tools** only;
- IP number according to degree of protection against ingress of water other than IPX0. If the first numeral for the IP numbering is omitted, the omitted numeral shall be replaced by the letter X, for example IPX5.

Compliance is checked by inspection.

8.1.1 Tools having a range of rated values such as for voltage and frequency and which can be operated without adjustment throughout the range shall be marked with the lower and upper limits of the range separated by a hyphen.

Example:

115-230 V: The tool is suitable for any value within the marked range.

Tools having different rated values and which have to be adjusted for use of a particular value by the user or installer shall be marked with the different values separated by an oblique stroke. This requirement is also applicable to tools with provision for connection to both single-phase and multi-phase supplies.

Examples:

115/230 V: The tool is only suitable for the marked values.

230/400 V: The tool is only suitable for the voltages values indicated, 230 V being for single-phase operation and 400 V for three-phase operation.

Compliance is checked by inspection.

8.1.2 For tools marked with more than one **rated voltage**, a **rated voltage range** or with more than one **rated voltage range**, the **rated input** for each of these voltages shall be marked.

The upper and lower limits of the rated power input shall be marked on the tool so that the relation between input and voltage appears distinctly, unless the difference between the upper and lower limits of a **rated voltage range** does not exceed 20 % of the mean value of the range, in which case the marking for **rated input** may be related to the mean value of the range.

Compliance is checked by inspection.

8.2 Tools shall be marked with a safety warning in one of the following versions:

- “ WARNING – To reduce the risk of injury, user must read instruction manual”, or
- symbol M002 of ISO 7010, or
- the appropriate symbol stated in the relevant part of IEC 62841-2, IEC 62841-3 or IEC 62841-4.

If used, the word “WARNING” shall be in capital letters not less than 2,4 mm high and shall not be separated from either the cautionary statement or the symbol ISO 7000-0434A or ISO 7000-0434B (2004-01).

If used, the statement shall be verbatim except the term “operator’s manual” or “user guide” may be used for the term “instruction manual”.

If additional symbols are used, they shall be in accordance with ISO 7010 or be designed in accordance with ISO 3864-2 or ISO 3864-3.

Cautionary statements having the same signal word such as “ WARNING” may be combined into one paragraph under one signal word. The order of statements shall be markings required by IEC 62841-1, markings required by the relevant part of IEC 62841-2, IEC 62841-3 or IEC 62841-4 and then any optional markings.

Compliance is checked by inspection and by measurement.

8.3 Tools shall be marked with additional information as follows:

- the business name and address of the manufacturer and, where applicable, his authorised representative. Any address shall be sufficient to ensure contact. Country or state, city and postal code (if any) are deemed sufficient for this purpose;
- designation of the tool,
designation of the tool may be achieved by a code that is any combination of letters, numbers or symbols, providing that this code is explained by giving the explicit designation such as “drill”, “planer” etc. in the instructions supplied with the tool;

NOTE 1 An example of such code is “A123-B”.

- designation of series or type,
allowing the technical identification of the product. This may be achieved by a combination of letters and/or numbers and may be combined with the designation of tool;

NOTE 2 The term “designation of series or type” is also known as model number.

- the year of manufacture and a date code identifying at least the month of manufacture;
- for tools manufactured such that its parts are shipped separately for assembly by the end user, each part shall be marked with a distinct identification on the part or the package;
- “> 25 kg” if the mass of the tool is over 25 kg.

If additional markings are used, they shall not give rise to misunderstanding.

Compliance is checked by inspection.

8.4 Markings specified in 8.1 to 8.3 shall not be on a **detachable part** of the tool.

Markings specified in 8.2 and 8.3 shall be clearly discernible from the outside of the tool. For markings other than symbols, this may be achieved by the use of a fold-over label on power cords of tools with **type Y attachment** or **type Z attachment**. Other markings on the tool may be visible after removal of a cover, if necessary.

Indications for switches and controls shall be placed on or in the vicinity of these components; they shall not be placed on parts which can be repositioned, or positioned in such a way that the marking is misleading.

Compliance is checked by inspection.

8.5 If the tool can be adjusted to suit different **rated voltages**, the voltage to which the tool is adjusted shall be clearly discernible.

This requirement does not apply to tools for star-delta connection.



For tools where frequent changes in voltage setting are not required, this requirement is considered to be met if the **rated voltage** to which the tool is adjusted can be determined from a wiring diagram fixed to the tool. The wiring diagram may be on the inside of a cover which has to be removed to connect the supply conductors. It shall not be on a label loosely attached to the tool.

Compliance is checked by inspection.

8.6 For units the following shall be used:

V	volts
A	amperes
Ah	ampere-hours
Hz	hertz
W	watts
kW	kilowatts
F	farads
μF	microfarads
l	litres
g	grams
kg	kilograms
bar	bars
Pa	pascals
h	hours
min	minutes
s	seconds
n_0	no-load speed
.../min or ...min ⁻¹	revolutions or reciprocations per minute (rpm)

For symbols the following shall be used:

	or d.c.	[symbol IEC 60417-5031 (2002-10)] direct current
	or a.c.	[symbol IEC 60417-5032 (2002-10)] alternating current
3 		three-phase alternating current
3N		three-phase alternating current with neutral
		rated current of the appropriate fuse-link in amperes
		time-lag miniature fuse-link where X is the symbol for the time/current characteristic, as given in IEC 60127
		[symbol IEC 60417-5019 (2006-08)] protective earth
		[symbol IEC 60417-5172 (2003-02)] class II tool
IPXX		IP symbol
		[symbol ISO 7000-0434A or ISO 7000-0434B (2004-01)] caution
		[symbol M002 of ISO 7010] read the instructions
		[symbol IEC 60417-5012 (2002-10)] lamp
NOTE The rated wattage of the lamp may be indicated in association with this symbol.		
		[symbol IEC 60417-6041 (2010-08)] visible radiation, instructional safeguard
Ø		diameter
Li-Ion		lithium-ion battery
NiCd		nickel-cadmium battery
NiMH		nickel-metal hydride battery

If additional symbols are used, they shall not give rise to misunderstanding and be explained in the instructions.

When other units are used, the units and their symbols shall be those of the international standardized system.

Compliance is checked by inspection.

8.7 Tools to be connected to more than two supply conductors shall be provided with a connection diagram, fixed to the tool, unless the terminals are clearly identified.

The earthing conductor is not considered to be a supply conductor. For tools for star-delta connection, the wiring diagram shall show how the windings are to be connected.

Compliance is checked by inspection.

8.8 Except for **type Z attachment**, terminals shall be indicated as follows:

- Terminals intended exclusively for the neutral conductor shall be indicated by the letter N.
- Earthing terminals shall be indicated by the symbol IEC 60417-5019 (2006-08).

These indications shall not be placed on screws, removable washers or other parts which might be removed when conductors are being connected.

Compliance is checked by inspection.

8.9 Switches which may give rise to a hazard when operated shall be marked or so placed as to indicate clearly which part of the tool they control.

Compliance is checked by inspection.

8.10 The “off” position of a multi-stable **power switch** shall be indicated; the indication shall be the figure O, as given by symbol IEC 60417-5008 (2002-10). A **momentary power switch** which can be locked in the “on” position is not considered as a multi-stable switch.

Push-buttons used only for the “off” function shall be indicated by marking the button/position with the figure O and the colour of the button shall be red or black.

The figure O shall not be used for any other indication.

NOTE The figure O can, for example, also be used on a digital programming keyboard.

For **transportable tools**, a power switch actuator or its cover shall not have a colour in a combination of yellow and red as specified for an emergency stop in accordance with ISO 13850.

When a flap/cover is provided and covers only the start button, the colour of the flap/cover shall not be black, red or yellow.

When a flap/cover is provided and covers the stop button, such flap/cover shall be red or black.

Compliance is checked by inspection.

8.11 Control devices intended to be adjusted during operation, shall be provided with an indication for the direction of adjustment to increase or to decrease the value of the characteristic being adjusted. An indication of + and – is considered to be sufficient for this requirement.

The requirement does not apply to **control devices** provided with an adjusting means, if its fully “on” position is opposite to its “off” position.

If figures are used for indicating the different positions, the “off” position shall be indicated by the figure O and the other positions shall be indicated by figures reflecting the greater output, input, speed, etc.

The indication for the different positions of the operating means of a **control device** shall be placed on the device itself, or adjacent to the operating means.

Compliance is checked by inspection.

8.12 Markings required by the standard shall be legible and durable. Signs shall be in contrast such as colour, texture, or relief, to their background such that the information or instructions provided by the signs are clearly legible when viewed with normal vision from a distance of (500 ± 50) mm. Signs need not be in accordance with the blue colour requirements of ISO 3864-2.

Compliance is checked by inspection and by rubbing the marking by hand for 15 s with a piece of cloth soaked with water and again for 15 s with a piece of cloth soaked with petroleum spirit.

After the tests of 8.12, the marking shall be easily legible, it shall not be easily possible to remove markings.

*In considering the durability of the marking, the effect of **normal use** is taken into account. Thus, for example, marking by means of paint or enamel other than vitreous enamel on containers that are likely to be cleaned frequently is not considered to be durable.*

The petroleum spirit to be used for the test shall be a reagent grade hexane with a minimum of 85 % as n-hexane.

NOTE The designation “n-hexane” is the chemical nomenclature for a “normal” or straight chain hydrocarbon. An example of this petroleum spirit is also known as a certified ACS (American Chemical Society) reagent grade hexane (CAS #110-54-3).

If the marking has an adhesive backing, the adhesive backing shall be durable.

Compliance is checked by either meeting the requirements of UL 969 under the conditions of occasional exposure to oil, humidity and water, and appropriate for the surface to which it is applied, or by the following tests.

- *Three labels applied to the tools or a panel of the test surface material are placed in an oven for a minimum of 24 h with the oven is maintained at a temperature of (120 ± 2) °C, or alternatively for a minimum of 200 h at the temperature that the label is exposed to during the test of Clause 12.*
- *Six additional labels applied to the tool or a panel of the test surface material are placed in a controlled atmosphere maintained at 21 °C to 30 °C with a relative humidity of minimum 45 % for at least 24 h. After this conditioning, immerse three labels in water and the other three labels in IRM 903 oil at a temperature of 21 °C to 30 °C for 48 h.*
- *Three additional labels applied to the tool or a panel of the test surface material are placed in a controlled atmosphere maintained at 21 °C to 30 °C with a relative humidity of minimum 45 % for 72 h.*

After these conditionings, it shall not be easy to remove the label by scraping across the label with a flat steel blade of 0,8 mm thickness and any convenient width, held at right angles, and the label shall show no signs of curling.

8.13 If compliance with this standard depends upon the operation of a replaceable **thermal link** or fuse-link, the reference number or other means for identifying the link shall be marked on the link, or in a place that it is clearly visible after the link has failed, when the tool has been dismantled to the extent necessary for replacing the link.

This requirement does not apply to links which can only be replaced together with a part of the tool.

Compliance is checked by inspection.

8.14 An instruction manual and safety instructions shall be provided with the tool and packaged in such a way that is noticed by the user when the tool is removed from the packaging. An explanation of the symbols required by this standard and used on the tool shall be provided in either the instruction manual or the safety instructions.

They shall be written in the official language(s) of the country in which the tool is sold.

NOTE In Europe (EN 62841-1), the following additional requirement applies:

The words "Original instructions" shall appear on the language version(s) verified by the manufacturer or his authorised representative. Where no "Original instructions" exist in the official language(s) of the country where the tool is to be used, a translation into that/those language(s) shall be provided by the manufacturer or his authorised representative or by the person bringing the tool into the language area in question. The translations shall bear the words "Translation of the original instructions", and they shall be accompanied by a copy of the "Original instructions".

They shall be legible and contrast with the background.

They shall include the business name and address of the manufacturer and, where applicable, his authorised representative. Any address shall be sufficient to ensure contact. Country or state, city and postal code (if any) are deemed sufficient for this purpose.

They shall include the designation of the tool and series or type as required by 8.3, including description of machine such as "drill", "planer" etc.

8.14.1 The subjects of safety instructions are the "General Power Tool Safety Warnings" of Part 1 as given in 8.14.1.1, the specific tool safety warnings of the relevant part of IEC 62841-2, IEC 62841-3 or IEC 62841-4 and any additional safety warning statements deemed necessary by the manufacturer. The "General Power Tool Safety Warnings" and the specific tool safety warnings, if in English, shall be verbatim and in any other official language to be equivalent. The numbering of the safety instructions, as given below, is not mandatory and may be omitted or replaced by other sorting means such as bullets. The "General Power Tool Safety Warnings" may be separate from the instruction manual.

As the term "power tool" or "tool" is not appropriate for **lawn and garden machinery**, for these products an appropriate term such as "machine" may be used.

The term verbatim means word-for-word but permits the differences in spelling between English-speaking countries.

Format of all safety warnings must differentiate, by font, highlighting or similar means, the context of clauses as illustrated below.

All notes in the safety instructions are not to be printed, they are information for the designer of the manual.

8.14.1.1 General power tool safety warnings

 **WARNING** Read all safety warnings, instructions, illustrations and specifications provided with this power tool. Failure to follow all instructions listed below may result in electric shock, fire and/or serious injury.

Save all warnings and instructions for future reference.

The term "power tool" in the warnings refers to your mains-operated (corded) power tool or battery-operated (cordless) power tool.

1) Work area safety

- a) **Keep work area clean and well lit.** *Cluttered or dark areas invite accidents.*
- b) **Do not operate power tools in explosive atmospheres, such as in the presence of flammable liquids, gases or dust.** *Power tools create sparks which may ignite the dust or fumes.*
- c) **Keep children and bystanders away while operating a power tool.** *Distractions can cause you to lose control.*

2) Electrical safety

- a) **Power tool plugs must match the outlet. Never modify the plug in any way. Do not use any adapter plugs with earthed (grounded) power tools.** *Unmodified plugs and matching outlets will reduce risk of electric shock.*
- b) **Avoid body contact with earthed or grounded surfaces, such as pipes, radiators, ranges and refrigerators.** *There is an increased risk of electric shock if your body is earthed or grounded.*
- c) **Do not expose power tools to rain or wet conditions.** *Water entering a power tool will increase the risk of electric shock.*
- d) **Do not abuse the cord. Never use the cord for carrying, pulling or unplugging the power tool. Keep cord away from heat, oil, sharp edges or moving parts.** *Damaged or entangled cords increase the risk of electric shock.*
- e) **When operating a power tool outdoors, use an extension cord suitable for outdoor use.** *Use of a cord suitable for outdoor use reduces the risk of electric shock.*
- f) **If operating a power tool in a damp location is unavoidable, use a residual current device (RCD) protected supply.** *Use of an RCD reduces the risk of electric shock.*

NOTE The term “residual current device (RCD)” can be replaced by the term “ground fault circuit interrupter (GFCI)” or “earth leakage circuit breaker (ELCB)”.

3) Personal safety

- a) **Stay alert, watch what you are doing and use common sense when operating a power tool. Do not use a power tool while you are tired or under the influence of drugs, alcohol or medication.** *A moment of inattention while operating power tools may result in serious personal injury.*
- b) **Use personal protective equipment. Always wear eye protection.** *Protective equipment such as a dust mask, non-skid safety shoes, hard hat or hearing protection used for appropriate conditions will reduce personal injuries.*
- c) **Prevent unintentional starting. Ensure the switch is in the off-position before connecting to power source and/or battery pack, picking up or carrying the tool.** *Carrying power tools with your finger on the switch or energising power tools that have the switch on invites accidents.*
- d) **Remove any adjusting key or wrench before turning the power tool on.** *A wrench or a key left attached to a rotating part of the power tool may result in personal injury.*
- e) **Do not overreach. Keep proper footing and balance at all times.** *This enables better control of the power tool in unexpected situations.*
- f) **Dress properly. Do not wear loose clothing or jewellery. Keep your hair and clothing away from moving parts.** *Loose clothes, jewellery or long hair can be caught in moving parts.*
- g) **If devices are provided for the connection of dust extraction and collection facilities, ensure these are connected and properly used.** *Use of dust collection can reduce dust-related hazards.*
- h) **Do not let familiarity gained from frequent use of tools allow you to become complacent and ignore tool safety principles.** *A careless action can cause severe injury within a fraction of a second.*

4) Power tool use and care

- a) **Do not force the power tool. Use the correct power tool for your application.** *The correct power tool will do the job better and safer at the rate for which it was designed.*

- b) **Do not use the power tool if the switch does not turn it on and off.** *Any power tool that cannot be controlled with the switch is dangerous and must be repaired.*
- c) **Disconnect the plug from the power source and/or remove the battery pack, if detachable, from the power tool before making any adjustments, changing accessories, or storing power tools.** *Such preventive safety measures reduce the risk of starting the power tool accidentally.*
- d) **Store idle power tools out of the reach of children and do not allow persons unfamiliar with the power tool or these instructions to operate the power tool.** *Power tools are dangerous in the hands of untrained users.*
- e) **Maintain power tools and accessories. Check for misalignment or binding of moving parts, breakage of parts and any other condition that may affect the power tool's operation. If damaged, have the power tool repaired before use.** *Many accidents are caused by poorly maintained power tools.*
- f) **Keep cutting tools sharp and clean.** *Properly maintained cutting tools with sharp cutting edges are less likely to bind and are easier to control.*
- g) **Use the power tool, accessories and tool bits etc. in accordance with these instructions, taking into account the working conditions and the work to be performed.** *Use of the power tool for operations different from those intended could result in a hazardous situation.*
- h) **Keep handles and grasping surfaces dry, clean and free from oil and grease.** *Slippery handles and grasping surfaces do not allow for safe handling and control of the tool in unexpected situations.*

5) Service

- a) **Have your power tool serviced by a qualified repair person using only identical replacement parts.** *This will ensure that the safety of the power tool is maintained.*

8.14.1.2 The order of the safety warnings shall be in accordance with either item A) or B) and in accordance with item C):

- A) The IEC 62841-1 warnings are followed by the relevant part of IEC 62841-2, IEC 62841-3 or IEC 62841-4 warnings. The order of the warnings within IEC 62841-1 and the IEC 62841-2, IEC 62841-3 or IEC 62841-4 warnings shall remain as given above and in the relevant part of IEC 62841-2, IEC 62841-3 or IEC 62841-4.
- B) The IEC 62841-1 and the IEC 62841-2, IEC 62841-3 or IEC 62841-4 warnings may be divided into the sections defined by the numbered subtitles and the associated warnings below the numbered subtitle. The order of warnings within each section shall remain as given above and in the relevant part of IEC 62841-2, IEC 62841-3 or IEC 62841-4.

When warnings are presented in this manner, the title of the IEC 62841-1 "General Power Tool Safety Warnings" shall be omitted and the 1st sentence of the warnings in 8.14.1.1 and 8.14.1.3, if applicable, shall be modified as follows:

 **WARNING** Read all safety warnings designated by the  symbol and all instructions.

The sections of the safety warnings shall be presented in the related topic of the instruction manual.

The instruction manual section titles for IEC 62841-1 warnings shall have a format:

 **General Power Tool Safety Warnings – [Section subtitle]**

Example:

 **General Power Tool Safety Warnings – Personal Safety**

The instruction manual section titles for IEC 62841-2, IEC 62841-3 or IEC 62841-4 warnings shall have a format:

 **[Tool category name] Safety Warnings – [Section subtitle]**

Example:

Circular Saw Safety Warnings – Cutting Procedures

If particular IEC 62841-2, IEC 62841-3 or IEC 62841-4 warnings do not have a numbered subtitle, then all warnings required by the particular IEC 62841-2, IEC 62841-3 or IEC 62841-4 shall be presented in the given order and the formatting rule above shall be followed without the [Section subtitle].

- C) Any additional warnings deemed necessary by the manufacturer, shall not be inserted within any of the IEC 62841-1 or IEC 62841-2, IEC 62841-3 or IEC 62841-4 warnings. They may be either appended to the section(s) of the IEC 62841-1 or IEC 62841-2, IEC 62841-3 or IEC 62841-4 in accordance with the topic of the safety warnings or located in any other part of the instruction manual.

8.14.1.3 If the safety instructions are separate from the instruction manual, then the following warnings shall be included in the instruction manual. These warnings, if in English, shall be verbatim and in any other official language to be equivalent.

 **WARNING** Read all safety warnings, instructions, illustrations and specifications provided with this power tool. *Failure to follow all instructions listed below may result in electric shock, fire and/or serious injury.*

Save all warnings and instructions for future reference.

8.14.2 The instruction manual shall be provided with the following, if appropriate.

- a) Instructions for putting into use
- 1) Setting-up or fixing power tools in a stable position as appropriate for power tools which can be mounted on a support or fixed to a bench or the floor;
 - 2) Assembly;
 - 3) Connection to power supply, cabling, fusing, socket type and earthing requirements;
 - 4) For tools adjustable to different **rated voltages**: instructions, illustrations, or both for changing the voltage. The terminal identification shall be provided if the motor connection has to be altered to operate at a voltage other than that for which it was connected when shipped from the factory;
 - 5) Illustrated description of functions;
 - 6) Limitations on ambient conditions;
 - 7) Fitting and adjusting of **guards** required by 19.1;
 - 8) Information about disassembly and reassembly if applicable for transportation and/or use.

101) Information on recommended straps to be used with the tool.

- b) Operating instructions
- 1) Setting and testing;
 - 2) Tool changing;
 - 3) Clamping of the workpiece;
 - 4) Limits on size of workpiece and type of material;
 - 5) General instructions for use;
 - 6) Identification of handle(s) and grasping surface(s) required by 19.4;
 - 7) For tools with electronic speed or load regulators which do not immediately restart the tool after a stalling: a warning that the tool will restart automatically if stalled;
 - 8) For **transportable tools** only: instruction on lifting and transportation.
- c) Maintenance and servicing instructions
- 1) **User maintenance**, such as cleaning, sharpening, lubricating, servicing and/or replacing of parts;
 - 2) Servicing by manufacturer or agent; list of addresses;

- 3) List of user-replaceable parts and instruction how to replace them;
 - 4) Special tools which may be required;
 - 5) For power tools with **type X attachment**: instruction that, if the **supply cord** of this power tool is damaged, it must be replaced by a specially prepared **supply cord** available through the service organization;
 - 6) For power tools with **type Y attachment**: instruction that, if the replacement of the **supply cord** is necessary, this has to be done by the manufacturer or his agent in order to avoid a safety hazard;
 - 7) For power tools with **type Z attachment**: information that the **supply cord** of this power tool cannot be replaced, and the power tool shall be scrapped.
- d) For tools with a **liquid system**, the substance of the following, as appropriate:
- 1) Instructions for
 - the connection to the liquid supply;
 - the use of the liquid and the use of **attachments** to comply with 14.3 in order to
 - avoid the tool being affected by the liquid;
 - the inspection of hoses and other critical parts which could deteriorate;
 - the maximum permitted pressure of the liquid supply;
 - 2) For tools provided with an **RCD**
 - warning never to use the tool without the **RCD** provided with the tool;
 - instruction always to test the correct operation of the **RCD** before starting work, unless the **RCD** is of a self-checking type;
 - 3) For tools for use in combination with an isolating transformer: warning never to use the tool without the transformer delivered with the tool or of the type as specified in these instructions;
 - 4) Instruction that replacement of the plug or the **supply cord** shall always be carried out by the manufacturer of the tool or his service organization;
 - 5) Instruction to keep liquid clear of the parts of the tool and away from persons in the working area.

NOTE In Europe (EN 62841-1), the following additional requirements apply:

Emissions

- 1) The noise emission, measured in accordance with I.2, as follows:
 - A-weighted sound pressure level L_{pA} and its uncertainty K_{pA} , where L_{pA} exceeds 70 dB(A). Where L_{pA} does not exceed 70 dB(A), this fact shall be indicated;
 - A-weighted sound power level L_{WA} and its uncertainty K_{WA} , where the A-weighted sound pressure level L_{pA} exceeds 80 dB(A);
 - peak C-weighted instantaneous sound pressure value L_{pCpeak} , where this exceeds 63 Pa (130 dB in relation to 20 μ Pa).
- 2) Recommendation for the operator to wear hearing protection.
- 3) The vibration total value and its uncertainty measured in accordance with I.3.
When the vibration total value does not exceed 2,5 m/s², this shall be stated.
When the vibration total value exceeds 2,5 m/s², its value shall be given in the instructions.
- 4) The following information:
 - that the declared vibration total value has been measured in accordance with a standard test method and may be used for comparing one tool with another;
 - that the declared vibration total value may also be used in a preliminary assessment of exposure.
- 5) A warning:
 - that the vibration emission during actual use of the power tool can differ from the declared total value depending on the ways in which the tool is used; and
 - of the need to identify safety measures to protect the operator that are based on an estimation of exposure in the actual conditions of use (taking account of all parts of the operating cycle such as the times when the tool is switched off and when it is running idle in addition to the trigger time).

8.14.3 If information about the mass or weight of the tool is provided, it shall be the mass specified in 5.17.

Compliance is checked by inspection.

9 Protection against access to live parts

9.1 Tools shall be so constructed and enclosed that there is adequate protection against accidental contact with live parts. The requirement applies for all positions of the tool, even after removal of detachable parts and soft materials (elastomers), such as soft grip coverings.

Compliance is checked by inspection, and by the tests of 9.2 to 9.4, as applicable.

9.2 An **accessible part** is not considered to be live if:

- the part is supplied with **safety extra-low voltage**
- or
- the part is separated from **live parts** by **protective impedance**.

In the case of **protective impedance**, the current between the part and the supply source shall not exceed 2 mA for d.c., and its peak value shall not exceed 0,7 mA for a.c., and moreover:

- for voltages having a peak value over 42,4 V up to and including 450 V, the capacitance shall not exceed 0,1 μF ;
- for voltages having a peak value over 450 V up to and including 15 kV, the discharge shall not exceed 45 μC .

*Compliance is checked by operating the tool at **rated voltage**. Voltages and currents are measured between the relevant parts and each pole of the supply source. Discharges are measured immediately after the interruption of the supply.*

The quantity of electricity in the discharge is measured using a resistor having a nominal non-inductive resistance of 2 000 Ω . The quantity of electricity is calculated from the sum of all areas recorded on the voltage/time graph without taking voltage polarity into account.

NOTE Details of a suitable circuit for measuring the current are given in Figure C.3.

9.3 Lamps located behind a detachable cover are not removed, provided the tool can be isolated from the supply by means of a plug or an **all-pole disconnection**. However, during insertion or removal of lamps which are located behind a detachable cover, protection against contact with **live parts** of the lamp cap shall be ensured.

This excludes the use of screw type fuses and screw-type miniature circuit breakers which are accessible without the aid of a tool.

Test probe B of IEC 61032:1997 is applied with a force not exceeding 5 N, the tool being in every possible position except that tools normally used on the floor and having a mass exceeding 40 kg are not tilted. Through openings, the test probe is applied to any depth that the probe will permit, and it is rotated or angled before, during, and after insertion to any position.

If the opening does not allow the entry of the probe, a rigid test probe with the dimensions of the test probe B of IEC 61032:1997, but without any articulation, is used, the force on the probe is increased to 20 N and the test with the articulated test probe B of IEC 61032:1997 repeated.

*It shall not be possible to touch with the test probe **live parts** or **live parts** protected only by lacquer, enamel, ordinary paper, cotton, oxide film, beads or sealing compound.*

NOTE Lacquer, enamel, ordinary paper, cotton, oxide film on metal parts, beads and sealing compound, except self-hardening resins, are not considered to give the required protection against contact with **live parts**.

9.4 *Test probe 13 of IEC 61032:1997 is applied with a force not exceeding 5 N through openings in **class II tools** and **class II constructions**, except for those giving access to lamp caps and **live parts** in socket-outlets.*

The test probe is also applied through openings in earthed metal enclosures having a non-conductive coating such as enamel or lacquer.

*It shall not be possible to touch **live parts** with the test probe.*

9.5 **Class II tools** and **class II constructions** shall be so constructed and enclosed that there is adequate protection against accidental contact with **basic insulation**, and metal parts separated from **live parts** by **basic insulation** only.

Parts which are not separated from **live parts** by **double insulation** or **reinforced insulation** shall not be accessible.

This requirement applies for all positions of the tool, even after removal of **detachable parts**.

Compliance is checked by inspection and by applying the test probe B of IEC 61032:1997, as described in 9.3.

10 Starting

10.1 Tools shall start under all normal voltage conditions which may occur in use.

*Compliance is checked by starting the tool 10 times at no-load in succession at a voltage equal to 0,85 times the lowest **rated voltage** or 0,85 times the lower limit of the **rated voltage range**, **control devices** other than speed controls, if any, being set as in **normal use**.*

*Tools shall in addition be started 10 times in succession at a voltage equal to 1,1 times **rated voltage**.*

The interval between consecutive starts is made sufficiently long enough to prevent undue heating.

In all cases, the tool shall operate and overload protection devices incorporated in the tool shall not activate. Centrifugal and other automatic starting switches, if any, shall operate reliably, and without contact chattering.

10.2 Tools shall not draw excessive input current during starting that could lead to nuisance operation of facility mains over-current protection devices.

*Compliance is checked by starting the tool once at **rated voltage** and no-load with any speed controls set for maximum speed and all other **control devices** set as in **normal use**.*

*The current drawn by the tool at $(2,0 \pm 0,2)$ s after starting shall not exceed the greater of 30 A or 4 times the **rated current** of the tool.*

11 Input and current

The **rated input** or **rated current** shall be at least 110 % of the measured no-load input or current.

*Compliance is checked by measuring the power input or current of the tool when stabilized while all circuits which can operate simultaneously are in operation. The test shall be conducted without **accessories** attached or external load.*

*For tools marked with one or more **rated voltages**, the test is made at each of the **rated voltages**. For tools marked with one or more **rated voltage ranges**, the test is made at both the upper and lower limits of the ranges, unless the marking of the **rated input** is related to the mean value of the relevant voltage range, in which case the test is made at a voltage equal to the mean value of that range.*

12 Heating

12.1 Tools shall not attain excessive temperatures with **rated input** or **rated current**.

*Compliance is checked by determining the temperature rise of the various parts under the conditions specified in 12.2 to 12.5. Then the test of Clause C.3 at 1,06 times the **rated voltage** is made under heated conditions.*

12.2 *For tools with one or more **rated voltages**, the tool is operated at each **rated voltage**, under the load conditions specified in 12.2.1.*

The temperatures are measured at the most unfavourable of the two voltage settings. The temperatures that are measured by means of thermocouples are taken while the tool is operating.

*For tools with a **rated voltage range**, the tool is operated*

- at the lower limit of the **rated voltage range**; and*
- at the upper limit of the **rated voltage range**.*

The temperatures are measured at the most unfavourable of the two voltage settings.

12.2.1 *The tool is operated for 30 cycles, each cycle comprising of clinching four straps around a test package within 2 min then the tool switched off for a period of 1 min. The most unfavourable straps recommended by the manufacturer in accordance with 8.14.2 a) 101) are used for the test. The test package is a wooden box 1 m cubic with an internal bracing to prevent collapsing.*

The temperature rises are measured at the end of the "on" period of the 30th cycle or, at the manufacturers option, the tool may be operated continuously until thermal stabilization.

12.3 *This subclause provides specific test conditions for heating elements and cord storage devices.*

12.3.1 *Heating elements, if any, are operated under the conditions specified in Clause 11 of IEC 60335-1:2010, when the tool is operated at a voltage equal to 1,06 times the **rated voltage**.*

12.3.2 *For tools provided with an automatic cord reel, one third of the total length of the cord is unreeled. The temperature rise of the cord sheath is determined as near as possible to the hub of the reel and also between the two outermost layers of the cord on the reel.*

*For cord storage devices, other than automatic cord reels, which are intended to accommodate the **supply cord** partially while the tool is in operation, 50 cm of the cord is*

unwound. The temperature rise of the stored part of the cord is determined at the most unfavourable place.

12.4 *Temperature rises, other than those of windings, are determined by means of fine-wire thermocouples so chosen and positioned that they have the minimum effect on the temperature of the part under test.*

*The temperature rise of electrical insulation, other than that of windings, is determined on the surface of insulation, at places where failure could cause a short circuit, contact between **live parts** and **accessible parts**, bridging of insulation, or reduction of **creepage distances** or **clearances** below the values specified in 28.1.*

Temperature rises of windings are determined by the resistance method, unless the windings are non-uniform, or the method involves severe complications to make the necessary connections for the resistance measurement. In that case, the measurement is made by thermocouples.

*In determining the temperature rises of handles, knobs, grips and the like, consideration is given to all parts which are gripped in **normal use**, and, if of insulating material, to those parts in contact with hot metal.*

NOTE 1 If it is necessary to dismantle the tool to position thermocouples, a remeasurement of the **no-load input** is a method to check that the tool has been correctly reassembled.

NOTE 2 The point of separation of the cores of a multicore cord is an example of a place where thermocouples are positioned.

NOTE 3 Thermocouples having wires with a diameter not exceeding 0,3 mm are considered to be fine-wire thermocouples.

12.5 *During the test, **protective devices** shall not operate and sealing compound, if any, shall not flow out. The temperature rises shall not exceed the values shown in Tables 1a and 1b, except as allowed by 12.6.*

Table 1 – Maximum normal temperature rises (1 of 2)

Parts	Temperature rise K	
Windings ^a , if the insulation system is		
– class 105	75	(65)
– class 120	90	(80)
Windings ^a , if the insulation system according to IEC 60085:2007 is		
– class 130	95	(85)
– class 155	115	
– class 180	140	
– class 200	160	
– class 220	180	
– class 250	210	
Pins of appliance inlets:		
– for hot conditions	95	
– for cold conditions	40	
Ambient of switches, temperature limiters ^b :		
– without <i>T</i> -marking	30	
– with <i>T</i> -marking	<i>T</i> -25	
Rubber or polyvinyl chloride insulation of internal and external wiring, including supply cords :		
– without temperature rating ^c	50	
– with temperature rating (<i>T</i>)	<i>T</i> -25	
Cord sheath used as supplementary insulation	35	
Rubber, other than synthetic, used for gaskets or other parts, the deterioration of which could affect safety:		
– when used as supplementary insulation or as reinforced insulation	40	
– in other cases	50	
Lampholders E14 and B15:		
– metal or ceramic type	130	
– insulated type, other than ceramic	90	
– with <i>T</i> -marking	<i>T</i> -25	
Material used as insulation other than that specified for wires and windings ^d		
– impregnated or varnished textile, paper or press board	70	
– laminates bonded with:		
• melamine-formaldehyde; phenol-formaldehyde or phenol-furfural resins	85	(175)
• urea-formaldehyde resin	65	(150)
– Printed circuit boards bonded with epoxy resin	120	
– moulding of:		
• phenol-formaldehyde with cellulose fillers	85	(175)
• phenol-formaldehyde with mineral fillers	100	(200)
• melamine-formaldehyde	75	(175)
• urea-formaldehyde	65	(150)
– polyester with glass-fibre reinforcement	110	
– silicone rubber	145	
– polytetrafluoroethylene	265	
– pure mica and tightly sintered ceramic material when such materials are used as supplementary insulation or reinforced insulation	400	
– thermoplastic material ^e	–	

Table 1 (2 of 2)

Parts	Temperature rise K
Wood, in general ^f	65
Outer surface of capacitors ^g : – with marking of maximum operating temperature (<i>T</i>) – without marking of maximum operating temperature: • small ceramic capacitors for radio and television interference suppression • capacitors complying with IEC 60384-14 or 14.2 of IEC 60065:2011 • other capacitors ^g	<i>T</i> -25 50 50 20
Parts in contact with oil having a flash-point of <i>t</i> °C	<i>t</i> -50
^a To allow for the fact that the average temperature of windings of universal motors, relays, solenoids, etc., is usually above the temperature at the points on the windings where thermocouples are placed, the figures without parentheses apply when the resistance method is used, and those within parentheses apply when thermocouples are used. For windings of vibrator coils and a.c. motors, the figures without parentheses apply in both cases. For motors constructed so that the circulation of the air between the inside and the outside of the case is prevented, but not necessarily sufficiently enclosed to be called airtight, the temperature rise limits may be increased by 5 K. ^b <i>T</i> signifies the maximum operating temperature. The ambient temperature of switches, thermostats and temperature limiters is the temperature of the air at the hottest point at a distance of 5 mm from the surface of the switch and component concerned. For the purpose of this test, switches and thermostats marked with individual ratings may be considered as having no marking for the maximum operating temperature, if requested by the tool manufacturer. ^c This limit applies to cables, cords and wires complying with the relevant IEC standards; for others, it may be different. While no limit applies to connectors, it is recognized that these limits for wiring apply to internal wiring at the point where it is terminated in a connector. ^d The values in parentheses apply, if the material is used for handles, knobs, grips and the like, and is in contact with hot metal. ^e There is no specific limit for thermoplastic material, which has to withstand the tests of 13.1, for which purpose the temperature rise must be determined. ^f The limit specified concerns the deterioration of wood, and it does not take into account deterioration of surface finishes. ^g There is no limit for the temperature rise of capacitors which are short-circuited in 18.6. If other materials than those mentioned in the table are used, they are not to be subjected to temperatures in excess of their thermal capabilities as determined by ageing tests. The value of the temperature rise of a winding is calculated from the formula: $\Delta t = \frac{R_2 - R_1}{R_1} (k + t_1) - (t_2 - t_1)$ where Δt is the temperature rise; R_1 is the resistance at the beginning of the test; R_2 is the resistance at the end of the test; <i>k</i> is equal to 234,5 for copper windings, and 225 for aluminium windings; t_1 is the ambient temperature at the beginning of the test; t_2 is the ambient temperature at the end of the test. At the beginning of the test, the windings are to be at ambient temperature. It is recommended that the resistance of windings at the end of the test be determined by taking resistance measurements as soon as possible after switching off, and then at short intervals so that a curve of resistance against time can be plotted for ascertaining the resistance at the instant of switching off.	

Table 2 – Maximum outside surface temperature rises

Parts	Temperature rise K
External enclosure, except handles held in normal use	60
Handles, knobs, grips, and the like which, in normal use , are continuously held:	
– of metal	30
– of porcelain or vitreous material	40
– of moulded material, rubber or wood	50
Handles, knobs, grips, and the like which, in normal use , are held for short periods only (e.g. switches):	
– of metal	35
– of porcelain or vitreous material	45
– of moulded material, rubber or wood	60

12.6 The following tests shall be conducted when the temperature rises of the armature and/or field windings exceed the values in Table 1 or when there is doubt with regards to the temperature classification of the insulation system.

Three samples of the armature and/or field are subjected to the following tests.

- a) *Windings are kept for 10 days (240 h) in a heating cabinet, the temperature of which is $(80 \pm 2) ^\circ\text{C}$ in excess of the temperature rise of the windings determined according to 12.4. Then the samples shall be gradually cooled to ambient temperature without introducing thermal shock.*
- b) *After this treatment, no interturn short circuit shall occur.*
- c) *The samples are then subjected to a humidity treatment as specified in 14.1.*
- d) *Immediately after this treatment, they shall withstand the tests of Annex D.*

NOTE The use of a growler is one method to detect interturn short circuits.

Faults which may occur in insulation, which did not show an excessive temperature rise during the test of 12.4, are ignored and are repaired, if necessary, in order to complete the tests of 12.6.

13 Resistance to heat and fire

13.1 The following parts shall be sufficiently resistant to distortion due to heat, if this could cause the tool to fail to comply with this standard:

- parts of thermoplastic material provided as an enclosure to comply with Clause 9;
- parts of thermoplastic material supporting current carrying parts;
- parts of thermoplastic material providing **supplementary insulation** or **reinforced insulation**.

For the purpose of 13.1, “supporting” means that the retention of the current carrying part by the insulating material is relied upon to fulfil 28.1. Contact alone does not constitute support.

This requirement does not apply to:

- insulation and sheath of flexible **supply cords** or internal wiring;
- cord guards;
- ceramic materials;
- insulating parts of motors: e.g. shaft insulation, end spiders, slot liners, wedges, commutators.

Compliance is checked by subjecting the relevant part of thermoplastic material to the ball pressure test of IEC 60695-10-2:2003. Any soft materials (elastomers), such as soft grip coverings, shall be removed.

The required thickness may be obtained by using two or more sections of the part.

The test is carried out at a temperature of $(40 \pm 2)^\circ\text{C}$ plus the maximum temperature rise determined during the test of Clause 12, but it shall be at least

- $(75 \pm 2)^\circ\text{C}$, for parts provided as an enclosure to comply with Clause 9 and for parts providing **supplementary insulation** or **reinforced insulation**;*
- $(125 \pm 2)^\circ\text{C}$, for parts supporting current carrying parts.*

13.2 Parts of non-metallic material shall be adequately resistant to ignition and to spread of fire.

This requirement does not apply to

- internal parts that are more than 13,0 mm from an arcing part such as a commutator, unenclosed switch contacts, and the like;
- internal parts that are more than 1,0 mm from a non-arcing uninsulated **live part**, such as a bus bar, a connecting strap, a terminal, enamelled wire, and the like;
- internal parts that are 1,0 mm or less from connections or conductors carrying 0,2 A or less during **normal operation** or from a low power-circuit as described in Annex H;
- the insulation of wires;
- gears, cams, belts, bearings, fans, decorative trims, knobs which would contribute negligible fuel to fire;
- ceramic materials;
- insulating parts of motors: e.g. shaft insulation, end spiders, slot liners, wedges, commutators;
- small parts, the plastic content of which is less than 5 g;
- other external parts not likely to be ignited or to propagate flames originating from inside the tool.

Compliance is checked by one of the following:

- subjecting parts of non-metallic material, or representative specimens no thicker than the relevant parts, to the glow-wire test of IEC 60695-2-11:2000, which is carried out at 550°C ;*
- the material is classified at least HB according to IEC 60695-11-10:2013 provided that the test sample was no thicker than the relevant part;*
- the material has a glow wire ignition temperature of at least 575°C according to IEC 60695-2-13:2010 provided that the test sample was no thicker than the relevant part.*

Parts for which the above cannot be carried out, such as those made of soft or foamy material, shall meet the requirements specified in ISO 9772:2012 for category HBF material, the test sample being no thicker than the relevant part.

14 Moisture resistance

14.1 Tools shall be proof against humid conditions which may occur.

Compliance is checked by the following humidity test.

Cable entries, if any, are left open; if knock-outs are provided, one of them is opened.

Electrical components, covers, and other parts which can be removed without the aid of a tool are removed and subjected, if necessary, to the humidity test with the main part.

The humidity treatment is carried out in a humidity cabinet containing air with a relative humidity of $(93 \pm 3) \%$, obtained e.g. by placing in the humidity cabinet a saturated solution of Na_2SO_4 or KNO_3 in water, having a sufficiently large contact surface with the air. The temperature of the air, at all places where samples can be located, is maintained within 2 K of any convenient value t between 20 °C and 30 °C. In order to achieve the specified conditions within the cabinet, it is necessary to ensure constant circulation of the air within and, in general, to use a cabinet which is thermally insulated.

Before being placed in the humidity cabinet, the sample is brought to a temperature between t and $(t + 4) \text{ °C}$. The tool is considered to be brought to the specified temperature by keeping it at this temperature for at least 4 h before the humidity treatment.

The tool is kept in the cabinet for 48 h.

*Immediately after this test, the tool shall withstand the tests of Clause C.2 at **rated voltage**. Then the tool shall withstand the test of Annex D in the humidity cabinet, or in the room in which the tool was brought to the prescribed temperature after reassembly of those parts which may have been removed.*

*In addition a test of Clause D.2 is applied between accessible metal parts and the **supply cord** which is wrapped with metal foil where it is located in an inlet bushing, a cord guard or a cord anchorage, any clamping screws being tightened to the torque specified in Table 11. The test voltage is 1 250 V for **class I tools** and 1 750 V for **class II tools**.*

14.2 The enclosure of the tool shall provide the degree of protection against moisture in accordance with the classification of the tool.

Compliance is checked by the appropriate treatment specified in 14.2.2, with the tool conditions as in 14.2.1.

14.2.1 *The tool is not connected to the supply.*

Tools are turned continuously at approximately 1 rev/min through the most unfavourable positions during the test.

Electrical components, covers and other parts which can be removed without the aid of a tool are removed and subjected, if necessary, to the relevant treatment with the main part.

14.2.2 *Tools other than IPX0 are subjected to tests of IEC 60529:2013 as follows:*

- *IPX1 tools are subjected to the test described in 14.2.1;*
- *IPX2 tools are subjected to the test described in 14.2.2;*
- *IPX3 tools are subjected to the test described in 14.2.3a;*
- *IPX4 tools are subjected to the test described in 14.2.4a;*
- *IPX5 tools are subjected to the test described in 14.2.5;*
- *IPX6 tools are subjected to the test described in 14.2.6;*
- *IPX7 tools are subjected to the test described in 14.2.7.*

For this last test, the tool is immersed in water containing approximately 1,0 % NaCl.

Immediately after the appropriate treatment, the tool shall withstand the electric strength test of Annex D, and inspection shall show that there is no trace of water on insulation which could

result in a reduction of **creepage distances** and **clearances** below the values specified in 28.1.

14.3 Liquid systems or spillage of liquid shall not subject the user to an increased risk of electrical shock.

Compliance is checked by the following test:

*The **residual current device**, if any, shall be disabled during the test. Electrical components, covers and other parts which can be removed without the aid of a tool are removed, except those fulfilling the test of 21.22.*

The tool is prepared with approximately 1,0 % NaCl solution in the following modes if applicable:

- *as described in 8.14.2;*
- *the liquid container of the tool is completely filled, and a further quantity, equal to 15 % of the capacity of the container, or 0,25 l, whichever is the greater, is poured in steadily over a period of 60^{+0}_{-10} s, while the tool is resting in its filling position according to 8.14.2 d);*
- *a detachable liquid container is filled completely and mounted and dismounted 10 times on the tool.*

*In each applicable preparation, the tool is operated at **rated voltage** in each position consistent with the relevant part of IEC 62841-2, IEC 62841-3 or IEC 62841-4 and the instructions according to 8.14.2 b) for 1 min while monitoring the leakage current as in Clause C.3. During the test the leakage current shall not exceed:*

- *2 mA for a **class II tool**;*
- *5 mA for a **class I tool**.*

*Following this test, the tool shall meet the electric strength test of D.2 between **live parts** and **accessible parts** after being allowed to dry for 24 h at ambient temperature.*

14.4 Liquid systems shall not subject the user to an increased risk of electrical shock by components not capable of withstanding the pressure during operation.

Compliance is checked by the following test.

*The **residual current device**, if any, shall be disabled during the test.*

*The **liquid system** is closed and an approximately 1,0 % NaCl solution at a hydrostatic pressure equal to twice the pressure stated in 8.14.2 d) 1) is applied for 1 h.*

The tool is then placed for 1 min, in all positions consistent with the relevant part of IEC 62841-2, IEC 62841-3 or IEC 62841-4 and the instructions according to 8.14.2 b) while monitoring the leakage current as in Clause C.2. During the test the leakage current shall not exceed:

- *2 mA for a **class II tool**;*
- *5 mA for a **class I tool**.*

*Following this test, the tool shall meet the electric strength test of Clause D.2 between **live parts** and **accessible parts** after being allowed to dry for 24 h at ambient temperature.*

14.5 Residual current devices used to provide protection from shock in the case of failure of the **liquid system** shall comply with IEC 61540:1999 and shall meet the following requirements a) to c):

- a) The **RCD** shall disconnect both mains conductors, but not the earth conductor if provided, when the leakage exceeds 10 mA and with a maximum response of 300 ms.

Compliance is checked by inspection and the test of 9.9.2 of IEC 61540:1999. In addition, during the test, the earthing conductor shall not become disconnected.

- b) The **RCD** shall be reliable for its intended use.

*Compliance is checked at **rated voltage** by operating the **residual current device** under conditions of simulated leakage as in a) above during conditions of locked rotor of the tool for 50 cycles. The **residual current device** shall operate correctly for all cycles.*

- c) The **RCD** shall be installed such that it is unlikely to be removed during use or normal maintenance.

*This requirement is considered fulfilled if the **residual current device** is fixed to the tool or the power **supply cord** connected to the tool.*

*Where fitted in the **supply cord** the **residual current device** shall be provided with **Type Y attachment** or **Type Z attachment** for connection with the **supply cord** and **interconnection cord**.*

Compliance is checked by inspection.

15 Resistance to rusting

15.1 Ferrous parts used to conduct electricity and those mechanical parts specified in the relevant part of IEC 62841-2, IEC 62841-3 or IEC 62841-4 shall be adequately protected against rusting.

Compliance is checked by the following test.

All grease is removed from the parts to be tested by immersing them in a suitable degreasing agent for 10 min.

The parts are then immersed for 10 min in a 10 % solution of ammonium chloride in water at a temperature of $(20 \pm 5) ^\circ\text{C}$.

Without drying, but after shaking off any drops, the parts are placed for 10 min in a box containing air saturated with moisture at a temperature of $(20 \pm 5) ^\circ\text{C}$.

When using the liquids specified for the test, adequate precautions must be taken to prevent the inhalation of their vapours.

After the parts have been dried for 10 min in a heating cabinet at a temperature of $(100 \pm 5) ^\circ\text{C}$, their surfaces shall show no signs of rust when viewed with normal vision from a distance of $(500 \pm 50) \text{ mm}$.

Traces of rust on sharp edges and any yellowish film removable by rubbing are ignored.

For small helical springs and the like, and for parts exposed to abrasion, a layer of grease may provide sufficient protection against rusting. Such parts are only subjected to the test if there is doubt about the effectiveness of the grease film, and the test is then made without previous removal of the grease.

16 Overload protection of transformers and associated circuits

Tools incorporating circuits supplied from a transformer shall be so constructed that, in the event of short circuits which are likely to occur, excessive temperatures do not occur in the transformer, or in the circuits associated to the transformer.

Examples of short-circuits which are likely to occur are the short-circuiting of bare or inadequately insulated conductors of **safety extra-low voltage** circuits which are accessible, and the internal short-circuiting of lamp filaments.

A failure of insulation complying with the requirements specified for **basic insulation** of class I or **class II construction** is not, for the purpose of this requirement, considered as likely to occur.

*Compliance is checked by applying the most unfavourable short circuit or overload which is likely to occur in **normal use**, the tool being operated as follows:*

- *for tools with **rated voltage(s)**, the tool is operated at a voltage equal to 1,06 times or 0,94 times **rated voltage**, whichever is the more unfavourable;*
- *for tools with a **rated voltage range**, the tool is operated at a voltage equal to 1,06 times the upper limit of the **rated voltage range** or at a voltage equal to 0,94 times the lower limit of the **rated voltage range**, whichever is the more unfavourable.*

*The temperature rise of the insulation of the conductors of **safety extra-low voltage** circuits is determined, and shall not exceed the relevant value specified in Table 1 by more than 15 K.*

The winding temperature of transformers shall not exceed the value specified for windings in Table 3, except for transformers which comply with IEC 61558-1.

NOTE Protection of transformer windings can be, for example, obtained by the inherent impedance of the winding, or by means of fuses, automatic switches, **thermal cut-outs** or similar devices incorporated in the transformer, or similar devices located inside the tool only accessible with the aid of a tool.

17 Endurance

17.1 Tools shall be so constructed that there will be no electrical or mechanical failure that might impair compliance with this standard. The insulation shall not be damaged and contacts and connections shall not work loose as a result of heating, vibrations, etc.

Moreover, overload protection devices incorporated in the tool shall not activate under normal running conditions.

Compliance is checked by the test of 17.2 and, for tools provided with a centrifugal or other starting switch, also by the test of 17.3.

*Immediately after these tests, the tool shall withstand an electric strength test as specified in Annex D, the test voltages being, however, reduced to 75 % of the specified values. Connections shall not have worked loose, and there shall be no deterioration impairing safety in **normal use**.*

17.2 Hand-held tools and transportable tools are operated intermittently at no-load.

NOTE 1 Requirements for **lawn and garden machinery** are specified in the relevant part of IEC 62841-4.

Each cycle of operation comprises an "on" period of 100 s and an "off" period of 20 s, the "off" periods being included in the specified operating time. If the cycle of operation limited by the construction and/or marking is less than 100 s "on" and 20 s "off", then this cycle may be used.

The tool may be switched on and off by means of a switch other than that incorporated in the tool unless this disables a functionality of the tool switch.

Hand-held tools are operated for 24 h at a voltage equal to 1,1 times the highest **rated voltage** or 1,1 times the upper limit of the **rated voltage range**, and then for 24 h at a supply voltage equal to 0,9 times the lowest **rated voltage** or 0,9 times the lower limit of the **rated voltage range**. The 24 h of operation need not be continuous. During the test, the tool is placed in three different positions, the operating time, at each test voltage, being approximately 8 h for each position.

NOTE 2 The change of position is made to prevent abnormal accumulation of carbon dust in any particular place. Examples of the three positions are horizontal, vertically up and vertically down.

Transportable tools are operated for 12 h at a voltage equal to 1,1 times the highest **rated voltage** or 1,1 times the upper limit of the **rated voltage range**, and then for 12 h at a supply voltage equal to 0,9 times the lowest **rated voltage** or 0,9 times the lower limit of the **rated voltage range**. The 12 h of operation need not be continuous. During the test, the tool is placed in its normal operating position according to 8.14.2.

*During this test, replacement of the carbon brushes is allowed, and the tool is oiled and greased as in **normal use**. If mechanical failure occurs and does not impair compliance with this standard, the part that failed may be replaced.*

If the temperature rise of any part of the tool exceeds the temperature rise determined during the test of 12.1, forced cooling or rest periods may be applied, the rest periods being excluded from the specified operating time. If forced cooling is applied, it shall not alter the air flow of the tool or redistribute carbon deposits.

During these tests, overload protection devices incorporated in the tool shall not activate.

17.3 Tools provided with a centrifugal or other automatic starting switch are started 10 000 times at **rated input** or **rated current**, and at a voltage equal to 0,9 times the lowest **rated voltage** or 0,9 times the lower limit of the **rated voltage range**, the operating cycle being that specified in 17.2.

18 Abnormal operation

18.1 Tools shall be so designed that the risk of fire and mechanical damage impairing safety and the protection against electric shock as a result of abnormal operation is obviated as far as is practicable.

Compliance is checked by the tests of 18.3 to 18.4 under the conditions specified in 18.2 applying the acceptance criteria of 18.1.1.

18.1.1 *During the tests, the tool shall not emit flames or molten metal, checked by inspection.*

*After the tests, and when the tool has returned to within 5 K of the ambient temperature, compliance with Clause 9 shall be maintained and the tool shall withstand the electric strength test of Annex D between **live parts** and **accessible parts**.*

If the tool can still operate at the conclusion of the test, it shall continue to comply with 19.1 but without repeating the tests of Clause 20.

18.2 Fuses, **non-self-resetting-thermal cut-outs**, overcurrent protection devices or the like, incorporated into the tool, may be used to provide the necessary protection. **Electronic circuits** that are relied upon for protection shall be evaluated for this **safety critical function** as in 18.8.

Unless otherwise specified, the tests are continued until a **protective device** operates, or until steady conditions are established or an open circuit occurs. If it is an intentionally weak part that is permanently open-circuited to terminate the test, the relevant test is repeated on a second sample. This second test shall be terminated in the same way, unless the test is otherwise satisfactorily completed.

An intentionally weak part is a part intended to fail under conditions of abnormal operation so as to prevent the occurrence of a condition which could impair compliance with this standard. Such a part may be a replaceable component, such as a resistor, a capacitor, or a **thermal link**, or a part of a component to be replaced, such as an inaccessible and non-resettable **thermal cut-out** incorporated in a motor.

18.3 Tools incorporating a series motor are operated without **accessories** at a voltage equal to 1,3 times **rated voltage** for 1 min at no-load.

During the test, parts shall not be ejected from the tool. After this test, the tool need not be capable of further use.

An additional device incorporated in the tool to limit the speed may operate during the test.

18.4 Tools incorporating multiphase induction motors are operated, starting from cold,

- for 30 s, if they are kept switched on by hand or continuously loaded by hand;
- or otherwise, for 5 min;

with one phase disconnected, and under the torque produced while operated at **rated voltage** or the mean value of the **rated voltage range** with **rated input** or **rated current**.

At the end of the test period specified, or at the instant of operation of fuses, **thermal cut-outs**, motor protection devices, and the like, the temperature of the windings shall not exceed the values shown in Table 3.

Table 3 – Maximum winding temperature

Class	105	120	130	155	180	200	220	250
Temperature °C	200	215	225	240	260	280	300	330

18.5 Protection against electric shock shall not be impaired when a **class II tool** or a **class I tool** employing **class II construction** (see 5.10) is subjected to running overload conditions.

For tools other than **lawn and garden machinery** covered by a relevant part of IEC 62841-4 with

- series motors, compliance is checked by the test of 18.5.1. In the case of a **class I tool** with a series motor employing a class II armature construction, the test of 18.5.1 is replaced by the test of 18.5.2;
- motors having electronically commutated stator windings, compliance is checked by the test of 18.5.4;
- other motors, compliance is checked by the test of 18.5.3.