

IEEE Standard for Information Technology—
Telecommunications and information exchange
between systems
Wireless Regional Area Networks (WRAN)—
Specific requirements

Part 22: Cognitive Wireless RAN Medium Access Control (MAC) and Physical Layer (PHY) Specifications: Policies and Procedures for Operation in the TV Bands

Amendment 1: Management and Control Plane Interfaces and Procedures and Enhancement to the Management Information Base (MIB)

IEEE Computer Society

Sponsored by the
LAN/MAN Standards Committee

IEEE
3 Park Avenue
New York, NY 10016-5997
USA

IEEE Std 802.22a™-2014
(Amendment to
IEEE Std 802.22™-2011)

**IEEE Standard for Information Technology—
Telecommunications and information exchange
between systems
Wireless Regional Area Networks (WRAN)—
Specific requirements**

Part 22: Cognitive Wireless RAN Medium Access Control (MAC) and Physical Layer (PHY) Specifications: Policies and Procedures for Operation in the TV Bands

Amendment 1: Management and Control Plane Interfaces and Procedures and Enhancement to the Management Information Base (MIB)

Sponsor

LAN/MAN Standards Committee
of the
IEEE Computer Society

Approved 27 March 2014

IEEE-SA Standards Board

Abstract: This air interface, including the medium access control layer (MAC) and physical layer (PHY), of the fixed and portable point-to-multipoint wireless regional area networks (WRANs) operating in spectrum allocated to the Television Broadcasting Service in the frequency range of 54 MHz to 862 MHz is described in this amendment.

Keywords: broadband wireless access network, cognitive radio, fixed user terminals, IEEE 802.22a™, portable user terminals, radio spectrum sensing, regional area network, WRAN standards

The Institute of Electrical and Electronics Engineers, Inc.
3 Park Avenue, New York, NY 10016-5997, USA

Copyright © 2014 by The Institute of Electrical and Electronics Engineers, Inc.
All rights reserved. Published 30 May 2014. Printed in the United States of America.

IEEE is a registered trademark in the U.S. Patent & Trademark Office, owned by The Institute of Electrical and Electronics Engineers, Incorporated.

PDF: ISBN 978-0-7381-9003-7 STD98586
Print: ISBN 978-0-7381-9004-4 STDPD98586

IEEE prohibits discrimination, harassment, and bullying.

For more information, visit <http://www.ieee.org/web/aboutus/whatis/policies/p9-26.html>.

No part of this publication may be reproduced in any form, in an electronic retrieval system or otherwise, without the prior written permission of the publisher.

Important Notices and Disclaimers Concerning IEEE Standards Documents

IEEE documents are made available for use subject to important notices and legal disclaimers. These notices and disclaimers, or a reference to this page, appear in all standards and may be found under the heading “Important Notice” or “Important Notices and Disclaimers Concerning IEEE Standards Documents.”

Notice and Disclaimer of Liability Concerning the Use of IEEE Standards documents

IEEE Standards documents (standards, recommended practices, and guides), both full-use and trial-use, are developed within IEEE Societies and the Standards Coordinating Committees of the IEEE Standards Association (“IEEE-SA”) Standards Board. IEEE (“the Institute”) develops its standards through a consensus development process, approved by the American National Standards Institute (“ANSI”), which brings together volunteers representing varied viewpoints and interests to achieve the final product. Volunteers are not necessarily members of the Institute and participate without compensation from IEEE. While IEEE administers the process and establishes rules to promote fairness in the consensus development process, IEEE does not independently evaluate, test, or verify the accuracy of any of the information or the soundness of any judgments contained in its standards.

IEEE does not warrant or represent the accuracy or content of the material contained in its standards, and expressly disclaims all warranties (express, implied and statutory) not included in this or any other document relating to the standard, including, but not limited to, the warranties of: merchantability; fitness for a particular purpose; non-infringement; and quality, accuracy, effectiveness, currency, or completeness of material. In addition, IEEE disclaims any and all conditions relating to: results; and workmanlike effort. IEEE standards documents are supplied “AS IS” and “WITH ALL FAULTS.”

Use of an IEEE standard is wholly voluntary. The existence of an IEEE standard does not imply that there are no other ways to produce, test, measure, purchase, market, or provide other goods and services related to the scope of the IEEE standard. Furthermore, the viewpoint expressed at the time a standard is approved and issued is subject to change brought about through developments in the state of the art and comments received from users of the standard.

In publishing and making its standards available, IEEE is not suggesting or rendering professional or other services for, or on behalf of, any person or entity nor is IEEE undertaking to perform any duty owed by any other person or entity to another. Any person utilizing any IEEE Standards document, should rely upon his or her own independent judgment in the exercise of reasonable care in any given circumstances or, as appropriate, seek the advice of a competent professional in determining the appropriateness of a given IEEE standard.

IN NO EVENT SHALL IEEE BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO: PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE PUBLICATION, USE OF, OR RELIANCE UPON ANY STANDARD, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE AND REGARDLESS OF WHETHER SUCH DAMAGE WAS FORESEEABLE.

Translations

The IEEE consensus development process involves the review of documents in English only. In the event that an IEEE standard is translated, only the English version published by IEEE should be considered the approved IEEE standard.

Official statements

A statement, written or oral, that is not processed in accordance with the IEEE-SA Standards Board Operations Manual shall not be considered or inferred to be the official position of IEEE or any of its committees and shall not be considered to be, or be relied upon as, a formal position of IEEE. At lectures, symposia, seminars, or educational courses, an individual presenting information on IEEE standards shall make it clear that his or her views should be considered the personal views of that individual rather than the formal position of IEEE.

Comments on standards

Comments for revision of IEEE Standards documents are welcome from any interested party, regardless of membership affiliation with IEEE. However, IEEE does not provide consulting information or advice pertaining to IEEE Standards documents. Suggestions for changes in documents should be in the form of a proposed change of text, together with appropriate supporting comments. Since IEEE standards represent a consensus of concerned interests, it is important that any responses to comments and questions also receive the concurrence of a balance of interests. For this reason, IEEE and the members of its societies and Standards Coordinating Committees are not able to provide an instant response to comments or questions except in those cases where the matter has previously been addressed. For the same reason, IEEE does not respond to interpretation requests. Any person who would like to participate in revisions to an IEEE standard is welcome to join the relevant IEEE working group.

Comments on standards should be submitted to the following address:

Secretary, IEEE-SA Standards Board
445 Hoes Lane
Piscataway, NJ 08854 USA

Laws and regulations

Users of IEEE Standards documents should consult all applicable laws and regulations. Compliance with the provisions of any IEEE Standards document does not imply compliance to any applicable regulatory requirements. Implementers of the standard are responsible for observing or referring to the applicable regulatory requirements. IEEE does not, by the publication of its standards, intend to urge action that is not in compliance with applicable laws, and these documents may not be construed as doing so.

Copyrights

IEEE draft and approved standards are copyrighted by IEEE under U.S. and international copyright laws. They are made available by IEEE and are adopted for a wide variety of both public and private uses. These include both use, by reference, in laws and regulations, and use in private self-regulation, standardization, and the promotion of engineering practices and methods. By making these documents available for use and adoption by public authorities and private users, IEEE does not waive any rights in copyright to the documents.

Photocopies

Subject to payment of the appropriate fee, IEEE will grant users a limited, non-exclusive license to photocopy portions of any individual standard for company or organizational internal use or individual, non-commercial use only. To arrange for payment of licensing fees, please contact Copyright Clearance Center, Customer Service, 222 Rosewood Drive, Danvers, MA 01923 USA; +1 978 750 8400. Permission to photocopy portions of any individual standard for educational classroom use can also be obtained through the Copyright Clearance Center.

Updating of IEEE Standards documents

Users of IEEE Standards documents should be aware that these documents may be superseded at any time by the issuance of new editions or may be amended from time to time through the issuance of amendments, corrigenda, or errata. An official IEEE document at any point in time consists of the current edition of the document together with any amendments, corrigenda, or errata then in effect.

Every IEEE standard is subjected to review at least every ten years. When a document is more than ten years old and has not undergone a revision process, it is reasonable to conclude that its contents, although still of some value, do not wholly reflect the present state of the art. Users are cautioned to check to determine that they have the latest edition of any IEEE standard.

In order to determine whether a given document is the current edition and whether it has been amended through the issuance of amendments, corrigenda, or errata, visit the IEEE-SA Website at <http://ieeexplore.ieee.org/xpl/standards.jsp> or contact IEEE at the address listed previously. For more information about the IEEE-SA or IEEE's standards development process, visit the IEEE-SA Website at <http://standards.ieee.org>.

Errata

Errata, if any, for all IEEE standards can be accessed on the IEEE-SA Website at the following URL: <http://standards.ieee.org/findstds/errata/index.html>. Users are encouraged to check this URL for errata periodically.

Patents

Attention is called to the possibility that implementation of this standard may require use of subject matter covered by patent rights. By publication of this standard, no position is taken by the IEEE with respect to the existence or validity of any patent rights in connection therewith. If a patent holder or patent applicant has filed a statement of assurance via an Accepted Letter of Assurance, then the statement is listed on the IEEE-SA Website at <http://standards.ieee.org/about/sasb/patcom/patents.html>. Letters of Assurance may indicate whether the Submitter is willing or unwilling to grant licenses under patent rights without compensation or under reasonable rates, with reasonable terms and conditions that are demonstrably free of any unfair discrimination to applicants desiring to obtain such licenses.

Essential Patent Claims may exist for which a Letter of Assurance has not been received. The IEEE is not responsible for identifying Essential Patent Claims for which a license may be required, for conducting inquiries into the legal validity or scope of Patents Claims, or determining whether any licensing terms or conditions provided in connection with submission of a Letter of Assurance, if any, or in any licensing agreements are reasonable or non-discriminatory. Users of this standard are expressly advised that determination of the validity of any patent rights, and the risk of infringement of such rights, is entirely their own responsibility. Further information may be obtained from the IEEE Standards Association.

Participants

At the time this amendment went to sponsor ballot, the IEEE 802.22 Working Group had the following officer:

Apurva Mody, *Chair*
Chang-woo Pyo, *Vice Chair*

When this amendment was sent to sponsor ballot, the Task Group a had the following membership:

Ranga Reddy, *Chair and Editor*

Winston Caldwell
Charles Einolf
Peter Flynn
Tom Gurley
Hiroshi Harada
Bob Heile
Byng Jeong Jang
Jerry Kalke

Hynduk Kang
Gwangzeen Ko
Bruce Kraemer
Donghun Lee
Liru Lu
Michael Lynch
Paul Nikolich

Shigenobu Sasaki
Steven Shellhammer
Chunyi Song
Victor Tawil
Keat-Beng Toh
Junyi Wang
Bing Xuan Zhao
Xin (Amy) Zhang

Major contributions were received from the following individuals:

Gerald Chouinard
Charles Einolf

Sunghyun Hwang
Gwangzeen Ko
Chang-woo Pyo

Ranga Reddy
Ivan Reede

The following members of the balloting committee voted on this amendment. Balloters may have voted for approval, disapproval, or abstention.

Wole Akpose
Thomas Alexander
Nobumitsu Amachi
Butch Anton
Mathild Benveniste
Harry Bims
Nancy Bravin
William Byrd
Juan Carreon
Dave Cavalcanti
Keith Chow
Richard Edgar
Charles Einolf
Peter Flynn
Avraham Freedman
Devon Gayle
Randall Groves
Michael Gundlach
Marco Hernandez
Werner Hoelzl
Sunghyun Hwang
Noriyuki Ikeuchi

Akio Iso
Atsushi Ito
Bobby Jose
Shinkyoo Kaku
Piotr Karocki
Stuart Kerry
Gwangzeen Ko
Bruce Kraemer
Yasushi Kudoh
Geoff Ladwig
Arthur H. Light
Liru Lu
William Lumpkins
Greg Luri
Elvis Maculuba
Jeffery Masters
Edward McCall
Michael McInnis
Apurva Mody
Jose Morales
Peter Murray
Nabil Nasser

Michael Newman
Nick S. A. Nikjoo
Venkatesha Prasad
Ivan Reede
Maximilian Riegel
Robert Robinson
William Rose
John Santhoff
Shigenobu Sasaki
Naotaka Sato
Kapil Sood
Thomas Starai
Rene Struik
Walter Struppler
Keat-Beng Toh
Ha-Nguyen Tran
Dmitri Varsanofiev
Prabodh Varshney
George Vlantis
Hung-Yu Wei
Oren Yuen
Daidi Zhong

When the IEEE-SA Standards Board approved this on 27 March 2014, it had the following membership:

John Kulick, *Chair*
Jon Walter Rosdahl, *Vice-chair*
Richard H. Hulett, *Past Chair*
Konstantinos Karachalios, *Secretary*

Peter Balma
Farooq Bari
Ted Burse
Clint Chaplain
Stephen Dukes
Jean-Phillippe Faure
Gary Hoffman

Michael Janezic
Jeffrey Katz
Joseph L. Koepfinger*
David J. Law
Hung Ling
Oleg Logvinov
Ted Olsen
Glenn Parsons

Ron Peterson
Adrian Stephens
Peter Sutherland
Yatin Trivedi
Phil Winston
Don Wright
Yu Yuan

*Member Emeritus

Also included are the following nonvoting IEEE-SA Standards Board liaisons:

Richard DeBlasio, *DOE Representative*
Michael Janezic, *NIST Representative*

Catherine Berger
IEEE Standards Senior Program Manager, Document Development

Lisa Perry
IEEE Standards Program Manager, Technical Program Development

Introduction

This introduction is not part of IEEE Std 802.22a-2014, IEEE Standard for Information Technology—Telecommunications and information exchange between systems—Wireless Regional Area Networks(WRAN)—Specific requirements—Part 22: Cognitive Wireless RAN Medium Access Control (MAC) and Physical Layer (PHY) Specifications: Policies and Procedures for Operation in the TV Bands—Amendment 1: Management and Control Plane Interfaces and Procedures and Enhancement to the Management Information Base (MIB).

This amendment to IEEE Std 802.22-2011 defines a new clause for Management and Control Plane interfaces and procedures for operation in very high frequency and ultra-high frequency (VHF/UHF) television (TV) broadcast bands between 54 MHz and 862 MHz. The Management Information Base (MIB) structure enhancement includes changes to comply with the ASN.1 format and support for the new clause. Modifications to the existing clause on primitives for cognitive radio capabilities (Clause 10) to align it with the content in the MIB clause (Clause 13) and the new clause (Clause 14) are also defined.

Contents

5	System architecture	2
5.2	Management reference architecture	2
5.2.1	Service access primitives (SAPs) PHY/MAC to NCMS interface	2
5.2.4	Managed objects	3
10	Cognitive radio capability	3
~~10.7~~	~~Primitives for cognitive radio capabilities~~	~~3~~
12	Parameters and connection management	4
12.1	Parameters, timers, message IEs	4
12.1.1	MAC (dynamic service flow, multicast, ARQ, capability, and bandwidth management)	4
12.1.2	PHY (initialization, operation, and DS/US synchronization)	6
12.1.3	Coexistence	8
12.1.4	Security	9
12.1.5	Cognitive radio capabilities (SM, SSA, incumbent protection, QP management)	10
13	MIB structure	14
13.1	MIB description	14
13.1.1	wranDevMib	14
13.1.2	wranIfBsMib	20
13.1.3	wranIfBsSfMgmtMibwranIfBsSMgmt	72
13.1.4	wranIfCpeMib	85
13.1.5	wranIfSmMib	90
13.1.6	wranIfSsaMib	102
13.1.7	wranIfDatabaseServiceMib	116
13.2	MIB module definitions (ASN.1)	126
13.2.1	wranDevMib	126
13.2.2	wranIfBsMib	144
13.2.3	wranIfBsSfMgmtMib	291
13.2.4	wranIfCpeMib	323
13.2.5	wranIfSmMib	335
13.2.6	wranIfSsaMib	367
13.2.7	wranIfDatabaseServiceMib	407
14	Management plane interfaces and procedures	430
14.1	Primitive format	430
14.1.1	Purpose	430
14.1.2	SAP type	430
14.1.3	Operation type	430
14.1.4	Destination	430
14.1.5	Data	430
14.1.6	When generated	431
14.1.7	Effect of receipt	431
14.2	Primitive definitions	431
14.2.1	Management SAP (M-SAP)	431
14.2.2	Spectrum Manager-Spectrum Sensing Function SAP (SM-SSF-SAP)	463
14.2.3	Spectrum Manager-Geolocation SAP (SM-GL-SAP)	467
14.2.4	Control SAP (C-SAP)	470

IEEE Standard for Information Technology—
Telecommunications and information exchange
between systems
Wireless Regional Area Networks (WRAN)—
Specific requirements

Part 22: Cognitive Wireless RAN Medium Access Control (MAC) and Physical Layer (PHY) Specifications: Policies and Procedures for Operation in the TV Bands

Amendment 1: Management and Control Plane Interfaces and Procedures and Enhancement to the Management Information Base (MIB)

IMPORTANT NOTICE: IEEE Standards documents are not intended to ensure safety, security, health, or environmental protection, or ensure against interference with or from other devices or networks. Implementers of IEEE Standards documents are responsible for determining and complying with all appropriate safety, security, environmental, health, and interference protection practices and all applicable laws and regulations.

This IEEE document is made available for use subject to important notices and legal disclaimers. These notices and disclaimers appear in all publications containing this document and may be found under the heading “Important Notice” or “Important Notices and Disclaimers Concerning IEEE Documents.” They can also be obtained on request from IEEE or viewed at <http://standards.ieee.org/IPR/disclaimers.html>.

NOTE—The editing instructions contained in this amendment define how to merge the material contained therein into the existing base standard and its amendments to form the comprehensive standard. The editing instructions are shown in ***bold italic***. Four editing instructions are used: change, delete, insert, and replace. ***Change*** is used to make corrections in existing text or tables. The editing instruction specifies the location of the change and describes what is being changed by using ~~strike through~~ (to remove old material) and underscore (to add new material). ***Delete*** removes existing material. ***Insert*** adds new material without disturbing the existing material. Insertions may require renumbering. If so, renumbering instructions are given in the editing instruction. ***Replace*** is used to make changes in figures or equations by removing the existing figure or equation and replacing it with a new one. Editing instructions, change markings, and this NOTE will not be carried over into future editions because the changes will be incorporated into the base standard.¹

¹ Notes in text, tables, and figures are given for information only and do not contain requirements needed to implement the standard.

5 System architecture

5.2 Management reference architecture

Change the second paragraph of 5.2 as follows:

Figure 5 shows an example of a management reference model for WRANs. ~~It~~ This example consists of a Network Management System (NMS), a Network Control System (NCS), and managed nodes. The BS and CPEs shall collect and store the managed objects (see 5.2.4) in the format as defined in the WRAN Management Information Base (MIB). The MIB is defined and specified in Clause 13. The Network Control System contains the service flow and the associated QoS information that is pre-populated in service classes at the BS and instantiated when a CPE requests services.

Change the fourth paragraph of 5.2 as follows:

In the management reference architecture example in Figure 5, management information that is stored in the form of MIBs must be conveyed using SNMP messages. Use of MIBs to define the structure of management information and SNMP to convey this data is optional. If MIBs and the SNMP are not used to store and transport management information, the network operator and device manufacturers will have to specify another means to enable management functions. The management information between the CPE and the BS may be carried over a secondary management connection. ~~The management information can also be conveyed using the normal SNMP messages.~~

Change 5.2.1 as follows:

5.2.1 Service access primitives (SAPs)~~PHY/MAC to NCMS interface~~

In the Management/Control Plane, ~~t~~The NCMS is interfaced to the MAC and PHY layer entities of the CPE and BS through two Service Access Primitives ~~Points~~ (SAPs). The BS and CPE shall include a Control-SAP (C-SAP) and Management-SAP (M-SAP) that provide NCMS access to the control plane and management plane functions from upper layers. The M-SAP is used for less time-sensitive Management plane primitives, and the C-SAP is used for more time-sensitive Control plane primitives. The C-SAP and M-SAP interfaces are described in 5.2.1.1 and 5.2.1.2. The NCMS uses the C-SAP and M-SAP to interface with the IEEE 802.22 managed nodes.

In the Cognitive Plane, the SM is interfaced with the SSA through two SAPs. The SM uses the SM-SSF SAP to interface with the Spectrum Sensing Function on the SSA and the SM-GL SAP to interface with the Geolocation function on the SSA.

Insert the following new subclauses (5.2.1.3 and 5.2.1.4) after 5.2.1.2:

5.2.1.3 SM-SSF SAP (SM-SSF-SAP)

The SM-SSF SAP includes, but is not limited to, primitives related to the following:

- Channel Sensing configuration
- Channel Sensing reporting

5.2.1.4 SM-GL SAP (SM-GL-SAP)

The SM-GL SAP includes, but is not limited to, primitives related to the following:

- Geolocation fix calculation request
- Geolocation fix calculation results

5.2.4 Managed objects

Change 5.2.4 as follows:

Managed information items are also known as “managed objects.” If managed objects are defined as MIBs (see Clause 13), the definition of them shall follow conventions. The definition of managed objects in this standard is expressed in IETF RFC 2578. It supports a management protocol agnostic approach, including SNMP. If managed objects are not defined as MIBs, use of conventions defined in IETF RFC 2578 to define them is optional, and use of SNMP to transport this information is optional as well.

10 Cognitive radio capability

Delete 10.7 to 10.7.6.4.2 (including Table 252 to Table 271) as follows:

~~10.7 Primitives for cognitive radio capabilities~~

~~10.7.1 Database service primitives [and its subclauses]~~

~~The following ... 10.7.1.8 ... (latitude, longitude)~~

NOTE—Information on database service primitives can now be found in 14.2.1.3.

~~10.7.2 BS configuration and monitoring primitives [and its subclauses]~~

~~The BS ... 10.7.2.4.2 ... another request.~~

NOTE—Information on BS configuration and monitoring primitives can now be found in 14.2.1.4.

~~10.7.3 CPE reports the resulting available WRAN services list [and its subclauses]~~

~~The selection ... 10.7.3.3.2 ... another query.~~

NOTE—Information on CPE reports the resulting available WRAN services list can now be found in 14.2.1.5.

~~10.7.4 Spectrum Sensing Services [and its subclauses]~~

~~The IEEE ... 10.7.4.3.2 ... PHY SSF.~~

NOTE—Information on spectrum sensing function primitives can now be found in 14.2.2.1.

10.7.5 Geolocation services [and its subclauses]

The PHY ... ~~10.7.5.3.2~~ ... another request.

NOTE—Information on geolocation primitives can now be found in 14.2.3.1.

10.7.6 Antenna primitives [and its subclauses]

Essential antenna ... ~~10.7.6.4.2~~ ... to EIRP.

NOTE—Information on antenna primitives can now be found in 14.2.1.6.

12 Parameters and connection management

12.1 Parameters, timers, message IEs

12.1.1 MAC (dynamic service flow, multicast, ARQ, capability, and bandwidth management)

Change Table 272 as follows:

Table 272—MAC parameters, timers, message IEs

Entity/ Scope	Name	Reference	Min value	Default value	Max value
CPE, BS	DSx Request Retries	Number of Timeout Retries on DSA/DSC/DSD Requests.	—	3	—
CPE, BS	DSx Response Retries	Number of Timeout Retries on DSA/DSC/DSD Responses.	—	3	—
CPE	T6	Wait for registration response.	—	—	3 s
CPE, BS	T7	Wait for DSA/DSC/DSD Response timeout.	—	—	1 s
CPE, BS	T8	Wait for DSA/DSC Acknowledge timeout.	—	—	300 ms
BS	T9	Registration Timeout, the time allowed between the BS's sending a RNG-CMD (success) to a CPE and receiving a CBC-REQ from that same CPE.	300 ms	300 ms	—
CPE, BS	T10	Wait for Transaction End timeout.	—	—	3 s
BS	T13	The time allowed for an CPE, following receipt of a REG-RSP message to send a TFTP-CPLT message to the BS.	15 min	15 min	—
CPE	T14	Wait for DSx-RSP/DSX-RVD Timeout.	—	—	200 ms
BS	T15	Wait for MCA-RSP.	20 ms	20 ms	—
CPE	T16	Wait for bandwidth request grant.	10 ms	—	Service QoS dependent
CPE	T18	Wait for CBC-RSP timeout.	—	5 ms	<< T9
CPE, BS	T22	Wait for ARQ-Reset.	—	—	0.5 s
CPE	T26	Wait for TFTP-RSP.	10 ms	10 ms	200 ms

Entity/ Scope	Name	Reference	Min value	Default value	Max value
BS	T27 as idle timer	Maximum time between unicast grants to CPE when BS believes CPE upstream transmission quality is <i>good enough</i> .	CPE Ranging Response Processing Time	—	—
BS	T27 as active timer	Maximum time between unicast grants to CPE when BS believes CPE upstream transmission quality is <i>not good enough</i> .	CPE Ranging Response Processing Time	—	—
BS	T28	Time allowed for the BS to complete the transmission of the backup/candidate channel list to its CPEs after initial registration by a new CPE, including the database service query.	—	60 s	$\ll T45$
CPE	CBC Request Retries	Number of retries on CBC Request.	—	3	—
	DSx Flow Control	Maximum # of ongoing dynamic service flow (DSx) transactions that are ongoing.	1	4	Infinite
	MCA Flow Control	Maximum # of ongoing multicast group assignment (MCA-REQ/RSP) transactions.	1	—	Infinite
	Max # of multicast groups	Maximum # of multicast groups the BS supports in a cell.	—	—	~~510544~~
BS, CPE	T30	CPE registration Timer (see 7.7.7.3.4 and 7.14.2.11).	160 ms	40.8 s	10,485.6 s
BS, CPE	ARQ_BSN_MODULUS	Number of unique BSN values.	—	2^{10}	—
BS, CPE	ARQ_WINDOW_SIZE	Max # of un-acknowledged ARQ blocks at a given time.	—	—	$\leq (\text{ARQ_BSN_MODULUS})/2$
BS, CPE	ARQ_BLOCK_LIFETIME	Max time interval an ARQ block shall be managed by the Tx ARQ state machine.	10 μ s	—	655.36 ms
BS, CPE	ARQ_RETRY_TIMEOUT (TRANSMITTER_DELAY/RECEIVER_DELAY)	Minimum time interval a transmitter shall wait before retransmission of a unacknowledged block.	10 μ s	—	655.36 ms
BS, CPE	ARQ_SYNC_LOSS_TIMEOUT	Max amount of time ARQ_TX_WINDOW_START or ARQ_RX_WINDOW_START shall be allowed to remain at the same value before declaring a loss of synchronization of the sender and receiver state machines for an ongoing transfer.	10 μ s	—	655.36 ms
BS, CPE	ARQ_RX_PURGE_TIMEOUT	Time interval the receiver shall wait after successful reception of a block that does not result in advancement of ARQ_RX_WINDOW_START, before advancing ARQ_RX_WINDOW_START.	10 μ s	—	655.36 ms
BS, CPE	ARQ_BLOCK_SIZE	Size of ARQ block that SDU is fragmented into.	1 octet	—	2040 octet

Entity/ Scope	Name	Reference	Min value	Default value	Max value
BS	Max CPE Transmit EIRP	Maximum CPE Transmit EIRP as negotiated during registration.	−64 dBm	—	+63.5 dBm
CPE	Registration Request Retries	Number of retries on registration requests.	3	—	—
CPE	Request Retries	Number of retries on bandwidth allocation requests.	16	—	—

12.1.2 PHY (initialization, operation, and DS/US synchronization)

Change Table 273 as follows:

Table 273—PHY parameters, timers, message IEs

Entity/ Scope	Name	Reference	Min value	Default value	Max value
BS	DCD Interval	Time between transmission of DCD messages.	—	—	10 s
BS	UCD Interval	Time between transmission of UCD messages.	—	—	10 s
BS	UCD Transition	The time the BS shall wait after repeating a UCD message with an incremented Configuration Change Count before issuing a US-MAP message referring to Upstream_Burst_Profiles defined in that UCD message.	2 MAC frames	—	—
BS	DCD Transition	The time the BS shall wait after repeating a DCD message with an incremented Configuration Change Count before issuing a DS-MAP message referring to Downstream_Burst_Profiles defined in that DCD message.	2 MAC frames	—	—
BS	Initial Ranging Interval	Time between Initial Ranging opportunities assigned by the BS.	—	—	2 s
BS	CLK-CMP Interval	Time between the clock compare measurements used for the generation of CLK-CMP messages.	50 ms	50 ms	50 ms
CPE	Lost DS-MAP Interval (T56)	Time since last received DS-MAP message before downstream synchronization is considered lost.	—	—	600 ms
CPE	Lost US-MAP Interval (T57)	Time since last received US-MAP message before upstream synchronization is considered lost.	—	—	600 ms
CPE	Lost SCH (T58)	Number of SCH that can be lost until synchronization is considered lost.	—	—	15
CPE	CDMA Ranging Retries	Number of retries on CDMA Ranging Requests.	1	—	4
CPE, BS	Invited Ranging Retries	Number of retries on inviting Ranging Requests.	16	—	—
BS	US-MAP Process Time	Time provided between arrival of the last bit of a US-MAP at a CPE and effectiveness of that map.	5 symbols	—	—

Entity/ Scope	Name	Reference	Min value	Default value	Max value
BS	CPE Ranging Response Processing Time	Time allowed for a CPE following receipt of a ranging response before it is expected to reply to an invited ranging request.	10 ms	—	—
CPE	T1	Wait for DCD timeout.	—	—	$5 \times$ DCD interval maximum value
CPE	T2	Wait for broadcast ranging timeout.	—	—	$5 \times$ ranging interval
CPE	T3	Ranging Response reception timeout following the transmission of a Ranging Request.	—	200 ms	200 ms
CPE	T4	Wait for unicast ranging opportunity. If the pending-until-complete field was used earlier by this CPE, then the value of that field shall be added to this interval.	1 s	30 min (fixed) 10 min (portable)	30 min
BS	T5	Wait for Upstream Channel Change response.	—	—	2 s
CPE	T12	Wait for UCD descriptor.	—	—	$5 \times$ UCD Interval maximum value
CPE	T20	Time the CPE searches for preambles on a given channel.	2 MAC frames	—	—
CPE	T21	Time the CPE searches for DS-MAP on a given channel.	—	—	10 s
BS	EIRP _{BS}	EIRP of BS (DS).	−64 dBm	—	63.5 dBm
BS	TTG	~~Transmit-receive Turnaround Gap.~~ ~~Transmit/Receive Transition Gap~~	~~—~~ ~~105 μs~~	210 μs	~~—~~ ~~333 μs~~
CPE	RTG	~~Receive-transmit Turnaround Gap.~~	~~81.8 μs~~	—	~~303.5 μs~~
BS	DIUC Mandatory Exit Threshold	CINR at or below which this DIUC can no longer be used and where change to a more robust DIUC is required.	−64 dB	—	+63.5 dB
BS	DIUC Mandatory Entry Threshold	The minimum CINR required to start using this DIUC when changing from a more robust DIUC is required.	−64 dB	—	+63.5 dB
BS	Boosting	Boosting applied to a DS allocation.	−12 dB	0 dB	+9 dB
BS, CPE	BW Request Backoff Start	Initial size of BW Request opportunity used by CPEs to contend to send BW requests to BS.	0	—	15
BS, CPE	BW Request Backoff End	Final size of BW Request opportunity used by CPEs to contend to send BW requests to BS.	~~0~~ 0+	—	15
BS, CPE	UCS Notification Backoff Start	Initial backoff window size in units of UCS Notification opportunity used by CPEs to contend to send UCS notifications to BS.	0	—	15
BS, CPE	UCS Notification Backoff End	Final size of UCS Notification opportunity used by CPEs to contend to send UCS Notification to BS.	~~0~~ 0+	—	15

Entity/ Scope	Name	Reference	Min value	Default value	Max value
BS, CPE	Contention-based reservation Timeout	Number of US-MAPs to receive before contention-based reservation is attempted again for the same connection.	0+	—	255
BS, CPE	BW Request opportunity size	Size (in OFDM slots) of PHY bursts, that a CPE may use to format and transmit a bandwidth request message in a contention request opportunity.	0+	—	255
BS, CPE	UCS Notification request opportunity size	Size (in OFDM slots) of PHY bursts that a CPE may use to transmit a UCS Notification.	0+	—	255
BS, CPE	# of initial ranging codes	Number of initial ranging CDMA codes (N).	0+	—	255
BS, CPE	# of periodic ranging codes	Number of periodic ranging CDMA codes (M).	0+	—	255
BS, CPE	# of bandwidth request codes	Number of bandwidth request CDMA codes (L).	0+	—	255
BS, CPE	# of UCS notification codes	Number of UCS notification CDMA codes (I).	0+	—	255
BS, CPE	Start of CDMA codes group	Indicates the starting number, S, of the group of codes used for the US.	0	See 6.10.3 =	255
BS, CPE	EIRP Density Level	EIRP Transmitted per subcarrier.	−104 dBm	—	+23.5 dBm
BS, CPE	EIRP Control	EIRP per subcarrier that the CPE should apply to correct its current transmission EIRP.	−104 dBm	—	+23.5 dBm
BS	EIRP Per subcarrier	EIRP transmitted per subcarrier.	−104 dBm	—	+23.5 dBm

12.1.3 Coexistence

Change Table 274 as follows:

Table 274—Coexistence parameters, timers, message IEs

Entity/ Scope	Name	Reference	Min value	Default value	Max value
BS	~~Tse (T33)~~	~~Time between transmission of the broadcast message of the operating backup and candidate channel sets for the purposes of spectrum etiquette.~~	—	—	~~60 s~~
BS	T32	Wait for the Frame Contention Response message.	1 superframe	—	32 superframes

Entity/ Scope	Name	Reference	Min value	Default value	Max value
BS	FCW	Frame Contention Window: number of superframes during which a BS (FC_DST) accumulates the frame contention requests before reacting to it and responding to the FC_SRCs.	0 superframe	—	16 superframes
BS	SCWBackoff_Max	Integer denoting the maximum superframes for the SCW backoff window.	<u>0</u>	—	<u>15</u>
BS	Frame Contention_Min	Number of frames not available for contention at a BS in a coexistence situation.	0	2	8
BS	FCN_range	Exponent in base 2 defining the extent of the range of the random number FCN.	4	—	16
BS	SF_release	Number of superframes after which the BS releases the frames won by another BS through frame contention.	—	5	—
CPE	T _{CBP} (T34)	The minimum time between transmissions of a CBP packet carrying its MAC address for identification by nearby CPEs and BSs for coexistence purpose, as well as by spectrum monitoring systems to identify potential interference situations. Timing value may depend on the regulatory domain where the WRAN system operates (see Annex A).	8 s	—	15 min
BS	SCWBackoff_Timer (T35)	Backoff timer that controls exiting or continuation of Frame contention procedure.	—	—	SCWBackoff_Max

12.1.4 Security

Change Table 275 as follows:

Table 275—Security parameters, timers, message IEs

Entity/ Scope	Name	Reference	Min value	Default value	Max value
CPE	EAP Authentication Timer (T36)	Timeout period between sending SCM EAP-Start or EAP-Transfer (8.2.2.5).	2 s	10 s	30 s
CPE	Authentication Grace Timer (T37)	Amount of time after authentication is complete that must pass before re-authentication is complete (8.2.2.5).	5 min (300 s)	10 min (600 s)	~~6 h (21,600 s)~~ ~~35 days (3,024,000 s)~~
CPE	Max #of Authentication Attempts	Maximum # of Times a CPE is allowed to attempt EAP Authentication (8.2.2.5).	1 s	5 s	10 s
CPE	Operational Wait Timeout (T38)	Timeout period between sending of Key Request messages from the Op Wait state (8.2.3.2.4).	1 s	1 s	10 s
CPE	Rekey Wait Timeout (T39)	Timeout period between sending of Key Request messages from the Rekey Wait state (8.2.3.2.4).	1 s	1 s	10 s
CPE	GTEK/TEK Grace Time (T40)	Time interval, in seconds before the estimated expiration of a GTEK/TEK (8.2.3.2.4).	5 min (300 s)	1 h (3600 s)	3.5 days (302,400 s)

Entity/ Scope	Name	Reference	Min value	Default value	Max value
BS	AK Lifetime	Lifetime BS assigns to new AK.	1 day (86,400 s)	7 days (604,800 s)	70 days (6,048,000 s)
BS	TEK Lifetime	Lifetime BS assigns to new TEK.	30 min (1800 s)	12 h (43,200 s)	7 days (604,800 s)
BS, CPE	SCM Flow Control	The maximum number of concurrent SCM transactions.	0 (Default: unlimited # of transactions)	—	255
BS, CPE	Number of Supported Security Associations	The maximum # of supported security associations.	2	—	2+m where m is the number of multicast groups
BS, CPE	PN_WINDOW_SIZE	Window that defines the acceptable PNs for received PDUs that are to be processed by encryption/decryption process.	16	—	512
BS	T17	Time allowed for CPE to complete CPE Authorization and Key Exchange.	5 min	5 min	—

12.1.5 Cognitive radio capabilities (SM, SSA, incumbent protection, QP management)

Change Table 276 as follows:

Table 276—Cognitive radio capability parameters, timers, message IEs

Entity/ Scope	Name	Reference	Min value	Default value	Max value
~~CPE~~	~~T19~~	~~Time DS channel remains unusable.~~	—	—	—
CPE	T29	Wait for BLM-ACK timeout.	10 ms	—	300 ms
BS	T31	Wait for BLM-REP timeout.	1 MAC Frame	—	—
CPE	BLM-REP Retries	Number of retries allowed for sending BLM-REP.	—	3	—
BS, CPE	Channel Availability Check Time	The time during which a channel SHALL be checked for the presence of licensed incumbent signals having a level above the Incumbent Detection Threshold prior to the commencement of WRAN operation in that channel and, in the case of TV, a related channel at an EIRP level that can affect the measured channel.	—	30 s	—
BS, CPE	Non-Occupancy Period	The required period during which WRAN device transmissions SHALL NOT occur in a given channel because of the detected presence of an incumbent signal in that channel above the Incumbent Detection Threshold, or in the case of TV, above a given EIRP level.	10 min	—	—

Entity/ Scope	Name	Reference	Min value	Default value	Max value
BS, CPE	Channel Detection Time	The maximum time taken by a WRAN device to detect a licensed incumbent signal above the Incumbent Detection Threshold within a given channel during normal WRAN operation.	—	≤ 2 s to $\geq 90\%$ Probability of Detection with a False Alarm rate of $\leq 10\%$	—
BS, CPE	Channel Setup Time	The window of time that may be taken by a WRAN CPE to transmit control information to a WRAN base station in order to establish operation with that base station at the prescribed power or, in the case of TV, at or below the allowable EIRP within a given channel.	—	2 s	—
BS, CPE	Channel Opening Transmission Time (Aggregate transmission time)	The aggregate duration of control transmissions by WRAN devices during the Channel Setup Time, which starts at the end of the Channel Availability Check Time.	—	100 ms	—
BS, CPE	Channel Move Time (In-service monitoring)	The time taken by a WRAN system to cease all interfering transmissions on the current channel upon detection of a licensed incumbent signal above the relevant Incumbent Detection Threshold, or in the case TV, to alternatively reduce its EIRP to that which is allowable within a given channel upon detection of a TV signal in the same or a related channel.	—	2 s	—
BS, CPE	Channel Closing Transmission Time (Aggregate transmission time)	The aggregate duration of control transmissions by the WRAN devices during the Channel Move/EIRP Reduction Time, which starts upon detection of a licensed incumbent signal above the relevant Incumbent Detection Threshold.	—	100 ms	—
BS, CPE	Channel Number	The channel number to be sensed by the SSF (10.4).	0	—	255
BS, CPE	Channel Bandwidth	The bandwidth of the channel to be sensed by the SSF (10.4).	—	6/7/8 MHz (depending on regulatory domain)	—
BS, CPE	Maximum Probability of false alarm	In sensing modes 0 and 1 this value specifies the maximum probability of false alarm for each sensing mode decision in the signal present array.	0.0	—	0.255
BS, CPE	NumSensingPeriods	Number of sensing periods field in a Sensing Window Specification Array entry.	0	1	127
BS, CPE	SensingPeriodDuration	Duration of sensing period field (in units of OFDM symbols) in a Sensing Window Specification Array entry.	0	16	1023
BS, CPE	SensingPeriodInterval	Periodicity of Sensing period field in a Sensing Window Specification Array entry.	0	200	2047

Entity/ Scope	Name	Reference	Min value	Default value	Max value
BS, CPE	Sensing Window Specification Array	Array containing Sensing Window specification for each signal type enumerated in Signal Type Array.	$1 \times \text{sizeof}(\text{NumSensingPeriods} + \text{SensingPeriodDuration} + \text{SensingPeriodInterval})$	—	$32 \times \text{sizeof}(\text{NumSensingPeriods} + \text{SensingPeriodDuration} + \text{SensingPeriodInterval})$
BS, CPE	Signal Type Array	Bitmap that indicates which signal types are to be sensed for in a given regulatory domain.	—	Set on a regulatory domain-by-domain basis (see Table A.11)	—
BS, CPE	Sensing Mode	The sensing mode a CPE supports. Negotiated during CPE initialization. Various modes are described in Table 238.	—	No Sensing	—
BS, CPE	Signal Present Decision	Indication of whether a signal of a specific type has been detected. All unused values are reserved.	0x00 (Absent)	0x7F (No Decision could be made)	0xFF (Signal Present)
BS, CPE	Confidence Metric	Confidence with which sensing can determine the signal type.	0x00 (No Confidence)	—	0xFF (Full confidence)
BS, CPE	Mean RSSI	Mean of M RSSI measurements.	−104 dBm	—	+23.5 dBm
BS, CPE	Standard Deviation of RSSI	Standard deviation of the M RSSI measurements.	+0.0 dB	—	+25.5 dB
BS, CPE	RSSI __ detection __ threshold	Energy detection threshold indicating the presence of an incumbent, other WRAN system, or interference.	−120 dBm	—	−10 dBm
BS, CPE	Microphone Protection Radius	Radius of the contour within which the WRAN system cannot operate due to potential interference with the microphone.	0.1 km	—	100 km
BS, CPE	T _{Candidate_Channel_Refresh} (T41)	Maximum time interval allowed before sensing is performed on the candidate channel to ensure that no incumbents are detected.	1 s	6 s	10 s
BS, CPE	T _{Backup_Channel_Refresh} (T42)	Maximum time interval allowed before sensing is performed on the backup channel to ensure that no incumbents are detected.	1 s	6 s	10 s
BS, CPE	T _{Candidate_to_Backup_Transition} (T43)	Minimum time duration without detection of any incumbent for a candidate channel to transition to the backup channel.	1 s	30 s	100 s
BS, CPE	T _{Ch_Move} (T44)	Maximum time to ensure that the channel move information is successfully conveyed to all the associated CPEs and BS (self-coexistence mode).	1 s	—	10 s
BS, CPE	T _{No_DB} (T45)	Maximum WRAN operation time without access to the incumbent database service.	0.1 h	—	72 h
BS	T _{Wait_Before_Channel_Move} (T46)	Waiting time before which the BS moves to the first backup channel. This is used to make sure that all the CPEs are ready to move to the backup channel before BS switches operation to this backup channel.	1 frame	—	256×16 frames

Entity/ Scope	Name	Reference	Min value	Default value	Max value
CPE	$T_{\text{Wait_Before_Channel_Move}}$ (T59)	Waiting time before which the CPE moves to its backup channels if it no longer hears from its BS. This is used to make sure that the CPE waits long enough after its UCS Notification so that the BS has had time to move to a backup channel, if it decided to do so.	1 frame	—	256×16 frames
BS, CPE	$T_{\text{Refresh_Database_Info}}$ (T47)	The prescribed time by the WRAN operator to refresh the incumbent database service.	0.1 h	—	72 h
BS, CPE	$T_{\text{Clear_N}}$ (T48)	Lapser Timer keeps track of whether the Operating Channel N has been cleared using spectrum sensing.	0.1 s	—	60 s
BS, CPE	$T_{\text{Clear_N-1}}$ (T49)	Lapser Timer keeps track of whether the Adjacent Channel N-1 has been cleared using spectrum sensing.	0.1 s	—	60 s
BS, CPE	$T_{\text{Clear_N+1}}$ (T50)	Lapser Timer keeps track of whether the Adjacent Channel N+1 has been cleared using spectrum sensing.	0.1 s	—	60 s
BS, CPE	$T_{\text{Loss_of_BS_Contact}}$ (T51)	Initiated when the CPE loses contact with the BS.	1 s	—	600 s
BS, CPE	T_{Range1} (T52)	Used for terrestrial geolocation. Initiated when the downstream burst leaves the BS (i.e., at the start of the frame preamble).	1 TU	—	1000 TU
BS, CPE	$T_{\text{INs}}_{\text{sens}}$ (T53)	The parameter $T_{\text{INs}}_{\text{sens}}$ is used to verify that in-band sensing has been done within the required In-service monitoring period. The $T_{\text{INs}}_{\text{sens}}$ parameter is driven by the regulatory domain requirements. See Annex A.	0.1 s	—	60 s
BS, CPE	$T_{\text{OUTs}}_{\text{sens}}$ (T54)	The parameter $T_{\text{OUTs}}_{\text{sens}}$ is used to verify that out-of-band sensing has been done within the required “Acquiring a channel monitoring period” specified in Annex A, Table A.13 (30 s in the US). This value would be used to either initialize a “lapse timer” for each channel in the backup/candidate list at each CPE so that it is compared to T_{sens} .	0.1 s	—	60 s
BS, CPE	T_{sensin} (T55)	T_{sensin} parameter corresponds to the maximum length of time required to carry out the sensing process on an in-band channel (N, N-1, or N+1). Manufacturers need to specify the sensing time required to detect the specified signals with required accuracy (see Figure 176).	1 ms	—	160 ms
CPE	T_{sensout} (T60)	T_{sensout} parameter corresponds to the maximum length of time required to carry out an out-of-band sensing process for a specified channel N (i.e., N, N-1, and N+1). Manufacturers need to specify the sensing time required to detect the specified signals out-of-band with required accuracy (see Figure 178).	20 ms	—	160 ms
BS, CPE	ISO 3166 IETF Country Code	3-character, ASCII string denoting the regulatory domain of operation (e.g., “USA” is for United States of America”).	—	3 characters	—

Entity/ Scope	Name	Reference	Min value	Default value	Max value
BS, CPE	TA _{CBP}	Timing Advance of the CBP burst (see step 2 of 10.5.2.3). Note that the geolocation process will have to pre-adjust TA _{CBP} depending on the distance between the two CPE to be geolocated and the reference CPEs so that the delays measured by Vernier ₃ fall within the symbol cyclic prefix (e.g., 74.68 μs corresponding to 22.4 km).	−1024 TU	—	+1024 TU

13 MIB structure

Change the third list item in the dashed list in the preliminary text of Clause 13 as follows:

- ~~wranIfBsSfMgmtMib~~: ~~wranIfBsSfMgmt~~ Basic MIB for managing items related to Service Flow configuration, instantiation, and management

13.1 MIB description

13.1.1 wranDevMib

Change the dashed list in 13.1.1 as follows:

- wranDevBsObjects: MIB objects to be implemented by the SNMP agent in BS
- wranDevCpeObjects: MIB objects to be implemented by the SNMP agent in CPE
- wranDevCommonObjects: MIB objects to be implemented by the SNMP agent in BS/CPE
- ~~wranDevMibConformance~~: ~~MIB objects related to conformance~~

13.1.1.1 wranDevBsObjects

13.1.1.1.1 wranDevBsSoftwareUpgradeTable

13.1.1.1.1.1 wranDevBsSoftwareUpgradeEntry

Change 13.1.1.1.1.9 as follows:

13.1.1.1.1.1.9 wranDevBsSoftwareUpgradeTimeStamp

This value is a timestamp to indicate when the last SW ~~download~~ or activation took place.

Change 13.1.1.1.2 and its subclauses as follows:

13.1.1.1.2 wranDevBsNotification

This group of objects relates to SNMP traps on the BS. There is a control element that enables/disables the traps (wranDevBsTrapControl) and ~~whether or not what event information is logged when a trap is sent (wranDevBsTrapDefinition) when an event is logged.~~

13.1.1.1.2.1 wranDevBsTrapControl

Defines control elements for traps. This is a 2-bit field that enables setting a trap to indicate when a BS event is logged (wranDevBsEvent) or when a event log buffer size overruns the configured threshold (wranDevBsLogBuffExceedThreshold).

~~13.1.1.1.2.2~~13.1.1.1.2.1 wranDevBsTrapDefinitionwranDevBsTrapPrefix

This object groups all of the notification objects for the BS. It is defined to be compatible with SNMPv1, following Sections 8.5 and 8.6 of IETF RFC 2758. It is a compound object made up of the contents of a logged BS event (wranDevBsEventTrap) and the indication of when the ratio of the portion used to total size of event log has been exceeded (wranDevBsLogBuffExceedThresholdTrap).

~~13.1.1.1.2.1.2~~ wranDevBsTrapControlRegister

~~This is ... wranDevBsLogBuffExceedThresholdTrapControl.~~

~~13.1.1.1.2.2~~ wranDevBsEventTrapControl

~~This trap ... wranDevCmnEventTable.~~

13.1.1.1.2.2.1 wranDevBsEventTrap

This object is a compound object that contains information that describes the event that is logged. This trap is caught when wranDevBsEvent in wranDevBsTrapControl is set.

~~13.1.1.1.2.2.2~~13.1.1.1.2.2.1 wranDevBsLogBuffExceedThresholdTrap

~~This trap is sent when the size of the event log buffer is greater than the configured threshold~~ object is a compound object that indicates the index of an entry (defined by wranDevCmnEventLogEntry) in wranDevCmnEventLogConfigTable and the object in that entry that defines the ratio (defined by wranDevCmnEventLogResidualBuffThreshold) of used capacity in Event Log versus total capacity. This trap is caught when wranDevBsLogBuffExceedThreshold in wranDevBsTrapControl is set.

13.1.1.2 wranDevCpeObjects

Change 13.1.1.2.2 and its subclauses as follows:

13.1.1.2.2 wranDevCpeNotification

This group of objects relates to SNMP traps on the BSCPE. There is a control element that enables/disables the traps (wranDevCpeTrapControl) and whether or not what event information is logged when a trap is sent (wranDevCpeTrapDefinition) when an event is logged.

13.1.1.2.2.1 wranDevCpeTrapControl

Defines control elements for traps. This is a 2-bit field that enables setting a trap to indicate when a CPE event is logged (wranDevCpeEvent) or when a event log buffer size overruns the configured threshold (wranDevCpeLogBuffExceedThreshold).

13.1.1.2.2.1.1 wranDevCpeTrapDefinitionwranDevCpeTrapPrefix

This object groups all of the notification objects for the BSCPE. It is defined to be compatible with SNMPv1, following Sections 8.5 and 8.6 of IETF RFC 2758. It is a compound object made up of the contents of a logged BS event (wranDevCpeEventTrap) and the indication of when the ratio of the portion used to total size of event log has been exceeded (wranDevCpeLogBuffExceedThresholdTrap).

13.1.1.2.2.1.2 wranDevCpeEventTrapwranDevCpeTrapControlRegister

This object is a compound object that contains information that describes the event that is logged. This trap is caught when wranDevCpeEvent in wranDevCpeTrapControl is set. ~~This is a 2-bit, bitmap that enables the two BS traps that are available: wranDevCpeEventTrapControl, wranDevBsLogBuffExceedThresholdTrapControl.~~

13.1.1.2.2.1.3 wranDevCpeLogBuffExceedThresholdTrap

This object is a compound object that indicates the index of an entry (defined by wranDevCmnEventLogEntry) in wranDevCmnEventLogConfigTable and the object in that entry that defines the ratio (defined by wranDevCmnEventLogResidualBuffThreshold) of used capacity in Event Log versus total capacity. This trap is caught when wranDevCpeLogBuffExceedThreshold in wranDevCpeTrapControl is set.

13.1.1.2.2.2 wranDevCpeEventTrapControl

~~This trap ... wranDevCmnEventTable.~~

13.1.1.2.2.2.1 wranDevBsLogBuffExceedThresholdTrap

~~This trap ... configured threshold.~~

13.1.1.3 wranDevCommonObjects

13.1.1.3.1 wranDevCmnEventLog

13.1.1.3.1.1 wranDevCmnEventLogConfigTable

Change the subclauses of 13.1.1.3.1.1 as follows:

13.1.1.3.1.1.1 wranDevCmnEventLogConfigEntry

This object ... wranDevCmnDeviceIndex.

~~13.1.1.3.1.1.1.1~~ 13.1.1.3.1.1.2 wranDevCmnDeviceIndex

Index value ... wranDevCmnEventLogConfigTable.

~~13.1.1.3.1.1.1.2~~ 13.1.1.3.1.1.3 wranDevCmnEventLogEntryLimit

Maximum number ... is reached.

~~13.1.1.3.1.1.1.3~~ 13.1.1.3.1.1.4 wranDevCmnEventLogLifeTimeLimit

A value of 0 means that an entry is kept indefinitely. Any other value, it is the maximum time an entry can exist in wranDevCmnEventLogTable. If this value is changed while entries exist in wranDevCmnEventLogTable, entries older than this limit will be discarded.

~~13.1.1.3.1.1.1.4~~ 13.1.1.3.1.1.5 wranDevCmnEventLogEntryLimitPerEventId

The number ... per event.

~~13.1.1.3.1.1.1.5~~ 13.1.1.3.1.1.6 wranDevCmnEventLogSeverityThreshold

Minimum severity ... Event Log.

~~13.1.1.3.1.1.1.6~~ 13.1.1.3.1.1.7 wranDevCmnEventLogWrapAroundBuffEnable

Indication of ... when full.

~~13.1.1.3.1.1.1.7~~ 13.1.1.3.1.1.8 wranDevCmnEventLogLatestEvent

Index of ... Event Log.

~~13.1.1.3.1.1.1.8~~ 13.1.1.3.1.1.9 wranDevCmnEventLogPersistenceSupported

Indication of ... of device.

~~13.1.1.3.1.1.1.9~~ 13.1.1.3.1.1.10 wranDevCmnEventLogResidualBuffThreshold

Threshold ratio ... is issued.

13.1.1.3.1.2 wranDevCmnEventTable

Change 13.1.1.3.1.2.1 as follows:

13.1.1.3.1.2.1 wranDevCmnEventEntry

This object defines the parameters of an event entry in the wranDevCmnEventTable. Each entry is indexed by ~~wranDevCmnDeviceIndex~~ and wranDevCmnEventIdentifier.

13.1.1.3.1.3 wranDevCmnEventLogTable

Change 13.1.1.3.1.3.1 and 13.1.1.3.1.3.1.1 as follows:

13.1.1.3.1.3.1 wranDevCmnEventLogEntry~~wranDevCmnEventEntry~~

Each entry ... several parameters.

13.1.1.3.1.3.1.1 wranDevCmnEventId

A counter used to index entries in the Event Log. When it reaches the maximum value, it will ~~with~~ wrap-around if configured to wrap-around or the log will be flushed if it is not configured to wrap-around.

Change 13.1.1.3.2 as follows:

13.1.1.3.2 wranDevCmnSnmpAgent

This compound object deals with the common objects (wranDevCmnSnmpAgent and wranDevCmnSnmpV1V2TrapDestTable) related to SNMP agent configuration.

Change 13.1.1.3.3 and its subclauses as follows:

13.1.1.3.3 wranDevCmnDeviceConfig

This compound attribute contains the following:

- wranDevCmnResetDevice: Object that is used to reset the device
- wranDevMibGroupswranDevMibConformance: MIB objects that are required for conformance
- wranDevMibCompliance: MIB objects that are required for conformance

13.1.1.3.3.1 wranDevCmnResetDevice

There are ... reset itself.

13.1.1.3.3.2 wranDevMibGroupswranDevMibConformance

This object ... each group.

13.1.1.3.3.2.1 wranDevMibBsGroup

This MIB group is mandatory. It is made up of wranDevBsTrapControl.
~~wranDevBsTrapControlRegister~~.

13.1.1.3.3.2.2 wranDevMibBsSwUpgradeGroup

This MIB group is ~~mandatory~~optional. It is a compound object made up of wranDevBsVendorId, wranDevBsHwId, wranDevBsCurrentSwVersion, wranDevBsDownloadSwVersion, wranDevBsUpgradeFileName, wranDevBsSoftwareUpgradeAdminState, wranDevBsDownloadSwProgress, wranDevBsSoftwareUpgradeTimeStamp. It contains the values of the most recent/current entry in wranDevBsSoftwareUpgradeTable.

13.1.1.3.3.2.3 wranDevMibCpeGroup

This MIB group is mandatory. It is a compound object made up of wranDevCpeMicConfigSetting, ~~wranDevCpeVendorId~~wranDevBsVendorId, wranDevCpeHwId, ~~wranDevCpeConfigFileVersion~~wranDevCpeSwVersion, wranDevCpeUpgradeFileName, wranDevCpeSwTftpServer, wranDevCpeTftpServerTimeStamp, ~~wranDevCpeTrapControl~~wranDevCpeTrapControlRegister. It contains the values of the most recent/current entry in wranDevCpeConfigFileEncodingTable for a particular CPE.

13.1.1.3.3.2.4 wranDevMibCmnGroup

This MIB ... wranDevCmnEventLogTable.

13.1.1.3.3.2.5 wranDevMibBsNotificationGroup

This MIB ... wranDevBsLogBuffExceedThresholdTrap.

13.1.1.3.3.2.6 wranDevMibCpeNotificationGroup

This MIB ... wranDevCpeLogBuffExceedThresholdTrap.

13.1.1.3.3.2.7 wranDevCpeTrapControlGroup

Contains objects related to enabling/disabling CPE device traps.

13.1.1.3.3.2.8 wranDevBsTrapControlGroup

Contains objects related to enabling/disabling BS device traps.

13.1.1.3.3.3 wranDevMibCompliance

This object indicates which MIB groups in wranDevMibGroups are optional and which ones are mandatory.

13.1.2 wranIfBsMib

Change 13.1.2.1 and 13.1.2.1.1 as follows:

13.1.2.1 wranIfBsFm

Exceptions and fault events can be reported by using the traps defined in this MIB. wranIfBsFm is made up of the following MIBs: wranIfBsTrapControl, wranIfBsTrapControlRegister, wranIfBsTrapDefinition, wranIfBsNotifactionObjectsTable, wranIfBsCpeNotifactionObjectsTable, wranIfBsFmMibGroups, and wranIfBsFmMibCompliance, wranIfBsThresholdConfigTable.

13.1.2.1.1 wranIfBsTrapControlwranIfBsTrapControlRegister

This MIB is a bitmap that is used to disable/enable the following BS traps:

wranIfBsCpeDynamicServiceNotification,
wranIfBsCpeDynamicServiceFailNotification,
wranIfBsCpeRssiStatusChangeNotification,
wranIfBsSignalPowerMetricsStatusNotification,
wranIfBsCpeEIRPStatusChangeNotification,
wranIfBsCpeRegisterNotification,
wranIfBsCpeScmNotification, wranIfBsCpeScmFailNotification,
wranIfBsCpeStartupStatusChangeNotification,
wranIfBsThroughputMetricsNotification,
wranIfBsNetworkEntryMetricsNotification,
wranIfBsPacketErrorRateChangeNotification,
wranIfBsUserMetricsChangeNotification,
wranIfBsCoexistenceStatusNotification,
wranIfBsCpeChpReceptionNotification,
wranIfBsCpeWiMicBeaconMSF1Notification,
wranIfBsCpeWiMicBeaconMSF12Notification,
wranIfBsCpeWiMicBeaconMSF123Notification,
wranIfBsInterFrameSensingStatusNotification,
wranIfBsMeasurementStatusNotification,
wranIfBsBasicCapabilityNotification, wranIfBsRangingNotification, and
wranIfBsAuthMetricsNotification. Enable of a trap indicates that the trap will be recorded in
wranIfBsCpeNotificationObjectsTable.

Insert the following new subclauses (13.1.2.1.2 to 13.1.2.1.14) after 13.1.2.1.1:

NOTE—For instructions for the former 13.1.2.1.2, see the new 13.1.2.1.3.

13.1.2.1.2 wranIfBsTrapDefinition

This object defines BS related traps for configuration, accounting, performance, and SCM management aspects in wranIfBsMib.

13.1.2.1.2.1 wranIfBsDynamicServiceTrap

This trap contains information related to updating the configuration of either provisioned service flows (`wranIfBsProvSfTable`) or active service flows (`wranIfBsActiveSfTable`).

13.1.2.1.2.2 wranIfBsSignalPowerMetricsTrap

This trap contains information related to updating of signal power metrics (`wranIfBsSignalPowerMetricsTable`).

13.1.2.1.2.3 wranIfBsRegNotificationTrap

This trap contains the information related to indicating successful registration of a CPE (`wranIfBsCpeRegCapabilityRspTable`).

13.1.2.1.2.4 wranIfBsScmNotificationTrap

This trap contains the information related to updating the configuration of the SCM protocol capabilities on a CPE (`wranIfBsCpeScmCapabilityConfigTable`) or current authentication status (`wranIfBsCpeScmAuthConfigTable`).

13.1.2.1.2.5 wranIfBsStartupStatusTrap

This trap contains the information related to changes in a CPE's status with regard to network entry (`wranIfBsStartupMetricsTable`).

13.1.2.1.2.6 wranIfBsTxMetricsTrap

This trap contains the information related to changes in throughput metrics (`wranIfBsThroughputMetricsTable`) or ARQ metrics (`wranIfBsArqMetricsTable`).

13.1.2.1.2.7 wranIfBsNetEntryMetricsTrap

This trap contains the information related to updates in network entry and re-entry latency measurements (`wranIfBsNetworkEntryMetricsTable`).

13.1.2.1.2.8 wranIfBsPktErrorTrap

This trap contains the information related to updates in packet error rate measurements (`wranIfBsPacketErrorRateTable`).

13.1.2.1.2.9 wranIfBsUserMetricsTrap

This trap contains the information related to updates in tracking the number of active and non-active users (`wranIfBsUserMetricsTable`).

13.1.2.1.2.10 wranIfBsCoexistenceTrap

This trap contains the information related to updates in tracking ongoing coexistence transaction (e.g., On-Demand Frame Contention in `wranIfBsCoexistenceStatusTable`), discovery of new potential coexistence sources (`wranIfBsCoexistenceSourceTable`), discovery of resource usage in neighboring networks (`wranIfBsCoexistenceResourceListTable`), and updates to a BS's own coexistence configuration (`wranIfBsCoexistenceCurrentConfigTable`).

13.1.2.1.2.11 wranIfBsBasicCapabilityTrap

This trap contains the information related to updates in tracking updates to the basic capability configuration of CPEs (wranIfBsCpeBasicCapabilityRspTable).

13.1.2.1.2.12 wranIfBsRangingTrap

This trap contains the information related to updates in tracking status of ranging of (wranIfBsCpeRngCapabilityCmdTable).

13.1.2.1.2.13 wranIfBsAuthMetricsTrap

This trap contains the information related to updates in tracking updates to authentication metrics (wranIfBsAuthenticationMetricsTable).

13.1.2.1.2.14 wranIfBsDynamicServiceMetricsTrap

This trap contains the information related to updates in tracking metrics for current provisioned and active service flows (wranIfBsAuthenticationMetricsTable).

To create a new 13.1.2.1.3 with subclauses, change the former 13.1.2.1.2 and its subclauses as follows:

NOTE—For instructions for the former 13.1.2.1.3, see the deletions after the new 13.1.2.1.3.1.20.

13.1.2.1.313.1.2.1.2 wranIfBsNotificationObjectsTablewranIfBsCpeNotificationObjectsTable

This table contains objects that represents notifications reported in BS fault traps. The table is made up of one or more entries.

13.1.2.1.3.143.1.2.1.2.4 wranIfBsNotificationObjectsEntry wranIfBsCpeNotificationObjectsEntry

This MIB is a compound object that represents an entry in the MIB object wranIfBsNotificationsObjectsTablewranIfBsCpeNotificationsObjectsTable.

13.1.2.1.3.1.1 wranIfBsNotificationObjectsIndex

Index of entry in the table.

13.1.2.1.3.1.213.1.2.1.2.1.1 wranIfBsNotificationMacAddrwranIfBsCpeNotificationMacAddr

The MAC ... the notification.

13.1.2.1.3.1.3 wranIfBsDynamicServiceType

Indication if the configuration for a provisioned or active service flow has been configured.

13.1.2.1.3.1.4 wranIfBsDynamicServiceNotificationIndex

Index into wranIfBsProvSfTable or wranIfBsActiveSfTable that indicates which service flow configuration was added/updated.

13.1.2.1.3.1.5 wranIfBsSignaPowerNotificationIndex

Index into wranIfBsSignalPowerMetricsTable that indicates the entry that contains updated signal power metrics data.

13.1.2.1.3.1.6 wranIfBsBsRegCapabilityNotificationIndex

Index into wranIfBsCpeRegCapabilityRspTable that indicates the entry that contains updated registration for a CPE.

13.1.2.1.3.1.7 wranIfBsScmNotificationType

Indication if the configuration of the SCM protocol or the authentication status of a CPE has been updated.

13.1.2.1.3.1.8 wranIfBsScmNotificationIndex

Index into wranIfBsCpeScmCapabilityConfigTable that indicates which CPE has updated their SCM configuration, or wranIfBsCpeScmAuthConfigTable that indicates which CPE has had their authentication status updated.

13.1.2.1.3.1.9 wranIfBsStartupNotificationIndex

This contains the index of entry in wranIfBsStartupMetricsTable that contains data on any changes in a CPE's status with regard to network entry.

13.1.2.1.3.1.10 wranIfBsTxMetricsType

Indication if throughput metrics contained or ARQ Metrics in have been updated.

13.1.2.1.3.1.11 wranIfBsTxMetricsNotificationIndex

Index into wranIfBsThroughputMetricsTable that indicates changes in measure throughput metrics, or wranIfBsArqMetricsTable that indicates changes in ARQ performance.

13.1.2.1.3.1.12 wranIfBsNetEntryMetricsNotificationIndex

This contains the index of entry in wranIfBsNetworkEntryMetricsTable that contains data on any changes in network entry and re-entry latency measurements.

13.1.2.1.3.1.13 wranIfBsPktErrorMetricsNotificationIndex

This contains the index of entry in wranIfBsPacketErrorRateTable that contains data on any changes in packet error rate measurements.

13.1.2.1.3.1.14 wranIfBsUserMetricsNotificationIndex

This contains the index of entry in wranIfBsUserMetricsTable that contains data on any changes in the number of active and non-active users in the cell.

13.1.2.1.3.1.15 wranIfBsCoexMetricsType

Indication if ongoing On-Demand Frame Coexistence Transactions, discovery of new potential coexistence resources, discovery of the resource usage in neighboring networks, and whether a BS's own coexistence configuration have been updated.

13.1.2.1.3.1.16 wranIfBsCoexNotificationIndex

Index into wranIfBsCoexistenaceStatusTable that indicates changes in ongoing On-Demand Frame Contention transactions, wranIfBsCoexistenceSourceTable that indicates changes in the discovery of new potential coexistence sources, wranIfBsCoexistenceResourceListTable that indicates discovery of resource usage in neighboring networks, or wranIfBsCoexistenceCurrentConfigTable that indicates whether a BS's own coexistence configuration have been updated.

13.1.2.1.3.1.17 wranIfBsBasicNotificationIndex

This contains the index of entry in wranIfBsCpeBasicCapabilityRspTable that contains data on any changes in tracking updates to the basic capability configuration of CPEs.

13.1.2.1.3.1.18 wranIfBsRngNotificationIndex

This contains the index of entry in wranIfBsCpeRngCapabilityCmdTable that contains data on any changes in tracking updates to the status of ranging of CPEs.

13.1.2.1.3.1.19 wranIfBsAuthNotificationIndex

This contains the index of entry in wranIfBsAuthenticationMetricsTable that contains data on any changes in tracking updates to authentication metrics.

13.1.2.1.3.1.20 wranIfBsDynSrvMetricsNotificationIndex

This contains the index of entry in wranIfBsServiceFlowMetricsTable that contains information related to tracking metrics of ongoing.

13.1.2.1.2.1.2 wranIfBsCpeStartupStatusChange

~~This object ... initialization procedures.~~

~~...~~

13.1.2.1.2.1.17 wranIfBsIntraFrameSensingStatus

~~Indication when ... been changed.~~

13.1.2.1.3 wranIfBsThresholdConfigTable

~~This MIB ... **13.1.2.1.3.1.4** ... EIRP alarm.~~

Insert the following new subclauses (13.1.2.1.4 with its subclauses and 13.1.2.1.5) after 13.1.2.1.3.1.20:

13.1.2.1.4 wranIfBsFmMibGroups

This object helps define which MIB groups are available in this module (`wranIfBsFm`) and which MIB objects are part of each group.

13.1.2.1.4.1 wranIfBsFmTrapControlGroup

This group contains objects related to enabling/disabling traps use for management of the BS.

13.1.2.1.4.2 wranIfBsFmNotificationGroup

This group contains objects related to traps used for management of the BS.

13.1.2.1.5 wranIfBsFmMibCompliance

MIB objects that are optional or mandatory for `wranIfBsFm` compliance.

Change 13.1.2.2 as follows:

13.1.2.2 wranIfBsCm

This MIB contains various objects related to Configuration Management. Within this MIB, the following tables are handled: `wranIfBsCpeRngCapabilityReqTable`, `wranIfBsCpeRngCapabilityCmdTable`, `wranIfBsCpeBasicCapabilityReqTable`, `wranIfBsCpeBasicCapabilityRspTable`, `wranIfBsCpeRegCapabilityReqTable`, `wranIfBsCpeMeasSupportReqTable`, `wranIfBsCpeRegCapabilityRspTable`, `wranIfBsCpeMeasSupportRspTable`, `wranIfBsCpeAntennaGainTable`, `wranIfBsScmCapabilityConfiguration`, `wranIfBsCpeScmCapabilityConfigTable`, `wranIfBsScmAuthConfigTable`, `wranIfBsActionsTable`, `wranIfBsCpeMulticastConfigTable`, `wranIfBsCoexistenceConfigTable`, `wranIfBsCpeBasicCapabilityCmn`, `wranIfBsCpeRegCapabilityCmn`, `wranIfBsCpeMeasSupportCmn`, `wranIfBsCpeSystemParametersTable`, `wranIfBsCpeRegCapabilityCmn`, `wranIfBsCmMibGroups`, and `wranIfBsCmMibCompliance`. For CBC-REQ/RSP and REG-REQ/RSP there are two MIB object groups that represent entries that are common to Basic and Registered Capability negotiation.

13.1.2.2.1 wranIfBsCpeRngCapabilityReqTable

13.1.2.2.1.1 wranIfBsCpeRngCapabilityReqEntry

Change the subclauses of 13.1.2.2.1.1 as follows:

13.1.2.2.1.1.1 wranIfBsCpeRngCapabilityReqIndex

Index of entry in the table.

13.1.2.2.1.1~~243.1.2.2.1.1.1~~ wranIfBsCpeMacAddress

The MAC ... the BS.

13.1.2.2.1.1~~343.1.2.2.1.1.2~~ wranIfMmpPn

Current value ... is used.

13.1.2.2.1.1~~443.1.2.2.1.1.3~~ wranIfCiphertextIcv

Calculated value ... (see 8.2.4.6.1.2).

13.1.2.2.1.1~~543.1.2.2.1.1.4~~ wranIfRngAnomaly

Indication of ... ranging process.

Change 13.1.2.2.2 and its subclauses as follows:

13.1.2.2.2 wranIfBsCpeRngCapabilityCmdTable

This object provides a table containing the ranging configuration the BS is specifying for CPE in the RNG-CMD during network entry. Each table is made up of multiple entries, one for each CPE that a RNG-CMD is sent to, that is defined by wranIfBsCpeRngCapabilityCmdEntry wranIfBsCpeRngCapabilityRspEntry.

13.1.2.2.2.1 wranIfBsCpeRngCapabilityCmdEntry

This object ... network entry.

13.1.2.2.2.1.1 wranIfBsCpeRngCapabilityCmdIndex

Index of entry in the table.

13.1.2.2.2.1~~243.1.2.2.2.1.1~~ wranIfBsCpeMacAddress

MAC Address ... initial ranging.

13.1.2.2.2.1~~343.1.2.2.2.1.2~~ wranIfBSCpeStationId

Station ID ... initial ranging.

13.1.2.2.2.1~~443.1.2.2.2.1.3~~ wranIfTimingAdvance

Timing advance ... Table 44.

13.1.2.2.2.1~~543.1.2.2.2.1.4~~ wranIfEirpPerSubcarrier

EIRP per ... Table 44.

13.1.2.2.2.1~~643.1.2.2.2.1.5~~ wranIfOffsetFreqAdjust

Offset frequency ... Table 44.

13.1.2.2.2.1.713.1.2.2.2.1.6 wranIfRangingStatus

Ranging status ... Table 44.

13.1.2.2.2.1.813.1.2.2.2.1.7 wranIfActionSuperFrameNum

The Action ... Table 44.

13.1.2.2.2.1.913.1.2.2.2.1.8 wranIfCdmaCode

The CDMA ... Table 44.

13.1.2.2.2.1.1013.1.2.2.2.1.9 wranIfTxOpportunityOffset

The Transmission ... Table 44.

13.1.2.2.3 wranIfBsCpeBasicCapabilityReqTable

Change 13.1.2.2.3.1 and its subclauses as follows:

13.1.2.2.3.1 wranIfBsCpeBasicCapabilityReqEntry

This object is a compound object that contains ~~the requested configuration of basic information on capabilities by that a CPE has declared to a BS during network entry.~~ The list of objects used to make up wranIfBsCpeBasicCapabilityReqEntry can be found in wranIfBsCpeBasicCapabilityCmn (13.1.2.2.16).

13.1.2.2.3.1.1 wranIfBsCpeBasicCapabilityReqEntryIndex

~~A unique ... this table.~~

13.1.2.2.3.1.11 wranIfCpeScmFlowControl

~~Maximum number ... in 7.7.11.3.3.3.~~

13.1.2.2.4 wranIfBsCpeBasicCapabilityRspTable

Change 13.1.2.2.4.1 as follows:

13.1.2.2.4.1 wranIfBsCpeBasicCapabilityRspEntry

This object is a compound object that contains the configuration of basic capabilities BS has selected for a CPE during network entry. This table reflects the current configuration of a CPE's basic capabilities. The list of objects used to make up wranIfBsCpeBasicCapabilityRspEntry can be found in wranIfBsCpeBasicCapabilityCmn (13.1.2.2.16).

NOTE—The relevant objects that make up this entry are described in 13.1.2.2.3.1.1 to 13.1.2.2.3.1.11. All items defined for the entry will need to move to the beginning of the ASN.1 formatting of `wranIfBsMib`.

13.1.2.2.5 `wranIfBsCpeRegCapabilityReqTable`

Change 13.1.2.2.5.1 and its subclauses as follows:

13.1.2.2.5.1 `wranIfBsCpeRegCapabilityReqEntry`

This object is a compound object that contains the information on the capabilities information for which that a CPE has requested confirmation from declared to the BS, e.g., through sending a REG-REQ to the BS. The objects that make up the entry are defined in `wranIfBsCpeRegCapabilityCmn` (13.1.2.2.17). A REG-REQ message comprises objects within this compound object, `wranIfBsCpeAntennaGainTable` (13.1.2.2.9), and `wranIfBsCpeMeasSupportReqTable` (13.1.2.2.6).

13.1.2.2.5.1.1 `wranIfBsRegisteredCpeMacAddress`

MAC address ... configured capabilities.

...

13.1.2.2.5.1.24 `wranIfCpeRegistrationTimer`

CPE Registration ... in 7.7.7.3.5.

Change 13.1.2.2.6 and its subclauses as follows:

13.1.2.2.6 `wranIfBsCpeMeasSupportReqTable`~~`wranIfBsCpeMeasurementSupportReqTable`~~

A compound object representing the Measurement Support IE of REG-REQ/RSP in 7.7.7.3.4.7. It is made up of multiple entries, one for each signal type ~~for which sensing is supported by sensing~~. Each entry is defined by `wranIfBsCpeMeasSupportReqEntry` ~~`wranIfBsCpeMeasurementSupportReqEntry`~~. Entries for a CPE are ~~only~~ present only if the value for `wranIfSensModeSupportArray` is anything other than “No Sensing.”

13.1.2.2.6.1 `wranIfBsCpeMeasSupportReqEntry` ~~`wranIfBsCpeMeasurementSupportReqEntry`~~

A compound object representing entries of Measurement Support IE of REG-REQ in 7.7.7.3.4.7. It is made up of multiple objects. A CPE will have one entry for each Signal Type in the Signal Type Array of the Measurement Support IE. The rest of the objects that represent each entry are defined in `wranIfBsCpeMeasSupportCmn` (13.1.2.2.18).

13.1.2.2.6.1.1 `wranIfMeasurementSupportEntryIndex`

A unique ... `wranIfBsCpeMeasurementSupportReqTable`.

...

13.1.2.2.6.1.9 ~~wranIfMeasurementRecSensPeriodInterval~~

Recommended length ... of frames.

13.1.2.2.7 ~~wranIfBsCpeRegCapabilityRspTable~~

Change 13.1.2.2.7.1 as follows:

13.1.2.2.7.1 ~~wranIfBsCpeRegCapabilityRspEntry~~

This object is a compound object that contains the capabilities information that a BS has configured for a the CPE, e.g., through sending a REG-RSP to the CPE. ~~wranIfRegCapabilityPermanentStationId is unique to REG-RSP. The objects that make up the entry are defined in wranIfBsCpeRegCapabilityCmn (13.1.2.2.17). A REG-RSP message comprises objects within this compound object and wranIfBsCpeMeasSupportRspTable (13.1.2.2.8).~~

NOTE 1—As with CBC-RSP, the entries will contain the objects that have scope in both REG-REQ and REG-RSP object types as the REG-REQ objects, e.g., this entry will be made up of objects in 13.1.2.2.5.1.1 13.1.2.2.15.1.24.

NOTE 2—In addition to having the objects in 13.1.2.2.5.1.1 through 13.1.2.2.5.1.24, this compound object will have an object containing the permanent station Id when CPE privacy (see 8.7) is being used.

Change 13.1.2.2.8 and 13.1.2.2.8.1 as follows:

13.1.2.2.8 ~~wranIfBsCpeMeasSupportRspTable~~ ~~wranIfBsCpeMeasurementSupportRspTable~~

A compound object representing the Measurement Support IE of REG-REQ/RSP in 7.7.7.3.4.7. It is made up of multiple entries, one for each signal type that sensing supports. Each entry is defined by ~~wranIfBsCpeMeasSupportRspEntry~~ ~~wranIfBsCpeMeasurementSupportRspEntry~~.

13.1.2.2.8.1 ~~wranIfBsCpeMeasSupportRspEntry~~ ~~wranIfBsCpeMeasurementSupportRspEntry~~

A compound object representing entries of Measurement Support IE of REG-RSP in 7.7.7.3.4.7. It is made up of multiple objects. A CPE will have one entry for each Signal Type in the Signal Type Array of the Measurement Support IE. Entries for a CPE are ~~only~~ present only if the value for ~~wranIfSensModeSupportArray~~ is anything other than “No Sensing.” ~~The rest of the objects that represent each entry are defined in wranIfBsCpeMeasSupportCmn (13.1.2.2.18).~~

NOTE—This will contain the same objects types, e.g., this entry will be made of the objects in 13.1.2.2.6.1.1 through 13.1.2.2.6.1.9.

Change 13.1.2.2.10 and its subclauses as follows:

13.1.2.2.10 wranIfBsScmCapabilityConfigurationwranIfBsCapabilitiesConfigTable

~~This MIB provides a bitmap that describes the cryptographic suites that the BS supports. The list of suites is provided in Table 193. This table is analogous to the wranIfBsCpeBasicCapabilityRspTable and wranIfBsCpeRegCapabilityRspTable, except there is ... contains all the entries specified in wranIfBsCpeBasicCapabilityRspEntry and wranIfBsCpeRegCapabilityRspEntry.~~

13.1.2.2.10.1 wranIfBsCapabilitiesConfigEntry

~~This object ... (wranIfBsMaxNumRegReqAttempts)].~~

13.1.2.2.10.1.1 wranIfBsMaxNumRegReqAttempts

~~This object ... is 5.~~

~~...~~

13.1.2.2.10.1.37 wranIfBsT17

~~Time allowed ... key exchange.~~

Change 13.1.2.2.11 and its subclauses as follows:

13.1.2.2.11 wranIfBsCpeScmCapabilityConfigTablewranIfBsMeasurementSupportTable

~~This MIB provides a table that provides contains a listing for the security capabilities for each CPE. Each CPE stores this table, with one entry for itself. On the BS, this table is made up of multiple entries, one for each CPE. Entries on the BS table do not contain the wranIfBsCpeEapTlsTtlsCredential object. Each entry is defined by wranIfBsCpeScmCapabilityConfigEntry. The list of capabilities is listed in Table 193. A compound object representing default values that a BS uses ... is defined by wranIfMeasurementSupportEntry.~~

13.1.2.2.11.1 wranIfBsCpeScmCapabilityConfigEntrywranIfBsMeasurementSupportEntry

~~This object is a compound object that provides the definition of the entries wranIfBsCpeScmCapabilityConfigTable. A compound object representing entries of wranIfBsMeasurementSupportTable ... Signal Type Array of the Measurement Support IE.~~

~~NOTE—This object is made up ... recommendations in Annex A.~~

13.1.2.2.11.1.1 wranIfBsCpeScmCapabilityConfigIndex

~~Index of entry in the table.~~

13.1.2.2.11.1.2 wranIfBsCpeScmCapabilityConfigMacAddress

~~The MAC address of the CPE.~~

13.1.2.2.11.1.3 wranIfBsCpeScmCapabilityConfiguration

This MIB provides a bitmap that describes the cryptographic suites that the CPE supports. The list of suites is provided in Table 193.

13.1.2.2.11.1.4 wranIfBsCpeEapTlsTtlsCredentialSize

Size, in number of octets, of X.509 certificate that defines the credential the CPE exchanges with the AAA server to perform authentication.

13.1.2.2.11.1.5 wranIfBsCpeEapTlsTtlsCredential

X.509 certificate that defines the credential the CPE exchanges with the AAA server to perform authentication.

Insert the following new subclauses (13.1.2.2.12 to 13.1.2.2.12.1.11) after 13.1.2.2.11.1.5:

NOTE—For instructions for the former 13.1.2.2.12, see the new 13.1.2.2.13.

13.1.2.2.12 wranIfBsCpeScmAuthConfigTable

This MIB provides a table that provides the configuration of the SCM attributes (e.g., timers and other items relating to the authorization process). This table is made up of one entry, defined by wranIfBsScmAuthConfigEntry.

13.1.2.2.12.1 wranIfBsCpeScmAuthConfigEntry

This object is a compound object that defines an entry in wranIfBsScmAuthConfigTable.

13.1.2.2.12.1.1 wranIfBsScmAuthConfigIndex

Index of entry in the table.

13.1.2.2.12.1.2 wranIfBsT36

EAP Authentication Timer, T36.

13.1.2.2.12.1.3 wranIfBsT37

Authentication Grace Timer, T37.

13.1.2.2.12.1.4 wranIfBsMaxNumAuthAttempts

Maximum number of Authentication Attempts.

13.1.2.2.12.1.5 wranIfBsT38

Operational Wait Timeout, T38.

13.1.2.2.12.1.6 wranIfBsT39

Rekey Wait Timeout, T39.

13.1.2.2.12.1.7 wranIfBsT40

GTEK/TEK Grace time, T40.

13.1.2.2.12.1.8 wranIfBsAkLifetime

Lifetime BS assigns to new AK.

13.1.2.2.12.1.9 wranIfBsTekLifetime

Lifetime BS assigns to new TEK.

13.1.2.2.12.1.10 wranIfBsMaxNumSa

Maximum number of SAs for which a CPE can be authorized.

13.1.2.2.12.1.11 wranIfBsT17

Time for CPE to complete authentication and key exchange.

To create a new 13.1.2.2.13 with subclauses, change the former 13.1.2.2.12 and its subclauses as follows:

NOTE—For instructions for the former 13.1.2.2.13, see the new 13.1.2.2.14.

13.1.2.2.13~~13.1.2.2.12~~ wranIfBsActionsTable

This object ... wranIfBsActionsEntry.

13.1.2.2.13.1~~13.1.2.2.12.1~~ wranIfBsActionsEntry

This object ... given time.

13.1.2.2.13.1.1 wranIfBsActionsIndex

Index of entry in this table.

13.1.2.2.13.1.1~~13.1.2.2.12.1.1~~ wranIfBsCpeActionsMacAddress

This uniquely ... MAC address.

13.1.2.2.13.1.1~~13.1.2.2.12.1.2~~ wranIfBsCpeActionsRngCpe~~wranIfBsCpeActionsRangeCpe~~

When set, ... is read.

13.1.2.2.13.1.1~~13.1.2.2.12.1.3~~ wranIfBsCpeActionsDeRegCpe

When set ... is specified.

13.1.2.2.13.1.5~~13.1.2.2.12.1.4~~ wranIfBsCpeActionsSchedule~~wranIfBsCpeActionsStatus~~

This object ... executed properly.

To create a new 13.1.2.2.14 with subclauses, change the former 13.1.2.2.13 and its subclauses as follows:

NOTE—For instructions for the former 13.1.2.2.14, see the new 13.1.2.2.15.

13.1.2.2.1413.1.2.2.13 wrranIfBsCpeMcastConfigTablewrranIfBsCpeMulticastConfigTable

This table ... multicast group.

13.1.2.2.14.113.1.2.2.13.1 wrranIfBsCpeMcastConfigEntrywrranIfBsCpeMulticastEntry

This object ... membership configuration.

13.1.2.2.14.1.1 wrranIfBsCpeMcastConfigIndex

Index of entry in this table.

13.1.2.2.14.1.113.1.2.2.13.1.1 wrranIfBsCpeMcastMacAddresswrranIfBsCpeMacAddress

This object ... wrranIfBsCpeMulticastCid.

13.1.2.2.14.1.113.1.2.2.13.1.2 wrranIfBsCpeMcastSidwrranIfBsMulticastSid

This object ... multicast group.

13.1.2.2.14.1.113.1.2.2.13.1.3 wrranIfBsCpeMcastPeriodicAllocParameterMwrranIfBsMulticastPeriodicAllocationParameterM

This object ... multicast transmission.

13.1.2.2.14.1.113.1.2.2.13.1.4 wrranIfBsCpeMcastPeriodicAllocParameterKwrranIfBsMulticastPeriodicAllocationParameterK

This object ... multicast transmission.

13.1.2.2.14.1.113.1.2.2.13.1.5 wrranIfBsCpeMcastPeriodicAllocParameterNwrranIfBsMulticastPeriodicAllocationParameterN

This object ... multicast transmission.

To create a new 13.1.2.2.15 with subclauses, change the former 13.1.2.2.14 and its subclauses as follows:

NOTE—For instructions for the former 13.1.2.2.15, see the new 13.1.2.2.23.

13.1.2.2.1513.1.2.2.14 wrranIfBsCoexistenceConfigTable

This table ... CBP transmission.

13.1.2.2.15.113.1.2.2.14.1 wrranIfBsCoexistenceConfigEntry

This object ... wrranIfBsCoexistenceConfigTable.

13.1.2.2.15.1.1 wranIfBsCoexistenceConfigIndex

Index of entry in this table.

13.1.2.2.15.1.2 wranIfBsT34

This governs ... is 300 s.

13.1.2.2.15.1.3 wranIfBsT33

Time between ... spectrum etiquette.

13.1.2.2.15.1.4 wranIfBsT32

Wait for ... (FC-RSP) message.

13.1.2.2.15.1.5 wranIfBsFcw

Frame contention ... to them.

13.1.2.2.15.1.6 wranIfBsScwBackoffMax

Maximum number ... backoff window.

13.1.2.2.15.1.7 wranIfBsFcMin

Number of ... the BS.

13.1.2.2.15.1.8 wranIfBsFcnRange

Exponent, base 2, ... the FCN.

13.1.2.2.15.1.9 wranIfBsSfRel

Number of ... frame contention.

13.1.2.2.15.1.10 wranIfBsT35

SCW Backoff ... Contention Procedure.

Insert the following new subclauses (13.1.2.2.16 to 13.1.2.2.22.1) after 13.1.2.2.15.1.10:

13.1.2.2.16 wranIfBsCpeBasicCapabilityCmn

This MIB object is a group containing objects that are common to wranIfBsCpeBasicCapabilityReqEntry and wranIfBsCpeBasicCapabilityRspEntry.

13.1.2.2.16.1 wranIfBasicCapabilityIndex

Index of entry in wranIfBsCpeBasicCapabilityReqTable or wranIfBsCpeBasicCapabilityRspTable.

13.1.2.2.16.2 wranIfBasicCapabilityNumAttempts

The current number of attempts that a CPE has attempted basic capability configuration during network entry. This item is set to 0 upon successful completion of registration process and a CPE is admitted into the network. This item is incremented every time a CPE attempts basic capability configuration, but is unsuccessful. If this value reaches the limit set by `wranIfBsMaxNumCbcReqAttempts`, then the BS shall reject the network entry request from the CPE. This object is only pertinent for entries in `wranIfBsCpeBasicCapabilityRspTable` (as the decision to reject basic capability negotiation is made by BS).

13.1.2.2.16.3 wranIfBasicCapabilityMacAddress

The MAC address of the CPE attempting basic capability configuration.

13.1.2.2.16.4 wranIfBasicCapabilityStationId

The Station ID of the CPE attempting basic capability configuration.

13.1.2.2.16.5 wranIfBasicCapabilityMacPduTxandConstruction

An integer value that indicates the methods for transmission and construction of MAC PDUs that the CPE supports. This reflects the setting of the IE defined in 7.7.11.3.1.

13.1.2.2.16.6 wranIfBasicCapabilityMaxCpeTxEirp

An integer value, encoded in hexadecimal, that indicates the maximum EIRP for which the CPE is configured. This reflects the setting of the IE defined in 7.7.11.3.2.1.

13.1.2.2.16.7 wranIfBasicCapabilityCpeDemodulator

A bit map that encodes the DIUCs that the CPE supports. This reflects the setting of the IE defined in 7.7.11.3.2.1.

13.1.2.2.16.8 wranIfBasicCapabilityCpeModulator

A bit map that encodes the UIUCs that the CPE supports. This reflects the setting of the IE defined in 7.7.11.3.2.2.

13.1.2.2.16.9 wranIfBasicCapabilityCpeScmVersionSupport

Indicator of what version of the SCM protocol that the CPE supports. This reflects the setting of the IE defined in 6.9.11.3.3.1.

13.1.2.2.16.10 wranIfBasicCapabilityCpePnWindowSize

Size of `PN_WINDOW` (see 7.4) that is used to protect against replay attacks. This reflects the setting of the IE defined in 7.7.11.3.3.2.

13.1.2.2.16.11 wranIfBasicCapabilityCpeScmFlowControl

Maximum number of ongoing SCM transactions that the CPE can support. This reflects the setting of the IE defined in 7.7.11.3.3.3.

13.1.2.2.17 wranIfBsCpeRegCapabilityCmn

This MIB object is a group containing objects that are common to wranIfBsCpeRegCapabilityReqEntry and wranIfBsCpeRegCapabilityRspEntry.

13.1.2.2.17.1 wranIfRegCapabilityIndex

Index for unique entry in tables relating to registered capabilities.

13.1.2.2.17.2 wranIfRegCapabilityMacAddress

MAC address of CPE that is currently registered with BS.

13.1.2.2.17.3 wranIfRegCapabilityReqNumAttempts

The current number of attempts that a CPE has attempted network entry. This item is set to 0 upon successful completion of registration process and a CPE is admitted into the network. This item is incremented every time a CPE attempts registration, but is unsuccessful. If this value reaches the limit set by wranIfBsMaxNumRegReqAttempts, then the CPE shall restart network entry process.

13.1.2.2.17.4 wranIfRegCapabilityNMEALocStringSize

Size of NMEA location string of the CPE in REG-REQ (see 7.7.7.3.1), in octets.

13.1.2.2.17.5 wranIfRegCapabilityNMEALocString

NMEA location string of the CPE in REG-REQ (see 7.7.7.3.1).

13.1.2.2.17.6 wranIfRegCapabilityCsConfig

Indication in REG-REQ/RSP of how the provider will operate the CPE on an ongoing basis; either with the Ethernet CS only or the IP CS (see 7.7.7.3.2).

13.1.2.2.17.7 wranIfRegCapabilityIpVersion

What version of the IP protocol (either v4 or v6) indicate in REG-REQ/RSP the CPE supports (see 7.7.7.3.3).

13.1.2.2.17.8 wranIfRegCapabilityIpRohcSupport

Indicator in REG-REQ/RSP of whether CPE supports IP Robust Header Compression (ROHC) (see 7.7.7.3.4.1).

13.1.2.2.17.9 wranIfRegCapabilityArqSupport

ARQ Support IE of REG-REQ/RSP in 7.7.7.3.4.2.

13.1.2.2.17.10 wranIfRegCapability2ndMgmtArqWindowSize

Secondary Management flow - ARQ Window Size IE of REG-REQ/RSP defined in 7.7.8.9.17.2.

13.1.2.2.17.11 wranIfRegCapability2ndMgmtArqRetryTxDelay

Secondary Management flow - Transmitter Delay component of ARQ Retry Timeout IE of REG-REQ/RSP defined in 7.7.8.9.17.3.

13.1.2.2.17.12 wranIfRegCapability2ndMgmtArqRetryRxDelay

Secondary Management flow - Receiver Delay component of ARQ Retry Timeout IE of REG-REQ/RSP defined in 7.7.8.9.17.3.

13.1.2.2.17.13 wranIfRegCapability2ndMgmtArqBlockLifetime

Secondary Management flow - ARQ Block Lifetime IE of REG-REQ/RSP defined in 7.7.8.9.17.4.

13.1.2.2.17.14 wranIfRegCapability2ndMgmtArqSyncLossTimeout

Secondary Management flow - ARQ Sync Loss Timeout IE of REG-REQ/RSP defined in 7.7.8.9.17.5.

13.1.2.2.17.15 wranIfRegCapability2ndMgmtArqDeliverInOrder

Secondary Management flow - ARQ Deliver In Order IE of REG-REQ/RSP defined in 7.7.8.9.17.6.

13.1.2.2.17.16 wranIfRegCapability2ndMgmtArqRxPurgeTimeout

Secondary Management flow - ARQ Rx Purge Timeout IE of REG-REQ/RSP defined in 7.7.8.9.17.7.

13.1.2.2.17.17 wranIfRegCapability2ndMgmtArqBlockSize

Secondary Management flow - ARQ Block Size IE of REG-REQ/RSP defined in 7.7.8.9.17.8.

13.1.2.2.17.18 wranIfRegCapabilityDsxFowControl

DSx Flow Control IE of REG-REQ/RSP in 7.7.7.3.4.4.

13.1.2.2.17.19 wranIfRegCapabilityMcaFlowControl

MCA Flow Control IE of REG-REQ/RSP in 7.7.7.3.4.5.

13.1.2.2.17.20 wranIfRegCapabilityMaxNumMcastGroups

Maximum Number of Multicast Groups IE of REG-REQ/RSP in 7.7.7.3.4.6.

13.1.2.2.17.21 wranIfRegCapabilitySensModeSupportArray

Value of the "Sensing Mode Support Array" of the Measurement Support IE in REG-REQ/RSP in 7.7.7.3.4.7. If the value of this is set to "No Sensing" then `wranIfBsCpeMeasSupportReqTable` and `wranIfBsCpeMeasSupportRspTable` will not be stored for the CPE.

13.1.2.2.17.22 wranIfRegCapabilityAntennaModelSize

Length of `wranIfRegCapabilityAntennaModel`, in octets (see Manufacturer Specific Antenna Model IE of REG-REQ in 7.7.7.3.4.8).

13.1.2.2.17.23 wranIfRegCapabilityAntennaModel

Manufacturer Specific Antenna Model IE of REG-REQ in 7.7.7.3.4.8.

13.1.2.2.17.24 wranIfRegCapabilityCpeResidualDelay

CPE Residual Delay IE of REG-REQ in 7.7.7.3.4.10.

13.1.2.2.17.25 wranIfRegCapability2ndMgmtIpAllocMethod

Method for allocating IP Addresses on Secondary Management Connection IE of REG-REQ/RSP in 7.7.7.3.4.11.

13.1.2.2.17.26 wranIfRegCapabilityCpeOperationalCapability

CPE Operation Capability IE of REG-REQ in 7.7.7.3.4.13.

13.1.2.2.17.27 wranIfRegCapabilityCpeRegistrationTimer

CPE Registration Timer IE of REG-REQ/RSP in 7.7.7.3.5. This value is used to set T30 for the CPE.

13.1.2.2.17.28 wranIfRegCapabilityPermanentSid

Permanent station ID assigned to CPE, when CPE is entering the network under the CPE Privacy method (see 8.7). The format of this IE is defined in 7.7.7.3.4.12.

13.1.2.2.18 wranIfBsCpeMeasSupportCmn

This MIB object is a group containing objects that are common to `wranIfBsCpeMeasSupportReqEntry` and `wranIfBsCpeMeasSupportRspEntry`.

13.1.2.2.18.1 wranIfMeasSupportIndex

Index into entry of tables storing Measurement Support IE that is part of REG-REQ/RSP.

13.1.2.2.18.2 wranIfMeasSupportMacAddress

MAC address of CPE. This corresponds to an entry in `wranIfBsCpeRegCapabilityReqTable` for a registered CPE.

13.1.2.2.18.3 wranIfMeasSupportSignalType

Signal type to which measurement configuration this entry pertains (see Table 237).

13.1.2.2.18.4 wranIfMeasSupportThreshold

Signed number that signifies the sensitivity threshold for the signal type.

13.1.2.2.18.5 wranIfMeasSupportPd

Probability of detection (PD) for the signal type.