

INTERNATIONAL
STANDARD

ISO/
IEC/IEEE
8802-3

Third edition
2021-02

AMENDMENT 14
2022-10

**Telecommunications and exchange
between information technology
systems — Requirements for local and
metropolitan area networks —**

**Part 3:
Standard for Ethernet**

**AMENDMENT 14: Bidirectional 10 Gb/s,
25 Gb/s, and 50 Gb/s optical access PHYs**

*Télécommunications et échange entre systèmes informatiques —
Exigences pour les réseaux locaux et métropolitains —*

Partie 3: Norme pour Ethernet

*AMENDEMENT 14: Liaisons physiques (PHY) d'accès optique 10 Gb/s,
25 Gb/s et 50 Gb/s bidirectionnelles*



Reference number
ISO/IEC/IEEE 8802-3:2021/Amd.14:2022(E)

Documents
Document Sharing Hub
© IEEE 2021

Authorized licensed use limited to: Tsinghua University. Downloaded on February 26, 2026 at 08:57:30 UTC from IEEE Xplore. Restrictions apply.



COPYRIGHT PROTECTED DOCUMENT

© IEEE 2021

All rights reserved. Unless otherwise specified, or required in the context of its implementation, no part of this publication may be reproduced or utilized otherwise in any form or by any means, electronic or mechanical, including photocopying, or posting on the internet or an intranet, without prior written permission. Permission can be requested from IEEE at the address below.

Institute of Electrical and Electronics Engineers, Inc
3 Park Avenue, New York
NY 10016-5997, USA

Email: stds.ipr@ieee.org
Website: www.ieee.org

Published in Switzerland

Foreword

ISO (the International Organization for Standardization) and IEC (the International Electrotechnical Commission) form the specialized system for worldwide standardization. National bodies that are members of ISO or IEC participate in the development of International Standards through technical committees established by the respective organization to deal with particular fields of technical activity. ISO and IEC technical committees collaborate in fields of mutual interest. Other international organizations, governmental and non-governmental, in liaison with ISO and IEC, also take part in the work.

The procedures used to develop this document and those intended for its further maintenance are described in the ISO/IEC Directives, Part 1. In particular, the different approval criteria needed for the different types of ISO/IEC documents should be noted. This document was drafted in accordance with the editorial rules of the ISO/IEC Directives, Part 2 (see www.iso.org/directives or www.iec.ch/members_experts/refdocs).

IEEE Standards documents are developed within the IEEE Societies and the Standards Coordinating Committees of the IEEE Standards Association (IEEE-SA) Standards Board. The IEEE develops its standards through a consensus development process, approved by the American National Standards Institute, which brings together volunteers representing varied viewpoints and interests to achieve the final product. Volunteers are not necessarily members of the Institute and serve without compensation. While the IEEE administers the process and establishes rules to promote fairness in the consensus development process, the IEEE does not independently evaluate, test, or verify the accuracy of any of the information contained in its standards.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO and IEC shall not be held responsible for identifying any or all such patent rights. Details of any patent rights identified during the development of the document will be in the Introduction and/or on the ISO list of patent declarations received (see www.iso.org/patents) or the IEC list of patent declarations received (see <https://patents.iec.ch>).

Any trade name used in this document is information given for the convenience of users and does not constitute an endorsement.

For an explanation of the voluntary nature of standards, the meaning of ISO specific terms and expressions related to conformity assessment, as well as information about ISO's adherence to the World Trade Organization (WTO) principles in the Technical Barriers to Trade (TBT), see www.iso.org/iso/foreword.html. In the IEC, see www.iec.ch/understanding-standards.

ISO/IEC/IEEE 8802-3:2021/Amd.14 was prepared by the LAN/MAN of the IEEE Computer Society (as IEEE 802.3cp-2021) and drafted in accordance with its editorial rules. It was adopted, under the “fast-track procedure” defined in the Partner Standards Development Organization cooperation agreement between ISO and IEEE, by Joint Technical Committee ISO/IEC JTC 1, *Information technology*, Subcommittee SC 6, *Telecommunications and information exchange between systems*.

A list of all parts in the ISO/IEC/IEEE 8802-3 series can be found on the ISO and IEC websites.

Any feedback or questions on this document should be directed to the user's national standards body. A complete listing of these bodies can be found at www.iso.org/members.html and www.iec.ch/national-committees.

IEEE Std 802.3cp™-2021

(Amendment to IEEE Std 802.3™-2018
as amended by IEEE Std 802.3cb™-2018,
IEEE Std 802.3bt™-2018,
IEEE Std 802.3cd™-2018,
IEEE Std 802.3cn™-2019,
IEEE Std 802.3cg™-2019,
IEEE Std 802.3cq™-2020,
IEEE Std 802.3cm™-2020,
IEEE Std 802.3ch™-2020,
IEEE Std 802.3ca™-2020,
IEEE Std 802.3cr™-2021,
IEEE Std 802.3cu™-2021,
IEEE Std 802.3cv™-2021,
and IEEE Std 802.3ct™-2021)

IEEE Standard for Ethernet

Amendment 14: Bidirectional 10 Gb/s, 25 Gb/s, and 50 Gb/s Optical Access PHYs

Developed by the

LAN/MAN Standards Committee
of the
IEEE Computer Society

Approved 16 June 2021

IEEE SA Standards Board

Abstract: This amendment to IEEE Std 802.3-2018 adds Physical Layer specifications and management parameters for 10 Gb/s, 25 Gb/s, and 50 Gb/s Ethernet optical interfaces for bidirectional operation over a single strand of single-mode fiber with reaches of at least 10 km, 20 km, and 40 km.

Keywords: 10GBASE-BR10, 10GBASE-BR20, 10GBASE-BR40, 25GBASE-BR10, 25GBASE-BR20, 25GBASE-BR40, 50GBASE-BR10, 50GBASE-BR20, 50GBASE-BR40, bidirectional (BiDi), Ethernet, forward error correction (FEC), IEEE 802.3™, IEEE 802.3cp™, multi-gigabit Ethernet bidirectional Physical Layers, Physical Coding Sublayer (PCS), Physical Medium Attachment (PMA) sublayer, Physical Medium Dependent (PMD) sublayer

The Institute of Electrical and Electronics Engineers, Inc.
3 Park Avenue, New York, NY 10016-5997, USA

Copyright © 2021 by The Institute of Electrical and Electronics Engineers, Inc.
All rights reserved. Published 16 July 2021. Printed in the United States of America.

IEEE and 802 are registered trademarks in the U.S. Patent & Trademark Office, owned by The Institute of Electrical and Electronics Engineers, Incorporated.

PDF: ISBN 978-1-5044-7692-8 STD24791
Print: ISBN 978-1-5044-7693-5 STDPD24791

IEEE prohibits discrimination, harassment and bullying.

For more information, visit <http://www.ieee.org/web/aboutus/whatis/policies/p9-26.html>.

No part of this publication may be reproduced in any form, in an electronic retrieval system or otherwise, without the prior written permission of the publisher.

Important Notices and Disclaimers Concerning IEEE Standards Documents

IEEE Standards documents are made available for use subject to important notices and legal disclaimers. These notices and disclaimers, or a reference to this page (<https://standards.ieee.org/ipr/disclaimers.html>), appear in all standards and may be found under the heading “Important Notices and Disclaimers Concerning IEEE Standards Documents.”

Notice and Disclaimer of Liability Concerning the Use of IEEE Standards Documents

IEEE Standards documents are developed within the IEEE Societies and the Standards Coordinating Committees of the IEEE Standards Association (IEEE SA) Standards Board. IEEE develops its standards through an accredited consensus development process, which brings together volunteers representing varied viewpoints and interests to achieve the final product. IEEE Standards are documents developed by volunteers with scientific, academic, and industry-based expertise in technical working groups. Volunteers are not necessarily members of IEEE or IEEE SA, and participate without compensation from IEEE. While IEEE administers the process and establishes rules to promote fairness in the consensus development process, IEEE does not independently evaluate, test, or verify the accuracy of any of the information or the soundness of any judgments contained in its standards.

IEEE does not warrant or represent the accuracy or completeness of the material contained in its standards, and expressly disclaims all warranties (express, implied and statutory) not included in this or any other document relating to the standard, including, but not limited to, the warranties of: merchantability; fitness for a particular purpose; non-infringement; and quality, accuracy, effectiveness, currency, or completeness of material. In addition, IEEE disclaims any and all conditions relating to results and workmanlike effort. In addition, IEEE does not warrant or represent that the use of the material contained in its standards is free from patent infringement. IEEE Standards documents are supplied “AS IS” and “WITH ALL FAULTS.”

Use of an IEEE standard is wholly voluntary. The existence of an IEEE Standard does not imply that there are no other ways to produce, test, measure, purchase, market, or provide other goods and services related to the scope of the IEEE standard. Furthermore, the viewpoint expressed at the time a standard is approved and issued is subject to change brought about through developments in the state of the art and comments received from users of the standard.

In publishing and making its standards available, IEEE is not suggesting or rendering professional or other services for, or on behalf of, any person or entity, nor is IEEE undertaking to perform any duty owed by any other person or entity to another. Any person utilizing any IEEE Standards document, should rely upon his or her own independent judgment in the exercise of reasonable care in any given circumstances or, as appropriate, seek the advice of a competent professional in determining the appropriateness of a given IEEE standard.

IN NO EVENT SHALL IEEE BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO: THE NEED TO PROCURE SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE PUBLICATION, USE OF, OR RELIANCE UPON ANY STANDARD, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE AND REGARDLESS OF WHETHER SUCH DAMAGE WAS FORESEEABLE.

Translations

The IEEE consensus development process involves the review of documents in English only. In the event that an IEEE standard is translated, only the English version published by IEEE is the approved IEEE standard.

Official statements

A statement, written or oral, that is not processed in accordance with the IEEE SA Standards Board Operations Manual shall not be considered or inferred to be the official position of IEEE or any of its committees and shall not be considered to be, nor be relied upon as, a formal position of IEEE. At lectures, symposia, seminars, or educational courses, an individual presenting information on IEEE standards shall make it clear that the presenter's views should be considered the personal views of that individual rather than the formal position of IEEE, IEEE SA, the Standards Committee, or the Working Group.

Comments on standards

Comments for revision of IEEE Standards documents are welcome from any interested party, regardless of membership affiliation with IEEE or IEEE SA. However, **IEEE does not provide interpretations, consulting information, or advice pertaining to IEEE Standards documents.**

Suggestions for changes in documents should be in the form of a proposed change of text, together with appropriate supporting comments. Since IEEE standards represent a consensus of concerned interests, it is important that any responses to comments and questions also receive the concurrence of a balance of interests. For this reason, IEEE and the members of its Societies and Standards Coordinating Committees are not able to provide an instant response to comments, or questions except in those cases where the matter has previously been addressed. For the same reason, IEEE does not respond to interpretation requests. Any person who would like to participate in evaluating comments or in revisions to an IEEE standard is welcome to join the relevant IEEE working group. You can indicate interest in a working group using the Interests tab in the Manage Profile & Interests area of the [IEEE SA myProject system](#). An IEEE Account is needed to access the application.

Comments on standards should be submitted using the [Contact Us](#) form.

Laws and regulations

Users of IEEE Standards documents should consult all applicable laws and regulations. Compliance with the provisions of any IEEE Standards document does not constitute compliance to any applicable regulatory requirements. Implementers of the standard are responsible for observing or referring to the applicable regulatory requirements. IEEE does not, by the publication of its standards, intend to urge action that is not in compliance with applicable laws, and these documents may not be construed as doing so.

Data privacy

Users of IEEE Standards documents should evaluate the standards for considerations of data privacy and data ownership in the context of assessing and using the standards in compliance with applicable laws and regulations.

Copyrights

IEEE draft and approved standards are copyrighted by IEEE under US and international copyright laws. They are made available by IEEE and are adopted for a wide variety of both public and private uses. These

include both use, by reference, in laws and regulations, and use in private self-regulation, standardization, and the promotion of engineering practices and methods. By making these documents available for use and adoption by public authorities and private users, IEEE does not waive any rights in copyright to the documents.

Photocopies

Subject to payment of the appropriate licensing fees, IEEE will grant users a limited, non-exclusive license to photocopy portions of any individual standard for company or organizational internal use or individual, non-commercial use only. To arrange for payment of licensing fees, please contact Copyright Clearance Center, Customer Service, 222 Rosewood Drive, Danvers, MA 01923 USA; +1 978 750 8400; <https://www.copyright.com/>. Permission to photocopy portions of any individual standard for educational classroom use can also be obtained through the Copyright Clearance Center.

Updating of IEEE Standards documents

Users of IEEE Standards documents should be aware that these documents may be superseded at any time by the issuance of new editions or may be amended from time to time through the issuance of amendments, corrigenda, or errata. An official IEEE document at any point in time consists of the current edition of the document together with any amendments, corrigenda, or errata then in effect.

Every IEEE standard is subjected to review at least every 10 years. When a document is more than 10 years old and has not undergone a revision process, it is reasonable to conclude that its contents, although still of some value, do not wholly reflect the present state of the art. Users are cautioned to check to determine that they have the latest edition of any IEEE standard.

In order to determine whether a given document is the current edition and whether it has been amended through the issuance of amendments, corrigenda, or errata, visit [IEEE Xplore](#) or [contact IEEE](#). For more information about the IEEE SA or IEEE's standards development process, visit the IEEE SA Website.

Errata

Errata, if any, for all IEEE standards can be accessed on the [IEEE SA Website](#). Search for standard number and year of approval to access the web page of the published standard. Errata links are located under the Additional Resources Details section. Errata are also available in [IEEE Xplore](#). Users are encouraged to periodically check for errata.

Patents

IEEE Standards are developed in compliance with the [IEEE SA Patent Policy](#).

IMPORTANT NOTICE

IEEE Standards do not guarantee or ensure safety, security, health, or environmental protection, or ensure against interference with or from other devices or networks. IEEE Standards development activities consider research and information presented to the standards development group in developing any safety recommendations. Other information about safety practices, changes in technology or technology implementation, or impact by peripheral systems also may be pertinent to safety considerations during implementation of the standard. Implementers and users of IEEE Standards documents are responsible for determining and complying with all appropriate safety, security, environmental, health, and interference protection practices and all applicable laws and regulations.

Participants

The following individuals were officers and members of the IEEE 802.3 Working Group at the beginning of the IEEE P802.3cp Working Group ballot.

David J. Law, *IEEE 802.3 Working Group Chair*
Adam Healey, *IEEE 802.3 Working Group Vice-Chair*
Jon Lewis, *IEEE 802.3 Working Group Secretary*
Steven B. Carlson, *IEEE 802.3 Working Group Executive Secretary*
Valerie Maguire, *IEEE 802.3 Working Group Treasurer*

Frank Effenberger, *IEEE P802.3cp Bidirectional 10 Gb/s, 25 Gb/s, and 50 Gb/s Optical Access PHYs Task Force Chair*

Duane Remein, *IEEE P802.3cp Bidirectional 10 Gb/s, 25 Gb/s, and 50 Gb/s Optical Access PHYs Task Force Editor-in-Chief, Phase 1*

Yuanqiu Luo, *IEEE P802.3cp Bidirectional 10 Gb/s, 25 Gb/s, and 50 Gb/s Optical Access PHYs Task Force Editor-in-Chief, Phase 2*

David Abramson
Pete Anslow
Michikazu Aono
Nobuyasu Araki
Tim Baggett
Thananya Baldwin
Steven Baumgartner
Denis Beaudoin
Gitesh Bhagwat
Rich Boyer
David Brandt
Ralf-Peter Braun
Theodore Brillhart
Paul Brooks
Matthew Brown
Leon Bruckman
Jairo Bustos Heredia
Adrian Butter
John Calvin
Clark Carty
David Chalupsky
Jacky Chang
Xin Chang
Chan Chen
Golam Choudhury
Keng Hua Chuang
John D'Ambrosia
Piers J. G. Dawe
Fred Dawson
Gerrit den Besten
Claudio DeSanti
Curtis Donahue
Liang Du
Kathryn Dube
Mike Dudek
David Estes
John Ewen
Vincent Ferretti
Brian Franchuk
Matthias Fritsche
Takashi Fukuoka

Ali Ghiasi
Joel Goergen
Steven Gorshe
Hideki Goto
Steffen Graber
Olaf Grau
Robert Grow
Martin Gubow
Mark Gustlin
Marek Hajduczenia
Howard Heck
David Hess
Brian Holden
Bernd Horrmeyer
Yasuhiro Hyakutake
Jonathan Ingham
Kazuhiko Ishibe
Hideki Isono
Tom Issenhuth
Hiroaki Ito
Kenneth Jackson
Andrew Jimenez
John Johnson
Chad Jones
Peter Jones
Lokesh Kabra
Haysam Kadry
Manabu Kagami
Upen Kareti
Athanasios Kasapi
Yong Kim
Mark Kimber
Michael Klempa
Curtis Knittle
Elizabeth Kochuparambil
Sam Kocsis
Wojciech Koczwara
Paul Kolesar
Taiji Kondo
Daniel Koppermueller
Glen Kramer

Taketo Kumada
Hans Lackner
Frank Lambrecht
Mark Laubach
Greg Le Cheminant
David Lewis
Mike-Peng Li
Alex Lin
Robert Lingle
Hai-Feng Liu
William Lo
Kent Lusted
Jeffery Maki
David Malicoat
Eric Maniloff
Flavio Marques
Arthur Marris
Takeo Masuda
Mick McCarthy
Brett McClellan
Larry McMillan
Greg McSorley
Richard Mellitz
Shimon Muller
Sean Murphy
James Nadolny
Edward Nakamoto
Raymond Nering
Paul Neveux
Gary Nicholl
Shawn Nicholl
Kevin Noll
Mark Nowell
David Ofelt
Ryo Okabe
Tom Palkert
Carlos Pardo
Earl Parsons
Gerald Pepper
Rubén Perez DeAranda Alonso
David Piehler

Fabio Pittala	Massimo Sorbara	Prasad Venugopal
Christopher Pohl	Edward Sprague	Edward Walter
William Powell	Peter Stassar	Roy Wang
Rick Rabinovich	Heath Stewart	Xuehuan Wang
Parthasarathy Raju	Junqing Sun	James Weaver
Adee Ran	Steve Swanson	Dong Wei
Alon Regev	Tomoo Takahara	Brian Welch
Victor Renteria	Satoshi Takahashi	Matthias Wendt
Thomas Rettig	Tadashi Takahashi	Natalie Wienckowski
Toshiaki Sakai	Kazuya Takayama	Dance Wu
Hamid Salehi	Michael Takefman	Peter Wu
Sam Sambasivan	Masaru Terada	Dayin Xu
Edward Sayre	Geoffrey Thompson	Yu Xu
Matthew Schmitt	Pirooz Tooyserkani	James Young
Hossein Sedarat	Nathan Tracy	Lennart Yseboodt
Masood Shariff	Viet Tran	Conrad Zerna
Masato Shiino	David Tremblay	Xingxin Zhang
Ramin Shirani	Stephen Trowbridge	Chunhui Zhu
Kapil Shrikhande	Mike Tu	Yan Zhuang
Jeff Slavick	Ed Ulrichs	Martin Zielinski
Scott Sommers	Alexander Umnov	George Zimmerman
		Pavel Zivny

The following members of the individual balloting committee voted on this standard. Balloters may have voted for approval, disapproval, or abstention.

Rob Aekins	Yasuhiro Hyakutake	Arumugam Paventhan
Robert Aiello	Osamu Ishida	Michael Peters
Thomas Alexander	Hideki Isono	David Pichler
Philip E. Beecher	Tom Issenhuth	Rick Pimpinella
Rich Boyer	Raj Jain	Fabio Pittala
Ralf-Peter Braun	Jack Jewell	Adee Ran
Jairo Bustos Heredia	Peter Jones	R. K. Rannow
William Byrd	Lokesh Kabra	Maximilian Riegel
Steven B. Carlson	Stuart Kerry	Benjamin Rolfe
Juan Carreon	Yong Kim	Olindo Savi
Clark Carty	Glen Kramer	Scott Sommers
Aniruddha Chandra	Frank Lambrecht	Peter Stassar
Pin Chang	Mark Laubach	Walter Struppler
Chan Chen	David J. Law	David Tepen
David Chen	Pi-Cheng Law	James Theodoras
Charles Cook	Han Hyub Lee	Nathan Tracy
Piers J. G. Dawe	Hyeong Ho Lee	David Tremblay
John Deandrea	David Lewis	Mark-Rene Uchida
Christopher Diminico	Jon Lewis	Alexander Umnov
Frank Effenberger	Yuanqiu Luo	Dmitri Varsanofiev
Avraham Freedman	Valerie Maguire	Ruoxu Wang
Matthias Fritsche	Jeffery Maki	James Weaver
Limin Geng	Scott Mansfield	Stephen Webb
Marek Hajduczenia	Brett McClellan	Karl Weber
Xiang He	Jonathon McLendon	Matthias Wendt
Adam Healey	Richard Mellitz	Andreas Wolf
Marco Hernandez	Raymond Nering	Peter Wu
David Hess	Satoshi Obara	James Young
Werner Hoelzl	Carlos Pardo	Yu Yuan
Gergely Huszak	Bansi Patel	Oren Yuen

When the IEEE SA Standards Board approved this standard on 16 June 2021, it had the following membership:

Gary Hoffman, *Chair*
Jon Walter Rosdahl, *Vice Chair*
John D. Kulick, *Past Chair*
Konstantinos Karachalios, *Secretary*

Edward A. Addy
Doug Edwards
Ramy Ahmed Fathy
J. Travis Griffith
Thomas Koshy
Joseph L. Koepfinger*
David J. Law

Howard Li
Daozhuang Lin
Kevin Lu
Daleep C. Mohla
Chenhui Niu
Damir Novosel
Annette Reilly
Dorothy Stanley

Mehmet Ulema
Lei Wang
F. Keith Waters
Karl Weber
Sha Wei
Howard Wolfman
Daidi Zhong

*Member Emeritus

Introduction

This introduction is not part of IEEE Std 802.3cp-2021, IEEE Standard for Ethernet—Amendment 14: Bidirectional 10 Gb/s, 25 Gb/s, and 50 Gb/s Optical Access PHYs.

IEEE Std 802.3™ was first published in 1985. Since the initial publication, many projects have added functionality or provided maintenance updates to the specifications and text included in the standard. Each IEEE 802.3 project/amendment is identified with a suffix (e.g., IEEE Std 802.3ba™-2010).

The half duplex Media Access Control (MAC) protocol specified in IEEE Std 802.3-1985 is Carrier Sense Multiple Access with Collision Detection (CSMA/CD). This MAC protocol was key to the experimental Ethernet developed at Xerox Palo Alto Research Center, which had a 2.94 Mb/s data rate. Ethernet at 10 Mb/s was jointly released as a public specification by Digital Equipment Corporation (DEC), Intel and Xerox in 1980. Ethernet at 10 Mb/s was approved as an IEEE standard by the IEEE Standards Board in 1983 and subsequently published in 1985 as IEEE Std 802.3-1985. Since 1985, new media options, new speeds of operation, and new capabilities have been added to IEEE Std 802.3. A full duplex MAC protocol was added in 1997.

Some of the major additions to IEEE Std 802.3 are identified in the marketplace with their project number. This is most common for projects adding higher speeds of operation or new protocols. For example, IEEE Std 802.3u™ added 100 Mb/s operation (also called Fast Ethernet), IEEE Std 802.3z added 1000 Mb/s operation (also called Gigabit Ethernet), IEEE Std 802.3ae added 10 Gb/s operation (also called 10 Gigabit Ethernet), IEEE Std 802.3ah™ specified access network Ethernet (also called Ethernet in the First Mile) and IEEE Std 802.3ba added 40 Gb/s operation (also called 40 Gigabit Ethernet) and 100 Gb/s operation (also called 100 Gigabit Ethernet). These major additions are all now included in and are superseded by IEEE Std 802.3-2018 and are not maintained as separate documents.

At the date of IEEE Std 802.3cp-2021 publication, IEEE Std 802.3 was composed of the following documents:

IEEE Std 802.3-2018

Section One—Includes Clause 1 through Clause 20 and Annex A through Annex H and Annex 4A. Section One includes the specifications for 10 Mb/s operation and the MAC, frame formats and service interfaces used for all speeds of operation.

Section Two—Includes Clause 21 through Clause 33 and Annex 22A through Annex 33E. Section Two includes management attributes for multiple protocols and speed of operation as well as specifications for providing power over twisted pair cabling for multiple operational speeds. It also includes general information on 100 Mb/s operation as well as most of the 100 Mb/s Physical Layer specifications.

Section Three—Includes Clause 34 through Clause 43 and Annex 36A through Annex 43C. Section Three includes general information on 1000 Mb/s operation as well as most of the 1000 Mb/s Physical Layer specifications.

Section Four—Includes Clause 44 through Clause 55 and Annex 44A through Annex 55B. Section Four includes general information on 10 Gb/s operation as well as most of the 10 Gb/s Physical Layer specifications.

Section Five—Includes Clause 56 through Clause 77 and Annex 57A through Annex 76A. Clause 56 through Clause 67 and Clause 75 through Clause 77, as well as associated annexes, specify subscriber access and other Physical Layers and sublayers for operation from 512 kb/s to 10 Gb/s, and defines

services and protocol elements that enable the exchange of IEEE Std 802.3 format frames between stations in a subscriber access network. Clause 68 specifies a 10 Gb/s Physical Layer specification. Clause 69 through Clause 74 and associated annexes specify Ethernet operation over electrical backplanes at speeds of 1000 Mb/s and 10 Gb/s.

Section Six—Includes Clause 78 through Clause 95 and Annex 83A through Annex 93C. Clause 78 specifies Energy-Efficient Ethernet. Clause 79 specifies IEEE 802.3 Organizationally Specific Link Layer Discovery Protocol (LLDP) type, length, and value (TLV) information elements. Clause 80 through Clause 95 and associated annexes include general information on 40 Gb/s and 100 Gb/s operation as well the 40 Gb/s and 100 Gb/s Physical Layer specifications. Clause 90 specifies Ethernet support for time synchronization protocols.

Section Seven—Includes Clause 96 through Clause 115 and Annex 97A through Annex 115A. Clause 96 through Clause 98, Clause 104, and associated annexes, specify Physical Layers and optional features for 100 Mb/s and 1000 Mb/s operation over a single twisted pair. Clause 100 through Clause 103, as well as associated annexes, specify Physical Layers for the operation of the EPON protocol over coaxial distribution networks. Clause 105 through Clause 114 and associated annexes include general information on 25 Gb/s operation as well as 25 Gb/s Physical Layer specifications. Clause 99 specifies a MAC merge sublayer for the interspersing of express traffic. Clause 115 and its associated annex specify a Physical Layer for 1000 Mb/s operation over plastic optical fiber.

Section Eight—Includes Clause 116 through Clause 126 and Annex 119A through Annex 120E. Clause 116 through Clause 124 and associated annexes include general information on 200 Gb/s and 400 Gb/s operation as well the 200 Gb/s and 400 Gb/s Physical Layer specifications. Clause 125 and Clause 126 include general information on 2.5 Gb/s and 5 Gb/s operation as well as 2.5 Gb/s and 5 Gb/s Physical Layer specifications.

IEEE Std 802.3cb™-2018

Amendment 1—This amendment includes changes to IEEE Std 802.3-2018 and its amendments, and adds Clause 127 through Clause 130, Annex 127A, Annex 128A, Annex 128B, and Annex 130A. This amendment adds new Physical Layers for operation at 2.5 Gb/s and 5 Gb/s over electrical backplanes.

IEEE Std 802.3bt™-2018

Amendment 2—This amendment includes changes to IEEE Std 802.3-2018 and adds Clause 145, Annex 145A, Annex 145B, and Annex 145C. This amendment adds power delivery using all four pairs in the structured wiring plant, resulting in greater power being available to end devices. This amendment also allows for lower standby power consumption in end devices and adds a mechanism to better manage the available power budget.

IEEE Std 802.3cd™-2018

Amendment 3—This amendment includes changes to IEEE Std 802.3-2018 and adds Clause 131 through Clause 140 and Annex 135A through Annex 136D. This amendment adds MAC parameters, Physical Layers, and management parameters for the transfer of IEEE 802.3 format frames at 50 Gb/s, 100 Gb/s, and 200 Gb/s.

IEEE Std 802.3cn™-2019

Amendment 4—This amendment includes changes to IEEE Std 802.3-2018 and adds 50 Gb/s, 200 Gb/s, and 400 Gb/s Physical Layer specifications and management parameters for operation over single-mode fiber with reaches of at least 40 km.

IEEE Std 802.3cg™-2019

Amendment 5—This amendment includes changes to IEEE Std 802.3-2018 and its amendments and adds Clause 146 through Clause 148 and Annex 146A and Annex 146B. This amendment adds 10 Mb/s Physical Layer specifications and management parameters for operation on a single balanced pair of conductors.

IEEE Std 802.3cq™-2020

Amendment 6—This amendment includes editorial and technical corrections, refinements, and clarifications to Clause 33 and related portions of the standard.

IEEE Std 802.3cm™-2020

Amendment 7—This amendment includes changes to IEEE Std 802.3-2018 and adds Clause 150. This amendment adds Physical Layer (PHY) specifications and management parameters for 400 Gb/s operation on four pairs (400GBASE-SR4.2) and eight pairs (400GBASE-SR8) of multimode fiber, over reaches of at least 100 m.

IEEE Std 802.3ch™-2020

Amendment 8—This amendment includes changes to IEEE Std 802.3-2018 and adds Clause 149, Annex 149A, Annex 149B, and Annex 149C. This amendment adds physical layer specifications and management parameters for operation at 2.5 Gb/s, 5 Gb/s, and 10 Gb/s over a single balanced pair of conductors.

IEEE Std 802.3ca™-2020

Amendment 9—This amendment to IEEE Std 802.3-2018 extends the operation of Ethernet passive optical networks (EPONs) to multiple channels of 25 Gb/s providing both symmetric and asymmetric operation for the following data rates (downstream/upstream): 25/10 Gb/s, 25/25 Gb/s, 50/10 Gb/s, 50/25 Gb/s, and 50/50 Gb/s. This amendment specifies the 25 Gb/s EPON Multi-Channel Reconciliation Sublayer (MCRS), Nx25G-EPON Physical Coding Sublayers (PCSs), Physical Media Attachment (PMA) sublayers, and Physical Medium Dependent (PMD) sublayers that support both symmetric and asymmetric data rates while maintaining backward compatibility with already deployed 10 Gb/s EPON equipment. The EPON operation is defined for distances of at least 20 km, and for a split ratio of at least 1:32.

IEEE Std 802.3cr™-2021

Amendment 10—This amendment includes changes to IEEE Std 802.3-2018 and adds Annex J. This amendment replaces references to the IEC 60950 series of standards (including IEC 60950-1 “Information technology equipment—Safety—Part 1: General requirements”) with appropriate references to the IEC 62368 “Audio/video, information and communication technology equipment” series and makes appropriate changes to the standard corresponding to the new references.

IEEE Std 802.3cu™-2021

Amendment 11—This amendment includes changes to IEEE Std 802.3-2018 and adds Clause 151. This amendment adds Physical Layer (PHY) specifications and management parameters for 100 Gb/s and 400 Gb/s operation over single-mode fiber, based on 100 Gb/s per wavelength optical signaling.

IEEE Std 802.3cv™-2021

Amendment 12—This amendment includes editorial and technical corrections, refinements, and clarifications to Clause 145, Power over Ethernet, and related portions of the standard.

IEEE Std 802.3ct™-2021

Amendment 13—This amendment includes changes to IEEE Std 802.3-2018 and adds Clause 152 through Clause 154 and Annex 154A. This amendment adds 100 Gb/s Physical Layer specifications and management parameters for operation over DWDM systems with reaches of at least 80 km.

IEEE Std 802.3cp™-2021

Amendment 14—This amendment includes changes to IEEE Std 802.3-2018 and adds Clause 157, Clause 158, Clause 159, and Clause 160. This amendment adds Physical Layer specifications and management parameters for 10 Gb/s, 25 Gb/s, and 50 Gb/s Ethernet optical interfaces for bidirectional operation over a single strand of single-mode fiber.

Two companion documents exist, IEEE Std 802.3.1 and IEEE Std 802.3.2. IEEE Std 802.3.1 describes Ethernet management information base (MIB) modules for use with the Simple Network Management Protocol (SNMP). IEEE Std 802.3.2 describes YANG data models for Ethernet. IEEE Std 802.3.1 and IEEE Std 802.3.2 are updated to add management capability for enhancements to IEEE Std 802.3 after approval of those enhancements.

IEEE Std 802.3 will continue to evolve. New Ethernet capabilities are anticipated to be added within the next few years as amendments to this standard.

Contents

1. Introduction.....	22
1.4 Definitions	22
1.5 Abbreviations.....	23
30. Management.....	24
30.5 Layer management for medium attachment units (MAUs).....	24
30.5.1 MAU managed object class.....	24
30.5.1.1 MAU attributes	24
30.5.1.1.2 aMAUType	24
30.5.1.1.16 aFECmode.....	25
44. Introduction to 10 Gb/s baseband network.....	26
44.3 Delay constraints.....	26
45. Management Data Input/Output (MDIO) Interface.....	27
45.2 MDIO Interface Registers.....	27
45.2.1 PMA/PMD registers.....	27
45.2.1.6 PMA/PMD control 2 register (Register 1.7)	28
45.2.1.7 PMA/PMD status 2 register (Register 1.8).....	29
45.2.1.7.1 Transmit fault (1.8.11).....	29
45.2.1.7.2 Receive fault (1.8.10).....	30
45.2.1.8 PMD transmit disable register (Register 1.9)	31
45.2.1.8.1 PMD transmit disable 14 (1.9.15).....	31
45.2.1.27a BiDi PMA/PMD extended ability 1 (Register 1.34)	32
45.2.1.27a.1 25GBASE-BR40-U ability (1.34.11).....	32
45.2.1.27a.2 25GBASE-BR40-D ability (1.34.10).....	33
45.2.1.27a.3 25GBASE-BR20-U ability (1.34.9).....	33
45.2.1.27a.4 25GBASE-BR20-D ability (1.34.8).....	33
45.2.1.27a.5 25GBASE-BR10-U ability (1.34.7).....	33
45.2.1.27a.6 25GBASE-BR10-D ability (1.34.6).....	33
45.2.1.27a.7 10GBASE-BR40-U ability (1.34.5).....	33
45.2.1.27a.8 10GBASE-BR40-D ability (1.34.4).....	33
45.2.1.27a.9 10GBASE-BR20-U ability (1.34.3).....	33
45.2.1.27a.10 10GBASE-BR20-D ability (1.34.2).....	33
45.2.1.27a.11 10GBASE-BR10-U ability (1.34.1).....	34
45.2.1.27a.12 10GBASE-BR10-D ability (1.34.0).....	34
45.2.1.27b BiDi PMA/PMD extended ability 2 (Register 1.35)	34
45.2.1.27b.1 50GBASE-BR40-U ability (1.35.5).....	34
45.2.1.27b.2 50GBASE-BR40-D ability (1.35.4).....	34
45.2.1.27b.3 50GBASE-BR20-U ability (1.35.3).....	35
45.2.1.27b.4 50GBASE-BR20-D ability (1.35.2).....	35
45.2.1.27b.5 50GBASE-BR10-U ability (1.35.1).....	35
45.2.1.27b.6 50GBASE-BR10-D ability (1.35.0).....	35
45.2.1.110 RS-FEC control register (Register 1.200)	35
45.2.1.110.1 25G RS-FEC enable (1.200.2).....	35
49. Physical Coding Sublayer (PCS) for 64B/66B, type 10GBASE-R.....	36

49.2	Physical Coding Sublayer (PCS)	36
49.2.2	Functions within the PCS	36
56.	Introduction to Ethernet for subscriber access networks	37
56.1	Overview	37
56.1.1	Summary of P2P sublayers	38
56.1.1.1	P2P fiber media	38
56.1.1.2	P2P copper media	38
56.1.2	Summary of P2MP sublayers	38
56.1.2.1	Multipoint MAC Control Protocol (MPCP)	38
56.1.2.2	Reconciliation Sublayer (RS) and media independent interfaces	38
56.1.3	Physical Layer signaling systems	39
78.	Energy-Efficient Ethernet (EEE)	42
78.1.4	PHY types optionally supporting EEE	42
105.	Introduction to 25 Gb/s networks	43
105.5	Delay constraints	43
108.	Reed-Solomon Forward Error Correction (RS-FEC) sublayer for 10GBASE-R and 25GBASE-R PHYs	44
108.1	Overview	44
108.1.1	Scope	44
108.1.2	Position of RS-FEC in the 10GBASE-R and 25GBASE-R PHY sublayers	44
108.1.3	Inter-sublayer interfaces	45
108.1.3.1	Functional Block Diagram for 10GBASE-R PHYs	46
108.1.3.2	Functional block diagram for 25GBASE-R PHYs	47
108.2	FEC service interface	47
108.2.1	10GBASE-R service primitives	49
108.2.1.1	FEC_UNITDATA.request	49
108.2.1.1.1	Semantics of the service primitive	49
108.2.1.1.2	When generated	49
108.2.1.1.3	Effect of receipt	49
108.2.1.2	FEC_UNITDATA.indication	49
108.2.1.2.1	Semantics of the service primitive	49
108.2.1.2.2	When generated	50
108.2.1.2.3	Effect of receipt	50
108.2.1.3	FEC_SIGNAL.indication	50
108.2.1.3.1	Semantics of the service primitive	50
108.2.1.3.2	When generated	50
108.2.1.3.3	Effect of receipt	50
108.2.2	25GBASE-R service primitives	50
108.3	PMA compatibility	51
108.4	Delay constraints	51
108.5	Functions within the 25GBASE-R RS-FEC sublayer	52
108.5.1	Functional block diagram	52
108.5.1.1	Reverse gearbox and gearbox functions for 10GBASE-R	52
108.5.2.2	Rate compensation for codeword markers in the transmit direction	52
108.5.2.4	Codeword marker insertion	53
108.5.2.5	Reed-Solomon encoder	53

108.5.3.1	Codeword marker lock	56
108.5.3.2	Reed-Solomon decoder.....	56
108.5.3.5	256B/257B to 64B/66B transcoder.....	56
108.5.3.6	Rate compensation for codeword markers in the receive direction.....	57
108.5.4.2	State variables.....	60
108.6	25GBASE-R RS-FEC MDIO function mapping.....	60
108.6.3	25G RS-FEC Enable	60
108.6.4	FEC_bypass_correction_ability	60
108.6.5	FEC_bypass_indication_ability	61
108.7	Protocol implementation conformance statement (PICS) proforma for Clause 108, Reed-Solomon Forward Error Correction (RS-FEC) sublayer for 10GBASE-R and 25GBASE-R PHYs.....	61
108.7.1	Introduction	61
108.7.2.2	Protocol summary.....	62
108.7.3	Major capabilities/options	62
108.7.4	PICS proforma tables for Reed-Solomon Forward Error Correction (RS-FEC) sublayer for 10GBASE-R and 25GBASE-R PHYs	62
108.7.4.2	Receive function	63
131.	Introduction to 50 Gb/s networks	64
131.4	Delay constraints.....	64
157.	Introduction to 10 Gb/s, 25 Gb/s, and 50 Gb/s BiDi PHYs.....	65
157.1	Overview.....	65
157.1.1	Scope	65
157.1.2	Relationship of Multi-Gigabit Ethernet BiDi PHYs to the ISO OSI reference model.....	66
157.1.3	Nomenclature	66
157.1.4	Physical Layer signaling systems.....	67
157.2	Summary of Multi-Gigabit Ethernet BiDi sublayers.....	69
157.2.1	Reconciliation Sublayer (RS) and Media Independent Interface (XGMII, 25GMII, and 50GMII).....	69
157.2.2	Physical Coding Sublayer (PCS).....	69
157.2.3	Forward Error Correction (FEC) sublayer	69
157.2.4	Physical Medium Attachment (PMA) sublayer	70
157.2.5	Physical Medium Dependent (PMD) sublayer.....	70
157.2.6	Management interface (MDIO/MDC)	70
157.2.7	Management.....	70
157.3	Service interface specification method and notation	70
157.4	Delay constraints.....	70
157.5	ONU silent start	71
157.6	Protocol implementation conformance statement (PICS) proforma.....	71
158.	Physical Medium Dependent (PMD) sublayer and medium, types 10GBASE-BR10, 10GBASE-BR20, and 10GBASE-BR40	72
158.1	Overview.....	72
158.1.1	Bit error ratio.....	72
158.2	PMD sublayer service interface.....	73
158.3	Delay constraints.....	73
158.4	PMD MDIO function mapping.....	73
158.5	PMD functional specifications.....	74

158.5.1	PMD block diagram	74
158.5.2	PMD transmit function.....	74
158.5.3	PMD receive function	74
158.5.4	PMD signal detect function.....	75
158.5.5	PMD reset function	76
158.5.6	PMD global transmit disable function	76
158.5.7	PMD fault function.....	76
158.5.8	PMD transmit fault function	76
158.5.9	PMD receive fault function	76
158.5.10	ONU silent start.....	76
158.6	PMD to MDI optical specifications for 10GBASE-BRx.....	76
158.6.1	10GBASE-BRx transmitter optical specifications.....	78
158.6.2	10GBASE-BRx receive optical specifications.....	78
158.6.3	10GBASE-BRx illustrative link power budgets	79
158.7	Jitter specifications for 10GBASE-BRx	80
158.8	Definition of optical parameters and measurement methods.....	80
158.8.1	Test patterns	80
158.8.1.1	Test pattern definition.....	80
158.8.1.2	Square wave pattern definition	81
158.8.2	Wavelength and side-mode suppression ratio (SMSR).....	81
158.8.3	Average optical power	81
158.8.4	Extinction ratio.....	81
158.8.5	Optical Modulation Amplitude (OMA)	82
158.8.6	Relative Intensity Noise (RINxOMA)	82
158.8.7	Transmitter optical waveform (transmitter eye).....	82
158.8.8	Receiver sensitivity	82
158.8.9	Stressed receiver sensitivity	83
158.8.9.1	Stressed receiver sensitivity for 10GBASE-BR10 and 10GBASE-BR40.....	83
158.8.9.1.1	Stressed receiver conformance test block diagram	83
158.8.9.1.2	Parameter definitions	85
158.8.9.1.3	Stressed receiver conformance test signal characteristics and calibration...	86
158.8.9.1.4	Stressed receiver conformance test procedure	87
158.8.9.1.5	Sinusoidal jitter for receiver conformance test	88
158.8.9.2	Stressed receiver sensitivity for 10GBASE-BR20	88
158.8.10	Transmitter and dispersion penalty (TDP).....	88
158.8.10.1	Reference transmitter requirements.....	88
158.8.10.2	Channel requirements	89
158.8.10.3	Reference receiver requirements	89
158.8.10.4	Test procedure	90
158.9	Safety, installation, environment, and labeling.....	90
158.9.1	General safety.....	90
158.9.2	Laser safety	90
158.9.3	Installation.....	90
158.9.4	Environment.....	90
158.9.5	Electromagnetic emission	90
158.9.6	Temperature, humidity, and handling	91
158.9.7	PMD labeling requirements	91
158.10	Fiber optic cabling model	91
158.11	Characteristics of the fiber optic cabling (channel)	92
158.11.1	Optical fiber and cable	92
158.11.2	Optical fiber connection	92
158.11.2.1	Connection insertion loss.....	92
158.11.2.2	Maximum discrete reflectance.....	92
158.11.3	Medium Dependent Interface (MDI) requirements	93

158.12	Requirements for interoperation between 10GBASE-BRx PMDs.....	93
158.13	Protocol implementation conformance statement (PICS) proforma for Clause 158, Physical Medium Dependent (PMD) sublayer and medium, types 10GBASE-BR10, 10GBASE-BR20, and 10GBASE-BR40	94
158.13.1	Introduction	94
158.13.2	Identification	94
158.13.2.1	Implementation identification.....	94
158.13.2.2	Protocol summary	94
158.13.3	Major capabilities/options	95
158.13.4	PICS proforma tables for PMD sublayer and medium, types 10GBASE-BR10, 10GBASE-BR20, and 10GBASE-BR40.....	95
158.13.4.1	PMD functional specifications	95
158.13.4.2	Management functions	96
158.13.4.3	PMD to MDI optical specifications for 10GBASE-BR10	97
158.13.4.4	PMD to MDI optical specifications for 10GBASE-BR20	97
158.13.4.5	PMD to MDI optical specifications for 10GBASE-BR40	97
158.13.4.6	Optical measurement methods.....	98
158.13.4.7	Environmental specifications	98
158.13.4.8	Characteristics of the fiber optic cabling and MDI	98
159.	Physical Medium Dependent (PMD) sublayer and medium, types 25GBASE-BR10, 25GBASE-BR20, and 25GBASE-BR40	99
159.1	Overview.....	99
159.1.1	Bit error ratio	100
159.2	Physical Medium Dependent (PMD) service interface	100
159.3	Delay constraints.....	100
159.4	PMD MDIO function mapping.....	101
159.5	PMD functional specifications.....	101
159.5.1	PMD block diagram	101
159.5.2	PMD transmit function.....	102
159.5.3	PMD receive function	102
159.5.4	PMD global signal detect function.....	102
159.5.5	PMD reset function	103
159.5.6	PMD global transmit disable function	103
159.5.7	PMD fault function (optional).....	103
159.5.8	PMD transmit fault function (optional).....	103
159.5.9	PMD receive fault function	103
159.5.10	ONU silent start.....	104
159.6	PMD to MDI optical specifications for 25GBASE-BRx.....	104
159.6.1	25GBASE-BRx transmitter optical specifications.....	104
159.6.2	25GBASE-BRx receiver optical specifications	105
159.6.3	25GBASE-BRx illustrative link power budgets	105
159.7	Definition of optical parameters and measurement methods.....	107
159.7.1	Test patterns for optical parameters	107
159.7.2	Wavelength and side-mode suppression ratio (SMSR).....	107
159.7.3	Average optical power	107
159.7.4	Optical Modulation Amplitude (OMA)	107
159.7.5	Transmitter and dispersion penalty (TDP).....	108
159.7.5.1	Reference transmitter requirements	108
159.7.5.2	Channel requirements	108
159.7.5.3	Reference receiver requirements	108
159.7.5.4	Test procedure	109
159.7.6	Extinction ratio	109

159.7.7	Relative Intensity Noise (RIN _{20OMA})	109
159.7.8	Transmitter optical waveform (transmit eye)	109
159.7.9	Receiver sensitivity	109
159.7.10	Stressed receiver sensitivity	110
159.8	Safety, installation, environment, and labeling	110
159.8.1	General safety	110
159.8.2	Laser safety	110
159.8.3	Installation	111
159.8.4	Environment	111
159.8.5	Electromagnetic emission	111
159.8.6	Temperature, humidity, and handling	111
159.8.7	PMD labeling requirements	111
159.9	Fiber optic cabling model	111
159.10	Characteristics of the fiber optic cabling (channel)	112
159.10.1	Optical fiber cable	113
159.10.2	Optical fiber connection	113
159.10.2.1	Connection insertion loss	113
159.10.2.2	Maximum discrete reflectance	113
159.10.3	Medium Dependent Interface (MDI) requirements	114
159.11	Requirements for interoperation between 25GBASE-BRx PMDs	114
159.12	Protocol implementation conformance statement (PICS) proforma for Clause 159, Physical Medium Dependent (PMD) sublayer and medium, types 25GBASE-BR10, 25GBASE-BR20, and 25GBASE-BR40	115
159.12.1	Introduction	115
159.12.2	Identification	115
159.12.2.1	Implementation identification	115
159.12.2.2	Protocol summary	115
159.12.3	Major capabilities/options	116
159.12.4	PICS proforma tables for PMD sublayer and medium, types 25GBASE-BR10, 25GBASE-BR20, and 25GBASE-BR40	116
159.12.4.1	PMD functional specifications	116
159.12.4.2	Management functions	117
159.12.4.3	PMD to MDI optical specifications for 25GBASE-BR10	118
159.12.4.4	PMD to MDI optical specifications for 25GBASE-BR20	118
159.12.4.5	PMD to MDI optical specifications for 25GBASE-BR40	118
159.12.4.6	Optical measurement methods	118
159.12.4.7	Environmental specifications	119
159.12.4.8	Characteristics of the fiber optic cabling and MDI	119
160	Physical Medium Dependent (PMD) sublayer and medium, types 50GBASE-BR10, 50GBASE-BR20, and 50GBASE-BR40	120
160.1	Overview	120
160.1.1	Bit error ratio	121
160.2	Physical Medium Dependent (PMD) service interface	121
160.3	Delay and Skew	122
160.3.1	Delay constraints	122
160.3.2	Skew constraints	122
160.4	PMD MDIO function mapping	123
160.5	PMD functional specifications	123
160.5.1	PMD block diagram	124
160.5.2	PMD transmit function	124
160.5.3	PMD receive function	124
160.5.4	PMD global signal detect function	124

160.5.5	PMD reset function	125
160.5.6	PMD global transmit disable function	125
160.5.7	PMD fault function (optional).....	125
160.5.8	PMD transmit fault function (optional).....	126
160.5.9	PMD receive fault function	126
160.5.10	ONU silent start.....	126
160.6	PMD to MDI optical specifications for 50GBASE-BRx.....	126
160.6.1	50GBASE-BRx transmitter optical specifications	126
160.6.2	50GBASE-BRx receive optical specifications.....	127
160.6.3	50GBASE-BRx illustrative link power budgets	129
160.7	Definition of optical parameters and measurement methods.....	129
160.7.1	Test patterns for optical parameters	129
160.7.2	Wavelength and side-mode suppression ratio (SMSR).....	130
160.7.3	Average optical power	130
160.7.4	Outer Optical Modulation Amplitude (OMA _{outer})	130
160.7.5	Transmitter and dispersion eye closure for PAM4 (TDECQ).....	131
160.7.5.1	TDECQ conformance test setup	131
160.7.5.2	Channel requirements	131
160.7.5.3	TDECQ measurement method.....	132
160.7.5.4	TDECQ reference equalizer	132
160.7.6	Transmitter eye closure for PAM4 (TECQ).....	133
160.7.7	Extinction ratio.....	133
160.7.8	Transmitter transition time	133
160.7.9	Relative intensity noise (RIN _{xOMA}).....	133
160.7.10	Receiver sensitivity	134
160.7.11	Stressed receiver sensitivity	135
160.7.11.1	Stressed receiver conformance test block diagram.....	135
160.7.11.2	Stressed receiver conformance test signal characteristics and calibration	135
160.7.11.3	Stressed receiver conformance test signal verification.....	136
160.8	Safety, installation, environment, and labeling.....	137
160.8.1	General safety.....	137
160.8.2	Laser safety	137
160.8.3	Installation.....	137
160.8.4	Environment.....	137
160.8.5	Electromagnetic emission	137
160.8.6	Temperature, humidity, and handling	137
160.8.7	PMD labeling requirements	138
160.9	Fiber optic cabling model	138
160.10	Characteristics of the fiber optic cabling (channel).....	139
160.10.1	Optical fiber cable	139
160.10.2	Optical fiber connection.....	139
160.10.2.1	Connection insertion loss.....	139
160.10.2.2	Maximum discrete reflectance.....	139
160.10.3	Medium Dependent Interface (MDI) requirements	139
160.11	Requirements for interoperation between 50GBASE-BRx PMDs.....	140
160.12	Protocol implementation conformance statement (PICS) proforma for Clause 160, Physical Medium Dependent (PMD) sublayer and medium, types 50GBASE-BR10, 50GBASE-BR20, and 50GBASE-BR40	141
160.12.1	Introduction	141
160.12.2	Identification	141
160.12.2.1	Implementation identification.....	141
160.12.2.2	Protocol summary.....	141
160.12.3	Major capabilities/options	142

160.12.3.1	PICS proforma tables for PMD sublayer and medium, types 50GBASE-BR10, 50GBASE-BR20, and 50GBASE-BR40 PMD functional specifications	142
160.12.3.2	Management functions	143
160.12.3.3	PMD to MDI optical specifications for 50GBASE-BR10	144
160.12.3.4	PMD to MDI optical specifications for 50GBASE-BR20	144
160.12.3.5	PMD to MDI optical specifications for 50GBASE-BR40	144
160.12.3.6	Optical measurement methods.....	144
160.12.3.7	Environmental specifications	145
160.12.3.8	Characteristics of the fiber optic cabling and MDI	145

IEEE Standard for Ethernet

Amendment 14: Bidirectional 10 Gb/s, 25 Gb/s, and 50 Gb/s Optical Access PHYs

(This amendment is based on IEEE Std 802.3™-2018 as amended by IEEE Std 802.3cb™-2018, IEEE Std 802.3bt™-2018, IEEE Std 802.3cd™-2018, IEEE Std 802.3cn™-2019, IEEE Std 802.3cg™-2019, IEEE Std 802.3cq™-2020, IEEE Std 802.3cm™-2020, IEEE Std 802.3ch™-2020, IEEE Std 802.3ca™-2020, IEEE Std 802.3cr™-2021, IEEE Std 802.3cu™-2021, IEEE Std 802.3cv™-2021, and IEEE Std 802.3ct™-2021.)

NOTE—The editing instructions contained in this amendment define how to merge the material contained therein into the existing base standard and its amendments to form the comprehensive standard.

The editing instructions are shown in ***bold italic***. Four editing instructions are used: change, delete, insert, and replace. ***Change*** is used to make corrections in existing text or tables. The editing instruction specifies the location of the change and describes what is being changed by using ~~strike through~~ (to remove old material) and underscore (to add new material). ***Delete*** removes existing material. ***Insert*** adds new material without disturbing the existing material. Deletions and insertions may require renumbering. If so, renumbering instructions are given in the editing instruction. ***Replace*** is used to make changes in figures or equations by removing the existing figure or equation and replacing it with a new one. Editing instructions, change markings, and this NOTE will not be carried over into future editions because the changes will be incorporated into the base standard.

Cross references that refer to clauses, tables, equations, or figures not covered by this amendment are highlighted in green.¹

¹ Notes in text, tables, and figures are given for information only and do not contain requirements needed to implement the standard.

1. Introduction

1.4 Definitions

Insert the following three new definitions after 1.4.52 “10BROAD36”:

1.4.52a 10GBASE-BR10: IEEE 802.3 Physical Layer specification for a 10 Gb/s bidirectional link over one single-mode fiber with reach up to at least 10 km. There are different specifications for 10GBASE-BR10-D and 10GBASE-BR10-U; a transmission path connects one to the other. (See IEEE Std 802.3, Clause 158.)

1.4.52b 10GBASE-BR20: IEEE 802.3 Physical Layer specification for a 10 Gb/s bidirectional link over one single-mode fiber with reach up to at least 20 km. There are different specifications for 10GBASE-BR20-D and 10GBASE-BR20-U; a transmission path connects one to the other. (See IEEE Std 802.3, Clause 158.)

1.4.52c 10GBASE-BR40: IEEE 802.3 Physical Layer specification for a 10 Gb/s bidirectional link over one single-mode fiber with reach up to at least 40 km. There are different specifications for 10GBASE-BR40-D and 10GBASE-BR40-U; a transmission path connects one to the other. (See IEEE Std 802.3, Clause 158.)

Insert the following three new definitions after 1.4.91 “25GBASE”:

1.4.91a 25GBASE-BR10: IEEE 802.3 Physical Layer specification for a 25 Gb/s bidirectional link over one single-mode fiber with reach up to at least 10 km. There are different specifications for 25GBASE-BR10-D and 25GBASE-BR10-U; a transmission path connects one to the other. (See IEEE Std 802.3, Clause 159.)

1.4.91b 25GBASE-BR20: IEEE 802.3 Physical Layer specification for a 25 Gb/s bidirectional link over one single-mode fiber with reach up to at least 20 km. There are different specifications for 25GBASE-BR20-D and 25GBASE-BR20-U; a transmission path connects one to the other. (See IEEE Std 802.3, Clause 159.)

1.4.91c 25GBASE-BR40: IEEE 802.3 Physical Layer specification for a 25 Gb/s bidirectional link over one single-mode fiber with reach up to at least 40 km. There are different specifications for 25GBASE-BR40-D and 25GBASE-BR40-U; a transmission path connects one to the other. (See IEEE Std 802.3, Clause 159.)

Insert the following three new definitions after 1.4.128aac “50/50G-EPON” as inserted by IEEE Std 802.3ca-2020:

1.4.128aad 50GBASE-BR10: IEEE 802.3 Physical Layer specification for a 50 Gb/s bidirectional link over one single-mode fiber with reach up to at least 10 km. There are different specifications for 50GBASE-BR10-D and 50GBASE-BR10-U; a transmission path connects one to the other. (See IEEE Std 802.3 Clause 160.)

1.4.128aae 50GBASE-BR20: IEEE 802.3 Physical Layer specification for a 50 Gb/s bidirectional link over one single-mode fiber with reach up to at least 20 km. There are different specifications for 50GBASE-BR20-D and 50GBASE-BR20-U; a transmission path connects one to the other. (See IEEE Std 802.3, Clause 160.)

1.4.128aaf 50GBASE-BR40: IEEE 802.3 Physical Layer specification for a 50 Gb/s bidirectional link over one single-mode fiber with reach up to at least 40 km. There are different specifications for 50GBASE-BR40-D and 50GBASE-BR40-U; a transmission path connects one to the other. (See IEEE Std 802.3, Clause 160.)

1.5 Abbreviations

Insert the following new abbreviation into the list in 1.5, in alphanumeric order:

BiDi	bidirectional
------	---------------

30. Management

30.5 Layer management for medium attachment units (MAUs)

30.5.1 MAU managed object class

30.5.1.1 MAU attributes

30.5.1.1.2 aMAUType

Insert the following new types into the “APPROPRIATE SYNTAX” section of 30.5.1.1.2 after 10GBASE-T1 (as inserted by IEEE Std 802.3ch-2020) as follows:

APPROPRIATE SYNTAX:

...

10GBASE-BR10-D	One single-mode fiber OLT PHY supporting a distance of at least 10 km as specified in Clause 158
10GBASE-BR10-U	One single-mode fiber ONU PHY supporting a distance of at least 10 km as specified in Clause 158
10GBASE-BR20-D	One single-mode fiber OLT PHY supporting a distance of at least 20 km as specified in Clause 158
10GBASE-BR20-U	One single-mode fiber ONU PHY supporting a distance of at least 20 km as specified in Clause 158
10GBASE-BR40-D	One single-mode fiber OLT PHY supporting a distance of at least 40 km as specified in Clause 158
10GBASE-BR40-U	One single-mode fiber ONU PHY supporting a distance of at least 40 km as specified in Clause 158

...

Insert the following new types into the “APPROPRIATE SYNTAX” section of 30.5.1.1.2 after 25GBASE-T as follows:

APPROPRIATE SYNTAX:

...

25GBASE-BR10-D	One single-mode fiber OLT PHY supporting a distance of at least 10 km as specified in Clause 159
25GBASE-BR10-U	One single-mode fiber ONU PHY supporting a distance of at least 10 km as specified in Clause 159
25GBASE-BR20-D	One single-mode fiber OLT PHY supporting a distance of at least 20 km as specified in Clause 159
25GBASE-BR20-U	One single-mode fiber ONU PHY supporting a distance of at least 20 km as specified in Clause 159
25GBASE-BR40-D	One single-mode fiber OLT PHY supporting a distance of at least 40 km as specified in Clause 159
25GBASE-BR40-U	One single-mode fiber ONU PHY supporting a distance of at least 40 km as specified in Clause 159

...

Insert the following new types into the “APPROPRIATE SYNTAX” section of 30.5.1.1.2 after 50GBASE-ER (as inserted by IEEE Std 802.3cn-2019) as follows:

APPROPRIATE SYNTAX:

...	
50GBASE-BR10-D	One single-mode fiber OLT PHY supporting a distance of at least 10 km as specified in Clause 160
50GBASE-BR10-U	One single-mode fiber ONU PHY supporting a distance of at least 10 km as specified in Clause 160
50GBASE-BR20-D	One single-mode fiber OLT PHY supporting a distance of at least 20 km as specified in Clause 160
50GBASE-BR20-U	One single-mode fiber ONU PHY supporting a distance of at least 20 km as specified in Clause 160
50GBASE-BR40-D	One single-mode fiber OLT PHY supporting a distance of at least 40 km as specified in Clause 160
50GBASE-BR40-U	One single-mode fiber ONU PHY supporting a distance of at least 40 km as specified in Clause 160
...	

Change the first paragraph of the “BEHAVIOUR DEFINED AS” section of 30.5.1.1.2 as follows:

BEHAVIOUR DEFINED AS:

Returns a value that identifies the internal MAU type. If an AUI is to be identified to access an external MAU, the type “AUI” is returned. A SET operation to one of the possible enumerations indicated by aMAUTypeList will force the MAU into the new operating mode. If a [Clause 22](#) MII or [Clause 35](#) GMII is present, then this will map to the mode force bits specified in [22.2.4.1](#). If a Clause 45 MDIO Interface is present, then this will map to the PCS type selection bit(s) in the 10G WIS Control 2 register specified in [45.2.2.6.6](#), the PCS Control 2 register specified in [45.2.3.6.1](#), the PMA/PMD type selection bits in the PMA/PMD Control 2 register specified in [45.2.1.6](#), the PMA/PMD control 1 register specified in [45.2.1.1](#), the ~~25G~~ RS-FEC Enable bit in the RS-FEC control register specified in [45.2.1.110.1](#), and the PCS control 1 register [45.2.3.1](#). If [Clause 28](#), [Clause 37](#), or [Clause 73](#) Auto-Negotiation is operational, then this will change the advertised ability to the single enumeration specified in the SET operation, and cause an immediate link renegotiation. A change in the MAU type will also be reflected in aPHYType.

30.5.1.1.16 aFECmode

Change the last paragraph of the “BEHAVIOUR DEFINED AS” section of 30.5.1.1.16 as follows:

BEHAVIOUR DEFINED AS:

...

If a Clause 45 MDIO Interface is present, then this attribute maps to the FEC control register (see [45.2.10.3](#)) for 1000BASE-PX, to the BASE-R FEC control register (see [45.2.1.102](#)) and the ~~25G~~ RS-FEC Enable bit in the RS-FEC control register (see [45.2.1.110](#)) for 10GBASE-R and 25GBASE-R, or FEC enable bit in the BASE-R FEC control register (see [45.2.1.102](#)).;

44. Introduction to 10 Gb/s baseband network

44.3 Delay constraints

Insert a new row at the end of Table 44–2, as modified by IEEE Std 802.3ch-2020, as follows (unchanged rows not shown):

Table 44–2—Round-trip delay constraints (informative)

Sublayer	Maximum (bit time)	Maximum (pause_quanta)	Notes
...			
10GBASE-BRx RS-FEC	24 576	48	See 108.4.

45. Management Data Input/Output (MDIO) Interface

45.2 MDIO Interface Registers

45.2.1 PMA/PMD registers

Change the row for registers 1.34 and 1.35 in Table 45–3 as follows (unchanged rows not shown):

Table 45–3—PMA/PMD registers

Register address	Register name	Subclause
...		
1.34, 1.35	BiDi PMA/PMD extended ability 1 ~~Reserved~~	45.2.1.27a
1.35	BiDi PMA/PMD extended ability 2	45.2.1.27b
...		

45.2.1.6 PMA/PMD control 2 register (Register 1.7)

Change the indicated reserved rows of Table 45–7 (as inserted by IEEE Std 802.3cn-2019) as follows (unchanged table rows and bit description lines not shown):

Table 45–7—PMA/PMD control 2 register bit definitions

Bit(s)	Name	Description	R/W ^a
...			
1.7.6:0	PMA/PMD type selection	6 5 4 3 2 1 0 <u>1 1 1 x x x x = reserved</u> <u>1 1 1 1 1 x x = reserved</u> <u>1 1 1 0 1 x = reserved</u> <u>1 1 1 0 0 1 = reserved</u> <u>1 1 1 0 0 0 = 50GBASE-BR40-U PMA/PMD</u> <u>1 1 1 0 1 1 1 = 50GBASE-BR20-U PMA/PMD</u> <u>1 1 1 0 1 1 0 = 50GBASE-BR10-U PMA/PMD</u> <u>1 1 1 0 1 0 1 = 50GBASE-BR40-D PMA/PMD</u> <u>1 1 1 0 1 0 0 = 50GBASE-BR20-D PMA/PMD</u> <u>1 1 1 0 0 1 1 = 50GBASE-BR10-D PMA/PMD</u> <u>1 1 1 0 0 1 0 = 25GBASE-BR40-U PMA/PMD</u> <u>1 1 1 0 0 0 1 = 25GBASE-BR20-U PMA/PMD</u> <u>1 1 1 0 0 0 0 = 25GBASE-BR10-U PMA/PMD</u> <u>1 1 0 1 x x x = reserved</u> <u>1 1 0 1 1 1 1 = 25GBASE-BR40-D PMA/PMD</u> <u>1 1 0 1 1 1 0 = 25GBASE-BR20-D PMA/PMD</u> <u>1 1 0 1 1 0 1 = 25GBASE-BR10-D PMA/PMD</u> <u>1 1 0 1 1 0 0 = 10GBASE-BR40-U PMA/PMD</u> <u>1 1 0 1 0 1 1 = 10GBASE-BR20-U PMA/PMD</u> <u>1 1 0 1 0 1 0 = 10GBASE-BR10-U PMA/PMD</u> <u>1 1 0 1 0 0 1 = 10GBASE-BR40-D PMA/PMD</u> <u>1 1 0 1 0 0 0 = 10GBASE-BR20-D PMA/PMD</u> <u>1 1 0 0 1 x x = reserved</u> <u>1 1 0 0 1 1 1 = 10GBASE-BR10-D PMA/PMD</u> <u>1 1 0 0 1 1 0 = reserved</u> <u>1 1 0 0 1 0 x = reserved</u> ...	R/W

^aR/W = Read/Write, RO = Read only

45.2.1.7 PMA/PMD status 2 register (Register 1.8)**45.2.1.7.4 Transmit fault (1.8.11)**

Insert a new row in Table 45–9 after the row for “5GBASE-KR” (as inserted by IEEE Std 802.3cb-2018) as follows (unchanged rows not shown):

Table 45–9—Transmit fault description location

PMA/PMD	Description location
...	
10GBASE-BR10, 10GBASE-BR20, 10GBASE-BR40	158.5.8
...	

Insert a new row in Table 45–9 after the row for “25GBASE-LR, 25GBASE-ER” as follows (unchanged rows not shown):

Table 45–9—Transmit fault description location

PMA/PMD	Description location
...	
25GBASE-BR10, 25GBASE-BR20, 25GBASE-BR40	159.5.8
...	

Insert a new row in Table 45–9 after the row for “50GBASE-FR, 50GBASE-LR, 50GBASE-ER” (as changed by IEEE Std 802.3cn-2019) as follows (unchanged rows not shown):

Table 45–9—Transmit fault description location

PMA/PMD	Description location
...	
50GBASE-BR10, 50GBASE-BR20, 50GBASE-BR40	160.5.8
...	

45.2.1.7.5 Receive fault (1.8.10)

Insert a new row in Table 45–10 after the row for “5GBASE-KR” (as inserted by IEEE Std 802.3cb-2018) as follows (unchanged rows not shown):

Table 45–10—Receive fault description location

PMA/PMD	Description location
...	
10GBASE-BR10, 10GBASE-BR20, 10GBASE-BR40	158.5.9
...	

Insert a new row in Table 45–10 after the row for “25GBASE-LR, 25GBASE-ER” as follows (unchanged rows not shown):

Table 45–10—Receive fault description location

PMA/PMD	Description location
...	
25GBASE-BR10, 25GBASE-BR20, 25GBASE-BR40	159.5.9
...	

Insert a new row in Table 45–9 after the row for “50GBASE-FR, 50GBASE-LR, 50GBASE-ER” (as changed by IEEE Std 802.3cn-2019) as follows (unchanged rows not shown):

Table 45–10—Receive fault description location

PMA/PMD	Description location
...	
50GBASE-BR10, 50GBASE-BR20, 50GBASE-BR40	160.5.9
...	

45.2.1.8 PMD transmit disable register (Register 1.9)

Insert a new row in Table 45–12 after the row for “5GBASE-KR” (as inserted by IEEE Std 802.3cb-2018) as follows (unchanged rows not shown):

Table 45–12—Transmit disable description location

PMA/PMD	Description location
...	
10GBASE-BR10, 10GBASE-BR20, and 10GBASE-BR40	158.5.6
...	

Insert a new row in Table 45–12 after the row for “25GBASE-LR and 25GBASE-ER” as follows (unchanged rows not shown):

Table 45–12—Transmit disable description location

PMA/PMD	Description location
...	
25GBASE-BR10, 25GBASE-BR20, and 25GBASE-BR40	159.5.6
...	

Insert a new row in Table 45–12 after the row for “50GBASE-FR, 50GBASE-LR, and 50GBASE-ER” (as changed by IEEE Std 802.3cn-2019) as follows (unchanged rows not shown):

Table 45–12—Transmit disable description location

PMA/PMD	Description location
...	
50GBASE-BR10, 50GBASE-BR20, and 50GBASE-BR40	160.5.6
...	

Insert new subclauses 45.2.1.27a and 45.2.1.27b after 45.2.1.27 as follows:

45.2.1.27a BiDi PMA/PMD extended ability 1 (Register 1.34)

The assignment of bits in the BiDi PMA/PMD extended ability 1 register is shown in Table 45–31a.

Table 45–31a—BiDi PMA/PMD extended ability 1 register bit definitions

Bit(s)	Name	Description	R/W ^a
1.34.15:12	Reserved	Value always 0	RO
1.34.11	25GBASE-BR40-U ability	1 = PMA/PMD is able to perform 25GBASE-BR40-U 0 = PMA/PMD is not able to perform 25GBASE-BR40-U	RO
1.34.10	25GBASE-BR40-D ability	1 = PMA/PMD is able to perform 25GBASE-BR40-D 0 = PMA/PMD is not able to perform 25GBASE-BR40-D	RO
1.34.9	25GBASE-BR20-U ability	1 = PMA/PMD is able to perform 25GBASE-BR20-U 0 = PMA/PMD is not able to perform 25GBASE-BR20-U	RO
1.34.8	25GBASE-BR20-D ability	1 = PMA/PMD is able to perform 25GBASE-BR20-D 0 = PMA/PMD is not able to perform 25GBASE-BR20-D	RO
1.34.7	25GBASE-BR10-U ability	1 = PMA/PMD is able to perform 25GBASE-BR10-U 0 = PMA/PMD is not able to perform 25GBASE-BR10-U	RO
1.34.6	25GBASE-BR10-D ability	1 = PMA/PMD is able to perform 25GBASE-BR10-D 0 = PMA/PMD is not able to perform 25GBASE-BR10-D	RO
1.34.5	10GBASE-BR40-U ability	1 = PMA/PMD is able to perform 10GBASE-BR40-U 0 = PMA/PMD is not able to perform 10GBASE-BR40-U	RO
1.34.4	10GBASE-BR40-D ability	1 = PMA/PMD is able to perform 10GBASE-BR40-D 0 = PMA/PMD is not able to perform 10GBASE-BR40-D	RO
1.34.3	10GBASE-BR20-U ability	1 = PMA/PMD is able to perform 10GBASE-BR20-U 0 = PMA/PMD is not able to perform 10GBASE-BR20-U	RO
1.34.2	10GBASE-BR20-D ability	1 = PMA/PMD is able to perform 10GBASE-BR20-D 0 = PMA/PMD is not able to perform 10GBASE-BR20-D	RO
1.34.1	10GBASE-BR10-U ability	1 = PMA/PMD is able to perform 10GBASE-BR10-U 0 = PMA/PMD is not able to perform 10GBASE-BR10-U	RO
1.34.0	10GBASE-BR10-D ability	1 = PMA/PMD is able to perform 10GBASE-BR10-D 0 = PMA/PMD is not able to perform 10GBASE-BR10-D	RO

^aRO = Read only

45.2.1.27a.1 25GBASE-BR40-U ability (1.34.11)

When read as a one, bit 1.34.11 indicates that the PMA/PMD is able to operate as a 25GBASE-BR40-U PMA/PMD type. When read as a zero, bit 1.34.11 indicates that the PMA/PMD is not able to operate as a 25GBASE-BR40-U PMA/PMD type.

45.2.1.27a.2 25GBASE-BR40-D ability (1.34.10)

When read as a one, bit 1.34.10 indicates that the PMA/PMD is able to operate as a 25GBASE-BR40-D PMA/PMD type. When read as a zero, bit 1.34.10 indicates that the PMA/PMD is not able to operate as a 25GBASE-BR40-D PMA/PMD type.

45.2.1.27a.3 25GBASE-BR20-U ability (1.34.9)

When read as a one, bit 1.34.9 indicates that the PMA/PMD is able to operate as a 25GBASE-BR20-U PMA/PMD type. When read as a zero, bit 1.34.9 indicates that the PMA/PMD is not able to operate as a 25GBASE-BR20-U PMA/PMD type.

45.2.1.27a.4 25GBASE-BR20-D ability (1.34.8)

When read as a one, bit 1.34.8 indicates that the PMA/PMD is able to operate as a 25GBASE-BR20-D PMA/PMD type. When read as a zero, bit 1.34.8 indicates that the PMA/PMD is not able to operate as a 25GBASE-BR20-D PMA/PMD type.

45.2.1.27a.5 25GBASE-BR10-U ability (1.34.7)

When read as a one, bit 1.34.7 indicates that the PMA/PMD is able to operate as a 25GBASE-BR10-U PMA/PMD type. When read as a zero, bit 1.34.7 indicates that the PMA/PMD is not able to operate as a 25GBASE-BR10-U PMA/PMD type.

45.2.1.27a.6 25GBASE-BR10-D ability (1.34.6)

When read as a one, bit 1.34.6 indicates that the PMA/PMD is able to operate as a 25GBASE-BR10-D PMA/PMD type. When read as a zero, bit 1.34.6 indicates that the PMA/PMD is not able to operate as a 25GBASE-BR10-D PMA/PMD type.

45.2.1.27a.7 10GBASE-BR40-U ability (1.34.5)

When read as a one, bit 1.34.5 indicates that the PMA/PMD is able to operate as a 10GBASE-BR40-U PMA/PMD type. When read as a zero, bit 1.34.5 indicates that the PMA/PMD is not able to operate as a 10GBASE-BR40-U PMA/PMD type.

45.2.1.27a.8 10GBASE-BR40-D ability (1.34.4)

When read as a one, bit 1.34.4 indicates that the PMA/PMD is able to operate as a 10GBASE-BR40-D PMA/PMD type. When read as a zero, bit 1.34.4 indicates that the PMA/PMD is not able to operate as a 10GBASE-BR40-D PMA/PMD type.

45.2.1.27a.9 10GBASE-BR20-U ability (1.34.3)

When read as a one, bit 1.34.3 indicates that the PMA/PMD is able to operate as a 10GBASE-BR20-U PMA/PMD type. When read as a zero, bit 1.34.3 indicates that the PMA/PMD is not able to operate as a 10GBASE-BR20-U PMA/PMD type.

45.2.1.27a.10 10GBASE-BR20-D ability (1.34.2)

When read as a one, bit 1.34.2 indicates that the PMA/PMD is able to operate as a 10GBASE-BR20-D PMA/PMD type. When read as a zero, bit 1.34.2 indicates that the PMA/PMD is not able to operate as a 10GBASE-BR20-D PMA/PMD type.

45.2.1.27a.11 10GBASE-BR10-U ability (1.34.1)

When read as a one, bit 1.34.1 indicates that the PMA/PMD is able to operate as a 10GBASE-BR10-U PMA/PMD type. When read as a zero, bit 1.34.1 indicates that the PMA/PMD is not able to operate as a 10GBASE-BR10-U PMA/PMD type.

45.2.1.27a.12 10GBASE-BR10-D ability (1.34.0)

When read as a one, bit 1.34.0 indicates that the PMA/PMD is able to operate as a 10GBASE-BR10-D PMA/PMD type. When read as a zero, bit 1.34.0 indicates that the PMA/PMD is not able to operate as a 10GBASE-BR10-D PMA/PMD type.

45.2.1.27b BiDi PMA/PMD extended ability 2 (Register 1.35)

The assignment of bits in the BiDi PMA/PMD extended ability 2 register is shown in Table 45–31b.

Table 45–31b—BiDi PMA/PMD extended ability 2 register bit definitions

Bit(s)	Name	Description	R/W ^a
1.35.15:6	Reserved	Value always 0	RO
1.35.5	50GBASE-BR40-U ability	1 = PMA/PMD is able to perform 50GBASE-BR40-U 0 = PMA/PMD is not able to perform 50GBASE-BR40-U	RO
1.35.4	50GBASE-BR40-D ability	1 = PMA/PMD is able to perform 50GBASE-BR40-D 0 = PMA/PMD is not able to perform 50GBASE-BR40-D	RO
1.35.3	50GBASE-BR20-U ability	1 = PMA/PMD is able to perform 50GBASE-BR20-U 0 = PMA/PMD is not able to perform 50GBASE-BR20-U	RO
1.35.2	50GBASE-BR20-D ability	1 = PMA/PMD is able to perform 50GBASE-BR20-D 0 = PMA/PMD is not able to perform 50GBASE-BR20-D	RO
1.35.1	50GBASE-BR10-U ability	1 = PMA/PMD is able to perform 50GBASE-BR10-U 0 = PMA/PMD is not able to perform 50GBASE-BR10-U	RO
1.35.0	50GBASE-BR10-D ability	1 = PMA/PMD is able to perform 50GBASE-BR10-D 0 = PMA/PMD is not able to perform 50GBASE-BR10-D	RO

^aRO = Read only

45.2.1.27b.1 50GBASE-BR40-U ability (1.35.5)

When read as a one, bit 1.35.5 indicates that the PMA/PMD is able to operate as a 50GBASE-BR40-U PMA/PMD type. When read as a zero, bit 1.35.5 indicates that the PMA/PMD is not able to operate as a 50GBASE-BR40-U PMA/PMD type.

45.2.1.27b.2 50GBASE-BR40-D ability (1.35.4)

When read as a one, bit 1.35.4 indicates that the PMA/PMD is able to operate as a 50GBASE-BR40-D PMA/PMD type. When read as a zero, bit 1.35.4 indicates that the PMA/PMD is not able to operate as a 50GBASE-BR40-D PMA/PMD type.

45.2.1.27b.3 50GBASE-BR20-U ability (1.35.3)

When read as a one, bit 1.35.3 indicates that the PMA/PMD is able to operate as a 50GBASE-BR20-U PMA/PMD type. When read as a zero, bit 1.35.3 indicates that the PMA/PMD is not able to operate as a 50GBASE-BR20-U PMA/PMD type.

45.2.1.27b.4 50GBASE-BR20-D ability (1.35.2)

When read as a one, bit 1.35.2 indicates that the PMA/PMD is able to operate as a 50GBASE-BR20-D PMA/PMD type. When read as a zero, bit 1.35.2 indicates that the PMA/PMD is not able to operate as a 50GBASE-BR20-D PMA/PMD type.

45.2.1.27b.5 50GBASE-BR10-U ability (1.35.1)

When read as a one, bit 1.35.1 indicates that the PMA/PMD is able to operate as a 50GBASE-BR10-U PMA/PMD type. When read as a zero, bit 1.35.1 indicates that the PMA/PMD is not able to operate as a 50GBASE-BR10-U PMA/PMD type.

45.2.1.27b.6 50GBASE-BR10-D ability (1.35.0)

When read as a one, bit 1.35.0 indicates that the PMA/PMD is able to operate as a 50GBASE-BR10-D PMA/PMD type. When read as a zero, bit 1.35.0 indicates that the PMA/PMD is not able to operate as a 50GBASE-BR10-D PMA/PMD type.

45.2.1.110 RS-FEC control register (Register 1.200)

Change the row for bit 1.200.2 in Table 45–88 as follows (unchanged rows not shown):

Table 45–88—RS-FEC control register bit definitions

Bit(s)	Name	Description	R/W ^a
1.200.2	~~25G~~ RS-FEC Enable	1 = ~~The 25GBASE-R Clause 108~~ Reed-Solomon FEC is enabled 0 = ~~The 25GBASE-R Clause 108~~ Reed-Solomon FEC is disabled	R/W

^aR/W = Read/Write, RO = Read only

Change the title and content of 45.2.1.110.1 as follows:

45.2.1.110.1 ~~25G~~RS-FEC enable (1.200.2)

Bit 1.200.2 enables the ~~25GBASE-R~~ Reed-Solomon FEC described in Clause 108. When set to a one, this bit enables the ~~25GBASE-R~~ Reed-Solomon FEC. When set to a zero, bit 1.200.2 disables the ~~25GBASE-R~~ Reed-Solomon FEC (see 108.6.3). Writes to bit 1.200.2 are ignored and reads return a one if the RS-FEC does not have the ability to disable the RS-FEC function.

49. Physical Coding Sublayer (PCS) for 64B/66B, type 10GBASE-R

49.2 Physical Coding Sublayer (PCS)

49.2.2 Functions within the PCS

Change the second to fifth paragraphs of 49.2.2 as follows:

When communicating with the XGMII, the PCS uses a four octet-wide, synchronous data path, with packet delimiting being provided by transmit control signals (TXCn = 1) and receive control signals (RXCn = 1). When communicating with the PMA, ~~or~~ WIS, ~~or~~ FEC, the PCS uses a 16-bit wide, synchronous data path that conveys 16 encoded bits. Alignment to 64B/66B block is performed in the PCS. The WIS, ~~and~~ PMA, ~~and~~ FEC sublayers operate independent of block and packet boundaries. The PCS provides the functions necessary to map packets between the XGMII format and the PMA service interface format.

When the transmit channel is in normal mode, the PCS Transmit process continuously generates blocks based upon the TXD <31:0> and TXC <3:0> signals on the XGMII. The Gearbox function of the PCS Transmit process then packs the resulting bits into 16-bit transmit data-units. Transmit data-units are sent to the PMA, ~~or~~ WIS, ~~or~~ FEC service interface via the PMA_UNITDATA.request, ~~or~~ WIS_UNITDATA.request, ~~or~~ FEC_UNITDATA.request primitive, respectively. When the WIS is present, the PCS Transmit process also adapts between the XGMII and WIS data rates by deleting idle characters.

When the transmit channel is in test-pattern mode, a test pattern is packed into the transmit data-units that are sent to the PMA service interface via the PMA_UNITDATA.request primitive.

When the receive channel is in normal mode, the PCS Synchronization process continuously monitors PMA_SIGNAL.indication(SIGNAL_OK), ~~or~~ WIS_SIGNAL.indication(SIGNAL_OK), ~~or~~ FEC_SIGNAL.indication(SIGNAL_OK). When SIGNAL_OK indicates OK, then the PCS Synchronization process accepts data-units via the PMA_UNITDATA.indication primitive, ~~or~~ the WIS_UNITDATA.indication primitive, ~~or~~ the FEC_UNITDATA.indication primitive. It attains block synchronization based on the 2-bit synchronization headers and conveys received blocks to the PCS Receive process. The PCS Synchronization process sets the sync_status flag to indicate whether the PCS has obtained synchronization.

49.2.13.2.2 Variables

Change the definition of the “signal_ok” variable in 49.2.13.2.2 as follows:

signal_ok

Boolean variable that is set based on the most recently received value of PMA_SIGNAL.indication(SIGNAL_OK), ~~or~~ WIS_SIGNAL.indication(SIGNAL_OK), ~~or~~ FEC_SIGNAL.indication(SIGNAL_OK). It is true if the value was OK and false if the value was FAIL.

56. Introduction to Ethernet for subscriber access networks

56.1 Overview

Change the second paragraph of 56.1 (as modified by IEEE Std 802.3ca-2020) splitting it into two paragraphs as follows:

In addition, a mechanism for network Operations, Administration, and Maintenance (OAM) is included to facilitate network operation and troubleshooting. ~~100BASE-LX10 extends the reach of 100BASE-X to achieve 10 km over conventional single mode two fiber cabling.~~

The relationships between these EFM elements and the ISO/IEC Open System Interconnection (OSI) reference model are shown in Figure 56–1 and Figure 56–1a for point-to-point topologies, Figure 56–2 for 1G-EPON topologies, Figure 56–3 for 10/10G-EPON topologies, Figure 56–4 for 10/1G-EPON topologies, Figure 56–5 for EPoC topologies, and Figure 56–6 for Nx25G-EPON topologies.

Insert new Figure 56–1a after Figure 56–1 as follows:




Figure 56–1a—Architectural positioning of EFM: higher rate P2P topologies

Change 56.1.1 as follows. Note that footnotes 2 and 3 are deleted.

56.1.1 Summary of P2P sublayers

EFM P2P supports operation at several different bit rates, depending on the characteristics of the underlying medium. ~~In the case of point-to-point optical fiber media, bit rates of 100 Mb/s and 1000 Mb/s are supported, using the 100BASE-X and 1000BASE-X Physical Coding Sublayer (PCS) and Physical Medium Attachment (PMA) sublayers defined in 66.1 and 66.2, respectively. In the case of point-to-point copper, EFM supports a variety of bit rates, depending on the span and the signal-to-noise ratio (SNR) characteristics of the medium as described in Clause 61 through Clause 63. 2BASE-TL supports a nominal bit rate of 2 Mb/s at a nominal reach of 2700 meters.² 10PASS-TS supports a nominal bit rate of 10 Mb/s at a nominal reach of 750 meters.³~~

Insert new subclauses 56.1.1.1 and 56.1.1.2 at the end of 56.1.1 as follows:

56.1.1.1 P2P fiber media

The 100BASE-X Physical Coding Sublayer (PCS) and Physical Medium Attachment (PMA) sublayers are used to support a bit rate of 100 Mb/s as defined in 66.1. 100BASE-LX10 extends the reach of 100BASE-X to achieve 10 km over conventional single-mode two-fiber cabling.

The 1000BASE-X PCS and PMA sublayers are used to support a bit rate of 1000 Mb/s as defined in 66.2.

The 10GBASE-R PCS, RS-FEC, and PMA sublayers are used to support a bit rate of 10 Gb/s as defined in Clause 158.

The 25GBASE-R PCS, RS-FEC, and PMA sublayers are used to support a bit rate of 25 Gb/s as defined in Clause 159.

The 50GBASE-R PCS, RS-FEC, and PMA sublayers are used to support a bit rate of 50 Gb/s as defined in Clause 160.

56.1.1.2 P2P copper media

The P2P copper links support a variety of bit rates, depending on the span and the signal-to-noise ratio (SNR) characteristics of the medium as described in Clause 61 and Clause 63.

The 2BASE-TL P2P link supports a nominal bit rate of 2 Mb/s at a nominal reach of 2700 meters (see Annex 63B for a more detailed discussion of bit rates and reach).

The 10PASS-TS P2P link supports a nominal bit rate of 10 Mb/s at a nominal reach of 750 meters (see Annex 62B for a more detailed discussion of bit rates and reach).

56.1.2 Summary of P2MP sublayers

56.1.2.2 Reconciliation Sublayer (RS) and media independent interfaces

Change the first sentence of 56.1.2.2 as follows:

The Clause 22 RS and MII, Clause 35 RS and GMII, ~~and Clause 46 RS and XGMII, Clause 106 RS and 25GMII, and Clause 132 RS and 50GMII~~ are all employed for the same purpose in EFM, that being the interconnection between the MAC sublayer and the PHY sublayers.

²Refer to Annex 63B for a more detailed discussion of bit rates and reach.

³Refer to Annex 62B for a more detailed discussion of bit rates and reach.

56.1.3 Physical Layer signaling systems

Insert the following text below the second paragraph of 56.1.3:

EFM extends the family of 10GBASE-R Physical Layer signaling systems to include the following combinations of bidirectional PMDs defined in Clause 158:

- 10GBASE-BR10-D and 10GBASE-BR10-U
- 10GBASE-BR20-D and 10GBASE-BR20-U
- 10GBASE-BR40-D and 10GBASE-BR40-U

EFM extends the family of 25GBASE-R Physical Layer signaling systems to include the following combinations of bidirectional PMDs defined in Clause 159:

- 25GBASE-BR10-D and 25GBASE-BR10-U
- 25GBASE-BR20-D and 25GBASE-BR20-U
- 25GBASE-BR40-D and 25GBASE-BR40-U

EFM extends the family of 50GBASE-R Physical Layer signaling systems to include the following combinations of bidirectional PMDs defined in Clause 160:

- 50GBASE-BR10-D and 50GBASE-BR10-U
- 50GBASE-BR20-D and 50GBASE-BR20-U
- 50GBASE-BR40-D and 50GBASE-BR40-U

Insert new rows into Table 56–1 and change table footnote a (as modified by IEEE Std 802.3ca-2020) after the row for “1000BASE-BX10-U” as follows (unchanged rows not shown):

Table 56–1—Summary of EFM Physical Layer signaling systems

Name	Location	Rate ^a	Nominal reach (km)	Medium	Clause
...					
10GBASE-BR10-D	OLT	10 Gb/s	10	One single-mode fiber	158
10GBASE-BR10-U	ONU				
10GBASE-BR20-D	OLT				
10GBASE-BR20-U	ONU				
10GBASE-BR40-D	OLT				
10GBASE-BR40-U	ONU				
25GBASE-BR10-D	OLT	25 Gb/s	10	One single-mode fiber	159
25GBASE-BR10-U	ONU				
25GBASE-BR20-D	OLT				
25GBASE-BR20-U	ONU				
25GBASE-BR40-D	OLT				
25GBASE-BR40-U	ONU				
50GBASE-BR10-D	OLT	50 Gb/s	10	One single-mode fiber	160
50GBASE-BR10-U	ONU				
50GBASE-BR20-D	OLT				
50GBASE-BR20-U	ONU				
50GBASE-BR40-D	OLT				
50GBASE-BR40-U	ONU				
...					

^aFor Physical Layer signaling systems the transmit rate is denoted with the abbreviation “(tx)” to the location; whereas, the receive rate is denoted with the abbreviation “(rx)”.

Change Table 56–2 as follows reformatting header rows to accommodate added columns:

Table 56–2—Nomenclature and clause correlation for P2P systems

Nomenclature	Clause																					
	57	78	58		59		61	62	63	66		49	51	158	107	108	109	159	133	134	135	160
	OAM	EEE	100BASE-LX10 PMD	100BASE-BX10 PMD	1000BASE-LX10 PMD	1000BASE-BX10 PMD	Cu PCS	10PASS-TS PMA & PMD	2BASE-TL PMA & PMD	100BASE-X PCS, PMA	1000BASE-X PCS, PMA	10GBASE-R PCS	10GBASE-R PMA	10GBASE-BR _x PMD	25GBASE-R PCS	Reed-Solomon FEC	25GBASE-R PMA	25GBASE-BR _x PMD	50GBASE-R PCS	50GBASE-R RS-FEC	50GBASE-R PMA	50GBASE-BR _x PMD
2BASE-TL	O ^a						M		M													
10PASS-TS	O						M	M														
100BASE-LX10	O		M							M												
100BASE-BX10	O			M						M												
1000BASE-LX10	O				M						M											
1000BASE-BX10	O					M					M											
10GBASE-BR10	Q											M	M	M								
10GBASE-BR20	Q											M	M	M		M						
10GBASE-BR40	Q											M	M	M								
25GBASE-BR10	Q	Q													M	M	M	M				
25GBASE-BR20	Q	Q													M	M	M	M				
25GBASE-BR40	Q	Q													M	M	M	M				
50GBASE-BR10	Q	Q																	M	M	M	M
50GBASE-BR20	Q	Q																	M	M	M	M
50GBASE-BR40	Q	Q																	M	M	M	M

^aO = Optional, M = Mandatory