
**Information technology —
Telecommunications and information
exchange between systems — XML
Schema Definitions for Computer
Supported Telecommunications
Applications (CSTA) Phase III**

*Technologies de l'information — Téléinformatique — Définitions de
schéma XML pour applications en télécommunications supportées par
ordinateur (CSTA) en phase III*



Reference number
ISO/IEC 18056:2012(E)

AVA Documents
Document Sharing Hub
© ISO/IEC 2012

PDF disclaimer

This PDF file may contain embedded typefaces. In accordance with Adobe's licensing policy, this file may be printed or viewed but shall not be edited unless the typefaces which are embedded are licensed to and installed on the computer performing the editing. In downloading this file, parties accept therein the responsibility of not infringing Adobe's licensing policy. The ISO Central Secretariat accepts no liability in this area.

Adobe is a trademark of Adobe Systems Incorporated.

Details of the software products used to create this PDF file can be found in the General Info relative to the file; the PDF-creation parameters were optimized for printing. Every care has been taken to ensure that the file is suitable for use by ISO member bodies. In the unlikely event that a problem relating to it is found, please inform the Central Secretariat at the address given below.



COPYRIGHT PROTECTED DOCUMENT

© ISO/IEC 2012

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either ISO at the address below or ISO's member body in the country of the requester.

ISO copyright office
Case postale 56 • CH-1211 Geneva 20
Tel. + 41 22 749 01 11
Fax + 41 22 749 09 47
E-mail copyright@iso.org
Web www.iso.org

Published in Switzerland

Contents

Page

1 Scope	1
2 Conformance	1
2.1 Static Requirements	1
2.2 Dynamic Requirements	1
2.3 PICS Requirement	1
2.4 XML Tag Options	1
2.4.1 ISO/IEC 18056 (ECMA-323) Specified Tags	2
2.4.2 ISO/IEC 18056 (ECMA-323) Specified Short Tags	2
2.4.3 Dynamic Transformations	2
2.5 CSTA Over SIP (uaCSTA) Transport Mechanism Option	2
3 Normative references	2
3.1 ISO Standards and Technical Reports	2
3.2 World Wide Web Consortium Specifications	2
4 Terms, definitions and abbreviations	3
5 CSTA Service Definition Model	3
5.1 Request/Response Interactions	3
5.2 Request/Response Protocol Requirements	3
5.3 Cross Referencing of Event Reports	3
5.4 Handling of Private Data	3
6 Interconnection service boundary	4
7 Association Management	4
7.1 Implicit association	4
7.2 Explicit association	4
8 XML Template Description	5
9 CSTA parameter types	5
9.1 Switching function objects	5
9.2 Device Identifiers	6
9.3 Call and connection identifiers	9
9.4 Connection states	10
9.5 Status reporting	11
9.6 Device and feature types and other parameters	16
9.7 Security	25
9.8 Common extensions	26
9.9 Call control	27
9.10 Capability Exchange	31
9.11 Call Detail Record	98
9.12 Charge information	100
9.13 Data call types	101
9.14 Escape types	102
9.15 Media services	102
9.16 Physical device features	105
9.17 Data Collection	107
9.18 Event Cause	108
9.19 Error Value	110
9.20 Empty (null element)	115
10 Top level schema	115
11 Capability exchange services	121
11.1 Services	121
11.1.1 Get csta features	121

11.1.2 Get logical device information	122
11.1.3 Get physical device information	123
11.1.4 Get switching function capabilities	124
11.1.5 Get switching function devices	128
11.1.6 Switching function devices	129
12 System services	130
12.1 Registration services	130
12.1.1 Change system status filter	130
12.1.2 System register	130
12.1.3 System register abort	131
12.1.4 System register cancel	132
12.2 Services	132
12.2.1 Request system status	132
12.2.2 System status	133
12.2.3 Switching function capabilities changed	133
12.2.4 Switching function devices changed	134
12.2.5 Get registrations	135
12.2.6 Registration info	135
13 Monitoring services	136
13.1 Services	136
13.1.1 Change monitor filter	136
13.1.2 Monitor start	136
13.1.3 Monitor stop	137
13.1.4 Get monitors	137
13.1.5 Monitor info	138
14 Snapshot services	139
14.1 Services	139
14.1.1 Snapshot call	139
14.1.2 Snapshot device	140
14.1.3 Snapshot calldata	140
14.1.4 Snapshot devicedata	141
15 Call control services and events	141
15.1 Services	141
15.1.1 Accept call	141
15.1.2 Alternate call	142
15.1.3 Answer call	143
15.1.4 Call back call-related	143
15.1.5 Call back message call-related	144
15.1.6 Camp on call	144
15.1.7 Clear call	145
15.1.8 Clear Connection	145
15.1.9 Conference call	146
15.1.10 Consultation call	147
15.1.11 Deflect call	147
15.1.12 Dial digits	148
15.1.13 Directed pickup call	149
15.1.14 Group pickup call	149
15.1.15 Hold call	150
15.1.16 Intrude call	151
15.1.17 Join call	151
15.1.18 Make call	152
15.1.19 Make connection	153
15.1.20 Make predictive call	154
15.1.21 Park call	155
15.1.22 Reconnect call	156

15.1.23 Retrieve call	156
15.1.24 Send Message	157
15.1.25 Single step conference call	158
15.1.26 Single step transfer call	159
15.1.27 Transfer call	160
15.2 Events	160
15.2.1 Bridged	160
15.2.2 Call cleared	161
15.2.3 Conferenced	162
15.2.4 Connection cleared	162
15.2.5 Delivered	163
15.2.6 Digits dialed	164
15.2.7 Diverted	165
15.2.8 Established	166
15.2.9 Failed	166
15.2.10 Held	167
15.2.11 Network capabilities changed	168
15.2.12 Network reached	169
15.2.13 Offered	170
15.2.14 Originated	170
15.2.15 Queued	171
15.2.16 Retrieved	172
15.2.17 Service initiated	173
15.2.18 Transferred	174
16 Call associated features	175
16.1 Services	175
16.1.1 Associate data	175
16.1.2 Cancel telephony tones	175
16.1.3 Change connection information	176
16.1.4 Generate digits	176
16.1.5 Generate telephony tones	177
16.1.6 Send user information	178
16.2 Events	178
16.2.1 Call information	178
16.2.2 Charging	179
16.2.3 Digits generated	179
16.2.4 Telephony tones generated	180
16.2.5 Service completion failure	181
17 Media attachment services and events	182
17.1 Services	182
17.1.1 Attach media service	182
17.1.2 Detach media service	183
17.2 Events	183
17.2.1 Media attached	183
17.2.2 Media detached	184
18 Routeing services	185
18.1 Registration services	185
18.1.1 Route register	185
18.1.2 Route register abort	185
18.1.3 Route register cancel	186
18.2 Services	186
18.2.1 Re-Route	186
18.2.2 Route end	187
18.2.3 Route reject	187
18.2.4 Route request	188

18.2.5 Route select.	189
18.2.6 Route used.	189
19 Physical device features	190
19.1 Services	190
19.1.1 Button press	190
19.1.2 Get auditory apparatus information	191
19.1.3 Get button information	191
19.1.4 Get display.	192
19.1.5 Get hookswitch status	193
19.1.6 Get lamp information	194
19.1.7 Get lamp mode	195
19.1.8 Get message waiting indicator	195
19.1.9 Get microphone gain	196
19.1.10 Get microphone mute	197
19.1.11 Get ringer status	198
19.1.12 Get speaker mute	199
19.1.13 Get speaker volume	199
19.1.14 Set button information	200
19.1.15 Set display	201
19.1.16 Set hookswitch status	202
19.1.17 Set lamp mode.	202
19.1.18 Set message waiting indicator.	203
19.1.19 Set microphone gain.	203
19.1.20 Set microphone mute	204
19.1.21 Set ringer status	204
19.1.22 Set speaker mute	205
19.1.23 Set speaker volume	206
19.2 Events	206
19.2.1 Button information	206
19.2.2 Button press	207
19.2.3 Display updated	207
19.2.4 Hookswitch	208
19.2.5 Lamp mode	208
19.2.6 Message waiting	209
19.2.7 Microphone gain	209
19.2.8 Microphone mute	210
19.2.9 Ringer status	210
19.2.10 Speaker mute.	211
19.2.11 Speaker volume.	212
20 Logical device features	212
20.1 Services	212
20.1.1 Call back non-call-related.	212
20.1.2 Call back message non-call-related	213
20.1.3 Cancel call back	213
20.1.4 Cancel call back message	214
20.1.5 Get agent state	214
20.1.6 Get auto answer	215
20.1.7 Get auto work mode	216
20.1.8 Get call back	216
20.1.9 Get caller id status	217
20.1.10 Get do not disturb.	218
20.1.11 Get forwarding.	218
20.1.12 Get last number dialed	219
20.1.13 Get presence state	220
20.1.14 Get routeing mode	220
20.1.15 Set agent state.	221

20.1.16 Set auto answer	221
20.1.17 Set auto work mode	222
20.1.18 Set caller id status	223
20.1.19 Set do not disturb	223
20.1.20 Set forwarding	224
20.1.21 Set presence state	225
20.1.22 Set routeing mode	225
20.2 Events	226
20.2.1 Agent busy	226
20.2.2 Agent logged off	226
20.2.3 Agent logged on	227
20.2.4 Agent not ready	227
20.2.5 Agent ready	228
20.2.6 Agent working after call	228
20.2.7 Auto answer	229
20.2.8 Auto work mode	229
20.2.9 Call back	230
20.2.10 Call back message	230
20.2.11 Caller id status	231
20.2.12 Do not disturb	231
20.2.13 Forwarding	232
20.2.14 Presence state	233
20.2.15 Routeing mode	233
21 Device maintenance events	234
21.1 Events	234
21.1.1 Back in service	234
21.1.2 Device capabilities changed	234
21.1.3 Out of service	235
21.1.4 Partially In service	235
22 I/O services	236
22.1 Registration services	236
22.1.1 I/O register	236
22.1.2 I/O register abort	236
22.1.3 I/O register cancel	237
22.2 Services	237
22.2.1 Data path resumed	237
22.2.2 Data path suspended	238
22.2.3 Fast data	238
22.2.4 Resume data path	239
22.2.5 Send broadcast data	240
22.2.6 Send data	240
22.2.7 Send multicast data	241
22.2.8 Start data path	242
22.2.9 Stop data path	243
22.2.10 Suspend data path	243
23 Data Collection Services	244
23.1 Services	244
23.1.1 Data Collected	244
23.1.2 Data Collection Resumed	246
23.1.3 Data Collection Suspended	246
23.1.4 Resume Data Collection	247
23.1.5 Start Data Collection	247
23.1.6 Stop Data Collection	248
23.1.7 Suspend Data Collection	249
24 Voice services and events	249

24.1 Services	249
24.1.1 Activate	249
24.1.2 Clear	250
24.1.3 Concatenate message	250
24.1.4 Deactivate	251
24.1.5 Delete message	252
24.1.6 Play message	252
24.1.7 Query voice attribute	253
24.1.8 Queue service	254
24.1.9 Record message	254
24.1.10 Reposition	255
24.1.11 Resume	256
24.1.12 Review	256
24.1.13 Set voice attribute	257
24.1.14 Start	258
24.1.15 Stop	259
24.1.16 Suspend	260
24.1.17 Synthesize message	260
24.2 Events	261
24.2.1 Bookmark reached	261
24.2.2 Completed	261
24.2.3 DTMF detected	262
24.2.4 Emptied	262
24.2.5 Interruption detected	263
24.2.6 Not recognized	263
24.2.7 Play	264
24.2.8 Recognized	265
24.2.9 Record	265
24.2.10 Review	266
24.2.11 Silence timeout expired	266
24.2.12 Speech detected	267
24.2.13 Started	267
24.2.14 Stop	268
24.2.15 Suspend play	268
24.2.16 Suspend record	269
24.2.17 Voice attribute changed	270
24.2.18 Voice error occurred	271
25 Call detail record services	272
25.1 Services	272
25.1.1 Call detail records notification	272
25.1.2 Call detail records report	272
25.1.3 Send stored call detail records	273
25.1.4 Start call detail records transmission	273
25.1.5 Stop call detail records transmission	274
26 Location services	275
26.1 Services	275
26.1.1 Get location information	275
26.1.2 Set location information	275
26.1.3 Location tracking session resumed	276
26.1.4 Location tracking session suspended	276
26.1.5 Resume location tracking session	277
26.1.6 Location information report	277
26.1.7 Start location tracking session	278
26.1.8 Stop location tracking session	279
26.1.9 Suspend location tracking session	280
26.1.10 Get location tracking capabilities	280

26.1.11 Get location tracking sessions	281
26.1.12 Location Session Info.	282
27 Vendor specific extensions services and events	283
27.1 Registration services.	283
27.1.1 Escape register	283
27.1.2 Escape register abort	283
27.1.3 Escape register cancel	284
27.2 Services	284
27.2.1 Escape	284
27.2.2 Private data version selection	285
27.3 Events	285
27.3.1 Private event	285
Annex A (normative) Protocol Implementation Conformance Statement (PICS) Proforma	287
Annex B (normative) Registration Template for application/CSTA+XML MIME Media Type.	404
Annex C (normative) CSTA Over SIP (uaCSTA) Transport Mechanism	405
Annex D (normative) ISO/IEC 18056 Specified Short Tags	407
Annex E (informative) Examples of Device Identifier Element Encodings	482
Annex F (informative) Examples of Connection ID Encodings	484
Annex G (informative) Examples of CSTA-specific XML	485
Annex H (informative) CSTA XML with SOAP	487
Annex I (informative) CSTA XML with SOAP with HTTP	490
Annex J (informative) CSTA XML over TCP	493
Annex K (informative) CSTA Data Type Schema for Encapsulation	495
Annex L (informative) Registration Template for application/CSTAdat+XML MIME Media Type ...	496
Annex M (informative) Summary of changes in this edition	497
Bibliography	498

Foreword

ISO (the International Organization for Standardization) and IEC (the International Electrotechnical Commission) form the specialized system for worldwide standardization. National bodies that are members of ISO or IEC participate in the development of International Standards through technical committees established by the respective organization to deal with particular fields of technical activity. ISO and IEC technical committees collaborate in fields of mutual interest. Other international organizations, governmental and non-governmental, in liaison with ISO and IEC, also take part in the work. In the field of information technology, ISO and IEC have established a joint technical committee, ISO/IEC JTC 1.

International Standards are drafted in accordance with the rules given in the ISO/IEC Directives, Part 2.

The main task of the joint technical committee is to prepare International Standards. Draft International Standards adopted by the joint technical committee are circulated to national bodies for voting. Publication as an International Standard requires approval by at least 75 % of the national bodies casting a vote.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO and IEC shall not be held responsible for identifying any or all such patent rights.

ISO/IEC 18056 was prepared by Ecma International (as ECMA-323) and was adopted, under a special "fast-track procedure", by Joint Technical Committee ISO/IEC JTC 1, *Information technology*, in parallel with its approval by the national bodies of ISO and IEC.

This fifth edition cancels and replaces the fourth edition (ISO/IEC 18056:2010), which has been technically revised.

Information technology — Telecommunications and information exchange between systems — XML Schema Definitions for Computer Supported Telecommunications Applications (CSTA) Phase III

1 Scope

This International Standard specifies an XML protocol for the services defined in ISO/IEC 18051. It provides an alternative protocol to the ASN.1 based protocol specified in ISO/IEC 18052.

In addition to the CSTA-specific protocol details, this International Standard describes the concepts underlying the request/response model, application association, notation and service, and describes the template used in this International Standard.

It also specifies the PICS for this International Standard and provides examples of CSTA XML encodings.

2 Conformance

A manufacturer may select any part of the CSTA protocol, as specified in this International Standard, for implementation on a system as long as it satisfies the minimum conformance requirements as specified in Clause 2 of ISO/IEC 18051:2010.

A Protocol Implementation Conformance Statement (PICS) shall be used to specify the operations which are provided by a particular implementation. A PICS shall also specify the parameter options which are used.

2.1 Static Requirements

To conform to this International Standard, a system shall support the syntax as defined by the XML 1.0 specification and the structures and data types as defined in the XML Schema Structure and XML Schema Data Types specifications for the purpose of generating and interpreting CSTA protocol information for the operations supported.

2.2 Dynamic Requirements

To conform to this International Standard, a system shall:

- a. follow the procedures as specified in this International Standard, and ISO/IEC 18051, relevant to each CSTA operation that the system claims to implement; and
- b. satisfy the definitions, as specified in ISO/IEC 18051, relevant to each CSTA service that the system claims to implement.

2.3 PICS Requirement

To conform to this International Standard, the following shall be stated by the implementer when defining a PICS corresponding to an application or implementation:

- a. which CSTA operations, as defined in ISO/IEC 18051, are supported by the system for the particular implementation; and
- b. which optional parameters are supported by each supported operations.

A PICS proforma is specified in Annex A of this International Standard.

2.4 XML Tag Options

To conform to this International Standard, a system shall support at least one of the XML tag options listed below.

2.4.1 ISO/IEC 18056 (ECMA-323) Specified Tags

Instance documents shall include the following URI for the namespace and conform to the schemas as specified in Clause 9 through 27 of this International Standard without transformations.

<http://www.ecma-international.org/standards/ecma-323/csta/ed6>

2.4.2 ISO/IEC 18056 (ECMA-323) Specified Short Tags

Instance documents shall include the following URI for the namespace and conform to the schemas as specified in Clause 9 through 27 of this International Standard with transformations as specified in Annex D.

[urn:www.ecma-international.org/standards/ecma-323/csta/ed6/short_tags](urn:www.ecma-international.org/standards/ecma-323/csta/ed6/short_tags)

2.4.3 Dynamic Transformations

Implementation claiming conformance to this option shall support XML schema transformations e.g. using `<?xml-stylesheet>` for the schemas specified in Clause 9 through 27.

2.5 CSTA Over SIP (uaCSTA) Transport Mechanism Option

An implementation that conforms to this International Standard can also claim conformance to the “CSTA Over SIP (uaCSTA Transport Mechanism Option)” by implementing the SIP and CSTA procedures specified in Annex C.

3 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

3.1 ISO Standards and Technical Reports

ISO/IEC 18051:2012	Information technology - Telecommunications and information exchange between systems - Services for Computer Supported Telecommunications Applications (CSTA) Phase III
ISO/IEC 18052:2011	Information technology - Telecommunications and information exchange between systems - Protocol for Computer Supported Telecommunications Applications (CSTA) Phase III
ISO/IEC TR 18053:2000	Information technology - Telecommunications and information exchange between systems - Glossary of definitions and terminology for Computer Supported Telecommunications Applications (CSTA) Phase III

3.2 World Wide Web Consortium Specifications

XML 1.0	XML 1.0. W3C Recommendation February 1998 (revised October 2000)
XML Schema Part 1	XML Schema Language Part 1: Structures. W3C Recommendation 2 May 2001
XML Schema Part 2	XML Schema Language Part 2: Datatypes. W3C Recommendation 2 May 2001

4 Terms, definitions and abbreviations

For the purposes of this document, the terms, definitions and abbreviations given in ISO/IEC TR 18053 apply.

5 CSTA Service Definition Model

CSTA services specified in ISO/IEC 18051 are modeled as a request/response interaction.

Typically, one entity requests that a particular operation be performed; the other entity attempts to perform the operation and responds to the requestor.

5.1 Request/Response Interactions

CSTA services consist of the following types of request/response interactions:

- Services which specify a response in case of success or failure. The protocol description for these services includes a response element that represents the success (i.e. positive acknowledgement). In case of service failure, a fault element is used to provide the failure information (i.e. negative acknowledgement).
- Services which only specify a response in case of failure. The protocol description for these services do not include a response element. A fault element is used to provide the failure information (i.e. negative acknowledgement).

For CSTA event reports, no response is generated.

5.2 Request/Response Protocol Requirements

This International Standard specifies CSTA-specific XML-encoded content for messages that are sent across a CSTA Service boundary. Typically this CSTA-specific XML is enveloped by a request/response protocol that provides a mechanism for correlating a CSTA request with a CSTA response, manages faults, defines header information, etc.

This International Standard does not mandate that a specific request/response protocol be used. However, this International Standard provides examples of how the CSTA-specific XML can be used with several industry request/response protocols and transports such as SOAP (Simple Object Access Protocol), HTTP, and TCP. These examples are provided beginning in Annex H.

5.3 Cross Referencing of Event Reports

The Monitor Cross Reference Identifier in CSTA event reports is used to correlate events to an earlier Monitor Start service request (see 6.7.2.1 of ISO/IEC 18051:2010).

5.4 Handling of Private Data

If an entity receives CSTA Private Data in a CSTA message, and it can not recognize the information contained, the CSTA Private Data shall be discarded, and the rest of the message shall be processed.

6 Interconnection service boundary

The protocol in this International Standard is an OSI Application Layer protocol that assumes certain services are provided by the underlying layers, and these services are also assumed by the protocol for CSTA.

This protocol also provides a mechanism for secure transmission of CSTA messages as defined in this International Standard.

7 Association Management

The protocol in this International Standard operates in the context of an application association as specified in ISO/IEC 18051:2012 Clause 7. This application association can be achieved by:

- an implicit association achieved via off-line agreement; or
- an explicit association that is achieved dynamically.

7.1 Implicit association

An a-priori agreement exists between switching and computing functions: the application context is implicit, dynamic negotiation is not possible. See ISO/IEC 18051:2012 7.1 and 7.2 for more information.

7.2 Explicit association

An explicit application association is established by a process of exchanging messages that define the application context for the association.

This International Standard does not require that a particular standard be used as part of the application association establishment procedure.

When ACSE (ISO/IEC 8649) is used to establish an application association per 7.3 of ISO/IEC 18051:2012, the CSTA Association Information includes CSTA Version information that indicates the CSTA protocol versions supported by an implementation.

The protocol defined in this International Standard is indicated by setting the following bit in the CSTAVersion parameter of the CSTA Association Information as defined in 8.2.2 of ISO/IEC 18052:2011.

- versionTwelve when using the ISO/IEC 18056 Specified Tag option (see 2.4.1)
- versionThirteen when using the ISO/IEC 18056 Specified Short Tag option (see 2.4.2)
- versionFourteen when using the Dynamic Transformation option (see 2.4.3)

Note that the ACSE messages are ASN.1 encoded while the CSTA messages are XML encoded as defined by this International Standard.

ISO/IEC 22534, Application Session Services can also be used to establish an application association per 7.4 of ISO/IEC 18051:2010. When this International Standard is used with ISO/IEC 22534 the following namespace is provided in the requestedProtocolVersions element of the Start Application Session service:

- <http://www.ecma-international.org/standards/ecma-323/csta/ed6> when using the ISO/IEC 18056 Specified Tag option (see 2.4.1)
- [url:www.ecma-international.org/standards/ecma-323/csta/ed6/short_tags](http://www.ecma-international.org/standards/ecma-323/csta/ed6/short_tags) when using the ISO/IEC 18056 Specified Short Tag option (see 2.4.2)
- http://www.ecma-international.org/standards/ecma-323/csta/ed6/dynamic_transformations when using the Dynamic Transformation option (see 2.4.3)

8 XML Template Description

This Clause describes the template format used to describe the XML schemas for CSTA services, events, and parameter types as specified in ISO/IEC 18051.

The template consists of the following parts:

- XML header - this consists of the text "<?xml version='1.0' encoding='UTF-8'?>" which identifies the XML version used.
- XML Schema header - this identifies the start of an XML schema and provides information such as:
 - the target namespace. In this edition of the Standard the target namespace is defined as "http://www.ecma-international.org/standards/ecma-323/csta/ed6". *Note that this URL uniquely identifies the namespace for the 6th Edition of ECMA-323.*
 - the csta namespace is the same as the target namespace. XML names that refer to names in the CSTA namespace are prefixed with "csta:".
 - the xsd namespace. This identifies the XML Schema. XML names that refer to names in the XML Schema namespace are prefixed with "xsd:".
 - the element form default is specified as "qualified" which requires that all element names must be prefixed with a namespace (csta: or xsd:)
- documentation - this provides a comment that indicates the CSTA specific service, event report, or data-type set.
- included schemas - this provides a list of other CSTA schemas that are referenced by the service, event, or data type set.
- CSTA specific XML:
 - for CSTA services, this consists of a service request element and a service response element. (A comment is provided in some cases where a service response is not specified per ISO/IEC 18051.). This is followed, in some cases, by service-specific XML types that are referenced in the previous elements.
 - for CSTA event reports, this consists of an event report element followed, in some cases, by event-specific XML type definitions that are referenced in the event report element.
 - for CSTA data types, this consists of the data types that are referenced (included) by other CSTA XML schemas.
- XML Schema end tag - indicates the end of the schema.

Note that in general, each parameter defined in ISO/IEC 18051 is represented as an XML element and each parameter type in ISO/IEC 18051 is represented as an XML simple or complex type.

9 CSTA parameter types

9.1 Switching function objects

```
<?xml version="1.0" encoding="UTF-8"?>
```

```
<xsd:schema targetNamespace="http://www.ecma-international.org/standards/ecma-323/csta/ed6"
xmlns:xsd="http://www.w3.org/2001/XMLSchema"
xmlns:csta="http://www.ecma-international.org/standards/ecma-323/csta/ed6"
elementFormDefault="qualified" attributeFormDefault="unqualified">
```

```
<xsd:annotation>
  <xsd:documentation>CSTA-switching-function-objects</xsd:documentation>
</xsd:annotation>
```

```
<xsd:include schemaLocation="device-identifiers.xsd"/>
<xsd:include schemaLocation="call-connection-identifiers.xsd"/>
```

```
<xsd:complexType name="CSTAObject">
  <xsd:choice>
    <xsd:element name="deviceObject" type="csta:DeviceID"/>
    <xsd:element name="callObject" type="csta:ConnectionID"/>
  </xsd:choice>
</xsd:complexType>
```

```
</xsd:choice>
</xsd:complexType>

</xsd:schema>
```

9.2 Device Identifiers

```
<?xml version="1.0" encoding="UTF-8"?>

<xsd:schema targetNamespace="http://www.ecma-international.org/standards/ecma-323/csta/ed6"
xmlns:csta="http://www.ecma-international.org/standards/ecma-323/csta/ed6"
xmlns:xsd="http://www.w3.org/2001/XMLSchema"
elementFormDefault="qualified" attributeFormDefault="unqualified">

  <xsd:annotation>
    <xsd:documentation>CSTA-device-identifiers</xsd:documentation>
  </xsd:annotation>

  <xsd:include schemaLocation="media-services.xsd"/>
  <xsd:include schemaLocation="empty.xsd"/>

  <xsd:complexType name="ExtendedDeviceID">
    <xsd:choice>
      <xsd:element name="deviceIdentifier" type="csta:DeviceID"/>
      <xsd:element name="notKnown" type="csta:Empty"/>
      <xsd:element name="restricted" type="csta:Empty"/>
    </xsd:choice>
  </xsd:complexType>

  <xsd:complexType name="CallingDeviceID">
    <xsd:complexContent>
      <xsd:extension base="csta:ExtendedDeviceID"/>
    </xsd:complexContent>
  </xsd:complexType>

  <xsd:element name="callingDevice" type="csta:CallingDeviceID"/>

  <xsd:complexType name="CalledDeviceID">
    <xsd:complexContent>
      <xsd:extension base="csta:ExtendedDeviceID"/>
    </xsd:complexContent>
  </xsd:complexType>

  <xsd:element name="calledDevice" type="csta:CalledDeviceID"/>

  <xsd:complexType name="SubjectDeviceID">
    <xsd:complexContent>
      <xsd:extension base="csta:ExtendedDeviceID"/>
    </xsd:complexContent>
  </xsd:complexType>

  <xsd:complexType name="RedirectionDeviceID">
    <xsd:choice>
      <xsd:element name="numberDialed" type="csta:DeviceID"/>
      <xsd:element name="notKnown" type="csta:Empty"/>
      <xsd:element name="notRequired" type="csta:Empty"/>
      <xsd:element name="notSpecified" type="csta:Empty"/>
      <xsd:element name="restricted" type="csta:Empty"/>
    </xsd:choice>
  </xsd:complexType>

  <xsd:element name="lastRedirectionDevice" type="csta:RedirectionDeviceID"/>

  <xsd:complexType name="AssociatedCallingDeviceID">
    <xsd:complexContent>
      <xsd:extension base="csta:ExtendedDeviceID"/>
    </xsd:complexContent>
```

```

</xsd:complexType>

<xsd:element name="associatedCallingDevice" type="csta:AssociatedCallingDeviceID"/>

<xsd:complexType name="AssociatedCalledDeviceID">
  <xsd:complexContent>
    <xsd:extension base="csta:ExtendedDeviceID"/>
  </xsd:complexContent>
</xsd:complexType>

<xsd:element name="associatedCalledDevice" type="csta:AssociatedCalledDeviceID"/>

<xsd:complexType name="NetworkCallingDeviceID">
  <xsd:complexContent>
    <xsd:extension base="csta:ExtendedDeviceID"/>
  </xsd:complexContent>
</xsd:complexType>

<xsd:element name="networkCallingDevice" type="csta:NetworkCallingDeviceID"/>

<xsd:complexType name="NetworkCalledDeviceID">
  <xsd:complexContent>
    <xsd:extension base="csta:ExtendedDeviceID"/>
  </xsd:complexContent>
</xsd:complexType>

<xsd:element name="networkCalledDevice" type="csta:NetworkCalledDeviceID"/>

<xsd:complexType name="DeviceID">
  <xsd:annotation>
    <xsd:documentation>uses flattened structure</xsd:documentation>
  </xsd:annotation>
  <xsd:simpleContent>
    <xsd:extension base="csta:DeviceIDType">
      <xsd:attribute name="typeOfNumber" default="dialingNumber">
        <xsd:simpleType>
          <xsd:restriction base="xsd:string">
            <xsd:enumeration value="dialingNumber"/>
            <xsd:enumeration value="deviceNumber"/>
            <xsd:enumeration value="implicitPublic"/>
            <xsd:enumeration value="explicitPublic:unknown"/>
            <xsd:enumeration value="explicitPublic:international"/>
            <xsd:enumeration value="explicitPublic:national"/>
            <xsd:enumeration value="explicitPublic:networkspecific"/>
            <xsd:enumeration value="explicitPublic:subscriber"/>
            <xsd:enumeration value="explicitPublic:abbreviated"/>
            <xsd:enumeration value="implicitPrivate"/>
            <xsd:enumeration value="explicitPrivate:unknown"/>
            <xsd:enumeration value="explicitPrivate:level3RegionalNumber"/>
            <xsd:enumeration value="explicitPrivate:level2RegionalNumber"/>
            <xsd:enumeration value="explicitPrivate:level1RegionalNumber"/>
            <xsd:enumeration value="explicitPrivate:pTNSpecificNumber"/>
            <xsd:enumeration value="explicitPrivate:localNumber"/>
            <xsd:enumeration value="explicitPrivate:abbreviated"/>
            <xsd:enumeration value="other"/>
          </xsd:restriction>
        </xsd:simpleType>
      </xsd:attribute>
      <xsd:attribute name="mediaClass" type="csta:MediaClassAttribute" default="notKnown"/>
      <xsd:attribute name="connectionRate" use="optional">
        <xsd:simpleType>
          <xsd:restriction base="xsd:long">
            <xsd:minInclusive value="0"/>
          </xsd:restriction>
        </xsd:simpleType>
      </xsd:attribute>
      <xsd:attribute name="bitRate" default="constant">
        <xsd:simpleType>

```

```

    <xsd:restriction base="xsd:string">
      <xsd:enumeration value="constant"/>
      <xsd:enumeration value="variable"/>
    </xsd:restriction>
  </xsd:simpleType>
</xsd:attribute>
<xsd:attribute name="delayTolerance" type="xsd:long" use="optional"/>
<xsd:attribute name="switchingSubDomainCCIEType" use="optional">
  <xsd:simpleType>
    <xsd:restriction base="xsd:string">
      <xsd:enumeration value="isdn"/>
      <xsd:enumeration value="atm"/>
      <xsd:enumeration value="isoEthernet"/>
      <xsd:enumeration value="rsvp"/>
      <xsd:enumeration value="sip"/>
      <xsd:enumeration value="other"/>
    </xsd:restriction>
  </xsd:simpleType>
</xsd:attribute>
<xsd:attribute name="switchingSubDomainInformationElements" use="optional">
  <xsd:simpleType>
    <xsd:restriction base="xsd:hexBinary"/>
  </xsd:simpleType>
</xsd:attribute>
<xsd:attribute name="privateNumber" type="xsd:boolean" use="optional" default="false"/>
<xsd:attribute name="privateName" type="xsd:boolean" use="optional" default="false"/>
</xsd:extension>
</xsd:simpleContent>
</xsd:complexType>

<xsd:simpleType name="OtherPlan">
  <xsd:restriction base="xsd:hexBinary"/>
</xsd:simpleType>

<xsd:simpleType name="DeviceIDType">
  <xsd:union memberTypes="csta:OtherPlan csta:Number"/>
</xsd:simpleType>

<xsd:simpleType name="Number">
  <xsd:restriction base="xsd:string"/>
</xsd:simpleType>

<xsd:simpleType name="MediaClassComponents">
  <xsd:restriction base="xsd:string">
    <xsd:enumeration value="voice"/>
    <xsd:enumeration value="data"/>
    <xsd:enumeration value="image"/>
    <xsd:enumeration value="audio"/>
    <xsd:enumeration value="other"/>
    <xsd:enumeration value="notKnown"/>
    <xsd:enumeration value="chat"/>
    <xsd:enumeration value="email"/>
    <xsd:enumeration value="message"/>
    <xsd:enumeration value="im"/>
    <xsd:enumeration value="sms"/>
    <xsd:enumeration value="mms"/>
  </xsd:restriction>
</xsd:simpleType>

<xsd:simpleType name="MediaClassAttribute">
  <xsd:list itemType="csta:MediaClassComponents"/>
</xsd:simpleType>

</xsd:schema>

```

9.3 Call and connection identifiers

```
<?xml version="1.0" encoding="UTF-8"?>

<xsd:schema targetNamespace="http://www.ecma-international.org/standards/ecma-323/csta/ed6"
xmlns:xsd="http://www.w3.org/2001/XMLSchema"
xmlns:csta="http://www.ecma-international.org/standards/ecma-323/csta/ed6"
elementFormDefault="qualified" attributeFormDefault="unqualified">

  <xsd:annotation>
    <xsd:documentation>CSTA-call-connection-identifiers</xsd:documentation>
  </xsd:annotation>

  <xsd:include schemaLocation="device-identifiers.xsd"/>

  <xsd:complexType name="ConnectionID">
    <xsd:choice>
      <xsd:element name="deviceID" type="csta:LocalDeviceID"/>
      <xsd:sequence>
        <xsd:element name="callID" type="csta:CallID"/>
        <xsd:element name="deviceID" type="csta:LocalDeviceID" minOccurs="0"/>
      </xsd:sequence>
    </xsd:choice>
  </xsd:complexType>

  <xsd:simpleType name="CallID">
    <xsd:restriction base="xsd:string">
      <xsd:minLength value="0"/>
    </xsd:restriction>
  </xsd:simpleType>

  <xsd:complexType name="LocalDeviceID">
    <xsd:annotation>
      <xsd:documentation>uses flattened structure - all types included here</xsd:documentation>
    </xsd:annotation>
    <xsd:simpleContent>
      <xsd:extension base="csta:DeviceIDType">
        <xsd:attribute name="typeOfNumber" default="dialingNumber">
          <xsd:simpleType>
            <xsd:restriction base="xsd:string">
              <xsd:enumeration value="dialingNumber"/>
              <xsd:enumeration value="deviceNumber"/>
              <xsd:enumeration value="implicitPublic"/>
              <xsd:enumeration value="explicitPublic:unknown"/>
              <xsd:enumeration value="explicitPublic:international"/>
              <xsd:enumeration value="explicitPublic:national"/>
              <xsd:enumeration value="explicitPublic:networkspecific"/>
              <xsd:enumeration value="explicitPublic:subscriber"/>
              <xsd:enumeration value="explicitPublic:abbreviated"/>
              <xsd:enumeration value="implicitPrivate"/>
              <xsd:enumeration value="explicitPrivate:unknown"/>
              <xsd:enumeration value="explicitPrivate:level3RegionalNumber"/>
              <xsd:enumeration value="explicitPrivate:level2RegionalNumber"/>
              <xsd:enumeration value="explicitPrivate:level1RegionalNumber"/>
              <xsd:enumeration value="explicitPrivate:pTNSpecificNumber"/>
              <xsd:enumeration value="explicitPrivate:localNumber"/>
              <xsd:enumeration value="explicitPrivate:abbreviated"/>
              <xsd:enumeration value="other"/>
              <xsd:enumeration value="dynamic"/>
            </xsd:restriction>
          </xsd:simpleType>
        </xsd:attribute>
        <xsd:attribute name="mediaClass" type="csta:MediaClassAttribute" default="notKnown"/>
        <xsd:attribute name="connectionRate" use="optional">
          <xsd:simpleType>
            <xsd:restriction base="xsd:long">
              <xsd:minInclusive value="0"/>
            </xsd:restriction>
          </xsd:simpleType>
        </xsd:attribute>
      </xsd:extension>
    </xsd:simpleContent>
  </xsd:complexType>
```

```

</xsd:simpleType>
</xsd:attribute>
<xsd:attribute name="bitRate" default="constant">
  <xsd:simpleType>
    <xsd:restriction base="xsd:string">
      <xsd:enumeration value="constant"/>
      <xsd:enumeration value="variable"/>
    </xsd:restriction>
  </xsd:simpleType>
</xsd:attribute>
<xsd:attribute name="delayTolerance" type="xsd:long" use="optional"/>
<xsd:attribute name="switchingSubDomainCCIEType" use="optional">
  <xsd:simpleType>
    <xsd:restriction base="xsd:string">
      <xsd:enumeration value="isdn"/>
      <xsd:enumeration value="atm"/>
      <xsd:enumeration value="isoEthernet"/>
      <xsd:enumeration value="rsvp"/>
      <xsd:enumeration value="sip"/>
      <xsd:enumeration value="other"/>
    </xsd:restriction>
  </xsd:simpleType>
</xsd:attribute>
<xsd:attribute name="switchingSubDomainInformationElements" use="optional">
  <xsd:simpleType>
    <xsd:restriction base="xsd:hexBinary"/>
  </xsd:simpleType>
</xsd:attribute>
<xsd:attribute name="privateNumber" type="xsd:boolean" use="optional" default="false"/>
<xsd:attribute name="privateName" type="xsd:boolean" use="optional" default="false"/>
</xsd:extension>
</xsd:simpleContent>
</xsd:complexType>
</xsd:schema>

```

9.4 Connection states

```

<?xml version="1.0" encoding="UTF-8"?>

<xsd:schema targetNamespace="http://www.ecma-international.org/standards/ecma-323/csta/ed6"
  xmlns:xsd="http://www.w3.org/2001/XMLSchema"
  xmlns:csta="http://www.ecma-international.org/standards/ecma-323/csta/ed6"
  elementFormDefault="qualified" attributeFormDefault="unqualified">

  <xsd:annotation>
    <xsd:documentation>CSTA-connection-states</xsd:documentation>
  </xsd:annotation>

  <xsd:include schemaLocation="call-connection-identifiers.xsd"/>
  <xsd:include schemaLocation="device-identifiers.xsd"/>
  <xsd:include schemaLocation="media-services.xsd"/>
  <xsd:include schemaLocation="empty.xsd"/>

  <xsd:complexType name="ConnectionList">
    <xsd:sequence>
      <xsd:element name="connectionListItem" type="csta:ConnectionListItem" maxOccurs="unbounded"/>
    </xsd:sequence>
  </xsd:complexType>
  <xsd:simpleType name="LocalConnectionState">
    <xsd:restriction base="xsd:string">
      <xsd:enumeration value="null"/>
      <xsd:enumeration value="initiated"/>
      <xsd:enumeration value="alerting"/>
      <xsd:enumeration value="connected"/>
      <xsd:enumeration value="hold"/>
      <xsd:enumeration value="queued"/>
    </xsd:restriction>
  </xsd:simpleType>

```

```

    <xsd:enumeration value="fail"/>
  </xsd:restriction>
</xsd:simpleType>

<xsd:element name="localConnectionInfo" type="csta:LocalConnectionState"/>

<xsd:complexType name="ConnectionListItem">
  <xsd:sequence>
    <xsd:element name="newConnection" type="csta:ConnectionID" minOccurs="0"/>
    <xsd:element name="oldConnection" type="csta:ConnectionID" minOccurs="0"/>
    <xsd:element name="endpoint" minOccurs="0">
      <xsd:complexType>
        <xsd:choice>
          <xsd:element name="deviceId" type="csta:DeviceID"/>
          <xsd:element name="notKnown" type="csta:Empty"/>
          <xsd:element name="restricted" type="csta:Empty"/>
        </xsd:choice>
      </xsd:complexType>
    </xsd:element>
    <xsd:element name="associatedNID" minOccurs="0">
      <xsd:complexType>
        <xsd:choice>
          <xsd:element name="deviceId" type="csta:DeviceID"/>
          <xsd:element name="notKnown" type="csta:Empty"/>
        </xsd:choice>
      </xsd:complexType>
    </xsd:element>
    <xsd:element name="resultingConnectionInfo" type="csta:ConnectionInformation"
      minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

</xsd:schema>

```

9.5 Status reporting

```

<?xml version="1.0" encoding="UTF-8"?>

<xsd:schema targetNamespace="http://www.ecma-international.org/standards/ecma-323/csta/ed6"
  xmlns:csta="http://www.ecma-international.org/standards/ecma-323/csta/ed6"
  xmlns:xsd="http://www.w3.org/2001/XMLSchema" elementFormDefault="qualified" attributeFormDefault="unqualified">

  <xsd:annotation>
    <xsd:documentation>CSTA-status-reporting</xsd:documentation>
  </xsd:annotation>

  <xsd:include schemaLocation="call-control.xsd"/>
  <xsd:include schemaLocation="switching-function-objects.xsd"/>
  <xsd:include schemaLocation="device-identifiers.xsd"/>
  <xsd:include schemaLocation="call-connection-identifiers.xsd"/>
  <xsd:include schemaLocation="connection-states.xsd"/>
  <xsd:include schemaLocation="media-services.xsd"/>
  <xsd:include schemaLocation="device-feature-types.xsd"/>
  <xsd:include schemaLocation="empty.xsd"/>

  <xsd:complexType name="MonitorObject">
    <xsd:complexContent>
      <xsd:extension base="csta:CSTAObject"/>
    </xsd:complexContent>
  </xsd:complexType>

  <xsd:simpleType name="MonitorCrossRefID">
    <xsd:restriction base="xsd:string">
      <xsd:minLength value="0"/>
    </xsd:restriction>
  </xsd:simpleType>

```

```

<xsd:element name="monitorCrossRefID" type="csta:MonitorCrossRefID"/>
<xsd:complexType name="MonitorFilter">
  <xsd:sequence>
    <xsd:element name="callcontrol" type="csta:CallControlEvents" minOccurs="0"/>
    <xsd:element name="callAssociated" type="csta:CallAssociatedEvents" minOccurs="0"/>
    <xsd:element name="mediaAttachment" type="csta:MediaAttachmentEvents" minOccurs="0"/>
    <xsd:element name="physicalDeviceFeature" type="csta:PhysicalDeviceFeatureEvents" minOccurs="0"/>
    <xsd:element name="logicalDeviceFeature" type="csta:LogicalDeviceFeatureEvents" minOccurs="0"/>
    <xsd:element name="maintenance" type="csta:DeviceMaintenanceEvents" minOccurs="0"/>
    <xsd:element name="voice" type="csta:VoiceEvents" minOccurs="0"/>
    <xsd:element name="private" type="csta:VendorSpecEvents" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:simpleType name="MonitorType">
  <xsd:restriction base="xsd:string">
    <xsd:enumeration value="call"/>
    <xsd:enumeration value="device"/>
  </xsd:restriction>
</xsd:simpleType>

<xsd:complexType name="MonitorMediaClass">
  <xsd:sequence>
    <xsd:element name="voice" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="data" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="image" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="audio" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="other" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="chat" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="email" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="message" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="im" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="sms" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="mms" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="CallControlEvents">
  <xsd:sequence>
    <xsd:element name="bridged" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callCleared" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="conferenced" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="connectionCleared" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="delivered" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="digitsDialed" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="diverted" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="established" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="failed" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="held" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="networkCapabilitiesChanged" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="networkReached" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="offered" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="originated" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="queued" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="retrieved" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="serviceInitiated" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="transferred" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="CallAssociatedEvents">
  <xsd:sequence>
    <xsd:element name="callInformation" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="charging" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="digitsGenerated" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="telephonyTonesGenerated" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="serviceCompletionFailure" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>

```

```

</xsd:complexType>

<xsd:complexType name="MediaAttachmentEvents">
  <xsd:sequence>
    <xsd:element name="mediaAttached" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="mediaDetached" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="PhysicalDeviceFeatureEvents">
  <xsd:sequence>
    <xsd:element name="buttonInformation" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="buttonPress" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="displayUpdated" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="hookswitch" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="lampMode" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="messageWaiting" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="microphoneGain" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="microphoneMute" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="ringerStatus" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="speakerMute" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="speakerVolume" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="LogicalDeviceFeatureEvents">
  <xsd:sequence>
    <xsd:element name="agentBusy" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="agentLoggedOn" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="agentLoggedOff" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="agentNotReady" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="agentReady" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="agentWorkingAfterCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="autoAnswer" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="autoWorkMode" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callBack" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callBackMessage" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callerIDStatus" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="doNotDisturb" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="forwarding" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="presenceState" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="routeingMode" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="DeviceMaintenanceEvents">
  <xsd:sequence>
    <xsd:element name="backInService" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="deviceCapabilityChanged" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="outOfService" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="partiallyInService" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="VoiceEvents">
  <xsd:sequence>
    <xsd:element name="bookmarkReached" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="completed" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="dtmfDetected" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="emptied" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="interruptionDetected" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="notRecognized" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="play" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="recognized" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="record" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="review" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="started" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="silenceTimeoutExpired" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

```

```

<xsd:element name="speechDetected" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="stop" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="suspendPlay" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="suspendRecord" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="voiceAttributesChanged" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="voiceErrorOccurred" type="xsd:boolean" minOccurs="0"/>
</xsd:sequence>
</xsd:complexType>

<xsd:complexType name="VendorSpecEvents">
  <xsd:sequence>
    <xsd:element name="private" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="SnapshotDeviceDataList">
  <xsd:sequence>
    <xsd:element name="snapshotDeviceResponseInfo" type="csta:SnapshotDeviceResponseInfo" minOccurs="0"
maxOccurs="unbounded"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="SnapshotDeviceResponseInfo">
  <xsd:sequence>
    <xsd:element name="connectionIdentifier" type="csta:ConnectionID"/>
    <xsd:element name="endpointDevice" type="csta:SubjectDeviceID" minOccurs="0"/>
    <xsd:element name="localCallState" type="csta:CallState"/>
    <xsd:element ref="csta:servicesPermitted" minOccurs="0"/>
    <xsd:element name="mediaServiceInfoList" type="csta:DeviceMediaInfoList" minOccurs="0"/>
    <xsd:element ref="csta:mediaCallCharacteristics" minOccurs="0"/>
    <xsd:element ref="csta:callLinkageData" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="DeviceMediaInfoList">
  <xsd:sequence>
    <xsd:element name="deviceMediaInfo" minOccurs="0" maxOccurs="unbounded">
      <xsd:complexType>
        <xsd:sequence>
          <xsd:element name="mediaStreamID" type="csta:MediaStreamID" minOccurs="0"/>
          <xsd:element name="connectionInformation" type="csta:ConnectionInformation" minOccurs="0"/>
        </xsd:sequence>
      </xsd:complexType>
    </xsd:element>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="SnapshotCallDataList">
  <xsd:sequence>
    <xsd:element name="snapshotCallResponseInfo" type="csta:SnapshotCallResponseInfo" minOccurs="0" maxOccurs="unbounded"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="SnapshotCallResponseInfo">
  <xsd:sequence>
    <xsd:element name="deviceOnCall" type="csta:SubjectDeviceID"/>
    <xsd:element name="callIdentifier" type="csta:ConnectionID" minOccurs="0"/>
    <xsd:element name="localConnectionInfo" type="csta:LocalConnectionState" minOccurs="0"/>
    <xsd:element ref="csta:servicesPermitted" minOccurs="0"/>
    <xsd:element name="mediaServiceInfoList" type="csta:CallMediaInfoList" minOccurs="0"/>
    <xsd:element name="locationInfo" type="csta:LocationInfo" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="CallMediaInfoList">
  <xsd:sequence>
    <xsd:element name="callMediaInfo" minOccurs="0" maxOccurs="unbounded">
      <xsd:complexType>

```

```

<xsd:sequence>
  <xsd:element name="mediaServiceType" type="csta:MediaServiceType"/>
  <xsd:element name="mediaServiceVersion" type="xsd:long" minOccurs="0"/>
  <xsd:element name="mediaServiceInstance" type="csta:MediaServiceInstanceID" minOccurs="0"/>
  <xsd:element name="mediaStreamID" type="csta:MediaStreamID" minOccurs="0"/>
  <xsd:element name="connectionInformation" type="csta:ConnectionInformation" minOccurs="0"/>
</xsd:sequence>
</xsd:complexType>
</xsd:element>
</xsd:sequence>
</xsd:complexType>

<xsd:complexType name="CallState">
  <xsd:choice>
    <xsd:element name="compoundCallState" type="csta:CompoundCallState"/>
    <xsd:element name="simpleCallState" type="csta:SimpleCallState"/>
    <xsd:element name="unknown" type="csta:Empty"/>
  </xsd:choice>
</xsd:complexType>
<xsd:complexType name="CompoundCallState">
  <xsd:sequence>
    <xsd:element name="localConnectionState" type="csta:LocalConnectionState" minOccurs="0" maxOccurs="unbounded"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:simpleType name="SimpleCallState">
  <xsd:restriction base="xsd:string">
    <xsd:enumeration value="callNull"/>
    <xsd:enumeration value="callPending"/>
    <xsd:enumeration value="callOriginated"/>
    <xsd:enumeration value="callDelivered"/>
    <xsd:enumeration value="callDeliveredHeld"/>
    <xsd:enumeration value="callReceived"/>
    <xsd:enumeration value="callEstablished"/>
    <xsd:enumeration value="callEstablishedHeld"/>
    <xsd:enumeration value="callReceivedOnHold"/>
    <xsd:enumeration value="callEstablishedOnHold"/>
    <xsd:enumeration value="callQueued"/>
    <xsd:enumeration value="callQueuedHeld"/>
    <xsd:enumeration value="callFailed"/>
    <xsd:enumeration value="callFailedHeld"/>
    <xsd:enumeration value="callBlocked"/>
  </xsd:restriction>
</xsd:simpleType>

<xsd:complexType name="RegistrationTypeList">
  <xsd:sequence>
    <xsd:element name="registrationType" type="csta:RegistrationType" maxOccurs="unbounded"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:simpleType name="RegistrationType">
  <xsd:restriction base="xsd:string">
    <xsd:enumeration value="escapeRegister"/>
    <xsd:enumeration value="ioRegister"/>
    <xsd:enumeration value="routeRegister"/>
    <xsd:enumeration value="sysStatRegister"/>
  </xsd:restriction>
</xsd:simpleType>

<xsd:complexType name="RegistrationList">
  <xsd:sequence>
    <xsd:element name="registrationListEntry" type="csta:RegistrationListEntry" maxOccurs="unbounded"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="RegistrationListEntry">
  <xsd:sequence>

```

```

    <xsd:element name="registrationType" type="csta:RegistrationType"/>
    <xsd:element name="registrationID" type="xsd:string"/>
    <xsd:element name="registrationObject" type="csta:DeviceID" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="MonitorList">
  <xsd:sequence>
    <xsd:element name="monitorListEntry" type="csta:MonitorListEntry" maxOccurs="unbounded"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="MonitorListEntry">
  <xsd:sequence>
    <xsd:element name="monitorCrossRefID" type="csta:MonitorCrossRefID"/>
    <xsd:element name="monitorObject" type="csta:DeviceID"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="LocationSessionInfoList">
  <xsd:sequence>
    <xsd:element name="locationSessionListEntry" type="csta:LocationSessionListEntry" maxOccurs="unbounded"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="LocationSessionListEntry">
  <xsd:sequence>
    <xsd:element ref="csta:locCrossRefID"/>
    <xsd:element name="locDevice" type="csta:DeviceID"/>
  </xsd:sequence>
</xsd:complexType>
</xsd:schema>

```

9.6 Device and feature types and other parameters

```

<?xml version="1.0" encoding="UTF-8"?>

<xsd:schema targetNamespace="http://www.ecma-international.org/standards/ecma-323/csta/ed6"
  xmlns:csta="http://www.ecma-international.org/standards/ecma-323/csta/ed6"
  xmlns:xsd="http://www.w3.org/2001/XMLSchema" elementFormDefault="qualified" attributeFormDefault="unqualified">

  <xsd:annotation>
    <xsd:documentation>CSTA-device-feature-types</xsd:documentation>
  </xsd:annotation>

  <xsd:include schemaLocation="call-connection-identifiers.xsd"/>
  <xsd:include schemaLocation="device-identifiers.xsd"/>
  <xsd:include schemaLocation="event-cause.xsd"/>

  <xsd:simpleType name="AccountInfo">
    <xsd:restriction base="xsd:hexBinary">
      <xsd:minLength value="0"/>
    </xsd:restriction>
  </xsd:simpleType>

  <xsd:element name="accountCode" type="csta:AccountInfo"/>
  <xsd:simpleType name="AgentID">
    <xsd:restriction base="xsd:string">
      <xsd:minLength value="0"/>
    </xsd:restriction>
  </xsd:simpleType>

  <xsd:simpleType name="AgentPassword">
    <xsd:restriction base="xsd:hexBinary">
      <xsd:minLength value="0"/>
    </xsd:restriction>
  </xsd:simpleType>

```

```

<xsd:simpleType name="AgentState">
  <xsd:restriction base="xsd:string">
    <xsd:enumeration value="agentNotReady"/>
    <xsd:enumeration value="agentNull"/>
    <xsd:enumeration value="agentReady"/>
    <xsd:enumeration value="agentBusy"/>
    <xsd:enumeration value="agentWorkingAfterCall"/>
  </xsd:restriction>
</xsd:simpleType>

<xsd:simpleType name="AuthCode">
  <xsd:restriction base="xsd:hexBinary">
    <xsd:minLength value="0"/>
  </xsd:restriction>
</xsd:simpleType>

<xsd:element name="authCode" type="csta:AuthCode"/>

<xsd:complexType name="CorrelatorData">
  <xsd:choice>
    <xsd:element name="string">
      <xsd:simpleType>
        <xsd:restriction base="xsd:hexBinary">
          <xsd:minLength value="0"/>
        </xsd:restriction>
      </xsd:simpleType>
    </xsd:element>
    <xsd:element name="private">
      <xsd:annotation>
        <xsd:documentation>private: the actual encoding has to be replaced here</xsd:documentation>
      </xsd:annotation>
      <xsd:complexType>
        <xsd:sequence>
          <xsd:any namespace="##any" maxOccurs="unbounded"/>
        </xsd:sequence>
      </xsd:complexType>
    </xsd:element>
  </xsd:choice>
</xsd:complexType>

<xsd:element name="correlatorData" type="csta:CorrelatorData"/>

<xsd:complexType name="IOCrossRefID">
  <xsd:choice>
    <xsd:element name="switchProvided">
      <xsd:simpleType>
        <xsd:restriction base="xsd:string">
          <xsd:minLength value="0"/>
        </xsd:restriction>
      </xsd:simpleType>
    </xsd:element>
    <xsd:element name="computerProvided">
      <xsd:simpleType>
        <xsd:restriction base="xsd:string">
          <xsd:minLength value="0"/>
        </xsd:restriction>
      </xsd:simpleType>
    </xsd:element>
  </xsd:choice>
</xsd:complexType>

<xsd:simpleType name="IORegisterReqID">
  <xsd:restriction base="xsd:string">
    <xsd:minLength value="0"/>
  </xsd:restriction>
</xsd:simpleType>

```

```

<xsd:simpleType name="MessageID">
  <xsd:restriction base="xsd:string"/>
</xsd:simpleType>

<xsd:simpleType name="ResourceID">
  <xsd:restriction base="xsd:string"/>
</xsd:simpleType>

<xsd:simpleType name="ParticipationType">
  <xsd:restriction base="xsd:string">
    <xsd:enumeration value="silent"/>
    <xsd:enumeration value="active"/>
    <xsd:enumeration value="none"/>
  </xsd:restriction>
</xsd:simpleType>

<xsd:element name="routeRegisterReqID" type="csta:RouteRegisterReqID"/>

<xsd:simpleType name="RouteRegisterReqID">
  <xsd:restriction base="xsd:string">
    <xsd:minLength value="0"/>
  </xsd:restriction>
</xsd:simpleType>

<xsd:element name="crossRefIdentifier" type="csta:RouteingCrossRefID"/>
<xsd:simpleType name="RouteingCrossRefID">
  <xsd:restriction base="xsd:string">
    <xsd:minLength value="0"/>
  </xsd:restriction>
</xsd:simpleType>

<xsd:simpleType name="SelectValue">
  <xsd:restriction base="xsd:string">
    <xsd:enumeration value="normal"/>
    <xsd:enumeration value="leastCost"/>
    <xsd:enumeration value="emergency"/>
    <xsd:enumeration value="aCD"/>
    <xsd:enumeration value="userDefined"/>
  </xsd:restriction>
</xsd:simpleType>

<xsd:complexType name="RetryValue">
  <xsd:choice>
    <xsd:element name="noListAvailable" type="xsd:boolean"/>
    <xsd:element name="noCountAvailable" type="xsd:boolean"/>
    <xsd:element name="retryCount" type="xsd:long"/>
  </xsd:choice>
</xsd:complexType>

<xsd:simpleType name="SysStatRegisterID">
  <xsd:restriction base="xsd:string">
    <xsd:minLength value="0"/>
  </xsd:restriction>
</xsd:simpleType>

<xsd:element name="sysStatRegisterID" type="csta:SysStatRegisterID"/>
<xsd:simpleType name="SystemStatusValue">
  <xsd:restriction base="xsd:string">
    <xsd:enumeration value="disabled"/>
    <xsd:enumeration value="partiallyDisabled"/>
    <xsd:enumeration value="enabled"/>
    <xsd:enumeration value="initializing"/>
    <xsd:enumeration value="messagesLost"/>
    <xsd:enumeration value="normal"/>
    <xsd:enumeration value="overloadImminent"/>
    <xsd:enumeration value="overloadReached"/>
    <xsd:enumeration value="overloadRelieved"/>
  </xsd:restriction>

```

```

</xsd:simpleType>

<xsd:complexType name="CallOrigination">
  <xsd:sequence>
    <xsd:element name="internal" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="external" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="ForwardList">
  <xsd:sequence>
    <xsd:element name="forwardListItem" type="csta:ForwardListItem" maxOccurs="unbounded"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="ForwardListItem">
  <xsd:sequence>
    <xsd:element name="forwardingType" type="csta:ForwardingType" minOccurs="0"/>
    <xsd:element name="forwardStatus" type="xsd:boolean"/>
    <xsd:element name="forwardDN" type="csta:DeviceID" minOccurs="0"/>
    <xsd:element name="forwardDefault" type="csta:ForwardDefault" minOccurs="0"/>
    <xsd:element name="ringCount" minOccurs="0">
      <xsd:simpleType>
        <xsd:restriction base="xsd:long">
          <xsd:minInclusive value="1"/>
          <xsd:maxInclusive value="100"/>
        </xsd:restriction>
      </xsd:simpleType>
    </xsd:element>
    <xsd:element name="ringDuration" type="xsd:integer" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:simpleType name="ForwardingType">
  <xsd:restriction base="xsd:string">
    <xsd:enumeration value="forwardImmediate"/>
    <xsd:enumeration value="forwardBusy"/>
    <xsd:enumeration value="forwardNoAns"/>
    <xsd:enumeration value="forwardDND"/>
    <xsd:enumeration value="forwardBusyInt"/>
    <xsd:enumeration value="forwardBusyExt"/>
    <xsd:enumeration value="forwardNoAnsInt"/>
    <xsd:enumeration value="forwardNoAnsExt"/>
    <xsd:enumeration value="forwardImmInt"/>
    <xsd:enumeration value="forwardImmExt"/>
    <xsd:enumeration value="forwardDNDInt"/>
    <xsd:enumeration value="forwardDNDExt"/>
  </xsd:restriction>
</xsd:simpleType>

<xsd:simpleType name="ForwardDefault">
  <xsd:restriction base="xsd:string">
    <xsd:enumeration value="forwardingTypeAndForwardDN"/>
    <xsd:enumeration value="forwardingType"/>
    <xsd:enumeration value="forwardDN"/>
  </xsd:restriction>
</xsd:simpleType>

<xsd:simpleType name="PendingAgentState">
  <xsd:restriction base="xsd:string">
    <xsd:enumeration value="agentNotReady"/>
    <xsd:enumeration value="agentNull"/>
    <xsd:enumeration value="agentReady"/>
    <xsd:enumeration value="agentWorkingAfterCall"/>
  </xsd:restriction>
</xsd:simpleType>

<xsd:simpleType name="DataPathType">

```

```

<xsd:restriction base="xsd:string">
  <xsd:enumeration value="text"/>
  <xsd:enumeration value="voice"/>
</xsd:restriction>
</xsd:simpleType>

<xsd:complexType name="DisplayAttributeList">
  <xsd:sequence>
    <xsd:element name="physicalBaseRowNumber" type="xsd:long" minOccurs="0"/>
    <xsd:element name="physicalBaseColumnNumber" type="xsd:long" minOccurs="0"/>
    <xsd:element name="offset" type="xsd:long" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="TerminatingConditions">
  <xsd:sequence>
    <xsd:element name="durationExceeded" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="dTMFDigitDetected" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="endOfMessageDetected" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="speechDetected" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="AttributeInfo">
  <xsd:choice>
    <xsd:element name="encodingAlgorithm" type="csta:EncodingAlgorithm"/>
    <xsd:element name="samplingRate" type="xsd:long"/>
    <xsd:element name="duration" type="xsd:long"/>
    <xsd:element name="filename" type="xsd:string"/>
    <xsd:element name="currentPosition" type="xsd:long"/>
    <xsd:element name="currentSpeed" type="xsd:long"/>
    <xsd:element name="currentVolume">
      <xsd:simpleType>
        <xsd:restriction base="xsd:long">
          <xsd:minInclusive value="0"/>
          <xsd:maxInclusive value="100"/>
        </xsd:restriction>
      </xsd:simpleType>
    </xsd:element>
    <xsd:element name="currentGain">
      <xsd:simpleType>
        <xsd:restriction base="xsd:long">
          <xsd:minInclusive value="0"/>
          <xsd:maxInclusive value="100"/>
        </xsd:restriction>
      </xsd:simpleType>
    </xsd:element>
    <xsd:element name="currentState" type="csta:CurrentState"/>
    <xsd:element name="grammars" maxOccurs="unbounded">
      <xsd:complexType>
        <xsd:sequence>
          <xsd:any namespace="##any" maxOccurs="unbounded"/>
        </xsd:sequence>
        <xsd:attribute name="name" type="xsd:string"/>
        <xsd:attribute name="src" type="xsd:anyURI"/>
        <xsd:anyAttribute namespace="##any"/>
      </xsd:complexType>
    </xsd:element>
    <xsd:element name="language" type="xsd:language"/>
    <xsd:element name="mode">
      <xsd:simpleType>
        <xsd:restriction base="xsd:string">
          <xsd:enumeration value="automatic"/>
          <xsd:enumeration value="single"/>
          <xsd:enumeration value="multiple"/>
        </xsd:restriction>
      </xsd:simpleType>
    </xsd:element>
  </xsd:choice>

```

```

<xsd:element name="retainAudio" type="xsd:boolean"/>
<xsd:element name="silenceTimeout" type="xsd:float"/>
<xsd:element name="maxTimeout" type="xsd:float"/>
<xsd:element name="babbleTimeout" type="xsd:float"/>
<xsd:element name="endSilence" type="xsd:float"/>
<xsd:element name="rejectionThreshold">
  <xsd:simpleType>
    <xsd:restriction base="xsd:float">
      <xsd:maxInclusive value="1.0"/>
      <xsd:minInclusive value="0.0"/>
    </xsd:restriction>
  </xsd:simpleType>
</xsd:element>
<xsd:element name="autoInterruptible" type="xsd:boolean"/>
<xsd:element name="innerXml">
  <xsd:complexType>
    <xsd:sequence>
      <xsd:any/>
    </xsd:sequence>
  </xsd:complexType>
</xsd:element>
<xsd:element name="interdigitTimeout" type="xsd:float"/>
<xsd:element name="preflush" type="xsd:boolean"/>
</xsd:choice>
</xsd:complexType>
<xsd:simpleType name="EncodingAlgorithm">
  <xsd:restriction base="xsd:string">
    <xsd:enumeration value="aDPCM6K"/>
    <xsd:enumeration value="aDPCM8K"/>
    <xsd:enumeration value="muLawPCM6K"/>
    <xsd:enumeration value="aLawPCM6K"/>
  </xsd:restriction>
</xsd:simpleType>
<xsd:simpleType name="CurrentState">
  <xsd:restriction base="xsd:string">
    <xsd:enumeration value="formed"/>
    <xsd:enumeration value="dtmfDetected"/>
    <xsd:enumeration value="play"/>
    <xsd:enumeration value="playing"/>
    <xsd:enumeration value="ready"/>
    <xsd:enumeration value="record"/>
    <xsd:enumeration value="review"/>
    <xsd:enumeration value="speechDetected"/>
    <xsd:enumeration value="started"/>
    <xsd:enumeration value="stop"/>
    <xsd:enumeration value="suspendPlay"/>
    <xsd:enumeration value="suspendRecord"/>
  </xsd:restriction>
</xsd:simpleType>
<xsd:complexType name="ControlData">
  <xsd:sequence>
    <xsd:element name="gender">
      <xsd:simpleType>
        <xsd:restriction base="xsd:string">
          <xsd:enumeration value="male"/>
          <xsd:enumeration value="female"/>
        </xsd:restriction>
      </xsd:simpleType>
    </xsd:element>
    <xsd:element name="language">
      <xsd:simpleType>
        <xsd:restriction base="xsd:string"/>
      </xsd:simpleType>
    </xsd:element>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="UserData">

```

```

<xsd:choice>
  <xsd:element name="string">
    <xsd:simpleType>
      <xsd:restriction base="xsd:hexBinary">
        <xsd:minLength value="0"/>
      </xsd:restriction>
    </xsd:simpleType>
  </xsd:element>
  <xsd:element name="private">
    <xsd:annotation>
      <xsd:documentation>private: the actual encoding has to be replaced here</xsd:documentation>
    </xsd:annotation>
  </xsd:element>
  <xsd:complexType>
    <xsd:sequence>
      <xsd:any namespace="##any" maxOccurs="unbounded"/>
    </xsd:sequence>
  </xsd:complexType>
</xsd:choice>
</xsd:complexType>

<xsd:element name="userData" type="csta:UserData"/>

<xsd:simpleType name="TelephonyTone">
  <xsd:restriction base="xsd:string">
    <xsd:enumeration value="beep"/>
    <xsd:enumeration value="billing"/>
    <xsd:enumeration value="busy"/>
    <xsd:enumeration value="carrier"/>
    <xsd:enumeration value="confirmation"/>
    <xsd:enumeration value="dial"/>
    <xsd:enumeration value="faxCNG"/>
    <xsd:enumeration value="hold"/>
    <xsd:enumeration value="howler"/>
    <xsd:enumeration value="intrusion"/>
    <xsd:enumeration value="modemCNG"/>
    <xsd:enumeration value="park"/>
    <xsd:enumeration value="recordWarning"/>
    <xsd:enumeration value="reorder"/>
    <xsd:enumeration value="ringback"/>
    <xsd:enumeration value="silence"/>
    <xsd:enumeration value="sitVC"/>
    <xsd:enumeration value="sitIC"/>
    <xsd:enumeration value="sitRO"/>
    <xsd:enumeration value="sitNC"/>
    <xsd:enumeration value="switchSpec0"/>
    <xsd:enumeration value="switchSpec1"/>
    <xsd:enumeration value="switchSpec2"/>
    <xsd:enumeration value="switchSpec3"/>
    <xsd:enumeration value="switchSpec4"/>
    <xsd:enumeration value="switchSpec5"/>
    <xsd:enumeration value="switchSpec6"/>
    <xsd:enumeration value="switchSpec7"/>
    <xsd:enumeration value="switchSpec8"/>
    <xsd:enumeration value="switchSpec9"/>
    <xsd:enumeration value="switchSpec10"/>
    <xsd:enumeration value="switchSpec11"/>
    <xsd:enumeration value="switchSpec12"/>
    <xsd:enumeration value="switchSpec13"/>
    <xsd:enumeration value="switchSpec14"/>
    <xsd:enumeration value="switchSpec15"/>
    <xsd:enumeration value="switchSpec16"/>
    <xsd:enumeration value="switchSpec17"/>
    <xsd:enumeration value="switchSpec18"/>
    <xsd:enumeration value="switchSpec19"/>
    <xsd:enumeration value="switchSpec20"/>
    <xsd:enumeration value="switchSpec21"/>
    <xsd:enumeration value="switchSpec22"/>
  </xsd:restriction>
</xsd:simpleType>

```

© ISO/IEC 2012 – All rights reserved

```

<xsd:enumeration value="switchSpec91"/>
<xsd:enumeration value="switchSpec92"/>
<xsd:enumeration value="switchSpec93"/>
<xsd:enumeration value="switchSpec94"/>
<xsd:enumeration value="switchSpec95"/>
<xsd:enumeration value="switchSpec96"/>
<xsd:enumeration value="switchSpec97"/>
<xsd:enumeration value="switchSpec98"/>
<xsd:enumeration value="switchSpec99"/>
<xsd:enumeration value="switchSpec100"/>
</xsd:restriction>
</xsd:simpleType>

<xsd:element name="subjectOfCall" type="xsd:string"/>
<xsd:complexType name="MessageInfo">
  <xsd:sequence>
    <xsd:element name="messageInfoItem" type="csta:MessageInfoItem" maxOccurs="unbounded"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:element name="messageInfo" type="csta:MessageInfo"/>

<xsd:complexType name="MessageInfoItem">
  <xsd:sequence>
    <xsd:element name="contentTypeAndSubtype" type="xsd:string" minOccurs="0"/>
    <xsd:element name="contents" type="xsd:string"/>
    <xsd:element name="contentsLength" type="xsd:nonNegativeInteger" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:element name="languagePreferences" type="xsd:string"/>
<xsd:complexType name="DeviceHistory">
  <xsd:sequence>
    <xsd:element name="DeviceHistoryListItem" type="csta:DeviceHistoryListItem"
      maxOccurs="unbounded"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:element name="deviceHistory" type="csta:DeviceHistory"/>

<xsd:complexType name="DeviceHistoryListItem">
  <xsd:sequence>
    <xsd:element name="oldDeviceID" type="csta:RedirectionDeviceID"/>
    <xsd:element name="eventCause" type="csta:EventCause" minOccurs="0"/>
    <xsd:element name="oldConnectionID" type="csta:ConnectionID" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:element name="reason" type="csta:EventCause"/>

  <xsd:element name="locReason" type="csta:LocReason"/>
  <xsd:simpleType name="LocReason">
    <xsd:restriction base="xsd:string">
      <xsd:enumeration value="connectionToDeviceOrNetworkRestored"/>
      <xsd:enumeration value="performanceConditionRelieved"/>
    </xsd:restriction>
  </xsd:simpleType>

<xsd:element name="locCrossRefIdentifier" type="csta:LocCrossRefID"/>
<xsd:simpleType name="LocCrossRefID">
  <xsd:restriction base="xsd:string">
    <xsd:minLength value="0"/>
  </xsd:restriction>
</xsd:simpleType>

<xsd:complexType name="PresenceState">
  <xsd:sequence>

```

```

<xsd:element name="available" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="away" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="busy" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="calling" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="dnd" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="meeting" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="offline" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="unknown" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="vacation" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="applicationSpec0" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="applicationSpec1" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="applicationSpec2" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="applicationSpec3" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="applicationSpec4" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="applicationSpec5" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="applicationSpec6" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="applicationSpec7" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="applicationSpec8" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="applicationSpec9" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="applicationSpec10" type="xsd:boolean" minOccurs="0"/>
</xsd:sequence>
</xsd:complexType>

</xsd:schema>

```

9.7 Security

```

<?xml version="1.0" encoding="UTF-8"?>

<xsd:schema targetNamespace="http://www.ecma-international.org/standards/ecma-323/csta/ed6"
xmlns:xsd="http://www.w3.org/2001/XMLSchema"
xmlns:csta="http://www.ecma-international.org/standards/ecma-323/csta/ed6"
elementFormDefault="qualified" attributeFormDefault="unqualified">

  <xsd:annotation>
    <xsd:documentation>CSTA-security</xsd:documentation>
  </xsd:annotation>

  <xsd:include schemaLocation="empty.xsd"/>

  <xsd:complexType name="CSTASecurityData">
    <xsd:sequence>
      <xsd:element name="messageSequenceNumber" type="xsd:long" minOccurs="0"/>
      <xsd:element name="timeStamp" type="csta:TimeInfo" minOccurs="0"/>
      <xsd:element name="securityInfo" type="csta:SecurityInfo" minOccurs="0"/>
    </xsd:sequence>
  </xsd:complexType>

  <xsd:complexType name="SecurityInfo">
    <xsd:choice>
      <xsd:element name="string">
        <xsd:simpleType>
          <xsd:restriction base="xsd:hexBinary"/>
        </xsd:simpleType>
      </xsd:element>
      <xsd:element name="private">
        <xsd:annotation>
          <xsd:documentation>private: the actual encoding has to be replaced here</xsd:documentation>
        </xsd:annotation>
        <xsd:complexType>
          <xsd:sequence>
            <xsd:any namespace="##any" maxOccurs="unbounded"/>
          </xsd:sequence>
        </xsd:complexType>
      </xsd:element>
    </xsd:choice>
  </xsd:complexType>

```

```
<xsd:simpleType name="TimeInfo">
  <xsd:restriction base="csta:GeneralizedTime"/>
</xsd:simpleType>
```

```
<xsd:simpleType name="GeneralizedTime">
  <xsd:restriction base="xsd:string">
    <xsd:pattern value="\d{14}[\.\.]?d*[+|-]\d{4}"/>
    <xsd:pattern value="\d{14}[\.\.]?d*Z"/>
    <xsd:pattern value="\d{14}[\.\.]?d*"/>
  </xsd:restriction>
</xsd:simpleType>
```

```
</xsd:schema>
```

9.8 Common extensions

```
<?xml version="1.0" encoding="UTF-8"?>
```

```
<xsd:schema targetNamespace="http://www.ecma-international.org/standards/ecma-323/csta/ed6"
xmlns:xsd="http://www.w3.org/2001/XMLSchema"
xmlns:csta="http://www.ecma-international.org/standards/ecma-323/csta/ed6"
elementFormDefault="qualified" attributeFormDefault="unqualified">
```

```
<xsd:annotation>
  <xsd:documentation>CSTA-extension-types</xsd:documentation>
</xsd:annotation>
```

```
<xsd:include schemaLocation="security.xsd"/>
```

```
<xsd:complexType name="CSTACCommonArguments">
  <xsd:sequence>
    <xsd:element name="security" type="csta:CSTASecurityData" minOccurs="0"/>
    <xsd:element name="privateData" type="csta:CSTAPrivateData" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>
```

```
<xsd:complexType name="CSTAPrivateData">
  <xsd:choice>
    <xsd:element name="string">
      <xsd:simpleType>
        <xsd:restriction base="xsd:hexBinary"/>
      </xsd:simpleType>
    </xsd:element>
    <xsd:element name="private">
      <xsd:annotation>
        <xsd:documentation>private: the actual encoding has to be replaced here</xsd:documentation>
      </xsd:annotation>
      <xsd:complexType>
        <xsd:sequence>
          <xsd:any namespace="##any" maxOccurs="unbounded"/>
        </xsd:sequence>
      </xsd:complexType>
    </xsd:element>
  </xsd:choice>
</xsd:complexType>
```

```
<xsd:element name="extensions" type="csta:CSTACCommonArguments"/>
```

```
</xsd:schema>
```

9.9 Call control

```
<?xml version="1.0" encoding="UTF-8"?>
```

```
<xsd:schema targetNamespace="http://www.ecma-international.org/standards/ecma-323/csta/ed6"
```

```

xmlns:csta="http://www.ecma-international.org/standards/ecma-323/csta/ed6"
xmlns:xsd="http://www.w3.org/2001/XMLSchema" elementFormDefault="qualified" attributeFormDefault="unqualified">

```

```

<xsd:annotation>
  <xsd:documentation>CSTA-call-control</xsd:documentation>
</xsd:annotation>

<xsd:include schemaLocation="security.xsd"/>

<xsd:simpleType name="AutoOriginate">
  <xsd:restriction base="xsd:string">
    <xsd:enumeration value="prompt"/>
    <xsd:enumeration value="doNotPrompt"/>
  </xsd:restriction>
</xsd:simpleType>

<xsd:complexType name="CallCharacteristics">
  <xsd:sequence>
    <xsd:element name="acdCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="lowPriorityCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="priorityCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="highPriorityCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="maintainanceCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="directAgent" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="assistCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="voiceUnitCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="personalCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="sensitiveCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="confidentialCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="encryptedCall" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:element name="callCharacteristics" type="csta:CallCharacteristics"/>
<xsd:simpleType name="CallQualifyingData">
  <xsd:restriction base="xsd:hexBinary">
    <xsd:minLength value="0"/>
  </xsd:restriction>
</xsd:simpleType>

<xsd:simpleType name="ConsultOptions">
  <xsd:restriction base="xsd:string">
    <xsd:enumeration value="unrestricted"/>
    <xsd:enumeration value="consultOnly"/>
    <xsd:enumeration value="transferOnly"/>
    <xsd:enumeration value="conferenceOnly"/>
  </xsd:restriction>
</xsd:simpleType>

<xsd:element name="consultOptions" type="csta:ConsultOptions"/>

<xsd:complexType name="NetworkCapability">
  <xsd:sequence>
    <xsd:element name="networkType">
      <xsd:simpleType>
        <xsd:restriction base="xsd:string">
          <xsd:enumeration value="iSDNPublic"/>
          <xsd:enumeration value="nonISDNPublic"/>
          <xsd:enumeration value="iSDNPrivate"/>
          <xsd:enumeration value="nonISDNPrivate"/>
          <xsd:enumeration value="other"/>
        </xsd:restriction>
      </xsd:simpleType>
    </xsd:element>

    <xsd:element name="eventsProvided" minOccurs="0">
      <xsd:complexType>

```

```

<xsd:sequence>
  <xsd:element name="bridged" type="xsd:boolean" minOccurs="0"/>
  <xsd:element name="callCleared" type="xsd:boolean" minOccurs="0"/>
  <xsd:element name="conferenced" type="xsd:boolean" minOccurs="0"/>
  <xsd:element name="connectionCleared" type="xsd:boolean" minOccurs="0"/>
  <xsd:element name="delivered" type="xsd:boolean" minOccurs="0"/>
  <xsd:element name="digitsDialed" type="xsd:boolean" minOccurs="0"/>
  <xsd:element name="diverted" type="xsd:boolean" minOccurs="0"/>
  <xsd:element name="established" type="xsd:boolean" minOccurs="0"/>
  <xsd:element name="failed" type="xsd:boolean" minOccurs="0"/>
  <xsd:element name="held" type="xsd:boolean" minOccurs="0"/>
  <xsd:element name="networkCapabilitiesChange" type="xsd:boolean" minOccurs="0"/>
  <xsd:element name="networkReached" type="xsd:boolean" minOccurs="0"/>
  <xsd:element name="offered" type="xsd:boolean" minOccurs="0"/>
  <xsd:element name="originated" type="xsd:boolean" minOccurs="0"/>
  <xsd:element name="queued" type="xsd:boolean" minOccurs="0"/>
  <xsd:element name="retrieved" type="xsd:boolean" minOccurs="0"/>
  <xsd:element name="serviceInitiated" type="xsd:boolean" minOccurs="0"/>
  <xsd:element name="transferred" type="xsd:boolean" minOccurs="0"/>
</xsd:sequence>
</xsd:complexType>
</xsd:element>
</xsd:sequence>
</xsd:complexType>

<xsd:complexType name="ProgressIndicator">
  <xsd:sequence>
    <xsd:element name="progressLocation">
      <xsd:simpleType>
        <xsd:restriction base="xsd:string">
          <xsd:enumeration value="user"/>
          <xsd:enumeration value="privateNetServingLocal"/>
          <xsd:enumeration value="publicNetServingLocal"/>
          <xsd:enumeration value="transitNetwork"/>
          <xsd:enumeration value="publicNetServingRemote"/>
          <xsd:enumeration value="privateNetServingRemote"/>
          <xsd:enumeration value="localInterface"/>
          <xsd:enumeration value="internationalNetwork"/>
          <xsd:enumeration value="networkBeyondInterwk"/>
          <xsd:enumeration value="other"/>
        </xsd:restriction>
      </xsd:simpleType>
    </xsd:element>

    <xsd:element name="progressDescription">
      <xsd:simpleType>
        <xsd:restriction base="xsd:string">
          <xsd:enumeration value="iSDNProgressDesc"/>
          <xsd:enumeration value="qSIGProgressDesc"/>
          <xsd:enumeration value="other"/>
        </xsd:restriction>
      </xsd:simpleType>
    </xsd:element>
  </xsd:sequence>

</xsd:complexType>
<xsd:complexType name="ServicesPermitted">
  <xsd:sequence>
    <xsd:element name="callControlServices" type="csta:CallControlServices"/>
    <xsd:element name="callAssociatedServices" type="csta:CallAssociatedServices"/>
    <xsd:element name="mediaAttachementServices" type="csta:MediaAttachmentServices"/>
    <xsd:element name="routeingServices" type="csta:RouteingServices"/>
    <xsd:element name="voiceServices" type="csta:VoiceServices"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:element name="servicesPermitted" type="csta:ServicesPermitted"/>

```

```

<xsd:complexType name="CallLinkageDataList">
  <xsd:sequence>
    <xsd:element name="newCallLinkageData" type="csta:CallLinkageData"/>
    <xsd:element name="oldCallLinkageData" type="csta:CallLinkageData"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="CallLinkageData">
  <xsd:sequence>
    <xsd:element name="globalCallData" type="csta:GlobalCallData"/>
    <xsd:element name="threadData" type="csta:ThreadData" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:element name="callLinkageData" type="csta:CallLinkageData"/>

<xsd:complexType name="GlobalCallData">
  <xsd:sequence>
    <xsd:element name="globalCallSwitchingSubDomainName" minOccurs="0">
      <xsd:simpleType>
        <xsd:restriction base="xsd:string">
          <xsd:minLength value="1"/>
        </xsd:restriction>
      </xsd:simpleType>
    </xsd:element>
    <xsd:element name="globalCallLinkageID" type="csta:GlobalCallLinkageID"/>
    <xsd:element name="callLinkageIDTimestamp" type="csta:TimeInfo" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="GlobalCallLinkageID">
  <xsd:choice>
    <xsd:element name="subDomainCallLinkageID">
      <xsd:simpleType>
        <xsd:restriction base="xsd:string">
          <xsd:minLength value="1"/>
        </xsd:restriction>
      </xsd:simpleType>
    </xsd:element>
    <xsd:element name="globallyUniqueCallLinkageID">
      <xsd:simpleType>
        <xsd:restriction base="xsd:string">
          <xsd:minLength value="1"/>
        </xsd:restriction>
      </xsd:simpleType>
    </xsd:element>
  </xsd:choice>
</xsd:complexType>

<xsd:complexType name="ThreadData">
  <xsd:sequence>
    <xsd:element name="threadSwitchingSubDomainName" minOccurs="0">
      <xsd:simpleType>
        <xsd:restriction base="xsd:string">
          <xsd:minLength value="1"/>
        </xsd:restriction>
      </xsd:simpleType>
    </xsd:element>
    <xsd:element name="threadLinkageID" type="csta:ThreadLinkageID"/>
    <xsd:element name="threadIDTimeStamp" type="csta:TimeInfo" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="ThreadLinkageID">
  <xsd:choice>
    <xsd:element name="subDomainThreadID">
      <xsd:simpleType>
        <xsd:restriction base="xsd:string">

```

```

        <xsd:minLength value="1"/>
      </xsd:restriction>
    </xsd:simpleType>
  </xsd:element>
  <xsd:element name="globallyUniqueThreadID">
    <xsd:simpleType>
      <xsd:restriction base="xsd:string">
        <xsd:minLength value="1"/>
      </xsd:restriction>
    </xsd:simpleType>
  </xsd:element>
</xsd:choice>
</xsd:complexType>

<xsd:complexType name="CallControlServices">
  <xsd:sequence>
    <xsd:element name="acceptCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="alternateCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="answerCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callBack" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callBackMessage" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="campOnCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="clearCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="clearConnection" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="conferenceCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="consultationCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="deflectCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="dialDigits" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="directedPickupCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="groupPickupCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="holdCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="intrudeCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="joinCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="makeCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="makePredictiveCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="parkCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="reconnectCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="retrieveCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="sendMessage" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="singleStepConference" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="singleStepTransfer" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="transferCall" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="CallAssociatedServices">
  <xsd:sequence>
    <xsd:element name="associateData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="cancelTelephonyTones" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="generateDigits" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="generateTelephonyTones" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="sendUserInformation" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="changeConnectionInformation" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="MediaAttachmentServices">
  <xsd:sequence>
    <xsd:element name="attachMediaService" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="detachMediaService" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="RouteingServices">
  <xsd:sequence>
    <xsd:element name="routeRegister" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="routeRegisterCancel" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="routeRegisterAbort" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

```

```

<xsd:element name="reRoute" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="routeEnd" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="routeReject" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="routeRequest" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="routeSelect" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="routeUsed" type="xsd:boolean" minOccurs="0"/>
</xsd:sequence>
</xsd:complexType>

<xsd:complexType name="VoiceServices">
  <xsd:sequence>
    <xsd:element name="activate" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="clear" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="deactivate" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="concatenateMessage" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="deleteMessage" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="playMessage" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="queryVoiceAttribute" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="recordMessage" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="reposition" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="resume" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="review" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="setVoiceAttribute" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="stop" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="suspend" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="synthesizeMessage" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="LocationInfo">
  <xsd:sequence>
    <xsd:any namespace="##any" maxOccurs="unbounded"/>
    <!-- Allows RFC-4119 (Presence), RFC-4479 (GEOPRIV), & RFC-4479 (Data-Model), etc. namespaces & objects in instance-->
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="LocationInfoList">
  <xsd:sequence>
    <xsd:element name="locationInfoEntry" type="csta:LocationInfo" maxOccurs="unbounded"/>
  </xsd:sequence>
</xsd:complexType>

</xsd:schema>

```

9.10 Capability Exchange

```

<?xml version="1.0" encoding="UTF-8"?>

<xsd:schema targetNamespace="http://www.ecma-international.org/standards/ecma-323/csta/ed6"
  xmlns:xsd="http://www.w3.org/2001/XMLSchema" xmlns:csta="http://www.ecma-international.org/standards/ecma-323/csta/ed6"
  elementFormDefault="qualified" attributeFormDefault="unqualified">

  <xsd:annotation>
    <xsd:documentation>CSTA-capability-exchange</xsd:documentation>
  </xsd:annotation>

  <xsd:include schemaLocation="media-services.xsd"/>
  <xsd:include schemaLocation="empty.xsd"/>

  <xsd:simpleType name="ServiceCrossRefID">
    <xsd:restriction base="xsd:string">
      <xsd:minLength value="0"/>
    </xsd:restriction>
  </xsd:simpleType>

  <xsd:annotation>
    <xsd:documentation>Capability Bitmaps</xsd:documentation>
  </xsd:annotation>

```

```

</xsd:annotation>

<xsd:complexType name="LogDevServList">
  <xsd:sequence>
    <xsd:element name="callControlServList" type="csta:CallControlServList" minOccurs="0"/>
    <xsd:element name="callAssociatedServList" type="csta:CallAssociatedServList" minOccurs="0"/>
    <xsd:element name="logicalServList" type="csta:LogicalServList" minOccurs="0"/>
    <xsd:element name="mediaServList" type="csta:MediaServList" minOccurs="0"/>
    <xsd:element name="iOServicesServList" type="csta:IOServicesServList" minOccurs="0"/>
    <xsd:element name="dataCollectionServList" type="csta:DataCollectionServList" minOccurs="0"/>
    <xsd:element name="voiceServList" type="csta:VoiceServList" minOccurs="0"/>
    <xsd:element name="locationServicesServList" type="csta:LocationServicesServList" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="LogDevEvtsList">
  <xsd:sequence>
    <xsd:element name="callControlEvtsList" type="csta:CallControlEvtsList" minOccurs="0"/>
    <xsd:element name="callAssociatedEvtsList" type="csta:CallAssociatedEvtsList" minOccurs="0"/>
    <xsd:element name="logicalEvtsList" type="csta:LogicalEvtsList" minOccurs="0"/>
    <xsd:element name="mediaEvtsList" type="csta:MediaEvtsList" minOccurs="0"/>
    <xsd:element name="voiceEvtsList" type="csta:VoiceEvtsList" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="CapExchangeServList">
  <xsd:sequence>
    <xsd:element name="getCSTAFeatures" type="csta:GetCSTAFeaturesCaps" minOccurs="0"/>
    <xsd:element name="getLogicalDeviceInformation" type="csta:GetLogicalDeviceInformationCaps" minOccurs="0"/>
    <xsd:element name="getPhysicalDeviceInformation" type="csta:GetPhysicalDeviceInformationCaps" minOccurs="0"/>
    <xsd:element name="getSwitchingFunctionCaps" type="csta:GetSwitchingFunctionCapabilitiesCaps" minOccurs="0"/>
    <xsd:element name="getSwitchingFunctionDevices" type="csta:GetSwitchingFunctionDevicesCaps" minOccurs="0"/>
    <xsd:element name="switchingFunctionDevices" type="csta:SwitchingFunctionDevicesCaps" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

  <xsd:complexType name="GetCSTAFeaturesCaps">
    <xsd:sequence>
      <xsd:element name="privateDataInReq" type="xsd:boolean" minOccurs="0"/>
      <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
    </xsd:sequence>
  </xsd:complexType>

</xsd:complexType>

<xsd:complexType name="GetLogicalDeviceInformationCaps">
  <xsd:sequence>
    <xsd:element name="privateDataInReq" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="namedDeviceTypeInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="shortFormDeviceIDInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="miscMonitorCapsInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="maxCallBacksInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="maxAutoAnswerRingsInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="maxActiveCallsInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="maxHeldCallsInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="maxFwdSettingsInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="maxDevicesInConflnAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="transAndConfSetupParameter" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="transAndConfSetupConsultationInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="transAndConfSetupHoldMakeInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="transAndConfSetupAlternateInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="transAndConfSetupTwoCallsHoldInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="transAndConfSetupTwoCallsConnectedInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="mediaClassSupportInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="connectionRateListInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="delayToleranceListInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="numberOfChannelsInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="maxChannelBindInAck" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>

```

```

    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="GetPhysicalDeviceInformationCaps">
  <xsd:sequence>
    <xsd:element name="privateDataInReq" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="namedDeviceTypesInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="otherLogicalDeviceListInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="deviceModelNameInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="maxDisplaysInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="maxButtonsInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="maxLampsInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="maxRingPatternsInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="GetSwitchingFunctionCapabilitiesCaps">
  <xsd:sequence>
    <xsd:element name="privateDataInReq" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="mediaClassSupportInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="numberOfChannelsInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="maxChannelBindInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="miscMediaCallCharacteristicsInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="connectionRateListInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="delayToleranceRateListInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="pauseTimeInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="currentTimeInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="transAndConfSetupParameterInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="transAndConfSetupConsultationInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="transAndConfSetupHoldMakeInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="transAndConfSetupAlternateInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="transAndConfSetupTwoCallsHoldInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="transAndConfSetupTwoCallsConnectedInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="miscMonitorCapsInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="correlatorDataSupportedInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="dynamicFeatureSupportedInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callLinkageOptionsInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="acdModelsInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="agentLogOnModelsInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="agentStateModelsInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataVersionListInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="simpleThresholdInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="filterThresholdInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="maxDeviceHistoryEntriesInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="GetSwitchingFunctionDevicesCaps">
  <xsd:sequence>
    <xsd:element name="requestedDeviceID" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestedDeviceCategoryACD" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestedDeviceCategoryACDGroup" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestedDeviceCategoryHuntGroup" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestedDeviceCategoryPickGroup" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestedDeviceCategoryUserGroup" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestedDeviceCategoryOtherGroup" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestedDeviceCategoryNetwInterface" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestedDeviceCategoryPark" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestedDeviceCategoryRouteingDevice" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestedDeviceCategoryStation" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestedDeviceCategoryVoiceUnit" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestedDeviceCategoryGenericIV" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestedDeviceCategoryListenerIV" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestedDeviceCategoryVDTMFIV" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestedDeviceCategoryPromptIV" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>

```

```

<xsd:element name="requestedDeviceCategoryPromptQueueIV" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="requestedDeviceCategoryMessageIV" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="requestedDeviceCategoryConference" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="requestedDeviceCategoryOther" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
</xsd:sequence>
</xsd:complexType>

<xsd:complexType name="SwitchingFunctionDevicesCaps">
  <xsd:sequence>
    <xsd:element name="segmentID" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="deviceListDeviceCategory" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="deviceListNamedDeviceTypes" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="deviceListDeviceAttributes" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="deviceListDeviceModelName" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="deviceListNidGroup" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="SystemStatusServList">
  <xsd:sequence>
    <xsd:element name="changeSystemStatusFilter" type="csta:ChangeSystemStatusFilterCaps" minOccurs="0"/>
    <xsd:element name="systemRegister" type="csta:SystemRegisterCaps" minOccurs="0"/>
    <xsd:element name="systemStatusRegisterAbort" type="csta:SystemStatusRegisterAbortCaps" minOccurs="0"/>
    <xsd:element name="systemStatusRegisterCancel" type="csta:SystemStatusRegisterCancelCaps" minOccurs="0"/>
    <xsd:element name="requestSystemStatus" type="csta:RequestSystemStatusCaps" minOccurs="0"/>
    <xsd:element name="systemStatus" type="csta:SystemStatusCaps" minOccurs="0"/>
    <xsd:element name="swFunctionCapsChanged" type="csta:SwFunctionCapsChangedCaps" minOccurs="0"/>
    <xsd:element name="swFunctionDevicesChanged" type="csta:SwFunctionDevicesChangedCaps" minOccurs="0"/>
    <xsd:element name="getRegistrations" type="csta:GetRegistrationsCaps" minOccurs="0"/>
    <xsd:element name="registrationInfo" type="csta:RegistrationInfoCaps" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="ChangeSystemStatusFilterCaps">
  <xsd:sequence>
    <xsd:element name="requestedStatusFilterInitializing" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestedStatusFilterEnabled" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestedStatusFilterNormal" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestedStatusFilterMessageLost" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestedStatusFilterDisabled" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestedStatusFilterPartiallyDisabled" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestedStatusFilterOverloadImminent" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestedStatusFilterOverloadReached" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestedStatusFilterOverloadRelieved" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="SystemRegisterCaps">
  <xsd:sequence>
    <xsd:element name="requestTypesSystemStatus" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestTypesRequestSystemStatus" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestTypesSwitchingFunctionCapsChanged" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestTypesSwitchingFunctionDevicesChanged" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="statusFilterInitializing" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="statusFilterEnabled" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="statusFilterNormal" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="statusFilterMessageLost" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="statusFilterDisabled" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="statusFilterPartiallyDisabled" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="statusFilterOverloadImminent" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="statusFilterOverloadReached" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="statusFilterOverloadRelieved" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataOctetString" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

```

```

    <xsd:element name="privateDataOctetStringInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>
<xsd:complexType name="SystemStatusRegisterCancelCaps">
  <xsd:sequence>
    <xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>
<xsd:complexType name="SystemStatusRegisterAbortCaps">
  <xsd:sequence>
    <xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>
<xsd:complexType name="RequestSystemStatusCaps">
  <xsd:sequence>
    <xsd:element name="privateDataInReq" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="systemStatusInitializing" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="systemStatusEnabled" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="systemStatusNormal" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="systemStatusMessageLost" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="systemStatusDisabled" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="systemStatusPartiallyDisabled" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="systemStatusOverloadImminent" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="systemStatusOverloadReached" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="systemStatusOverloadRelieved" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="switchingFunctionSupportsSending" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="switchingFunctionSupportsReceiving" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>
<xsd:complexType name="SystemStatusCaps">
  <xsd:sequence>
    <xsd:element name="systemStatusInitializing" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="systemStatusEnabled" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="systemStatusNormal" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="systemStatusMessageLost" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="systemStatusDisabled" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="systemStatusPartiallyDisabled" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="systemStatusOverloadImminent" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="systemStatusOverloadReached" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="systemStatusOverloadRelieved" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="switchingFunctionSupportsSending" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="switchingFunctionSupportsReceiving" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>
<xsd:complexType name="SwFunctionCapsChangedCaps">
  <xsd:sequence>
    <xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>
<xsd:complexType name="SwFunctionDevicesChangedCaps">
  <xsd:sequence>
    <xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>
<xsd:complexType name="GetRegistrationsCaps">
  <xsd:sequence>
    <xsd:element name="requestedRegTypes" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>

```

```

    <xsd:element name="segmentedResponseProvided" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>

</xsd:complexType> <xsd:complexType name="RegistrationInfoCaps">
  <xsd:sequence>
    <xsd:element name="segmentID" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="MonitoringServList">
  <xsd:sequence>
    <xsd:element name="changeMonitorFilter" type="csta:ChangeMonitorFilterCaps" minOccurs="0"/>
    <xsd:element name="monitorStart" type="csta:MonitorStartCaps" minOccurs="0"/>
    <xsd:element name="monitorStop" type="csta:MonitorStopCaps" minOccurs="0"/>
    <xsd:element name="getMonitors" type="csta:GetMonitorsCaps" minOccurs="0"/>
    <xsd:element name="monitorInfo" type="csta:MonitorInfoCaps" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="ChangeMonitorFilterCaps">
  <xsd:sequence>
    <xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="MonitorStartCaps">
  <xsd:sequence>
    <xsd:element name="monitorObjectDevice" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="monitorObjectCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="requestedMonitorFilter" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="monitorTypeCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="monitorTypeDevice" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="monitorMediaClassParameter" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="monitorMediaClassAudio" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="monitorMediaClassData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="monitorMediaClassImage" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="monitorMediaClassVoice" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="monitorMediaClassChat" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="monitorMediaClassEmail" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="monitorMediaClassMessage" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="monitorMediaClassIM" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="monitorMediaClassSMS" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="monitorMediaClassMMS" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="monitorExistingCallsInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callIDOnly" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="swDomainDefaultForMonitorTypeIsDevice" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="acceptsMonitorStartWhileOOS" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="MonitorStopCaps">
  <xsd:sequence>
    <xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="switchingFunctionSupportsSending" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="switchingFunctionSupportsReceiving" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="GetMonitorsCaps">
  <xsd:sequence>
    <xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="segmentedResponseProvided" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="MonitorInfoCaps">

```

```

<xsd:sequence>
  <xsd:element name="segmentID" type="xsd:boolean" minOccurs="0"/>
  <xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
</xsd:sequence>
</xsd:complexType>

<xsd:complexType name="SnapshotServList">
  <xsd:sequence>
    <xsd:element name="snapshotCall" type="csta:SnapshotCallCaps" minOccurs="0"/>
    <xsd:element name="snapshotDevice" type="csta:SnapshotDeviceCaps" minOccurs="0"/>
    <xsd:element name="snapshotCallData" type="csta:SnapshotCallDataCaps" minOccurs="0"/>
    <xsd:element name="snapshotDeviceData" type="csta:SnapshotDeviceDataCaps" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="SnapshotCallCaps">
  <xsd:sequence>
    <xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="localConnectionStateInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="mediaServiceInfoListInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="mediaServiceVersionInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="mediaServiceInstanceInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="mediaStreamID" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="connectionInformation" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="mediaCallCharacteristicsInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callCharacteristicsInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callingDeviceInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="calledDeviceInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="subjectOfCallInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="messageInfoInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="languagePreferencesInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="deviceHistoryInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callIDOnly" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="reportsWithSnapsCallData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="locationInfoList" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="SnapshotDeviceCaps">
  <xsd:sequence>
    <xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="localCallStateCompoundCallState" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="localCallStateSimpleCallState" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="localCallStateUnknown" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="mediaServiceInfoListInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="mediaServiceVersionInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="mediaServiceInstanceInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="mediaStreamID" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="connectionInformation" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="mediaCallCharacteristicsInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="reportsWithSnapsDeviceData" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="SnapshotCallDataCaps">
  <xsd:sequence>
    <xsd:element name="segmentID" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="localConnectionState" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="mediaServiceInformationList" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="mediaServiceVersion" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="mediaServiceInstance" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="mediaStreamID" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="connectionInformation" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="locationInfoList" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>

<xsd:complexType name="SnapshotDeviceDataCaps">
  <xsd:sequence>

```

```

<xsd:element name="segmentID" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="localCallStateCompoundCallState" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="localCallStateSimpleCallState" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="localCallStateUnknown" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="mediaServiceInformationList" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="mediaServiceVersion" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="mediaServiceInstance" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="mediaStreamID" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="connectionInformation" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="mediaCallCharacteristics" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="endpointDeviceID" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
</xsd:sequence>
</xsd:complexType>
<xsd:complexType name="CallControlServList">
<xsd:sequence>
<xsd:element name="acceptCall" type="csta:AcceptCallCaps" minOccurs="0"/>
<xsd:element name="alternateCall" type="csta:AlternateCallCaps" minOccurs="0"/>
<xsd:element name="answerCall" type="csta:AnswerCallCaps" minOccurs="0"/>
<xsd:element name="callBack" type="csta:CallBackCaps" minOccurs="0"/>
<xsd:element name="callBackMessage" type="csta:CallBackMessageCaps" minOccurs="0"/>
<xsd:element name="campOnCall" type="csta:CampOnCallCaps" minOccurs="0"/>
<xsd:element name="clearCall" type="csta:ClearCallCaps" minOccurs="0"/>
<xsd:element name="clearConnection" type="csta:ClearConnectionCaps" minOccurs="0"/>
<xsd:element name="conferenceCall" type="csta:ConferenceCallCaps" minOccurs="0"/>
<xsd:element name="consultationCall" type="csta:ConsultationCallCaps" minOccurs="0"/>
<xsd:element name="deflectCall" type="csta:DeflectCallCaps" minOccurs="0"/>
<xsd:element name="dialDigits" type="csta:DialDigitsCaps" minOccurs="0"/>
<xsd:element name="directedPickupCall" type="csta:DirectedPickupCallCaps" minOccurs="0"/>
<xsd:element name="groupPickupCall" type="csta:GroupPickupCallCaps" minOccurs="0"/>
<xsd:element name="holdCall" type="csta:HoldCallCaps" minOccurs="0"/>
<xsd:element name="intrudeCall" type="csta:IntrudeCallCaps" minOccurs="0"/>
<xsd:element name="joinCall" type="csta:JoinCallCaps" minOccurs="0"/>
<xsd:element name="makeCall" type="csta:MakeCallCaps" minOccurs="0"/>
<xsd:element name="makeConnection" type="csta:MakeConnectionCaps" minOccurs="0"/>
<xsd:element name="makePredictiveCall" type="csta:MakePredictiveCallCaps" minOccurs="0"/>
<xsd:element name="parkCall" type="csta:ParkCallCaps" minOccurs="0"/>
<xsd:element name="reconnectCall" type="csta:ReconnectCallCaps" minOccurs="0"/>
<xsd:element name="retrieveCall" type="csta:RetrieveCallCaps" minOccurs="0"/>
<xsd:element name="sendMessage" type="csta:SendMessageCaps" minOccurs="0"/>
<xsd:element name="singleStepConference" type="csta:SingleStepConferenceCaps" minOccurs="0"/>
<xsd:element name="singleStepTransfer" type="csta:SingleStepTransferCaps" minOccurs="0"/>
<xsd:element name="transferCall" type="csta:TransferCallCaps" minOccurs="0"/>
</xsd:sequence>
</xsd:complexType>
<xsd:complexType name="AcceptCallCaps">
<xsd:sequence>
<xsd:element name="correlatorData" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="userData" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="deviceIDOnly" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="ackModelMultiStep" type="xsd:boolean" minOccurs="0"/>
</xsd:sequence>
</xsd:complexType>
<xsd:complexType name="AlternateCallCaps">
<xsd:sequence>
<xsd:element name="alerting" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="hold" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="queued" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="connectionReservation" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="consultOptionConsultOnly" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="consultOptionTransferOnly" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="consultOptionConferenceOnly" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="consultOptionUnrestricted" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="deviceIDOnly" type="xsd:boolean" minOccurs="0"/>

```

```

    <xsd:element name="ackModelMultiStep" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="supportsOfferedModeOfAlerting" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>
<xsd:complexType name="AnswerCallCaps">
  <xsd:sequence>
    <xsd:element name="alerting" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="initiated" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="queued" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="correlatorData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="userData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="deviceIDOnly" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="supportsOfferedModeOfAlerting" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="ackModelMultiStep" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>
<xsd:complexType name="CallBackCaps">
  <xsd:sequence>
    <xsd:element name="alerting" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="null" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="failed" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="queued" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callCharacteristics" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="subjectOfCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="languagePreferences" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="targetDeviceInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="deviceIDOnly" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="moreCallBacksNegAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="ackModelMultiStep" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>
<xsd:complexType name="CallBackMessageCaps">
  <xsd:sequence>
    <xsd:element name="alerting" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="null" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="failed" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="queued" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="targetDeviceInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="deviceIDOnly" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="moreCallBacksNegAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="ackModelMultiStep" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>
<xsd:complexType name="CampOnCallCaps">
  <xsd:sequence>
    <xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="deviceIDOnly" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="ackModelMultiStep" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>
<xsd:complexType name="ClearCallCaps">
  <xsd:sequence>
    <xsd:element name="alerting" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="connected" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="failed" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="queued" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="initiated" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="hold" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="userData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>

```

```

<xsd:element name="deviceIdOnly" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="callIDOnly" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="ackModelMultiStep" type="xsd:boolean" minOccurs="0"/>
<xsd:element name="reason" type="xsd:boolean" minOccurs="0"/>
</xsd:sequence>
</xsd:complexType>
<xsd:complexType name="ClearConnectionCaps">
  <xsd:sequence>
    <xsd:element name="alerting" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="connected" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="fail" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="queued" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="initiated" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="hold" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="correlatorData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="userData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="reason" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="deviceIdOnly" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="ackModelMultiStep" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>
<xsd:complexType name="ConferenceCallCaps">
  <xsd:sequence>
    <xsd:element name="activeCallConnected" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="activeCallHold" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="heldCallConnected" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="heldCallHold" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="connectionParameterInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="endpointDeviceID" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="resultingConnectionInfo" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="conferenceCallOnfolnAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="privateDataInAck" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="protectedAgainstClearing" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="deviceIdOnly" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="ackModelMultiStep" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>
</xsd:complexType>
<xsd:complexType name="ConsultationCallCaps">
  <xsd:sequence>
    <xsd:element name="connectionReservation" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="accountCode" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="authCode" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="correlatorData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="userData" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callCharacteristics" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callCharacteristicsACDCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callCharacteristicsLowPriorityCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callCharacteristicsPriorityCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callCharacteristicsHighPriorityCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callCharacteristicsMaintenanceCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callCharacteristicsDirectAgent" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callCharacteristicsAssistCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callCharacteristicsVoiceUnitCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callCharacteristicsPrivateCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callCharacteristicsPersonalCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callCharacteristicsSensitiveCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callCharacteristicsConfidentialCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callCharacteristicsEncryptedCall" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="mediaCallCharacteristics" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="callingConnectionInfo" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="flowDirectionTransmit" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="flowDirectionReceive" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="flowDirectionTransmitAndReceive" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="flowDirectionNone" type="xsd:boolean" minOccurs="0"/>
    <xsd:element name="numberOfChannels" type="xsd:boolean" minOccurs="0"/>
  </xsd:sequence>

```