

INTERNATIONAL STANDARD

ISO/IEC
7811-2

Second edition
1995-08-15

Identification cards — Recording technique — Part 2: Magnetic stripe

*Cartes d'identification — Technique d'enregistrement —
Partie 2: Raie magnétique*



Reference number
ISO/IEC 7811-2:1995(E)

AVA **Documents**
Document Sharing Hub

Foreword

ISO (the International Organization for Standardization) and IEC (the International Electrotechnical Commission) form the specialized system for worldwide standardization. National bodies that are members of ISO or IEC participate in the development of International Standards through technical committees established by the respective organization to deal with particular fields of technical activity. ISO and IEC technical committees collaborate in fields of mutual interest. Other international organizations, governmental and non-governmental, in liaison with ISO and IEC, also take part in the work.

In the field of information technology, ISO and IEC have established a joint technical committee, ISO/IEC JTC 1. Draft international Standards adopted by the joint technical committee are circulated to the member bodies for voting. Publication as an International Standard requires approval by at least 75 % of the national bodies casting a vote.

International Standard ISO/IEC 7811-2 was prepared by Joint Technical Committee ISO/IEC JTC 1, *Information technology*, Subcommittee SC 17, *Identification cards and related devices*.

This second edition cancels and replaces the first edition (ISO 7811-2:1985), of which it constitutes a technical revision.

ISO/IEC 7811 consists of the following parts, under the general title *Identification cards — Recording technique*:

- Part 1: *Embossing*
- Part 2: *Magnetic stripe*
- Part 3: *Location of embossed characters on ID-1 cards*
- Part 4: *Location of read-only magnetic tracks — Tracks 1 and 2*
- Part 5: *Location of read-write magnetic tracks — Track 2*

© ISO/IEC 1995

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from the publisher.

ISO/IEC Copyright Office • Case postale 56 • CH-1211 Genève 20 • Switzerland

Printed in Switzerland

Introduction

ISO/IEC 7811 is one of a series of standards describing the parameters for identification cards as defined in clause 4 and the use of such cards for international interchange.

This page intentionally left blank

Identification cards — Recording technique —

Part 2: Magnetic stripe

1 Scope

This part of ISO/IEC 7811 specifies characteristics for a magnetic stripe (including any protective overlay) on an identification card, the encoding technique and coded character sets. The magnetic recordings are intended for machine reading.

ISO/IEC 10373 specifies the test procedures used to check cards against the parameters specified in this part of ISO/IEC 7811.

This part of ISO/IEC 7811 specifies the requirements for cards used for identification. It takes into consideration both human and machine aspects and states minimum requirements.

NOTE — Numeric values in the SI and/or Imperial measurement system in this part of ISO/IEC 7811 may have been rounded off and therefore are consistent with, but not exactly equal to, each other. Either system may be used, but the two should not be intermixed or reconverted. The original design was made using the Imperial measurement system.

2 Conformance

An identification card is in conformance with this part of ISO/IEC 7811 if it meets all mandatory requirements specified herein.

A prerequisite for conformance with this part of ISO/IEC 7811 is conformance with ISO/IEC 7810.

3 Normative references

The following standards contain provisions which, through reference in this text, constitute provisions of

this part of ISO/IEC 7811. At the time of publication the editions indicated were valid. All standards are subject to revision and parties to agreements based on this part of ISO/IEC 7811 are encouraged to investigate the possibility of applying the most recent editions of the standards indicated below. Members of IEC and ISO maintain registers of currently valid International Standards.

ISO/IEC 7810:1995, *Identification cards — Physical characteristics*.

ISO/IEC 7811-4:1995, *Identification cards — Recording technique — Part 4: Location of read-only magnetic tracks — Tracks 1 and 2*.

ISO/IEC 7811-5:1995, *Identification cards — Recording technique — Part 5: Location of read-write magnetic track — Track 3*.

ISO/IEC 10373:1993, *Identification cards — Test methods*.

4 Definitions

For the purposes of this part of ISO/IEC 7811, the definition of "identification card" given in ISO/IEC 7810 and the following definition apply.

4.1 primary standard: The primary standard is based on the Master Standard Reference Tape (computer amplitude reference) established by the United States National Institute of Standards and Technology (NIST).

NOTE — The relationship between the Master Standard Reference Tape and secondary reference tapes SRM 3200 is stated on the NIST certificate.

For the purposes of this part of ISO/IEC 7811, reference cards RM 7811-2 batch C equipped with SRM 3200 No. 18-67B are considered as primary standards defining not only the average signal amplitude at 8 flux transitions per mm (certified by NIST) but also that at 20 flux transitions per mm.

A group of such reference cards is held at the Physikalisch-Technische Bundesanstalt (PTB). They represent this primary standard.

4.2 secondary standard (reference card):

Identification card with defined properties and equipped with a SRM 3200 or equivalent tape, the properties of which are known and stated in relation to the primary standard.

It is intended that reference cards be used for the calibration of tertiary standards for use in routine calibration.

NOTE — Reference cards, Part No. RM 7811/2 Batch D, can be ordered from Physikalisch-Technische Bundesanstalt, Lab. 1.41 - Bundesallee 100, D-38116 Braunschweig, Germany, as long as supplies are available (probably from 1995 to 2001).

4.3 unused un-encoded card: Card possessing all components required for its intended purpose, which has not been subjected to any personalization or testing operation. The card has been stored in a clean environment without more than 48 hour exposure to day-light at temperatures between 5 °C to 30 °C (41 °F to 86 °F) and humidity between 10 % to 90 % without experiencing thermal shock.

4.4 unused encoded card: Unused, unencoded card according to 4.3 which has only been encoded with all the data required for its intended purpose (e.g. magnetic encoding, embossing, electronic encoding).

The environmental conditions in which the unused encoded card experiences are to be the same as for the unused un-encoded card.

4.5 returned card: Embossed and/or encoded card after it has been issued to the card holder and returned for the purpose of testing.

4.6 flux transition: Location of the maximum magnetic flux component normal to the surface of the magnetic stripe.

4.7 reference current (I_R): Minimum recorded current amplitude which causes on the reference card, under the given test conditions, a readback

voltage amplitude equal to 80 % of the reference signal amplitude U_R , (see figure 5) at a density of 8 flux transitions per mm (200 flux transitions per in).

4.8 test recording currents: Two test recording currents at 350 % ($I_{\min}$) and 500 % ($I_{\max}$) of the reference current (I_R) shall be used. $I_{\min} = 3,5 I_R$; $I_{\max} = 5,0 I_R$.

4.9 individual signal amplitude (U_i): Base-to-peak amplitude of a single readback voltage signal.

4.10 average signal amplitude (U_A): Average signal amplitude (U_A) is the sum of the absolute value of the amplitude of each signal peak (U_i) divided by the number of signal peaks (n).

$$U_A = \frac{\sum_{k=1}^n |U_{ik}|}{n}$$

4.11 reference signal amplitude (U_R): Maximum average signal amplitude of the reference card corrected to the primary standard.

4.12 physical recording density: Number of flux transitions recorded on a track per unit length.

NOTE — When testing with densities of 6 flux transitions per mm (150 flux transitions per in) and 16,6 flux transitions per mm (420 flux transitions per in) the correlation factors are:

$$\frac{U_A \text{ at 6 flux transitions per mm (150 flux transitions per in)}}{U_A \text{ at 8 flux transitions per mm (200 flux transitions per in)}} \cdot 100 = 100 \%$$

$$U_A \text{ at 8 flux transitions per mm (200 flux transitions per in)}$$

$$U_A \text{ at 16,6 flux transitions per mm (420 flux transitions per in)}$$

$$\frac{U_A \text{ at 16,6 flux transitions per mm (420 flux transitions per in)}}{U_A \text{ at 20 flux transitions per mm (500 flux transitions per in)}} \cdot 100 = 105 \%$$

$$U_A \text{ at 20 flux transitions per mm (500 flux transitions per in)}$$

4.13 bit density: Number of data bits stored per unit of length (bits per mm or bits per in).

4.14 bit cell: Distance between two clocking flux transitions.

4.15 sub interval: Bit cell divided by two.