

---

---

**Information technology —  
Telecommunications and information  
exchange between systems — Local  
and metropolitan area networks —  
Specific requirements —**

**Part 3:  
Standard for Ethernet**

**AMENDMENT 10: Media access control  
parameters, physical layers, and  
management parameters for 200 Gb/s  
and 400 Gb/s operation**

*Technologies de l'information — Télécommunications et échange  
d'information entre systèmes — Réseaux locaux et métropolitains —  
Prescriptions spécifiques —*

*Partie 3: Norme pour Ethernet*

*AMENDEMENT 10: Paramètres de commande d'accès aux supports,  
couches physiques et paramètres de gestion pour le fonctionnement  
en 200 Gb/s et 400 Gb/s*



**COPYRIGHT PROTECTED DOCUMENT**

© IEEE 2017

All rights reserved. Unless otherwise specified, or required in the context of its implementation, no part of this publication may be reproduced or utilized otherwise in any form or by any means, electronic or mechanical, including photocopying, or posting on the internet or an intranet, without prior written permission. Permission can be requested from either ISO or IEEE at the respective address below or ISO's member body in the country of the requester.

ISO copyright office  
CP 401 • Ch. de Blandonnet 8  
CH-1214 Vernier, Geneva  
Phone: +41 22 749 01 11  
Fax: +41 22 749 09 47  
Email: [copyright@iso.org](mailto:copyright@iso.org)  
Website: [www.iso.org](http://www.iso.org)

Published in Switzerland

Institute of Electrical and Electronics Engineers, Inc  
3 Park Avenue, New York  
NY 10016-5997, USA

Email: [stds.ipr@ieee.org](mailto:stds.ipr@ieee.org)  
Website: [www.ieee.org](http://www.ieee.org)

## Foreword

ISO (the International Organization for Standardization) and IEC (the International Electrotechnical Commission) form the specialized system for worldwide standardization. National bodies that are members of ISO or IEC participate in the development of International Standards through technical committees established by the respective organization to deal with particular fields of technical activity. ISO and IEC technical committees collaborate in fields of mutual interest. Other international organizations, governmental and non-governmental, in liaison with ISO and IEC, also take part in the work. In the field of information technology, ISO and IEC have established a joint technical committee, ISO/IEC JTC 1.

The procedures used to develop this document and those intended for its further maintenance are described in the ISO/IEC Directives, Part 1. In particular, the different approval criteria needed for the different types of ISO documents should be noted (see [www.iso.org/directives](http://www.iso.org/directives)).

IEEE Standards documents are developed within the IEEE Societies and the Standards Coordinating Committees of the IEEE Standards Association (IEEE-SA) Standards Board. The IEEE develops its standards through a consensus development process, approved by the American National Standards Institute, which brings together volunteers representing varied viewpoints and interests to achieve the final product. Volunteers are not necessarily members of the Institute and serve without compensation. While the IEEE administers the process and establishes rules to promote fairness in the consensus development process, the IEEE does not independently evaluate, test, or verify the accuracy of any of the information contained in its standards.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO and IEC shall not be held responsible for identifying any or all such patent rights. Details of any patent rights identified during the development of the document will be in the Introduction and/or on the ISO list of patent declarations received (see [www.iso.org/patents](http://www.iso.org/patents)).

Any trade name used in this document is information given for the convenience of users and does not constitute an endorsement.

For an explanation of the voluntary nature of standards, the meaning of ISO specific terms and expressions related to conformity assessment, as well as information about ISO's adherence to the World Trade Organization (WTO) principles in the Technical Barriers to Trade (TBT), see [www.iso.org/iso/foreword.html](http://www.iso.org/iso/foreword.html).

ISO/IEC/IEEE 8802-3:2017/Amd.10 was prepared by the LAN/MAN of the IEEE Computer Society (as IEEE Std 802.3bs-2017) and drafted in accordance with its editorial rules. It was adopted, under the “fast-track procedure” defined in the Partner Standards Development Organization cooperation agreement between ISO and IEEE, by Joint Technical Committee ISO/IEC JTC 1, *Information technology*, Subcommittee SC6, *Telecommunications and information exchange between systems*.

A list of all parts in the ISO/IEC/IEEE 8802 series can be found on the ISO website.

Any feedback or questions on this document should be directed to the user's national standards body. A complete listing of these bodies can be found at [www.iso.org/members.html](http://www.iso.org/members.html).



**IEEE Std 802.3bs™-2017**  
(Amendment to  
IEEE Std 802.3™-2015  
as amended by  
IEEE Std 802.3bw™-2015,  
IEEE Std 802.3by™-2016,  
IEEE Std 802.3bq™-2016,  
IEEE Std 802.3bp™-2016,  
IEEE Std 802.3br™-2016,  
IEEE Std 802.3bn™-2016,  
IEEE Std 802.3bz™-2016,  
IEEE Std 802.3bu™-2016,  
IEEE Std 802.3bv™-2017, and  
IEEE Std 802.3-2015/Cor 1-2017)

# **IEEE Standard for Ethernet**

## **Amendment 10: Media Access Control Parameters, Physical Layers, and Management Parameters for 200 Gb/s and 400 Gb/s Operation**

**LAN/MAN Standards Committee  
of the  
IEEE Computer Society**

**Approved 6 December 2017  
of the  
IEEE-SA Standards Board**

**Abstract:** Clause 116 through Clause 124 and Annex 119A through Annex 120E are added by this amendment to IEEE Std 802.3-2015. This amendment includes IEEE 802.3 Media Access Control (MAC) parameters, Physical Layer specifications, and management parameters for the transfer of IEEE 802.3 format frames at 200 Gb/s and 400 Gb/s.

**Keywords:** 200 Gb/s Ethernet, 200GAUI-4, 200GAUI-8, 200GBASE-DR4, 200GBASE-FR4, 200GBASE-LR4, 200GBASE-R, 200GMII, 200GXS, 400 Gb/s Ethernet, 400GAUI-8, 400GAUI-16, 400GBASE-DR4, 400GBASE-FR8, 400GBASE-LR8, 400GBASE-SR16, 400GBASE-R, 400GMII, 400GXS, EEE, Energy Efficient Ethernet, Ethernet, FEC, forward error correction, IEEE 802.3™, IEEE 802.3bs™, MMF, PAM4, Physical Medium Dependent sublayer, PMD, SMF

---

The Institute of Electrical and Electronics Engineers, Inc.  
3 Park Avenue, New York, NY 10016-5997, USA

Copyright © 2017 by The Institute of Electrical and Electronics Engineers, Inc.  
All rights reserved. Published 12 December 2017. Printed in the United States of America.

IEEE and 802 are registered trademarks in the U.S. Patent & Trademark Office, owned by The Institute of Electrical and Electronics Engineers, Incorporated.

PDF: ISBN 978-1-5044-4450-7 STD22871  
Print: ISBN 978-1-5044-4451-4 STDPD22871

IEEE prohibits discrimination, harassment and bullying. For more information, visit <http://www.ieee.org/web/aboutus/whatis/policies/p9-26.html>.

No part of this publication may be reproduced in any form, in an electronic retrieval system or otherwise, without the prior written permission of the publisher.

## Important Notices and Disclaimers Concerning IEEE Standards Documents

IEEE documents are made available for use subject to important notices and legal disclaimers. These notices and disclaimers, or a reference to this page, appear in all standards and may be found under the heading “Important Notices and Disclaimers Concerning IEEE Standards Documents.” They can also be obtained on request from IEEE or viewed at <http://standards.ieee.org/IPR/disclaimers.html>.

### Notice and Disclaimer of Liability Concerning the Use of IEEE Standards Documents

IEEE Standards documents (standards, recommended practices, and guides), both full-use and trial-use, are developed within IEEE Societies and the Standards Coordinating Committees of the IEEE Standards Association (“IEEE-SA”) Standards Board. IEEE (“the Institute”) develops its standards through a consensus development process, approved by the American National Standards Institute (“ANSI”), which brings together volunteers representing varied viewpoints and interests to achieve the final product. IEEE Standards are documents developed through scientific, academic, and industry-based technical working groups. Volunteers in IEEE working groups are not necessarily members of the Institute and participate without compensation from IEEE. While IEEE administers the process and establishes rules to promote fairness in the consensus development process, IEEE does not independently evaluate, test, or verify the accuracy of any of the information or the soundness of any judgments contained in its standards.

IEEE Standards do not guarantee or ensure safety, security, health, or environmental protection, or ensure against interference with or from other devices or networks. Implementers and users of IEEE Standards documents are responsible for determining and complying with all appropriate safety, security, environmental, health, and interference protection practices and all applicable laws and regulations.

IEEE does not warrant or represent the accuracy or content of the material contained in its standards, and expressly disclaims all warranties (express, implied and statutory) not included in this or any other document relating to the standard, including, but not limited to, the warranties of: merchantability; fitness for a particular purpose; non-infringement; and quality, accuracy, effectiveness, currency, or completeness of material. In addition, IEEE disclaims any and all conditions relating to: results; and workmanlike effort. IEEE standards documents are supplied “AS IS” and “WITH ALL FAULTS.”

Use of an IEEE standard is wholly voluntary. The existence of an IEEE standard does not imply that there are no other ways to produce, test, measure, purchase, market, or provide other goods and services related to the scope of the IEEE standard. Furthermore, the viewpoint expressed at the time a standard is approved and issued is subject to change brought about through developments in the state of the art and comments received from users of the standard.

In publishing and making its standards available, IEEE is not suggesting or rendering professional or other services for, or on behalf of, any person or entity nor is IEEE undertaking to perform any duty owed by any other person or entity to another. Any person utilizing any IEEE Standards document, should rely upon his or her own independent judgment in the exercise of reasonable care in any given circumstances or, as appropriate, seek the advice of a competent professional in determining the appropriateness of a given IEEE standard.

IN NO EVENT SHALL IEEE BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO: PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE PUBLICATION, USE OF, OR RELIANCE UPON ANY STANDARD, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE AND REGARDLESS OF WHETHER SUCH DAMAGE WAS FORESEEABLE.

## Translations

The IEEE consensus development process involves the review of documents in English only. In the event that an IEEE standard is translated, only the English version published by IEEE should be considered the approved IEEE standard.

## Official statements

A statement, written or oral, that is not processed in accordance with the IEEE-SA Standards Board Operations Manual shall not be considered or inferred to be the official position of IEEE or any of its committees and shall not be considered to be, or be relied upon as, a formal position of IEEE. At lectures, symposia, seminars, or educational courses, an individual presenting information on IEEE standards shall make it clear that his or her views should be considered the personal views of that individual rather than the formal position of IEEE.

## Comments on standards

Comments for revision of IEEE Standards documents are welcome from any interested party, regardless of membership affiliation with IEEE. However, IEEE does not provide consulting information or advice pertaining to IEEE Standards documents. Suggestions for changes in documents should be in the form of a proposed change of text, together with appropriate supporting comments. Since IEEE standards represent a consensus of concerned interests, it is important that any responses to comments and questions also receive the concurrence of a balance of interests. For this reason, IEEE and the members of its societies and Standards Coordinating Committees are not able to provide an instant response to comments or questions except in those cases where the matter has previously been addressed. For the same reason, IEEE does not respond to interpretation requests. Any person who would like to participate in revisions to an IEEE standard is welcome to join the relevant IEEE working group.

Comments on standards should be submitted to the following address:

Secretary, IEEE-SA Standards Board  
445 Hoes Lane  
Piscataway, NJ 08854 USA

## Laws and regulations

Users of IEEE Standards documents should consult all applicable laws and regulations. Compliance with the provisions of any IEEE Standards document does not imply compliance to any applicable regulatory requirements. Implementers of the standard are responsible for observing or referring to the applicable regulatory requirements. IEEE does not, by the publication of its standards, intend to urge action that is not in compliance with applicable laws, and these documents may not be construed as doing so.

## Copyrights

IEEE draft and approved standards are copyrighted by IEEE under U.S. and international copyright laws. They are made available by IEEE and are adopted for a wide variety of both public and private uses. These include both use, by reference, in laws and regulations, and use in private self-regulation, standardization, and the promotion of engineering practices and methods. By making these documents available for use and adoption by public authorities and private users, IEEE does not waive any rights in copyright to the documents.

## Photocopies

Subject to payment of the appropriate fee, IEEE will grant users a limited, non-exclusive license to photocopy portions of any individual standard for company or organizational internal use or individual, non-commercial use only. To arrange for payment of licensing fees, please contact Copyright Clearance Center, Customer Service, 222 Rosewood Drive, Danvers, MA 01923 USA; +1 978 750 8400. Permission to photocopy portions of any individual standard for educational classroom use can also be obtained through the Copyright Clearance Center.

## Updating of IEEE Standards documents

Users of IEEE Standards documents should be aware that these documents may be superseded at any time by the issuance of new editions or may be amended from time to time through the issuance of amendments, corrigenda, or errata. An official IEEE document at any point in time consists of the current edition of the document together with any amendments, corrigenda, or errata then in effect.

Every IEEE standard is subjected to review at least every ten years. When a document is more than ten years old and has not undergone a revision process, it is reasonable to conclude that its contents, although still of some value, do not wholly reflect the present state of the art. Users are cautioned to check to determine that they have the latest edition of any IEEE standard.

In order to determine whether a given document is the current edition and whether it has been amended through the issuance of amendments, corrigenda, or errata, visit the IEEE Xplore at <http://ieeexplore.ieee.org/> or contact IEEE at the address listed previously. For more information about the IEEE-SA or IEEE's standards development process, visit the IEEE-SA Website at <http://standards.ieee.org>.

## Errata

Errata, if any, for all IEEE standards can be accessed on the IEEE-SA Website at the following URL: <http://standards.ieee.org/findstds/errata/index.html>. Users are encouraged to check this URL for errata periodically.

## Patents

Attention is called to the possibility that implementation of this standard may require use of subject matter covered by patent rights. By publication of this standard, no position is taken by the IEEE with respect to the existence or validity of any patent rights in connection therewith. If a patent holder or patent applicant has filed a statement of assurance via an Accepted Letter of Assurance, then the statement is listed on the IEEE-SA Website at <http://standards.ieee.org/about/sasb/patcom/patents.html>. Letters of Assurance may indicate whether the Submitter is willing or unwilling to grant licenses under patent rights without compensation or under reasonable rates, with reasonable terms and conditions that are demonstrably free of any unfair discrimination to applicants desiring to obtain such licenses.

Essential Patent Claims may exist for which a Letter of Assurance has not been received. The IEEE is not responsible for identifying Essential Patent Claims for which a license may be required, for conducting inquiries into the legal validity or scope of Patents Claims, or determining whether any licensing terms or conditions provided in connection with submission of a Letter of Assurance, if any, or in any licensing agreements are reasonable or non-discriminatory. Users of this standard are expressly advised that determination of the validity of any patent rights, and the risk of infringement of such rights, is entirely their own responsibility. Further information may be obtained from the IEEE Standards Association.

## Participants

The following individuals were officers and members of the IEEE 802.3 working group at the beginning of the IEEE P802.3bs working group ballot. Individuals may have not voted or may have voted for approval, disapproval, or abstention on this amendment.

**David J. Law**, *IEEE 802.3 Working Group Chair*  
**Adam Healey**, *IEEE 802.3 Working Group Vice-Chair*  
**Pete Anslow**, *IEEE 802.3 Working Group Secretary*  
**Steven B. Carlson**, *IEEE 802.3 Working Group Executive Secretary*  
**Valerie Maguire**, *IEEE 802.3 Working Group Treasurer*

**John D'Ambrosia**, *IEEE P802.3bs 200 Gb/s and 400 Gb/s Ethernet Task Force Chair*  
**Pete Anslow**, *IEEE P802.3bs 200 Gb/s and 400 Gb/s Ethernet Task Force Editor-in-Chief*  
**Mark Gustlin**, *IEEE P802.3bs 200 Gb/s and 400 Gb/s Ethernet Task Force Editor*  
*for Clauses 117, 118, 119, Annex 119A*  
**Steve Trowbridge**, *IEEE P802.3bs 200 Gb/s and 400 Gb/s Ethernet Task Force Editor*  
*for Clause 120, Annex 120A*  
**Peter Stassar**, *IEEE P802.3bs 200 Gb/s and 400 Gb/s Ethernet Task Force Editor*  
*for Clauses 121, 122, 124*  
**Jonathan King**,<sup>1</sup> *IEEE P802.3bs 200 Gb/s and 400 Gb/s Ethernet Task Force Editor*  
*for Clause 123*  
**Andre Szczepanek**, *IEEE P802.3bs 200 Gb/s and 400 Gb/s Ethernet Task Force Editor*  
*for Annexes 120D, 120E*

|                       |                     |                    |
|-----------------------|---------------------|--------------------|
| Justin Abbott         | David Chalupsky     | Andrew Gardner     |
| David Abramson        | Jacky Chang         | Claude Gauthier    |
| Shadi Abughazaleh     | Xin Chang           | Ali Ghiasi         |
| Mohammad Ahmed        | Ahmad Chini         | Joel Goergen       |
| Eric Baden            | Keng Hua Chuang     | Volker Goetzfried  |
| Amrik Bains           | Christopher R. Cole | Zhigang Gong       |
| Thananya Baldwin      | Yair Darshan        | Steven Gorshe      |
| Denis Beaudoin        | Piers Dawe          | Robert Grow        |
| Christian Beia        | Fred Dawson         | Marek Hajduczenia  |
| Michael Bennett       | Wael Diab           | Takehiro Hayashi   |
| Vipul Bhatt           | Eric DiBiaso        | Yasuo Hidaka       |
| William Bliss         | John Dillard        | Rita Horner        |
| Brad Booth            | Daniel Dillow       | Bernd Hormmeyer    |
| Martin Bouda          | Thuyen Dinh         | Victor Hou         |
| Ralf-Peter Braun      | Curtis Donahue      | Yasuhiro Hyakutake |
| Theodore Brillhart    | Dan Dove            | Hideki Isono       |
| Paul Brooks           | Mike Dudek          | Tom Issenhuth      |
| Alan Brown            | David Dwelley       | Kenneth Jackson    |
| Matthew Brown         | Frank Effenberger   | Andrew Jimenez     |
| Chris Bullock         | Hesham Elbakoury    | Chad Jones         |
| Jairo Bustos Heredia  | David Estes         | Peter Jones        |
| Adrian Butter         | John Ewen           | Manabu Kagami      |
| Francesco Caggioni    | Ramin Farjad        | Upen Kareti        |
| Anthony Calbone       | Shahar Feldman      | Keisuke Kawahara   |
| Clark Carty           | James Fife          | Yasuaki Kawatsu    |
| Craig Chabot          | Alan Flatman        | Michael Kelsen     |
| Geoffrey Chacon Simon | Matthias Fritsche   | Scott Kipp         |
| Mandeep Chadha        | Richard Frosch      | Michael Klempa     |

<sup>1</sup>Not a member of the IEEE 802.3 working group at the beginning of the working group ballot.

|                      |                              |                     |
|----------------------|------------------------------|---------------------|
| Curtis Knittle       | Edward Nakamoto              | Robert Stone        |
| Shigeru Kobayashi    | Gary Nicholl                 | David Stover        |
| Daniel Koehler       | Kevin Noll                   | Junqing Sun         |
| Paul Kolesar         | Mark Nowell                  | Ken-Ichi Suzuki     |
| Tom Kolze            | David Ofelt                  | Steve Swanson       |
| Glen Kramer          | Tom Palkert                  | William Szeto       |
| Hans Lackner         | Hui Pan                      | Bharat Tailor       |
| Jeffrey Lapak        | Sesha Panguluri              | Takayuki Tajima     |
| Mark Laubach         | Vasu Parthasarathy           | Satoshi Takahashi   |
| Han Hyub Lee         | Petar Pepeljugin             | Kohichi Tamura      |
| David Lewis          | Gerald Pepper                | Brian Teipen        |
| Jon Lewis            | Ruben Perez De Aranda Alonso | Geoffrey Thompson   |
| Mike Peng Li         | Michael Peters               | Pirooz Tooyserkani  |
| Jane Lim             | Phong Pham                   | Albert Tretter      |
| Dekun Liu            | Jean Picard                  | Yoshihiro Tsukamoto |
| Hai-Feng Liu         | William Powell               | Ed Ulrichs          |
| William Lo           | Rick Rabinovich              | Alexander Umnov     |
| Miklos Lukacs        | Adee Ran                     | Sterling A. Vaden   |
| Kent Lusted          | Alon Regev                   | Stefano Valle       |
| Jeffery Maki         | Duane Remein                 | Paul Vanderlaan     |
| David Malicoat       | Victor Renteria              | Robert Wagner       |
| Yonatan Malkiman     | Christopher Roth             | Dylan Walker        |
| Arthur Marris        | Salvatore Rotolo             | Haifei Wang         |
| Takeo Masuda         | Toshiaki Sakai               | Roy Wang            |
| Erdem Matoglu        | Jorge Salinger               | Tongtong Wang       |
| Naoki Matsuda        | Sam Sambasivan               | Xinyuan Wang        |
| Mick McCarthy        | Edward Sayre                 | Matthias Wendt      |
| Brett McClellan      | Dieter Schicketanz           | Oded Wertheim       |
| Thomas McDermott     | Fred Schindler               | Natalie Wienckowski |
| John McDonough       | Hossein Sedarat              | Ludwig Winkel       |
| Larry McMillan       | Naoshi Serizawa              | Peter Wu            |
| Richard Mei          | Masood Shariff               | Dayin Xu            |
| Richard Mellitz      | Ramin Shirani                | Yu Xu               |
| Bryan Moffitt        | Tom Skaar                    | Jun Yi              |
| Ardeshir Mohammadian | Jeff Slavick                 | Lennart Yseboodt    |
| Paul Mooney          | Daniel Smith                 | Hayato Yuki         |
| Dale Murray          | Scott Sommers                | Andrew Zambell      |
| Henry Muyschondt     | Yoshiaki Sone                | Yan Zhuang          |
| James Nadolny        | Tom Souvignier               | George Zimmerman    |
|                      | Heath Stewart                |                     |

The following members of the individual balloting committee voted on this amendment. Balloters may have voted for approval, disapproval, or abstention.

|                      |                   |                     |
|----------------------|-------------------|---------------------|
| Mohammad Ahmed       | Werner Hoelzl     | Glenn Parsons       |
| Thomas Alexander     | Rita Horner       | Bansi Patel         |
| Pete Anslow          | Noriyuki Ikeuchi  | Arumugam Paventhan  |
| Butch Anton          | Sergiu Iordanescu | Michael Peters      |
| Stefan Aust          | Osamu Ishida      | David Piehler       |
| Eric Baden           | Atsushi Ito       | Rick Pimpinella     |
| Saman Behtash        | Raj Jain          | Adee Ran            |
| Ralf-Peter Braun     | SangKwon Jeong    | Alon Regev          |
| Nancy Bravin         | Piotr Karocki     | Maximilian Riegel   |
| Theodore Brillhart   | Stuart Kerry      | Robert Robinson     |
| Matthew Brown        | Yongbum Kim       | Toshiaki Sakai      |
| Jairo Bustos Heredia | Jonathan King     | Osman Sakr          |
| William Byrd         | Paul Kolesar      | Dieter Schicketanz  |
| Steven B. Carlson    | Mark Laubach      | Takeshi Shimizu     |
| Juan Carreon         | David J. Law      | Kapil Shrikhande    |
| David Chalupsky      | June Hee Lee      | Jeff Slavick        |
| Boung Wook Cho       | David Lewis       | Thomas Starai       |
| Keith Chow           | Jon Lewis         | Peter Stassar       |
| Keng Hua Chuang      | Mike-Peng Li      | Rene Struik         |
| Charles Cook         | Arthur H. Light   | Walter Struppler    |
| Eugene Dai           | Kent Lusted       | Mitsutoshi Sugawara |
| John D'Ambrosia      | Elvis Maculuba    | Patrik Sundstrom    |
| Piers J. G. Dawe     | Valerie Maguire   | James Theodoras     |
| Patrick Diamond      | Jeffery Maki      | David Thompson      |
| Michael Dudek        | Arthur Marris     | Geoffrey Thompson   |
| John French          | Mick McCarthy     | Michael Thompson    |
| Matthias Fritsche    | Brett McClellan   | Steven Tilden       |
| Yukihiro Fujimoto    | Thomas McDermott  | Steve Trowbridge    |
| Ali Ghiasi           | Michael McInnis   | Mark-Rene Uchida    |
| Joel Goergen         | Richard Mellitz   | Alexander Umnov     |
| Zhigang Gong         | Tremont Miao      | Paul Vanderlaan     |
| James Graba          | Jeffrey Moore     | Dmitri Varsanofiev  |
| Randall Groves       | Charles Moorwood  | George Vlantis      |
| Robert Grow          | Jose Morales      | Khurram Waheed      |
| Mark Gustlin         | Michael Newman    | Oded Wertheim       |
| Adam Healey          | Nick S. A. Nikjoo | Andreas Wolf        |
| Marco Hernandez      | Paul Nikolich     | Peter Wu            |
| David Hess           | Mark Nowell       | Jun Xu              |
| Yasuo Hidaka         | Satoshi Obara     | Oren Yuen           |
| Guido Hiertz         | Thomas Palkert    | Zhen Zhou           |

When the IEEE-SA Standards Board approved this amendment on 6 December 2017, it had the following membership:

**Jean-Philippe Faure**, *Chair*  
**Gary Hoffman**, *Vice Chair*  
**John D. Kulick**, *Past Chair*  
**Konstantinos Karachalios**, *Secretary*

|                    |                       |                 |
|--------------------|-----------------------|-----------------|
| Chuck Adams        | Thomas Kochy          | Robby Robson    |
| Masayuki Ariyoshi  | Joseph L. Koepfinger* | Dorothy Stanley |
| Ted Burse          | Kevin Lu              | Adrian Stephens |
| Stephen Dukes      | Daleep Mohla          | Mehmet Ulema    |
| Doug Edwards       | Damir Novosel         | Phil Wennblom   |
| J. Travis Griffith | Ronald C. Petersen    | Howard Wolfman  |
| Michael Janezic    | Annette D. Reilly     | Yu Yuan         |

\*Member Emeritus

## Introduction

This introduction is not part of IEEE Std 802.3bs-2017, IEEE Standard for Ethernet—Amendment 10: Media Access Control Parameters, Physical Layers, and Management Parameters for 200 Gb/s and 400 Gb/s Operation.

IEEE Std 802.3™ was first published in 1985. Since the initial publication, many projects have added functionality or provided maintenance updates to the specifications and text included in the standard. Each IEEE 802.3 project/amendment is identified with a suffix (e.g., IEEE Std 802.3ba™-2010).

The half duplex Media Access Control (MAC) protocol specified in IEEE Std 802.3-1985 is Carrier Sense Multiple Access with Collision Detection (CSMA/CD). This MAC protocol was key to the experimental Ethernet developed at Xerox Palo Alto Research Center, which had a 2.94 Mb/s data rate. Ethernet at 10 Mb/s was jointly released as a public specification by Digital Equipment Corporation (DEC), Intel and Xerox in 1980. Ethernet at 10 Mb/s was approved as an IEEE standard by the IEEE Standards Board in 1983 and subsequently published in 1985 as IEEE Std 802.3-1985. Since 1985, new media options, new speeds of operation, and new capabilities have been added to IEEE Std 802.3. A full duplex MAC protocol was added in 1997.

Some of the major additions to IEEE Std 802.3 are identified in the marketplace with their project number. This is most common for projects adding higher speeds of operation or new protocols. For example, IEEE Std 802.3u™ added 100 Mb/s operation (also called Fast Ethernet), IEEE Std 802.3z added 1000 Mb/s operation (also called Gigabit Ethernet), IEEE Std 802.3ae added 10 Gb/s operation (also called 10 Gigabit Ethernet), IEEE Std 802.3ah™ specified access network Ethernet (also called Ethernet in the First Mile) and IEEE Std 802.3ba added 40 Gb/s operation (also called 40 Gigabit Ethernet) and 100 Gb/s operation (also called 100 Gigabit Ethernet). These major additions are all now included in and are superseded by IEEE Std 802.3-2015 and are not maintained as separate documents.

At the publication date of IEEE Std 802.3bs-2017, IEEE Std 802.3 is composed of the following documents:

IEEE Std 802.3-2015

Section One—Includes Clause 1 through Clause 20 and Annex A through Annex H and Annex 4A. Section One includes the specifications for 10 Mb/s operation and the MAC, frame formats and service interfaces used for all speeds of operation.

Section Two—Includes Clause 21 through Clause 33 and Annex 22A through Annex 33E. Section Two includes management attributes for multiple protocols and speed of operation as well as specifications for providing power over twisted pair cabling for multiple operational speeds. It also includes general information on 100 Mb/s operation as well as most of the 100 Mb/s Physical Layer specifications.

Section Three—Includes Clause 34 through Clause 43 and Annex 36A through Annex 43C. Section Three includes general information on 1000 Mb/s operation as well as most of the 1000 Mb/s Physical Layer specifications.

Section Four—Includes Clause 44 through Clause 55 and Annex 44A through Annex 55B. Section Four includes general information on 10 Gb/s operation as well as most of the 10 Gb/s Physical Layer specifications.

Section Five—Includes Clause 56 through Clause 77 and Annex 57A through Annex 76A. Clause 56 through Clause 67 and Clause 75 through Clause 77, as well as associated annexes, specify subscriber access and other Physical Layers and sublayers for operation from 512 kb/s to 10 Gb/s, and defines services and protocol elements that enable the exchange of IEEE Std 802.3 format frames between

stations in a subscriber access network. Clause 68 specifies a 10 Gb/s Physical Layer specification. Clause 69 through Clause 74 and associated annexes specify Ethernet operation over electrical backplanes at speeds of 1000 Mb/s and 10 Gb/s.

Section Six—Includes Clause 78 through Clause 95 and Annex 83A through Annex 93C. Clause 78 specifies Energy-Efficient Ethernet. Clause 79 specifies IEEE 802.3 Organizationally Specific Link Layer Discovery Protocol (LLDP) type, length, and value (TLV) information elements. Clause 80 through Clause 95 and associated annexes includes general information on 40 Gb/s and 100 Gb/s operation as well the 40 Gb/s and 100 Gb/s Physical Layer specifications. Clause 90 specifies Ethernet support for time synchronization protocols.

#### IEEE Std 802.3bw™-2015

Amendment 1—This amendment includes changes to IEEE Std 802.3-2015 and adds Clause 96. This amendment adds 100 Mb/s Physical Layer (PHY) specifications and management parameters for operation on a single balanced twisted-pair copper cable.

#### IEEE Std 802.3by™-2016

Amendment 2—This amendment includes changes to IEEE Std 802.3-2015 and adds Clause 105 through Clause 112, Annex 109A, Annex 109B, Annex 109C, Annex 110A, Annex 110B, and Annex 110C. This amendment adds MAC parameters, Physical Layers, and management parameters for the transfer of IEEE 802.3 format frames at 25 Gb/s.

#### IEEE Std 802.3bq™-2016

Amendment 3—This amendment includes changes to IEEE Std 802.3-2015 and adds Clause 113 and Annex 113A. This amendment adds new Physical Layers for 25 Gb/s and 40 Gb/s operation over balanced twisted-pair structured cabling systems.

#### IEEE Std 802.3bp™-2016

Amendment 4—This amendment includes changes to IEEE Std 802.3-2015 and adds Clause 97 and Clause 98. This amendment adds point-to-point 1 Gb/s Physical Layer (PHY) specifications and management parameters for operation on a single balanced twisted-pair copper cable in automotive and other applications not utilizing the structured wiring plant.

#### IEEE Std 802.3br™-2016

Amendment 5—This amendment includes changes to IEEE Std 802.3-2015 and adds Clause 99. This amendment adds a MAC Merge sublayer and a MAC Merge Service Interface to support for Interspersing Express Traffic over a single link.

#### IEEE Std 802.3bn™-2016

Amendment 6—This amendment adds the Physical Layer specifications and management parameters for symmetric and/or asymmetric operation of up to 10 Gb/s on point-to-multipoint Radio Frequency (RF) distribution plants comprising either amplified or passive coaxial media. It also extends the operation of Ethernet Passive Optical Networks (EPON) protocols, such as Multipoint Control Protocol (MPCP) and Operation Administration and Management (OAM).

IEEE Std 802.3bz™-2016

Amendment 7—This amendment includes changes to IEEE Std 802.3-2015 and adds Clause 125 and Clause 126. This amendment adds new rates of 2.5 Gb/s and 5 Gb/s and new Physical Layers for operation at 2.5 Gb/s and 5 Gb/s over balanced twisted-pair structured cabling systems.

IEEE Std 802.3bu™-2016

Amendment 8—This amendment includes changes to IEEE Std 802.3-2015 to define a methodology for the provision of power via a single twisted pair to connected Data Terminal Equipment (DTE) with IEEE 802.3 single twisted-pair interfaces.

IEEE Std 802.3bv™-2017

Amendment 9—This amendment includes changes to IEEE Std 802.3-2015 and adds Clause 115 and Annex 115A. This amendment adds point-to-point 1000 Mb/s Physical Layer (PHY) specifications and management parameters for operation on duplex plastic optical fiber (POF) targeting use in automotive, industrial, home-network, and other applications.

IEEE Std 802.3™-2015/Cor 1-2017

This corrigendum clarifies which lane of the media dependent interface (MDI) of a multi-lane Physical Layer entity (PHY) is used as the timestamping reference point.

IEEE Std 802.3bs™-2017

Amendment 10—This amendment includes changes to IEEE Std 802.3-2015 and adds Clause 116 through Clause 124 and Annex 119A through Annex 120E. This amendment adds MAC parameters, Physical Layers, and management parameters for the transfer of IEEE 802.3 format frames at 200 Gb/s and 400 Gb/s.

A companion document IEEE Std 802.3.1 describes Ethernet management information base (MIB) modules for use with the Simple Network Management Protocol (SNMP). IEEE Std 802.3.1 is updated to add management capability for enhancements to IEEE Std 802.3 after approval of the enhancements.

IEEE Std 802.3 will continue to evolve. New Ethernet capabilities are anticipated to be added within the next few years as amendments to this standard.

## Contents

|                                                               |    |
|---------------------------------------------------------------|----|
| 1. Introduction.....                                          | 31 |
| 1.1 Overview.....                                             | 31 |
| 1.1.3 Architectural perspectives.....                         | 31 |
| 1.1.3.2 Compatibility interfaces.....                         | 31 |
| 1.3 Normative references.....                                 | 32 |
| 1.4 Definitions.....                                          | 32 |
| 1.5 Abbreviations.....                                        | 34 |
| 4. Media Access Control.....                                  | 35 |
| 4.4 Specific implementations.....                             | 35 |
| 4.4.2 MAC parameters.....                                     | 35 |
| 30. Management.....                                           | 36 |
| 30.2 Managed objects.....                                     | 36 |
| 30.2.5 Capabilities.....                                      | 36 |
| 30.3 Layer management for DTEs.....                           | 36 |
| 30.3.2 PHY device managed object class.....                   | 36 |
| 30.3.2.1 PHY device attributes.....                           | 36 |
| 30.3.2.1.2 aPhyType.....                                      | 36 |
| 30.3.2.1.3 aPhyTypeList.....                                  | 37 |
| 30.3.2.1.5 aSymbolErrorDuringCarrier.....                     | 37 |
| 30.5 Layer management for medium attachment units (MAUs)..... | 37 |
| 30.5.1 MAU managed object class.....                          | 37 |
| 30.5.1.1 MAU attributes.....                                  | 37 |
| 30.5.1.1.2 aMAUType.....                                      | 37 |
| 30.5.1.1.4 aMediaAvailable.....                               | 38 |
| 30.5.1.1.12 aLaneMapping.....                                 | 38 |
| 30.5.1.1.15 aFECAbility.....                                  | 38 |
| 30.5.1.1.17 aFECCorrectedBlocks.....                          | 39 |
| 30.5.1.1.18 aFECUncorrectableBlocks.....                      | 39 |
| 30.5.1.1.32 aPCSFECIndicationAbility.....                     | 40 |
| 30.5.1.1.33 aPCSFECIndicationEnable.....                      | 40 |
| 45. Management Data Input/Output (MDIO) Interface.....        | 41 |
| 45.2 MDIO Interface Registers.....                            | 41 |
| 45.2.1 PMA/PMD registers.....                                 | 41 |
| 45.2.1.1 PMA/PMD control 1 register (Register 1.0).....       | 43 |
| 45.2.1.1.3 Speed selection (1.0.13, 1.0.6, 1.0.5:2).....      | 44 |
| 45.2.1.1.4 PMA remote loopback (1.0.1).....                   | 44 |
| 45.2.1.1.5 PMA local loopback (1.0.0).....                    | 44 |
| 45.2.1.2 PMA/PMD status 1 register (Register 1.1).....        | 44 |
| 45.2.1.2.3 Fault (1.1.7).....                                 | 44 |
| 45.2.1.4 PMA/PMD speed ability (Register 1.4).....            | 45 |
| 45.2.1.4.aaa 400G capable (1.4.15).....                       | 45 |
| 45.2.1.4.ac 200G capable (1.4.12).....                        | 45 |
| 45.2.1.6 PMA/PMD control 2 register (Register 1.7).....       | 45 |
| 45.2.1.6.3 PMA/PMD type selection (1.7.65:0).....             | 47 |
| 45.2.1.7 PMA/PMD status 2 register (Register 1.8).....        | 48 |

|               |                                                                                                                                                    |    |
|---------------|----------------------------------------------------------------------------------------------------------------------------------------------------|----|
| 45.2.1.7.4    | Transmit fault (1.8.11)                                                                                                                            | 48 |
| 45.2.1.7.5    | Receive fault (1.8.10)                                                                                                                             | 48 |
| 45.2.1.8      | PMD transmit disable register (Register 1.9)                                                                                                       | 48 |
| 45.2.1.8.1    | PMD transmit disable 914 (1.9.1015)                                                                                                                | 49 |
| 45.2.1.8.2    | PMD transmit disable 4, 5, 6, 7, 8 through 13 (1.9.5, 1.9.6, 1.9.7, 1.9.8, 1.9.9 through 1.9.14)                                                   | 50 |
| 45.2.1.9      | PMD receive signal detect register (Register 1.10)                                                                                                 | 50 |
| 45.2.1.9.1    | PMD receive signal detect 914 (1.10.1015)                                                                                                          | 50 |
| 45.2.1.9.2    | PMD receive signal detect 4, 5, 6, 7, 8 through 13 (1.10.5, 1.10.6, 1.10.7, 1.10.8, 1.10.9 through 1.10.14)                                        | 51 |
| 45.2.1.10     | PMA/PMD extended ability register (Register 1.11)                                                                                                  | 51 |
| 45.2.1.10.aab | 200G/400G extended abilities (1.11.13)                                                                                                             | 51 |
| 45.2.1.14e    | 200G PMA/PMD extended ability register (Register 1.23)                                                                                             | 51 |
| 45.2.1.14e.1  | 200G PMA remote loopback ability (1.23.15)                                                                                                         | 52 |
| 45.2.1.14e.2  | 200GBASE-LR4 ability (1.23.5)                                                                                                                      | 52 |
| 45.2.1.14e.3  | 200GBASE-FR4 ability (1.23.4)                                                                                                                      | 52 |
| 45.2.1.14e.4  | 200GBASE-DR4 ability (1.23.3)                                                                                                                      | 52 |
| 45.2.1.14f    | 400G PMA/PMD extended ability register (Register 1.24)                                                                                             | 52 |
| 45.2.1.14f.1  | 400G PMA remote loopback ability (1.24.15)                                                                                                         | 53 |
| 45.2.1.14f.2  | 400GBASE-LR8 ability (1.24.5)                                                                                                                      | 53 |
| 45.2.1.14f.3  | 400GBASE-FR8 ability (1.24.4)                                                                                                                      | 53 |
| 45.2.1.14f.4  | 400GBASE-DR4 ability (1.24.3)                                                                                                                      | 53 |
| 45.2.1.14f.5  | 400GBASE-SR16 ability (1.24.2)                                                                                                                     | 53 |
| 45.2.1.14g    | PMD transmit disable extension register (Register 1.27)                                                                                            | 53 |
| 45.2.1.14g.1  | PMD transmit disable 15 (1.27.0)                                                                                                                   | 54 |
| 45.2.1.14h    | PMD receive signal detect extension register (Register 1.28)                                                                                       | 54 |
| 45.2.1.14h.1  | PMD receive signal detect 15 (1.28.0)                                                                                                              | 54 |
| 45.2.1.116a   | 200GAUI-8 and 400GAUI-16 chip-to-module recommended CTLE, lane 0 register (Register 1.400)                                                         | 55 |
| 45.2.1.116a.1 | Recommended CTLE peaking (1.400.4:1)                                                                                                               | 55 |
| 45.2.1.116b   | 200GAUI-8 and 400GAUI-16 chip-to-module recommended CTLE, lane 1 through lane 7 registers (Registers 1.401 through 1.407)                          | 55 |
| 45.2.1.116c   | 400GAUI-16 chip-to-module recommended CTLE, lane 8 through lane 15 registers (Registers 1.408 through 1.415)                                       | 55 |
| 45.2.1.116d   | 200GAUI-n and 400GAUI-n chip-to-chip transmitter equalization, receive direction, lane 0 register (Register 1.500)                                 | 56 |
| 45.2.1.116d.1 | Request flag (1.500.15)                                                                                                                            | 57 |
| 45.2.1.116d.2 | Post-cursor request (1.500.14:12)                                                                                                                  | 57 |
| 45.2.1.116d.3 | Pre-cursor request (1.500.11:10)                                                                                                                   | 57 |
| 45.2.1.116d.4 | Post-cursor remote setting (1.500.9:7)                                                                                                             | 57 |
| 45.2.1.116d.5 | Pre-cursor remote setting (1.500.6:5)                                                                                                              | 57 |
| 45.2.1.116d.6 | Post-cursor local setting (1.500.4:2)                                                                                                              | 57 |
| 45.2.1.116d.7 | Pre-cursor local setting (1.500.1:0)                                                                                                               | 57 |
| 45.2.1.116e   | 200GAUI-n and 400GAUI-n chip-to-chip transmitter equalization, receive direction, lane 1 through lane 15 registers (Registers 1.501 through 1.515) | 58 |
| 45.2.1.116f   | 200GAUI-n and 400GAUI-n chip-to-chip transmitter equalization, transmit direction, lane 0 register (Register 1.516)                                | 58 |
| 45.2.1.116f.1 | Request flag (1.516.15)                                                                                                                            | 59 |
| 45.2.1.116f.2 | Post-cursor request (1.516.14:12)                                                                                                                  | 59 |
| 45.2.1.116f.3 | Pre-cursor request (1.516.11:10)                                                                                                                   | 59 |
| 45.2.1.116f.4 | Post-cursor remote setting (1.516.9:7)                                                                                                             | 59 |
| 45.2.1.116f.5 | Pre-cursor remote setting (1.516.6:5)                                                                                                              | 60 |
| 45.2.1.116f.6 | Post-cursor local setting (1.516.4:2)                                                                                                              | 60 |
| 45.2.1.116f.7 | Pre-cursor local setting (1.516.1:0)                                                                                                               | 60 |

|              |                                                                                                                                                     |    |
|--------------|-----------------------------------------------------------------------------------------------------------------------------------------------------|----|
| 45.2.1.116g  | 200GAUI-n and 400GAUI-n chip-to-chip transmitter equalization, transmit direction, lane 1 through lane 15 registers (Registers 1.517 through 1.531) | 60 |
| 45.2.1.123   | Test-pattern ability (Register 1.1500)                                                                                                              | 60 |
| 45.2.1.124   | PRBS pattern testing control (Register 1.1501)                                                                                                      | 62 |
| 45.2.1.125   | Square wave testing control (Register 1.1510)                                                                                                       | 63 |
| 45.2.1.125a  | PRBS13Q testing control (Register 1.1512)                                                                                                           | 64 |
| 45.2.1.126   | PRBS Tx pattern testing error counter (Register 1.1600 through 1.1615, 1.1601, 1.1602, 1.1603, 1.1604, 1.1605, 1.1606, 1.1607, 1.1608, 1.1609)      | 65 |
| 45.2.1.127   | PRBS Rx pattern testing error counter (Register 1.1700 through 1.1715, 1.1701, 1.1702, 1.1703, 1.1704, 1.1705, 1.1706, 1.1707, 1.1708, 1.1709)      | 66 |
| 45.2.3       | PCS registers                                                                                                                                       | 66 |
| 45.2.3.1     | PCS control 1 register (Register 3.0)                                                                                                               | 67 |
| 45.2.3.2     | PCS status 1 register (Register 3.1)                                                                                                                | 67 |
| 45.2.3.2.7   | PCS receive link status (3.1.2)                                                                                                                     | 67 |
| 45.2.3.4     | PCS speed ability (Register 3.4)                                                                                                                    | 67 |
| 45.2.3.4.8   | 200G capable (3.4.8)                                                                                                                                | 68 |
| 45.2.3.4.9   | 400G capable (3.4.9)                                                                                                                                | 68 |
| 45.2.3.6     | PCS control 2 register (Register 3.7)                                                                                                               | 68 |
| 45.2.3.6.1   | PCS type selection (3.7.3:0)                                                                                                                        | 69 |
| 45.2.3.7a    | PCS status 3 register (Register 3.9)                                                                                                                | 69 |
| 45.2.3.7a.1  | 400GBASE-R capable (3.9.1)                                                                                                                          | 69 |
| 45.2.3.7a.2  | 200GBASE-R capable (3.9.0)                                                                                                                          | 69 |
| 45.2.3.9a    | EEE control and capability 2 (Register 3.21)                                                                                                        | 69 |
| 45.2.3.9a.a  | 400GBASE-R EEE fast wake supported (3.21.5)                                                                                                         | 70 |
| 45.2.3.9a.b  | 200GBASE-R EEE fast wake supported (3.21.3)                                                                                                         | 70 |
| 45.2.3.13    | BASE-R and MultiGBASE-T PCS status 1 register (Register 3.32)                                                                                       | 70 |
| 45.2.3.13.1  | BASE-R and MultiGBASE-T receive link status (3.32.12)                                                                                               | 70 |
| 45.2.3.17    | BASE-R PCS test-pattern control register (Register 3.42)                                                                                            | 70 |
| 45.2.3.46    | Lane 0 mapping register (Register 3.400)                                                                                                            | 70 |
| 45.2.3.47h   | PCS FEC symbol error counter lane 0 (Register 3.600, 3.601)                                                                                         | 71 |
| 45.2.3.47i   | PCS FEC symbol error counter lane 1 through 15 (Registers 3.602 through 3.631)                                                                      | 71 |
| 45.2.3.47j   | PCS FEC control register (Register 3.800)                                                                                                           | 71 |
| 45.2.3.47j.1 | PCS FEC degraded SER enable (3.800.2)                                                                                                               | 72 |
| 45.2.3.47j.2 | PCS FEC bypass indication enable (3.800.1)                                                                                                          | 72 |
| 45.2.3.47k   | PCS FEC status register (Register 3.801)                                                                                                            | 72 |
| 45.2.3.47k.1 | Local degraded SER received (3.801.6)                                                                                                               | 72 |
| 45.2.3.47k.2 | Remote degraded SER received (3.801.5)                                                                                                              | 73 |
| 45.2.3.47k.3 | PCS FEC degraded SER (3.801.4)                                                                                                                      | 73 |
| 45.2.3.47k.4 | PCS FEC degraded SER ability (3.801.3)                                                                                                              | 73 |
| 45.2.3.47k.5 | PCS FEC high SER (3.801.2)                                                                                                                          | 73 |
| 45.2.3.47k.6 | PCS FEC bypass indication ability (3.801.1)                                                                                                         | 73 |
| 45.2.3.47l   | PCS corrected codewords counter (Register 3.802, 3.803)                                                                                             | 73 |
| 45.2.3.47m   | PCS FEC uncorrected codewords counter (Register 3.804, 3.805)                                                                                       | 74 |
| 45.2.3.47n   | PCS FEC degraded SER activate threshold register (Register 3.806, 3.807)                                                                            | 74 |
| 45.2.3.47o   | PCS FEC degraded SER deactivate threshold register (Register 3.808, 3.809)                                                                          | 74 |
| 45.2.3.47p   | PCS FEC degraded SER interval register (Register 3.810, 3.811)                                                                                      | 75 |
| 45.2.4       | PHY XS registers                                                                                                                                    | 75 |
| 45.2.4.1     | PHY XS control 1 register (Register 4.0)                                                                                                            | 76 |
| 45.2.4.4     | PHY XS speed ability (Register 4.4)                                                                                                                 | 76 |
| 45.2.4.4.a   | 400G capable (4.4.9)                                                                                                                                | 77 |
| 45.2.4.4.b   | 200G capable (4.4.8)                                                                                                                                | 77 |
| 45.2.4.11a   | BASE-R PHY XS status 1 register (Register 4.32)                                                                                                     | 77 |
| 45.2.4.11a.1 | BASE-R PHY XS receive link status (4.32.12)                                                                                                         | 77 |

|              |                                                                                            |    |
|--------------|--------------------------------------------------------------------------------------------|----|
| 45.2.4.11b   | BASE-R PHY XS test-pattern control register (Register 4.42).....                           | 78 |
| 45.2.4.11b.1 | Transmit test-pattern enable (4.42.3).....                                                 | 78 |
| 45.2.4.11c   | Multi-lane BASE-R PHY XS alignment status 1 register (Register 4.50).....                  | 78 |
| 45.2.4.11c.1 | PHY XS lane alignment status (4.50.12).....                                                | 78 |
| 45.2.4.11d   | Multi-lane BASE-R PHY XS alignment status 3 register (Register 4.52).....                  | 79 |
| 45.2.4.11d.1 | Lane 7 aligned (4.52.7).....                                                               | 79 |
| 45.2.4.11d.2 | Lane 6 aligned (4.52.6).....                                                               | 79 |
| 45.2.4.11d.3 | Lane 5 aligned (4.52.5).....                                                               | 79 |
| 45.2.4.11d.4 | Lane 4 aligned (4.52.4).....                                                               | 80 |
| 45.2.4.11d.5 | Lane 3 aligned (4.52.3).....                                                               | 80 |
| 45.2.4.11d.6 | Lane 2 aligned (4.52.2).....                                                               | 80 |
| 45.2.4.11d.7 | Lane 1 aligned (4.52.1).....                                                               | 80 |
| 45.2.4.11d.8 | Lane 0 aligned (4.52.0).....                                                               | 80 |
| 45.2.4.11e   | Multi-lane BASE-R PHY XS alignment status 4 register (Register 4.53).....                  | 80 |
| 45.2.4.11e.1 | Lane 15 aligned (4.53.7).....                                                              | 81 |
| 45.2.4.11e.2 | Lane 14 aligned (4.53.6).....                                                              | 81 |
| 45.2.4.11e.3 | Lane 13 aligned (4.53.5).....                                                              | 81 |
| 45.2.4.11e.4 | Lane 12 aligned (4.53.4).....                                                              | 81 |
| 45.2.4.11e.5 | Lane 11 aligned (4.53.3).....                                                              | 81 |
| 45.2.4.11e.6 | Lane 10 aligned (4.53.2).....                                                              | 82 |
| 45.2.4.11e.7 | Lane 9 aligned (4.53.1).....                                                               | 82 |
| 45.2.4.11e.8 | Lane 8 aligned (4.53.0).....                                                               | 82 |
| 45.2.4.11f   | PHY XS lane mapping, lane 0 register (Register 4.400).....                                 | 82 |
| 45.2.4.11g   | PHY XS lane mapping, lane 1 through lane 15 registers (Registers 4.401 through 4.415)..... | 82 |
| 45.2.4.11h   | PHY XS FEC symbol error counter lane 0 (Register 4.600, 4.601).....                        | 82 |
| 45.2.4.11i   | PHY XS FEC symbol error counter lane 1 through 15 (Registers 4.602 through 4.631).....     | 83 |
| 45.2.4.11j   | PHY XS FEC control register (Register 4.800).....                                          | 83 |
| 45.2.4.11j.1 | PHY XS FEC degraded SER enable (4.800.2).....                                              | 83 |
| 45.2.4.11j.2 | PHY XS FEC bypass indication enable (4.800.1).....                                         | 83 |
| 45.2.4.11k   | PHY XS FEC status register (Register 4.801).....                                           | 84 |
| 45.2.4.11k.1 | Remote degraded SER received (4.801.5).....                                                | 84 |
| 45.2.4.11k.2 | PHY XS FEC degraded SER (4.801.4).....                                                     | 84 |
| 45.2.4.11k.3 | PHY XS FEC degraded SER ability (4.801.3).....                                             | 84 |
| 45.2.4.11k.4 | PHY XS FEC high SER (4.801.2).....                                                         | 85 |
| 45.2.4.11k.5 | PHY XS FEC bypass indication ability (4.801.1).....                                        | 85 |
| 45.2.4.11l   | PHY XS FEC corrected codewords counter (Register 4.802, 4.803).....                        | 85 |
| 45.2.4.11m   | PHY XS FEC uncorrected codewords counter (Register 4.804, 4.805).....                      | 85 |
| 45.2.4.11n   | PHY XS FEC degraded SER activate threshold register (Register 4.806, 4.807).....           | 86 |
| 45.2.4.11o   | PHY XS FEC degraded SER deactivate threshold register (Register 4.808, 4.809).....         | 86 |
| 45.2.4.11p   | PHY XS FEC degraded SER interval register (Register 4.810, 4.811).....                     | 86 |
| 45.2.5       | DTE XS registers.....                                                                      | 87 |
| 45.2.5.1     | DTE XS control 1 register (Register 5.0).....                                              | 88 |
| 45.2.5.4     | DTE XS speed ability (Register 5.4).....                                                   | 88 |
| 45.2.5.4.a   | 400G capable (5.4.9).....                                                                  | 88 |
| 45.2.5.4.b   | 200G capable (5.4.8).....                                                                  | 89 |
| 45.2.5.11a   | BASE-R DTE XS status 1 register (Register 5.32).....                                       | 89 |
| 45.2.5.11a.1 | BASE-R DTE XS receive link status (5.32.12).....                                           | 89 |
| 45.2.5.11b   | BASE-R DTE XS test-pattern control register (Register 5.42).....                           | 89 |
| 45.2.5.11b.1 | Transmit test-pattern enable (5.42.3).....                                                 | 90 |
| 45.2.5.11c   | Multi-lane BASE-R DTE XS alignment status 1 register (Register 5.50).....                  | 90 |

|              |                                                                                       |     |
|--------------|---------------------------------------------------------------------------------------|-----|
| 45.2.5.11c.1 | DTE XS lane alignment status (5.50.12)                                                | 90  |
| 45.2.5.11d   | Multi-lane BASE-R DTE XS alignment status 3 register (Register 5.52)                  | 90  |
| 45.2.5.11d.1 | Lane 7 aligned (5.52.7)                                                               | 91  |
| 45.2.5.11d.2 | Lane 6 aligned (5.52.6)                                                               | 91  |
| 45.2.5.11d.3 | Lane 5 aligned (5.52.5)                                                               | 91  |
| 45.2.5.11d.4 | Lane 4 aligned (5.52.4)                                                               | 91  |
| 45.2.5.11d.5 | Lane 3 aligned (5.52.3)                                                               | 91  |
| 45.2.5.11d.6 | Lane 2 aligned (5.52.2)                                                               | 92  |
| 45.2.5.11d.7 | Lane 1 aligned (5.52.1)                                                               | 92  |
| 45.2.5.11d.8 | Lane 0 aligned (5.52.0)                                                               | 92  |
| 45.2.5.11e   | Multi-lane BASE-R DTE XS alignment status 4 register (Register 5.53)                  | 92  |
| 45.2.5.11e.1 | Lane 15 aligned (5.53.7)                                                              | 93  |
| 45.2.5.11e.2 | Lane 14 aligned (5.53.6)                                                              | 93  |
| 45.2.5.11e.3 | Lane 13 aligned (5.53.5)                                                              | 93  |
| 45.2.5.11e.4 | Lane 12 aligned (5.53.4)                                                              | 93  |
| 45.2.5.11e.5 | Lane 11 aligned (5.53.3)                                                              | 93  |
| 45.2.5.11e.6 | Lane 10 aligned (5.53.2)                                                              | 93  |
| 45.2.5.11e.7 | Lane 9 aligned (5.53.1)                                                               | 93  |
| 45.2.5.11e.8 | Lane 8 aligned (5.53.0)                                                               | 93  |
| 45.2.5.11f   | DTE XS lane mapping, lane 0 register (Register 5.400)                                 | 93  |
| 45.2.5.11g   | DTE XS lane mapping, lane 1 through lane 15 registers (Registers 5.401 through 5.415) | 94  |
| 45.2.5.11h   | DTE XS FEC symbol error counter lane 0 (Register 5.600, 5.601)                        | 94  |
| 45.2.5.11i   | DTE XS FEC symbol error counter lane 1 through 15 (Registers 5.602 through 5.631)     | 94  |
| 45.2.5.11j   | DTE XS FEC control register (Register 5.800)                                          | 95  |
| 45.2.5.11j.1 | DTE XS FEC degraded SER enable (5.800.2)                                              | 95  |
| 45.2.5.11j.2 | DTE XS FEC bypass indication enable (5.800.1)                                         | 95  |
| 45.2.5.11k   | DTE XS FEC status register (Register 5.801)                                           | 95  |
| 45.2.5.11k.1 | Local degraded SER received (5.801.6)                                                 | 96  |
| 45.2.5.11k.2 | Remote degraded SER received (5.801.5)                                                | 96  |
| 45.2.5.11k.3 | DTE XS FEC degraded SER (5.801.4)                                                     | 96  |
| 45.2.5.11k.4 | DTE XS FEC degraded SER ability (5.801.3)                                             | 96  |
| 45.2.5.11k.5 | DTE XS FEC high SER (5.801.2)                                                         | 96  |
| 45.2.5.11k.6 | DTE XS FEC bypass indication ability (5.801.1)                                        | 97  |
| 45.2.5.11l   | DTE XS FEC corrected codewords counter (Register 5.802, 5.803)                        | 97  |
| 45.2.5.11m   | DTE XS FEC uncorrected codewords counter (Register 5.804, 5.805)                      | 97  |
| 45.2.5.11n   | DTE XS FEC degraded SER activate threshold register (Register 5.806, 5.807)           | 97  |
| 45.2.5.11o   | DTE XS FEC degraded SER deactivate threshold register (Register 5.808, 5.809)         | 98  |
| 45.2.5.11p   | DTE XS FEC degraded SER interval register (Register 5.810, 5.811)                     | 98  |
| 78.          | Energy-Efficient Ethernet (EEE)                                                       | 99  |
| 78.1         | Overview                                                                              | 99  |
| 78.1.4       | PHY types optionally supporting EEE                                                   | 99  |
| 78.5         | Communication link access latency                                                     | 100 |
| 78.5.1       | 10 Gb/s PHY extension using extender sublayers XGXS                                   | 100 |
| 90.          | Ethernet support for time synchronization protocols                                   | 101 |
| 90.1         | Introduction                                                                          | 101 |

|                                                                                                                                  |     |
|----------------------------------------------------------------------------------------------------------------------------------|-----|
| 116. Introduction to 200 Gb/s and 400 Gb/s networks .....                                                                        | 102 |
| 116.1 Overview.....                                                                                                              | 102 |
| 116.1.1 Scope.....                                                                                                               | 102 |
| 116.1.2 Relationship of 200 Gigabit and 400 Gigabit Ethernet to the ISO OSI reference model .....                                | 102 |
| 116.1.3 Nomenclature.....                                                                                                        | 103 |
| 116.1.4 Physical Layer signaling systems .....                                                                                   | 104 |
| 116.2 Summary of 200 Gigabit and 400 Gigabit Ethernet sublayers .....                                                            | 105 |
| 116.2.1 Reconciliation Sublayer (RS) and Media Independent Interface .....                                                       | 105 |
| 116.2.2 200GMII and 400GMII Extender Sublayers (200GXS and 400GXS).....                                                          | 105 |
| 116.2.3 Physical Coding Sublayer (PCS).....                                                                                      | 106 |
| 116.2.4 Physical Medium Attachment (PMA) sublayer.....                                                                           | 106 |
| 116.2.5 Physical Medium Dependent (PMD) sublayer .....                                                                           | 106 |
| 116.2.6 Management interface (MDIO/MDC) .....                                                                                    | 106 |
| 116.2.7 Management.....                                                                                                          | 106 |
| 116.3 Service interface specification method and notation .....                                                                  | 106 |
| 116.3.1 Inter-sublayer service interface.....                                                                                    | 107 |
| 116.3.2 Instances of the Inter-sublayer service interface.....                                                                   | 107 |
| 116.3.3 Semantics of inter-sublayer service interface primitives .....                                                           | 107 |
| 116.3.3.1 IS_UNITDATA_i.request.....                                                                                             | 107 |
| 116.3.3.1.1 Semantics of the service primitive.....                                                                              | 108 |
| 116.3.3.1.2 When generated .....                                                                                                 | 109 |
| 116.3.3.1.3 Effect of receipt .....                                                                                              | 109 |
| 116.3.3.2 IS_UNITDATA_i.indication .....                                                                                         | 110 |
| 116.3.3.2.1 Semantics of the service primitive.....                                                                              | 110 |
| 116.3.3.2.2 When generated .....                                                                                                 | 110 |
| 116.3.3.2.3 Effect of receipt .....                                                                                              | 110 |
| 116.3.3.3 IS_SIGNAL.indication .....                                                                                             | 110 |
| 116.3.3.3.1 Semantics of the service primitive.....                                                                              | 110 |
| 116.3.3.3.2 When generated .....                                                                                                 | 110 |
| 116.3.3.3.3 Effect of receipt .....                                                                                              | 110 |
| 116.4 Delay constraints.....                                                                                                     | 111 |
| 116.5 Skew constraints .....                                                                                                     | 112 |
| 116.6 FEC Degrade.....                                                                                                           | 115 |
| 116.7 State diagrams.....                                                                                                        | 116 |
| 116.8 Protocol implementation conformance statement (PICS) proforma.....                                                         | 117 |
| 117. Reconciliation Sublayer (RS) and Media Independent Interface for 200 Gb/s and 400 Gb/s operation (200GMII and 400GMII)..... | 118 |
| 117.1 Overview.....                                                                                                              | 118 |
| 117.1.1 Summary of major concepts .....                                                                                          | 119 |
| 117.1.2 Application.....                                                                                                         | 119 |
| 117.1.3 Rate of operation.....                                                                                                   | 119 |
| 117.1.4 Delay constraints.....                                                                                                   | 119 |
| 117.1.5 Allocation of functions .....                                                                                            | 120 |
| 117.1.6 200GMII/400GMII structure .....                                                                                          | 120 |
| 117.1.7 Mapping of 200GMII/400GMII signals to PLS service primitives.....                                                        | 120 |
| 117.2 200GMII/400GMII data stream.....                                                                                           | 120 |
| 117.3 200GMII/400GMII functional specifications .....                                                                            | 120 |
| 117.4 LPI Assertion and Detection .....                                                                                          | 120 |

|           |                                                                                                                                                                                                           |     |
|-----------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----|
| 117.5     | Protocol implementation conformance statement (PICS) proforma for Clause 117, Reconciliation Sublayer (RS) and Media Independent Interface for 200 Gb/s and 400 Gb/s operation (200GMII and 400GMII)..... | 121 |
| 117.5.1   | Introduction.....                                                                                                                                                                                         | 121 |
| 117.5.2   | Identification.....                                                                                                                                                                                       | 121 |
| 117.5.2.1 | Implementation identification.....                                                                                                                                                                        | 121 |
| 117.5.2.2 | Protocol summary.....                                                                                                                                                                                     | 121 |
| 117.5.3   | Major capabilities/options.....                                                                                                                                                                           | 122 |
| 117.5.4   | PICS proforma tables for Reconciliation Sublayer (RS) and Media Independent Interface for 200 Gb/s and 400 Gb/s operation (200GMII and 400GMII).....                                                      | 122 |
| 117.5.4.1 | General.....                                                                                                                                                                                              | 122 |
| 117.5.4.2 | Mapping of PLS service primitives.....                                                                                                                                                                    | 122 |
| 117.5.4.3 | Data stream structure.....                                                                                                                                                                                | 123 |
| 117.5.4.4 | 200GMII/400GMII signal functional specifications.....                                                                                                                                                     | 123 |
| 117.5.4.5 | Link fault signaling state diagram.....                                                                                                                                                                   | 124 |
| 117.5.4.6 | LPI functions.....                                                                                                                                                                                        | 124 |
| 118.      | 200GMII Extender, 400GMII Extender, 200GMII Extender Sublayer (200GXS), and 400GMII Extender Sublayer (400GXS).....                                                                                       | 125 |
| 118.1     | Overview.....                                                                                                                                                                                             | 125 |
| 118.1.1   | Summary of major concepts.....                                                                                                                                                                            | 126 |
| 118.1.2   | 200GXS/400GXS Sublayer.....                                                                                                                                                                               | 126 |
| 118.1.3   | 200GAUI-n/400GAUI-n.....                                                                                                                                                                                  | 126 |
| 118.2     | FEC Degrade.....                                                                                                                                                                                          | 126 |
| 118.2.1   | DTE XS FEC Degrade signaling.....                                                                                                                                                                         | 126 |
| 118.2.2   | PHY XS FEC Degrade signaling.....                                                                                                                                                                         | 127 |
| 118.3     | 200GXS and 400GXS partitioning example.....                                                                                                                                                               | 127 |
| 118.4     | 200GXS and 400GXS MDIO function mapping.....                                                                                                                                                              | 127 |
| 118.5     | Protocol implementation conformance statement (PICS) proforma for Clause 118, 200GMII Extender, 400GMII Extender, 200GMII Extender Sublayer (200GXS), and 400GMII Extender Sublayer (400GXS).....         | 131 |
| 118.5.1   | Introduction.....                                                                                                                                                                                         | 131 |
| 118.5.2   | Identification.....                                                                                                                                                                                       | 131 |
| 118.5.2.1 | Implementation identification.....                                                                                                                                                                        | 131 |
| 118.5.2.2 | Protocol summary.....                                                                                                                                                                                     | 131 |
| 118.5.3   | Major capabilities/options.....                                                                                                                                                                           | 132 |
| 118.5.4   | PICS proforma tables for 200GMII Extender, 400GMII Extender, 200GMII Extender Sublayer (200GXS), and 400GMII Extender Sublayer (400GXS).....                                                              | 132 |
| 118.5.4.1 | Transmit function.....                                                                                                                                                                                    | 132 |
| 118.5.4.2 | Receive function.....                                                                                                                                                                                     | 133 |
| 118.5.4.3 | 64B/66B coding rules.....                                                                                                                                                                                 | 133 |
| 118.5.4.4 | Scrambler and descrambler.....                                                                                                                                                                            | 134 |
| 118.5.4.5 | Alignment markers.....                                                                                                                                                                                    | 134 |
| 118.5.5   | Test-pattern modes.....                                                                                                                                                                                   | 134 |
| 118.5.6   | Bit order.....                                                                                                                                                                                            | 134 |
| 118.5.7   | Management.....                                                                                                                                                                                           | 135 |
| 118.5.7.1 | State diagrams.....                                                                                                                                                                                       | 135 |
| 118.5.7.2 | Loopback.....                                                                                                                                                                                             | 135 |
| 118.5.7.3 | Delay constraints.....                                                                                                                                                                                    | 136 |
| 119.      | Physical Coding Sublayer (PCS) for 64B/66B, type 200GBASE-R and 400GBASE-R.....                                                                                                                           | 137 |
| 119.1     | Overview.....                                                                                                                                                                                             | 137 |

|             |                                                                    |     |
|-------------|--------------------------------------------------------------------|-----|
| 119.1.1     | Scope.....                                                         | 137 |
| 119.1.2     | Relationship of 200GBASE-R and 400GBASE-R to other standards ..... | 137 |
| 119.1.3     | Physical Coding Sublayer (PCS) .....                               | 137 |
| 119.1.4     | Inter-sublayer interfaces .....                                    | 138 |
| 119.1.4.1   | PCS service interface (200GMII/400GMII) .....                      | 138 |
| 119.1.4.2   | Physical Medium Attachment (PMA) service interface .....           | 138 |
| 119.1.5     | Functional block diagram .....                                     | 139 |
| 119.2       | Physical Coding Sublayer (PCS) .....                               | 140 |
| 119.2.1     | Functions within the PCS .....                                     | 140 |
| 119.2.2     | Use of blocks .....                                                | 140 |
| 119.2.3     | 64B/66B code .....                                                 | 141 |
| 119.2.3.1   | Notation conventions .....                                         | 141 |
| 119.2.3.2   | 64B/66B block structure .....                                      | 141 |
| 119.2.3.3   | Control codes .....                                                | 141 |
| 119.2.3.4   | Valid and invalid blocks .....                                     | 142 |
| 119.2.3.5   | Idle (/I/) .....                                                   | 142 |
| 119.2.3.6   | Start (/S/) .....                                                  | 142 |
| 119.2.3.7   | Terminate (/T/) .....                                              | 142 |
| 119.2.3.8   | Ordered set (/O/) .....                                            | 142 |
| 119.2.3.9   | Error (/E/) .....                                                  | 142 |
| 119.2.4     | Transmit .....                                                     | 142 |
| 119.2.4.1   | Encode and rate matching .....                                     | 142 |
| 119.2.4.2   | 64B/66B to 256B/257B transcoder .....                              | 143 |
| 119.2.4.3   | Scrambler .....                                                    | 145 |
| 119.2.4.4   | Alignment marker mapping and insertion .....                       | 145 |
| 119.2.4.4.1 | AM creation for the 200GBASE-R PCS .....                           | 146 |
| 119.2.4.4.2 | AM creation for the 400GBASE-R PCS .....                           | 148 |
| 119.2.4.5   | Pre-FEC distribution .....                                         | 150 |
| 119.2.4.6   | Reed-Solomon encoder .....                                         | 150 |
| 119.2.4.7   | Symbol distribution .....                                          | 152 |
| 119.2.4.8   | Transmit bit ordering and distribution .....                       | 153 |
| 119.2.4.9   | Test-pattern generators .....                                      | 155 |
| 119.2.5     | Receive function .....                                             | 155 |
| 119.2.5.1   | Alignment lock and deskew .....                                    | 155 |
| 119.2.5.2   | Lane reorder and de-interleave .....                               | 155 |
| 119.2.5.3   | Reed-Solomon decoder .....                                         | 155 |
| 119.2.5.4   | Post FEC interleave .....                                          | 156 |
| 119.2.5.5   | Alignment marker removal .....                                     | 156 |
| 119.2.5.6   | Descrambler .....                                                  | 156 |
| 119.2.5.7   | 256B/257B to 64B/66B transcoder .....                              | 157 |
| 119.2.5.8   | Decode and rate matching .....                                     | 157 |
| 119.2.6     | Detailed functions and state diagrams .....                        | 158 |
| 119.2.6.1   | State diagram conventions .....                                    | 158 |
| 119.2.6.2   | State variables .....                                              | 158 |
| 119.2.6.2.1 | Constants .....                                                    | 158 |
| 119.2.6.2.2 | Variables .....                                                    | 158 |
| 119.2.6.2.3 | Functions .....                                                    | 160 |
| 119.2.6.2.4 | Counters .....                                                     | 162 |
| 119.2.6.3   | State diagrams .....                                               | 162 |
| 119.3       | PCS management .....                                               | 167 |
| 119.3.1     | PCS MDIO function mapping .....                                    | 167 |
| 119.4       | Loopback .....                                                     | 168 |
| 119.5       | Delay constraints .....                                            | 168 |

|              |                                                                                                                                                               |     |
|--------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------|-----|
| 119.6        | Protocol implementation conformance statement (PICS) proforma for Clause 119, Physical Coding Sublayer (PCS) for 64B/66B, type 200GBASE-R and 400GBASE-R..... | 169 |
| 119.6.1      | Introduction.....                                                                                                                                             | 169 |
| 119.6.2      | Identification.....                                                                                                                                           | 169 |
| 119.6.2.1    | Implementation identification.....                                                                                                                            | 169 |
| 119.6.2.2    | Protocol summary.....                                                                                                                                         | 169 |
| 119.6.3      | Major capabilities/options.....                                                                                                                               | 170 |
| 119.6.4      | PICS proforma tables for Physical Coding Sublayer (PCS) 64B/66B, type 200GBASE-R and 400GBASE-R.....                                                          | 170 |
| 119.6.4.1    | Transmit function.....                                                                                                                                        | 170 |
| 119.6.4.2    | Receive function.....                                                                                                                                         | 171 |
| 119.6.4.3    | 64B/66B coding rules.....                                                                                                                                     | 171 |
| 119.6.4.4    | Scrambler and descrambler.....                                                                                                                                | 172 |
| 119.6.4.5    | Alignment markers.....                                                                                                                                        | 172 |
| 119.6.4.6    | Test-pattern modes.....                                                                                                                                       | 172 |
| 119.6.4.7    | Bit order.....                                                                                                                                                | 173 |
| 119.6.4.8    | Management.....                                                                                                                                               | 173 |
| 119.6.4.9    | State diagrams.....                                                                                                                                           | 173 |
| 119.6.4.10   | Loopback.....                                                                                                                                                 | 173 |
| 119.6.4.11   | Delay constraints.....                                                                                                                                        | 174 |
| 120.         | Physical Medium Attachment (PMA) sublayer, type 200GBASE-R and 400GBASE-R.....                                                                                | 175 |
| 120.1        | Overview.....                                                                                                                                                 | 175 |
| 120.1.1      | Scope.....                                                                                                                                                    | 175 |
| 120.1.2      | Position of the PMA in the 200GBASE-R and 400GBASE-R sublayers.....                                                                                           | 175 |
| 120.1.3      | Summary of functions.....                                                                                                                                     | 175 |
| 120.1.4      | PMA sublayer positioning.....                                                                                                                                 | 176 |
| 120.2        | PMA interfaces.....                                                                                                                                           | 178 |
| 120.3        | PMA service interface.....                                                                                                                                    | 178 |
| 120.4        | Service interface below PMA.....                                                                                                                              | 181 |
| 120.5        | Functions within the PMA.....                                                                                                                                 | 182 |
| 120.5.1      | Per input-lane clock and data recovery.....                                                                                                                   | 182 |
| 120.5.2      | Bit-level multiplexing.....                                                                                                                                   | 182 |
| 120.5.3      | Skew and Skew Variation.....                                                                                                                                  | 183 |
| 120.5.3.1    | Skew generation toward SP1.....                                                                                                                               | 183 |
| 120.5.3.2    | Skew tolerance at SP1.....                                                                                                                                    | 183 |
| 120.5.3.3    | Skew generation toward SP2.....                                                                                                                               | 183 |
| 120.5.3.4    | Skew tolerance at SP5.....                                                                                                                                    | 185 |
| 120.5.3.5    | Skew generation at SP6.....                                                                                                                                   | 185 |
| 120.5.3.6    | Skew tolerance at SP6.....                                                                                                                                    | 185 |
| 120.5.4      | Delay constraints.....                                                                                                                                        | 185 |
| 120.5.5      | Clocking architecture.....                                                                                                                                    | 185 |
| 120.5.6      | Signal drivers.....                                                                                                                                           | 186 |
| 120.5.7      | Gray mapping for PAM4 encoded lanes.....                                                                                                                      | 186 |
| 120.5.8      | Link status.....                                                                                                                                              | 186 |
| 120.5.9      | PMA local loopback mode (optional).....                                                                                                                       | 187 |
| 120.5.10     | PMA remote loopback mode (optional).....                                                                                                                      | 187 |
| 120.5.11     | PMA test patterns (optional).....                                                                                                                             | 187 |
| 120.5.11.1   | Test patterns for NRZ encoded signals.....                                                                                                                    | 188 |
| 120.5.11.1.1 | PRBS31 test pattern.....                                                                                                                                      | 188 |
| 120.5.11.1.2 | PRBS9 test pattern.....                                                                                                                                       | 189 |
| 120.5.11.1.3 | Square wave test pattern.....                                                                                                                                 | 189 |
| 120.5.11.2   | Test patterns for PAM4 encoded signals.....                                                                                                                   | 189 |

|              |                                                                                                                                                               |     |
|--------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------|-----|
| 120.5.11.2.1 | PRBS13Q test pattern .....                                                                                                                                    | 190 |
| 120.5.11.2.2 | PRBS31Q test pattern .....                                                                                                                                    | 190 |
| 120.5.11.2.3 | SSPRQ test pattern .....                                                                                                                                      | 192 |
| 120.5.11.2.4 | Square wave (quaternary) test pattern .....                                                                                                                   | 193 |
| 120.6        | PMA MDIO function mapping .....                                                                                                                               | 193 |
| 120.7        | Protocol implementation conformance statement (PICS) proforma for Clause 120, Physical Medium Attachment (PMA) sublayer, type 200GBASE-R and 400GBASE-R ..... | 198 |
| 120.7.1      | Introduction .....                                                                                                                                            | 198 |
| 120.7.2      | Identification .....                                                                                                                                          | 198 |
| 120.7.2.1    | Implementation identification .....                                                                                                                           | 198 |
| 120.7.2.2    | Protocol summary .....                                                                                                                                        | 198 |
| 120.7.3      | Major capabilities/options .....                                                                                                                              | 199 |
| 120.7.4      | Skew generation and tolerance .....                                                                                                                           | 201 |
| 120.7.5      | Test patterns .....                                                                                                                                           | 201 |
| 120.7.6      | Loopback modes .....                                                                                                                                          | 202 |
| 121.         | Physical Medium Dependent (PMD) sublayer and medium, type 200GBASE-DR4 .....                                                                                  | 203 |
| 121.1        | Overview .....                                                                                                                                                | 203 |
| 121.1.1      | Bit error ratio .....                                                                                                                                         | 203 |
| 121.2        | Physical Medium Dependent (PMD) service interface .....                                                                                                       | 204 |
| 121.3        | Delay and Skew .....                                                                                                                                          | 205 |
| 121.3.1      | Delay constraints .....                                                                                                                                       | 205 |
| 121.3.2      | Skew constraints .....                                                                                                                                        | 205 |
| 121.4        | PMD MDIO function mapping .....                                                                                                                               | 206 |
| 121.5        | PMD functional specifications .....                                                                                                                           | 206 |
| 121.5.1      | PMD block diagram .....                                                                                                                                       | 206 |
| 121.5.2      | PMD transmit function .....                                                                                                                                   | 207 |
| 121.5.3      | PMD receive function .....                                                                                                                                    | 207 |
| 121.5.4      | PMD global signal detect function .....                                                                                                                       | 207 |
| 121.5.5      | PMD lane-by-lane signal detect function .....                                                                                                                 | 208 |
| 121.5.6      | PMD reset function .....                                                                                                                                      | 208 |
| 121.5.7      | PMD global transmit disable function (optional) .....                                                                                                         | 208 |
| 121.5.8      | PMD lane-by-lane transmit disable function (optional) .....                                                                                                   | 209 |
| 121.5.9      | PMD fault function (optional) .....                                                                                                                           | 209 |
| 121.5.10     | PMD transmit fault function (optional) .....                                                                                                                  | 209 |
| 121.5.11     | PMD receive fault function (optional) .....                                                                                                                   | 209 |
| 121.6        | Lane assignments .....                                                                                                                                        | 209 |
| 121.7        | PMD to MDI optical specifications for 200GBASE-DR4 .....                                                                                                      | 209 |
| 121.7.1      | 200GBASE-DR4 transmitter optical specifications .....                                                                                                         | 210 |
| 121.7.2      | 200GBASE-DR4 receive optical specifications .....                                                                                                             | 210 |
| 121.7.3      | 200GBASE-DR4 illustrative link power budget .....                                                                                                             | 211 |
| 121.8        | Definition of optical parameters and measurement methods .....                                                                                                | 212 |
| 121.8.1      | Test patterns for optical parameters .....                                                                                                                    | 212 |
| 121.8.2      | Wavelength .....                                                                                                                                              | 212 |
| 121.8.3      | Average optical power .....                                                                                                                                   | 213 |
| 121.8.4      | Outer Optical Modulation Amplitude (OMA <sub>outer</sub> ) .....                                                                                              | 213 |
| 121.8.5      | Transmitter and dispersion eye closure for PAM4 (TDECQ) .....                                                                                                 | 213 |
| 121.8.5.1    | TDECQ conformance test setup .....                                                                                                                            | 213 |
| 121.8.5.2    | Channel requirements .....                                                                                                                                    | 214 |
| 121.8.5.3    | TDECQ measurement method .....                                                                                                                                | 215 |
| 121.8.5.4    | TDECQ reference equalizer .....                                                                                                                               | 218 |
| 121.8.6      | Extinction ratio .....                                                                                                                                        | 218 |
| 121.8.7      | Relative intensity noise (RIN <sub>21.4OMA</sub> ) .....                                                                                                      | 218 |

|            |                                                                                                                                                            |     |
|------------|------------------------------------------------------------------------------------------------------------------------------------------------------------|-----|
| 121.8.8    | Receiver sensitivity .....                                                                                                                                 | 218 |
| 121.8.9    | Stressed receiver sensitivity .....                                                                                                                        | 218 |
| 121.8.9.1  | Stressed receiver conformance test block diagram .....                                                                                                     | 219 |
| 121.8.9.2  | Stressed receiver conformance test signal characteristics and calibration .....                                                                            | 220 |
| 121.8.9.3  | Stressed receiver conformance test signal verification .....                                                                                               | 220 |
| 121.8.9.4  | Sinusoidal jitter for receiver conformance test .....                                                                                                      | 221 |
| 121.9      | Safety, installation, environment, and labeling .....                                                                                                      | 221 |
| 121.9.1    | General safety .....                                                                                                                                       | 221 |
| 121.9.2    | Laser safety .....                                                                                                                                         | 222 |
| 121.9.3    | Installation .....                                                                                                                                         | 222 |
| 121.9.4    | Environment .....                                                                                                                                          | 222 |
| 121.9.5    | Electromagnetic emission .....                                                                                                                             | 222 |
| 121.9.6    | Temperature, humidity, and handling .....                                                                                                                  | 222 |
| 121.9.7    | PMD labeling requirements .....                                                                                                                            | 222 |
| 121.10     | Fiber optic cabling model .....                                                                                                                            | 223 |
| 121.11     | Characteristics of the fiber optic cabling (channel) .....                                                                                                 | 223 |
| 121.11.1   | Optical fiber cable .....                                                                                                                                  | 224 |
| 121.11.2   | Optical fiber connection .....                                                                                                                             | 224 |
| 121.11.2.1 | Connection insertion loss .....                                                                                                                            | 224 |
| 121.11.2.2 | Maximum discrete reflectance .....                                                                                                                         | 224 |
| 121.11.3   | Medium Dependent Interface (MDI) .....                                                                                                                     | 225 |
| 121.11.3.1 | Optical lane assignments .....                                                                                                                             | 225 |
| 121.11.3.2 | Medium Dependent Interface (MDI) requirements .....                                                                                                        | 225 |
| 121.12     | Protocol implementation conformance statement (PICS) proforma for Clause 121, Physical Medium Dependent (PMD) sublayer and medium, type 200GBASE-DR4 ..... | 226 |
| 121.12.1   | Introduction .....                                                                                                                                         | 226 |
| 121.12.2   | Identification .....                                                                                                                                       | 226 |
| 121.12.2.1 | Implementation identification .....                                                                                                                        | 226 |
| 121.12.2.2 | Protocol summary .....                                                                                                                                     | 226 |
| 121.12.3   | Major capabilities/options .....                                                                                                                           | 227 |
| 121.12.4   | PICS proforma tables for Physical Medium Dependent (PMD) sublayer and medium, type 200GBASE-DR4 .....                                                      | 227 |
| 121.12.4.1 | PMD functional specifications .....                                                                                                                        | 227 |
| 121.12.4.2 | Management functions .....                                                                                                                                 | 228 |
| 121.12.4.3 | PMD to MDI optical specifications for 200GBASE-DR4 .....                                                                                                   | 228 |
| 121.12.4.4 | Optical measurement methods .....                                                                                                                          | 229 |
| 121.12.4.5 | Environmental specifications .....                                                                                                                         | 229 |
| 121.12.4.6 | Characteristics of the fiber optic cabling and MDI .....                                                                                                   | 229 |
| 122        | Physical Medium Dependent (PMD) sublayer and medium, type 200GBASE-FR4, 200GBASE-LR4, 400GBASE-FR8, and 400GBASE-LR8 .....                                 | 230 |
| 122.1      | Overview .....                                                                                                                                             | 230 |
| 122.1.1    | Bit error ratio .....                                                                                                                                      | 231 |
| 122.2      | Physical Medium Dependent (PMD) service interface .....                                                                                                    | 232 |
| 122.3      | Delay and Skew .....                                                                                                                                       | 232 |
| 122.3.1    | Delay constraints .....                                                                                                                                    | 232 |
| 122.3.2    | Skew constraints .....                                                                                                                                     | 232 |
| 122.4      | PMD MDIO function mapping .....                                                                                                                            | 233 |
| 122.5      | PMD functional specifications .....                                                                                                                        | 234 |
| 122.5.1    | PMD block diagram .....                                                                                                                                    | 234 |
| 122.5.2    | PMD transmit function .....                                                                                                                                | 234 |
| 122.5.3    | PMD receive function .....                                                                                                                                 | 235 |
| 122.5.4    | PMD global signal detect function .....                                                                                                                    | 235 |

|            |                                                                                                                                                                                                                 |     |
|------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----|
| 122.5.5    | PMD lane-by-lane signal detect function .....                                                                                                                                                                   | 236 |
| 122.5.6    | PMD reset function .....                                                                                                                                                                                        | 236 |
| 122.5.7    | PMD global transmit disable function (optional) .....                                                                                                                                                           | 236 |
| 122.5.8    | PMD lane-by-lane transmit disable function .....                                                                                                                                                                | 236 |
| 122.5.9    | PMD fault function (optional) .....                                                                                                                                                                             | 236 |
| 122.5.10   | PMD transmit fault function (optional) .....                                                                                                                                                                    | 236 |
| 122.5.11   | PMD receive fault function (optional) .....                                                                                                                                                                     | 237 |
| 122.6      | Wavelength-division-multiplexed lane assignments .....                                                                                                                                                          | 237 |
| 122.7      | PMD to MDI optical specifications for 200GBASE-FR4, 200GBASE-LR4,<br>400GBASE-FR8, and 400GBASE-LR8 .....                                                                                                       | 238 |
| 122.7.1    | 200GBASE-FR4, 200GBASE-LR4, 400GBASE-FR8, and 400GBASE-LR8<br>transmitter optical specifications .....                                                                                                          | 238 |
| 122.7.2    | 200GBASE-FR4, 200GBASE-LR4, 400GBASE-FR8, and 400GBASE-LR8 receive<br>optical specifications .....                                                                                                              | 241 |
| 122.7.3    | 200GBASE-FR4, 200GBASE-LR4, 400GBASE-FR8, and 400GBASE-LR8<br>illustrative link power budgets .....                                                                                                             | 243 |
| 122.8      | Definition of optical parameters and measurement methods .....                                                                                                                                                  | 243 |
| 122.8.1    | Test patterns for optical parameters .....                                                                                                                                                                      | 243 |
| 122.8.2    | Wavelength .....                                                                                                                                                                                                | 244 |
| 122.8.3    | Average optical power .....                                                                                                                                                                                     | 244 |
| 122.8.4    | Outer Optical Modulation Amplitude (OMA <sub>outer</sub> ) .....                                                                                                                                                | 244 |
| 122.8.5    | Transmitter and dispersion eye closure for PAM4 (TDECQ) .....                                                                                                                                                   | 245 |
| 122.8.5.1  | TDECQ conformance test setup .....                                                                                                                                                                              | 245 |
| 122.8.5.2  | Channel requirements .....                                                                                                                                                                                      | 246 |
| 122.8.5.3  | TDECQ measurement method .....                                                                                                                                                                                  | 247 |
| 122.8.5.4  | TDECQ reference equalizer .....                                                                                                                                                                                 | 247 |
| 122.8.6    | Extinction ratio .....                                                                                                                                                                                          | 247 |
| 122.8.7    | Relative intensity noise (RIN <sub>16.5OMA</sub> and RIN <sub>15.1OMA</sub> ) .....                                                                                                                             | 247 |
| 122.8.8    | Receiver sensitivity .....                                                                                                                                                                                      | 247 |
| 122.8.9    | Stressed receiver sensitivity .....                                                                                                                                                                             | 247 |
| 122.8.9.1  | Stressed receiver conformance test block diagram .....                                                                                                                                                          | 248 |
| 122.8.9.2  | Stressed receiver conformance test signal characteristics and calibration .....                                                                                                                                 | 248 |
| 122.8.9.3  | Stressed receiver conformance test signal verification .....                                                                                                                                                    | 248 |
| 122.9      | Safety, installation, environment, and labeling .....                                                                                                                                                           | 249 |
| 122.9.1    | General safety .....                                                                                                                                                                                            | 249 |
| 122.9.2    | Laser safety .....                                                                                                                                                                                              | 249 |
| 122.9.3    | Installation .....                                                                                                                                                                                              | 250 |
| 122.9.4    | Environment .....                                                                                                                                                                                               | 250 |
| 122.9.5    | Electromagnetic emission .....                                                                                                                                                                                  | 250 |
| 122.9.6    | Temperature, humidity, and handling .....                                                                                                                                                                       | 250 |
| 122.9.7    | PMD labeling requirements .....                                                                                                                                                                                 | 250 |
| 122.10     | Fiber optic cabling model .....                                                                                                                                                                                 | 251 |
| 122.11     | Characteristics of the fiber optic cabling (channel) .....                                                                                                                                                      | 252 |
| 122.11.1   | Optical fiber cable .....                                                                                                                                                                                       | 252 |
| 122.11.2   | Optical fiber connection .....                                                                                                                                                                                  | 252 |
| 122.11.2.1 | Connection insertion loss .....                                                                                                                                                                                 | 252 |
| 122.11.2.2 | Maximum discrete reflectance .....                                                                                                                                                                              | 252 |
| 122.11.3   | Medium Dependent Interface (MDI) requirements .....                                                                                                                                                             | 253 |
| 122.12     | Protocol implementation conformance statement (PICS) proforma for Clause 122, Physical<br>Medium Dependent (PMD) sublayer and medium, type 200GBASE-FR4, 200GBASE-<br>LR4, 400GBASE-FR8, and 400GBASE-LR8 ..... | 254 |
| 122.12.1   | Introduction .....                                                                                                                                                                                              | 254 |
| 122.12.2   | Identification .....                                                                                                                                                                                            | 254 |
| 122.12.2.1 | Implementation identification .....                                                                                                                                                                             | 254 |

|            |                                                                                                                                                    |     |
|------------|----------------------------------------------------------------------------------------------------------------------------------------------------|-----|
| 122.12.2.2 | Protocol summary .....                                                                                                                             | 254 |
| 122.12.3   | Major capabilities/options.....                                                                                                                    | 255 |
| 122.12.4   | PICS proforma tables for Physical Medium Dependent (PMD) sublayer and medium, type 200GBASE-FR4, 200GBASE-LR4, 400GBASE-FR8, and 400GBASE-LR8..... | 255 |
| 122.12.4.1 | PMD functional specifications.....                                                                                                                 | 255 |
| 122.12.4.2 | Management functions.....                                                                                                                          | 256 |
| 122.12.4.3 | PMD to MDI optical specifications for 200GBASE-FR4.....                                                                                            | 257 |
| 122.12.4.4 | PMD to MDI optical specifications for 200GBASE-LR4.....                                                                                            | 257 |
| 122.12.4.5 | PMD to MDI optical specifications for 400GBASE-FR8.....                                                                                            | 257 |
| 122.12.4.6 | PMD to MDI optical specifications for 400GBASE-LR8.....                                                                                            | 257 |
| 122.12.4.7 | Optical measurement methods.....                                                                                                                   | 258 |
| 122.12.4.8 | Environmental specifications.....                                                                                                                  | 258 |
| 122.12.4.9 | Characteristics of the fiber optic cabling and MDI.....                                                                                            | 258 |
| 123.       | Physical Medium Dependent (PMD) sublayer and medium, type 400GBASE-SR16.....                                                                       | 259 |
| 123.1      | Overview.....                                                                                                                                      | 259 |
| 123.1.1    | Bit error ratio .....                                                                                                                              | 260 |
| 123.2      | Physical Medium Dependent (PMD) service interface .....                                                                                            | 260 |
| 123.3      | Delay and Skew .....                                                                                                                               | 261 |
| 123.3.1    | Delay constraints.....                                                                                                                             | 261 |
| 123.3.2    | Skew constraints .....                                                                                                                             | 261 |
| 123.4      | PMD MDIO function mapping.....                                                                                                                     | 262 |
| 123.5      | PMD functional specifications.....                                                                                                                 | 262 |
| 123.5.1    | PMD block diagram.....                                                                                                                             | 262 |
| 123.5.2    | PMD transmit function .....                                                                                                                        | 263 |
| 123.5.3    | PMD receive function.....                                                                                                                          | 263 |
| 123.5.4    | PMD global signal detect function .....                                                                                                            | 264 |
| 123.5.5    | PMD lane-by-lane signal detect function .....                                                                                                      | 264 |
| 123.5.6    | PMD reset function.....                                                                                                                            | 264 |
| 123.5.7    | PMD global transmit disable function (optional) .....                                                                                              | 265 |
| 123.5.8    | PMD lane-by-lane transmit disable function (optional) .....                                                                                        | 265 |
| 123.5.9    | PMD fault function (optional) .....                                                                                                                | 265 |
| 123.5.10   | PMD transmit fault function (optional) .....                                                                                                       | 265 |
| 123.5.11   | PMD receive fault function (optional).....                                                                                                         | 265 |
| 123.6      | Lane assignments.....                                                                                                                              | 265 |
| 123.7      | PMD to MDI optical specifications for 400GBASE-SR16 .....                                                                                          | 266 |
| 123.7.1    | 400GBASE-SR16 transmitter optical specifications .....                                                                                             | 266 |
| 123.7.2    | 400GBASE-SR16 receive optical specifications.....                                                                                                  | 266 |
| 123.7.3    | 400GBASE-SR16 illustrative link power budget.....                                                                                                  | 266 |
| 123.8      | Definition of optical parameters and measurement methods.....                                                                                      | 266 |
| 123.8.1    | Test patterns for optical parameters.....                                                                                                          | 266 |
| 123.8.2    | Center wavelength and spectral width .....                                                                                                         | 267 |
| 123.8.3    | Average optical power .....                                                                                                                        | 267 |
| 123.8.4    | Optical Modulation Amplitude (OMA).....                                                                                                            | 267 |
| 123.8.5    | Transmitter and dispersion eye closure (TDEC) .....                                                                                                | 267 |
| 123.8.6    | Extinction ratio .....                                                                                                                             | 267 |
| 123.8.7    | Transmitter optical waveform (transmit eye) .....                                                                                                  | 267 |
| 123.8.8    | Stressed receiver sensitivity.....                                                                                                                 | 267 |
| 123.9      | Safety, installation, environment, and labeling.....                                                                                               | 268 |
| 123.9.1    | General safety .....                                                                                                                               | 268 |
| 123.9.2    | Laser safety .....                                                                                                                                 | 268 |
| 123.9.3    | Installation .....                                                                                                                                 | 268 |

|            |                                                                                                                                                               |     |
|------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------|-----|
| 123.9.4    | Environment.....                                                                                                                                              | 268 |
| 123.9.5    | Electromagnetic emission .....                                                                                                                                | 268 |
| 123.9.6    | Temperature, humidity, and handling.....                                                                                                                      | 268 |
| 123.9.7    | PMD labeling requirements .....                                                                                                                               | 269 |
| 123.10     | Fiber optic cabling model .....                                                                                                                               | 269 |
| 123.11     | Characteristics of the fiber optic cabling (channel) .....                                                                                                    | 269 |
| 123.11.1   | Optical fiber cable.....                                                                                                                                      | 270 |
| 123.11.2   | Optical fiber connection.....                                                                                                                                 | 270 |
| 123.11.2.1 | Connection insertion loss.....                                                                                                                                | 270 |
| 123.11.2.2 | Maximum discrete reflectance.....                                                                                                                             | 270 |
| 123.11.3   | Medium Dependent Interface (MDI) .....                                                                                                                        | 270 |
| 123.11.3.1 | Optical lane assignments .....                                                                                                                                | 271 |
| 123.11.3.2 | Medium Dependent Interface (MDI) requirements .....                                                                                                           | 271 |
| 123.12     | Protocol implementation conformance statement (PICS) proforma for Clause 123, Physical<br>Medium Dependent (PMD) sublayer and medium, type 400GBASE-SR16..... | 272 |
| 123.12.1   | Introduction.....                                                                                                                                             | 272 |
| 123.12.2   | Identification .....                                                                                                                                          | 272 |
| 123.12.2.1 | Implementation identification.....                                                                                                                            | 272 |
| 123.12.2.2 | Protocol summary .....                                                                                                                                        | 272 |
| 123.12.3   | Major capabilities/options.....                                                                                                                               | 273 |
| 123.12.4   | PICS proforma tables for Physical Medium Dependent (PMD) sublayer and<br>medium, type 400GBASE-SR16 .....                                                     | 273 |
| 123.12.4.1 | PMD functional specifications.....                                                                                                                            | 273 |
| 123.12.4.2 | Management functions.....                                                                                                                                     | 274 |
| 123.12.4.3 | PMD to MDI optical specifications for 400GBASE-SR16 .....                                                                                                     | 274 |
| 123.12.4.4 | Optical measurement methods.....                                                                                                                              | 275 |
| 123.12.4.5 | Environmental specifications.....                                                                                                                             | 275 |
| 123.12.4.6 | Characteristics of the fiber optic cabling and MDI.....                                                                                                       | 275 |
| 124.       | Physical Medium Dependent (PMD) sublayer and medium, type 400GBASE-DR4 .....                                                                                  | 277 |
| 124.1      | Overview.....                                                                                                                                                 | 277 |
| 124.1.1    | Bit error ratio .....                                                                                                                                         | 277 |
| 124.2      | Physical Medium Dependent (PMD) service interface .....                                                                                                       | 278 |
| 124.3      | Delay and Skew .....                                                                                                                                          | 279 |
| 124.3.1    | Delay constraints.....                                                                                                                                        | 279 |
| 124.3.2    | Skew constraints .....                                                                                                                                        | 279 |
| 124.4      | PMD MDIO function mapping.....                                                                                                                                | 279 |
| 124.5      | PMD functional specifications.....                                                                                                                            | 280 |
| 124.5.1    | PMD block diagram.....                                                                                                                                        | 280 |
| 124.5.2    | PMD transmit function .....                                                                                                                                   | 281 |
| 124.5.3    | PMD receive function.....                                                                                                                                     | 281 |
| 124.5.4    | PMD global signal detect function .....                                                                                                                       | 281 |
| 124.5.5    | PMD lane-by-lane signal detect function .....                                                                                                                 | 282 |
| 124.5.6    | PMD reset function.....                                                                                                                                       | 282 |
| 124.5.7    | PMD global transmit disable function (optional) .....                                                                                                         | 282 |
| 124.5.8    | PMD lane-by-lane transmit disable function (optional) .....                                                                                                   | 283 |
| 124.5.9    | PMD fault function (optional) .....                                                                                                                           | 283 |
| 124.5.10   | PMD transmit fault function (optional) .....                                                                                                                  | 283 |
| 124.5.11   | PMD receive fault function (optional).....                                                                                                                    | 283 |
| 124.6      | Lane assignments.....                                                                                                                                         | 283 |
| 124.7      | PMD to MDI optical specifications for 400GBASE-DR4 .....                                                                                                      | 283 |
| 124.7.1    | 400GBASE-DR4 transmitter optical specifications .....                                                                                                         | 284 |
| 124.7.2    | 400GBASE-DR4 receive optical specifications .....                                                                                                             | 284 |

|                       |                                                                                                                                                            |     |
|-----------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------|-----|
| 124.7.3               | 400GBASE-DR4 illustrative link power budget .....                                                                                                          | 285 |
| 124.8                 | Definition of optical parameters and measurement methods .....                                                                                             | 286 |
| 124.8.1               | Test patterns for optical parameters .....                                                                                                                 | 286 |
| 124.8.2               | Wavelength .....                                                                                                                                           | 286 |
| 124.8.3               | Average optical power .....                                                                                                                                | 287 |
| 124.8.4               | Outer Optical Modulation Amplitude (OMA <sub>outer</sub> ) .....                                                                                           | 287 |
| 124.8.5               | Transmitter and dispersion eye closure for PAM4 (TDECQ) .....                                                                                              | 287 |
| 124.8.6               | Extinction ratio .....                                                                                                                                     | 287 |
| 124.8.7               | Relative intensity noise (RIN <sub>21.4OMA</sub> ) .....                                                                                                   | 288 |
| 124.8.8               | Receiver sensitivity .....                                                                                                                                 | 288 |
| 124.8.9               | Stressed receiver sensitivity .....                                                                                                                        | 288 |
| 124.9                 | Safety, installation, environment, and labeling .....                                                                                                      | 288 |
| 124.9.1               | General safety .....                                                                                                                                       | 288 |
| 124.9.2               | Laser safety .....                                                                                                                                         | 288 |
| 124.9.3               | Installation .....                                                                                                                                         | 289 |
| 124.9.4               | Environment .....                                                                                                                                          | 289 |
| 124.9.5               | Electromagnetic emission .....                                                                                                                             | 289 |
| 124.9.6               | Temperature, humidity, and handling .....                                                                                                                  | 289 |
| 124.9.7               | PMD labeling requirements .....                                                                                                                            | 289 |
| 124.10                | Fiber optic cabling model .....                                                                                                                            | 289 |
| 124.11                | Characteristics of the fiber optic cabling (channel) .....                                                                                                 | 290 |
| 124.11.1              | Optical fiber cable .....                                                                                                                                  | 290 |
| 124.11.2              | Optical fiber connection .....                                                                                                                             | 291 |
| 124.11.2.1            | Connection insertion loss .....                                                                                                                            | 291 |
| 124.11.2.2            | Maximum discrete reflectance .....                                                                                                                         | 291 |
| 124.11.3              | Medium Dependent Interface (MDI) .....                                                                                                                     | 291 |
| 124.11.3.1            | Optical lane assignments .....                                                                                                                             | 291 |
| 124.11.3.2            | Medium Dependent Interface (MDI) requirements .....                                                                                                        | 292 |
| 124.12                | Protocol implementation conformance statement (PICS) proforma for Clause 124, Physical Medium Dependent (PMD) sublayer and medium, type 400GBASE-DR4 ..... | 293 |
| 124.12.1              | Introduction .....                                                                                                                                         | 293 |
| 124.12.2              | Identification .....                                                                                                                                       | 293 |
| 124.12.2.1            | Implementation identification .....                                                                                                                        | 293 |
| 124.12.2.2            | Protocol summary .....                                                                                                                                     | 293 |
| 124.12.3              | Major capabilities/options .....                                                                                                                           | 294 |
| 124.12.4              | PICS proforma tables for Physical Medium Dependent (PMD) sublayer and medium, type 400GBASE-DR4 .....                                                      | 294 |
| 124.12.4.1            | PMD functional specifications .....                                                                                                                        | 294 |
| 124.12.4.2            | Management functions .....                                                                                                                                 | 295 |
| 124.12.4.3            | PMD to MDI optical specifications for 400GBASE-DR4 .....                                                                                                   | 295 |
| 124.12.4.4            | Optical measurement methods .....                                                                                                                          | 296 |
| 124.12.4.5            | Environmental specifications .....                                                                                                                         | 296 |
| 124.12.4.6            | Characteristics of the fiber optic cabling and MDI .....                                                                                                   | 296 |
| Annex A (informative) | Bibliography .....                                                                                                                                         | 297 |
| Annex 4A (normative)  | Simplified full duplex media access control .....                                                                                                          | 298 |
| 4A.4                  | Specific implementations .....                                                                                                                             | 298 |
| 4A.4.2                | MAC parameters .....                                                                                                                                       | 298 |
| Annex 31B (normative) | MAC Control PAUSE operation .....                                                                                                                          | 299 |
| 31B.3                 | Detailed specification of PAUSE operation .....                                                                                                            | 299 |

|            |                                                                                                                                                                                                                                               |     |
|------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----|
| 31B.3.7    | Timing considerations for PAUSE operation .....                                                                                                                                                                                               | 299 |
| 31B.4      | Protocol implementation conformance statement (PICS) proforma for MAC Control<br>PAUSE operation .....                                                                                                                                        | 299 |
| 31B.4.3    | Major capabilities/options .....                                                                                                                                                                                                              | 299 |
| 31B.4.6    | PAUSE command MAC timing considerations .....                                                                                                                                                                                                 | 300 |
| Annex 93A  | (normative) Specification methods for electrical channels .....                                                                                                                                                                               | 301 |
| 93A.1      | Channel Operating Margin .....                                                                                                                                                                                                                | 301 |
| 93A.1.2    | Transmitter and receiver device package models .....                                                                                                                                                                                          | 302 |
| 93A.1.2.3  | Two-port network for the package transmission line .....                                                                                                                                                                                      | 302 |
| 93A.1.4    | Filters .....                                                                                                                                                                                                                                 | 302 |
| 93A.1.4.3  | Receiver equalizer .....                                                                                                                                                                                                                      | 302 |
| 93A.1.6    | Determination of variable equalizer parameters .....                                                                                                                                                                                          | 303 |
| 93A.1.7    | Interference and noise amplitude .....                                                                                                                                                                                                        | 303 |
| Annex 119A | (informative) 200GBASE-R and 400GBASE-R PCS FEC codeword examples .....                                                                                                                                                                       | 304 |
| Annex 120A | (informative) 200 Gb/s and 400 Gb/s PMA sublayer partitioning examples .....                                                                                                                                                                  | 310 |
| 120A.1     | Partitioning example supporting 400GBASE-SR16 .....                                                                                                                                                                                           | 310 |
| 120A.2     | Partitioning examples supporting 200GBASE-DR4/FR4/LR4 and 400GBASE-FR8/LR8 ....                                                                                                                                                               | 311 |
| 120A.3     | Partitioning examples supporting 400GBASE-DR4 .....                                                                                                                                                                                           | 313 |
| 120A.4     | Partitioning example using 200GXS and 400GXS .....                                                                                                                                                                                            | 314 |
| Annex 120B | (normative) Chip-to-chip 200 Gb/s eight-lane Attachment Unit Interface (200GAUI-8<br>C2C) and 400 Gb/s sixteen-lane Attachment Unit Interface (400GAUI-16 C2C) .....                                                                          | 315 |
| 120B.1     | Overview .....                                                                                                                                                                                                                                | 315 |
| 120B.2     | 200GAUI-8 and 400GAUI-16 chip-to-chip compliance point definition .....                                                                                                                                                                       | 317 |
| 120B.3     | 200GAUI-8 and 400GAUI-16 chip-to-chip electrical characteristics .....                                                                                                                                                                        | 318 |
| 120B.3.1   | 200GAUI-8 and 400GAUI-16 C2C transmitter characteristics .....                                                                                                                                                                                | 318 |
| 120B.3.2   | 200GAUI-8 and 400GAUI-16 C2C receiver characteristics .....                                                                                                                                                                                   | 318 |
| 120B.4     | 200GAUI-8 and 400GAUI-16 chip-to-chip channel characteristics .....                                                                                                                                                                           | 319 |
| 120B.5     | Protocol implementation conformance statement (PICS) proforma for Annex 120B, Chip-<br>to-chip 200 Gb/s eight-lane Attachment Unit Interface (200GAUI-8 C2C) and 400 Gb/s<br>sixteen-lane Attachment Unit Interface<br>(400GAUI-16 C2C) ..... | 320 |
| 120B.5.1   | Introduction .....                                                                                                                                                                                                                            | 320 |
| 120B.5.2   | Identification .....                                                                                                                                                                                                                          | 320 |
| 120B.5.2.1 | Implementation identification .....                                                                                                                                                                                                           | 320 |
| 120B.5.2.2 | Protocol summary .....                                                                                                                                                                                                                        | 320 |
| 120B.5.3   | Major capabilities/options .....                                                                                                                                                                                                              | 321 |
| 120B.5.4   | PICS proforma tables for Chip-to-chip 200 Gb/s eight-lane Attachment Unit<br>Interface (200GAUI-8 C2C) and 400 Gb/s sixteen-lane Attachment Unit Interface<br>(400GAUI-16 C2C) .....                                                          | 321 |
| 120B.5.4.1 | Transmitter .....                                                                                                                                                                                                                             | 321 |
| 120B.5.4.2 | Receiver .....                                                                                                                                                                                                                                | 322 |
| 120B.5.4.3 | Channel .....                                                                                                                                                                                                                                 | 322 |
| Annex 120C | (normative) Chip-to-module 200 Gb/s eight-lane Attachment Unit Interface (200GAUI-8<br>C2M) and 400 Gb/s sixteen-lane Attachment Unit Interface (400GAUI-16 C2M) .....                                                                        | 323 |
| 120C.1     | Overview .....                                                                                                                                                                                                                                | 323 |

|                                                                                                                                                                                                                                              |     |
|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----|
| 120C.1.1 Bit error ratio .....                                                                                                                                                                                                               | 325 |
| 120C.2 200GAUI-8 and 400GAUI-16 chip-to-module compliance point definitions .....                                                                                                                                                            | 325 |
| 120C.3 200GAUI-8 and 400GAUI-16 chip-to-module electrical characteristics .....                                                                                                                                                              | 325 |
| 120C.3.1 200GAUI-8 and 400GAUI-16 C2M host output characteristics .....                                                                                                                                                                      | 325 |
| 120C.3.2 200GAUI-8 and 400GAUI-16 C2M module output characteristics .....                                                                                                                                                                    | 325 |
| 120C.3.3 200GAUI-8 and 400GAUI-16 C2M host input characteristics .....                                                                                                                                                                       | 325 |
| 120C.3.4 200GAUI-8 and 400GAUI-16 C2M module input characteristics .....                                                                                                                                                                     | 326 |
| 120C.4 200GAUI-8 and 400GAUI-16 C2M measurement methodology .....                                                                                                                                                                            | 326 |
| 120C.5 Protocol implementation conformance statement (PICS) proforma for Annex 120C, Chip-to-module 200 Gb/s eight-lane Attachment Unit Interface (200GAUI-8 C2M) and 400 Gb/s sixteen-lane Attachment Unit Interface (400GAUI-16 C2M) ..... | 327 |
| 120C.5.1 Introduction .....                                                                                                                                                                                                                  | 327 |
| 120C.5.2 Identification .....                                                                                                                                                                                                                | 327 |
| 120C.5.2.1 Implementation identification .....                                                                                                                                                                                               | 327 |
| 120C.5.2.2 Protocol summary .....                                                                                                                                                                                                            | 327 |
| 120C.5.3 Major capabilities/options .....                                                                                                                                                                                                    | 328 |
| 120C.5.4 PICS proforma tables for Chip-to-module 200 Gb/s eight-lane Attachment Unit Interface (200GAUI-8 C2M) and 400 Gb/s sixteen-lane Attachment Unit Interface (400GAUI-16 C2M) .....                                                    | 328 |
| 120C.5.4.1 Host output .....                                                                                                                                                                                                                 | 328 |
| 120C.5.4.2 Module output .....                                                                                                                                                                                                               | 329 |
| 120C.5.4.3 Host input .....                                                                                                                                                                                                                  | 329 |
| 120C.5.4.4 Module input .....                                                                                                                                                                                                                | 329 |
| Annex 120D (normative) Chip-to-chip 200 Gb/s four-lane Attachment Unit Interface (200GAUI-4 C2C) and 400 Gb/s eight-lane Attachment Unit Interface (400GAUI-8 C2C) .....                                                                     | 330 |
| 120D.1 Overview .....                                                                                                                                                                                                                        | 330 |
| 120D.2 200GAUI-4 and 400GAUI-8 chip-to-chip compliance point definition .....                                                                                                                                                                | 333 |
| 120D.3 200GAUI-4 and 400GAUI-8 chip-to-chip electrical characteristics .....                                                                                                                                                                 | 333 |
| 120D.3.1 200GAUI-4 and 400GAUI-8 C2C transmitter characteristics .....                                                                                                                                                                       | 333 |
| 120D.3.1.1 Transmitter differential output return loss .....                                                                                                                                                                                 | 334 |
| 120D.3.1.2 Transmitter linearity .....                                                                                                                                                                                                       | 335 |
| 120D.3.1.2.1 Measurement of mean signal levels .....                                                                                                                                                                                         | 335 |
| 120D.3.1.3 Linear fit to the measured waveform .....                                                                                                                                                                                         | 336 |
| 120D.3.1.4 Steady-state voltage and linear fit pulse peak .....                                                                                                                                                                              | 336 |
| 120D.3.1.5 Transmitter equalization settings .....                                                                                                                                                                                           | 336 |
| 120D.3.1.6 Transmitter output noise and distortion .....                                                                                                                                                                                     | 338 |
| 120D.3.1.7 Transmitter output residual ISI .....                                                                                                                                                                                             | 338 |
| 120D.3.1.8 Output jitter .....                                                                                                                                                                                                               | 338 |
| 120D.3.1.8.1 J4u and JRMS jitter .....                                                                                                                                                                                                       | 339 |
| 120D.3.1.8.2 Even-odd Jitter .....                                                                                                                                                                                                           | 340 |
| 120D.3.2 200GAUI-4 and 400GAUI-8 C2C receiver characteristics .....                                                                                                                                                                          | 340 |
| 120D.3.2.1 Receiver interference tolerance .....                                                                                                                                                                                             | 340 |
| 120D.3.2.2 Receiver jitter tolerance .....                                                                                                                                                                                                   | 342 |
| 120D.3.2.3 Transmitter equalization feedback (optional) .....                                                                                                                                                                                | 342 |
| 120D.4 200GAUI-4 and 400GAUI-8 chip-to-chip channel characteristics .....                                                                                                                                                                    | 343 |
| 120D.4.1 Channel Operating Margin .....                                                                                                                                                                                                      | 343 |
| 120D.4.2 Channel return loss .....                                                                                                                                                                                                           | 344 |
| 120D.5 Protocol implementation conformance statement (PICS) proforma for Annex 120D, Chip-to-chip 200 Gb/s four-lane Attachment Unit Interface (200GAUI-4 C2C) and 400 Gb/s eight-lane Attachment Unit Interface (400GAUI-8 C2C) .....       | 346 |
| 120D.5.1 Introduction .....                                                                                                                                                                                                                  | 346 |

|                                                                                                                                                                                                                                          |     |
|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----|
| 120D.5.2 Identification .....                                                                                                                                                                                                            | 346 |
| 120D.5.2.1 Implementation identification .....                                                                                                                                                                                           | 346 |
| 120D.5.2.2 Protocol summary .....                                                                                                                                                                                                        | 346 |
| 120D.5.3 Major capabilities/options .....                                                                                                                                                                                                | 347 |
| 120D.5.4 PICS proforma tables for Chip-to-chip 200 Gb/s four-lane Attachment Unit Interface (200GAUI-4 C2C) and 400 Gb/s eight-lane Attachment Unit Interface (400GAUI-8 C2C) .....                                                      | 347 |
| 120D.5.4.1 Transmitter .....                                                                                                                                                                                                             | 347 |
| 120D.5.4.2 Receiver .....                                                                                                                                                                                                                | 348 |
| 120D.5.4.3 Channel .....                                                                                                                                                                                                                 | 348 |
| Annex 120E (normative) Chip-to-module 200 Gb/s four-lane Attachment Unit Interface (200GAUI-4 C2M) and 400 Gb/s eight-lane Attachment Unit Interface (400GAUI-8 C2M) .....                                                               | 349 |
| 120E.1 Overview .....                                                                                                                                                                                                                    | 349 |
| 120E.1.1 Bit error ratio .....                                                                                                                                                                                                           | 351 |
| 120E.2 200GAUI-4 and 400GAUI-8 chip-to-module compliance point definitions .....                                                                                                                                                         | 351 |
| 120E.3 200GAUI-4 and 400GAUI-8 chip-to-module electrical characteristics .....                                                                                                                                                           | 352 |
| 120E.3.1 200GAUI-4 and 400GAUI-8 C2M host output characteristics .....                                                                                                                                                                   | 352 |
| 120E.3.1.1 Signaling rate and range .....                                                                                                                                                                                                | 353 |
| 120E.3.1.2 Signal levels .....                                                                                                                                                                                                           | 353 |
| 120E.3.1.3 Output return loss .....                                                                                                                                                                                                      | 354 |
| 120E.3.1.4 Differential termination mismatch .....                                                                                                                                                                                       | 354 |
| 120E.3.1.5 Transition time .....                                                                                                                                                                                                         | 354 |
| 120E.3.1.6 Host output eye width and eye height .....                                                                                                                                                                                    | 354 |
| 120E.3.1.7 Reference receiver for eye width and eye height evaluation .....                                                                                                                                                              | 355 |
| 120E.3.2 200GAUI-4 and 400GAUI-8 C2M module output characteristics .....                                                                                                                                                                 | 357 |
| 120E.3.2.1 Module output eye width, eye height, and pre-cursor ISI ratio .....                                                                                                                                                           | 358 |
| 120E.3.2.1.1 Reference receiver for module output evaluation .....                                                                                                                                                                       | 359 |
| 120E.3.2.1.2 Far-end pre-cursor ISI ratio .....                                                                                                                                                                                          | 359 |
| 120E.3.3 200GAUI-4 and 400GAUI-8 C2M host input characteristics .....                                                                                                                                                                    | 359 |
| 120E.3.3.1 Input return loss .....                                                                                                                                                                                                       | 359 |
| 120E.3.3.2 Host stressed input test .....                                                                                                                                                                                                | 360 |
| 120E.3.3.2.1 Host stressed input test procedure .....                                                                                                                                                                                    | 360 |
| 120E.3.4 200GAUI-4 and 400GAUI-8 C2M module input characteristics .....                                                                                                                                                                  | 362 |
| 120E.3.4.1 Module stressed input test .....                                                                                                                                                                                              | 362 |
| 120E.3.4.1.1 Module stressed input test procedure .....                                                                                                                                                                                  | 362 |
| 120E.4 200GAUI-4 and 400GAUI-8 C2M measurement methodology .....                                                                                                                                                                         | 364 |
| 120E.4.1 HCB/MCB characteristics .....                                                                                                                                                                                                   | 364 |
| 120E.4.2 Eye width and eye height measurement method .....                                                                                                                                                                               | 365 |
| 120E.5 Protocol implementation conformance statement (PICS) proforma for Annex 120E, Chip-to-module 200 Gb/s four-lane Attachment Unit Interface (200GAUI-4 C2M) and 400 Gb/s eight-lane Attachment Unit Interface (400GAUI-8 C2M) ..... | 368 |
| 120E.5.1 Introduction .....                                                                                                                                                                                                              | 368 |
| 120E.5.2 Identification .....                                                                                                                                                                                                            | 368 |
| 120E.5.2.1 Implementation identification .....                                                                                                                                                                                           | 368 |
| 120E.5.2.2 Protocol summary .....                                                                                                                                                                                                        | 368 |
| 120E.5.3 Major capabilities/options .....                                                                                                                                                                                                | 369 |
| 120E.5.4 PICS proforma tables for Chip-to-module 200 Gb/s four-lane Attachment Unit Interface (200GAUI-4 C2M) and 400 Gb/s eight-lane Attachment Unit Interface (400GAUI-8 C2M) .....                                                    | 369 |
| 120E.5.4.1 Host output .....                                                                                                                                                                                                             | 369 |
| 120E.5.4.2 Module output .....                                                                                                                                                                                                           | 370 |

|                              |     |
|------------------------------|-----|
| 120E.5.4.3 Host input.....   | 370 |
| 120E.5.4.4 Module input..... | 370 |

# IEEE Standard for Ethernet

## Amendment 10: Media Access Control Parameters, Physical Layers, and Management Parameters for 200 Gb/s and 400 Gb/s Operation

NOTE—The editing instructions contained in this amendment define how to merge the material contained therein into the existing base standard and its amendments to form the comprehensive standard.

The editing instructions are shown in ***bold italic***. Four editing instructions are used: change, delete, insert, and replace. ***Change*** is used to make corrections in existing text or tables. The editing instruction specifies the location of the change and describes what is being changed by using ~~striketrough~~ (to remove old material) and underscore (to add new material). ***Delete*** removes existing material. ***Insert*** adds new material without disturbing the existing material. Deletions and insertions may require renumbering. If so, renumbering instructions are given in the editing instruction. ***Replace*** is used to make changes in figures or equations by removing the existing figure or equation and replacing it with a new one. Editing instructions, change markings, and this NOTE will not be carried over into future editions because the changes will be incorporated into the base standard.

Cross references that refer to clauses, tables, equations, or figures not covered by this amendment are highlighted in green.

### 1. Introduction

#### 1.1 Overview

##### 1.1.3 Architectural perspectives

##### 1.1.3.2 Compatibility interfaces

***Insert the following compatibility interfaces after “100 Gb/s Parallel Physical Interface (CPPI)”:***

- q) ***200 Gb/s Media Independent Interface (200GMII)***. The 200GMII is designed to connect a 200 Gb/s capable MAC to a 200 Gb/s PHY. While conformance with implementation of this interface is not necessary to ensure communication, it allows flexibility in intermixing PHYs and DTEs at 200 Gb/s speeds. The 200GMII is a logical interconnection intended for use as an intra-chip interface. No mechanical connector is specified for use with the 200GMII. The 200GMII is optional.

- r) *200 Gb/s Attachment Unit Interface (200GAUI-n)*. The 200GAUI-n is a physical instantiation of the PMA service interface to extend the connection between 200 Gb/s capable PMAs. While conformance with implementation of this interface is not necessary to ensure communication, it is recommended, since it allows maximum flexibility in intermixing PHYs and DTEs at 200 Gb/s speeds. The 200GAUI-n is intended for use as a chip-to-chip or a chip-to-module interface. Two widths of 200GAUI-n are defined: an eight-lane version (200GAUI-8) in Annex 120B and Annex 120C, and a four-lane version (200GAUI-4) in Annex 120D and Annex 120E. No mechanical connector is specified for use with the 200GAUI-n. The 200GAUI-n is optional.
- s) *400 Gb/s Media Independent Interface (400GMII)*. The 400GMII is designed to connect a 400 Gb/s capable MAC to a 400 Gb/s PHY. While conformance with implementation of this interface is not necessary to ensure communication, it allows flexibility in intermixing PHYs and DTEs at 400 Gb/s speeds. The 400GMII is a logical interconnection intended for use as an intra-chip interface. No mechanical connector is specified for use with the 400GMII. The 400GMII is optional.
- t) *400 Gb/s Attachment Unit Interface (400GAUI-n)*. The 400GAUI-n is a physical instantiation of the PMA service interface to extend the connection between 400 Gb/s capable PMAs. While conformance with implementation of this interface is not necessary to ensure communication, it is recommended, since it allows maximum flexibility in intermixing PHYs and DTEs at 400 Gb/s speeds. The 400GAUI-n is intended for use as a chip-to-chip or a chip-to-module interface. Two widths of 400GAUI-n are defined: a sixteen-lane version (400GAUI-16) in Annex 120B and Annex 120C, and an eight-lane version (400GAUI-8) in Annex 120D and Annex 120E. No mechanical connector is specified for use with the 400GAUI-n. The 400GAUI-n is optional.

### 1.3 Normative references

*Insert the following references in alphanumeric order:*

ANSI/TIA-604-18:2015, FOCIS 18—Fiber Optic Connector Intermateability Standard—Type MPO-16

IEC 61753-021-2:2007, Fibre optic interconnecting devices and passive components performance standard—Part 021-2: Grade C/3 single-mode fibre optic connectors for category C—Controlled environment.

*Change the reference for IEC 60793-2-10 as follows:*

IEC 60793-2-10:2014, Optical fibres—Part 2-10: Product specifications—Sectional specification for category A1 multimode fibres.

### 1.4 Definitions

*Insert the following 17 new definitions into the list after 1.4.72a 40GBASE-T (as inserted by IEEE Std 802.3bq-2016):*

**1.4.72b 200GBASE-DR4:** IEEE 802.3 Physical Layer specification for 200 Gb/s using 200GBASE-R encoding and 4-level pulse amplitude modulation over four lanes of single-mode fiber, with reach up to at least 500 m. (See IEEE Std 802.3, Clause 121.)

**1.4.72c 200GBASE-FR4:** IEEE 802.3 Physical Layer specification for 200 Gb/s using 200GBASE-R encoding and 4-level pulse amplitude modulation over four WDM lanes on single-mode fiber, with reach up to at least 2 km. (See IEEE Std 802.3, Clause 122.)

**1.4.72d 200GBASE-LR4:** IEEE 802.3 Physical Layer specification for 200 Gb/s using 200GBASE-R encoding and 4-level pulse amplitude modulation over four WDM lanes on single-mode fiber, with reach up to at least 10 km. (See IEEE Std 802.3, Clause 122.)

**1.4.72e 200GBASE-R:** An IEEE 802.3 family of Physical Layer devices using the physical coding sublayer defined in Clause 119 for 200 Gb/s operation. (See IEEE Std 802.3, Clause 119.)

**1.4.72f 200 Gb/s Attachment Unit Interface (200GAUI-n):** A physical instantiation of the PMA service interface to extend the connection between 200 Gb/s capable PMAs over n lanes, used for chip-to-chip or chip-to-module interconnections. Two widths of 200GAUI-n are defined: an eight-lane version (200GAUI-8), and a four-lane version (200GAUI-4). (See IEEE Std 802.3, Annex 120B and Annex 120C for 200GAUI-8, or Annex 120D and Annex 120E for 200GAUI-4.)

**1.4.72g 200 Gb/s Media Independent Interface (200GMII):** The interface between the Reconciliation Sublayer (RS) and the Physical Coding Sublayer (PCS) for 200 Gb/s operation. (See IEEE Std 802.3, Clause 117.)

**1.4.72h 200GMII Extender:** The 200 Gb/s Media Independent Interface Extender extends the reach of the 200GMII and consists of two 200GXS sublayers with a 200GAUI-n between them. (See IEEE Std 802.3, Clause 118.)

**1.4.72i 200GXS:** The 200 Gb/s Extender Sublayer (200GXS) is part of the 200GMII Extender. In functionality, it is almost identical to the 200GBASE-R PCS Sublayer defined in Clause 119. Two types of 200GXS are defined: the DTE 200GXS adjacent to the RS sublayer and the PHY 200GXS adjacent to the PHY. (See IEEE Std 802.3, Clause 118.)

**1.4.72j 400GBASE-DR4:** IEEE 802.3 Physical Layer specification for 400 Gb/s using 400GBASE-R encoding and 4-level pulse amplitude modulation over four lanes of single-mode fiber, with reach up to at least 500 m. (See IEEE Std 802.3, Clause 124.)

**1.4.72k 400GBASE-FR8:** IEEE 802.3 Physical Layer specification for 400 Gb/s using 400GBASE-R encoding and 4-level pulse amplitude modulation over eight WDM lanes on single-mode fiber, with reach up to at least 2 km. (See IEEE Std 802.3, Clause 122.)

**1.4.72l 400GBASE-LR8:** IEEE 802.3 Physical Layer specification for 400 Gb/s using 400GBASE-R encoding and 4-level pulse amplitude modulation over eight WDM lanes on single-mode fiber, with reach up to at least 10 km. (See IEEE Std 802.3, Clause 122.)

**1.4.72m 400GBASE-R:** An IEEE 802.3 family of Physical Layer devices using the physical coding sublayer defined in Clause 119 for 400 Gb/s operation. (See IEEE Std 802.3, Clause 119.)

**1.4.72n 400GBASE-SR16:** IEEE 802.3 Physical Layer specification for 400 Gb/s using 400GBASE-R encoding over sixteen lanes of multimode fiber, with reach up to at least 100 m. (See IEEE Std 802.3, Clause 123.)

**1.4.72o 400 Gb/s Attachment Unit Interface (400GAUI-n):** A physical instantiation of the PMA service interface to extend the connection between 400 Gb/s capable PMAs over n lanes, used for chip-to-chip or chip-to-module interconnections. Two widths of 400GAUI-n are defined: a sixteen-lane version (400GAUI-16), and an eight-lane version (400GAUI-8). (See IEEE Std 802.3, Annex 120B and Annex 120C for 400GAUI-16, or Annex 120D and Annex 120E for 400GAUI-8.)

**1.4.72p 400 Gb/s Media Independent Interface (400GMII):** The interface between the Reconciliation Sublayer (RS) and the Physical Coding Sublayer (PCS) for 400 Gb/s operation. (See IEEE Std 802.3, Clause 117.)

**1.4.72q 400GMII Extender:** The 400 Gb/s Media Independent Interface Extender extends the reach of the 400GMII and consists of two 400GXS sublayers with a 400GAUI-n between them. (See IEEE Std 802.3, Clause 118.)

**1.4.72r 400GXS:** The 400 Gb/s Extender Sublayer (400GXS) is part of the 400GMII Extender. In functionality, it is almost identical to the 400GBASE-R PCS Sublayer defined in Clause 119. Two types of 400GXS are defined: the DTE 400GXS adjacent to the RS sublayer and the PHY 400GXS adjacent to the PHY. (See IEEE Std 802.3, Clause 118.)

*Change 1.4.107 (as modified by IEEE Std 802.3by-2016) as follows:*

**1.4.107 BASE-R:** An IEEE 802.3 family of Physical Layer devices using the 64B/66B encoding defined in Clause 49, Clause 82, ~~or~~ Clause 107, or Clause 119. (See IEEE Std 802.3, Clause 49, Clause 82, ~~or~~ Clause 107, or Clause 119.)

*Change 1.4.325 as follows:*

**1.4.325 PCS lane (PCSL):** In 40GBASE-R, ~~and~~ 100GBASE-R, 200GBASE-R, and 400GBASE-R, the PCS distributes encoded data to multiple logical lanes, these logical lanes are called PCS lanes. One or more PCS lanes can be multiplexed and carried on a physical lane together at the PMA service interface. (See IEEE Std 802.3, Clause 83 and Clause 120.)

## 1.5 Abbreviations

*Insert the following new abbreviations into the list, in alphanumeric order:*

|           |                                                 |
|-----------|-------------------------------------------------|
| 200GAUI-n | 200 Gb/s Attachment Unit Interface over n lanes |
| 200GMII   | 200 Gb/s Media Independent Interface            |
| 200GXS    | 200GMII Extender Sublayer                       |
| 400GAUI-n | 400 Gb/s Attachment Unit Interface over n lanes |
| 400GMII   | 400 Gb/s Media Independent Interface            |
| 400GXS    | 400GMII Extender Sublayer                       |
| SER       | symbol error ratio                              |

## 4. Media Access Control

### 4.4 Specific implementations

#### 4.4.2 MAC parameters

*Change Table 4-2 (as modified by IEEE Std 802.3by-2016 and IEEE Std 802.3bz-2016) as follows:*

**Table 4–2—MAC parameters**

| Parameters                  | MAC data rate                |                      |                                                                                               |                      |
|-----------------------------|------------------------------|----------------------|-----------------------------------------------------------------------------------------------|----------------------|
|                             | Up to and including 100 Mb/s | 1 Gb/s               | 2.5 Gb/s, 5 Gb/s, 25 Gb/s, 40 Gb/s, <del>and 100 Gb/s,</del><br><u>200 Gb/s, and 400 Gb/s</u> | 10 Gb/s              |
| slotTime                    | 512 bit times                | 4096 bit times       | not applicable                                                                                | not applicable       |
| interPacketGap <sup>a</sup> | 96 bits                      | 96 bits              | 96 bits                                                                                       | 96 bits              |
| attemptLimit                | 16                           | 16                   | not applicable                                                                                | not applicable       |
| backoffLimit                | 10                           | 10                   | not applicable                                                                                | not applicable       |
| jamSize                     | 32 bits                      | 32 bits              | not applicable                                                                                | not applicable       |
| maxBasicFrameSize           | 1518 octets                  | 1518 octets          | 1518 octets                                                                                   | 1518 octets          |
| maxEnvelopeFrameSize        | 2000 octets                  | 2000 octets          | 2000 octets                                                                                   | 2000 octets          |
| minFrameSize                | 512 bits (64 octets)         | 512 bits (64 octets) | 512 bits (64 octets)                                                                          | 512 bits (64 octets) |
| burstLimit                  | not applicable               | 65 536 bits          | not applicable                                                                                | not applicable       |
| ipgStretchRatio             | not applicable               | not applicable       | not applicable                                                                                | 104 bits             |

<sup>a</sup> References to interFrameGap or interFrameSpacing in other clauses (e.g., 13, 35, and 42) shall be interpreted as interPacketGap.

*Change Note 7 below Table 4-2 as follows:*

NOTE 7—For 40 Gb/s, ~~and 100 Gb/s, 200 Gb/s, and 400 Gb/s~~ operation, the received interpacket gap (the spacing between two packets, from the last bit of the FCS field of the first packet to the first bit of the Preamble of the second packet) can have a minimum value of 8 BT (bit times), as measured at the XLGMII, ~~or CGMII, 200GMII, or 400GMII~~ receive signals at the DTE due to clock tolerance and lane alignment requirements.

## 30. Management

### 30.2 Managed objects

#### 30.2.5 Capabilities

*Insert two new rows between the rows for `aRSFECIndicationEnable` and `aSNOpMarginChnIA` in Table 30-1e (as modified by IEEE Std 802.3bq-2016) as follows (unchanged rows not shown):*

**Table 30-1e—Capabilities**

|                          |           |         | DTE                                                 | Repeater | MAU |   |
|--------------------------|-----------|---------|-----------------------------------------------------|----------|-----|---|
|                          |           |         | Basic Package (mandatory)                           |          |     |   |
|                          |           |         | Mandatory Package (mandatory)                       |          |     |   |
|                          |           |         | Recommended Package (optional)                      |          |     |   |
|                          |           |         | Optional Package (optional)                         |          |     |   |
|                          |           |         | Array Package (optional)                            |          |     |   |
|                          |           |         | Excessive Deferral Package (optional)               |          |     |   |
|                          |           |         | Multiple PHY Package (optional)                     |          |     |   |
|                          |           |         | PHY Error Monitor Capability (optional)             |          |     |   |
|                          |           |         | Basic Control Capability (mandatory)                |          |     |   |
|                          |           |         | Performance Monitor Capability (optional)           |          |     |   |
|                          |           |         | Address Tracking Capability (optional)              |          |     |   |
|                          |           |         | 100/1000 Mb/s Monitor Capability (optional)         |          |     |   |
|                          |           |         | 1000 Mb/s Burst Monitor Capability (optional)       |          |     |   |
|                          |           |         | Basic Package (mandatory)                           |          |     |   |
|                          |           |         | MAU Control Package (optional)                      |          |     |   |
|                          |           |         | Media Loss Tracking Package (conditional)           |          |     |   |
|                          |           |         | Broadband DTE MAU Package (conditional)             |          |     |   |
|                          |           |         | MLT Capability (conditional)                        |          |     |   |
|                          |           |         | PHY Error Monitor Capability (optional)             |          |     |   |
|                          |           |         | MultiGBASE-T Operating Margin package (conditional) |          |     |   |
|                          |           |         | Forward Error Correction Package (conditional)      |          |     |   |
|                          |           |         | Energy-Efficient Ethernet (optional)                |          |     |   |
|                          |           |         | Auto-Negotiation Package (mandatory)                |          |     |   |
| ...                      |           |         |                                                     |          |     |   |
| aPCSFECIndicationAbility | ATTRIBUTE | GET     |                                                     |          |     | X |
| aPCSFECIndicationEnable  | ATTRIBUTE | GET-SET |                                                     |          |     | X |
| ...                      |           |         |                                                     |          |     |   |

### 30.3 Layer management for DTEs

#### 30.3.2 PHY device managed object class

##### 30.3.2.1 PHY device attributes

##### 30.3.2.1.2 aPhyType

*Insert 200GBASE-R and 400GBASE-R PHY types at the end of “APPROPRIATE SYNTAX” section of 30.3.2.1.2 as follows:*

APPROPRIATE SYNTAX:

|            |                                            |
|------------|--------------------------------------------|
| ...        |                                            |
| 200GBASE-R | Clause 119 200 Gb/s multi-PCS lane 64B/66B |
| 400GBASE-R | Clause 119 400 Gb/s multi-PCS lane 64B/66B |

### 30.3.2.1.3 aPhyTypeList

*Insert 200GBASE-R and 400GBASE-R PHY types at the end of “APPROPRIATE SYNTAX” section of 30.3.2.1.3 as follows:*

APPROPRIATE SYNTAX:

|            |                                            |
|------------|--------------------------------------------|
| ...        |                                            |
| 200GBASE-R | Clause 119 200 Gb/s multi-PCS lane 64B/66B |
| 400GBASE-R | Clause 119 400 Gb/s multi-PCS lane 64B/66B |

### 30.3.2.1.5 aSymbolErrorDuringCarrier

*Change the fourth paragraph of the “BEHAVIOUR DEFINED AS” section of 30.3.2.1.5 (as modified by IEEE Std 802.3by-2016) as follows:*

BEHAVIOUR DEFINED AS:

For operation at 10 Gb/s, 25 Gb/s, 40 Gb/s, ~~and 100 Gb/s~~, 200 Gb/s, and 400 Gb/s, it is a count of the number of times the receiving media is non-idle (the time between the Start of Packet Delimiter and the End of Packet Delimiter as defined by 46.2.5 and 81.2.5) for a period of time equal to or greater than minFrameSize, and during which there was at least one occurrence of an event that causes the PHY to indicate “Receive Error” on the media independent interface (see Table 46-4 and Table 81-3).

## 30.5 Layer management for medium attachment units (MAUs)

### 30.5.1 MAU managed object class

#### 30.5.1.1 MAU attributes

##### 30.5.1.1.2 aMAUType

*Insert new MAU types immediately above 802.9a in “APPROPRIATE SYNTAX” section of 30.5.1.1.2 as follows:*

APPROPRIATE SYNTAX:

|               |                                                                                                                     |
|---------------|---------------------------------------------------------------------------------------------------------------------|
| ...           |                                                                                                                     |
| 200GBASE-R    | Multi-lane PCS as specified in Clause 119 over undefined PMA/PMD                                                    |
| 200GBASE-DR4  | 200GBASE-R PCS/PMA over 4-lane single-mode fiber PMD as specified in Clause 121                                     |
| 200GBASE-FR4  | 200GBASE-R PCS/PMA over 4 WDM lane single-mode fiber PMD with reach up to at least 2 km as specified in Clause 122  |
| 200GBASE-LR4  | 200GBASE-R PCS/PMA over 4 WDM lane single-mode fiber PMD with reach up to at least 10 km as specified in Clause 122 |
| 400GBASE-R    | Multi-lane PCS as specified in Clause 119 over undefined PMA/PMD                                                    |
| 400GBASE-SR16 | 400GBASE-R PCS/PMA over 16-lane multimode fiber PMD as specified in Clause 123                                      |
| 400GBASE-DR4  | 400GBASE-R PCS/PMA over 4-lane single-mode fiber PMD as specified in Clause 124                                     |
| 400GBASE-FR8  | 400GBASE-R PCS/PMA over 8 WDM lane single-mode fiber PMD with reach up to at least 2 km as specified in Clause 122  |
| 400GBASE-LR8  | 400GBASE-R PCS/PMA over 8 WDM lane single-mode fiber PMD with reach up to at least 10 km as specified in Clause 122 |
| ...           |                                                                                                                     |

***Change the last paragraph of the “BEHAVIOUR DEFINED AS” section of 30.5.1.1.2 (as modified by IEEE Std 802.3by-2016) as follows:***

The enumerations 1000BASE-X, 1000BASE-XHD, 1000BASE-XFD, 10GBASE-X, 10GBASE-R, 10GBASE-W, 25GBASE-R, 40GBASE-R, ~~and 100GBASE-R, 200GBASE-R, and 400GBASE-R~~ shall only be returned if the underlying PMD type is unknown.;

#### **30.5.1.1.4 aMediaAvailable**

***Change the sixth paragraph of the “BEHAVIOUR DEFINED AS” section of 30.5.1.1.4 (as modified by IEEE Std 802.3bq-2016) as follows:***

For 40 Gb/s, ~~and 100 Gb/s, 200 Gb/s, and 400 Gb/s~~, the enumerations map to value of the link\_fault variable (see 81.3.4) within the Link Fault Signaling state diagram (see 81.3.4.1 and Figure 46–11) as follows: the values OK and Link Interruption map to the enumeration “available”, the value Local Fault maps to the enumeration “not available” and the value Remote Fault maps to the enumeration “remote fault.”

#### **30.5.1.1.12 aLaneMapping**

***Change 30.5.1.1.12 as follows:***

ATTRIBUTE

APPROPRIATE SYNTAX:

A SEQUENCE of INTEGERS.

BEHAVIOUR DEFINED AS:

For 40/100/~~200/400~~GBASE-R PHYs and 100GBASE-P PHYs, an array of PCS lane identifiers. The indices of this array (0 to n – 1) denote the service interface lane number where n is the number of PCS lanes in use. Each element of this array contains the PCS lane number for the PCS lane that has been detected in the corresponding service interface lane.

If a Clause 45 MDIO Interface to the PCS is present, then this attribute will map to the Lane mapping registers (see 45.2.3.46 and 45.2.3.47).;

#### **30.5.1.1.15 aFECAbility**

***Change 30.5.1.1.15 (as modified by IEEE Std 802.3by-2016) as follows:***

ATTRIBUTE

APPROPRIATE SYNTAX:

An ENUMERATED VALUE that meets the requirement of the description below

|               |                                        |
|---------------|----------------------------------------|
| unknown       | initializing, true state not yet known |
| supported     | FEC supported                          |
| not supported | FEC not supported                      |

BEHAVIOUR DEFINED AS:

A read-only value that indicates if the PHY supports ~~a FEC sublayer for~~ forward error correction (see 65.2, Clause 74, Clause 91, ~~and Clause 108, and Clause 119~~).

If a Clause 45 MDIO Interface is present ~~and support for FEC is optional~~, then this attribute maps to the FEC capability register (see 45.2.8.2 or 45.2.1.92).;

### 30.5.1.1.17 aFECCorrectedBlocks

*Change 30.5.1.1.17 (as modified by IEEE Std 802.3by-2016) as follows:*

ATTRIBUTE

APPROPRIATE SYNTAX:

A SEQUENCE of generalized nonresettable counters. Each counter has a maximum increment rate of 1 200 000 counts per second for 1000 Mb/s implementations, 5 000 000 counts per second for 10 Gb/s, 25 Gb/s, and 40 Gb/s implementations, ~~and 2 500 000 counts per second for 100 Gb/s implementations, 40 000 000 counts per second for 200 Gb/s implementations, and 80 000 000 counts per second for 400 Gb/s implementations.~~

BEHAVIOUR DEFINED AS:

For 1000BASE-PX, 10/25/40/100/200/400GBASE-R, 100GBASE-P, 10GBASE-PR, or 10/1GBASE-PRX PHYs, an array of corrected FEC block counters. The counters do not increment for other PHY types. The indices of this array (0 to N – 1) denote the FEC sublayer instance number where N is the number of FEC sublayer instances in use. The number of FEC sublayer instances in use is set to one for PHYs that do not use PCS lanes or use a single FEC instance for ~~all multiple FEC lanes.~~ Each element of this array contains a count of corrected FEC blocks for that FEC sublayer instance.

Increment the counter by one for each received block that is corrected by the FEC function in the PHY for the corresponding lane or FEC sublayer instance.

If a Clause 45 MDIO Interface is present, then this attribute maps to the FEC corrected blocks counter(s) (see 45.2.8.5 and 45.2.1.94 for 10GBASE-R, 45.2.3.39 for 10GBASE-PR and 10/1GBASE-PRX, 45.2.1.116 for BASE-R, ~~and 45.2.1.103 for RS-FEC, and 45.2.3.471 for PCS FEC).~~;

### 30.5.1.1.18 aFECUncorrectableBlocks

*Change 30.5.1.1.18 (as modified by IEEE Std 802.3by-2016) as follows:*

ATTRIBUTE

APPROPRIATE SYNTAX:

A SEQUENCE of generalized nonresettable counters. Each counter has a maximum increment rate of 1 200 000 counts per second for 1000 Mb/s implementations, and 5 000 000 counts per second for 10 Gb/s, 25 Gb/s, and 40 Gb/s implementations, ~~and 2 500 000 counts per second for 100 Gb/s implementations, 40 000 000 counts per second for 200 Gb/s implementations, and 80 000 000 counts per second for 400 Gb/s implementations.~~

BEHAVIOUR DEFINED AS:

For 1000BASE-PX, 10/25/40/100/200/400GBASE-R, 100GBASE-P, 10GBASE-PR, or 10/1GBASE-PRX PHYs, an array of uncorrectable FEC block counters. The counters do not increment for other PHY types. The indices of this array (0 to N – 1) denote the FEC sublayer instance number where N is the number of FEC sublayer instances in use. The number of FEC sublayer instances in use is set to one for PHYs that do not use PCS lanes or use a single FEC instance for ~~all multiple FEC lanes.~~ Each element of this array contains a count of uncorrectable ~~corrected~~ FEC blocks for that FEC sublayer instance.

Increment the counter by one for each FEC block that is determined to be uncorrectable by the FEC function in the PHY for the corresponding lane or FEC sublayer instance.

If a Clause 45 MDIO Interface is present, then this attribute maps to the FEC uncorrectable blocks counter(s) (see 45.2.8.6 and 45.2.1.95 for 10GBASE-R, 45.2.3.40 for 10GBASE-PR and 10/1GBASE-PRX, 45.2.1.117 for BASE-R, and ~~45.2.1.104~~ for RS-FEC, and 45.2.3.47m for PCS FEC).;

*Insert 30.5.1.1.32 and 30.5.1.1.33 after 30.5.1.1.31 as follows:*

#### **30.5.1.1.32 aPCSFECIndicationAbility**

ATTRIBUTE

APPROPRIATE SYNTAX:

An ENUMERATED VALUE that meets the requirement of the following description:

|               |                                                       |
|---------------|-------------------------------------------------------|
| unknown       | initializing, true state not yet known                |
| supported     | PCS FEC error indication bypass ability supported     |
| not supported | PCS FEC error indication bypass ability not supported |

BEHAVIOUR DEFINED AS:

A read-only value that indicates if the PHY supports an optional PCS FEC error indication bypass ability (see 119.2.5.3).

If a Clause 45 MDIO Interface is present, then this attribute maps to the PCS FEC status register (see 45.2.3.47k).;

#### **30.5.1.1.33 aPCSFECIndicationEnable**

ATTRIBUTE

APPROPRIATE SYNTAX:

An ENUMERATED VALUE that meets the requirement of the following description:

|          |                                          |
|----------|------------------------------------------|
| unknown  | initializing, true state not yet known   |
| disabled | PCS FEC error indication bypass disabled |
| enabled  | PCS FEC error indication bypass enabled  |

BEHAVIOUR DEFINED AS:

A read-write value that indicates the mode of operation of the PCS FEC error indication bypass function (see 119.2.5.3).

A GET operation returns the current mode of operation of the PCS FEC. A SET operation changes the mode of operation of the PCS FEC to the indicated value.

If a Clause 45 MDIO Interface is present, then this attribute maps to the RS-FEC control register (see 45.2.3.47j).;

## 45. Management Data Input/Output (MDIO) Interface

### 45.2 MDIO Interface Registers

#### 45.2.1 PMA/PMD registers

*Change the first sentence of 45.2.1 (as modified by IEEE Std 802.3by-2016) as follows:*

For devices operating at 25 Gb/s or higher speeds, the PMA may be instantiated as multiple sublayers (see [83.1.4](#), ~~and 109.1.4~~, and [120.1.4](#) for how MMD addresses are allocated to multiple PMA sublayers for the respective speeds).

*Change the reserved row for 1.23 through 1.29 in Table 45-3 (as modified by IEEE Std 802.3bv-2017) as follows (unchanged rows not shown):*

**Table 45-3—PMA/PMD registers**

| Register address                            | Register name                                       | Subclause                  |
|---------------------------------------------|-----------------------------------------------------|----------------------------|
| ...                                         |                                                     |                            |
| <a href="#">1.23</a>                        | <a href="#">200G PMA/PMD extended ability</a>       | <a href="#">45.2.1.14e</a> |
| <a href="#">1.24</a>                        | <a href="#">400G PMA/PMD extended ability</a>       | <a href="#">45.2.1.14f</a> |
| <a href="#">1.25</a> , <a href="#">1.26</a> | <a href="#">Reserved</a>                            |                            |
| <a href="#">1.27</a>                        | <a href="#">PMD transmit disable extension</a>      | <a href="#">45.2.1.14g</a> |
| <a href="#">1.28</a>                        | <a href="#">PMD receive signal detect extension</a> | <a href="#">45.2.1.14h</a> |
| <del>1.23 through 1.29</del>                | Reserved                                            |                            |
| ...                                         |                                                     |                            |

*Change the reserved row for 1.340 through 1.699 in Table 45-3 as follows (unchanged rows not shown):*

**Table 45-3—PMA/PMD registers**

| Register address                   | Register name                                                                                                    | Subclause                                  |
|------------------------------------|------------------------------------------------------------------------------------------------------------------|--------------------------------------------|
| ...                                |                                                                                                                  |                                            |
| 1.340 through 1.399 <del>699</del> | Reserved                                                                                                         |                                            |
| <u>1.400 through 1.407</u>         | <u>200GAUI-8 and 400GAUI-16 chip-to-module recommended CTLE, lane 0 through lane 7</u>                           | <u>45.2.1.116a</u> ,<br><u>45.2.1.116b</u> |
| <u>1.408 through 1.415</u>         | <u>400GAUI-16 chip-to-module recommended CTLE, lane 8 through lane 15</u>                                        | <u>45.2.1.116c</u>                         |
| <u>1.416 through 1.499</u>         | Reserved                                                                                                         |                                            |
| <u>1.500 through 1.515</u>         | <u>200GAUI-n and 400GAUI-n chip-to-chip transmitter equalization, receive direction, lane 0 through lane 15</u>  | <u>45.2.1.116d</u> ,<br><u>45.2.1.116e</u> |
| <u>1.516 through 1.531</u>         | <u>200GAUI-n and 400GAUI-n chip-to-chip transmitter equalization, transmit direction, lane 0 through lane 15</u> | <u>45.2.1.116f</u> ,<br><u>45.2.1.116g</u> |
| <u>1.532 through 1.699</u>         | Reserved                                                                                                         |                                            |
| ...                                |                                                                                                                  |                                            |

*Change the reserved row for 1.1511 through 1.1599 in Table 45-3 as follows (unchanged rows not shown):*

**Table 45-3—PMA/PMD registers**

| Register address                 | Register name                  | Subclause          |
|----------------------------------|--------------------------------|--------------------|
| ...                              |                                |                    |
| <del>1.1511 through 1.1599</del> | Reserved                       |                    |
| <u>1.1512</u>                    | <u>PRBS13Q testing control</u> | <u>45.2.1.125a</u> |
| <u>1.1513 through 1.1599</u>     | Reserved                       |                    |
| ...                              |                                |                    |

Change the rows for 1.1600 through 1.1799 in Table 45-3 as follows (unchanged rows not shown):

**Table 45-3—PMA/PMD registers**

| Register address                    | Register name                                              | Subclause  |
|-------------------------------------|------------------------------------------------------------|------------|
| ...                                 |                                                            |            |
| 1.1600 through 1.161 <del>509</del> | PRBS Tx error counters, lane 0 through lane <del>159</del> | 45.2.1.126 |
| 1.161 <del>60</del> through 1.1699  | Reserved                                                   |            |
| 1.1700 through 1.171 <del>509</del> | PRBS Rx error counters, lane 0 through lane <del>159</del> | 45.2.1.127 |
| 1.171 <del>60</del> through 1.1799  | Reserved                                                   |            |
| ...                                 |                                                            |            |

#### 45.2.1.1 PMA/PMD control 1 register (Register 1.0)

Change the row for bits 1.0.5:2 in Table 45-4 (as modified by IEEE Std 802.3by-2016 and IEEE Std 802.3bz-2016) as follows (unchanged rows not shown):

**Table 45-4—PMA/PMD control 1 register bit definitions**

| Bit(s)  | Name            | Description                                                                                                                                                                                                                                                                                                           | R/W <sup>a</sup> |
|---------|-----------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------|
| ...     |                 |                                                                                                                                                                                                                                                                                                                       |                  |
| 1.0.5:2 | Speed selection | 5 4 3 2<br><del>1 * * *</del> = Reserved<br>1 1 x x = Reserved<br>1 0 1 x = Reserved<br>1 0 0 1 = 400 Gb/s<br>1 0 0 0 = 200 Gb/s<br>0 1 1 1 = 5 Gb/s<br>0 1 1 0 = 2.5 Gb/s<br>0 1 0 1 = Reserved<br>0 1 0 0 = 25 Gb/s<br>0 0 1 1 = 100 Gb/s<br>0 0 1 0 = 40 Gb/s<br>0 0 0 1 = 10PASS-TS/2BASE-TL<br>0 0 0 0 = 10 Gb/s | R/W              |
| ...     |                 |                                                                                                                                                                                                                                                                                                                       |                  |

<sup>a</sup> R/W = Read/Write, SC = Self-clearing, RO = Read only

**45.2.1.1.3 Speed selection (1.0.13, 1.0.6, 1.0.5:2)**

*Change the last paragraph of 45.2.1.1.3 (as modified by IEEE Std 802.3by-2016 and IEEE Std 802.3bz-2016) as follows:*

When bits 5 through 2 are set to 0010 the use of a 40G PMA/PMD is selected; when set to 0011 the use of a 100G PMA/PMD is selected; when set to 0100 the use of a 25G PMA/PMD is selected; when set to 0110 the use of a 2.5G PMA/PMD is selected; when set to 0111 the use of a 5G PMA/PMD is selected; when set to 1000 the use of a 200G PMA/PMD is selected; when set to 1001 the use of a 400G PMA/PMD is selected. More specific selection is performed using the PMA/PMD control 2 register (Register 1.7) (see 45.2.1.6.3).

**45.2.1.1.4 PMA remote loopback (1.0.1)**

*Change the last two sentences of the second paragraph of 45.2.1.1.4 as follows:*

~~For 40/100 Gb/s operation, the remote loopback functionality is detailed in 83.5.9. For 25/40/100 Gb/s operation, the remote loopback ability bit is specified in register 1.13 the 40G/100G PMA/PMD extended ability register. For 200 Gb/s and 400 Gb/s operation, the remote loopback ability bit is specified in registers 1.23 and 1.24, respectively.~~

**45.2.1.1.5 PMA local loopback (1.0.0)**

*Change the second paragraph of 45.2.1.1.5 as follows:*

The local loopback function is mandatory for the 1000BASE-KX, 10GBASE-KR, 10GBASE-X, 40GBASE-KR4, 40GBASE-CR4, and 100GBASE-CR10 port type and optional for all other port types, except 2BASE-TL, 10PASS-TS, and 10/1GBASE-PRX, which do not support loopback. ~~A device's ability to perform the local loopback function is advertised in the local loopback ability bit of the related speed-dependent status register. A PMA that is unable to perform the local loopback function shall ignore writes to this bit and shall return a value of zero when read. For 10 Gb/s operation, the~~ The local loopback functionality is detailed in the relevant PMA clause ~~48.3.3 and 51.8. For 40/100 Gb/s operation, the local loopback functionality is detailed in 83.5.8.~~ For 10/25/40/100/200/400 Gb/s operation, the local loopback ability bit is specified in the PMA/PMD status 2 register.

**45.2.1.2 PMA/PMD status 1 register (Register 1.1)****45.2.1.2.3 Fault (1.1.7)**

*Change the fourth sentence of 45.2.1.2.3 (as modified by IEEE Std 802.3by-2016) as follows:*

For 10/25/40/100/200/400 Gb/s operation, bit 1.1.7 is set to a one when either of the fault bits (1.8.11, 1.8.10) located in register 1.8 are set to a one.

#### 45.2.1.4 PMA/PMD speed ability (Register 1.4)

*Change the reserved rows of Table 45–6 (as modified by IEEE Std 802.3bz-2016) as follows (unchanged rows not shown):*

**Table 45–6—PMA/PMD speed ability register bit definitions**

| Bit(s) | Name                                                   | Description                                                                                                                         | R/W <sup>a</sup> |
|--------|--------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------|------------------|
| 1.4.15 | <del>Reserved for future speeds-</del><br>400G capable | <del>Value always 0</del><br>1 = PMA/PMD is capable of operating at 400 Gb/s<br>0 = PMA/PMD is not capable of operating at 400 Gb/s | RO               |
| ...    |                                                        |                                                                                                                                     |                  |
| 1.4.12 | <del>Reserved for future speeds-</del><br>200G capable | <del>Value always 0</del><br>1 = PMA/PMD is capable of operating at 200 Gb/s<br>0 = PMA/PMD is not capable of operating at 200 Gb/s | RO               |
| ...    |                                                        |                                                                                                                                     |                  |

<sup>a</sup> RO = Read only

*Insert 45.2.1.4.aaa before 45.2.1.4.aa (as inserted by IEEE Std 802.3bz-2016) as follows:*

##### 45.2.1.4.aaa 400G capable (1.4.15)

When read as a one, bit 1.4.15 indicates that the PMA/PMD is able to operate at a data rate of 400 Gb/s. When read as a zero, bit 1.4.15 indicates that the PMA/PMD is not able to operate at a data rate of 400 Gb/s.

*Insert 45.2.1.4.ac after 45.2.1.4.ab (as inserted by IEEE Std 802.3bz-2016) and before 45.2.1.4.a (as inserted by IEEE Std 802.3by-2016) as follows:*

##### 45.2.1.4.ac 200G capable (1.4.12)

When read as a one, bit 1.4.12 indicates that the PMA/PMD is able to operate at a data rate of 200 Gb/s. When read as a zero, bit 1.4.12 indicates that the PMA/PMD is not able to operate at a data rate of 200 Gb/s.

#### 45.2.1.6 PMA/PMD control 2 register (Register 1.7)

*Change Table 45–7 (as modified by IEEE Std 802.3bw-2015, IEEE Std 802.3by-2016, IEEE Std 802.3bq-2016, IEEE Std 802.3bp-2016, IEEE Std 802.3bn-2016, IEEE Std 802.3bz-2016, and IEEE Std 802.3bv-2017) as follows:*

**Table 45–7—PMA/PMD control 2 register bit definitions**

| Bit(s)    | Name     | Description                 | R/W <sup>a</sup> |
|-----------|----------|-----------------------------|------------------|
| 1.7.15:10 | Reserved | Value always 0              | RO               |
| 1.7.9     | PIASE    | PMA ingress AUI stop enable | R/W              |
| 1.7.8     | PEASE    | PMA egress AUI stop enable  | R/W              |

Table 45–7—PMA/PMD control 2 register bit definitions (*continued*)

| Bit(s)                               | Name                   | Description                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              | R/W <sup>a</sup> |
|--------------------------------------|------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------|
| <del>1.7.7:6</del><br><u>1.7.7</u>   | Reserved               | Value always 0                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           | RO               |
| <del>1.7.5:0</del><br><u>1.7.6:0</u> | PMA/PMD type selection | <u>6 5 4 3 2 1 0</u><br><u>1 1 x x x x = reserved</u><br><u>1 0 1 1 1 1 x = reserved</u><br><u>1 0 1 1 1 0 1 = reserved</u><br><u>1 0 1 1 1 0 0 = 400GBASE-LR8 PMA/PMD</u><br><u>1 0 1 1 0 1 1 = 400GBASE-FR8 PMA/PMD</u><br><u>1 0 1 1 0 1 0 = 400GBASE-DR4 PMA/PMD</u><br><u>1 0 1 1 0 0 1 = 400GBASE-SR16 PMA/PMD</u><br><u>1 0 1 1 0 0 0 = reserved</u><br><u>1 0 1 0 1 1 x = reserved</u><br><u>1 0 1 0 1 0 1 = 200GBASE-LR4 PMA/PMD</u><br><u>1 0 1 0 1 0 0 = 200GBASE-FR4 PMA/PMD</u><br><u>1 0 1 0 0 1 1 = 200GBASE-DR4 PMA/PMD</u><br><u>1 0 1 0 0 1 0 = reserved</u><br><u>1 0 1 0 0 0 x = reserved</u><br><u>1 0 0 x x x x = reserved</u><br><u>0 1 1 1 1 1 x = reserved</u><br><u>0 1 1 1 1 0 1 = BASE-T1 PMA/PMD<sup>b</sup></u><br><u>0 1 1 1 1 0 0 = reserved</u><br><u>0 1 1 1 0 1 1 = reserved</u><br><u>0 1 1 1 0 1 0 = 25GBASE-SR PMA/PMD</u><br><u>0 1 1 1 0 0 1 = 25GBASE-KR or 25GBASE-KR-S PMA/PMD</u><br><u>0 1 1 1 0 0 0 = 25GBASE-CR or 25GBASE-CR-S PMA/PMD</u><br><u>0 1 1 0 1 1 1 = 25GBASE-T PMA</u><br><u>0 1 1 0 1 1 0 = reserved</u><br><u>0 1 1 0 1 0 1 = reserved</u><br><u>0 1 1 0 1 0 0 = BASE-H PMA/PMD<sup>c</sup></u><br><u>0 1 1 0 0 1 1 = 10GPASS-XR-U PMA/PMD</u><br><u>0 1 1 0 0 1 0 = 10GPASS-XR-D PMA/PMD</u><br><u>0 1 1 0 0 0 1 = 5GBASE-T PMA</u><br><u>0 1 1 0 0 0 0 = 2.5GBASE-T PMA</u><br><u>0 1 0 1 1 1 1 = 100GBASE-SR4 PMA/PMD</u><br><u>0 1 0 1 1 1 0 = 100GBASE-CR4 PMA/PMD</u><br><u>0 1 0 1 1 0 1 = 100GBASE-KR4 PMA/PMD</u><br><u>0 1 0 1 1 0 0 = 100GBASE-KP4 PMA/PMD</u><br><u>0 1 0 1 0 1 1 = 100GBASE-ER4 PMA/PMD</u><br><u>0 1 0 1 0 1 0 = 100GBASE-LR4 PMA/PMD</u><br><u>0 1 0 1 0 0 1 = 100GBASE-SR10 PMA/PMD</u><br><u>0 1 0 1 0 0 0 = 100GBASE-CR10 PMA/PMD</u><br><u>0 1 0 0 1 1 1 = reserved</u> | R/W              |