

INTERNATIONAL
STANDARD

ISO/
IEC/IEEE
8802-3

Third edition
2021-02

AMENDMENT 1
2021-12

**Telecommunications and exchange
between information technology
systems — Requirements for local and
metropolitan area networks —**

**Part 3:
Standard for Ethernet**

**AMENDMENT 1: Physical layer
specifications and management
parameters for 2.5 Gb/s and 5 Gb/s
operation over backplane**

*Télécommunications et échange entre systèmes informatiques —
Exigences pour les réseaux locaux et métropolitains —*

Partie 3: Norme pour Ethernet

*AMENDEMENT 1: Spécifications de la couche physique et
paramètres de gestion pour fonctionnement à 2,5 Gb/s et 5 Gb/s sur
fond de panier*



Reference number
ISO/IEC/IEEE 8802-3:2021/Amd.1:2021(E)

Documents
Document Sharing Hub
© IEEE 2019



COPYRIGHT PROTECTED DOCUMENT

© IEEE 2019

All rights reserved. Unless otherwise specified, or required in the context of its implementation, no part of this publication may be reproduced or utilized otherwise in any form or by any means, electronic or mechanical, including photocopying, or posting on the internet or an intranet, without prior written permission. Permission can be requested from IEEE at the address below.

Institute of Electrical and Electronics Engineers, Inc
3 Park Avenue, New York
NY 10016-5997, USA

Email: stds.ipr@ieee.org
Website: www.ieee.org

Published in Switzerland

Foreword

ISO (the International Organization for Standardization) and IEC (the International Electrotechnical Commission) form the specialized system for worldwide standardization. National bodies that are members of ISO or IEC participate in the development of International Standards through technical committees established by the respective organization to deal with particular fields of technical activity. ISO and IEC technical committees collaborate in fields of mutual interest. Other international organizations, governmental and non-governmental, in liaison with ISO and IEC, also take part in the work.

The procedures used to develop this document and those intended for its further maintenance are described in the ISO/IEC Directives, Part 1. In particular, the different approval criteria needed for the different types of ISO/IEC documents should be noted.

IEEE Standards documents are developed within the IEEE Societies and the Standards Coordinating Committees of the IEEE Standards Association (IEEE-SA) Standards Board. The IEEE develops its standards through a consensus development process, approved by the American National Standards Institute, which brings together volunteers representing varied viewpoints and interests to achieve the final product. Volunteers are not necessarily members of the Institute and serve without compensation. While the IEEE administers the process and establishes rules to promote fairness in the consensus development process, the IEEE does not independently evaluate, test, or verify the accuracy of any of the information contained in its standards.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO and IEC shall not be held responsible for identifying any or all such patent rights. Details of any patent rights identified during the development of the document will be in the Introduction and/or on the ISO list of patent declarations received (see www.iso.org/patents) or the IEC list of patent declarations received (see patents.iec.ch).

Any trade name used in this document is information given for the convenience of users and does not constitute an endorsement.

For an explanation of the voluntary nature of standards, the meaning of ISO specific terms and expressions related to conformity assessment, as well as information about ISO's adherence to the World Trade Organization (WTO) principles in the Technical Barriers to Trade (TBT), see www.iso.org/iso/foreword.html. In the IEC, see www.iec.ch/understanding-standards.

ISO/IEC/IEEE 8802-3:2021/Amd.1 was prepared by the LAN/MAN of the IEEE Computer Society (as IEEE Std 802.3cb-2018) and drafted in accordance with its editorial rules. It was adopted, under the “fast-track procedure” defined in the Partner Standards Development Organization cooperation agreement between ISO and IEEE, by Joint Technical Committee ISO/IEC JTC 1, *Information technology*, Subcommittee SC 6, *Telecommunications and information exchange between systems*.

A list of all parts in the ISO/IEC/IEEE 8802 series can be found on the ISO and IEC websites.

Any feedback or questions on this document should be directed to the user's national standards body. A complete listing of these bodies can be found at www.iso.org/members.html and www.iec.ch/national-committees.

IEEE Standard for Ethernet

Amendment 1: Physical Layer Specifications and Management Parameters for 2.5 Gb/s and 5 Gb/s Operation over Backplane

Sponsor

LAN/MAN Standards Committee
of the
IEEE Computer Society

Approved 27 September 2018

IEEE-SA Standards Board

Abstract: Ethernet Media Access Control (MAC) parameters, Physical Layer specifications, and management objects for the serial transfer of Ethernet format frames at 2.5 Gb/s and 5 Gb/s over electrical backplanes are defined in this amendment to IEEE Std 802.3-2018.

Keywords: 2.5 Gigabit Ethernet, 5 Gigabit Ethernet, 2.5GBASE-KX, 2.5GBASE-X, 5GBASE-KR, 5GBASE-R, amendment, AN, Auto-Negotiation, Backplane Ethernet, BASE-R, BASE-X, EEE, Energy Efficient Ethernet, Ethernet, IEEE 802.3™, IEEE 802.3cb™

The Institute of Electrical and Electronics Engineers, Inc.
3 Park Avenue, New York, NY 10016-5997, USA

Copyright © 2019 by The Institute of Electrical and Electronics Engineers, Inc.
All rights reserved. Published 4 January 2019. Printed in the United States of America.

IEEE and 802 are registered trademarks in the U.S. Patent & Trademark Office, owned by The Institute of Electrical and Electronics Engineers, Incorporated.

PDF: ISBN 978-1-5044-5278-6 STD23391
Print: ISBN 978-1-5044-5279-3 STDPD23391

IEEE prohibits discrimination, harassment and bullying.

For more information, visit <http://www.ieee.org/web/aboutus/whatis/policies/p9-26.html>.

No part of this publication may be reproduced in any form, in an electronic retrieval system or otherwise, without the prior written permission of the publisher.

Important Notices and Disclaimers Concerning IEEE Standards Documents

IEEE documents are made available for use subject to important notices and legal disclaimers. These notices and disclaimers, or a reference to this page, appear in all standards and may be found under the heading “Important Notices and Disclaimers Concerning IEEE Standards Documents.” They can also be obtained on request from IEEE or viewed at <http://standards.ieee.org/ipr/disclaimers.html>.

Notice and Disclaimer of Liability Concerning the Use of IEEE Standards Documents

IEEE Standards documents (standards, recommended practices, and guides), both full-use and trial-use, are developed within IEEE Societies and the Standards Coordinating Committees of the IEEE Standards Association (“IEEE-SA”) Standards Board. IEEE (“the Institute”) develops its standards through a consensus development process, approved by the American National Standards Institute (“ANSI”), which brings together volunteers representing varied viewpoints and interests to achieve the final product. IEEE Standards are documents developed through scientific, academic, and industry-based technical working groups. Volunteers in IEEE working groups are not necessarily members of the Institute and participate without compensation from IEEE. While IEEE administers the process and establishes rules to promote fairness in the consensus development process, IEEE does not independently evaluate, test, or verify the accuracy of any of the information or the soundness of any judgments contained in its standards.

IEEE Standards do not guarantee or ensure safety, security, health, or environmental protection, or ensure against interference with or from other devices or networks. Implementers and users of IEEE Standards documents are responsible for determining and complying with all appropriate safety, security, environmental, health, and interference protection practices and all applicable laws and regulations.

IEEE does not warrant or represent the accuracy or content of the material contained in its standards, and expressly disclaims all warranties (express, implied and statutory) not included in this or any other document relating to the standard, including, but not limited to, the warranties of: merchantability; fitness for a particular purpose; non-infringement; and quality, accuracy, effectiveness, currency, or completeness of material. In addition, IEEE disclaims any and all conditions relating to: results; and workmanlike effort. IEEE standards documents are supplied “AS IS” and “WITH ALL FAULTS.”

Use of an IEEE standard is wholly voluntary. The existence of an IEEE standard does not imply that there are no other ways to produce, test, measure, purchase, market, or provide other goods and services related to the scope of the IEEE standard. Furthermore, the viewpoint expressed at the time a standard is approved and issued is subject to change brought about through developments in the state of the art and comments received from users of the standard.

In publishing and making its standards available, IEEE is not suggesting or rendering professional or other services for, or on behalf of, any person or entity nor is IEEE undertaking to perform any duty owed by any other person or entity to another. Any person utilizing any IEEE Standards document, should rely upon his or her own independent judgment in the exercise of reasonable care in any given circumstances or, as appropriate, seek the advice of a competent professional in determining the appropriateness of a given IEEE standard.

IN NO EVENT SHALL IEEE BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO: PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE PUBLICATION, USE OF, OR RELIANCE UPON ANY STANDARD, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE AND REGARDLESS OF WHETHER SUCH DAMAGE WAS FORESEEABLE.

Translations

The IEEE consensus development process involves the review of documents in English only. In the event that an IEEE standard is translated, only the English version published by IEEE should be considered the approved IEEE standard.

Official statements

A statement, written or oral, that is not processed in accordance with the IEEE-SA Standards Board Operations Manual shall not be considered or inferred to be the official position of IEEE or any of its committees and shall not be considered to be, or be relied upon as, a formal position of IEEE. At lectures, symposia, seminars, or educational courses, an individual presenting information on IEEE standards shall make it clear that his or her views should be considered the personal views of that individual rather than the formal position of IEEE.

Comments on standards

Comments for revision of IEEE Standards documents are welcome from any interested party, regardless of membership affiliation with IEEE. However, IEEE does not provide consulting information or advice pertaining to IEEE Standards documents. Suggestions for changes in documents should be in the form of a proposed change of text, together with appropriate supporting comments. Since IEEE standards represent a consensus of concerned interests, it is important that any responses to comments and questions also receive the concurrence of a balance of interests. For this reason, IEEE and the members of its societies and Standards Coordinating Committees are not able to provide an instant response to comments or questions except in those cases where the matter has previously been addressed. For the same reason, IEEE does not respond to interpretation requests. Any person who would like to participate in revisions to an IEEE standard is welcome to join the relevant IEEE working group.

Comments on standards should be submitted to the following address:

Secretary, IEEE-SA Standards Board
445 Hoes Lane
Piscataway, NJ 08854 USA

Laws and regulations

Users of IEEE Standards documents should consult all applicable laws and regulations. Compliance with the provisions of any IEEE Standards document does not imply compliance to any applicable regulatory requirements. Implementers of the standard are responsible for observing or referring to the applicable regulatory requirements. IEEE does not, by the publication of its standards, intend to urge action that is not in compliance with applicable laws, and these documents may not be construed as doing so.

Copyrights

IEEE draft and approved standards are copyrighted by IEEE under U.S. and international copyright laws. They are made available by IEEE and are adopted for a wide variety of both public and private uses. These include both use, by reference, in laws and regulations, and use in private self-regulation, standardization, and the promotion of engineering practices and methods. By making these documents available for use and adoption by public authorities and private users, IEEE does not waive any rights in copyright to the documents.

Photocopies

Subject to payment of the appropriate fee, IEEE will grant users a limited, non-exclusive license to photocopy portions of any individual standard for company or organizational internal use or individual, non-commercial use only. To arrange for payment of licensing fees, please contact Copyright Clearance Center, Customer Service, 222 Rosewood Drive, Danvers, MA 01923 USA; +1 978 750 8400. Permission to photocopy portions of any individual standard for educational classroom use can also be obtained through the Copyright Clearance Center.

Updating of IEEE Standards documents

Users of IEEE Standards documents should be aware that these documents may be superseded at any time by the issuance of new editions or may be amended from time to time through the issuance of amendments, corrigenda, or errata. An official IEEE document at any point in time consists of the current edition of the document together with any amendments, corrigenda, or errata then in effect.

Every IEEE standard is subjected to review at least every ten years. When a document is more than ten years old and has not undergone a revision process, it is reasonable to conclude that its contents, although still of some value, do not wholly reflect the present state of the art. Users are cautioned to check to determine that they have the latest edition of any IEEE standard.

In order to determine whether a given document is the current edition and whether it has been amended through the issuance of amendments, corrigenda, or errata, visit the IEEE-SA Website at <http://ieeexplore.ieee.org> or contact IEEE at the address listed previously. For more information about the IEEE SA or IEEE's standards development process, visit the IEEE-SA Website at <http://standards.ieee.org>.

Errata

Errata, if any, for all IEEE standards can be accessed on the IEEE-SA Website at the following URL: <http://standards.ieee.org/findstds/errata/index.html>. Users are encouraged to check this URL for errata periodically.

Patents

Attention is called to the possibility that implementation of this standard may require use of subject matter covered by patent rights. By publication of this standard, no position is taken by the IEEE with respect to the existence or validity of any patent rights in connection therewith. If a patent holder or patent applicant has filed a statement of assurance via an Accepted Letter of Assurance, then the statement is listed on the IEEE-SA Website at <http://standards.ieee.org/about/sasb/patcom/patents.html>. Letters of Assurance may indicate whether the Submitter is willing or unwilling to grant licenses under patent rights without compensation or under reasonable rates, with reasonable terms and conditions that are demonstrably free of any unfair discrimination to applicants desiring to obtain such licenses.

Essential Patent Claims may exist for which a Letter of Assurance has not been received. The IEEE is not responsible for identifying Essential Patent Claims for which a license may be required, for conducting inquiries into the legal validity or scope of Patents Claims, or determining whether any licensing terms or conditions provided in connection with submission of a Letter of Assurance, if any, or in any licensing agreements are reasonable or non-discriminatory. Users of this standard are expressly advised that determination of the validity of any patent rights, and the risk of infringement of such rights, is entirely their own responsibility. Further information may be obtained from the IEEE Standards Association.

Participants

The following individuals were officers and members of the IEEE 802.3 Working Group at the beginning of the IEEE P802.3cb Working Group ballot.

David J. Law, *IEEE 802.3 Working Group Chair*
Adam Healey, *IEEE 802.3 Working Group Vice-Chair*
Peter Anslow, *IEEE 802.3 Working Group Secretary*
Steven B. Carlson, *IEEE 802.3 Working Group Executive Secretary*
Valerie Maguire, *IEEE 802.3 Working Group Treasurer*

Yong Kim, *IEEE P802.3cb Task Force Chair, Phase 1**
Daniel F. Smith, *IEEE P802.3cb Task Force Chair, Phase 2*
William Lo, *IEEE P802.3cb Task Force Editor-in-Chief, Phase 1*
Daniel F. Smith, *IEEE P802.3cb Task Force Editor-in-Chief, Phase 2*
Jim Hatfield, *IEEE P802.3cb Task Force Editor, Phase 2**

Justin Abbott
David Abramson
Shadi Abughazaleh
Mohammad Ahmed
Eric Baden
Amrik Bains
Thananya Baldwin
Denis Beaudoin
Christian Beia
Michael Bennett
Vipul Bhatt
William Bliss
Brad Booth
Martin Bouda
Ralf-Peter Braun
Theodore Brillhart
Paul Brooks
Alan Brown
Matthew Brown
Chris Bullock
Jairo Bustos Heredia
Adrian Butter
Francesco Caggioni
Anthony Calbone
Clark Carty
Craig Chabot
Geoffrey Chacon Simon
Mandeep Chadha
David Chalupsky
Jacky Chang
Xin Chang
Ahmad Chini
Keng Hua Chuang
Christopher R. Cole
John D'Ambrosia
Yair Darshan
Piers Dawe
Fred Dawson
Wael Diab
Eric DiBiaso

John Dillard
Daniel Dillow
Thuyen Dinh
Curtis Donahue
Dan Dove
Mike Dudek
David Dwelley
Frank Effenberger
Hesham Elbakoury
David Estes
John Ewen
Ramin Farjad
Shahar Feldman
James Fife
Alan Flatman
Matthias Fritsche
Richard Frosch
Andrew Gardner
Claude Gauthier
Ali Ghiasi
Joel Goergen
Volker Goetzfried
Zhipang Gong
Steven Gorshe
Robert Grow
Mark Gustlin
Marek Hajduczenia
Takehiro Hayashi
Yasuo Hidaka
Rita Horner
Bernd Hormmeyer
Victor Hou
Yasuhiro Hyakutake
Hideki Isono
Tom Issenhuth
Kenneth Jackson
Andrew Jimenez
Chad Jones
Peter Jones
Manabu Kagami

Upen Kareti
Keisuke Kawahara
Yasuaki Kawatsu
Michael Kelsen
Scott Kipp
Michael Klempa
Curtis Knittle
Shigeru Kobayashi
Daniel Koehler
Paul Kolesar
Tom Kolze
Glen Kramer
Hans Lackner
Jeffrey Lapak
Mark Laubach
Han Hyub Lee
David Lewis
Jon Lewis
Mike Peng Li
Jane Lim
Dekun Liu
Hai-Feng Liu
Miklos Lukacs
Kent Lusted
Jeffery Maki
David Malicoat
Yonatan Malkiman
Arthur Marris
Takeo Masuda
Erdem Matoglu
Naoki Matsuda
Mick McCarthy
Brett McClellan
Thomas McDermott
John McDonough
Larry McMillan
Richard Mei
Richard Mellitz
Bryan Moffitt
Ardeshir Mohammadian
Paul Mooney

* Not a member of the IEEE 802.3 working group at the beginning of the working group ballot.

Dale Murray	Sam Sambasivan	Pirooz Tooyserkani
Henry Muyshondt	Edward Sayre	Albert Tretter
James Nadolny	Dieter Schicketanz	Stephen Trowbridge
Edward Nakamoto	Fred Schindler	Yoshihiro Tsukamoto
Gary Nicholl	Hossein Sedarat	Ed Ulrichs
Kevin Noll	Naoshi Serizawa	Alexander Umnov
Mark Nowell	Masood Shariff	Sterling A. Vaden
David Ofelt	Ramin Shirani	Stefano Valle
Thomas Palkert	Tom Skaar	Paul Vanderlaan
Hui Pan	Jeff Slavick	Robert Wagner
Sesha Panguluri	Scott Sommers	Dylan Walker
Vasu Parthasarathy	Yoshiaki Sone	Haifei Wang
Petar Pepeljugoski	Tom Souvignier	Roy Wang
Gerald Pepper	Peter Stassar	Tongtong Wang
Ruben Perez De Aranda Alonso	Heath Stewart	Xinyuan Wang
Michael Peters	Robert Stone	Matthias Wendt
Phong Pham	David Stover	Oded Wertheim
Jean Picard	Junqing Sun	Natalie Wienckowski
William Powell	Ken-Ichi Suzuki	Ludwig Winkel
Rick Rabinovich	Steve Swanson	Peter Wu
Adee Ran	Andre Szczepanek	Dayin Xu
Alon Regev	William Szeto	Yu Xu
Duane Remein	Bharat Tailor	Jun Yi
Victor Renteria	Takayuki Tajima	Lennart Yseboodt
Christopher Roth	Satoshi Takahashi	Hayato Yuki
Salvatore Rotolo	Kohichi Tamura	Andrew Zambell
Toshiaki Sakai	Brian Teipen	Yan Zhuang
Jorge Salinger	Geoffrey Thompson	George Zimmerman

The following members of the individual balloting committee voted on this amendment. Balloters may have voted for approval, disapproval, or abstention.

Shadi Abughazaleh	Marco Hernandez	Thomas Palkert
Thomas Alexander	David Hess	Bansi Patel
Peter Anslow	Werner Hoelzl	Arumugam Paventhan
Butch Anton	Rita Horner	Michael Peters
Amrik Bains	C. Huntley	Rick Pimpinella
Ralf-Peter Braun	Noriyuki Ikeuchi	Adee Ran
Nancy Bravin	Atsushi Ito	Alon Regev
Theodore Brillhart	Raj Jain	Maximilian Riegel
Matthew Brown	SangKwon Jeong	Robert Robinson
Demetrio Bucaneg	Piotr Karocki	Benjamin Rolfe
Jairo Bustos Heredia	Stuart Kerry	Daniel F. Smith
William Byrd	Yong Kim	Thomas Starai
Steven B. Carlson	Mark Laubach	Walter Struppler
Juan Carreon	David J. Law	Mitsutoshi Sugawara
Mandeep Chadha	Jon Lewis	Junqing Sun
Keith Chow	Mike Peng Li	Geoffrey Thompson
Keng Hua Chuang	Elvis Maculuba	Michael Thompson
Charles Cook	Valerie Maguire	Steven Tilden
Rodney Cummings	Jeffery Maki	David Tremblay
Sourav Dutta	Arthur Marris	Mark-Rene Uchida
Michael Fischer	Mick McCarthy	Alexander Umnov
Matthias Fritsche	Brett McClellan	Paul Vanderlaan
Yukihiro Fujimoto	Thomas McDermott	George Vlantis
Zhigang Gong	Larry McMillan	Khurram Waheed
James Graba	Richard Mellitz	Lisa Ward
Eric W. Gray	Charles Moorwood	Karl Weber
Randall Groves	Michael Newman	Andreas Wolf
Robert Grow	Nick S. A. Nikjoo	Peter Wu
Michael Gundlach	Paul Nikolich	Jun Xu
Marek Hajduczenia	Satoshi Obara	Oren Yuen
Adam Healey		Zhen Zhou

When the IEEE-SA Standards Board approved this amendment on 27 September 2018, it had the following membership:

Jean-Philippe Faure, *Chair*
Gary Hoffman, *Vice Chair*
John D. Kulick, *Past Chair*
Konstantinos Karachalios, *Secretary*

Ted Burse
Guido R. Hiertz
Christel Hunter
Joseph L. Koepfinger*
Thomas Koshy
Hung Ling
Dong Liu

Xiaohui Liu
Kevin Lu
Daleep Mohla
Andrew Myles
Paul Nikolich
Ronald C. Petersen
Annette D. Reilly

Robby Robson
Dorothy Stanley
Mehmet Ulema
Phil Wennblom
Philip Winston
Howard Wolfman
Jingyi Zhou

*Member Emeritus

Introduction

This introduction is not part of IEEE Std 802.3cb-2018, IEEE Standard for Ethernet—Amendment 1: Physical Layer Specifications and Management Parameters for 2.5 Gb/s and 5 Gb/s Operation over Backplane.

IEEE Std 802.3™ was first published in 1985. Since the initial publication, many projects have added functionality or provided maintenance updates to the specifications and text included in the standard. Each IEEE 802.3 project/amendment is identified with a suffix (e.g., IEEE Std 802.3ba™-2010).

The half duplex Media Access Control (MAC) protocol specified in IEEE Std 802.3-1985 is Carrier Sense Multiple Access with Collision Detection (CSMA/CD). This MAC protocol was key to the experimental Ethernet developed at Xerox Palo Alto Research Center, which had a 2.94 Mb/s data rate. Ethernet at 10 Mb/s was jointly released as a public specification by Digital Equipment Corporation (DEC), Intel and Xerox in 1980. Ethernet at 10 Mb/s was approved as an IEEE standard by the IEEE Standards Board in 1983 and subsequently published in 1985 as IEEE Std 802.3-1985. Since 1985, new media options, new speeds of operation, and new capabilities have been added to IEEE Std 802.3. A full duplex MAC protocol was added in 1997.

Some of the major additions to IEEE Std 802.3 are identified in the marketplace with their project number. This is most common for projects adding higher speeds of operation or new protocols. For example, IEEE Std 802.3u™ added 100 Mb/s operation (also called Fast Ethernet), IEEE Std 802.3z added 1000 Mb/s operation (also called Gigabit Ethernet), IEEE Std 802.3ae added 10 Gb/s operation (also called 10 Gigabit Ethernet), IEEE Std 802.3ah™ specified access network Ethernet (also called Ethernet in the First Mile) and IEEE Std 802.3ba added 40 Gb/s operation (also called 40 Gigabit Ethernet) and 100 Gb/s operation (also called 100 Gigabit Ethernet). These major additions are all now included in and are superseded by IEEE Std 802.3-2018 and are not maintained as separate documents.

At the date of publication for IEEE Std 802.3cb-2018, IEEE Std 802.3 was composed of the following documents:

IEEE Std 802.3-2018

Section One—Includes Clause 1 through Clause 20 and Annex A through Annex H and Annex 4A. Section One includes the specifications for 10 Mb/s operation and the MAC, frame formats and service interfaces used for all speeds of operation.

Section Two—Includes Clause 21 through Clause 33 and Annex 22A through Annex 33E. Section Two includes management attributes for multiple protocols and speed of operation as well as specifications for providing power over twisted pair cabling for multiple operational speeds. It also includes general information on 100 Mb/s operation as well as most of the 100 Mb/s Physical Layer specifications.

Section Three—Includes Clause 34 through Clause 43 and Annex 36A through Annex 43C. Section Three includes general information on 1000 Mb/s operation as well as most of the 1000 Mb/s Physical Layer specifications.

Section Four—Includes Clause 44 through Clause 55 and Annex 44A through Annex 55B. Section Four includes general information on 10 Gb/s operation as well as most of the 10 Gb/s Physical Layer specifications.

Section Five—Includes Clause 56 through Clause 77 and Annex 57A through Annex 76A. Clause 56 through Clause 67 and Clause 75 through Clause 77, as well as associated annexes, specify subscriber access and other Physical Layers and sublayers for operation from 512 kb/s to 10 Gb/s, and defines

services and protocol elements that enable the exchange of IEEE Std 802.3 format frames between stations in a subscriber access network. Clause 68 specifies a 10 Gb/s Physical Layer specification. Clause 69 through Clause 74 and associated annexes specify Ethernet operation over electrical backplanes at speeds of 1000 Mb/s and 10 Gb/s.

Section Six—Includes Clause 78 through Clause 95 and Annex 83A through Annex 93C. Clause 78 specifies Energy-Efficient Ethernet. Clause 79 specifies IEEE 802.3 Organizationally Specific Link Layer Discovery Protocol (LLDP) type, length, and value (TLV) information elements. Clause 80 through Clause 95 and associated annexes includes general information on 40 Gb/s and 100 Gb/s operation as well the 40 Gb/s and 100 Gb/s Physical Layer specifications. Clause 90 specifies Ethernet support for time synchronization protocols.

Section Seven—Includes Clause 96 through Clause 115 and Annex 97A through Annex 115A. Clause 96 through Clause 98, Clause 104, and associated annexes, specify Physical Layers and optional features for 100 Mb/s and 1000 Mb/s operation over a single twisted pair. Clause 100 through Clause 103, as well as associated annexes, specify Physical Layers for the operation of the EPON protocol over coaxial distribution networks. Clause 105 through Clause 114 and associated annexes include general information on 25 Gb/s operation as well as 25 Gb/s Physical Layer specifications. Clause 99 specifies a MAC merge sublayer for the interspersing of express traffic. Clause 115 and its associated annex specify a Physical Layer for 1000 Mb/s operation over plastic optical fiber.

Section Eight—Includes Clause 116 through Clause 126 and Annex 119A through Annex 120E. Clause 116 through Clause 124 and associated annexes include general information on 200 Gb/s and 400 Gb/s operation as well the 200 Gb/s and 400 Gb/s Physical Layer specifications. Clause 125 and Clause 126 include general information on 2.5 Gb/s and 5 Gb/s operation as well as 2.5 Gb/s and 5 Gb/s Physical Layer specifications.

IEEE Std 802.3cb-2018

Amendment 1—This amendment includes changes to IEEE Std 802.3-2018 and its amendments, and adds Clause 127 through Clause 130, Annex 127A, Annex 128A, Annex 128B, and Annex 130A. This amendment adds new Physical Layers for operation at 2.5 Gb/s and 5 Gb/s over electrical backplanes.

Two companion documents exist, IEEE Std 802.3.1 and IEEE Std 802.3.2. IEEE Std 802.3.1 describes Ethernet management information base (MIB) modules for use with the Simple Network Management Protocol (SNMP). IEEE Std 802.3.2 describes YANG data models for Ethernet. IEEE Std 802.3.1 and IEEE Std 802.3.2 are updated to add management capability for enhancements to IEEE Std 802.3 after approval of those enhancements.

IEEE Std 802.3 will continue to evolve. New Ethernet capabilities are anticipated to be added within the next few years as amendments to this standard.

Contents

1. Introduction.....	23
1.3 Normative references	23
1.4 Definitions	23
1.5 Abbreviations.....	24
30. Management.....	25
30.3 Layer management for DTEs.....	25
30.3.2 PHY device managed object class	25
30.3.2.1 PHY device attributes	25
30.3.2.1.2 aPhyType	25
30.3.2.1.3 aPhyTypeList	25
30.3.2.1.5 aSymbolErrorDuringCarrier	25
30.5 Layer management for medium attachment units (MAUs)	26
30.5.1 MAU managed object class	26
30.5.1.1 MAU attributes	26
30.5.1.1.2 aMAUType	26
30.6 Management for link Auto-Negotiation	26
30.6.1 Auto-Negotiation managed object class	26
30.6.1.1 Auto-Negotiation attributes	26
30.6.1.1.5 aAutoNegLocalTechnologyAbility	26
45. Management Data Input/Output (MDIO) Interface.....	27
45.2 MDIO Interface Registers.....	27
45.2.1 PMA/PMD registers	27
45.2.1.1 PMA/PMD control 1 register (Register 1.0).....	27
45.2.1.1.5 PMA local loopback (1.0.0).....	27
45.2.1.6 PMA/PMD control 2 register (Register 1.7).....	27
45.2.1.7 PMA/PMD status 2 register (Register 1.8).....	28
45.2.1.7.4 Transmit fault (1.8.11).....	28
45.2.1.7.5 Receive fault (1.8.10).....	28
45.2.1.8 PMD transmit disable register (Register 1.9)	28
45.2.1.18 2.5G/5G PMA/PMD extended ability register (Register 1.21)	29
45.2.1.18.a 5GBASE-KR ability (1.21.3).....	29
45.2.1.18.b 2.5GBASE-KX ability (1.21.2)	29
45.2.1.89 BASE-R PMD control register (Register 1.150)	29
45.2.1.89.3 Transmitter equalizer disable (1.150.2)	30
45.2.1.97 1000BASE-KX/2.5GBASE-KX control register (Register 1.160)	30
45.2.1.97.1 PMD transmit disable (1.160.0).....	30
45.2.1.98 1000BASE-KX/2.5GBASE-KX status register (Register 1.161).....	30
45.2.1.98.6 1000BASE-KX/2.5GBASE-KX signal detect (1.161.0).....	31
45.2.1.140 Test-pattern ability (Register 1.1500).....	31
45.2.3 PCS registers.....	31
45.2.3.1 PCS control 1 register (Register 3.0).....	31
45.2.3.1.2 Loopback (3.0.14).....	31
45.2.3.6 PCS control 2 register (Register 3.7).....	32
45.2.3.8 PCS status 3 register (Register 3.9).....	32
45.2.3.8.a 5GBASE-R capable (3.9.3).....	32
45.2.3.8.b 2.5GBASE-X capable (3.9.2)	32

45.2.3.11	EEE control and capability 2 register (Register 3.21)	33
45.2.3.11.a	5GBASE-KR EEE supported (3.21.8)	33
45.2.3.11.b	2.5GBASE-KX EEE supported (3.21.7)	33
45.2.3.15	BASE-R and MultiGBASE-T PCS status 1 register (Register 3.32)	33
45.2.3.15.1	BASE-R and MultiGBASE-T receive link status (3.32.12)	33
45.2.3.15.4	BASE-R and MultiGBASE-T PCS high BER (3.32.1)	34
45.2.3.15.5	BASE-R and MultiGBASE-T PCS block lock (3.32.0)	34
45.2.3.16	BASE-R and MultiGBASE-T PCS status 2 register (Register 3.33)	34
45.2.3.16.1	Latched block lock (3.33.15)	34
45.2.3.16.2	Latched high BER (3.33.14)	34
45.2.3.16.3	BER(3.33.13:8)	34
45.2.3.16.4	Errored blocks (3.33.7:0)	35
45.2.3.17	5/10/25GBASE-R PCS test pattern seed A (Registers 3.34 through 3.37)	35
45.2.3.18	5/10/25GBASE-R PCS test pattern seed B (Registers 3.38 through 3.41)	35
45.2.7	Auto-Negotiation registers	35
45.2.7.2	AN status (Register 7.1)	35
45.2.7.2.1	Parallel detection fault (7.1.9)	35
45.2.7.12	Backplane Ethernet, BASE-R copper status (Register 7.48)	36
45.2.7.12.3	Negotiated Port Type (7.48.1, 7.48.2, 7.48.3, 7.48.5, 7.48.6, 7.48.8, 7.48.9, 7.48.10, 7.48.11, 7.48.12, 7.48.13, 7.48.14, 7.48.15)	36
45.2.7.15	EEE advertisement 2 (Register 7.62)	36
45.2.7.15.a	5GBASE-KR EEE (7.62.3)	37
45.2.7.15.b	2.5GBASE-KX EEE (7.62.2)	37
45.2.7.16	EEE link partner ability 2 (Register 7.63)	37
45.5	Protocol implementation conformance statement (PICS) proforma for Clause 45, Management Data Input/Output (MDIO) interface	38
45.5.3	PICS proforma tables for the Management Data Input Output (MDIO) interface	38
45.5.3.2	PMA/PMD MMD options	38
45.5.3.3	PMA/PMD management functions	38
45.5.3.6	PCS options	38
46.	Reconciliation Sublayer (RS) and 10 Gigabit Media Independent Interface (XGMII)	39
46.3	XGMII functional specifications	39
46.3.3	Error and fault handling	39
46.3.3.3	Response to received invalid frame sequences	39
69.	Introduction to Ethernet operation over electrical backplanes	40
69.1	Overview	40
69.1.1	Scope	40
69.1.2	Relationship of Backplane Ethernet to the ISO OSI reference model	40
69.2	Summary of Backplane Ethernet Sublayers	41
69.2.3	Physical Layer signaling systems	41
69.3	Delay constraints	42
69.5	Protocol implementation conformance statement (PICS) proforma	42
70.	Physical Medium Dependent sublayer and baseband medium, type 1000BASE-KX	43
70.5	PMD MDIO function mapping	43
73.	Auto-Negotiation for backplane and copper cable assembly	44
73.2	Relationship to the ISO/IEC Open Systems Interconnection (OSI) reference model	44

73.6	Link codeword encoding	44
73.6.4	Technology Ability Field.....	44
73.7	Receive function requirements	45
73.7.4	Arbitration function requirements	45
73.7.4.1	Parallel Detection function	45
73.7.6	Priority Resolution function.....	45
73.10	State diagrams and variable definitions	46
73.10.1	State diagram variables.....	46
73.10.2	State diagram timers	46
73.11	Protocol implementation conformance statement (PICS) proforma for Clause 73, Auto-Negotiation for backplane and copper cable assembly.....	47
73.11.4	PICS proforma tables for Auto-Negotiation for backplane and copper cable assembly	47
73.11.4.4	Receive function requirements	47
78.	Energy-Efficient Ethernet (EEE).....	48
78.1	Overview.....	48
78.1.1	LPI Signaling.....	48
78.1.4	PHY types optionally supporting EEE	48
78.2	LPI mode timing parameters description.....	48
78.5	Communication link access latency.....	49
125.	Introduction to 2.5 Gb/s and 5 Gb/s networks.....	50
125.1	Overview.....	50
125.1.2	Relationship of 2.5 Gigabit and 5 Gigabit Ethernet to the ISO OSI reference model.....	50
125.1.3	Nomenclature.....	50
125.1.4	Physical Layer signaling systems	51
125.2	Summary of 2.5 Gigabit and 5 Gigabit Ethernet sublayers	52
125.2.2	Physical coding sublayer (PCS).....	52
125.2.3	Physical Medium Attachment sublayer (PMA).....	52
125.2.4	Auto-Negotiation, type BASE-T	52
125.2.4.1	Auto-Negotiation, type BASE-T	52
125.2.4.2	Auto-Negotiation, type Backplane	53
125.3	Delay Constraints.....	53
127.	Physical Coding Sublayer (PCS) and Physical Medium Attachment (PMA) sublayer for 2.5 Gb/s 8B/10B 2.5GBASE-X	54
127.1	Overview.....	54
127.1.1	Scope.....	54
127.1.2	Relationship of 2.5GBASE-X to other standards	54
127.1.3	Summary of 2.5GBASE-X sublayers	54
127.1.3.1	Physical Coding Sublayer (PCS)	54
127.1.3.2	Physical Medium Attachment (PMA) sublayer.....	54
127.1.3.3	Physical Medium Attachment (PMA) service interface rates	55
127.1.4	Inter-sublayer interfaces	55
127.1.5	Functional block diagram	56
127.2	Physical Coding Sublayer (PCS).....	56
127.2.1	PCS Interface (XGMII)	56
127.2.2	Functions within the PCS	57
127.2.3	PCS used with 2.5GBASE-KX PMD	57
127.2.4	Use of code-groups	58
127.2.5	XGMII to 2.5GPII mapping.....	58

127.2.5.1	2.5 Gb/s PCS Internal Interface (2.5GPII).....	58
127.2.5.2	Word Encode	59
127.2.5.3	Word-to-Octets	61
127.2.5.4	Octets-to-Word	61
127.2.5.5	Word Decode	62
127.2.6	8B/10B transmission code	62
127.2.6.1	Notation conventions	62
127.2.6.2	Transmission order	62
127.2.6.3	Generating code-groups and checking the validity of received code	64
127.2.6.4	Ordered sets	64
127.2.6.5	Comma considerations.....	65
127.2.6.6	Sequence (/Q/)	65
127.2.6.7	Data (/D/)	65
127.2.6.8	IDLE (/I/)	65
127.2.6.9	Low Power Idle (/LI/)	65
127.2.6.10	Start_of_Packet delimiter (SPD)	65
127.2.6.11	End_of_Packet delimiter (EPD)	66
127.2.6.12	Error_Propagation (/V/).....	66
127.2.7	Detailed functions and state diagrams	66
127.2.7.1	State variables	66
127.2.7.1.1	Notation conventions	66
127.2.7.1.2	Constants.....	66
127.2.7.1.3	Variables	67
127.2.7.1.4	Functions.....	72
127.2.7.1.5	Counters	73
127.2.7.1.6	Messages	74
127.2.7.1.7	Timers	75
127.2.7.2	State diagrams.....	76
127.2.7.2.1	Word Encode and Word-to-Octets	76
127.2.7.2.2	Transmit.....	76
127.2.7.2.3	Synchronization	80
127.2.7.2.4	Receive.....	80
127.2.7.2.5	Octets-to-Word and Decode	80
127.2.7.2.6	LPI state diagram	86
127.2.7.2.7	LPI status and management	87
127.3	Physical Medium Attachment (PMA) sublayer.....	87
127.3.1	Service Interface	87
127.3.1.1	PMA_UNITDATA.request.....	87
127.3.1.1.1	Semantics of the service primitive	87
127.3.1.1.2	When generated	87
127.3.1.1.3	Effect of receipt	87
127.3.1.2	PMA_UNITDATA.indication	88
127.3.1.2.1	Semantics of the service primitive	88
127.3.1.2.2	When generated	88
127.3.1.2.3	Effect of receipt	88
127.3.2	Functions within the PMA	88
127.3.2.1	Data delay	88
127.3.2.2	PMA transmit function	88
127.3.2.3	PMA receive function	89
127.3.2.4	Code-group alignment	89
127.3.3	Loopback mode.....	89
127.3.3.1	Receiver considerations	89
127.3.3.2	Transmitter considerations.....	89
127.3.4	Test functions.....	89

127.3.4.1	PMA PRBS9 test pattern (optional).....	90
127.4	Compatibility considerations	90
127.5	Delay constraints.....	90
127.6	Environmental specifications.....	90
127.7	Protocol implementation conformance statement (PICS) proforma for Clause 127, Physical Coding Sublayer (PCS) and Physical Medium Attachment (PMA) sublayer for 2.5 Gb/s 8B/10B 2.5GBASE-X.....	91
127.7.1	Introduction.....	91
127.7.2	Identification.....	91
127.7.2.1	Implementation identification.....	91
127.7.2.2	Protocol summary	91
127.7.3	Major capabilities/options.....	92
127.7.4	PICS proforma tables for the PCS and PMA sublayer, type 2.5GBASE-X.....	92
127.7.4.1	PCS	92
127.7.4.2	Code-group functions	93
127.7.4.3	EEE	93
127.7.4.4	PMA functions.....	94
127.7.4.5	Compatibility considerations	94
128.	Physical Medium Dependent sublayer and baseband medium, type 2.5GBASE-KX.....	95
128.1	Overview.....	95
128.2	Physical Medium Dependent (PMD) service interface	95
128.2.1	PMD_UNITDATA.request.....	96
128.2.1.1	Semantics of the service primitive.....	96
128.2.1.2	When generated	96
128.2.1.3	Effect of receipt	96
128.2.2	PMD_UNITDATA.indication	96
128.2.2.1	Semantics of the service primitive.....	96
128.2.2.2	When generated	96
128.2.2.3	Effect of receipt	96
128.2.3	PMD_SIGNAL.indication	96
128.2.3.1	Semantics of the service primitive.....	96
128.2.3.2	When generated	97
128.2.3.3	Effect of receipt	97
128.2.4	PMD_RXQUIET.request.....	97
128.2.4.1	Semantics of the service primitive.....	97
128.2.4.2	When generated	97
128.2.4.3	Effect of receipt	97
128.2.5	PMD_TXQUIET.request.....	97
128.2.5.1	Semantics of the service primitive.....	97
128.2.5.2	When generated	97
128.2.5.3	Effect of receipt	98
128.3	PCS requirements for Auto-Negotiation (AN) service interface.....	98
128.4	Delay constraints.....	98
128.5	PMD MDIO function mapping.....	98
128.6	PMD functional specifications.....	99
128.6.1	Link block diagram	99
128.6.2	PMD transmit function	100
128.6.3	PMD receive function	100
128.6.4	PMD signal detect function	100
128.6.5	PMD transmit disable function.....	100
128.6.6	Loopback mode.....	100
128.6.7	PMD fault function	101

128.6.8	PMD transmit fault function	101
128.6.9	PMD receive fault function	101
128.6.10	PMD LPI function	101
128.7	2.5GBASE-KX electrical characteristics	102
128.7.1	Transmitter characteristics	102
128.7.1.1	Test fixtures	102
128.7.1.2	Test fixture characteristics	102
128.7.1.3	Signaling speed	103
128.7.1.4	Output amplitude	103
128.7.1.5	Differential output return loss	104
128.7.1.6	Common-mode output return loss	104
128.7.1.7	Transition time	105
128.7.1.8	Transmit jitter test requirements	105
128.7.1.9	Transmit jitter	105
128.7.2	Receiver characteristics	106
128.7.2.1	Receiver interference tolerance	106
128.7.2.2	Signaling speed range	106
128.7.2.3	AC-coupling	106
128.7.2.4	Input signal amplitude	107
128.7.2.5	Differential input return loss	107
128.8	Interconnect characteristics	107
128.9	Environmental specifications	107
128.9.1	General safety	107
128.9.2	Network safety	107
128.9.3	Installation and maintenance guidelines	107
128.9.4	Electromagnetic compatibility	107
128.9.5	Temperature and humidity	107
128.10	Protocol implementation conformance statement (PICS) proforma for Clause 128, Physical Medium Dependent sublayer and baseband medium, type 2.5GBASE-KX	108
128.10.1	Introduction	108
128.10.2	Identification	108
128.10.2.1	Implementation identification	108
128.10.2.2	Protocol summary	108
128.10.3	Major capabilities/options	109
128.10.4	PICS proforma tables for Clause 128, Physical Medium Dependent (PMD) sublayer and baseband medium, type 2.5GBASE-KX	109
128.10.4.1	PMD functional specifications	109
128.10.4.2	Management functions	110
128.10.4.3	Transmitter electrical characteristics	111
128.10.4.4	Receiver electrical characteristics	112
128.10.4.5	Environmental and safety specifications	112
129	Physical Coding Sublayer (PCS) and Physical Medium Attachment (PMA) sublayer for 5 Gb/s 64B/66B, type 5GBASE-R	113
129.1	Overview	113
129.1.1	Scope	113
129.1.2	Relationship of 5GBASE-R to other standards	113
129.1.3	Summary of 5GBASE-R sublayers	114
129.1.3.1	Physical Coding Sublayer (PCS)	114
129.1.3.2	Physical Medium Attachment (PMA) sublayer	114
129.1.4	Inter-sublayer interfaces	115
129.2	Physical Coding Sublayer (PCS)	115
129.2.1	Functions within the PCS	115

129.2.2	Notation conventions	116
129.2.3	Transmission order	116
129.2.4	Low Power Idle	117
129.2.5	PCS used with 5GBASE-KR PMD	118
129.3	Physical Medium Attachment (PMA) sublayer	118
129.3.1	Service Interface	118
129.3.2	Functions within the PMA	118
129.3.2.1	PMA transmit function	119
129.3.2.2	PMA receive function	119
129.3.3	PMA loopback mode (optional)	119
129.4	Compatibility considerations	119
129.5	Delay constraints	119
129.6	Environmental specifications	119
129.7	Protocol implementation conformance statement (PICS) proforma for Clause 129, Physical Coding Sublayer (PCS) and Physical Medium Attachment (PMA) sublayer for 5 Gb/s 64B/66B, type 5GBASE-R	120
129.7.1	Introduction	120
129.7.2	Identification	120
129.7.2.1	Implementation identification	120
129.7.2.2	Protocol summary	120
129.7.3	Major capabilities/options	121
129.7.4	PICS Proforma Tables for PCS, type 5GBASE-R	121
129.7.4.1	Coding rules	121
129.7.4.2	Scrambler and Descrambler	121
129.7.5	Test-pattern modes	122
129.7.5.1	Bit order	122
129.7.6	Management	122
129.7.6.1	State diagrams	123
129.7.6.2	Loopback	123
129.7.6.3	Delay Constraints	123
129.7.6.4	Auto-Negotiation for Backplane Ethernet functions	123
129.7.6.5	LPI functions	124
130	Physical Medium Dependent sublayer and baseband medium, type 5GBASE-KR	125
130.1	Overview	125
130.2	Physical Medium Dependent (PMD) service interface	125
130.2.1	PMD_UNITDATA.request	126
130.2.1.1	Semantics of the service primitive	126
130.2.1.2	When generated	126
130.2.1.3	Effect of receipt	126
130.2.2	PMD_UNITDATA.indication	126
130.2.2.1	Semantics of the service primitive	126
130.2.2.2	When generated	126
130.2.2.3	Effect of receipt	126
130.2.3	PMD_SIGNAL.indication	126
130.2.3.1	Semantics of the service primitive	126
130.2.3.2	When generated	127
130.2.3.3	Effect of receipt	127
130.2.4	PMD_RX_MODE.request	127
130.2.4.1	Semantics of the service primitive	127
130.2.4.2	When generated	127
130.2.4.3	Effect of receipt	127
130.2.5	PMD_TX_MODE.request	127

130.2.5.1	Semantics of the service primitive	127
130.2.5.2	When generated	127
130.2.5.3	Effect of receipt	128
130.3	PCS requirements for Auto-Negotiation (AN) service interface	128
130.4	Delay constraints	128
130.5	PMD MDIO function mapping	128
130.6	PMD functional specifications	129
130.6.1	Link block diagram	129
130.6.2	PMD transmit function	129
130.6.3	PMD receive function	129
130.6.4	PMD signal detect function	129
130.6.5	PMD transmit disable function	130
130.6.6	Loopback mode	130
130.6.7	PMD_fault function	131
130.6.8	PMD transmit fault function	131
130.6.9	PMD receive fault function	131
130.6.10	PMD LPI function	131
130.7	5GBASE-KR electrical characteristics	132
130.7.1	Transmitter characteristics	132
130.7.1.1	Test fixture	132
130.7.1.2	Test fixture characteristics	133
130.7.1.3	Signaling speed	133
130.7.1.4	Output amplitude	133
130.7.1.5	Differential output return loss	134
130.7.1.6	Common-mode output return loss	135
130.7.1.7	Transition time	135
130.7.1.8	Transmit jitter test requirements	135
130.7.1.9	Transmit jitter	136
130.7.1.10	Transmitter output waveform	136
130.7.2	Receiver characteristics	137
130.7.2.1	Receiver interference tolerance	138
130.7.2.2	Signaling speed range	138
130.7.2.3	AC-coupling	138
130.7.2.4	Input signal amplitude	138
130.7.2.5	Differential input return loss	138
130.8	Interconnect characteristics	139
130.9	Environmental specifications	139
130.9.1	General safety	139
130.9.2	Network safety	139
130.9.3	Installation and maintenance guidelines	139
130.9.4	Electromagnetic compatibility	139
130.9.5	Temperature and humidity	139
130.10	Protocol implementation conformance statement (PICS) proforma for Clause 130, Physical Medium Dependent (PMD) sublayer and baseband medium, type 5GBASE-KR	140
130.10.1	Introduction	140
130.10.2	Identification	140
130.10.2.1	Implementation identification	140
130.10.2.2	Protocol summary	140
130.10.3	Major capabilities/options	141
130.10.4	PICS proforma tables for Clause 130, Physical Medium Dependent (PMD) sublayer and baseband medium, type 5GBASE-KR	141
130.10.4.1	PCS requirements for AN service interface	141
130.10.4.2	PMD functional specifications	142
130.10.4.3	Management functions	143

130.10.4.4 PMD Transmitter electrical characteristics.....	143
130.10.4.5 Receiver electrical characteristics.....	144
130.10.4.6 Environmental specifications.....	144
Annex 31B (normative) MAC Control PAUSE operation	145
31B.3 Detailed specification of PAUSE operation.....	145
31B.3.7 Timing considerations for PAUSE operation	145
31B.4 Protocol implementation conformance statement (PICS) proforma for MAC Control PAUSE operation	146
31B.4.3 Major capabilities/options.....	146
31B.4.6 PAUSE command MAC timing considerations	146
Annex 69A (normative) Interference tolerance testing	147
69A.1 Introduction.....	147
69A.2 Test setup	147
69A.2.1 Pattern generator	147
69A.2.2 Test channel	148
69A.2.4 Transmitter control	148
69A.3 Test methodology.....	148
Annex 69B (normative) Interconnect characteristics	149
69B.4 Channel parameters.....	149
69B.4.1 Overview.....	149
69B.4.2 Fitted attenuation	149
69B.4.3 Insertion loss	151
69B.4.4 Insertion loss deviation	153
69B.4.5 Return loss	155
69B.4.6 Crosstalk	156
69B.4.6.4 Insertion loss to crosstalk ratio (ICR).....	156
Annex 127A (informative) Compatibility of 2.5GBASE-X PCS/PMA with 1000BASE-X PCS/PMA running 2.5 times faster	158
Annex 128A (normative) 2.5 Gb/s Storage Enclosure Interface (2.5GSEI).....	159
128A.1 Overview	159
128A.1.1 Bit error ratio	161
128A.2 2.5GSEI compliance point definitions	161
128A.3 2.5GSEI electrical characteristics	164
128A.3.1 2.5GSEI host output characteristics.....	164
128A.3.1.1 Signaling rate and range	164
128A.3.1.2 Signaling levels.....	165
128A.3.1.3 Output return loss.....	165
128A.3.1.4 Transmit jitter test requirements	166
128A.3.1.5 Transmit jitter	166
128A.3.1.6 Transmitter output noise and distortion	166
128A.3.2 2.5GSEI host input characteristics.....	167
128A.3.2.1 Input differential return loss	167
128A.3.2.2 Receiver interference tolerance	167
128A.3.2.3 Receiver jitter tolerance	169
128A.3.3 2.5GSEI drive output characteristics	170

128A.3.4 2.5GSEI drive input characteristics	171
128A.3.4.1 Input differential return loss	171
128A.3.4.2 Receiver interference tolerance	171
128A.3.4.3 Receiver jitter tolerance	172
128A.4 Protocol implementation conformance statement (PICS) proforma for Annex 128A, 2.5 Gb/s Storage Enclosure Interface (2.5GSEI)	174
128A.4.1 Introduction	174
128A.4.2 Identification	174
128A.4.2.1 Implementation identification	174
128A.4.2.2 Protocol summary	174
128A.4.3 Major capabilities/options	175
128A.4.4 PICS proforma tables for 2.5 Gb/s Storage Enclosure Interface (2.5GSEI)	175
128A.4.4.1 Host output functions	175
128A.4.4.2 Host input functions	175
128A.4.4.3 Drive output functions	176
128A.4.4.4 Drive input functions	176
Annex 128B (normative) Test fixtures for 2.5 Gb/s and 5 Gb/s Storage Enclosure Interfaces	177
128B.1 Host and drive compliance boards	177
128B.1.1 Test fixture return loss	177
128B.1.2 Test fixture insertion loss	177
128B.2 Mated test fixtures	178
128B.2.1 Mated test fixtures insertion loss	179
128B.2.2 Mated test fixtures return loss	179
128B.2.3 Mated test fixtures integrated crosstalk noise	180
128B.2.3.1 Mated test fixture near-end crosstalk (NEXT) loss	180
128B.3 Protocol implementation conformance statement (PICS) proforma for Annex 128B, Test fixtures for 2.5 Gb/s and 5 Gb/s Storage Enclosure Interfaces	182
128B.3.1 Introduction	182
128B.3.2 Identification	182
128B.3.2.1 Implementation identification	182
128B.3.2.2 Protocol summary	182
128B.3.3 Major capabilities/options	183
128B.3.4 PICS proforma tables for test fixtures	183
128B.3.4.1 Management functions	183
Annex 130A (normative) 5 Gb/s Storage Enclosure Interface (5GSEI)	184
130A.1 Overview	184
130A.1.1 Bit error ratio	186
130A.2 5GSEI compliance point definitions	186
130A.3 5GSEI electrical characteristics	189
130A.3.1 5GSEI host output characteristics	189
130A.3.1.1 Signaling rate and range	189
130A.3.1.2 Signaling levels	190
130A.3.1.3 Output return loss	190
130A.3.1.4 Transmitter output waveform	191
130A.3.1.4.1 Linear fit to the measured waveform	191
130A.3.1.4.2 Steady-state voltage and linear fit pulse peak	191
130A.3.1.4.3 Pre-cursor coefficient	191
130A.3.1.5 Transmit jitter test requirements	192
130A.3.1.6 Transmit jitter	192
130A.3.1.7 Transmitter output noise and distortion	192

130A.3.2 5GSEI host input characteristics	193
130A.3.2.1 Input differential return loss	193
130A.3.2.2 Receiver interference tolerance	193
130A.3.2.3 Receiver jitter tolerance	195
130A.3.3 5GSEI drive output characteristics	196
130A.3.3.1 Linear fit to the measured waveform	197
130A.3.3.2 Steady-state voltage and linear fit pulse peak	197
130A.3.3.3 Precursor coefficient	197
130A.3.3.4 Transmitter output noise and distortion	197
130A.3.4 5GSEI drive input characteristics	198
130A.3.4.1 Input differential return loss	198
130A.3.4.2 Receiver interference tolerance	198
130A.3.4.3 Receiver jitter tolerance	200
130A.4 Protocol implementation conformance statement (PICS) proforma for Annex 130A, 5 Gb/s Storage Enclosure Interface (5GSEI)	202
130A.4.1 Introduction	202
130A.4.2 Identification	202
130A.4.2.1 Implementation identification	202
130A.4.2.2 Protocol summary	202
130A.4.3 Major capabilities/options	203
130A.4.4 PICS proforma tables for 5 Gb/s Storage Enclosure Interface (5GSEI)	203
130A.4.4.1 Host output functions	203
130A.4.4.2 Host input functions	203
130A.4.4.3 Drive output functions	204
130A.4.4.4 Drive input functions	204

IEEE Standard for Ethernet

Amendment 1: Physical Layer Specifications and Management Parameters for 2.5 Gb/s and 5 Gb/s Operation over Backplane

[This amendment is based on IEEE Std 802.3™-2018.]

NOTE—The editing instructions contained in this amendment define how to merge the material contained therein into the existing base standard and its amendments to form the comprehensive standard.

The editing instructions are shown in bold italic. Four editing instructions are used: change, delete, insert, and replace. ***Change*** is used to make corrections in existing text or tables. The editing instruction specifies the location of the change and describes what is being changed by using ~~strike through~~ (to remove old material) and underscore (to add new material). ***Delete*** removes existing material. ***Insert*** adds new material without disturbing the existing material. Deletions and insertions may require renumbering. If so, renumbering instructions are given in the editing instruction. ***Replace*** is used to make changes in figures or equations by removing the existing figure or equation and replacing it with a new one. Editing instructions, change markings, and this NOTE will not be carried over into future editions because the changes will be incorporated into the base standard.

Cross references that refer to clauses, tables, equations, or figures not covered by this amendment are highlighted in green.¹

¹ Notes in text, tables, and figures are given for information only and do not contain requirements needed to implement the standard.

1. Introduction

1.3 Normative references

Insert the following new reference (for SFF-8482 connector) in alphanumerical order:

SFF-8482, Specification for Serial Attachment 2X Unshielded Connector.²

1.4 Definitions

Insert the following new definition (for 2.5GBASE-KX) after 1.4.81 1G-EPON:

1.4.81a 2.5GBASE-KX: IEEE 802.3 Physical Layer specification for 2.5 Gb/s using 2.5GBASE-X encoding over an electrical backplane. (See IEEE Std 802.3, Clause 128.)

Insert the following new definitions (for 2.5GBASE-X, 2.5GP11, and 2.5GSEI) after 1.4.82 2.5GBASE-T:

1.4.82a 2.5GBASE-X: IEEE 802.3 physical coding and physical medium attachment for serial 2.5 Gb/s operation. (See IEEE Std 802.3, Clause 127.)

1.4.82b 2.5GP11: The 2.5 Gb/s PCS Internal Interface is a logical interface that is internal to the 2.5GBASE-X PCS and exists solely for the purposes of defining the 2.5GBASE-X PCS functionality. (See IEEE Std 802.3, 127.2.5.1.)

1.4.82c 2.5GSEI: The 2.5 Gb/s Interface from storage sub-system or bridge subsystem onto backplane (See IEEE Std 802.3, Annex 128A.)

Insert the following new definitions (for 5GBASE-KR and 5GBASE-R) after 1.4.128 4D-PAM5:

1.4.128a 5GBASE-KR: IEEE 802.3 Physical Layer specification for 5 Gb/s using 5GBASE-R encoding over an electrical backplane. (See IEEE Std 802.3, Clause 130.)

1.4.128b 5GBASE-R: An IEEE 802.3 physical coding sublayer and physical medium attachment sublayer for serial 5 Gb/s operation. (See IEEE Std 802.3, Clause 129.)

Insert the following new definition (for 5GSEI) after 1.4.129 5GBASE-T:

1.4.129a 5GSEI: The 5 Gb/s Interface from storage sub-system or bridge subsystem onto backplane (See IEEE Std 802.3, Annex 130A.)

Change 1.4.150 as shown:

1.4.150 BASE-R: An IEEE 802.3 family of Physical Layer devices using 64B/66B encoding defined in Clause 49, Clause 82, Clause 107, or Clause 119, or Clause 129 of IEEE Std 802.3. (~~See IEEE Std 802.3, Clause 49, Clause 82, Clause 107, Clause 119.~~)

²SFF documents are available from the Storage Networking Industry Association (www.snia.org/sff/specifications).

1.5 Abbreviations

Insert the following new abbreviations into 1.5 in alphanumeric order:

2.5GPII	2.5 Gb/s PCS Internal Interface
2.5GSEI	2.5 Gb/s Storage Enclosure Interface
5GSEI	5 Gb/s Storage Enclosure Interface

30. Management

30.3 Layer management for DTEs

30.3.2 PHY device managed object class

30.3.2.1 PHY device attributes

30.3.2.1.2 aPhyType

Insert the following new entry in "APPROPRIATE SYNTAX" in 30.3.2.1.2 after the entry for 2.5GBASE-T:

2.5GBASE-X	Clause 127 2.5 Gb/s 8B/10B
------------	----------------------------

Insert the following new entry in "APPROPRIATE SYNTAX" in 30.3.2.1.2 after the entry for 5GBASE-T:

5GBASE-R	Clause 129 5 Gb/s 64/66B
----------	--------------------------

30.3.2.1.3 aPhyTypeList

Insert the following new entry in "APPROPRIATE SYNTAX" in 30.3.2.1.3 after the entry for 2.5GBASE-T:

2.5GBASE-X	Clause 127 2.5 Gb/s 8B/10B
------------	----------------------------

Insert the following new entry in "APPROPRIATE SYNTAX" in 30.3.2.1.3 after the entry for 5GBASE-T:

5GBASE-R	Clause 129 5 Gb/s 64/66B
----------	--------------------------

30.3.2.1.5 aSymbolErrorDuringCarrier

Change the fourth paragraph of "BEHAVIOUR DEFINED AS" in 30.3.2.1.5 as shown:

BEHAVIOUR DEFINED AS:

For operation at 5 Gb/s, 10 Gb/s, 25 Gb/s, 40 Gb/s, 100 Gb/s, 200 Gb/s, and 400 Gb/s, it is a count of the number of times the receiving media is non-idle (the time between the Start of Packet Delimiter and the End of Packet Delimiter as defined by 46.2.5 and 81.2.5) for a period of time equal to or greater than minFrameSize, and during which there was at least one occurrence of an event that causes the PHY to indicate "Receive Error" on the media independent interface (see Table 46–4 and Table 81–4).

30.5 Layer management for medium attachment units (MAUs)

30.5.1 MAU managed object class

30.5.1.1 MAU attributes

30.5.1.1.2 aMAUType

Insert the following new entry in "APPROPRIATE SYNTAX" in 30.5.1.1.2 before the entry for 2.5GBASE-T:

2.5GBASE-KX 2.5GBASE-X PMD as specified in Clause 128 over an electrical backplane as specified in Clause 128

Insert the following new entry in "APPROPRIATE SYNTAX" in 30.5.1.1.2 after the entry for 2.5GBASE-T:

2.5GBASE-X 2.5GBASE-X PCS/PMA as specified in Clause 127 over undefined PMD

Insert the following new entries in "APPROPRIATE SYNTAX" in 30.5.1.1.2 before the entry for 5GBASE-T:

5GBASE-KR 5GBASE-KR PMD as specified in Clause 130 over an electrical backplane as specified in Clause 130
5GBASE-R 5GBASE-R PCS/PMA as specified in Clause 129 over undefined PMD

Change the second paragraph of "BEHAVIOUR DEFINED AS" in 30.5.1.1.2 as shown:

The enumerations 1000BASE-X, 1000BASE-XHD, 1000BASE-XFD, 2.5GBASE-X, 5GBASE-R, 10GBASE-X, 10GBASE-R, 10GBASE-W, 25GBASE-R, 40GBASE-R, 100GBASE-R, 200GBASE-R, and 400GBASE-R shall only be returned if the underlying PMD type is unknown.;

30.6 Management for link Auto-Negotiation

30.6.1 Auto-Negotiation managed object class

30.6.1.1 Auto-Negotiation attributes

30.6.1.1.5 aAutoNegLocalTechnologyAbility

Insert the following new entry in "APPROPRIATE SYNTAX" in 30.6.1.1.5 after the entry for 2.5GBASE-T:

2.5GKX 2.5GBASE-KX as specified in Clause 128

Insert the following new entry in "APPROPRIATE SYNTAX" in 30.6.1.1.5 after the entry for 5GBASE-T:

5GKR 5GBASE-KR as specified in Clause 130

45. Management Data Input/Output (MDIO) Interface

45.2 MDIO Interface Registers

45.2.1 PMA/PMD registers

Change the name of registers 1.160 and 1.161 in Table 45–3 as shown (unchanged rows not shown):

Table 45–3—PMA/PMD registers

Register address	Register name	Subclause
1.160	1000BASE-KX/ 2.5GBASE-KX control	45.2.1.97
1.161	1000BASE-KX/ 2.5GBASE-KX status	45.2.1.98

45.2.1.1 PMA/PMD control 1 register (Register 1.0)

45.2.1.1.5 PMA local loopback (1.0.0)

Change the first sentence of the second paragraph of 45.2.1.1.5 as shown:

The local loopback function is mandatory for the 1000BASE-KX, 2.5GBASE-X, 5GBASE-R, 10GBASE-KR, 10GBASE-X, 40GBASE-KR4, 40GBASE-CR4, and 100GBASE-CR10 port type and optional for all other port types, except 2BASE-TL, 10PASS-TS, and 10/1GBASE-PRX, which do not support loopback.

45.2.1.6 PMA/PMD control 2 register (Register 1.7)

Change the description for bits 1.7.6:0 in Table 45–7 as shown (unchanged table rows and bit description lines not shown):

Table 45–7—PMA/PMD control 2 register bit definitions

Bit(s)	Name	Description	R/W ^a
1.7.6:0	PMA/PMD type selection	6 5 4 3 2 1 0 0 1 1 1 1 0 0 = 5GBASE-KR PMA/PMD reserved 0 1 1 1 0 1 1 = 2.5GBASE-KX PMA/PMD reserved	R/W

^aR/W = Read/Write, RO = Read only

45.2.1.7 PMA/PMD status 2 register (Register 1.8)**45.2.1.7.4 Transmit fault (1.8.11)**

Change Table 45-9 by adding the following new rows for 2.5GBASE-KX and 5GBASE-KR as shown (other unchanged rows not shown):

Table 45–9—Transmit fault description location

PMA/PMD	Description location
<u>2.5GBASE-KX</u>	<u>128.6.8</u>
2.5GBASE-T, 5GBASE-T	126.4.2.2
<u>5GBASE-KR</u>	<u>130.6.8</u>

45.2.1.7.5 Receive fault (1.8.10)

Change Table 45-10 by adding the following new rows for 2.5GBASE-KX and 5GBASE-KR as shown (other unchanged rows not shown):

Table 45–10—Receive fault description location

PMA/PMD	Description location
<u>2.5GBASE-KX</u>	<u>128.6.9</u>
2.5GBASE-T, 5GBASE-T	126.4.2.4
<u>5GBASE-KR</u>	<u>130.6.9</u>

45.2.1.8 PMD transmit disable register (Register 1.9)

Change Table 45-12 by adding the following new rows for 2.5GBASE-KX and 5GBASE-KR as shown (other unchanged rows not shown):

Table 45–12—Transmit disable description location

PMA/PMD	Description location
<u>2.5GBASE-KX</u>	<u>128.6.5</u>
2.5GBASE-T and 5GBASE-T	126.4.2.3
<u>5GBASE-KR</u>	<u>130.6.5</u>

45.2.1.18 2.5G/5G PMA/PMD extended ability register (Register 1.21)

Change Table 45–21 as shown:

Table 45–21— 2.5G/5G PMA/PMD extended ability register bit definitions

Bit(s)	Name	Description	R/W ^a
1.21.15:24	Reserved	Value always 0	RO
1.21.3	5GBASE-KR ability	1 = PMA/PMD is able to perform 5GBASE-KR 0 = PMA/PMD is not able to perform 5GBASE-KR	RO
1.21.2	2.5GBASE-KX ability	1 = PMA/PMD is able to perform 2.5GBASE-KX 0 = PMA/PMD is not able to perform 2.5GBASE-KX	RO
1.21.1	5GBASE-T ability	1 = PMA/PMD is able to perform 5GBASE-T 0 = PMA/PMD is not able to perform 5GBASE-T	RO
1.21.0	2.5GBASE-T ability	1 = PMA/PMD is able to perform 2.5GBASE-T 0 = PMA/PMD is not able to perform 2.5GBASE-T	RO

^aRO = Read only

Insert the following new subclauses (45.2.1.18.a and 45.2.1.18.b) after the introductory text of 45.2.1.18 (i.e., before 45.2.1.18.1):

45.2.1.18.a 5GBASE-KR ability (1.21.3)

When read as a one, bit 1.21.3 indicates that the PMA/PMD is able to operate as a 5GBASE-KR PMA/PMD type. When read as a zero, bit 1.21.3 indicates that the PMA/PMD is not able to operate as a 5GBASE-KR PMA/PMD type.

45.2.1.18.b 2.5GBASE-KX ability (1.21.2)

When read as a one, bit 1.21.2 indicates that the PMA/PMD is able to operate as a 2.5GBASE-KX PMA/PMD type. When read as a zero, bit 1.21.2 indicates that the PMA/PMD is not able to operate as a 2.5GBASE-KX PMA/PMD type.

45.2.1.89 BASE-R PMD control register (Register 1.150)

Insert the following new paragraph after the first paragraph of 45.2.1.89:

The BASE-R PMD control register is also used by 5GBASE-KR described in Clause 130 to disable the transmitter equalizer for test purposes. 5GBASE-KR does not use the start-up protocol.

Change Table 45-69 as shown:

Table 45-69— BASE-R PMD control register

Bit(s)	Name	Description	R/W ^a
1.150.15:2 1.150.15:3	Reserved	Value always 0	RO
1.150.2	Transmitter equalizer disable	1 = Disable the 5GBASE-KR transmitter equalizer 0 = Normal operation	R/W
1.150.1	Training enable	1 = Enable the BASE-R start-up protocol 0 = Disable the BASE-R start-up protocol	R/W
1.150.0	Restart training	1 = Restart BASE-R start-up protocol 0 = Normal operation	R/W SC

^aR/W = Read/Write, SC = Self-clearing, RO = Read only

Insert the following new subclause (45.2.1.89.3) after 45.2.1.89.2:

45.2.1.89.3 Transmitter equalizer disable (1.150.2)

When bit 1.150.2 is set to one, 5GBASE-KR transmitter equalization is disabled. The default value of bit 1.150.2 is zero.

Change the title and text of 45.2.1.97 as shown:

45.2.1.97 1000BASE-KX/2.5GBASE-KX control register (Register 1.160)

The assignment of bits in the 1000BASE-KX/2.5GBASE-KX control register is shown in Table 45-77.

Change the title of Table 45-77 as shown:

Table 45-77—1000BASE-KX/2.5GBASE-KX control register

45.2.1.97.1 PMD transmit disable (1.160.0)

Change 45.2.1.97.1 as shown:

This bit disables the 1000BASE-KX transmitter as defined in 70.6.5 or the 2.5GBASE-KX transmitter as defined in 128.6.5.

Change the title and text of 45.2.1.98 as shown:

45.2.1.98 1000BASE-KX/2.5GBASE-KX status register (Register 1.161)

The assignment of bits in the 1000BASE-KX/2.5GBASE-KX status register is shown in Table 45-78.

Change the title of Table 45-78 as shown:

Table 45-78—1000BASE-KX/2.5GBASE-KX status register

Change the title and text of 45.2.1.98.6 as shown:

45.2.1.98.6 1000BASE-KX/2.5GBASE-KX signal detect (1.161.0)

The PMD signal detect function is ~~optional~~ for both 1000BASE-KX PMD (see 70.6.4) and 2.5GBASE-KX PMD (see 128.6.4) is ~~mandatory~~ if EEE is implemented and ~~optional~~ otherwise. The 1000BASE-X PCS and 2.5GBASE-X PCS requires signal detect to be one before synchronization can occur. If the signal detect function is not implemented, this bit is set to one.

45.2.1.140 Test-pattern ability (Register 1.1500)

Change the first paragraph of 45.2.1.140 as shown:

The test-pattern ability register is used for PHY types that implement SSPRQ, square wave, and PRBS testing in the PMA. These functions are described in 127.3.4.1, 83.5.10, and 120.5.11. The assignment of bits in the test-pattern ability register is shown in Table 45–105.

45.2.3 PCS registers

Change the indicated rows of Table 45–176 as shown (unchanged rows not shown):

Table 45–176—PCS registers

Register address	Register name	Subclause
3.34 through 3.37	5/10/25GBASE-R PCS test pattern seed A	45.2.3.17
3.38 through 3.41	5/10/25GBASE-R PCS test pattern seed B	45.2.3.18

45.2.3.1 PCS control 1 register (Register 3.0)

45.2.3.1.2 Loopback (3.0.14)

Change the first paragraph of 45.2.3.1.2 as shown:

When the 100BASE-T1, any MultiGBASE-T, or the 5/10GBASE-R mode of operation is selected for the PCS using the PCS type selection field (3.7.3:0), the PCS shall be placed in a loopback mode of operation when bit 3.0.14 is set to a one. When bit 3.0.14 is set to a one, the 100BASE-T1, 5/10GBASE-R, or any PCS in the MultiGBASE-T set shall accept data on the transmit path and return it on the receive path. The speed of the loopback is selected by the PCS control 1 (Register 3.0) defined in 45.2.3.1. The specific behavior of the 100BASE-T1 PCS during loopback is specified in 96.3.5. The specific behavior of the 5/10GBASE-R PCS during loopback is specified in 49.2. The specific behavior for the 10GBASE-T PCS during loopback is specified in 55.3.7.3. The specific behavior for the 25GBASE-T and 40GBASE-T PCS during loopback is specified in 113.3.7.3. The specific behavior for the 2.5GBASE-T or 5GBASE-T PCS during loopback is specified in 126.3.7.3. For all other port types, the PCS loopback functionality is not applicable and writes to this bit shall be ignored and reads from this bit shall return a value of zero.

45.2.3.6 PCS control 2 register (Register 3.7)

Change the description for bits 3.7.3:0 in Table 45–180 as shown (unchanged table rows and bit description lines not shown):

Table 45–180—PCS control 2 register bit definitions

Bit(s)	Name	Description	R/W ^a
3.7.3:0	PCS type selection	<div> <div>3 2 1 0</div> <div>1 1 1 x reserved</div> <div>1 1 1 1 = Select 5GBASE-R PCS type</div> <div>1 1 1 0 = Select 2.5GBASE-X PCS type</div> </div>	R/W

^aRO = Read only, R/W = Read/Write

45.2.3.8 PCS status 3 register (Register 3.9)

Change Table 45–182 as shown:

Table 45–182—PCS status 3 register bit definitions

Bit(s)	Name	Description	R/W ^a
3.9.15:24	Reserved	Value always 0	RO
3.9.3	5GBASE-R capable	<div>1 = PCS is able to support 5GBASE-R PCS type</div> <div>0 = PCS is not able to support 5GBASE-R PCS type</div>	RO
3.9.2	2.5GBASE-X capable	<div>1 = PCS is able to support 2.5GBASE-X PCS type</div> <div>0 = PCS is not able to support 2.5GBASE-X PCS type</div>	RO
3.9.1	400GBASE-R capable	<div>1 = PCS is able to support 400GBASE-R PCS type</div> <div>0 = PCS is not able to support 400GBASE-R PCS type</div>	RO
3.9.0	200GBASE-R capable	<div>1 = PCS is able to support 200GBASE-R PCS types</div> <div>0 = PCS is not able to support 200GBASE-R PCS types</div>	RO

^aRO = Read only

Insert the following new subclauses (45.2.3.8.a and 45.2.3.8.b) after the introductory text of 45.2.3.8 (i.e., before 45.2.3.8.1):

45.2.3.8.a 5GBASE-R capable (3.9.3)

When read as a one, bit 3.9.3 indicates that the PCS is able to support the 5GBASE-R PCS type. When read as a zero, bit 3.9.3 indicates that the PCS is not able to support the 5GBASE-R PCS type.

45.2.3.8.b 2.5GBASE-X capable (3.9.2)

When read as a one, bit 3.9.2 indicates that the PCS is able to support operation in a 2.5GBASE-X PCS type. When read as a zero, bit 3.9.2 indicates that the PCS is not able to support operation in a 2.5GBASE-X PCS type.

45.2.3.11 EEE control and capability 2 register (Register 3.21)

Change Table 45–184 as shown:

Table 45–184—EEE control and capability 2 register bit definitions

Bit(s)	Name	Description	R/W ^a
3.21.15:69	Reserved	Value always 0	RO
<u>3.21.8</u>	<u>5GBASE-KR EEE</u>	<u>1 = EEE is supported for 5GBASE-R</u> <u>0 = EEE is not supported for 5GBASE-R</u>	<u>RO</u>
<u>3.21.7</u>	<u>2.5GBASE-KX EEE</u>	<u>1 = EEE is supported for 2.5GBASE-X</u> <u>0 = EEE is not supported for 2.5GBASE-X</u>	<u>RO</u>
<u>3.21.6</u>	<u>Reserved</u>	<u>Value always 0</u>	<u>RO</u>
3.21.5	400GBASE-R fast wake	1 = EEE fast wake is supported for 400GBASE-R 0 = EEE fast wake is not supported for 400GBASE-R	RO
3.21.4	Reserved	Value always 0	RO
3.21.3	200GBASE-R fast wake	1 = EEE fast wake is supported for 200GBASE-R 0 = EEE fast wake is not supported for 200GBASE-R	RO
3.21.2	25GBASE-T EEE	1 = EEE is supported for 25GBASE-T 0 = EEE is not supported for 25GBASE-T	RO
3.21.1	5GBASE-T EEE	1 = EEE is supported for 5GBASE-T 0 = EEE is not supported for 5GBASE-T	RO
3.21.0	2.5GBASE-T EEE	1 = EEE is supported for 2.5GBASE-T 0 = EEE is not supported for 2.5GBASE-T	RO

^aRO = Read only

Insert the following new subclauses (45.2.3.11.a and 45.2.3.11.b) after the introductory text of 45.2.3.11 (i.e., before 45.2.3.11.1):

45.2.3.11.a 5GBASE-KR EEE supported (3.21.8)

If the device supports EEE operation for 5GBASE-KR as defined in 130.1, this bit shall be set to one.

45.2.3.11.b 2.5GBASE-KX EEE supported (3.21.7)

If the device supports EEE operation for 2.5GBASE-KX as defined in 128.1, this bit shall be set to one.

45.2.3.15 BASE-R and MultiGBASE-T PCS status 1 register (Register 3.32)**45.2.3.15.1 BASE-R and MultiGBASE-T receive link status (3.32.12)**

Change last sentence of 45.2.3.15.1 as shown:

This bit is a reflection of the PCS_status variable defined in 49.2.14.1 for 5/10/25GBASE-R, in 126.3.7.1 for 2.5GBASE-T and 5GBASE-T, in 55.3.7.1 for 10GBASE-T, in 113.3.7.1 for 25GBASE-T and 40GBASE-T, in 82.3.1 for 40/100GBASE-R, and in 119.3 for 200/400GBASE-R.

45.2.3.15.4 BASE-R and MultiGBASE-T PCS high BER (3.32.1)

Change the last sentence of the first paragraph of 45.2.3.15.4 as shown:

This bit is a direct reflection of the state of the `hi_ber` variable in the BER monitor state diagrams as defined in 49.2.13.2.2 for 5/10/25GBASE-R and in 82.2.19.2.2 for 40/100GBASE-R.

45.2.3.15.5 BASE-R and MultiGBASE-T PCS block lock (3.32.0)

Change the third sentence of 45.2.3.15.5 as shown:

For a ~~10GBASE-R~~ or 5/10/25GBASE-R PCS, this bit is a direct reflection of the state of the `block_lock` variable defined in 49.2.13.2.2.

45.2.3.16 BASE-R and MultiGBASE-T PCS status 2 register (Register 3.33)

45.2.3.16.1 Latched block lock (3.33.15)

Change 45.2.3.16.1 as shown:

When read as a one, bit 3.33.15 indicates that the 5/10/25/40/100GBASE-R or a member of the MultiGBASE-T set PCS has achieved block lock. When read as a zero, bit 3.33.15 indicates that the 5/10/25/40/100GBASE-R or a member of the MultiGBASE-T set PCS has lost block lock.

The latched block lock bit shall be implemented with latching low behavior.

This bit is a latching low version of the 5/10/25/40/100GBASE-R and MultiGBASE-T PCS block lock status bit (3.32.0).

45.2.3.16.2 Latched high BER (3.33.14)

Change 45.2.3.16.2 as shown:

When read as a one, bit 3.33.14 indicates that the 5/10/25/40/100GBASE-R or a member of the MultiGBASE-T set PCS has detected a high BER. When read as a zero, bit 3.33.14 indicates that the 5/10/25/40/100GBASE-R or a member of the MultiGBASE-T set PCS has not detected a high BER.

The latched high BER bit shall be implemented with latching high behavior.

This bit is a latching high version of the 5/10/25/40/100GBASE-R and MultiGBASE-T PCS high BER status bit (3.32.1).

45.2.3.16.3 BER(3.33.13:8)

Change the first sentence of 45.2.3.16.3 as shown:

The BER counter is a six-bit count as defined by the `ber_count` variable in 49.2.14.2 and 82.2.19.2.4 for 5/10/25/40/100GBASE-R and defined by counter `lfer_count` in 126.3.7.2 for 2.5GBASE-T and 5GBASE-T, in 55.3.7.2 for 10GBASE-T, and in 113.3.7.2 for 25GBASE-T and 40GBASE-T.

45.2.3.16.4 Errored blocks (3.33.7:0)

Change the first sentence of 45.2.3.16.4 as shown:

The errored blocks counter is an eight-bit count defined by the counter errored_block_count specified in 49.2.14.2 for 5/10/25GBASE-R, in 82.3.1 for 40/100GBASE-R, in 126.3.7.2 for 2.5GBASE-T and 5GBASE-T, in 55.3.7.2 for 10GBASE-T, and in 113.3.7.2 for 25GBASE-T and 40GBASE-T.

Change the title and the first and second sentences of 45.2.3.17 as shown:

45.2.3.17 5/10/25GBASE-R PCS test pattern seed A (Registers 3.34 through 3.37)

The assignment of bits in the 5/10/25GBASE-R PCS test pattern seed A registers is shown in Table 45–189. This register is only required when the 5GBASE-R, 10GBASE-R, or 25GBASE-R capability is supported.

Change the title of Table 45–189 as shown:

Table 45–189—5/10/25GBASE-R PCS test pattern seed A 0-3 register bit definitions

Change the title and the first and second sentences of 45.2.3.18 as shown:

45.2.3.18 5/10/25GBASE-R PCS test pattern seed B (Registers 3.38 through 3.41)

The assignment of bits in the 5/10/25GBASE-R PCS test pattern seed B registers is shown in Table 45–190. This register is only required when the 5GBASE-R, 10GBASE-R, or 25GBASE-R capability is supported.

Change the title of Table 45–190 as shown:

Table 45–190—5/10/25GBASE-R PCS test pattern seed B 0-3 register bit definitions

45.2.7 Auto-Negotiation registers

45.2.7.2 AN status (Register 7.1)

45.2.7.2.1 Parallel detection fault (7.1.9)

Change 45.2.7.2.1 as shown:

The parallel detection Fault bit (7.1.9) shall be set to one to indicate that more than one of 1000BASE-KX, 2.5GBASE-KX, or 10GBASE-KX4 PMAs have indicated link_status=OK when the autoneg_wait_timer expires. The parallel detection fault bit shall be reset to zero on a read of the AN status register (Register 7.1).

45.2.7.12 Backplane Ethernet, BASE-R copper status (Register 7.48)

Change Table 45–318 by adding the following new rows for 7.48.15 and 7.48.14 in numeric order and deleting the Reserved row as shown (unchanged rows not shown):

Table 45–318—Backplane Ethernet, BASE-R copper status register (Register 7.48) bit definitions

Bit(s)	Name	Description	R/W ^a
7.48.15:14	Reserved	Value always 0	RØ
7.48.15	5GBASE-KR	1 = PMA/PMD is negotiated to perform 5GBASE-KR 0 = PMA/PMD is not negotiated to perform 5GBASE-KR	RO
7.48.14	2.5GBASE-KX	1 = PMA/PMD is negotiated to perform 2.5GBASE-KX 0 = PMA/PMD is not negotiated to perform 2.5GBASE-KX	RO

^aRO = Read only

Change the title of 45.2.7.12.3 as shown:

45.2.7.12.3 Negotiated Port Type (7.48.1, 7.48.2, 7.48.3, 7.48.5, 7.48.6, 7.48.8, 7.48.9, 7.48.10, 7.48.11, 7.48.12, 7.48.13, 7.48.14, 7.48.15)

45.2.7.15 EEE advertisement 2 (Register 7.62)

Change Table 45–321 as shown:

Table 45–321—EEE advertisement 2 register (Register 7.62) bit definitions

Bit(s)	Name	Description	Subclause reference; Next Page bit number	R/W ^a
7.62.15:24	Reserved	Value always 0		RO
7.62.3	5GBASE-KR EEE	1 = Advertise that the 5GBASE-KR has EEE capability 0 = Do not advertise that the 5GBASE-KR has EEE capability	73.7.7.1; U17	R/W
7.62.2	2.5GBASE-KX EEE	1 = Advertise that the 2.5GBASE-KX has EEE capability 0 = Do not advertise that the 2.5GBASE-KX has EEE capability	73.7.7.1; U16	R/W
7.62.1	5GBASE-T EEE	1 = Advertise that the 5GBASE-T has EEE capability 0 = Do not advertise that the 5GBASE-T has EEE capability	126.4.2.5.10	R/W
7.62.0	2.5GBASE-T EEE	1 = Advertise that the 2.5GBASE-T has EEE capability 0 = Do not advertise that the 2.5GBASE-T has EEE capability	126.4.2.5.10	R/W

^aR/W = Read/Write, RO = Read only

Insert the following new subclauses (45.2.7.15.a and 45.2.7.15.b) after the introductory text of 45.2.7.15 (i.e., before 45.2.7.15.1):

45.2.7.15.a 5GBASE-KR EEE (7.62.3)

If the device supports EEE operation for 5GBASE-KR as defined in 130.1 and EEE operation is desired, this bit shall be set to one.

45.2.7.15.b 2.5GBASE-KX EEE (7.62.2)

If the device supports EEE operation for 2.5GBASE-KX as defined in 128.1 and EEE operation is desired, this bit shall be set to one.

45.2.7.16 EEE link partner ability 2 (Register 7.63)

Change Table 45–322 as shown:

Table 45–322—EEE advertisement 2 register (Register 7.63) bit definitions

Bit(s)	Name	Description	Subclause reference; Next Page bit number	R/W ^a
7.62.15: 24	Reserved	Value always 0		RO
<u>7.63.3</u>	<u>5GBASE-KR EEE</u>	<u>1 = Link partner is advertising that the 5GBASE-KR has EEE capability</u> <u>0 = Link partner is not advertising that the 5GBASE-KR has EEE capability</u>	<u>73.7.7.1; U17</u>	<u>RO</u>
<u>7.63.2</u>	<u>2.5GBASE-KX EEE</u>	<u>1 = Link partner is advertising that the 2.5GBASE-KX has EEE capability</u> <u>0 = Link partner is not advertising that the 2.5GBASE-KX has EEE capability</u>	<u>73.7.7.1; U16</u>	<u>RO</u>
7.63.1	5GBASE-T EEE	1 = Link partner is advertising that the 5GBASE-T has EEE capability 0 = Link partner is not advertising that the 5GBASE-T has EEE capability	126.4.2.5.10	RO
7.63.0	2.5GBASE-T EEE	1 = Link partner is advertising that the 2.5GBASE-T has EEE capability 0 = Link partner is not advertising that the 2.5GBASE-T has EEE capability	126.4.2.5.10	RO

^aRO = Read only

45.5 Protocol implementation conformance statement (PICS) proforma for Clause 45, Management Data Input/Output (MDIO) interface³

45.5.3 PICS proforma tables for the Management Data Input Output (MDIO) interface

45.5.3.2 PMA/PMD MMD options

Change the table in 45.5.3.2 by adding the following new rows for 2.5KX and 5KR as shown (other unchanged rows not shown):

Item	Feature	Subclause	Value/Comment	Status	Support
*2.5T	Implementation of a 2.5GBASE-T PMA	45.2.1.18		PMA:O	Yes [] No []
<u>2.5GKX</u>	<u>Implementation of 2.5GBASE-KX PMA/PMD</u>	<u>45.2.1.18.b</u>		<u>PMA:O</u>	<u>Yes []</u> <u>No []</u>
<u>5GKR</u>	<u>Implementation of 5GBASE-KR PMA/PMD</u>	<u>45.2.1.18.a</u>		<u>PMA:O</u>	<u>Yes []</u> <u>No []</u>
*5T	Implementation of a 2.5GBASE-T PMA	45.2.1.18		PMA:O	Yes [] No []

45.5.3.3 PMA/PMD management functions

Change the MM124 row in the table in 45.5.3.3 as shown (unchanged rows not shown):

Item	Feature	Subclause	Value/Comment	Status	Support
MM124	Backplane Ethernet AN ability bit is set to one for 1000BASE-KX, 2.5GBASE-KX, 5GBASE-KR, 10GBASE-KX ₄ and 10GBASE-KR PHYs.	45.2.7.12.4		<u>2.5GKX:M</u> <u>5GKR:M</u> KX:M KX4:M KR:M	Yes [] N/A []

45.5.3.6 PCS options

Insert the following new rows (for 2.5GX and 5GX) at the end of the table in 45.5.3.6:

Item	Feature	Subclause	Value/Comment	Status	Support
2.5GX	Implementation of 2.5GBASE-X PCS	45.2.3.8		PCS:O	Yes [] No [] N/A []
5GR	Implementation of 5GBASE-R PCS	45.2.3.8		PCS:O	Yes [] No [] N/A []

³Copyright release for PICS proformas: Users of this standard may freely reproduce the PICS proforma in this subclause so that it can be used for its intended purpose and may further publish the completed PICS.

46. Reconciliation Sublayer (RS) and 10 Gigabit Media Independent Interface (XGMII)

46.3 XGMII functional specifications

46.3.3 Error and fault handling

46.3.3.3 Response to received invalid frame sequences

Insert the following new text at the end of 46.3.3.3:

To support 2.5GBASE-X compatibility with a 1000BASE-X PCS/PMA running 2.5 times faster as described in Annex 127A, a 2.5 Gb/s MAC/RS implementation connected to a 2.5GBASE-X PHY is required to support an SFD received on either lane 2 or lane 3.

69. Introduction to Ethernet operation over electrical backplanes

69.1 Overview

69.1.1 Scope

Change the first sentence of the second paragraph of 69.1.1 as shown:

Backplane Ethernet supports the IEEE 802.3 full duplex MAC operating at 1000 Mb/s, 2.5 Gb/s, 5 Gb/s, 10 Gb/s, 25 Gb/s, 40 Gb/s, or 100 Gb/s providing a bit error ratio (BER) better than or equal to 10^{-12} at the MAC/PLS service interface.

Insert the following new lines after the 1000BASE-KX line in the list after the second paragraph of 69.1.1:

- 2.5GBASE-KX for 2.5 Gb/s operation over a single lane
- 5GBASE-KR for 5 Gb/s operation over a single lane

69.1.2 Relationship of Backplane Ethernet to the ISO OSI reference model

Change the first paragraph of 69.1.2 as shown:

Backplane Ethernet couples the IEEE 802.3 MAC to a family of Physical Layers defined for operation over electrical backplanes. The relationships among Backplane Ethernet, the IEEE 802.3 MAC, and the ISO Open System Interconnection (OSI) reference model are shown in [Figure 69-1](#), [Figure 69-2](#), ~~and~~ [Figure 69-3](#), ~~and~~ [Figure 69-4](#).

Insert the new figure on the next page (Figure 69-4) after Figure 69-3.

Change list item i) in the lettered list of 69.1.2 as shown:

- i) The MDIs for 1000BASE-KX, 2.5GBASE-KX, 5GBASE-KR, 10GBASE-KR, 25GBASE-KR, and 25GBASE-KR-S use a serial data path while the MDIs for 10GBASE-KX4, 40GBASE-KR4, 100GBASE-KR4, and 100GBASE-KP4 use a four-lane data path.

IEEE Std 802.3cb-2018
IEEE Standard for Ethernet—Amendment 1: Physical Layer Specifications and Management Parameters
for 2.5 Gb/s and 5 Gb/s Operation over Backplane




Figure 69-4—Architectural positioning of 2.5 Gb/s and 5 Gb/s Backplane Ethernet

69.2 Summary of Backplane Ethernet Sublayers

69.2.3 Physical Layer signaling systems

Insert the following new paragraphs after the first paragraph (“Backplane Ethernet extends”) in 69.2.3:

Backplane Ethernet also extends the family of 2.5GBASE-X Physical Layer signaling systems to include 2.5GBASE-KX. This embodiment specifies operation at 2.5 Gb/s over two differential, controlled impedance pairs of traces (one pair for transmit, one pair for receive). This system employs the 2.5GBASE-X PCS and PMA as defined in Clause 127. The 2.5GBASE-KX PMD is defined in Clause 128.

Backplane Ethernet also extends the family of 5GBASE-R Physical Layer signaling systems to include the 5GBASE-KR. This embodiment specifies 5 Gb/s operation over two differential, controlled impedance pairs of traces (one pair for transmit, one pair for receive). This system employs the 5GBASE-R PCS and PMA as defined in Clause 129. The 5GBASE-KR PMD is defined in Clause 130.

Change the last paragraph in 69.2.3 as shown:

Table 69-1, Table 69-1a, Table 69-2, and Table 69-3 specify the correlation between nomenclature and clauses. A complete implementation conforming to one or more nomenclatures meets the requirements of the corresponding clauses.

Insert the following new table (Table 69–1a) after Table 69-1:

Table 69–1a—Nomenclature and clause correlation for 2.5 Gb/s and 5 Gb/s Backplane Ethernet Physical Layers

Nomenclature	Clause							
	46		73	78	127	128	129	130
	RS	XGMII	Auto-Negotiation	Energy-Efficient Ethernet (EEE)	2.5GBASE-X PCS/PMA	2.5GBASE-KX PMD	5GBASE-R PCS/PMA	5GBASE-KR PMD
2.5GBASE-KX	M ^a	O ^a	M	O	M	M		
5GBASE-KR	M	O	M	O			M	M

^aO = Optional, M = Mandatory

69.3 Delay constraints

Insert the following new paragraph after the third paragraph (“Table 69-5”) of 69.3:

For 2.5GBASE-KX, normative delay specifications may be found in 127.5 and 128.4. For 5GBASE-KR, normative delay specifications may be found in 129.5 and 130.4. They are also referenced in 125.3.

69.5 Protocol implementation conformance statement (PICS) proforma

Change the first paragraph of 69.5 as shown:

The supplier of a protocol implementation that is claimed to conform to any part of IEEE Std 802.3, [Clause 70](#) through [Clause 74](#), [Clause 84](#), [Clause 91](#), [Clause 93](#), [Clause 94](#), [Clause 108](#), [Clause 111](#), [Clause 128](#), [Clause 130](#), and related annexes demonstrates compliance by completing a protocol implementation conformance statement (PICS) proforma.

70. Physical Medium Dependent sublayer and baseband medium, type 1000BASE-KX

70.5 PMD MDIO function mapping

Change Table 70–2 as shown:

Table 70–2—MDIO/PMD control variable mapping

MDIO control variable	PMA/PMD register name	Register/ bit number	PMD control variable
Reset	Control register 1	1.0.15	PMD_reset
PMD Transmit Disable	1000BASE-KX/2.5GBASE-KX control register	1.160.0	PMD_transmit_disable

Change Table 70–3 as shown:

Table 70–3—MDIO/PMD status variable mapping

MDIO status variable	PMA/PMD register name	Register/ bit number	PMD status variable
Fault	Status register 1	1.1.7	PMD_fault
Transmit fault ability	1000BASE-KX/2.5GBASE-KX status register	1.161.13	PMD_Transmit_fault_ability
Receive fault ability	1000BASE-KX/2.5GBASE-KX status register	1.161.12	PMD_Receive_fault_ability
Transmit fault	1000BASE-KX/2.5GBASE-KX status register	1.161.11	PMD_transmit_fault
Receive fault	1000BASE-KX/2.5GBASE-KX status register	1.161.10	PMD_receive_fault
PMD transmit disable ability	1000BASE-KX/2.5GBASE-KX status register	1.161.8	PMD_transmit_disable_ability
Signal detect from PMD	1000BASE-KX/2.5GBASE-KX status register	1.161.0	PMD_signal_detect

73. Auto-Negotiation for backplane and copper cable assembly

73.2 Relationship to the ISO/IEC Open Systems Interconnection (OSI) reference model

Replace Figure 73–1 with the following figure (which adds 2.5 Gb/s and 5 Gb/s in the medium rates):




Figure 73–1—Location of Auto-Negotiation function within the ISO/IEC OSI reference model

73.6 Link codeword encoding

73.6.4 Technology Ability Field

Change Table 73–4 by adding the following new rows for A11 and A12 in numeric order and revising the reserved row as shown (unchanged rows not shown):

Table 73–4—Technology Ability Field encoding

Bit	Technology
A11	2.5GBASE-KX
A12	5GBASE-KR
A11 A13 through A22	Reserved for future technology

Change the last paragraph of 73.6.4 as shown:

The fields A[22:13+4] are reserved for future use. Reserved fields shall be sent as zero and ignored on receive.

73.7 Receive function requirements

73.7.4 Arbitration function requirements

73.7.4.1 Parallel Detection function

Change the first two paragraphs of 73.7.4.1 as shown:

The local device detects a link partner that supports Auto-Negotiation by DME page detection. The Parallel Detection function allows detection of link partners that support 1000BASE-KX, 2.5GBASE-KX, and 10GBASE-KX4 but have disabled Auto-Negotiation, and detection of legacy devices that can interoperate with 1000BASE-KX, 2.5GBASE-KX, and 10GBASE-KX4 devices but do not provide [Clause 73](#) Auto-Negotiation.

A local device shall provide Parallel Detection for 1000BASE-KX, 2.5GBASE-KX, and 10GBASE-KX4 if it supports those PHYs. Additionally, parallel detection may be used for 10GBASE-CX4. Parallel detection of 10GBASE-CX4 will be indicated by the setting of the Negotiated Port Type to “10GBASE-KX4 or 10GBASE-CX4” in the management register bit 7.48.2. The means to distinguish between 10GBASE-KX4 and 10GBASE-CX4 is implementation dependent. Parallel Detection shall be performed by directing the MDI receive activity to the PHY. This detection may be done in sequence between detection of DME pages and detection of each supported PHY. If at least one of the 1000BASE-KX, 2.5GBASE-KX, or 10GBASE-KX4 establishes link_status=OK, the LINK STATUS CHECK state is entered and the autoneg_wait timer is started. If exactly one link_status=OK indication is present when the autoneg_wait timer expires, then Auto-Negotiation shall set link_control=ENABLE for the PHY indicating link_status=OK. If a PHY is enabled, the Arbitration function shall set link_control=DISABLE to all other PHYs and indicate that Auto-Negotiation has completed. On transition to the AN GOOD CHECK state from the LINK STATUS CHECK state, the Parallel Detection function shall set the bit in the AN LP Base Page ability registers (see [45.2.7.7](#)) corresponding to the technology detected by the Parallel Detection function.

73.7.6 Priority Resolution function

Change Table 73-5 by adding the following new rows for Priority 11 and Priority 12 in numeric order and revising the last row as shown (unchanged rows not shown):

Table 73-5—Priority Resolution

Priority	Technology	Capability
<u>11</u>	<u>5GBASE-KR</u>	<u>5 Gb/s 1 lane</u>
<u>12</u>	<u>2.5GBASE-KX</u>	<u>2.5 Gb/s 1 lane</u>
4+13	1000BASE-KX	1 Gb/s 1 lane, lowest priority

73.10 State diagrams and variable definitions

73.10.1 State diagram variables

Insert the following new entries (for 2.5GKX and 5GKR) after the entry for 1GKX in the variable list after the first paragraph ('A variable with "[x]"') in 73.10.1:

2.5GKX; represents the 2.5GBASE-KX PMD.
5GKR; represents the 5GBASE-KR PMD.

Change the PD entry in the variable list after the first paragraph ('A variable with "[x]"') in 73.10.1 as shown:

PD; represents all of the following that are present: 1000BASE-KX PMD, 2.5GBASE-KX PMD, and 10GBASE-KX4 (or 10GBASE-CX4) PMD.

Change the single_link_ready entry in the list after the third paragraph ('Variables of the form "mr_x",') in 73.10.1 as shown:

single_link_ready
Status indicating that an_receive_idle = true and only one of the following indications is being received:

- 1) link_status_[1GKX] = OK
- 2) link_status_[2.5GKX] = OK
- 3) link_status_[5GKR] = OK
- ~~4~~2) link_status_[10GKX4] = OK
- ~~5~~3) link_status_[10GKR] = OK
- ~~6~~4) link_status_[25GR] = OK
- ~~7~~5) link_status_[40GKR4] = OK
- ~~8~~6) link_status_[40GCR4] = OK
- ~~9~~7) link_status_[100GCR10] = OK
- ~~10~~8) link_status_[100GKP4] = OK
- ~~11~~9) link_status_[100GKR4] = OK
- ~~12~~40) link_status_[100GCR4] = OK

73.10.2 State diagram timers

Change the two link_fail_inhibit_timer rows in Table 73-7 as shown (unchanged rows not shown):

Table 73-7—Timer min/max value summary

Parameter	Min	Value and tolerance	Max	Units
link_fail_inhibit_timer (when the link is not neither 1000BASE-KX, 2.5GBASE-KX, 5GBASE-KR, or not 10GBASE-KX4)	500		510	ms
link_fail_inhibit_timer (when the link is 1000BASE-KX, <u>2.5GBASE-KX</u> , <u>5GBASE-KR</u> , or 10GBASE-KX4)	40		50	ms