

INTERNATIONAL
STANDARD

ISO/
IEC/IEEE
8802-3

Third edition
2021-02

AMENDMENT 2
2021-12

**Telecommunications and exchange
between information technology
systems — Requirements for local and
metropolitan area networks —**

**Part 3:
Standard for Ethernet**

**AMENDMENT 2: Physical layer and
management parameters for power over
Ethernet over 4 pairs**

*Télécommunications et échange entre systèmes informatiques —
Exigences pour les réseaux locaux et métropolitains —*

Partie 3: Norme pour Ethernet

*AMENDEMENT 2: Couche physique et paramètres de gestion pour la
puissance par ethernet sur 4 paires*



Reference number
ISO/IEC/IEEE 8802-3:2021/Amd.2:2021(E)

Documents
Document Sharing Hub
© IEEE 2019



COPYRIGHT PROTECTED DOCUMENT

© IEEE 2019

All rights reserved. Unless otherwise specified, or required in the context of its implementation, no part of this publication may be reproduced or utilized otherwise in any form or by any means, electronic or mechanical, including photocopying, or posting on the internet or an intranet, without prior written permission. Permission can be requested from IEEE at the address below.

Institute of Electrical and Electronics Engineers, Inc
3 Park Avenue, New York
NY 10016-5997, USA

Email: stds.ipr@ieee.org
Website: www.ieee.org

Published in Switzerland

Foreword

ISO (the International Organization for Standardization) and IEC (the International Electrotechnical Commission) form the specialized system for worldwide standardization. National bodies that are members of ISO or IEC participate in the development of International Standards through technical committees established by the respective organization to deal with particular fields of technical activity. ISO and IEC technical committees collaborate in fields of mutual interest. Other international organizations, governmental and non-governmental, in liaison with ISO and IEC, also take part in the work.

The procedures used to develop this document and those intended for its further maintenance are described in the ISO/IEC Directives, Part 1. In particular, the different approval criteria needed for the different types of ISO/IEC documents should be noted.

IEEE Standards documents are developed within the IEEE Societies and the Standards Coordinating Committees of the IEEE Standards Association (IEEE-SA) Standards Board. The IEEE develops its standards through a consensus development process, approved by the American National Standards Institute, which brings together volunteers representing varied viewpoints and interests to achieve the final product. Volunteers are not necessarily members of the Institute and serve without compensation. While the IEEE administers the process and establishes rules to promote fairness in the consensus development process, the IEEE does not independently evaluate, test, or verify the accuracy of any of the information contained in its standards.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO and IEC shall not be held responsible for identifying any or all such patent rights. Details of any patent rights identified during the development of the document will be in the Introduction and/or on the ISO list of patent declarations received (see www.iso.org/patents) or the IEC list of patent declarations received (see patents.iec.ch).

Any trade name used in this document is information given for the convenience of users and does not constitute an endorsement.

For an explanation of the voluntary nature of standards, the meaning of ISO specific terms and expressions related to conformity assessment, as well as information about ISO's adherence to the World Trade Organization (WTO) principles in the Technical Barriers to Trade (TBT), see www.iso.org/iso/foreword.html. In the IEC, see www.iec.ch/understanding-standards.

ISO/IEC/IEEE 8802-3:2021/Amd.2 was prepared by the LAN/MAN of the IEEE Computer Society (as IEEE Std 802.3bt-2018) and drafted in accordance with its editorial rules. It was adopted, under the “fast-track procedure” defined in the Partner Standards Development Organization cooperation agreement between ISO and IEEE, by Joint Technical Committee ISO/IEC JTC 1, *Information technology*, Subcommittee SC 6, *Telecommunications and information exchange between systems*.

A list of all parts in the ISO/IEC/IEEE 8802 series can be found on the ISO and IEC websites.

Any feedback or questions on this document should be directed to the user's national standards body. A complete listing of these bodies can be found at www.iso.org/members.html and www.iec.ch/national-committees.

IEEE Standard for Ethernet

Amendment 2: Physical Layer and Management Parameters for Power over Ethernet over 4 Pairs

Sponsor

**LAN/MAN Standards Committee
of the
IEEE Computer Society**

Approved 27 September 2018

IEEE-SA Standards Board

Abstract: The maximum Powered Device (PD) power available is increased by this amendment to IEEE Std 802.3-2018 by utilizing all four pairs in the specified structured wiring plant. This represents a substantial change to the capabilities of Ethernet with standardized power. The power classification information exchanged during negotiation is extended to allow meaningful power management capability. These enhancements solve the problem of higher power and more efficient standardized Power over Ethernet (PoE) delivery systems.

Keywords: amendment, DTE power via MDI, Ethernet, IEEE 802.3™, IEEE 802.3bt™, PoE, Power over Ethernet

*This standard is dedicated to the memory
of our friend and colleague Martin Patoka.*

The Institute of Electrical and Electronics Engineers, Inc.
3 Park Avenue, New York, NY 10016-5997, USA

Copyright © 2019 by The Institute of Electrical and Electronics Engineers, Inc.
All rights reserved. Published 31 January 2019. Printed in the United States of America.

IEEE and 802 are registered trademarks in the U.S. Patent & Trademark Office, owned by The Institute of Electrical and Electronics Engineers, Incorporated.

National Electrical Code, NEC, and NFPA 70 are registered trademarks in the U.S. Patent & Trademark Office, owned by the National Fire Protection Association.

PDF: ISBN 978-1-5044-5276-2 STD23390
Print: ISBN 978-1-5044-5277-9 STDPD23390

IEEE prohibits discrimination, harassment and bullying.

For more information, visit <http://www.ieee.org/web/aboutus/whatis/policies/p9-26.html>.

No part of this publication may be reproduced in any form, in an electronic retrieval system or otherwise, without the prior written permission of the publisher.

Important Notices and Disclaimers Concerning IEEE Standards Documents

IEEE documents are made available for use subject to important notices and legal disclaimers. These notices and disclaimers, or a reference to this page, appear in all standards and may be found under the heading “Important Notices and Disclaimers Concerning IEEE Standards Documents.” They can also be obtained on request from IEEE or viewed at <http://standards.ieee.org/ipr/disclaimers.html>.

Notice and Disclaimer of Liability Concerning the Use of IEEE Standards Documents

IEEE Standards documents (standards, recommended practices, and guides), both full-use and trial-use, are developed within IEEE Societies and the Standards Coordinating Committees of the IEEE Standards Association (“IEEE-SA”) Standards Board. IEEE (“the Institute”) develops its standards through a consensus development process, approved by the American National Standards Institute (“ANSI”), which brings together volunteers representing varied viewpoints and interests to achieve the final product. IEEE Standards are documents developed through scientific, academic, and industry-based technical working groups. Volunteers in IEEE working groups are not necessarily members of the Institute and participate without compensation from IEEE. While IEEE administers the process and establishes rules to promote fairness in the consensus development process, IEEE does not independently evaluate, test, or verify the accuracy of any of the information or the soundness of any judgments contained in its standards.

IEEE Standards do not guarantee or ensure safety, security, health, or environmental protection, or ensure against interference with or from other devices or networks. Implementers and users of IEEE Standards documents are responsible for determining and complying with all appropriate safety, security, environmental, health, and interference protection practices and all applicable laws and regulations.

IEEE does not warrant or represent the accuracy or content of the material contained in its standards, and expressly disclaims all warranties (express, implied and statutory) not included in this or any other document relating to the standard, including, but not limited to, the warranties of: merchantability; fitness for a particular purpose; non-infringement; and quality, accuracy, effectiveness, currency, or completeness of material. In addition, IEEE disclaims any and all conditions relating to: results; and workmanlike effort. IEEE standards documents are supplied “AS IS” and “WITH ALL FAULTS.”

Use of an IEEE standard is wholly voluntary. The existence of an IEEE standard does not imply that there are no other ways to produce, test, measure, purchase, market, or provide other goods and services related to the scope of the IEEE standard. Furthermore, the viewpoint expressed at the time a standard is approved and issued is subject to change brought about through developments in the state of the art and comments received from users of the standard.

In publishing and making its standards available, IEEE is not suggesting or rendering professional or other services for, or on behalf of, any person or entity nor is IEEE undertaking to perform any duty owed by any other person or entity to another. Any person utilizing any IEEE Standards document, should rely upon his or her own independent judgment in the exercise of reasonable care in any given circumstances or, as appropriate, seek the advice of a competent professional in determining the appropriateness of a given IEEE standard.

IN NO EVENT SHALL IEEE BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO: PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE PUBLICATION, USE OF, OR RELIANCE UPON ANY STANDARD, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE AND REGARDLESS OF WHETHER SUCH DAMAGE WAS FORESEEABLE.

Translations

The IEEE consensus development process involves the review of documents in English only. In the event that an IEEE standard is translated, only the English version published by IEEE should be considered the approved IEEE standard.

Official statements

A statement, written or oral, that is not processed in accordance with the IEEE-SA Standards Board Operations Manual shall not be considered or inferred to be the official position of IEEE or any of its committees and shall not be considered to be, or be relied upon as, a formal position of IEEE. At lectures, symposia, seminars, or educational courses, an individual presenting information on IEEE standards shall make it clear that his or her views should be considered the personal views of that individual rather than the formal position of IEEE.

Comments on standards

Comments for revision of IEEE Standards documents are welcome from any interested party, regardless of membership affiliation with IEEE. However, IEEE does not provide consulting information or advice pertaining to IEEE Standards documents. Suggestions for changes in documents should be in the form of a proposed change of text, together with appropriate supporting comments. Since IEEE standards represent a consensus of concerned interests, it is important that any responses to comments and questions also receive the concurrence of a balance of interests. For this reason, IEEE and the members of its societies and Standards Coordinating Committees are not able to provide an instant response to comments or questions except in those cases where the matter has previously been addressed. For the same reason, IEEE does not respond to interpretation requests. Any person who would like to participate in revisions to an IEEE standard is welcome to join the relevant IEEE working group.

Comments on standards should be submitted to the following address:

Secretary, IEEE-SA Standards Board
445 Hoes Lane
Piscataway, NJ 08854 USA

Laws and regulations

Users of IEEE Standards documents should consult all applicable laws and regulations. Compliance with the provisions of any IEEE Standards document does not imply compliance to any applicable regulatory requirements. Implementers of the standard are responsible for observing or referring to the applicable regulatory requirements. IEEE does not, by the publication of its standards, intend to urge action that is not in compliance with applicable laws, and these documents may not be construed as doing so.

Copyrights

IEEE draft and approved standards are copyrighted by IEEE under U.S. and international copyright laws. They are made available by IEEE and are adopted for a wide variety of both public and private uses. These include both use, by reference, in laws and regulations, and use in private self-regulation, standardization, and the promotion of engineering practices and methods. By making these documents available for use and adoption by public authorities and private users, IEEE does not waive any rights in copyright to the documents.

Photocopies

Subject to payment of the appropriate fee, IEEE will grant users a limited, non-exclusive license to photocopy portions of any individual standard for company or organizational internal use or individual, non-commercial use only. To arrange for payment of licensing fees, please contact Copyright Clearance Center, Customer Service, 222 Rosewood Drive, Danvers, MA 01923 USA; +1 978 750 8400. Permission to photocopy portions of any individual standard for educational classroom use can also be obtained through the Copyright Clearance Center.

Updating of IEEE Standards documents

Users of IEEE Standards documents should be aware that these documents may be superseded at any time by the issuance of new editions or may be amended from time to time through the issuance of amendments, corrigenda, or errata. An official IEEE document at any point in time consists of the current edition of the document together with any amendments, corrigenda, or errata then in effect.

Every IEEE standard is subjected to review at least every ten years. When a document is more than ten years old and has not undergone a revision process, it is reasonable to conclude that its contents, although still of some value, do not wholly reflect the present state of the art. Users are cautioned to check to determine that they have the latest edition of any IEEE standard.

In order to determine whether a given document is the current edition and whether it has been amended through the issuance of amendments, corrigenda, or errata, visit the IEEE-SA Website at <http://ieeexplore.ieee.org> or contact IEEE at the address listed previously. For more information about the IEEE SA or IEEE's standards development process, visit the IEEE-SA Website at <http://standards.ieee.org>.

Errata

Errata, if any, for all IEEE standards can be accessed on the IEEE-SA Website at the following URL: <http://standards.ieee.org/findstds/errata/index.html>. Users are encouraged to check this URL for errata periodically.

Patents

Attention is called to the possibility that implementation of this standard may require use of subject matter covered by patent rights. By publication of this standard, no position is taken by the IEEE with respect to the existence or validity of any patent rights in connection therewith. If a patent holder or patent applicant has filed a statement of assurance via an Accepted Letter of Assurance, then the statement is listed on the IEEE-SA Website at <http://standards.ieee.org/about/sasb/patcom/patents.html>. Letters of Assurance may indicate whether the Submitter is willing or unwilling to grant licenses under patent rights without compensation or under reasonable rates, with reasonable terms and conditions that are demonstrably free of any unfair discrimination to applicants desiring to obtain such licenses.

Essential Patent Claims may exist for which a Letter of Assurance has not been received. The IEEE is not responsible for identifying Essential Patent Claims for which a license may be required, for conducting inquiries into the legal validity or scope of Patents Claims, or determining whether any licensing terms or conditions provided in connection with submission of a Letter of Assurance, if any, or in any licensing agreements are reasonable or non-discriminatory. Users of this standard are expressly advised that determination of the validity of any patent rights, and the risk of infringement of such rights, is entirely their own responsibility. Further information may be obtained from the IEEE Standards Association.

Participants

The following individuals were officers and members of the IEEE 802.3 Working Group at the beginning of the IEEE P802.3bt Working Group ballot.

David J. Law, *IEEE 802.3 Working Group Chair*
Adam Healey, *IEEE 802.3 Working Group Vice-Chair*
Pete Anslow, *IEEE 802.3 Working Group Secretary*
Steven B. Carlson, *IEEE 802.3 Working Group Executive Secretary*
Valerie Maguire, *IEEE 802.3 Working Group Treasurer*

Chad Jones, *IEEE P802.3bt DTE Power via MDI over 4-Pair Task Force Chair*
Koussalya Balasubramanian¹, *IEEE P802.3bt DTE Power via MDI over 4-Pair Task Force
Chief Editor (1st phase)*
Lennart Yseboodt, *IEEE P802.3bt DTE Power via MDI over 4-Pair Task Force
Chief Editor (2nd phase)*

David Abramson, *IEEE P802.3bt DTE Power via MDI over 4-Pair Task Force Comment Editor*

Justin Abbott
Shadi Abughazaleh
Mohammad Ahmed
Eric Baden
Amrik Bains
Thananya Baldwin
Denis Beaudoin
Christian Beia
Michael Bennett
Vipul Bhatt
William Bliss
Brad Booth
Martin Bouda
Ralf-Peter Braun
Theodore Brillhart
Paul Brooks
Alan Brown
Matthew Brown
Chris Bullock
Jairo Bustos Heredia
Adrian Butter
Francesco Caggioni
Anthony Calbone
Clark Carty
Craig Chabot
Geoffrey Chacon Simon
Mandeep Chadha
David Chalupsky
Jacky Chang
Xin Chang
Ahmad Chini
Keng Hua Chuang
Christopher R. Cole
John D'Ambrosia

Yair Darshan
Piers Dawe
Fred Dawson
Wael Diab
Eric DiBiaso
John Dillard
Daniel Dillow
Thuyen Dinh
Curtis Donahue
Dan Dove
Mike Dudek
David Dwelley
Frank Effenberger
Hesham Elbakoury
David Estes
John Ewen
Ramin Farjad
Shahar Feldman
James Fife
Alan Flatman
Matthias Fritzsche
Richard Frosch
Andrew Gardner
Claude Gauthier
Ali Ghiasi
Joel Goergen
Volker Goetzfried
Zhigang Gong
Steven Gorshe
Robert Grow
Mark Gustlin
Marek Hajduczenia
Takehiro Hayashi
Yasuo Hidaka

Rita Horner
Bernd Horrmeyer
Victor Hou
Yasuhiro Hyakutake
Hideki Isono
Tom Issenhuth
Kenneth Jackson
Andrew Jimenez
Peter Jones
Manabu Kagami
Upen Kareti
Keisuke Kawahara
Yasuaki Kawatsu
Michael Kelsen
Scott Kipp
Michael Klempa
Curtis Knittle
Shigeru Kobayashi
Daniel Koehler
Paul Kolesar
Tom Kolze
Glen Kramer
Hans Lackner
Jeffrey Lapak
Mark Laubach
Han Hyub Lee
David Lewis
Jon Lewis
Mike Peng Li
Jane Lim
Dekun Liu
Hai-Feng Liu
William Lo
Miklos Lukacs
Kent Lusted

¹Not a member of the IEEE 802.3 working group at the beginning of the working group ballot.

Jeffery Maki
 David Malicoat
 Yonatan Malkiman
 Arthur Marris
 Takeo Masuda
 Erdem Matoglu
 Naoki Matsuda
 Mick McCarthy
 Brett McClellan
 Thomas McDermott
 John McDonough
 Larry McMillan
 Richard Mei
 Richard Mellitz
 Bryan Moffitt
 Ardeshir Mohammadian
 Paul Mooney
 Dale Murray
 Henry Muyschondt
 James Nadolny
 Edward Nakamoto
 Gary Nicholl
 Kevin Noll
 Mark Nowell
 David Ofelt
 Thomas Palkert
 Hui Pan
 Sessa Panguluri
 Vasu Parthasarathy
 Petar Pepeljugin
 Gerald Pepper
 Ruben Perez De Aranda Alonso
 Michael Peters
 Phong Pham

Jean Picard
 William Powell
 Rick Rabinovich
 Adeo Ran
 Alon Regev
 Duane Remein
 Victor Renteria
 Christopher Roth
 Salvatore Rotolo
 Toshiaki Sakai
 Jorge Salinger
 Sam Sambasivan
 Edward Sayre
 Dieter Schicketanz
 Fred Schindler
 Hossein Sedarat
 Naoshi Serizawa
 Masood Shariff
 Ramin Shirani
 Tom Skaar
 Jeff Slavick
 Daniel Smith
 Scott Sommers
 Yoshiaki Sone
 Tom Souvignier
 Peter Stassar
 Heath Stewart
 Robert Stone
 David Stover
 Junqing Sun
 Ken-Ichi Suzuki
 Steve Swanson
 Andre Szczepanek
 William Szeto

Bharat Tailor
 Takayuki Tajima
 Satoshi Takahashi
 Kohichi Tamura
 Brian Teipen
 Geoffrey Thompson
 Pirooz Tooyserkani
 Albert Tretter
 Stephen Trowbridge
 Yoshihiro Tsukamoto
 Ed Ulrichs
 Alexander Umnov
 Sterling A. Vaden
 Stefano Valle
 Paul Vanderlaan
 Robert Wagner
 Dylan Walker
 Haifei Wang
 Roy Wang
 Tongtong Wang
 Xinyuan Wang
 Matthias Wendt
 Oded Wertheim
 Natalie Wienckowski
 Ludwig Winkel
 Peter Wu
 Dayin Xu
 Yu Xu
 Jun Yi
 Hayato Yuki
 Andrew Zambell
 Yan Zhuang
 George Zimmerman

The following members of the individual balloting committee voted on this amendment. Balloters may have voted for approval, disapproval, or abstention.

David Abramson	Yasuhiro Hyakutake	Adee Ran
Shadi Abughazaleh	Noriyuki Ikeuchi	R. K. Rannow
Iwan Adhicandra	Atsushi Ito	Maximilian Riegel
Andrea Agnes	Raj Jain	Robert Robinson
Thomas Alexander	Sang Kwon Jeong	Benjamin Rolfe
Dale Amason	Chad Jones	Veselin Skendzic
Peter Anslow	Peter Jones	Daniel Smith
John Ballingall	Piotr Karocki	Dorothy Stanley
Christian Boiger	Stuart J. Kerry	Thomas Starai
Ralf-Peter Braun	Yongbum Kim	Heath Stewart
Nancy Bravin	Mark Laubach	David Stover
Theodore Brillhart	David J. Law	Walter Struppler
Demetrio Bucaneg	Hyeong Ho Lee	Mitsutoshi Sugawara
Chris Bullock	Joris Lemahieu	Kohichi Tamura
Jairo Bustos Heredia	Jon Lewis	Geoffrey Thompson
William Byrd	Shen Loh	Nathan Tracy
Steven B. Carlson	Miklos Lukacs	David Tremblay
Juan Carreon	Elvis Maculuba	Mark-Rene Uchida
Clark Carty	Valerie Maguire	Alexander Umnov
Mandeep Chadha	Jeffery Maki	Dmitri Varsanofiev
Keith Chow	Jeffery Masters	George Vlantis
Keng Hua Chuang	Michael Maytum	Khurram Waheed
Ian Crayford	Mick McCarthy	Dylan Walker
Sourav Dutta	Brett McClellan	Lisa Ward
Avraham Freedman	Thomas McDermott	Keith Waters
Matthias Fritsche	Richard Mellitz	Stephen Webb
Yukihiro Fujimoto	Tremont Miao	Matthias Wendt
Joel Goergen	Charles Moorwood	Andreas Wolf
Zhigang Gong	Rick Murphy	Peter Wu
Eric W. Gray	Satoshi Obara	Dayin Xu
Randall Groves	Thomas Palkert	Lennart Yseboodt
Adam Healey	Bansi Patel	Oren Yuen
Marco Hernandez	Arkadiy Peker	Andrew Zambell
David Hess	Michael Peters	Zhen Zhou
Werner Hoelzl	Jean Picard	George Zimmerman
Rita Horner	Rick Pimpinella	Pavel Zivny

When the IEEE-SA Standards Board approved this amendment on 27 September 2018, it had the following membership:

Jean-Philippe Faure, *Chair*
Gary Hoffman, *Vice Chair*
John D. Kulick, *Past Chair*
Konstantinos Karachalios, *Secretary*

Ted Burse	Xiaohui Liu	Robby Robson
Guido R. Hiertz	Kevin Lu	Dorothy Stanley
Christel Hunter	Daleep Mohla	Mehmet Ulema
Joseph L. Koepfinger*	Andrew Myles	Phil Wennblom
Thomas Koshy	Paul Nikolich	Philip Winston
Hung Ling	Ronald C. Petersen	Howard Wolfman
Dong Liu	Annette D. Reilly	Jingyi Zhou

*Member Emeritus

Introduction

This introduction is not part of IEEE Std 802.3bt-2018, IEEE Standard for Ethernet—Amendment 2: Physical Layer and Management Parameters for Power over Ethernet over 4 Pairs.

IEEE Std 802.3™ was first published in 1985. Since the initial publication, many projects have added functionality or provided maintenance updates to the specifications and text included in the standard. Each IEEE 802.3 project/amendment is identified with a suffix (e.g., IEEE Std 802.3ba™-2010).

The half duplex Media Access Control (MAC) protocol specified in IEEE Std 802.3-1985 is Carrier Sense Multiple Access with Collision Detection (CSMA/CD). This MAC protocol was key to the experimental Ethernet developed at Xerox Palo Alto Research Center, which had a 2.94 Mb/s data rate. Ethernet at 10 Mb/s was jointly released as a public specification by Digital Equipment Corporation (DEC), Intel and Xerox in 1980. Ethernet at 10 Mb/s was approved as an IEEE standard by the IEEE Standards Board in 1983 and subsequently published in 1985 as IEEE Std 802.3-1985. Since 1985, new media options, new speeds of operation, and new capabilities have been added to IEEE Std 802.3. A full duplex MAC protocol was added in 1997.

Some of the major additions to IEEE Std 802.3 are identified in the marketplace with their project number. This is most common for projects adding higher speeds of operation or new protocols. For example, IEEE Std 802.3u™ added 100 Mb/s operation (also called Fast Ethernet), IEEE Std 802.3z added 1000 Mb/s operation (also called Gigabit Ethernet), IEEE Std 802.3ae added 10 Gb/s operation (also called 10 Gigabit Ethernet), IEEE Std 802.3ah™ specified access network Ethernet (also called Ethernet in the First Mile) and IEEE Std 802.3ba added 40 Gb/s operation (also called 40 Gigabit Ethernet) and 100 Gb/s operation (also called 100 Gigabit Ethernet). These major additions are all now included in and are superseded by IEEE Std 802.3-2018 and are not maintained as separate documents.

At the date of publication for IEEE Std 802.3bt-2018, IEEE Std 802.3 was composed of the following documents:

IEEE Std 802.3-2018

Section One—Includes Clause 1 through Clause 20 and Annex A through Annex H and Annex 4A. Section One includes the specifications for 10 Mb/s operation and the MAC, frame formats and service interfaces used for all speeds of operation.

Section Two—Includes Clause 21 through Clause 33 and Annex 22A through Annex 33E. Section Two includes management attributes for multiple protocols and speed of operation as well as specifications for providing power over twisted pair cabling for multiple operational speeds. It also includes general information on 100 Mb/s operation as well as most of the 100 Mb/s Physical Layer specifications.

Section Three—Includes Clause 34 through Clause 43 and Annex 36A through Annex 43C. Section Three includes general information on 1000 Mb/s operation as well as most of the 1000 Mb/s Physical Layer specifications.

Section Four—Includes Clause 44 through Clause 55 and Annex 44A through Annex 55B. Section Four includes general information on 10 Gb/s operation as well as most of the 10 Gb/s Physical Layer specifications.

Section Five—Includes Clause 56 through Clause 77 and Annex 57A through Annex 76A. Clause 56 through Clause 67 and Clause 75 through Clause 77, as well as associated annexes, specify subscriber access and other Physical Layers and sublayers for operation from 512 kb/s to 10 Gb/s, and defines

services and protocol elements that enable the exchange of IEEE Std 802.3 format frames between stations in a subscriber access network. Clause 68 specifies a 10 Gb/s Physical Layer specification. Clause 69 through Clause 74 and associated annexes specify Ethernet operation over electrical backplanes at speeds of 1000 Mb/s and 10 Gb/s.

Section Six—Includes Clause 78 through Clause 95 and Annex 83A through Annex 93C. Clause 78 specifies Energy-Efficient Ethernet. Clause 79 specifies IEEE 802.3 Organizationally Specific Link Layer Discovery Protocol (LLDP) type, length, and value (TLV) information elements. Clause 80 through Clause 95 and associated annexes include general information on 40 Gb/s and 100 Gb/s operation as well the 40 Gb/s and 100 Gb/s Physical Layer specifications. Clause 90 specifies Ethernet support for time synchronization protocols.

Section Seven—Includes Clause 96 through Clause 115 and Annex 97A through Annex 115A. Clause 96 through Clause 98, Clause 104, and associated annexes, specify Physical Layers and optional features for 100 Mb/s and 1000 Mb/s operation over a single twisted pair. Clause 100 through Clause 103, as well as associated annexes, specify Physical Layers for the operation of the EPON protocol over coaxial distribution networks. Clause 105 through Clause 114 and associated annexes include general information on 25 Gb/s operation as well as 25 Gb/s Physical Layer specifications. Clause 99 specifies a MAC merge sublayer for the interspersing of express traffic. Clause 115 and its associated annex specify a Physical Layer for 1000 Mb/s operation over plastic optical fiber.

Section Eight—Includes Clause 116 through Clause 126 and Annex 119A through Annex 120E. Clause 116 through Clause 124 and associated annexes include general information on 200 Gb/s and 400 Gb/s operation as well the 200 Gb/s and 400 Gb/s Physical Layer specifications. Clause 125 and Clause 126 include general information on 2.5 Gb/s and 5 Gb/s operation as well as 2.5 Gb/s and 5 Gb/s Physical Layer specifications.

IEEE Std 802.3cb™-2018

Amendment 1—This amendment includes changes to IEEE Std 802.3-2018 and its amendments, and adds Clause 127 through Clause 130, Annex 127A, Annex 128A, Annex 128B, and Annex 130A. This amendment adds new Physical Layers for operation at 2.5 Gb/s and 5 Gb/s over electrical backplanes.

IEEE Std 802.3bt-2018

Amendment 2—This amendment includes changes to IEEE Std 802.3-2018 and adds Clause 145, Annex 145A, Annex 145B, and Annex 145C. This amendment adds power delivery using all four pairs in the structured wiring plant, resulting in greater power being available to end devices. This amendment also allows for lower standby power consumption in end devices and adds a mechanism to better manage the available power budget.

A companion document, IEEE Std 802.3.1, describes Ethernet management information base (MIB) modules for use with the Simple Network Management Protocol (SNMP). IEEE Std 802.3.1 is updated to add management capability for enhancements to IEEE Std 802.3 after approval of those enhancements.

IEEE Std 802.3 will continue to evolve. New Ethernet capabilities are anticipated to be added within the next few years as amendments to this standard.

Contents

1.	Introduction.....	21
1.3	Normative references	21
1.4	Definitions	21
1.5	Abbreviations.....	22
14.	Twisted-pair medium attachment unit (MAU) and baseband medium, type 10BASE-T including type 10BASE-Te.....	23
14.3	MAU electrical specifications	23
14.3.1	MAU-to-MDI interface characteristics.....	23
14.3.1.1	Isolation requirement	23
25.	Physical Medium Dependent (PMD) sublayer and baseband medium, type 100BASE-TX.....	24
25.4	Specific requirements and exceptions.....	24
25.4.5	Change to 9.1.7, “Worst case droop of transformer”	24
25.4.6	Replacement of 8.4.1, “UTP isolation requirements”	24
25.4.7	Addition to 10.1, “Receiver”	24
25.6	Protocol implementation conformance statement (PICS) proforma for Clause 25, Physical Medium Dependent (PMD) sublayer and baseband medium, type 100BASE-TX	25
25.6.3	Major capabilities/options.....	25
25.6.3.1	DTE Power via MDI Power over Ethernet major capabilities/options	25
25.6.4	PICS proforma tables for the Physical Medium Dependent (PMD) sublayer and baseband medium, type 100BASE-TX.....	25
25.6.4.4	DTE Power via MDI Power over Ethernet compliance	25
30.	Management.....	26
30.2	Managed objects	26
30.2.2	Overview of managed objects.....	26
30.2.2.1	Text description of managed objects	26
30.2.3	Containment.....	26
30.2.5	Capabilities	27
30.9	Management for DTE Power via MDI Power over Ethernet	35
30.9.1	PSE managed object class.....	35
30.9.1.1	PSE attributes.....	35
30.9.1.1.2	aPSEAdminState.....	35
30.9.1.1.3	aPSEPowerPairsControlAbility	35
30.9.1.1.4	aPSEPowerPairs.....	35
30.9.1.1.5	aPSEPowerDetectionStatus	36
30.9.1.1.5a	aPSEPowerDetectionStatusA	36
30.9.1.1.5b	aPSEPowerDetectionStatusB.....	37
30.9.1.1.6	aPSEPowerClassification.....	37
30.9.1.1.6a	aPSEPowerClassificationA.....	38
30.9.1.1.6b	aPSEPowerClassificationB	38
30.9.1.1.7	aPSEInvalidSignatureCounter	39
30.9.1.1.7a	aPSEInvalidSignatureCounterA	39
30.9.1.1.7b	aPSEInvalidSignatureCounterB.....	39
30.9.1.1.8	aPSEPowerDeniedCounter	39
30.9.1.1.8a	aPSEPowerDeniedCounterA	40

30.9.1.1.8b	aPSEPowerDeniedCounterB	40
30.9.1.1.9	aPSEOverLoadCounter.....	40
30.9.1.1.9a	aPSEOverLoadCounterA.....	40
30.9.1.1.10	aPSEShortCounter aPSEOverLoadCounterB.....	41
30.9.1.1.11	aPSEMPSAbsentCounter.....	41
30.9.1.1.11a	aPSEMPSAbsentCounterA.....	41
30.9.1.1.11b	aPSEMPSAbsentCounterB.....	42
30.9.1.2	PSE actions	42
30.9.1.2.1	acPSEAdminControl.....	42
30.12	Layer Management for Link Layer Discovery Protocol (LLDP)	42
30.12.2	LLDP Local System Group managed object class	42
30.12.2.1	LLDP Local System Group attributes	42
30.12.2.1.6	aLldpXdot3LocPowerMDISupported	42
30.12.2.1.7	aLldpXdot3LocPowerMDIEnabled.....	42
30.12.2.1.8	aLldpXdot3LocPowerPairControllable	43
30.12.2.1.9	aLldpXdot3LocPowerPairs.....	43
30.12.2.1.10	aLldpXdot3LocPowerClass	43
30.12.2.1.14	aLldpXdot3LocPowerType	44
30.12.2.1.17	aLldpXdot3LocPDRequestedPowerValue	44
30.12.2.1.17a	aLldpXdot3LocPDRequestedPowerValueA	44
30.12.2.1.17b	aLldpXdot3LocPDRequestedPowerValueB.....	45
30.12.2.1.18	aLldpXdot3LocPSEAllocatedPowerValue.....	45
30.12.2.1.18a	aLldpXdot3LocPSEAllocatedPowerValueA.....	45
30.12.2.1.18b	aLldpXdot3LocPSEAllocatedPowerValueB.....	45
30.12.2.1.18c	aLldpXdot3LocPSEPoweringStatus.....	46
30.12.2.1.18d	aLldpXdot3LocPDPoweredStatus	46
30.12.2.1.18e	aLldpXdot3LocPowerPairsExt	46
30.12.2.1.18f	aLldpXdot3LocPowerClassExtA.....	46
30.12.2.1.18g	aLldpXdot3LocPowerClassExtB.....	47
30.12.2.1.18h	aLldpXdot3LocPowerClassExt	47
30.12.2.1.18i	aLldpXdot3LocPowerTypeExt.....	48
30.12.2.1.18j	aLldpXdot3LocPDLoad.....	48
30.12.2.1.18k	aLldpXdot3LocPD4PID	48
30.12.2.1.18l	aLldpXdot3LocPSEMaxAvailPower.....	48
30.12.2.1.18m	aLldpXdot3LocPSEAutoclassSupport.....	48
30.12.2.1.18n	aLldpXdot3LocAutoclassCompleted.....	49
30.12.2.1.18o	aLldpXdot3LocAutoclassRequest	49
30.12.2.1.18p	aLldpXdot3LocPowerDownRequest.....	49
30.12.2.1.18q	aLldpXdot3LocPowerDownTime	49
30.12.2.1.18r	aLldpXdot3LocMeasVoltageSupport.....	49
30.12.2.1.18s	aLldpXdot3LocMeasCurrentSupport	50
30.12.2.1.18t	aLldpXdot3LocMeasPowerSupport	50
30.12.2.1.18u	aLldpXdot3LocMeasEnergySupport	50
30.12.2.1.18v	aLldpXdot3LocMeasurementSource	50
30.12.2.1.18w	aLldpXdot3LocMeasVoltageRequest.....	50
30.12.2.1.18x	aLldpXdot3LocMeasCurrentRequest	50
30.12.2.1.18y	aLldpXdot3LocMeasPowerRequest	51
30.12.2.1.18z	aLldpXdot3LocMeasEnergyRequest.....	51
30.12.2.1.18aa	aLldpXdot3LocMeasVoltageValid.....	51
30.12.2.1.18ab	aLldpXdot3LocMeasCurrentValid	51
30.12.2.1.18ac	aLldpXdot3LocMeasPowerValid	51
30.12.2.1.18ad	aLldpXdot3LocMeasEnergyValid.....	52
30.12.2.1.18ae	aLldpXdot3LocMeasVoltageUncertainty.....	52
30.12.2.1.18af	aLldpXdot3LocMeasCurrentUncertainty	52

30.12.2.1.18ag	aLldpXdot3LocMeasPowerUncertainty	52
30.12.2.1.18ah	aLldpXdot3LocMeasEnergyUncertainty	52
30.12.2.1.18ai	aLldpXdot3LocVoltageMeasurement	53
30.12.2.1.18aj	aLldpXdot3LocCurrentMeasurement	53
30.12.2.1.18ak	aLldpXdot3LocPowerMeasurement	53
30.12.2.1.18al	aLldpXdot3LocEnergyMeasurement	53
30.12.2.1.18am	aLldpXdot3LocPSEPowerPriceIndex	53
30.12.3	LLDP Remote System Group managed object class	54
30.12.3.1	LLDP Remote System Group attributes	54
30.12.3.1.6	aLldpXdot3RemPowerMDISupported	54
30.12.3.1.7	aLldpXdot3RemPowerMDIEnabled	54
30.12.3.1.8	aLldpXdot3RemPowerPairControllable	54
30.12.3.1.9	aLldpXdot3RemPowerPairs	54
30.12.3.1.10	aLldpXdot3RemPowerClass	55
30.12.3.1.14	aLldpXdot3RemPowerType	55
30.12.3.1.17	aLldpXdot3RemPDRrequestedPowerValue	55
30.12.3.1.17a	aLldpXdot3RemPDRrequestedPowerValueA	56
30.12.3.1.17b	aLldpXdot3RemPDRrequestedPowerValueB	56
30.12.3.1.18	aLldpXdot3RemPSEAllocatedPowerValue	56
30.12.3.1.18a	aLldpXdot3RemPSEAllocatedPowerValueA	57
30.12.3.1.18b	aLldpXdot3RemPSEAllocatedPowerValueB	57
30.12.3.1.18c	aLldpXdot3RemPSEPoweringStatus	57
30.12.3.1.18d	aLldpXdot3RemPDPoweredStatus	57
30.12.3.1.18e	aLldpXdot3RemPowerPairsExt	58
30.12.3.1.18f	aLldpXdot3RemPowerClassExtA	58
30.12.3.1.18g	aLldpXdot3RemPowerClassExtB	58
30.12.3.1.18h	aLldpXdot3RemPowerClassExt	59
30.12.3.1.18i	aLldpXdot3RemPowerTypeExt	59
30.12.3.1.18j	aLldpXdot3RemPDLoad	59
30.12.3.1.18k	aLldpXdot3RemPD4PID	60
30.12.3.1.18l	aLldpXdot3RemPSEMaxAvailPower	60
30.12.3.1.18m	aLldpXdot3RemPSEAutoclassSupport	60
30.12.3.1.18n	aLldpXdot3RemAutoclassCompleted	60
30.12.3.1.18o	aLldpXdot3RemAutoclassRequest	60
30.12.3.1.18p	aLldpXdot3RemPowerDownRequest	60
30.12.3.1.18q	aLldpXdot3RemPowerDownTime	61
30.12.3.1.18r	aLldpXdot3RemMeasVoltageSupport	61
30.12.3.1.18s	aLldpXdot3RemMeasCurrentSupport	61
30.12.3.1.18t	aLldpXdot3RemMeasPowerSupport	61
30.12.3.1.18u	aLldpXdot3RemMeasEnergySupport	61
30.12.3.1.18v	aLldpXdot3RemMeasurementSource	62
30.12.3.1.18w	aLldpXdot3RemMeasVoltageRequest	62
30.12.3.1.18x	aLldpXdot3RemMeasCurrentRequest	62
30.12.3.1.18y	aLldpXdot3RemMeasPowerRequest	62
30.12.3.1.18z	aLldpXdot3RemMeasEnergyRequest	62
30.12.3.1.18aa	aLldpXdot3RemMeasVoltageValid	63
30.12.3.1.18ab	aLldpXdot3RemMeasCurrentValid	63
30.12.3.1.18ac	aLldpXdot3RemMeasPowerValid	63
30.12.3.1.18ad	aLldpXdot3RemMeasEnergyValid	63
30.12.3.1.18ae	aLldpXdot3RemMeasVoltageUncertainty	63
30.12.3.1.18af	aLldpXdot3RemMeasCurrentUncertainty	63
30.12.3.1.18ag	aLldpXdot3RemMeasPowerUncertainty	64
30.12.3.1.18ah	aLldpXdot3RemMeasEnergyUncertainty	64
30.12.3.1.18ai	aLldpXdot3RemVoltageMeasurement	64

30.12.3.1.18aj	aLldpXdot3RemCurrentMeasurement.....	64
30.12.3.1.18ak	aLldpXdot3RemPowerMeasurement.....	64
30.12.3.1.18al	aLldpXdot3RemEnergyMeasurement.....	65
30.12.3.1.18am	aLldpXdot3RemPSEPowerPriceIndex.....	65
33.	<u>Data Terminal Equipment (DTE) Power via Media Dependent Interface (MDI) Power over Ethernet over 2 Pairs.....</u>	66
33.1	Overview.....	66
33.1.1	Objectives.....	66
33.1.3	Relationship of <u>DTE Power via MDI Power over Ethernet</u> to the IEEE 802.3 Architecture.....	67
33.2	Power sourcing equipment (PSE).....	68
33.2.1	PSE location.....	68
33.2.2	Midspan PSE types.....	68
33.3	Powered devices (PDs).....	69
33.3.1	PD PI.....	69
33.4	Additional electrical specifications.....	69
33.4.2	Fault tolerance.....	69
33.4.3	Impedance balance.....	69
33.4.4	Common-mode output voltage.....	70
33.4.6	Differential noise voltage.....	71
33.4.7	Return loss.....	71
33.4.9	Midspan PSE device additional requirements.....	71
33.4.9.1	“Connector” or “telecom outlet” Midspan PSE device transmission requirements.....	71
33.4.9.1.1	Near End Crosstalk (NEXT).....	72
33.4.9.1.2	Insertion loss.....	73
33.4.9.1.3	Return loss.....	73
33.4.9.1a	33.4.9.1.4 Work area or equipment cable Cord Midspan PSE.....	73
33.4.9.1a.1	Maximum link delay.....	74
33.4.9.1a.2	Maximum link delay skew.....	74
33.4.9.1b	Coupling parameters between link segments.....	74
33.4.9.1b.1	Multiple disturber power sum alien near-end crosstalk (PSANEXT) loss.....	75
33.4.9.1b.2	Multiple disturber power sum alien far-end crosstalk (PSAFEXT) loss.....	75
33.6	Data Link Layer classification.....	75
33.6.3	Power control state diagrams.....	75
33.6.3.3	Variables.....	75
33.8	Protocol implementation conformance statement (PICS) proforma for Clause 33, <u>DTE Power via MDI Power over Ethernet over 2 Pairs</u>	76
33.8.1	Introduction.....	76
33.8.2	Identification.....	76
33.8.2.2	Protocol summary.....	76
33.8.3	PICS proforma tables for DTE Power via MDI Power over Ethernet over 2 Pairs.....	77
33.8.3.4	Electrical specifications applicable to the PSE and PD.....	77
40.	Physical Coding Sublayer (PCS), Physical Medium Attachment (PMA) sublayer and baseband medium, type 1000BASE-T.....	78
40.6	PMA electrical specifications.....	78
40.6.1	PMA-to-MDI interface tests.....	78
40.6.1.1	Isolation requirement.....	78

55.	Physical Coding Sublayer (PCS), Physical Medium Attachment (PMA) sublayer and baseband medium, type 10GBASE-T.....	79
55.5	PMA electrical specifications	79
55.5.1	Isolation requirement	79
79.	IEEE 802.3 Organizationally Specific Link Layer Discovery Protocol (LLDP) type, length, and value (TLV) information elements	80
79.1	Overview.....	80
79.1.1	IEEE 802.3 LLDP frame format.....	80
79.1.1.3	Length/Type field	80
79.3	IEEE 802.3 Organizationally Specific TLVs	80
79.3.2	Power Via MDI TLV	80
79.3.2.1	MDI power support.....	82
79.3.2.1.1	Port class	82
79.3.2.1.2	PSE MDI power support.....	82
79.3.2.1.3	PSE MDI power state	82
79.3.2.1.4	PSE pairs control ability	82
79.3.2.2	PSE power pair	83
79.3.2.3	Power class	83
79.3.2.4	Requested pPower type/source/priority	84
79.3.2.4.1	Power type	84
79.3.2.4.2a	PD 4PID	84
79.3.2.5	PD requested power value	85
79.3.2.6	PSE allocated power value	85
79.3.2.6a	Dual-signature PD requested power value for Mode A and Mode B	86
79.3.2.6b	PSE allocated power value Alternative A and Alternative B	86
79.3.2.6c	Power status	87
79.3.2.6c.1	PSE powering status	88
79.3.2.6c.2	PD powered status	88
79.3.2.6c.3	PSE power pairs ext.....	88
79.3.2.6c.4	Dual-signature power Class ext Mode A	88
79.3.2.6c.5	Dual-signature power Class ext Mode B	89
79.3.2.6c.6	Power Class ext.....	89
79.3.2.6d	System setup	89
79.3.2.6d.1	Power Type ext.....	89
79.3.2.6d.2	PD Load	89
79.3.2.6e	PSE maximum available power value	89
79.3.2.6f	Autoclass.....	90
79.3.2.6f.1	PSE Autoclass support.....	90
79.3.2.6f.2	Autoclass completed	90
79.3.2.6f.3	Autoclass request	90
79.3.2.6g	Power down	91
79.3.2.6g.1	Power down request.....	91
79.3.2.6g.2	Power down time	91
79.3.8	Power via MDI Measurements TLV	91
79.3.8.1	Measurements	91
79.3.8.2	PSE power price index.....	93
79.3.8.3	Power Via MDI Measurements TLV usage rules.....	94
79.4	IEEE 802.3 Organizationally Specific TLV selection management	94
79.4.2	IEEE 802.3 Organizationally Specific TLV/LLDP Local and Remote System group managed object class cross references.....	94

79.5	Protocol implementation conformance statement (PICS) proforma for IEEE 802.3 Organizationally Specific Link Layer Discovery Protocol (LLDP) type, length, and value (TLV) information elements	98
79.5.3	Major capabilities/options	98
79.5.8	Power Via MDI TLV	99
79.5.12	Power via MDI Measurements TLV	102
126.	Physical Coding Sublayer (PCS), Physical Medium Attachment (PMA) sublayer, and baseband medium, types 2.5GBASE-T and 5GBASE-T	103
126.5	PMA electrical specifications	103
126.5.1	Isolation requirement	103
145.	Power over Ethernet	104
145.1	Overview	104
145.1.1	Compatibility considerations	105
145.1.2	Relationship of Power over Ethernet to the IEEE 802.3 Architecture	105
145.1.3	System parameters	106
145.1.4	Cabling requirements	108
145.2	Power sourcing equipment (PSE)	109
145.2.1	PSE Type descriptions	109
145.2.2	PSE location	110
145.2.3	Midspace PSE variants	110
145.2.4	PSE PI	117
145.2.5	PSE state diagrams	118
145.2.5.1	State diagram overview and timing	118
145.2.5.2	Conventions	119
145.2.5.3	Constants	120
145.2.5.4	Variables	120
145.2.5.5	Timers	130
145.2.5.6	Functions	132
145.2.5.7	State diagrams	137
145.2.6	PSE detection of PDs	152
145.2.6.1	PSE detection validation circuit	152
145.2.6.2	Detection probe requirements	153
145.2.6.3	Detection criteria	154
145.2.6.4	Rejection criteria	154
145.2.6.5	Open circuit criteria	155
145.2.7	Connection check	155
145.2.8	PSE classification of PDs and mutual identification	155
145.2.8.1	PSE Multiple-Event Physical Layer classification	159
145.2.8.2	Autoclass (optional)	162
145.2.9	4PID requirements	163
145.2.10	Power supply output	163
145.2.10.1	Output voltage in the power on states	167
145.2.10.2	Output voltage pair-to-pair difference	167
145.2.10.3	Voltage transients	167
145.2.10.4	Reflected voltage	167
145.2.10.5	Power feeding ripple and noise	167
145.2.10.6	Continuous current capability in the power on states	167
145.2.10.6.1	PSE pair-to-pair current unbalance	170
145.2.10.7	Current during power up	172
145.2.10.8	Overload current	174

145.2.10.9	Short circuit current	174
145.2.10.10	Turn off time	177
145.2.10.11	Turn off voltage	177
145.2.10.12	Intra-pair current unbalance	177
145.2.10.13	Type power	177
145.2.10.14	Power turn on time	178
145.2.10.15	Error delay timing	178
145.2.10.16	PSE stability	178
145.2.11	Power supply allocation	178
145.2.12	PSE Maintain Power Signature (MPS) requirements	178
145.3	Powered devices (PDs)	179
145.3.1	PD Type descriptions	180
145.3.2	PD PI	180
145.3.3	PD state diagrams	182
145.3.3.1	Conventions	182
145.3.3.2	Mode designation	182
145.3.3.3	Single-signature PD state diagrams	182
145.3.3.3.1	Constants	182
145.3.3.3.2	Variables	182
145.3.3.3.3	Timers	185
145.3.3.3.4	Functions	186
145.3.3.3.5	State diagrams	187
145.3.3.4	Dual-signature PD state diagram	189
145.3.3.4.1	Constants	189
145.3.3.4.2	Variables	189
145.3.3.4.3	Timers	192
145.3.3.4.4	Functions	192
145.3.3.4.5	State diagram	193
145.3.4	PD valid and non-valid detection signatures	194
145.3.5	PD signature configurations	196
145.3.6	PD classification	197
145.3.6.1	PD Multiple-Event class signature	198
145.3.6.1.1	Mark Event behavior	200
145.3.6.2	Autoclass (optional)	200
145.3.7	PSE Type identification	201
145.3.8	PD power	201
145.3.8.1	Input voltage	204
145.3.8.2	Input average power	204
145.3.8.2.1	Input average power exceptions	205
145.3.8.2.2	System stability test conditions during startup and steady state operation	205
145.3.8.3	Input inrush current	205
145.3.8.4	Peak operating power	206
145.3.8.4.1	Peak operating power exceptions	207
145.3.8.5	Input current slew rate	207
145.3.8.6	PD behavior during transients at the PSE PI	207
145.3.8.7	Ripple and noise	208
145.3.8.8	Reflected voltage	208
145.3.8.9	PD pair-to-pair current unbalance	209
145.3.9	PD Maintain Power Signature	211
145.4	Additional electrical specifications	213
145.4.1	Isolation	213
145.4.1.1	Electrical isolation environments	213
145.4.1.1.1	Environment A requirements	214

145.4.1.1.2	Environment B requirements	214
145.4.2	Fault tolerance.....	214
145.4.3	Impedance balance.....	215
145.4.4	Common-mode output voltage	216
145.4.5	Pair-to-pair output noise voltage.....	218
145.4.6	Differential noise voltage.....	218
145.4.7	Return loss	219
145.4.8	100BASE-TX transformer droop.....	219
145.4.9	Midspan PSE device additional requirements	219
145.4.9.1	Connector Midspan PSE device transmission requirements	221
145.4.9.1.1	Near End Crosstalk (NEXT).....	221
145.4.9.1.2	Insertion loss	222
145.4.9.1.3	Return loss	222
145.4.9.2	Cord Midspan PSE.....	222
145.4.9.2.1	Maximum link delay	223
145.4.9.2.2	Maximum link delay skew.....	223
145.4.9.3	Midspan signal path requirements	223
145.4.9.3.1	Alternative A Midspan PSE signal path transfer function.....	223
145.4.9.4	Coupling parameters between link segments.....	224
145.4.9.4.1	Multiple disturber power sum alien near-end crosstalk (PSANEXT) loss.....	224
145.4.9.4.2	Multiple disturber power sum alien far-end crosstalk (PSAFEXT) loss	224
145.5	Data Link Layer classification.....	225
145.5.1	TLV frame definition.....	225
145.5.2	Data Link Layer classification timing requirements.....	225
145.5.3	Power control state diagrams	225
145.5.3.1	Conventions	226
145.5.3.2	PSE power control state diagrams	226
145.5.3.2.1	Alternative designation	226
145.5.3.2.2	Variables	226
145.5.3.2.3	Functions.....	230
145.5.3.2.4	Attribute to state diagram variable mapping.....	231
145.5.3.2.5	State diagrams.....	232
145.5.3.3	Single-signature PD power control state diagrams	236
145.5.3.3.1	Variables	236
145.5.3.3.2	Timers	238
145.5.3.3.3	Functions.....	238
145.5.3.3.4	Attribute to state diagram variable mapping.....	239
145.5.3.3.5	State diagrams.....	240
145.5.3.4	Dual-signature PD power control state diagrams	241
145.5.3.4.1	Mode designation.....	241
145.5.3.4.2	Variables	242
145.5.3.4.3	Functions.....	244
145.5.3.4.4	Attribute to state diagram variable mapping.....	245
145.5.3.4.5	State diagrams.....	246
145.5.4	Power requests and allocations	248
145.5.5	State change procedure across a link (single-signature).....	248
145.5.5.1	PSE state change procedure across a link (single-signature).....	249
145.5.5.2	PD state change procedure across a link (single-signature)	249
145.5.6	State change procedure across a link (dual-signature).....	250
145.5.6.1	Transitions between 2-pair and 4-pair mode (dual-signature).....	250
145.5.6.2	PSE state change procedure across a link (dual-signature)	251
145.5.6.3	PD state change procedure across a link (dual-signature)	251

145.5.7 Autoclass.....	251
145.6 Environmental.....	252
145.6.1 General safety	252
145.6.2 Network safety	252
145.6.3 Installation and maintenance guidelines	252
145.6.4 Patch panel considerations.....	253
145.6.5 Electromagnetic emissions	253
145.6.6 Temperature and humidity.....	253
145.6.7 Labeling	253
145.7 Protocol implementation conformance statement (PICS) proforma for Clause 145, Power over Ethernet.....	254
145.7.1 Introduction.....	254
145.7.2 Identification.....	254
145.7.2.1 Implementation identification.....	254
145.7.2.2 Protocol summary	254
145.7.2.3 PD Major capabilities/options	255
145.7.2.4 PSE Major capabilities/options.....	256
145.7.3 PICS proforma tables for Power over Ethernet	257
145.7.3.1 Power sourcing equipment.....	257
145.7.3.2 Powered devices	262
145.7.3.3 Electrical specifications applicable to the PSE and PD.....	267
145.7.3.4 Electrical specifications applicable to the PSE.....	269
145.7.3.5 Electrical specifications applicable to the PD.....	271
145.7.3.6 Data Link Layer classification requirements	271
145.7.3.7 Environmental specifications applicable to PSEs and PDs	272
145.7.3.8 Environmental specifications applicable to the PSE	272
Annex A (informative) Bibliography	273
Annex 145A (informative) Resistance and current unbalance	274
145A.1 Intra pair resistance unbalance.....	274
145A.2 Pair-to-pair unbalance overview	274
145A.3 Pair-to-pair link section resistance unbalance requirements for 4-pair operation	276
145A.4 PSE resistance and current unbalance	276
145A.4.1 Direct RPSE measurement	277
145A.5 PD resistance and current unbalance	278
Annex 145B (informative) Timing diagrams	279
145B.1 CC_DET_SEQ timing diagrams.....	279
145B.1.1 CC_DET_SEQ=0 timing diagrams.....	279
145B.1.2 CC_DET_SEQ=1 timing diagrams.....	280
145B.1.3 CC_DET_SEQ=2 timing diagrams.....	281
145B.1.4 CC_DET_SEQ=3 timing diagrams.....	282
145B.2 PSE Single-Event Physical Layer classification timing diagram	283
145B.3 PSE Multiple-Event Physical Layer classification timing diagram.....	283
Annex 145C (informative) Power system and parameters	285
145C.1 Constant power	285
145C.2 Current	287
145C.3 Direct current resistance (DCR)	288
145C.4 Bundled cabling applications.....	289

IEEE Standard for Ethernet

Amendment 2: Physical Layer and Management Parameters for Power over Ethernet over 4 Pairs

[This amendment is based on IEEE Std 802.3™-2018 as amended by IEEE Std 802.3cb™-2018.]

NOTE—The editing instructions contained in this amendment define how to merge the material contained therein into the existing base standard and its amendments to form the comprehensive standard.

The editing instructions are shown in ***bold italic***. Four editing instructions are used: change, delete, insert, and replace. ***Change*** is used to make corrections in existing text or tables. The editing instruction specifies the location of the change and describes what is being changed by using ~~strike through~~ (to remove old material) and underscore (to add new material). ***Delete*** removes existing material. ***Insert*** adds new material without disturbing the existing material. Deletions and insertions may require renumbering. If so, renumbering instructions are given in the editing instruction. ***Replace*** is used to make changes in figures or equations by removing the existing figure or equation and replacing it with a new one. Editing instructions, change markings, and this NOTE will not be carried over into future editions because the changes will be incorporated into the base standard.

Cross references that refer to clauses, tables, equations, or figures not covered by this amendment are highlighted in green.¹

¹ Notes in text, tables, and figures are given for information only and do not contain requirements needed to implement the standard.

1. Introduction

1.3 Normative references

Insert the following reference into 1.3 in alphanumeric order:

ANSI/TIA-568.0-D, Generic Telecommunications Cabling for Customer Premises.²

1.4 Definitions

Insert the following new term and definition, 1.4.139a, after 1.4.139 “agile device”:

1.4.139a ampacity: The maximum current, in ampere, that a conductor can carry continuously under the conditions of use without exceeding its temperature rating.

Insert the following new term and definition, 1.4.236a, after 1.4.236 “dual duplex”:

1.4.236a dual-signature PD: A PD that has independent detection signatures, class signatures, and maintain power signatures on each pairset. (See IEEE Std 802.3, Clause 145.)

Insert the following new term and definition, 1.4.287a, after 1.4.287 “Idle mode”:

1.4.287a IEEE 802.3 Power over Ethernet (IEEE 802.3 PoE): A system consisting of one PSE and one PD that provides power across balanced twisted-pair cabling. (See IEEE Std 802.3, Clause 33 and Clause 145.)

Change 1.4.308 as follows:

1.4.308 link section: ~~The point-to-point medium connection between the active PSE Power Interface (PI) and the PD PI.~~ The portion of the link between the PSE Power Interface (PI) and the PD PI.

Insert the following new term and definition, 1.4.374a, after 1.4.374 “page”:

1.4.374a pairset: Either of the two valid 4-conductor connections, Alternative A or Alternative B, as listed in IEEE Std 802.3, 145.2.4. The PSE Alternative A and Alternative B connections are referred to as Mode A and Mode B, respectively, at the PD.

Change 1.4.407 as follows:

1.4.407 Power Sourcing Equipment (PSE): ~~A DTE or midspan device that provides the power to a single link section. PSEs are defined for use with two different types of balanced twisted pair PHYs. When used with 2 or 4 pair balanced twisted pair (BASE-T) PHYs, (see IEEE Std 802.3, Clause 33), DTE powering is intended to provide a single 10BASE-T, 100BASE-TX, or 1000BASE-T device with a unified interface for both the data it requires and the power to process these data. When used with single balanced twisted pair (BASE-T1) PHYs (see IEEE Std 802.3, Clause 104), DTE powering is intended to provide a single 100BASE-T1 or 1000BASE-T1 device with a unified interface for both the data it requires and the power to process these data. A PSE used with balanced single twisted pair PHYs is also referred to as a PoDL PSE. A DTE or midspan device that provides power to a single link section, which may also carry data (for 2 or~~

² ANSI/TIA publications are available from the IHS Standards Store (<http://global.ihs.com/>) or from the Telecommunications Industry Association (<http://www.tiaonline.org>).

4 pair systems, see IEEE Std 802.3, Clause 33 and Clause 145; for single pair systems, see IEEE Std 802.3, Clause 104).

Insert the following new term and definition, 1.4.453a, after 1.4.453 “single-port device”:

1.4.453a single-signature PD: A PD that simultaneously shares the same detection signature, class signature, and maintain power signature between both pairsets. (See IEEE Std 802.3, Clause 145.)

Change 1.4.488, 1.4.489, 1.4.490, and 1.4.491 as follows:

1.4.488 Type 1 PD: A PD that ~~provides a Class 0, 1, 2, or 3 signature requests Class 0 to Class 3 during Physical Layer classification, and that is not a PoDL PD.~~ (See IEEE Std 802.3, Clause 33.)

1.4.489 Type 1 PSE: A PSE that ~~supports only a Type 1 PD Class 0 to Class 3 power levels and provides power over 2 pairs.~~ (See IEEE Std 802.3, Clause 33.)

1.4.490 Type 2 PD: A PD that ~~provides a Class 4 signature during Physical Layer classification, understands 2-Event classification, and is capable of Data Link Layer classification requests Class 4 during Physical Layer classification, supports 2-Event Classification, and supports Data Link Layer classification.~~ (See IEEE Std 802.3, Clause 33.)

1.4.491 Type 2 PSE: A PSE that ~~supports both a Type 1 and a Type 2 PD Class 0 to Class 4 power levels and provides power over 2 pairs.~~ (See IEEE Std 802.3, Clause 33.)

Insert the following new terms and definitions, 1.4.491a to 1.4.491d, after 1.4.491 “Type 2 PSE”:

1.4.491a Type 3 PD: A single-signature PD that requests Class 1 to Class 6, or a dual-signature PD that requests Class 1 to Class 4 on both Modes, during Physical Layer classification. Additionally, the PD implements Multiple-Event classification and accepts power on both Modes simultaneously. (See IEEE Std 802.3, Clause 145.)

1.4.491b Type 3 PSE: A PSE that supports up to Class 6 power levels, supports short MPS, and may support 4-pair power. (See IEEE Std 802.3, Clause 145.)

1.4.491c Type 4 PD: A single-signature PD that requests Class 7 or Class 8, or a dual-signature PD that request Class 5 on at least one Mode, during Physical Layer classification. Additionally, the PD implements Multiple-Event classification, is capable of Data Link Layer classification, and accepts power on both Modes simultaneously. (See IEEE Std 802.3, Clause 145.)

1.4.491d Type 4 PSE: A PSE that supports at least Class 7 power levels, in addition to lower PD Classes, short MPS, and 4-pair power. (See IEEE Std 802.3, Clause 145.)

Delete the definitions for I_{Port} (1.4.294), V_{PD} (1.4.502), and V_{PSE} (1.4.503).

1.5 Abbreviations

Insert the following new abbreviation into 1.5 in alphabetic order:

PoE Power over Ethernet

14. Twisted-pair medium attachment unit (MAU) and baseband medium, type 10BASE-T including type 10BASE-Te

14.3 MAU electrical specifications

14.3.1 MAU-to-MDI interface characteristics

14.3.1.1 Isolation requirement

Change the first paragraph of 14.3.1.1 as follows:

A MAU with a MDI that is a PI (see 33.1.3) shall meet the isolation requirements defined in 33.4.1 or 145.4.1.

25. Physical Medium Dependent (PMD) sublayer and baseband medium, type 100BASE-TX

25.4 Specific requirements and exceptions

25.4.5 Change to 9.1.7, “Worst case droop of transformer”

Change 25.4.5 as follows:

A 100BASE-TX receiver in a Type 2, Type 3, or Type 4 Endpoint PSE or Type 2, Type 3, or Type 4 PD (see Clause 33 and Clause 145) shall meet the requirements of 25.4.7. A 100BASE-TX transmitter in a Type 2 Endpoint PSE or Type 2 PD delivering or accepting more than 13.0 W average power shall meet either the Open Circuit Inductance (OCL) requirement in 9.1.7 of TP-PMD; or meet the requirements of 25.4.5.1. A 100BASE-TX transmitter in a Type 3 or Type 4 Endpoint PSE or Type 3 or Type 4 PD shall meet either the Open Circuit Inductance (OCL) requirement in 9.1.7 of TP-PMD, or meet the requirements of 25.4.5.1.

25.4.6 Replacement of 8.4.1, “UTP isolation requirements”

Change the first paragraph of 25.4.6 as follows:

A PMD with a MDI that is a PI (see 33.1.3 and 145.1.3) shall meet the isolation requirements defined in 33.4.1 and 145.4.1.

25.4.7 Addition to 10.1, “Receiver”

Change 25.4.7 as follows:

Differential voltage signals generated by a remote transmitter that meets the specifications of Clause 25; passed through a link specified in 25.4.8; and received at the MDI of a 100BASE-TX PMD in a Type 2, Type 3, or Type 4 Endpoint PSE or a Type 2, Type 3, or Type 4 PD shall be translated into one of the PMD_UNITDATA.indicate messages with a bit error ratio less than 10^{-9} after link reset completion.

**25.6 Protocol implementation conformance statement (PICS) proforma for Clause 25,
Physical Medium Dependent (PMD) sublayer and baseband medium, type
100BASE-TX³**

25.6.3 Major capabilities/options

Change the title of 25.6.3.1 as follows:

25.6.3.1 ~~DTE Power via MDI~~ Power over Ethernet major capabilities/options

**25.6.4 PICS proforma tables for the Physical Medium Dependent (PMD) sublayer and
baseband medium, type 100BASE-TX**

Change the title of 25.6.4.4 as follows:

25.6.4.4 ~~DTE Power via MDI~~ Power over Ethernet compliance

³ Copyright release for PICS proformas: Users of this standard may freely reproduce the PICS proforma in this subclause so that it can be used for its intended purpose and may further publish the completed PICS.

30. Management

30.2 Managed objects

30.2.2 Overview of managed objects

30.2.2.1 Text description of managed objects

Delete entry “oPD” and its description (“The managed object ... PSE system.”) in 30.2.2.1.

30.2.3 Containment

Replace Figure 30-4 as follows (oPD object deleted):




Figure 30-4—Repeater entity relationship diagram

Change Table 30-4 as follows:

				PSE Basic Package (mandatory)	PSE Recommended Package (optional)	Midspan Basic Capability (mandatory)	PD-Basic-Package-(mandatory)
oResourceTypeID managed object							
aResourceTypeIDName	ATTRIBUTE	GET			X		
aResourceInfo	ATTRIBUTE	GET			X		
oMidSpan managed object class (30.10.1)							
aMidSpanID	ATTRIBUTE	GET			X		
aMidSpanPSEGroupCapacity	ATTRIBUTE	GET			X		
aMidSpanPSEGroupMap	ATTRIBUTE	GET			X		
nMidSpanPSEGroupMapChange	NOTIFICATION				X		
oPSEGroup managed object class (30.10.2)							
aPSEGroupID	ATTRIBUTE	GET			X		
aPSECapacity	ATTRIBUTE	GET			X		
aPSEMap	ATTRIBUTE	GET			X		
nPSEMapChange	NOTIFICATION				X		
oPSE managed object class (30.9.1)							
aPSEID	ATTRIBUTE	GET	X				
aPSEAdminState	ATTRIBUTE	GET	X				
aPSEPowerPairsControlAbility	ATTRIBUTE	GET	X				
aPSEPowerPairs	ATTRIBUTE	GET-SET	X				
aPSEPowerDetectionStatus	ATTRIBUTE	GET	X				
<u>aPSEPowerDetectionStatusA</u>	<u>ATTRIBUTE</u>	<u>GET</u>	<u>X</u>				
<u>aPSEPowerDetectionStatusB</u>	<u>ATTRIBUTE</u>	<u>GET</u>	<u>X</u>				
aPSEPowerClassification	ATTRIBUTE	GET		X			
<u>aPSEPowerClassificationA</u>	<u>ATTRIBUTE</u>	<u>GET</u>		<u>X</u>			
<u>aPSEPowerClassificationB</u>	<u>ATTRIBUTE</u>	<u>GET</u>		<u>X</u>			
aPSEInvalidSignatureCounter	ATTRIBUTE	GET		X			
<u>aPSEInvalidSignatureCounterA</u>	<u>ATTRIBUTE</u>	<u>GET</u>		<u>X</u>			
<u>aPSEInvalidSignatureCounterB</u>	<u>ATTRIBUTE</u>	<u>GET</u>		<u>X</u>			
aPSEPowerDeniedCounter	ATTRIBUTE	GET		X			

Table 30–4—DTE Power via MDI capabilities (*continued*)

				PSE Basic Package (mandatory)	PSE Recommended Package (optional)	Midspan Basic Capability (mandatory)	PD Basic Package (mandatory)
aPSEPowerDeniedCounterA	ATTRIBUTE	GET		X			
aPSEPowerDeniedCounterB	ATTRIBUTE	GET		X			
aPSEOverLoadCounter	ATTRIBUTE	GET		X			
aPSEOverLoadCounterA	ATTRIBUTE	GET		X			
aPSEOverLoadCounterB	ATTRIBUTE	GET		X			
aPSEShortCounter	ATTRIBUTE	GET		X			
aPSEMPSAbsentCounter	ATTRIBUTE	GET		X			
aPSEMPSAbsentCounterA	ATTRIBUTE	GET		X			
aPSEMPSAbsentCounterB	ATTRIBUTE	GET		X			
acPSEAdminControl	ACTION			X			
aPSEActualPower	ATTRIBUTE	GET		X			
aPSEPowerAccuracy	ATTRIBUTE	GET		X			
aPSECumulativeEnergy	ATTRIBUTE	GET		X			
PD managed object class (30.9.2)							
aPDIID	ATTRIBUTE	GET					X
Common Attributes Template							
aCMCounter	ATTRIBUTE	GET		X			

Table 30-7—LLDP capabilities

29
Copyright © 2019 IEEE. All rights reserved.

Table 30–7—LLDP capabilities (continued)

			LLDP Basic Package (mandatory)	LLDP MAC/PHY Configuration/Status Local Package (conditional)	LLDP MAC/PHY Configuration/Status Remote Package (conditional)	LLDP Power via MDI Local Package (conditional)	LLDP Power via MDI Remote Package (conditional)	LLDP Power via MDI Measurements Local Package (conditional)	LLDP Power via MDI Measurements Remote Package (conditional)	LLDP Link Aggregation Local Package (conditional)	LLDP Link Aggregation Remote Package (conditional)	LLDP Maximum Frame Size Local Package (conditional)	LLDP Maximum Frame Size Remote Package (conditional)	LLDP EEE Local Package (optional)	LLDP EEE Remote Package (optional)
aLldpXdot3LocPSEAllocatedPowerValueB	ATTRIBUTE	GET				X									
aLldpXdot3LocPSEPoweringStatus	ATTRIBUTE	GET				X									
aLldpXdot3LocPDPoweredStatus	ATTRIBUTE	GET				X									
aLldpXdot3LocPowerpairsExt	ATTRIBUTE	GET				X									
aLldpXdot3LocPDLoad	ATTRIBUTE	GET				X									
aLldpXdot3LocPowerClassExtA	ATTRIBUTE	GET				X									
aLldpXdot3LocPowerClassExtB	ATTRIBUTE	GET				X									
aLldpXdot3LocPowerClassExt	ATTRIBUTE	GET				X									
aLldpXdot3LocPowerTypeExt	ATTRIBUTE	GET				X									
aLldpXdot3LocPD4PID	ATTRIBUTE	GET				X									
aLldpXdot3LocPSEMaxAvailPower	ATTRIBUTE	GET				X									
aLldpXdot3LocPSEAutoclassSupport	ATTRIBUTE	GET				X									
aLldpXdot3LocAutoclassCompleted	ATTRIBUTE	GET				X									
aLldpXdot3LocAutoclassRequest	ATTRIBUTE	SET				X									
aLldpXdot3LocPowerDownRequest	ATTRIBUTE	SET				X									
aLldpXdot3LocPowerDownTime	ATTRIBUTE	SET				X									
aLldpXdot3LocMeasVoltageSupport	ATTRIBUTE	GET					X								
aLldpXdot3LocMeasCurrentSupport	ATTRIBUTE	GET					X								
aLldpXdot3LocMeasPowerSupport	ATTRIBUTE	GET					X								
aLldpXdot3LocMeasEnergySupport	ATTRIBUTE	GET					X								
aLldpXdot3LocMeasurementSource	ATTRIBUTE	GET					X								
aLldpXdot3LocMeasVoltageRequest	ATTRIBUTE	GET					X								
aLldpXdot3LocMeasCurrentRequest	ATTRIBUTE	GET					X								
aLldpXdot3LocMeasPowerRequest	ATTRIBUTE	GET					X								
aLldpXdot3LocMeasEnergyRequest	ATTRIBUTE	GET					X								
aLldpXdot3LocMeasVoltageValid	ATTRIBUTE	GET					X								
aLldpXdot3LocMeasCurrentValid	ATTRIBUTE	GET					X								

Table 30–7—LLDP capabilities (continued)

			LLDP Basic Package (mandatory)	LLDP MAC/PHY Configuration/Status Local Package (conditional)	LLDP MAC/PHY Configuration/Status Remote Package (conditional)	LLDP Power via MDI Local Package (conditional)	LLDP Power via MDI Remote Package (conditional)	LLDP Power via MDI Measurements Local Package (conditional)	LLDP Power via MDI Measurements Remote Package (conditional)	LLDP Link Aggregation Local Package (conditional)	LLDP Link Aggregation Remote Package (conditional)	LLDP Maximum Frame Size Local Package (conditional)	LLDP Maximum Frame Size Remote Package (conditional)	LLDP EEE Local Package (optional)	LLDP EEE Remote Package (optional)
aLldpXdot3LocMeasPowerValid	ATTRIBUTE	GET					X								
aLldpXdot3LocMeasEnergyValid	ATTRIBUTE	GET					X								
aLldpXdot3LocMeasVoltageUncertainty	ATTRIBUTE	GET					X								
aLldpXdot3LocMeasCurrentUncertainty	ATTRIBUTE	GET					X								
aLldpXdot3LocMeasPowerUncertainty	ATTRIBUTE	GET					X								
aLldpXdot3LocMeasEnergyUncertainty	ATTRIBUTE	GET					X								
aLldpXdot3LocVoltageMeasurement	ATTRIBUTE	GET					X								
aLldpXdot3LocCurrentMeasurement	ATTRIBUTE	GET					X								
aLldpXdot3LocPowerMeasurement	ATTRIBUTE	GET					X								
aLldpXdot3LocEnergyMeasurement	ATTRIBUTE	GET					X								
aLldpXdot3LocPSEPowerPriceIndex	ATTRIBUTE	GET					X								
aLldpXdot3LocResponseTime	ATTRIBUTE	GET				X									
aLldpXdot3LocReady	ATTRIBUTE	GET				X									
aLldpXdot3LocReducedOperationPowerValue	ATTRIBUTE	GET				X									
aLldpXdot3LocTxTwSys	ATTRIBUTE	GET												X	
aLldpXdot3LocTxTwSysEcho	ATTRIBUTE	GET												X	
aLldpXdot3LocRxTwSys	ATTRIBUTE	GET												X	
aLldpXdot3LocRxTwSysEcho	ATTRIBUTE	GET												X	
aLldpXdot3LocFbTwSys	ATTRIBUTE	GET												X	
aLldpXdot3TxDllReady	ATTRIBUTE	GET												X	
aLldpXdot3RxDllReady	ATTRIBUTE	GET												X	
aLldpXdot3LocDllEnabled	ATTRIBUTE	GET												X	
aLldpXdot3LocTxFw	ATTRIBUTE	GET												X	
aLldpXdot3LocTxFwEcho	ATTRIBUTE	GET												X	
aLldpXdot3LocRxFw	ATTRIBUTE	GET												X	
aLldpXdot3LocRxFwEcho	ATTRIBUTE	GET												X	

Table 30–7—LLDP capabilities (continued)

[illegible]

Table 30–7—LLDP capabilities (continued)

			LLDP Basic Package (mandatory)	LLDP MAC/PHY Configuration/Status Local Package (conditional)	LLDP MAC/PHY Configuration/Status Remote Package (conditional)	LLDP Power via MDI Local Package (conditional)	LLDP Power via MDI Remote Package (conditional)	LLDP Power via MDI Measurements Local Package (conditional)	LLDP Power via MDI Measurements Remote Package (conditional)	LLDP Link Aggregation Local Package (conditional)	LLDP Link Aggregation Remote Package (conditional)	LLDP Maximum Frame Size Local Package (conditional)	LLDP Maximum Frame Size Remote Package (conditional)	LLDP EEE Local Package (optional)	LLDP EEE Remote Package (optional)
aLldpXdot3RemPowerClassExtA	ATTRIBUTE	GET					X								
aLldpXdot3RemPowerClassExtB	ATTRIBUTE	GET					X								
aLldpXdot3RemPowerClassExt	ATTRIBUTE	GET					X								
aLldpXdot3RemPowerTypeExt	ATTRIBUTE	GET					X								
aLldpXdot3RemPD4PID	ATTRIBUTE	GET					X								
aLldpXdot3RemPSEMaxAvailPower	ATTRIBUTE	GET					X								
aLldpXdot3RemPSEAutoclassSupport	ATTRIBUTE	GET					X								
aLldpXdot3RemAutoclassCompleted	ATTRIBUTE	GET					X								
aLldpXdot3RemAutoclassRequest	ATTRIBUTE	GET					X								
aLldpXdot3RemPowerDownRequest	ATTRIBUTE	GET					X								
aLldpXdot3RemPowerDownTime	ATTRIBUTE	GET					X								
aLldpXdot3RemMeasVoltageSupport	ATTRIBUTE	GET						X							
aLldpXdot3RemMeasCurrentSupport	ATTRIBUTE	GET						X							
aLldpXdot3RemMeasPowerSupport	ATTRIBUTE	GET						X							
aLldpXdot3RemMeasEnergySupport	ATTRIBUTE	GET						X							
aLldpXdot3RemMeasurementSource	ATTRIBUTE	GET						X							
aLldpXdot3RemMeasVoltageRequest	ATTRIBUTE	GET						X							
aLldpXdot3RemMeasCurrentRequest	ATTRIBUTE	GET						X							
aLldpXdot3RemMeasPowerRequest	ATTRIBUTE	GET						X							
aLldpXdot3RemMeasEnergyRequest	ATTRIBUTE	GET						X							
aLldpXdot3RemMeasVoltageValid	ATTRIBUTE	GET						X							
aLldpXdot3RemMeasCurrentValid	ATTRIBUTE	GET						X							
aLldpXdot3RemMeasPowerValid	ATTRIBUTE	GET						X							
aLldpXdot3RemMeasEnergyValid	ATTRIBUTE	GET						X							
aLldpXdot3RemMeasVoltageUncertainty	ATTRIBUTE	GET						X							
aLldpXdot3RemMeasCurrentUncertainty	ATTRIBUTE	GET						X							
aLldpXdot3RemMeasPowerUncertainty	ATTRIBUTE	GET						X							

Table 30–7—LLDP capabilities (*continued*)

			LLDP Basic Package (mandatory)	LLDP MAC/PHY Configuration/Status Local Package (conditional)	LLDP MAC/PHY Configuration/Status Remote Package (conditional)	LLDP Power via MDI Local Package (conditional)	LLDP Power via MDI Remote Package (conditional)	LLDP Power via MDI Measurements Local Package (conditional)	LLDP Power via MDI Measurements Remote Package (conditional)	LLDP Link Aggregation Local Package (conditional)	LLDP Link Aggregation Remote Package (conditional)	LLDP Maximum Frame Size Local Package (conditional)	LLDP Maximum Frame Size Remote Package (conditional)	LLDP EEE Local Package (optional)	LLDP EEE Remote Package (optional)
<u>aLldpXdot3RemMeasEnergyUncertainty</u>	ATTRIBUTE	GET						X							
<u>aLldpXdot3RemVoltageMeasurement</u>	ATTRIBUTE	GET						X							
<u>aLldpXdot3RemCurrentMeasurement</u>	ATTRIBUTE	GET						X							
<u>aLldpXdot3RemPowerMeasurement</u>	ATTRIBUTE	GET						X							
<u>aLldpXdot3RemEnergyMeasurement</u>	ATTRIBUTE	GET						X							
<u>aLldpXdot3RemPSEPowerPriceIndex</u>	ATTRIBUTE	GET						X							
aLldpXdot3RemTxTwSys	ATTRIBUTE	GET													X
aLldpXdot3RemTxTwSysEcho	ATTRIBUTE	GET													X
aLldpXdot3RemRxTwSys	ATTRIBUTE	GET													X
aLldpXdot3RemRxTwSysEcho	ATTRIBUTE	GET													X
aLldpXdot3RemFbTwSys	ATTRIBUTE	GET													X
aLldpXdot3RemTxFw	ATTRIBUTE	GET													X
aLldpXdot3RemTxFwEcho	ATTRIBUTE	GET													X
aLldpXdot3RemRxFw	ATTRIBUTE	GET													X
aLldpXdot3RemRxFwEcho	ATTRIBUTE	GET													X

Change the title of 30.9 as follows:

30.9 Management for ~~DTE Power via MDI~~ Power over Ethernet

30.9.1 PSE managed object class

30.9.1.1 PSE attributes

Change 30.9.1.1.2 through 30.9.1.1.5 as follows:

30.9.1.1.2 aPSEAdminState

ATTRIBUTE

APPROPRIATE SYNTAX:

An ENUMERATED VALUE that has one of the following entries:

enabled	PSE functions enabled
disabled	PSE functions disabled

BEHAVIOUR DEFINED AS:

A read-only value that identifies the operational state of the PSE functions. An interface which can provide the PSE functions specified in Clause 33 will be enabled to do so when this attribute has the enumeration “enabled”. When this attribute has the enumeration “disabled”, the interface will act as it would if it had no PSE function. The operational state of the PSE function can be changed using the acPSEAdminControl action. For Type 1 or Type 2 PSEs, if a Clause 22 MII or Clause 35 GMII is present, then this will map to the PSE Enable bit specified in 33.5.1.1.6;

30.9.1.1.3 aPSEPowerPairsControlAbility

ATTRIBUTE

APPROPRIATE SYNTAX:

BOOLEAN

BEHAVIOUR DEFINED AS:

Indicates the ability to control which PSE Pinout Alternative (see 33.2.3 and 145.2.4) is used for PD detection and power. When “true”, the PSE Pinout Alternative used can be controlled through the ~~aSectionSESS~~ aPSEPowerPairs attribute. When “false”, the PSE Pinout Alternative used cannot be controlled through the ~~aSectionSESS~~ aPSEPowerPairs attribute. For Type 1 or Type 2 PSEs, if a Clause 22 MII or Clause 35 GMII is present, then this will map to the Pair Control Ability bit specified in 33.5.1.2.12;

30.9.1.1.4 aPSEPowerPairs

ATTRIBUTE

APPROPRIATE SYNTAX:

An ENUMERATED VALUE that has one of the following entries:

signal	PSE Pinout Alternative A
spare	PSE Pinout Alternative B
<u>both</u>	<u>PSE Pinout Alternative A and Alternative B</u>

BEHAVIOUR DEFINED AS:

A read-write value that identifies the supported PSE Pinout Alternative specified in 33.2.3 and 145.2.4. A GET operation returns the PSE Pinout Alternative in use. ~~A SET operation changes the PSE Pinout Alternative used to the indicated value only if the attribute aSectionSESThreshold is “true”. If the attribute aPSEPowerPairsControlAbility is “true”, a SET operation will cause the~~

PSE functions to be disabled, the PSE Pinout Alternative used to be changed to the value indicated if supported, and then the PSE functions to be enabled. If the attribute ~~aSectionSESThreshold~~ ~~aPSEPowerPairsControlAbility~~ is “false”, a SET operation has no effect.

The enumeration “signal” indicates that PSE Pinout Alternative A is used for PD detection and power. The enumeration “spare” indicates that PSE Pinout Alternative B is used for PD detection and power. The enumeration “both” indicates that the PSE Pinout uses both Alternative A and Alternative B for detection and power. For Type 1 or Type 2 PSEs, ~~if a Clause 22 MII or Clause 35 GMII is present, then this will map to the Pair Control bits specified in 33.5.1.1.4.;~~

30.9.1.1.5 aPSEPowerDetectionStatus

ATTRIBUTE

APPROPRIATE SYNTAX:

An ENUMERATED VALUE that has one of the following entries:

disabled	PSE disabled
searching	PSE searching
deliveringPower	PSE delivering power
test	PSE test mode
fault	PSE fault detected
otherFault	PSE implementation specific fault detected

BEHAVIOUR DEFINED AS:

A read-only value that indicates the current status of the PD Detection function specified in 33.2.5 and 145.2.6.

The enumeration “disabled” indicates that the PSE State diagram (Figure 33–9 or Figure 145–13) is in the state DISABLED. The enumeration “deliveringPower” indicates that the PSE State diagram is in the state POWER_ON. The enumeration “test” indicates that the PSE State diagram is in the state TEST_MODE. The enumeration “fault” indicates that the PSE State diagram is in the state TEST_ERROR. The enumeration “otherFault” indicates that the PSE State diagram is in the state IDLE due to the variable error_condition = ~~true~~ TRUE. The enumeration “searching” indicates the PSE State diagram is in a state other than those listed above. Type 3 and Type 4 PSEs do not use the values “test” or “fault”. For Type 1 or Type 2 PSEs, ~~if a Clause 22 MII or Clause 35 GMII is present, then this will map to the PSE Status bits specified in 33.5.1.2.11.~~

NOTE—A derivative attribute may wish to apply a delay to the use of the “deliveringPower” enumeration as the PSE state diagram will enter and then quickly exit the POWER_ON state if a short-circuit or overcurrent condition is present when power is first applied.;

Insert the following new subclauses, 30.9.1.1.5a and 30.9.1.1.5b, after 30.9.1.1.5:

30.9.1.1.5a aPSEPowerDetectionStatusA

ATTRIBUTE

APPROPRIATE SYNTAX:

An ENUMERATED VALUE that has one of the following entries:

searchingAltA	PSE searching
deliveringPowerAltA	PSE delivering power
faultAltA	PSE fault detected

BEHAVIOUR DEFINED AS:

A read-only value that indicates the current status of the PD Detection function specified in 145.2.6.

The enumeration “deliveringPowerAltA” indicates that the PSE State diagram is in the state POWER_ON_PRI if alt_pri=‘a’ or the state POWER_ON_SEC if alt_pri=‘b’. The enumeration “faultAltA” indicates that the PSE State diagram is in the state IDLE_PRI if alt_pri=‘a’ or the state IDLE_SEC if alt_pri=‘b’ due to the variable error_condition_pri = TRUE (if alt_pri=‘a’) or error_condition_sec = TRUE (if alt_pri=‘b’). The enumeration “searchingAltA” indicates the PSE State diagram is in a state other than those listed above.

NOTE—A derivative attribute may wish to apply a delay to the use of the “deliveringPowerAltA” enumeration as the PSE state diagram will enter and then quickly exit the POWER_ON_PRI (if alt_pri=‘a’) state or the POWER_ON_SEC (if alt_pri=‘b’) state if a short-circuit or overcurrent condition is present when power is first applied.;

30.9.1.1.5b aPSEPowerDetectionStatusB

ATTRIBUTE

APPROPRIATE SYNTAX:

An ENUMERATED VALUE that has one of the following entries:

searchingAltB	PSE searching
deliveringPowerAltB	PSE delivering power
faultAltB	PSE fault detected

BEHAVIOUR DEFINED AS:

A read-only value that indicates the current status of the PD Detection function specified in 145.2.6.

The enumeration “deliveringPowerAltB” indicates that the PSE State diagram is in the state POWER_ON_SEC if alt_pri=‘a’ or the state POWER_ON_PRI if alt_pri=‘b’. The enumeration “faultAltB” indicates that the PSE State diagram is in the state IDLE_SEC if alt_pri=‘a’ or the state IDLE_PRI if alt_pri=‘b’ due to the variable error_condition_sec = TRUE (if alt_pri=‘a’) or error_condition_pri = TRUE (if alt_pri=‘b’). The enumeration “searchingAltB” indicates the PSE State diagram is in a state other than those listed above.

NOTE—A derivative attribute may wish to apply a delay to the use of the “deliveringPowerAltB” enumeration as the PSE state diagram will enter and then quickly exit the POWER_ON_SEC (if alt_pri=‘a’) state or the POWER_ON_PRI (if alt_pri=‘b’) state if a short-circuit or overcurrent condition is present when power is first applied.;

Change 30.9.1.1.6 as follows:

30.9.1.1.6 aPSEPowerClassification

ATTRIBUTE

APPROPRIATE SYNTAX:

An ENUMERATED VALUE that has one of the following entries:

class0	Class 0 PD
class1	Class 1 PD
class2	Class 2 PD
class3	Class 3 PD
class4	Class 4 PD
<u>class5</u>	<u>Class 5 PD</u>
<u>class6</u>	<u>Class 6 PD</u>
<u>class7</u>	<u>Class 7 PD</u>
<u>class8</u>	<u>Class 8 PD</u>

BEHAVIOUR DEFINED AS:

A read-only value that indicates the PD Class of a detected PD as specified in [33.2.6.1](#) and [145.2.8.1](#).

This value is only valid while a PD is being powered, that is the attribute ~~aLineSESThreshold~~ ~~aPSEPowerDetectionStatus~~ reporting the enumeration “deliveringPower”. For Type 1 or Type 2 PSEs, if a [Clause 22](#) MII or [Clause 35](#) GMII is present, then this will map to the PD Class bits specified in [33.5.1.2.10](#);

Insert the following new subclauses, 30.9.1.1.6a and 30.9.1.1.6b, after 30.9.1.1.6:

30.9.1.1.6a aPSEPowerClassificationA

ATTRIBUTE

APPROPRIATE SYNTAX:

An ENUMERATED VALUE that has one of the following entries:

class1	Class 1 PD
class2	Class 2 PD
class3	Class 3 PD
class4	Class 4 PD
class5	Class 5 PD

BEHAVIOUR DEFINED AS:

A read-only value that indicates the PD Class of a detected dual-signature PD as specified in [145.2.8.1](#).

This value is only valid while a PD is being powered, that is the attribute aPSEPowerDetectionStatusA reporting the enumeration “deliveringPowerAltA”;

30.9.1.1.6b aPSEPowerClassificationB

ATTRIBUTE

APPROPRIATE SYNTAX:

An ENUMERATED VALUE that has one of the following entries:

class1	Class 1 PD
class2	Class 2 PD
class3	Class 3 PD
class4	Class 4 PD
class5	Class 5 PD

BEHAVIOUR DEFINED AS:

A read-only value that indicates the PD Class of a detected dual-signature PD as specified in [145.2.8.1](#).

This value is only valid while a PD is being powered, that is the attribute aPSEPowerDetectionStatusB reporting the enumeration “deliveringPowerAltB”;

Change 30.9.1.1.7 as follows:

30.9.1.1.7 aPSEInvalidSignatureCounter

ATTRIBUTE

APPROPRIATE SYNTAX:

Generalized nonresettable counter. This counter has a maximum increment rate of 2 counts per second.

BEHAVIOUR DEFINED AS:

This counter is incremented when the Type 1 and Type 2 PSE state diagram (Figure 33–9) enters the state SIGNATURE_INVALID. This counter is not defined for Type 3 and Type 4 PSEs. For Type 1 or Type 2 PSEs, if a Clause 22 MII or Clause 35 GMII is present, then this will map to the Invalid Signature bit specified in 33.5.1.2.6.;

Insert the following new subclauses, 30.9.1.1.7a and 30.9.1.1.7b, after 30.9.1.1.7:

30.9.1.1.7a aPSEInvalidSignatureCounterA

ATTRIBUTE

APPROPRIATE SYNTAX:

Generalized nonresettable counter. This counter has a maximum increment rate of 2 counts per second.

BEHAVIOUR DEFINED AS:

This counter is incremented when the do_detect_pri or do_detect_sec function in Figure 145–13, Figure 145–15, and Figure 145–16, whichever corresponds to Alternative A depending on the value of alt_pri, returns ‘invalid’.;

30.9.1.1.7b aPSEInvalidSignatureCounterB

ATTRIBUTE

APPROPRIATE SYNTAX:

Generalized nonresettable counter. This counter has a maximum increment rate of 2 counts per second.

BEHAVIOUR DEFINED AS:

This counter is incremented when the do_detect_pri or do_detect_sec function in Figure 145–13, Figure 145–15, and Figure 145–16, whichever corresponds to Alternative B depending on the value of alt_pri, returns ‘invalid’.;

Change 30.9.1.1.8 as follows:

30.9.1.1.8 aPSEPowerDeniedCounter

ATTRIBUTE

APPROPRIATE SYNTAX:

Generalized nonresettable counter. This counter has a maximum increment rate of 2 counts per second.

BEHAVIOUR DEFINED AS:

This counter is incremented when the PSE state diagram (Figure 33–9 and Figure 145–13) enters the state POWER_DENIED. For Type 1 or Type 2 PSEs, if a Clause 22 MII or Clause 35 GMII is present, then this will map to the Power Denied bit specified in 33.5.1.2.4.;

Insert the following new subclauses, 30.9.1.1.8a and 30.9.1.1.8b, after 30.9.1.1.8:

30.9.1.1.8a aPSEPowerDeniedCounterA

ATTRIBUTE

APPROPRIATE SYNTAX:

Generalized nonresettable counter. This counter has a maximum increment rate of 2 counts per second.

BEHAVIOUR DEFINED AS:

This counter is incremented when the PSE state diagram (Figure 145–15 or Figure 145–16) enters the state POWER_DENIED_PRI if alt_pri='a' or enters the state POWER_DENIED_SEC if alt_pri='b';

30.9.1.1.8b aPSEPowerDeniedCounterB

ATTRIBUTE

APPROPRIATE SYNTAX:

Generalized nonresettable counter. This counter has a maximum increment rate of 2 counts per second.

BEHAVIOUR DEFINED AS:

This counter is incremented when the PSE state diagram (Figure 145–15 or Figure 145–16) enters the state POWER_DENIED_SEC if alt_pri='a' or enters the state POWER_DENIED_PRI if alt_pri='b';

Change 30.9.1.1.9 as follows:

30.9.1.1.9 aPSEOverLoadCounter

ATTRIBUTE

APPROPRIATE SYNTAX:

Generalized nonresettable counter. This counter has a maximum increment rate of 2 counts per second.

BEHAVIOUR DEFINED AS:

This counter is incremented when the PSE state diagram (Figure 33–9 and Figure 145–13) enters the state ~~ERROR_DELAY_OVER~~ ERROR_DELAY. For Type 1 or Type 2 PSEs, if a Clause 22 MII or Clause 35 GMII is present, then this will map to the Overload bit specified in 33.5.1.2.8.;

Insert the following new subclause, 30.9.1.1.9a, after 30.9.1.1.9:

30.9.1.1.9a aPSEOverLoadCounterA

ATTRIBUTE

APPROPRIATE SYNTAX:

Generalized nonresettable counter. This counter has a maximum increment rate of 2 counts per second.

BEHAVIOUR DEFINED AS:

This counter is incremented when the PSE state diagram (Figure 145–15 or Figure 145–16) enters the state ERROR_DELAY_PRI if alt_pri='a' or enters the state ERROR_DELAY_SEC if alt_pri='b';

Change 30.9.1.1.10 as follows:

30.9.1.1.10 ~~aPSEShortCounter~~ aPSEOverLoadCounterB

ATTRIBUTE

APPROPRIATE SYNTAX:

Generalized nonresettable counter. This counter has a maximum increment rate of 2 counts per second.

BEHAVIOUR DEFINED AS:

~~This counter is incremented when the PSE state diagram (Figure 33–9) enters the state ERROR_DELAY_SHORT. If a Clause 22 MII or Clause 35 GMII is present, then this will map to the Short Circuit bit specified in 33.5.1.2.7.;~~

This counter is incremented when the PSE state diagram (Figure 145–15 or Figure 145–16) enters the state ERROR_DELAY_SEC if alt_pri='a' or enters the state ERROR_DELAY_PRI if alt_pri='b'.;

Change 30.9.1.1.11 as follows:

30.9.1.1.11 aPSEMPSAbsentCounter

ATTRIBUTE

APPROPRIATE SYNTAX:

Generalized nonresettable counter. This counter has a maximum increment rate of 2 counts per second.

BEHAVIOUR DEFINED AS:

This counter is incremented when the PSE state diagram (Figure 33–9 and Figure 145–13) transitions directly from the state POWER_ON to the state IDLE due to tmpdo_timer_done being asserted. For Type 1 or Type 2 PSEs, if a Clause 22 MII or Clause 35 GMII is present, then this will map to the MPS Absent bit specified in 33.5.1.2.9.;

Insert the following new subclauses, 30.9.1.1.11a and 30.9.1.1.11b, after 30.9.1.1.11:

30.9.1.1.11a aPSEMPSAbsentCounterA

ATTRIBUTE

APPROPRIATE SYNTAX:

Generalized nonresettable counter. This counter has a maximum increment rate of 2 counts per second.

BEHAVIOUR DEFINED AS:

This counter is incremented when the PSE state diagram (Figure 145–15 or Figure 145–16) transitions directly from the state POWER_ON_PRI to the state IDLE_PRI due to mpdo_timer_pri_done being asserted if alt_pri='a' or transitions directly from the state POWER_ON_SEC to the state IDLE_SEC due to mpdo_timer_sec_done being asserted if alt_pri='b'.;

30.9.1.1.11b aPSEMPSAbsentCounterB

ATTRIBUTE

APPROPRIATE SYNTAX:

Generalized nonresettable counter. This counter has a maximum increment rate of 2 counts per second.

BEHAVIOUR DEFINED AS:

This counter is incremented when the PSE state diagram (Figure 145–15 or Figure 145–16) transitions directly from the state POWER_ON_SEC to the state IDLE_SEC due to mpdo_timer_sec_done being asserted if alt_pri='a' or transitions directly from the state POWER_ON_PRI to the state IDLE_PRI due to mpdo_timer_pri_done being asserted if alt_pri='b';

30.9.1.2 PSE actions

Change 30.9.1.2.1 as follows:

30.9.1.2.1 acPSEAdminControl

ACTION

APPROPRIATE SYNTAX:

Same as ~~aSectionStatus~~ aPSEAdminState

BEHAVIOUR DEFINED AS:

This action provides a means to alter ~~aSectionStatus~~ aPSEAdminState;

Delete 30.9.2 “PD managed object class” and its subclauses in their entirety.

30.12 Layer Management for Link Layer Discovery Protocol (LLDP)

30.12.2 LLDP Local System Group managed object class

30.12.2.1 LLDP Local System Group attributes

Change 30.12.2.1.6 through 30.12.2.1.10 as follows:

30.12.2.1.6 aLldpXdot3LocPowerMDISupported

ATTRIBUTE

APPROPRIATE SYNTAX:

BOOLEAN

BEHAVIOUR DEFINED AS:

For a PSE, this attribute contains a ~~A~~ read-only Boolean value used to indicate whether the MDI power is supported on the given port associated with the local system. For a PD, the value of this attribute is undefined.

30.12.2.1.7 aLldpXdot3LocPowerMDIEnabled

ATTRIBUTE

APPROPRIATE SYNTAX:

BOOLEAN

BEHAVIOUR DEFINED AS:

For a PSE, this attribute contains a read-only Boolean value used to identify whether MDI power is enabled on the given port associated with the local system. For a PD, the value of this attribute is undefined.

30.12.2.1.8 aLdpXdot3LocPowerPairControllable

ATTRIBUTE

APPROPRIATE SYNTAX:

BOOLEAN

BEHAVIOUR DEFINED AS:

~~A read-only Boolean value derived from the value of pethPsePortPowerPairsControlAbility object (defined in IETF RFC 3621) and used to indicate whether the pair selection can be controlled on the given port associated with the local system.~~

A read-only Boolean value used to indicate the ability to control which PSE Pinout Alternative (see 33.2.3 and 145.2.4) is used for PD detection and power. For a PSE, this attribute contains the value of the aPSEPowerPairsControlAbility attribute (see 30.9.1.1.3). For a PD, the contents of this attribute are undefined.

30.12.2.1.9 aLdpXdot3LocPowerPairs

ATTRIBUTE

APPROPRIATE SYNTAX:

~~The same as used for aPSEPowerPairs~~

An ENUMERATED value list that has the following entries:

<u>signal</u>	<u>PSE Pinout Alternative A</u>
<u>spare</u>	<u>PSE Pinout Alternative B</u>

BEHAVIOUR DEFINED AS:

~~A read-only the value that contains the value of the pethPsePortPowerPairs object (defined in IETF RFC 3621) which is associated with the given port on the local system.~~

A read-only value that identifies the PSE Pinout Alternative (see 33.2.3 and 145.2.4) in use for detecting and supplying power to the PD. For a PSE, this attribute contains a value derived from the aPSEPowerPairs attribute (see 30.9.1.1.4). For a PD, the contents of this attribute are undefined. A Type 3 or Type 4 PSE detecting or supplying power on both PSE Pinout Alternatives may return either PSE Pinout Alternative as this configuration is communicated through the aLdpXdot3LocPowerPairsExt attribute. A Type 3 or Type 4 PSE supplying power on only one PSE Pinout Alternative returns that PSE Pinout Alternative. For a PD, the contents of this attribute are undefined.

30.12.2.1.10 aLdpXdot3LocPowerClass

ATTRIBUTE

APPROPRIATE SYNTAX:

~~The same as used for aPSEPowerClassification~~

An ENUMERATED value list that has the following entries:

<u>class0</u>	<u>Class 0 PD</u>
<u>class1</u>	<u>Class 1 PD</u>
<u>class2</u>	<u>Class 2 PD</u>
<u>class3</u>	<u>Class 3 PD</u>
<u>class4</u>	<u>Class 4 PD</u>

BEHAVIOUR DEFINED AS:

~~A read-only value that contains the value of the `pathPsePortPowerClassifications` object (defined in IETF RFC 3621) which is associated with the given port on the local system.;~~
A read-only value that indicates the requested Class of the PD as specified in 33.2.6 and 145.2.8. This attribute returns an enumeration of “class4” for a PD of Class 4 or higher as such PD Classes are identified through the `aLldpXdot3LocPowerClassExt` attribute.;

Change 30.12.2.1.14 as follows:

30.12.2.1.14 aLldpXdot3LocPowerType

ATTRIBUTE

APPROPRIATE SYNTAX:

BIT STRING [SIZE (2)]

BEHAVIOUR DEFINED AS:

A GET attribute that returns a bit string indicating whether the local system is a PSE or a PD and whether it is Type 1 or ~~Type 2 greater than Type 1~~. The first bit indicates Type 1 or ~~Type 2 greater than Type 1~~. The second bit indicates PSE or PD. A PSE ~~shall~~ sets this bit to indicate a PSE. A PD ~~shall~~ sets this bit to indicate a PD. See also `aLldpXdot3LocPowerTypeExt`.;

Change 30.12.2.1.17 as follows:

30.12.2.1.17 aLldpXdot3LocPDRequestedPowerValue

ATTRIBUTE

APPROPRIATE SYNTAX:

INTEGER

BEHAVIOUR DEFINED AS:

A GET attribute that returns the PD requested power value in units of 0.1 W. For a PD, it is the power value that the PD has currently requested from the remote system. The PD requested power value is the maximum input average power the PD ever draws under this power allocation if accepted. For a PSE, it is the power value that the PSE ~~mirrors-echoes~~ back to the remote system. This is the PD requested power value that was used by the PSE to compute the power it has currently allocated to the remote system. ~~The PD requested power value is encoded according to Equation (79-1), where X is the decimal value of aLldpXdot3LocPDRequestedPowerValue.;~~

Insert the following new subclauses, 30.12.2.1.17a and 30.12.2.1.17b, after 30.12.2.1.17:

30.12.2.1.17a aLldpXdot3LocPDRequestedPowerValueA

ATTRIBUTE

APPROPRIATE SYNTAX:

INTEGER

BEHAVIOUR DEFINED AS:

A GET attribute that returns the PD requested power value for the Mode A pairset in units of 0.1 W. For a PD, it is the power value that the PD has currently requested from the remote system for the Mode A pairset. For a PSE, it is the power value for the Alternative A pairset that the PSE echoes back to the remote system.;

30.12.2.1.17b aLldpXdot3LocPDRequestedPowerValueB

ATTRIBUTE

APPROPRIATE SYNTAX:

INTEGER

BEHAVIOUR DEFINED AS:

A GET attribute that returns the PD requested power value for the Mode B pairset in units of 0.1 W. For a PD, it is the power value that the PD has currently requested from the remote system for the Mode B pairset. For a PSE, it is the power value for the Alternative B pairset that the PSE echoes back to the remote system.;

*Change 30.12.2.1.18 as follows:***30.12.2.1.18 aLldpXdot3LocPSEAllocatedPowerValue**

ATTRIBUTE

APPROPRIATE SYNTAX:

INTEGER

BEHAVIOUR DEFINED AS:

A GET attribute that returns the PSE allocated power value in units of 0.1 W. For a PSE, it is the power value that the PSE has currently allocated to the remote system. The PSE allocated power value is the maximum input average power that the PSE wants the PD to ever draw under this allocation if it is accepted. For a PD, it is the power value that the PD ~~mirrors-echoed~~ back to the remote system. ~~This is the PSE allocated power value that was used by the PD to compute the power that it has currently requested from the remote system. The PSE allocated power value is encoded according to Equation (79-2), where X is the decimal value of~~ aLldpXdot3LocPSEAllocatedPowerValue.;

*Insert the following new subclauses, 30.12.2.1.18a through 30.12.2.1.18am, after 30.12.2.1.18:***30.12.2.1.18a aLldpXdot3LocPSEAllocatedPowerValueA**

ATTRIBUTE

APPROPRIATE SYNTAX:

INTEGER

BEHAVIOUR DEFINED AS:

A GET attribute that returns the PSE allocated power value for the Alternative A pairset in units of 0.1 W. For a PSE, it is the power value for the Alternative A pairset that the PSE has currently allocated to the remote system. For a PD, it is the power value for the Mode A pairset that the PD echoes back to the remote system.;

30.12.2.1.18b aLldpXdot3LocPSEAllocatedPowerValueB

ATTRIBUTE

APPROPRIATE SYNTAX:

INTEGER

BEHAVIOUR DEFINED AS:

A GET attribute that returns the PSE allocated power value for the Alternative B pairset in units of 0.1 W. For a PSE, it is the power value for the Alternative B pairset that the PSE has currently

allocated to the remote system. For a PD, it is the power value for the Mode B pairset that the PD echoes back to the remote system.;

30.12.2.1.18c aLldpXdot3LocPSEPoweringStatus

ATTRIBUTE

APPROPRIATE SYNTAX:

An ENUMERATED VALUE that has one of the following entries:

4PdualsigPD	4-pair powering a dual-signature PD
4Psingle sigPD	4-pair powering a single-signature PD
2P	2-pair powering

BEHAVIOUR DEFINED AS:

A read only value that indicates the powering status of the PSE. For a PD, the contents of this attribute are undefined.;

30.12.2.1.18d aLldpXdot3LocPDPoweredStatus

ATTRIBUTE

APPROPRIATE SYNTAX:

An ENUMERATED VALUE that has one of the following entries:

4PdualsigPD	4-pair powered dual-signature PD
2PdualsigPD	2-pair powered dual-signature PD
single sigPD	powered single-signature PD

BEHAVIOUR DEFINED AS:

A read only value that indicates the powering status of the PD. For a PSE, the contents of this attribute are undefined.;

30.12.2.1.18e aLldpXdot3LocPowerPairsExt

ATTRIBUTE

APPROPRIATE SYNTAX:

An ENUMERATED VALUE that has one of the following entries:

altA	Alternative A
altB	Alternative B
both	Both Alternatives

BEHAVIOUR DEFINED AS:

A read-only value that identifies the supported PSE Pinout Alternative specified in 145.2.4. For a PSE, this attribute contains the value of the aPSEPowerPairs attribute (see 30.9.1.1.4). For a PD, the contents of this attribute are undefined.;

30.12.2.1.18f aLldpXdot3LocPowerClassExtA

ATTRIBUTE

APPROPRIATE SYNTAX:

An ENUMERATED VALUE that has one of the following entries:

single sig	Single-signature PD or 2-pair only PSE
class1	Class 1
class2	Class 2
class3	Class 3