
**Information technology —
Telecommunications and information
exchange between systems — Local
and metropolitan area networks —
Specific requirements —**

**Part 22:
Cognitive Wireless RAN Medium
Access Control (MAC) and Physical
Layer (PHY) Specifications: Policies
and Procedures for Operation in the
TV Bands**

**AMENDMENT 2: Enhancement for
broadband services and monitoring
applications**

*Technologies de l'information — Télécommunications et échange
d'information entre systèmes — Réseaux locaux et métropolitains —
Exigences spécifiques —*

*Partie 22: Spécifications du contrôle d'accès du milieu sans fil cognitif
(MAC) et de la couche physique (PHY) : Politiques et procédures pour
le fonctionnement dans les bandes TV*

*AMENDEMENT 2: Amélioration des services à bande large et
applications de la surveillance*





COPYRIGHT PROTECTED DOCUMENT

© IEEE 2015

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from ISO, IEC or IEEE at the respective address below.

ISO copyright office
Ch. de Blandonnet 8 • CP 401
CH-1214 Vernier, Geneva, Switzerland
Tel. +41 22 749 01 11
Fax +41 22 749 09 47
copyright@iso.org
www.iso.org

Institute of Electrical and Electronics Engineers, Inc
3 Park Avenue, New York
NY 10016-5997, USA

stds.ipr@ieee.org
www.ieee.org

Foreword

ISO (the International Organization for Standardization) and IEC (the International Electrotechnical Commission) form the specialized system for worldwide standardization. National bodies that are members of ISO or IEC participate in the development of International Standards through technical committees established by the respective organization to deal with particular fields of technical activity. ISO and IEC technical committees collaborate in fields of mutual interest. Other international organizations, governmental and non-governmental, in liaison with ISO and IEC, also take part in the work. In the field of information technology, ISO and IEC have established a joint technical committee, ISO/IEC JTC 1.

IEEE Standards documents are developed within the IEEE Societies and the Standards Coordinating Committees of the IEEE Standards Association (IEEE-SA) Standards Board. The IEEE develops its standards through a consensus development process, approved by the American National Standards Institute, which brings together volunteers representing varied viewpoints and interests to achieve the final product. Volunteers are not necessarily members of the Institute and serve without compensation. While the IEEE administers the process and establishes rules to promote fairness in the consensus development process, the IEEE does not independently evaluate, test, or verify the accuracy of any of the information contained in its standards.

The main task of ISO/IEC JTC 1 is to prepare International Standards. Draft International Standards adopted by the joint technical committee are circulated to national bodies for voting. Publication as an International Standard requires approval by at least 75 % of the national bodies casting a vote.

Attention is called to the possibility that implementation of this standard may require the use of subject matter covered by patent rights. By publication of this standard, no position is taken with respect to the existence or validity of any patent rights in connection therewith. ISO/IEEE is not responsible for identifying essential patents or patent claims for which a license may be required, for conducting inquiries into the legal validity or scope of patents or patent claims or determining whether any licensing terms or conditions provided in connection with submission of a Letter of Assurance or a Patent Statement and Licensing Declaration Form, if any, or in any licensing agreements are reasonable or non-discriminatory. Users of this standard are expressly advised that determination of the validity of any patent rights, and the risk of infringement of such rights, is entirely their own responsibility. Further information may be obtained from ISO or the IEEE Standards Association.

ISO/IEC/IEEE 8802-22:2015/Amd 2 was prepared by the LAN/MAN of the IEEE Computer Society (as IEEE 802.22b-2015). It was adopted by Joint Technical Committee ISO/IEC JTC 1, *Information technology*, Subcommittee SC 6, *Telecommunications and information exchange between systems*, in parallel with its approval by the ISO/IEC national bodies, under the “fast-track procedure” defined in the Partner Standards Development Organization cooperation agreement between ISO and IEEE. IEEE is responsible for the maintenance of this document with participation and input from ISO/IEC national bodies.

IEEE Std 802.22b™-2015
(Amendment to
IEEE Std 802.22™-2011
as amended by IEEE Std 802.22a™-2014)

**IEEE Standard for Information Technology—
Telecommunications and information exchange
between systems
Wireless Regional Area Networks (WRAN)—
Specific requirements**

**Part 22: Cognitive Wireless RAN
Medium Access Control (MAC) and
Physical Layer (PHY) Specifications:
Policies and Procedures for
Operation in the TV Bands**

**Amendment 2: Enhancement for Broadband
Services and Monitoring Applications**

Sponsor
**LAN/MAN Standards Committee
of the
IEEE Computer Society**

Approved 3 September 2015
IEEE-SA Standards Board

Abstract: Alternate physical layer (PHY) and necessary medium access control layer (MAC) enhancements to IEEE Std 802.22-2011 are specified in this amendment for operation in very high frequency/ultra-high frequency (VHF/UHF) television broadcast bands between 54 MHz and 862 MHz to support enhanced broadband services and monitoring applications. The amendment supports aggregate data rates greater than the maximum data rate supported by the IEEE Std 802.22-2011. This amendment defines new classes of IEEE 802.22™ devices to address these applications and supports more than 512 devices in a network. This amendment also specifies techniques to enhance communications among the devices and makes necessary amendments to the cognitive, security, and parameters and connection management clauses. This amendment supports mechanisms to enable coexistence with other IEEE 802® systems in the same band.

Keywords: broadband wireless access network, enhanced broadband services, high capacity, high throughput, IEEE 802.22™, IEEE 802.22b™, monitoring applications, WRAN standard

The Institute of Electrical and Electronics Engineers, Inc.
3 Park Avenue, New York, NY 10016-5997, USA

Copyright © 2015 by The Institute of Electrical and Electronics Engineers, Inc.
All rights reserved. Published 30 October 2015. Printed in the United States of America.

IEEE and IEEE 802 are registered trademarks in the U.S. Patent & Trademark Office, owned by The Institute of Electrical and Electronics Engineers, Incorporated.

PDF: ISBN 978-0-7381-9838-5 STD20318
Print: ISBN 978-0-7381-9839-2 STDPD20318

IEEE prohibits discrimination, harassment and bullying.

For more information, visit <http://www.ieee.org/web/aboutus/whatis/policies/p9-26.html>.

No part of this publication may be reproduced in any form, in an electronic retrieval system or otherwise, without the prior written permission of the publisher.

Important Notices and Disclaimers Concerning IEEE Standards Documents

IEEE documents are made available for use subject to important notices and legal disclaimers. These notices and disclaimers, or a reference to this page, appear in all standards and may be found under the heading “Important Notice” or “Important Notices and Disclaimers Concerning IEEE Standards Documents.”

Notice and Disclaimer of Liability Concerning the Use of IEEE Standards Documents

IEEE Standards documents (standards, recommended practices, and guides), both full-use and trial-use, are developed within IEEE Societies and the Standards Coordinating Committees of the IEEE Standards Association (“IEEE-SA”) Standards Board. IEEE (“the Institute”) develops its standards through a consensus development process, approved by the American National Standards Institute (“ANSI”), which brings together volunteers representing varied viewpoints and interests to achieve the final product. Volunteers are not necessarily members of the Institute and participate without compensation from IEEE. While IEEE administers the process and establishes rules to promote fairness in the consensus development process, IEEE does not independently evaluate, test, or verify the accuracy of any of the information or the soundness of any judgments contained in its standards.

IEEE does not warrant or represent the accuracy or content of the material contained in its standards, and expressly disclaims all warranties (express, implied and statutory) not included in this or any other document relating to the standard, including, but not limited to, the warranties of: merchantability; fitness for a particular purpose; non-infringement; and quality, accuracy, effectiveness, currency, or completeness of material. In addition, IEEE disclaims any and all conditions relating to: results; and workmanlike effort. IEEE standards documents are supplied “AS IS” and “WITH ALL FAULTS.”

Use of an IEEE standard is wholly voluntary. The existence of an IEEE standard does not imply that there are no other ways to produce, test, measure, purchase, market, or provide other goods and services related to the scope of the IEEE standard. Furthermore, the viewpoint expressed at the time a standard is approved and issued is subject to change brought about through developments in the state of the art and comments received from users of the standard.

In publishing and making its standards available, IEEE is not suggesting or rendering professional or other services for, or on behalf of, any person or entity nor is IEEE undertaking to perform any duty owed by any other person or entity to another. Any person utilizing any IEEE Standards document, should rely upon his or her own independent judgment in the exercise of reasonable care in any given circumstances or, as appropriate, seek the advice of a competent professional in determining the appropriateness of a given IEEE standard.

IN NO EVENT SHALL IEEE BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO: PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE PUBLICATION, USE OF, OR RELIANCE UPON ANY STANDARD, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE AND REGARDLESS OF WHETHER SUCH DAMAGE WAS FORESEEABLE.

Translations

The IEEE consensus development process involves the review of documents in English only. In the event that an IEEE standard is translated, only the English version published by IEEE should be considered the approved IEEE standard.

Official statements

A statement, written or oral, that is not processed in accordance with the IEEE-SA Standards Board Operations Manual shall not be considered or inferred to be the official position of IEEE or any of its committees and shall not be considered to be, or be relied on as, a formal position of IEEE. At lectures, symposia, seminars, or educational courses, an individual presenting information on IEEE standards shall make it clear that his or her views should be considered the personal views of that individual rather than the formal position of IEEE.

Comments on standards

Comments for revision of IEEE Standards documents are welcome from any interested party, regardless of membership affiliation with IEEE. However, IEEE does not provide consulting information or advice pertaining to IEEE Standards documents. Suggestions for changes in documents should be in the form of a proposed change of text, together with appropriate supporting comments. Since IEEE standards represent a consensus of concerned interests, it is important that any responses to comments and questions also receive the concurrence of a balance of interests. For this reason, IEEE and the members of its societies and Standards Coordinating Committees are not able to provide an instant response to comments or questions except in those cases where the matter has previously been addressed. For the same reason, IEEE does not respond to interpretation requests. Any person who would like to participate in revisions to an IEEE standard is welcome to join the relevant IEEE working group.

Comments on standards should be submitted to the following address:

Secretary, IEEE-SA Standards Board
445 Hoes Lane
Piscataway, NJ 08854 USA

Laws and regulations

Users of IEEE Standards documents should consult all applicable laws and regulations. Compliance with the provisions of any IEEE Standards document does not imply compliance to any applicable regulatory requirements. Implementers of the standard are responsible for observing or referring to the applicable regulatory requirements. IEEE does not, by the publication of its standards, intend to urge action that is not in compliance with applicable laws, and these documents may not be construed as doing so.

Copyrights

IEEE draft and approved standards are copyrighted by IEEE under U.S. and international copyright laws. They are made available by IEEE and are adopted for a wide variety of both public and private uses. These include both use, by reference, in laws and regulations, and use in private self-regulation, standardization, and the promotion of engineering practices and methods. By making these documents available for use and adoption by public authorities and private users, IEEE does not waive any rights in copyright to the documents.

Photocopies

Subject to payment of the appropriate fee, IEEE will grant users a limited, non-exclusive license to photocopy portions of any individual standard for company or organizational internal use or individual, non-commercial use only. To arrange for payment of licensing fees, please contact Copyright Clearance Center, Customer Service, 222 Rosewood Drive, Danvers, MA 01923 USA; +1 978 750 8400. Permission to photocopy portions of any individual standard for educational classroom use can also be obtained through the Copyright Clearance Center.

Updating of IEEE Standards documents

Users of IEEE Standards documents should be aware that these documents may be superseded at any time by the issuance of new editions or may be amended from time to time through the issuance of amendments, corrigenda, or errata. An official IEEE document at any point in time consists of the current edition of the document together with any amendments, corrigenda, or errata then in effect.

Every IEEE standard is subjected to review at least every ten years. When a document is more than ten years old and has not undergone a revision process, it is reasonable to conclude that its contents, although still of some value, do not wholly reflect the present state of the art. Users are cautioned to check to determine that they have the latest edition of any IEEE standard.

In order to determine whether a given document is the current edition and whether it has been amended through the issuance of amendments, corrigenda, or errata, visit the IEEE-SA Website at <http://ieeexplore.ieee.org/xpl/standards.jsp> or contact IEEE at the address listed previously. For more information about the IEEE-SA or IEEE's standards development process, visit the IEEE-SA Website at <http://standards.ieee.org>.

Errata

Errata, if any, for all IEEE standards can be accessed on the IEEE-SA Website at the following URL: <http://standards.ieee.org/findstds/errata/index.html>. Users are encouraged to check this URL for errata periodically.

Patents

Attention is called to the possibility that implementation of this standard may require use of subject matter covered by patent rights. By publication of this standard, no position is taken by the IEEE with respect to the existence or validity of any patent rights in connection therewith. If a patent holder or patent applicant has filed a statement of assurance via an Accepted Letter of Assurance, then the statement is listed on the IEEE-SA Website at <http://standards.ieee.org/about/sasb/patcom/patents.html>. Letters of Assurance may indicate whether the Submitter is willing or unwilling to grant licenses under patent rights without compensation or under reasonable rates, with reasonable terms and conditions that are demonstrably free of any unfair discrimination to applicants desiring to obtain such licenses.

Essential Patent Claims may exist for which a Letter of Assurance has not been received. The IEEE is not responsible for identifying Essential Patent Claims for which a license may be required, for conducting inquiries into the legal validity or scope of Patents Claims, or determining whether any licensing terms or conditions provided in connection with submission of a Letter of Assurance, if any, or in any licensing agreements are reasonable or non-discriminatory. Users of this standard are expressly advised that determination of the validity of any patent rights, and the risk of infringement of such rights, is entirely their own responsibility. Further information may be obtained from the IEEE Standards Association.

Participants

When this amendment went to sponsor ballot, the IEEE 802.22 Working Group had the following officers:

Apurva Mody, Chair
Chang-woo Pyo, Vice Chair

When this amendment was sent to sponsor ballot, the Task Group b had the following membership:

Chang-woo Pyo, Chair and Editor
Sung Hyun Hwang, Vice Chair
Gabriel Villardi, Secretary

Gregory Buchwald
 Winston Caldwell
 Gerald Chouinard
 Subir Das
 Peter Flynn
 Thomas Gurley
 Hiroshi Harada
 Bob Heile
 Dien Hoang
 Byung Jang Jeong

Jerome J. Kalke
 Hynduk Kang
 Gwangzeen Ko
 Bruce Kraemer
 Donghun Lee
 PinHsun Lin
 Liru Lu
 Michael Lynch
 Apurva Mody
 Paul Nikolich

Masayuki Oodo
 Ranga K. Reddy
 Ivan Reede
 Shigenobu Sasaki
 Steve Shellhammer
 Chunyi Song
 Keat-Beng Toh
 Xin (Amy) Zhang
 Bing Xuan Zhao
 Lei Zhongding

Major contributions were received from the following individuals:

Sung Hyun Hwang
 Masayuki Oodo
 Chang-woo Pyo
 Aziz Rahman

Ranga K. Reddy
 Shigenobu Sasaki
 Chunyi Song

Keat-Beng Toh
 Gabriel Villardi
 Xin (Amy) Zhang
 Bing Xuan Zhao

The following members of the individual balloting committee voted on this amendment. Balloters may have voted for approval, disapproval, or abstention.

Iwan Adhicandra
 Nobumitsu Amachi
 Butch Anton
 Madhusudan Banavara
 Tuncer Baykas
 Harry Bims
 Nancy Bravin
 William Byrd
 Edgar Callaway
 Juan Carreon
 Keith Chow
 Charles Cook
 Carlo Donati
 Sourav Dutta
 Richard Edgar
 Charles Einolf
 Stanislav Filin
 Devon Gayle
 Alexander Gelman
 Tim Godfrey
 Randall Groves
 Michael Gundlach
 Thomas Gurley
 Chris Guy

Werner Hoelzl
 Sung Hyun Hwang
 Noriyuki Ikeuchi
 Akio Iso
 Atsushi Ito
 Raj Jain
 Shinkyō Kaku
 Jerome J. Kalke
 Piotr Karocki
 Stuart Kerry
 Adrian Kliks
 Bruce Kraemer
 Yasushi Kudoh
 Paul Lambert
 Arthur H. Light
 Daniel Lubar
 William Lumpkins
 Elvis Maculuba
 James Marin
 Jeffery Masters
 Michael McInnis
 Apurva Mody
 Nabil Nasser
 Michael Newman
 Nick S. A. Nikjoo

Paul Nikolich
 Masayuki Oodo
 Satoshi Oyama
 Subburajan Ponnuswamy
 Venkatesha Prasad
 Chang-woo Pyo
 Verotiana Rabarijaona
 Robert Robinson
 William Rose
 John Santhoff
 Shigenobu Sasaki
 Naotaka Sato
 Chunyi Song
 Kapil Sood
 Thomas Starai
 Walter Struppler
 Keat-Beng Toh
 Ha-Nguyen Tran
 David Trejo Pizzo
 Mark-Rene Uchida
 Gabriel Villardi
 Hung-Yu Wei
 Oren Yuen
 Mingtuo Zhou

When the IEEE-SA Standards Board approved this amendment on 3 September 2015, it had the following membership:

John Kulick, *Chair*
Jon Walter Rosdahl, *Vice Chair*
Richard H. Hulett, *Past Chair*
Konstantinos Karachalios, *Secretary*

Masayuki Ariyoshi
Ted Burse
Stephen Dukes
Jean-Phillippe Faure
J. Travis Griffith
Gary Hoffman
Michael Janezic

Joseph L. Koepfinger*
David J. Law
Hung Ling
Andrew Myles
T. W. Olsen
Glenn Parsons
Ronald C. Peterson
Annette D. Reilly

Stephen J. Shellhammer
Adrian P. Stephens
Yatin Trivedi
Phillip Winston
Don Wright
Yu Yuan
Daidi Zhong

*Member Emeritus

Introduction

This introduction is not part of IEEE Std 802.22b™-2015, IEEE Standard for Information Technology—Telecommunications and information exchange between systems—Wireless Regional Area Networks (WRAN)—Specific requirements—Part 22: Cognitive Wireless RAN Medium Access Control (MAC) and Physical Layer (PHY) Specifications: Policies and Procedures for Operation in the TV Bands—Amendment 2: Enhancement for Broadband Services and Monitoring Applications.

This amendment specifies alternate physical layer (PHY) and necessary medium access control layer (MAC) enhancements to IEEE Std 802.22-2011 for operation in very high frequency/ultra high frequency (VHF/UHF) television broadcast bands between 54 MHz and 862 MHz to support enhanced broadband services and monitoring applications. PHY specifications (i.e., Operation Mode 1 and Operation Mode 2) in Clause 9 and Clause 9a are designed to meet the needs required by channel models. A multi-channel operation (7.24), high modulation and coding (9.2 and 9a.2), and multiple-input, multiple-output (MIMO) (9.15 and 9a.15) provide higher throughput (compared to the IEEE Std 802.22-2011), which may be achieved by individual use or combinational use. Point-to-multipoint connections and relay connections are specified in Clause 7.

Contents

1. Overview	2
1.3 Reference application	2
3. Definitions	2
4. Abbreviations and acronyms	4
7. MAC Common Part sublayer	5
7.1 General.....	5
7.2 Addressing and connections	6
7.3 General superframe structure.....	7
7.4 General frame structure (on PHY-OM1).....	7
7.4a General frame structure (on PHY-OM2).....	8
7.4a.1 General frame structure for normal mode.....	8
7.4a.2 General frame structure for self-coexistence mode	8
7.4a.3 Frame format.....	8
7.4b General frame structure for a relay network.....	12
7.4b.1 General frame structure for a centralized scheduling mode	12
7.4b.2 General frame structure for a distributed scheduling mode.....	13
7.4b.3 Detail of zones	15
7.4b.3.1 Access zone (AZ).....	15
7.4b.3.2 Centralized relay zone (CRZ)	16
7.4b.3.3 Distributed relay zone (DRZ)	17
7.4b.3.4 Application of PHY Operation Mode to Zone Type	18
7.5 Control header	18
7.5.1 Superframe Control header	18
7.5.2 Frame Control header.....	18
7.5.2a Frame control header for PHY-OM2	19
7.5.2a.1 General.....	19
7.5.2a.2 Extended frame control header (Ex-FCH).....	20
7.5.2b Distributed relay zone (DRZ) Frame Control header (DRZ-FCH).....	23
7.6 MAC PDU formats	24
7.6.1 MAC headers	24
7.6.1.1 Generic MAC header	24
7.6.1.2 MAC subheaders and special payloads	25
7.6.1.2.5 Extended subheader types	26
7.6.1.3 CBP MAC PDU format.....	27
7.6.1.3.1 CBP information elements	28
7.7 Management messages	30
7.7.1 Downstream Channel Descriptor (DCD).....	30
7.7.1.1 DCD Channel information elements.....	32
7.7.2 Downstream MAP (DS-MAP).....	34
7.7.2.1 DS-MAP IE.....	35
7.7.2.1.1 DIUC allocations	35
7.7.2.1.2 DS-MAP Extended DIUC IE	37
7.7.3 Upstream Channel Descriptor (UCD).....	42
7.7.3.1 UCD Channel IEs	44
7.7.4 Upstream MAP (US-MAP).....	45
7.7.4.1 US-MAP IE.....	46
7.7.4.1.1 UIUC allocations	49
7.7.4.1.4 US-MAP Extended UIUC IE	50

7.7.7	REG-REQ/RSP	60
7.7.7.3	REG-REQ/RSP information elements.....	60
7.7.7.3.4	CPE capability	60
7.7.7.3.6	Local SID Group	61
7.7.8.9	Service Flow encodings.....	61
7.7.8.9.19	Per-RS QoS	61
7.7.11	CPE Basic Capability Request/Response (CBC-REQ/RSP)	62
7.7.11.3	CBC-REQ/RSP information elements.....	62
7.7.11.3.2	Physical parameters supported	62
7.7.11.3.4	Relay CPE Mode	63
7.7.11.3.5	Multi-channel operation supported	64
7.7.24	Confirmation codes	64
7.7.25	Local Cell Update messages	64
7.7.25.1	Local Cell Update Indication (LCU-IND) message	64
7.7.25.2	Local Cell Update Acknowledgment (LCU-ACK) message.....	65
7.7.26	Container message	66
7.7.26.1	Message format.....	66
7.7.26.2	Container ACK message.....	66
7.7.27	Downstream Transmit Test (DTT) messages	67
7.7.27.1	DTT Request (DTT-REQ) message	67
7.7.27.1.1	Message format	67
7.7.27.1.2	DTT-REQ information element	67
7.7.27.2	DTT Response (DTT-RSP) message.....	67
7.7.27.2.1	Message format	67
7.7.27.2.2	DTT-RSP information element	68
7.7.27.3	DTT Report (DTT-RPT) message	68
7.7.27.3.1	Message format	68
7.7.27.3.2	DTT-RPT information element	68
7.7.27.4	DTT Confirmation (DTT-CFM) message	69
7.7.27.4.1	Message format	69
7.7.27.4.2	DTT-CFM information element	69
7.7.28	Relay-Schedule (Relay-SCHE) message	69
7.7.29	Channel Allocation Manager management messages.....	70
7.7.29.1	Overview.....	70
7.7.29.2	Add new operating channel (CAM-ADD) message	70
7.7.29.3	Stop operating channel (CAM-STP) message.....	71
7.7.29.4	Stop operating channel acknowledgment (CAM-STP-ACK) message.....	71
7.7.29.5	Switch operating channel (CAM-SWH) message	71
7.7.29.6	Switch operating channel acknowledgment (CAM-SWH-ACK) message.....	72
7.7.30	Group Resource Allocation management messages	72
7.7.30.1	Group Resource Allocation Configuration (GRA-CFG) message	72
7.7.30.2	Group Resource Allocation Update (GRA-UPD) message.....	73
7.7.31	Ranging Report (RNG-RPT) message.....	75
7.8	Management of MAC PDUs	75
7.8.4	Packing.....	75
7.8.4.3	ARQ Feedback IEs	75
7.8.7	MAC PDU construction for relay	76
7.8.7.1	General.....	76
7.8.7.2	MAC PDU construction for distributed scheduling A-CPE on non-ARQ connections	76
7.8.7.2.1	Overview	76
7.8.7.2.2	Procedure 1 on non-ARQ connections	76
7.8.7.2.3	Procedure 2 on non-ARQ connections	77
7.8.7.2.4	Procedure 3 on non-ARQ connections	78

7.8.7.2.5	Procedure 4 on non-ARQ connections	78
7.8.7.3	MAC PDU construction for distributed scheduling A-CPE on ARQ connections	79
7.8.7.3.1	Overview	79
7.8.7.3.2	Procedure 1 for ARQ connections	79
7.8.7.3.3	Procedure 2 for ARQ connections	80
7.8.7.3.4	Procedure 3 on ARQ connections	83
7.8.7.3.5	Procedure 4 on ARQ connections	84
7.8.8	MAC PDU transmission for relay	87
7.8.8.1	Overview	87
7.8.8.2	US through a distributed scheduling A-CPE	87
7.8.8.3	US through a centralized scheduling A-CPE	87
7.8.8.4	DS through a distributed scheduling A-CPE	88
7.8.8.5	DS through a centralized scheduling A-CPE	88
7.9	ARQ mechanism	89
7.9.6	ARQ operation	89
7.9.6.4	ARQ for a relay network	89
7.9.6.4.1	Overview	89
7.9.6.4.2	Two-link ARQ mode	89
7.9.6.4.3	ARQ state machine	91
7.10	Scheduling services	91
7.10.2	Upstream request/grant scheduling	91
7.10.2.1	UGS	91
7.10.2.2	rtPS	92
7.11	Bandwidth management	92
7.11.1	Bandwidth Requests	92
7.11.1.3	Bandwidth Request for a relay network	92
7.11.1.3.1	Overview	92
7.11.1.3.2	Bandwidth Request by a distributed scheduling A-CPE	92
7.11.1.3.3	Bandwidth Request by a centralized scheduling A-CPE	93
7.11.2	Grants	93
7.11.2.1	Grants for a relay network	93
7.11.2.1.1	Bandwidth grant for relay with a distributed scheduling A-CPE	93
7.11.2.1.2	Bandwidth grant for relay with a centralized scheduling A-CPE	94
7.11.3	Polling	94
7.11.3.4	Polling for a relay network	94
7.13	Contention resolution	96
7.13.1	Transmission opportunities	96
7.14	Initialization and network association	97
7.14.3	A-BS initialization	97
7.14.3.1	General	97
7.14.3.2	Professional installation	97
7.14.3.3	A-BS antenna gain information acquisition	97
7.14.3.4	Determine geographic location	99
7.14.3.5	Access TV bands database service and receive list of available channels	99
7.14.3.6	Operator disallows channels	99
7.14.3.7	Perform incumbent detection and synchronize network with neighboring networks ...	99
7.14.3.8	Present the available channel list to the higher layers	99
7.14.3.9	Commence single channel operation or multi-channel operation	100
7.14.4	CPE initialization for relay	100
7.14.4.1	General	100
7.14.4.2	CPE performs self test	103
7.14.4.3	CPE antenna gain information acquisition	103
7.14.4.4	CPE senses for and identifies A-WRAN services and incumbents	103
7.14.4.5	Present sensing results to the higher layers	103

7.14.4.6 CPE chooses an A-WRAN service for single channel operation or for multi-channel operation	103
7.14.4.7 CPE performs satellite-based geolocation	103
7.14.4.8 Acquire DS and US parameters	104
7.14.4.8.1 Overview	104
7.14.4.8.2 Obtaining DS parameters from an A-BS	104
7.14.4.8.3 Obtaining DS parameters from a distributed scheduling A-CPE	104
7.14.4.8.4 Obtaining US parameters from an A-BS	106
7.14.4.8.5 Obtaining US parameters from a distributed scheduling A-CPE	107
7.14.4.9 CPE transmits ranging/CDMA burst	108
7.14.4.9.1 General	108
7.14.4.9.2 CDMA initial ranging and automatic adjustments to an A-BS	109
7.14.4.9.3 CDMA initial ranging and automatic adjustments to a distributed scheduling A-CPE (Local initial ranging)	110
7.14.4.9.4 CDMA initial ranging and automatic adjustments by relaying on a centralized scheduling A-CPE (Relay initial ranging)	112
7.14.4.9.5 Ranging parameter adjustment	114
7.14.4.10 CPE transmit basic capabilities for a relay network	114
7.14.4.10.1 CPE transmit basic capabilities to a distributed scheduling A-CPE	114
7.14.4.10.2 CPE transmit basic capabilities relaying on a centralized scheduling A-CPE	115
7.14.4.11 CPE authentication and key exchange	116
7.14.4.12 Registration for a relay network	117
7.14.4.12.1 Overview	117
7.14.4.12.2 Local cell management on relay	117
7.14.4.13 A-BS transmits channel sets to CPE	119
7.14.4.14 Establish IP connectivity	120
7.14.4.15 Establish time of day	120
7.14.4.16 Transfer operational parameters	120
7.14.4.17 Establish dynamic service flows	120
7.14.4.18 Neighboring network discovery	120
7.15 Ranging	121
7.15.1 DS management	121
7.15.1.1 DS management (A-BS and CPE)	121
7.15.1.2 Local DS management (distributed scheduling A-CPE and S-CPE)	121
7.15.1.3 Relay DS management (A-BS and S-CPE via centralized scheduling A-CPE)	123
7.15.2 US management	126
7.15.2.3 CDMA initial ranging and automatic adjustments for a relay network	127
7.15.2.3.1 CDMA initial ranging and automatic adjustments (A-BS and CPE)	127
7.15.2.3.2 CDMA local initial ranging and automatic adjustments (distributed scheduling A-CPE and S-CPE)	127
7.15.2.3.3 CDMA relay initial ranging and automatic adjustments (centralized scheduling A-CPE and S-CPE)	128
7.15.2.4 CDMA Periodic ranging and automatic adjustments for a relay network	129
7.15.2.4.1 CDMA periodic ranging and automatic adjustments (A-BS and CPE)	129
7.15.2.4.2 CDMA local periodic ranging and automatic adjustments (distributed scheduling A-CPE and CPE)	129
7.15.2.4.3 CDMA relay periodic ranging and automatic adjustments (centralized scheduling A-CPE and CPE)	130
7.16 Channel descriptor management	131
7.18 QoS	131
7.18.9 Service Flow Management	131
7.18.9.3 Dynamic Service Addition	131
7.18.9.3.1 CPE-initiated DSA	131

7.18.9.3.2	BS-initiated DSA	132
7.18.9.4	Dynamic Service Change.....	132
7.18.9.4.1	CPE-initiated DSC	132
7.18.9.4.2	BS-initiated DSC	133
7.18.9.5	Dynamic Service Deletion.....	133
7.18.9.5.1	CPE-initiated DSD	133
7.18.9.5.2	BS-initiated DSD	134
7.19	Incumbent protection	134
7.19.2	Measurements management.....	134
7.19.2.1	Measurements management for a relay network	134
7.19.4	Measurement report and notification	135
7.19.4.2	Measurement report and notification for a relay network	135
7.20	Self-coexistence.....	136
7.20.1	Coexistence Beacon Protocol (CBP)	136
7.20.1.1	CBP packet structure	136
7.20.4	Self-coexistence for a relay network.....	137
7.20.4.1	General	137
7.20.4.2	Mechanism for inter-A-BS self-coexistence on a relay network.....	138
7.20.4.3	CBP-based neighboring network discovery	139
7.20.4.3.1	Overview	139
7.20.4.3.2	Discovery with SCW	139
7.21	Quiet periods and sensing.....	140
7.21.2	Synchronization of overlapping quiet periods	140
7.21.2.1	Intra-frame quiet period synchronization	140
7.21.2.2	Inter-frame Quiet Period Synchronization.....	141
7.21.4	Quiet periods and sensing for a relay network.....	141
7.21.4.1	Quiet period synchronization for an A-BS's cell.....	141
7.21.4.2	Quiet period synchronization for a local network	141
7.22	Channel management	142
7.22.3	Channel management on a relay network	142
7.22.3.1	Overview.....	142
7.22.3.2	Initialization and channel sets updating.....	143
7.22.3.3	Scheduling of channel switching time.....	144
7.23	Synchronization of the IEEE 802.22 base stations and IEEE 802.22b base stations	145
7.24	Multi-channel operation	145
7.24.1	General	145
7.24.2	Channel allocation manager.....	147
7.24.2.1	General	147
7.24.2.2	Add new operating channel operation	148
7.24.2.2.1	General	148
7.24.2.2.2	BS-CAM selects a specific BS-CHU	149
7.24.2.2.3	BS-CAM commences operation request	149
7.24.2.2.4	BS-CHU commences operation acknowledgment	149
7.24.2.2.5	BS-CAM sends management information notification to BS-CHU	150
7.24.2.2.6	BS-CHU memorizes management information	150
7.24.2.2.7	BS-CHU performs frequency setting	150
7.24.2.2.8	BS-CHU performs synchronization	150
7.24.2.2.9	BS-CHU sends operation preparation completed notification to BS-CAM	150
7.24.2.2.10	BS-CHU broadcasts SCH on PHY-OM1 or FCH on PHY-OM2	150
7.24.2.2.11	BS-CAM checks unused BS-CHU	150
7.24.2.2.12	CPE-CAM selects a specific CPE-CHU	150
7.24.2.2.13	CPE-CAM sends BS search command (All or specific channel) to the specific CPE-CHU	151
7.24.2.2.14	CPE-CHU performs BS search	151

7.24.2.2.15 CPE-CHU sends BS detected notification to CPE-CAM	151
7.24.2.2.16 CPE-CAM determines other operating CPE-CHU	151
7.24.2.2.17 CPE-CAM performs BSID matching	151
7.24.2.2.18 CPE-CAM sends BSID mismatch notification to CPE-CHU	151
7.24.2.2.19 CPE-CAM sends proceed notification to CPE-CHU	151
7.24.2.2.20 CPE-CHU performs synchronization	152
7.24.2.2.21 CPE-CHU sends synchronization completed notification to CPE-CAM	152
7.24.2.2.22 CPE-CAM checks unused CPE-CHU	152
7.24.2.2.23 CPE-CAM sends registration request to CPE management unit	152
7.24.2.2.24 CPE management unit sends registration completed notification to CPE-CAM	152
7.24.2.3 Add new operating channel operation by using BS search command (specific channel)	152
7.24.2.3.1 General	152
7.24.2.3.2 BS-CAM sends aggregation information to BS-CHU1	153
7.24.2.3.3 BS-CHU1 forwards aggregation information to CPE-CHU1	153
7.24.2.3.4 CPE-CHU1 forwards aggregation information to CPE-CAM	153
7.24.2.3.5 BS-CAM selects a specific BS-CHU	153
7.24.2.3.6 BS-CAM commences operation request	154
7.24.2.3.7 BS-CHUn commences operation acknowledgment	154
7.24.2.3.8 BS-CAM sends management information notification to BS-CHUn	154
7.24.2.3.9 BS-CHUn memorizes management information	155
7.24.2.3.10 BS-CHUn performs frequency setting	155
7.24.2.3.11 BS-CHUn performs synchronization	155
7.24.2.3.12 BS-CHUn sends operation preparation completed notification to BS-CAM ..	155
7.24.2.3.13 BS-CHUn broadcasts SCH on PHY-OM1 or FCH on PHY-OM2	155
7.24.2.3.14 BS-CAM checks unused BS-CHU	155
7.24.2.3.15 CPE-CAM selects a specific CPE-CHU	155
7.24.2.3.16 CPE-CAM sends BS search command (specific channel) to the specific CPE-CHUn	155
7.24.2.3.17 CPE-CHUn performs BS search	156
7.24.2.3.18 CPE-CHUn sends BS detected notification to CPE-CAM	156
7.24.2.3.19 CPE-CAM determines other operating CPE-CHU	156
7.24.2.3.20 CPE-CAM performs BSID matching	156
7.24.2.3.21 CPE-CAM sends BSID mismatch notification to CPE-CHUn	156
7.24.2.3.22 CPE-CAM sends proceed notification to CPE-CHUn	156
7.24.2.3.23 CPE-CHUn performs synchronization	156
7.24.2.3.24 CPE-CHUn sends synchronization completed notification to CPE-CAM	156
7.24.2.3.25 CPE-CAM checks unused CPE-CHU	157
7.24.2.3.26 CPE-CAM sends registration request to CPE management unit	157
7.24.2.3.27 CPE management unit sends registration completed notification to CPE-CAM	157
7.24.2.4 Stop operating channel operation	157
7.24.2.4.1 General	157
7.24.2.4.2 BS-CAM sends stop operation request to BS-CHU	157
7.24.2.4.3 BS-CHU starts stop operation timer	157
7.24.2.4.4 BS-CHU sends stop operation request acknowledgment to BS-CAM	158
7.24.2.4.5 BS-CHU sends stop operation request to CPE-CHU	158
7.24.2.4.6 CPE-CHU starts stop operation timer	158
7.24.2.4.7 CPE-CHU sends stop operation notification to CPE-CAM	158
7.24.2.4.8 CPE-CAM sends stop operation approval/command to CPE-CHU	158
7.24.2.4.9 CPE-CHU sends stop operation request acknowledgment to BS-CHU	159
7.24.2.4.10 CPE-CHU checks stop operation timer expired and stops operation	159
7.24.2.4.11 CPE-CHU sends stop operation completed notification to CPE-CAM	159

7.24.2.4.12	BS-CHU checks stop operation timer expired and stops operation	159
7.24.2.4.13	BS-CHU sends stop operation completed notification to CPE management unit	159
7.24.2.5	Switch operating channel operation	159
7.24.2.5.1	General	159
7.24.2.5.2	BS-CAM sends channel switch request to BS-CHU	160
7.24.2.5.3	BS-CHU starts channel switch timer	160
7.24.2.5.4	BS-CHU sends channel switch request acknowledgment to BS-CAM	161
7.24.2.5.5	BS-CHU sends channel switch request to CPE-CHU	161
7.24.2.5.6	CPE-CHU starts channel switch timer	161
7.24.2.5.7	CPE-CHU sends channel switch notification to CPE-CAM	161
7.24.2.5.8	CPE-CAM sends channel switch approval/command to CPE-CHU	161
7.24.2.5.9	CPE-CHU sends channel switch request acknowledgment to BS-CHU	161
7.24.2.5.10	BS-CHU checks channel switch timer expired and performs channel switch	161
7.24.2.5.11	CPE-CHU checks channel switch timer expired and performs channel switch	161
7.24.2.5.12	BS-CHU sends channel switch completed notification to BS-CAM	162
7.24.2.5.13	BS-CHU broadcasts SCH on PHY-OM1 or FCH on PHY-OM2	162
7.24.2.5.14	BS-CHU sends DS-MAP/DCD/US-MAP/UCD to CPE-CHU	162
7.24.2.5.15	CPE-CHU sends channel switch completed notification to CPE-CAM	162
7.24.2.5.16	CPE-CHU sends channel switch completed notification to CPE management unit	162
7.24.3	Multi-channel operation at A-BS	162
7.24.4	Multi-channel operation at A-CPE	163
7.25	Group Resource Allocation	164
8.	Security mechanism in IEEE 802.22	166
8.1	Security Architecture for the Data/Control and Management Planes	167
8.1.2	Key management and authentication overview	167
8.2	SCM protocol	167
8.2.2	Authentication state machine	167
8.2.2.7	Security capabilities negotiation	167
8.2.3	TEK exchange overview	168
8.2.3.1	TEK exchange overview for PMP topology	168
8.2.3.2	TEK state machine	168
8.3	Key usage	168
8.3.1	BS key usage	168
8.3.1.5	BS usage of TEK and GTEK	168
8.4	Cryptographic methods	169
8.4.1	Selection of Data Encryption and Authentication methods	169
8.4.2	Data Encryption and Authentication with AES GCM	170
8.4.2.1	PDU format	170
8.4.2.1.1	Packet number (PN)	170
8.4.2.1.2	PDU format—Authentication only	172
8.4.2.1.3	PDU format—Authentication and encryption	173
8.4.2.1.4	PDU format—Encryption only	174
8.4.2.2	GCM algorithm constraints	175
8.4.2.3	Receive processing rules	176
8.6	Security sublayer 2—Security mechanisms for the cognitive functions	176
8.6.2	CBP Authentication mechanisms	176
8.6.2.4	ECQV implicit certificate generation, processing, and validation requirements	177
8.6.2.4.1	ECQV certificate generation requirements	177
8.6.2.5	Signature generation, processing, and validation requirements	177

8.6.2.5.1	Signature generation requirements	177
8.6.2.6	BS Implicit Certificate Exchange	178
9.	PHY Operation Mode 1 (PHY-OM1)	178
9.2	Data rates	179
9.4	Superframe and frame structure.....	192
9.4.1	Preamble.....	192
9.4.1.5	Local frame preamble	192
9.4.1.6	Local CBP preamble.....	193
9.7	Channel coding.....	194
9.7.2	Forward Error Correction (FEC).....	194
9.7.2.1	Binary Convolutional code (BCC) mode (mandatory).....	194
9.7.2.1.2	Puncturing	194
9.7.2.1.3	OFDM slot concatenation	195
9.7.2.5	Multidimensional trellis coded modulation (MD-TCM) mode (optional)	196
9.7.2.5.1	Overview of multidimensional trellis coded modulation (MD-TCM)	196
9.7.2.5.2	Coset selection	197
9.7.2.5.3	Region pair selection	198
9.7.2.5.4	Symbol selection	200
9.8	Constellation mapping and modulation.....	200
9.8.1	Data modulation.....	200
9.9	Control mechanisms	203
9.9.4	Power control	203
9.9.4.2	Transmit Power Control mechanism	203
9.14	Receiver requirements	205
9.14.1	Receiver minimum sensitivity	205
9.15	Multiple-input, multiple-output (MIMO).....	205
9.15.1	Overview.....	205
9.15.2	MIMO pilot allocation	205
9.15.2.1	Overview.....	205
9.15.2.2	Pilot allocation for two antennas	205
9.15.2.3	Pilot allocation for four antennas.....	206
9.15.3	Space time coding (STC).....	207
9.15.3.1	Overview.....	207
9.15.3.2	Transmit diversity using two antennas (Alamouti O-STBC)	208
9.15.3.3	Transmit diversity with array-interference gain	208
9.15.3.3.1	Overview	208
9.15.3.3.2	Transmit diversity with array-interference gain for two antennas	209
9.15.3.3.3	Transmit diversity with array-interference gain for four antennas	210
9.15.4	Spatial multiplexing.....	212
9.15.4.1	Overview.....	212
9.15.4.2	Spatial multiplexing using two antennas	212
9.15.4.3	Spatial multiplexing using four antennas.....	213
9a.	PHY Operation Mode 2 (PHY-OM2)	213
9a.1	Symbol description	214
9a.1.1	OFDM symbol mathematical representation	214
9a.1.1.1	Time domain description	215
9a.1.1.2	Frequency domain description.....	215
9a.1.2	Symbol parameters.....	215
9a.1.2.1	Subcarrier spacing.....	215
9a.1.2.2	Symbol duration for different cyclic prefix modes.....	216
9a.1.2.3	Transmission parameters	216
9a.1.3	OFDMA basic terms definition.....	217

9a.1.3.1 Tile, slot, and data region.....	217
9a.1.3.2 Data mapping.....	219
9a.2 Data rates.....	221
9a.3 Functional block diagram applicable to the PHY.....	233
9a.4 Frame structure.....	234
9a.4.1 Preamble.....	235
9a.4.1.1 Frame preamble and local frame preamble.....	235
9a.4.1.2 CBP preamble.....	237
9a.4.2 Control header and MAP definitions.....	237
9a.4.2.1 Frame control header (FCH).....	237
9a.4.2.2 DS-MAP, US-MAP, DCD, and UCD.....	238
9a.5 CBP packet format.....	238
9a.6 OFDM subcarrier allocation.....	238
9a.6.1 Pilot pattern.....	238
9a.6.1.1 Downstream (DS).....	238
9a.6.1.2 Upstream (US).....	239
9a.6.2 DS subcarrier allocation.....	239
9a.6.2.1 Symbol structure for subchannel in the DS.....	239
9a.6.2.2 Subcarrier allocation and data mapping onto subcarriers.....	240
9a.6.3 Upstream subcarrier allocation.....	242
9a.6.3.1 Symbol structure for subchannel in the upstream.....	242
9a.6.3.2 Subcarrier allocation and data mapping onto subcarriers.....	243
9a.6.3.3 Data subchannel rotation scheme.....	245
9a.6.4 Bit interleaving.....	246
9a.7 Channel coding.....	246
9a.7.1 Data scrambling.....	246
9a.7.2 Forward error correction (FEC).....	246
9a.7.2.1 BCC mode (mandatory).....	247
9a.7.2.1.1 Binary convolutional coding.....	247
9a.7.2.1.2 Puncturing.....	247
9a.7.2.1.3 OFDM slot concatenation.....	247
9a.7.2.2 Multidimensional trellis coded modulation (MD-TCM) mode (optional).....	249
9a.8 Constellation mapping and modulation.....	249
9a.8.1 Data modulation.....	249
9a.8.2 Pilot modulation.....	250
9a.9 Control mechanisms.....	250
9a.9.1 DS synchronization.....	250
9a.9.2 US synchronization.....	250
9a.9.3 Opportunistic US bursts.....	250
9a.9.3.1 CDMA bursts.....	250
9a.9.3.1.1 CDMA codes.....	251
9a.9.3.1.2 Initial-ranging transmission.....	251
9a.9.3.1.3 CDMA periodic-ranging, BW-request, and UCS notification transmission.....	252
9a.9.3.1.4 Ranging, BW request, and UCS notification opportunity windows.....	253
9a.9.4 Power control.....	254
9a.9.4.1 Transmit power control boundaries and EIRP limits.....	254
9a.9.4.2 Transmit power control mechanism.....	254
9a.10 Network synchronization.....	255
9a.11 Frequency control requirements.....	255
9a.12 Antenna.....	255
9a.13 RF mask.....	255
9a.14 Receiver requirements.....	255
9a.15 MIMO pilot allocation.....	256
9a.15.1 Overview.....	256

9a.15.2 Pilot allocation for two antennas.....	256
9a.15.3 Pilot allocation for four antennas.....	257
9a.15.4 Space time coding (STC).....	257
10. Cognitive radio capability	257
10.1 General.....	257
12. Parameters and connection management	258
12.1 Parameters, timers, message IEs.....	258
12.1.1 MAC (dynamic service flow, multicast, ARQ, capability, and bandwidth management).....	258
12.1.1.1 MAC (Relay, Multi-channel).....	258
12.1.2 PHY (initialization, operation, and DS/US synchronization).....	258
14. Management plane interfaces and procedures	263
14.2 Primitive definitions	263
14.2.1 Management SAP (M-SAP).....	263
14.2.1.4 BS configuration and monitoring primitives	263
14.2.1.4.1 M-AVAIL-TV-CH-REPORT.REQUEST	263
14.2.1.4.2 M-AVAIL-TV-CH-REPORT-INDICATION	264
14.2.1.4.5 M-OPERATING-TV-CHS-CONFIRMATION	264
14.2.1.5 CPE reports the resulting available WRAN services list.....	266
14.2.1.5.4 M-WRAN-SERVICES-INDICATION	266
Annex G (informative) Bibliography	268
Annex H (informative) Multiple-input, multiple-output (MIMO)—Receiver side implementation	269

IEEE Standard for Information Technology—
Telecommunications and information exchange
between systems
Wireless Regional Area Networks (WRAN)—
Specific requirements

Part 22: Cognitive Wireless RAN
Medium Access Control (MAC) and
Physical Layer (PHY) Specifications:
Policies and Procedures for
Operation in the TV Bands

Amendment 2: Enhancement for Broadband
Services and Monitoring Applications

IMPORTANT NOTICE: IEEE Standards documents are not intended to ensure safety, security, health, or environmental protection, or ensure against interference with or from other devices or networks. Implementers of IEEE Standards documents are responsible for determining and complying with all appropriate safety, security, environmental, health, and interference protection practices and all applicable laws and regulations.

This IEEE document is made available for use subject to important notices and legal disclaimers. These notices and disclaimers appear in all publications containing this document and may be found under the heading “Important Notice” or “Important Notices and Disclaimers Concerning IEEE Documents.” They can also be obtained on request from IEEE or viewed at <http://standards.ieee.org/IPR/disclaimers.html>.

(This amendment is based on IEEE 802.22™-2011 as amended by IEEE Std 802.22a™-2014.)

NOTE—The editing instructions contained in this amendment define how to merge the material contained therein into the existing base standard and its amendments to form the comprehensive standard. The editing instructions are shown in **bold italic**. Four editing instructions are used: change, delete, insert, and replace. **Change** is used to make corrections in existing text or tables. The editing instruction specifies the location of the change and describes what is being changed by using ~~strike through~~ (to remove old material) and underscore (to add new material). **Delete** removes existing material. **Insert** adds new material without disturbing the existing material. Insertions may require renumbering. If so, renumbering instructions are given in the editing instruction. **Replace** is used to make changes in figures or equations by removing the existing figure or equation and replacing it with a new one. Editing instructions, change markings, and this NOTE will not be carried over into future editions because the changes will be incorporated into the base standard.¹

¹Notes in text, tables, and figures are given for information only and do not contain requirements needed to implement the standard.

1. Overview

1.3 Reference application

Insert the following paragraphs after the third paragraph in 1.3:

The Advanced Wireless Regional Area Networks (A-WRANs) for which this standard has been developed are expected to support enhanced broadband services and monitoring applications such as real-time and/or near real-time monitoring, emergency broadband services, remote medical services, etc. The A-WRAN provides all essential functionalities of PHY, MAC, security, and cognitive radio technologies defined in the IEEE 802.22 WRAN and supports an additional PHY mode and additional functionalities of multi-hop relay operations, multiple channel operations, multiple-input-multiple-output (MIMO) operations, and advanced security to extend regional area broadband services to the regional monitoring applications and the enhanced broadband services.

Figure 1a illustrates an A-WRAN. An advanced base station (A-BS) complying with this standard shall be able to provide broadband services for the customer premise equipments (CPEs) such as an advanced CPE (A-CPE) and a subscriber CPE (S-CPE) through direct or multi-hop relay connectivity. An advanced customer premise equipment (A-CPE) can provide multi-hop relay connectivity for the S-CPEs, which allows for enhancing connection reliability between the A-BS and S-CPEs and reducing the network management overhead of the A-BS as well as could extend the service coverage of A-WRAN.




Figure 1a—An A-WRAN with an A-BS, A-CPEs, and S-CPEs

3. Definitions

Insert the following definitions in alphabetical order and renumber appropriately:

3.x access zone (AZ): A communication zone between an A-BS and A-CPE or between an A-BS and S-CPE in a frame.

3.x advanced base station (A-BS): A generalized equipment set providing connectivity, management and control of the customer premise equipment (CPE) such as the advanced customer premise equipment (A-CPE) and the subscriber CPE (S-CPE). The functionalities attributed to the A-BS, in the context of this standard, may be implemented by a device or a collection of devices. Anything that is not an A-BS shall be either of S-CPE or A-CPE.

3.x advanced customer premise equipment (A-CPE): A generalized equipment set providing direct or relay connectivity between an A-BS and S-CPEs. A-CPE operates one of two modes: centralized scheduling mode and distributed scheduling mode.

3.x Advanced Wireless Regional Area Network (A-WRAN): The A-WRAN provides all essential functionalities of PHY, MAC, security, and cognitive radio technologies defined in the IEEE 802.22 WRAN and supports additional functionalities of an additional PHY mode, multi-hop relay operations, multiple channel operations, multiple-input-multiple-output (MIMO) operations, and advanced security to extend regional area broadband services to the regional monitoring applications and the enhanced broadband services.

3.x centralized relay zone (CRZ): A communication zone between a centralized scheduling A-CPE and S-CPE in a frame.

3.x centralized scheduling A-CPE: A generalized equipment set providing relay connectivity between an A-BS and S-CPEs.

3.x centralized scheduling mode: A mode where an A-CPE operates as a centralized scheduling A-CPE.

3.x distributed relay zone (DRZ): A communication zone between a distributed scheduling A-CPE and S-CPE in a frame.

3.x distributed scheduling A-CPE: A generalized equipment set providing relay connectivity between an A-BS and S-CPEs, and providing connectivity, management and control of the subscriber CPEs (S-CPEs) within a local network.

3.x distributed scheduling mode: A mode where an A-CPE operates as a distributed scheduling A-CPE.

3.x group resource allocation (GRA): The group is composed of one A-CPE and many S-CPEs. The A-BS allocates the resources on a group basis, and manages the backup and candidate channels on a group basis.

3.x local cell: A cell is formed by a distributed scheduling A-CPE and zero or more S-CPEs associated with and under control of the distributed scheduling A-CPE. The coverage area of this local cell extends up to the point where the signal received from the distributed scheduling A-CPE is sufficient to allow S-CPEs to associate and maintain communication with the A-BS on relay connection.

3.x multiple channel: Refers to more than one specific physical radio frequency (RF) channel in the TV broadcast frequency bands, which may be 6 MHz, 7 MHz, or 8 MHz wide depending on the relevant regulatory domains.

3.x multiple-input, multiple-output (MIMO): A system employing at least two transmit (Tx) antennas and at least two receive (Rx) antennas to improve the system capacity, coverage, or throughput.

3.x PHY Operation Mode 1 (PHY-OM1): A physical layer mode supporting the system defined in Clause 9 of IEEE Std 802.22b-2015.

3.x PHY Operation Mode 2 (PHY-OM2): A physical layer mode supporting the system defined in Clause 9a of IEEE Std 802.22b-2015.

3.x receive/transmit transition gap (RTG): A gap between the last sample of the upstream (US) subframe and the first sample of the subsequent downstream (DS) subframe at the antenna port of the BS in a time division duplex (TDD) transceiver. This gap allows time for the BS to switch from receive (Rx) to transmit (Tx) mode. During this gap, the BS is not transmitting modulated data but simply allowing the BS transmitter carrier to ramp up and the Tx/Rx antenna switch to actuate.

3.x relay receive/transmit transition gap (RRTG): A gap between the last sample of the downstream (DS) access zone and the first sample of the subsequent DS relay zone at the antenna port of the A-CPE in a time division duplex (TDD) transceiver. This gap allows time for the A-CPE to switch from receive (Rx) to transmit (Tx) mode. During this gap, the A-CPE is not transmitting modulated data but simply allowing the A-CPE transmitter carrier to ramp up and the Tx/Rx antenna switch to actuate.

3.x relay transmit/receive transition gap (RTTG): A gap between the last sample of the upstream (US) access zone and the first sample of the subsequent US relay zone at the antenna port of the A-CPE in a time division duplex (TDD) transceiver. This gap allows time for the A-CPE to switch from transmit (Tx) to receive (Rx) mode. During this gap, the A-CPE is not transmitting modulated data but simply allowing the A-CPE transmitter carrier to ramp down and the Tx/Rx antenna switch to actuate, and the A-CPE receiver section to activate.

3.x relay zone (RZ): A communication zone between any A-CPE and an S-CPE or A-BS. A relay zone is operated as one of the following two relay zones: centralized relay zone (CRZ) and distributed relay zone (DRZ).

3.x subscriber customer premise equipment (S-CPE): A generalized equipment set providing connectivity between a A-BS and a subscriber premise, or between an A-CPE and a subscriber premise. S-CPE is used for any CPE that is not an A-CPE.

3.x transmit/receive transition gap (TTG): A gap between the last sample of the downstream (DS) subframe and the first sample of the subsequent upstream (US) subframe at the antenna port of the BS in a time division duplex (TDD) transceiver. This gap allows time for the BS to switch from transmit (Tx) to receive (Rx) mode. During this gap, the BS is not transmitting modulated data but simply allowing the BS transmitter carrier to ramp down and the Tx/Rx antenna switch to actuate, and the BS receiver section to activate.

3.x urgent coexistence situation (UCS): A situation where a WRAN detects incumbents in the current operating channel.

4. Abbreviations and acronyms

Insert the following abbreviations and acronyms in alphabetical order:

A-BS	advanced base station
A-CPE	advanced customer premise equipment
AZ	access zone
A-WRAN	advanced wireless regional area network
CRZ	centralized relay zone
CAM	channel allocation manager
CHU	channel transceiver unit
DL	downlink
DRZ	distributed relay zone
DTT	downstream transit test
Ex-FCH	extended frame control header
GRA	group resource allocation
LCU	local cell update
MD-TCM	multidimensional trellis coded modulation
MIMO	multiple-input, multiple-output
OSIC	ordered successive interference cancellation
OSTBC	orthogonal space-time block codes
PHY-OM1	Physical Layer Operation Mode 1

PHY-OM2	Physical Layer Operation Mode 2
QP	quiet period
RRTG	relay receive/transmit transition gap
RTTG	relay transmit/receive transition gap
S-CPE	subscriber CPE
STC	space time coding
UL	uplink
ZF	zero-forcing

7. MAC Common Part sublayer

Change the preliminary text of Clause 7 as follows:

This clause describes the MAC layer used by the IEEE 802.22 WRAN point-to-multipoint medium access control standard and the IEEE 802.22b advanced WRAN (A-WRAN) multi-hop relay medium access control standard. The MAC provides tools for protection of TV bands incumbent services as well as for coexistence. The A-WRAN MAC provides all functionalities of the WRAN MAC and additionally supports multi-hop relay operations, multiple channel operations, multiple-input-multiple-output (MIMO) operations, etc. ~~The MAC is Both WRAN and A-WRAN MACs are connection-oriented and provides flexibility in terms of QoS support. The MAC regulates~~ The WRAN MAC and the A-WRAN MAC regulate downstream medium access by TDM, while and the upstream is managed by using a DAMA/OFDMA system. In the WRAN MAC, the BS manages all the activities within its IEEE 802.22 cell, and the associated CPEs are under the control of the BS. The A-WRAN MAC provides point-to-multipoint connections and relay connections between the advanced base station (A-BS) and the CPEs within an A-BS's cell. The multi-hop relaying is facilitated by an advanced CPE (A-CPE). An A-CPE shall operate one of two modes (centralized scheduling mode and distributed scheduling mode) depending on capability or network situations. The A-CPE that operates in the centralized scheduling mode (called a *centralized scheduling A-CPE*) provides relay connections for the subscriber CPEs (S-CPEs) under the management of the A-BS. The A-CPE that operates in the distributed scheduling mode (called a *distributed scheduling A-CPE*) may configure a local cell and has similar capabilities to that of A-BS, in that it manages S-CPEs within the local cell. The A-BS manages the A-WRAN cell's CPEs and local cells. A higher throughput compared to the IEEE Std 802.22™-2011 may be achieved by individual use or combinational use of multi-channel operation (7.24), high modulation and coding (9.2, 9a.2), or MIMO (9.15, 9a.15).

7.1 General

Insert the following paragraph after the first paragraph of 7.1:

In an A-WRAN cell consisting of CPEs (e.g., A-CPEs and S-CPEs), all A-CPEs and multiple S-CPEs are managed by a single A-BS, and other S-CPEs are managed by distributed scheduling A-CPEs. The downstream is TDM where the A-BS transmits and the CPEs receive. The upstream transmissions, where the CPEs transmit and the A-BS receives, are shared by the CPEs on a demand basis, according to a DAMA/OFDMA scheme. Within a local cell consisting of a distributed scheduling A-CPE and S-CPEs, multiple S-CPEs are managed by the distributed scheduling A-CPE. The downstream within a local cell is TDM where the distributed scheduling A-CPE transmits and the S-CPEs receive. The upstream transmissions within a local cell, where the S-CPEs transmit and the distributed scheduling A-CPE receives, are shared by the S-CPEs on a demand basis, according to a DAMA/OFDMA scheme.

Change the now third and fourth paragraphs in 7.1 as follows:

~~The Both WRAN MAC and A-WRAN MAC~~ implements a combination of access schemes that efficiently control contention between CPEs within a cell and overlapping cells sharing the same channel while at the same time attempting to meet the latency and bandwidth requirements of each user application. This is accomplished through four different types of upstream scheduling mechanisms that are implemented using unsolicited bandwidth grants, polling, and two contention procedures (i.e., MAC header and CDMA based). The use of polling simplifies the access operation and attempts to allow applications to receive service on a deterministic basis if it is required.

~~The Both WRAN MAC and A-WRAN MAC~~ ~~is~~ are connection-oriented, and as such, connections are a key component that require active maintenance and hence can be dynamically created, deleted, and changed as the need arises. A connection defines both the mapping between convergence processes at CPEs and BS or A-BS and the related service flow (one connection per service flow). For the purposes of mapping to services on CPEs and associating varying levels of QoS, all data communications are instantiated in the context of a connection, and this provides a mechanism for upstream and downstream QoS management. In particular, the QoS parameters are integral to the bandwidth allocation process as the CPE requests upstream bandwidth on a per connection basis (implicitly identifying the service flow). The BS, ~~A-BS, or the distributed scheduling A-CPE,~~ in turn, grants bandwidth to a CPE as an aggregate of grants in response to per-connection requests from the CPE.

Insert the following paragraph at the end of 7.1:

An A-WRAN may support multiple connections between A-BS and A-CPE(s) or S-CPE(s), or between A-CPE and S-CPE(s), by using multiple channels (7.24). When multiple channels are available and used for the connections between A-BS and A-CPE(s) or S-CPE(s), or between A-CPE and S-CPE(s), a frame is assigned to the connection on the different channel into multiple channels. The frame format on each channel shall follow the frame format described in 7.4, 7.4a, and 7.4b.

7.2 Addressing and connections

Insert the following paragraph after the first paragraph in 7.2:

Each A-BS and CPE in an A-WRAN shall have a 48-bits universal MAC address, as defined in IEEE Std 802[®]. This address uniquely defines the A-BS and CPE from within the set of all possible vendors and equipment types. It is used as part of the authentication process by which the A-BS and CPE each verifies the identity of the other at the time of network association. The A-BS MAC address is broadcast by the A-BS on superframe control header (SCH) on PHY Operation Mode 1 (Clause 9) or frame control header (FCH) on PHY Operation Mode 2 (Clause 9a) and is present in every CBP burst. Each A-WRAN device regularly broadcasts a CBP burst containing its Device ID and Serial Number. This is done as part of the device's self-identification process that helps identify potential interference sources to incumbent services and for coexistence purposes.

Change the now third and fourth paragraphs of 7.2 as follows:

Connections are identified by two items, a ~~913~~-bit station ID (SID) and a 3-bit flow ID (FID). The SID uniquely identifies a station that is under the control of the BS, ~~the A-BS, or the distributed scheduling A-CPE.~~ A SID can be for a unicast station, when referencing a single CPE, or for a multicast station, when referencing a multicast group (of CPEs). A FID identifies a particular traffic flow assigned to a CPE. The tuple of SID and FID (SID | FID) forms a connection identifier (CID) that identifies a connection for the CPE. The SID is signaled in the DS/US-MAP allocation, and the FID is signaled in the generic MAC header (GMH) of a MAC PDU. This allows for a total of up to ~~512-8192~~ stations, each with a maximum of eight flows that can be supported within each downstream and upstream channel.

At CPE initialization, three flows shall be dedicated for management connections (see 12.2) for the purpose of carrying MAC management messages and data between a CPE and the BS/A-BS or the distributed scheduling A-CPE. The three flows reflect the fact that there are inherently three different levels of QoS for traffic sent on management connections between a CPE and the BS/A-BS or the distributed scheduling A-CPE. The basic flow is used by the BS/A-BS MAC or the distributed scheduling A-CPE MAC and CPE MAC to exchange short, time-urgent MAC management messages; whereas, the primary management flow is used by the BS/A-BS or the distributed scheduling A-CPE MAC and CPE MAC to exchange longer, more delay-tolerant MAC management messages (Table 19 specifies which MAC management messages are transferred on which type of connections). Finally, the secondary management flow is used by the BS/A-BS or the distributed scheduling A-CPE and CPE to transfer more delay-tolerant, standards-based (e.g., DHCP, TFTP, and SNMP) messages that are carried in IP datagrams. The secondary management flow may be packed and/or fragmented, similarly to the primary management except that no ARQ should be used for the latter since it is more time critical.

Change the now seventh paragraph of 7.2 as follows:

Many higher-layer sessions may operate over the same wireless connection. For example, many users within a company may be communicating with Transmission Control Protocol (TCP)/IP to different destinations, but since they all operate within the same overall service parameters, all of their traffic is pooled for request/grant purposes. A service flow is a unidirectional flow of traffic (BS/A-BS to CPE, or CPE to BS/A-BS, distributed scheduling A-CPE to CPE, or CPE to distributed scheduling A-CPE) that defines the mapping of higher-layer application service parameters (e.g., QoS) to a FID assigned to a particular CPE's unicast SID or multicast group (multicast SID).

7.3 General superframe structure

Insert the following paragraphs as the first three paragraphs of the preliminary text in 7.3:

The A-WRAN supports two PHY operation modes: PHY Operation Mode 1 (PHY-OM1, Clause 9) and PHY Operation Mode 2 (PHY-OM2, Clause 9a).

The WRAN system and the A-WRAN system on PHY-OM1 shall support the following superframe structure.

The A-WRAN on PHY-OM2 does not support the following superframe structure.

Change the now fourth paragraph of the preliminary text in 7.3 as follows:

The ~~IEEE 802.22~~ WRAN system and the A-WRAN system on PHY-OM1 includes two operational modes: a normal mode and a self-coexistence mode. In normal mode, one WRAN/A-WRAN cell occupies one or more channels and operates on all the frames in a superframe. In self-coexistence mode, multiple WRAN and/or A-WRAN cells share the same channel, and each coexisting WRAN and/or A-WRAN cell operates on one or several different frames exclusively.

Change the title of 7.4 as follows:

7.4 General frame structure (on PHY-OM1)

Insert the following paragraph as the first paragraph in 7.4:

The WRAN system and the A-WRAN system on PHY-OM1 described in Clause 9 shall support the following frame structure.

Insert the following subclauses (7.4a and 7.4b and their subclauses, figures, and tables) after 7.4:

7.4a General frame structure (on PHY-OM2)

The A-WRAN on PHY-OM2 described in Clause 9a shall support the following frame structure.

The A-WRAN on PHY-OM2 includes two operational modes: a normal mode and a self-coexistence mode. In normal mode, one A-WRAN cell occupies one or more channels and operates on all the frames. In self-coexistence mode, multiple A-WRAN cells share the same channel, and each coexisting WRAN cell operates on one or several different frames exclusively.

The A-WRAN on PHY-OM2 shall transmit the Frame Control Header (FCH) (7.5.2a, Table 2a) at the beginning of every frame on the operating channel in both normal mode and self-coexistence mode. An A-WRAN runs in normal mode by default and transits to self-coexistence mode when the A-WRAN can detect and decode an FCH or a CBP from an adjacent A-WRAN cell on its operating channel.

7.4a.1 General frame structure for normal mode

The A-WRAN frame structure depicted in Figure 12 shall be used and the first frame shall be constituted of the following:

- A PHY frame preamble (Clause 9a)
- A Frame Control header (FCH) (7.5.2a)
- The rest of the first frame including its frame header and data payload

At the beginning of every frame, the A-BS shall transmit the frame preamble and the FCH on the operating channel using the modulation/coding specified in 9a.2 and Table 231e, respectively. In order to associate with an A-BS, a CPE must receive the FCH to establish communication with the A-BS. During each MAC frame, the A-BS shall manage the upstream and downstream operations, which may include ordinary data communication, measurement activities, coexistence procedures, and so on.

7.4a.2 General frame structure for self-coexistence mode

The A-WRAN frame structure in self-coexistence mode is shown in Figure 13a. The self-coexistence mode is for the scenario when multiple A-BSs with overlapping coverage have to share the same channel. The frequency reuse factor cannot be maintained as one due to the mutual interference of these A-BSs. In this case, the A-BSs shall share the channel on a per-frame basis, i.e., each A-BS is allocated the frames on a non-interference basis. The negotiation process of frame allocation can be found in 7.20.

In self-coexistence mode, the A-BS and CPEs in an A-WRAN cell shall transmit only during the active frames allocated to that A-WRAN cell. They can transmit during other frames only when a self-coexistence window (SCW) has been scheduled. During the frames not allocated to the present cell, the A-BS and CPEs may monitor the channel for any transmission from neighboring A-WRAN cells to improve self-coexistence.

7.4a.3 Frame format

The A-WRAN system on PHY-OM2 described in Clause 9a shall support the following frame structure.

The top-down time division duplex (TDD) frame structure employed in the MAC is illustrated in Figure 12.

IEEE Std 802.22b-2015
IEEE Standard for Wireless Regional Area Networks
Part 22: Cognitive WRAN MAC and PHY Specifications: Policies and Procedures for Operation in the TV Bands
Amendment 2: Enhancement for Broadband Services and Monitoring Applications




Figure 13a—General frame structure on PHY-OM2 for self-coexistence mode

As illustrated in Figure 13b, a frame comprises two parts: a downstream (DS) subframe and an upstream (US) subframe. A portion of the US subframe may be allocated as a window to facilitate self-coexistence. This SCW may be scheduled by the A-BS at the end of the US subframe when necessary to allow transmission of opportunistic coexistence beacon protocol bursts. The SCW includes the necessary time buffers to absorb the difference in propagation delay between nearby and distant A-BSs and CPEs operating on the same channel. The boundary between the DS and US subframes shall be adaptive to adjust to the DS and US relative capacity. The US subframe may contain scheduled US PHY PDUs, each transmitted from different CPEs for their US traffic. It may also include contention intervals scheduled for the following:

- CPE association (initial ranging)
- CPE link synchronization, power control, and geolocation (periodic ranging)
- Bandwidth request
- Urgent coexistence situation (UCS) notification
- Quiet period (QP) resource adjustment

The definitions of the fields/messages are given in 7.6 and 7.7.

The PHY PDUs may be transmitted across several subchannels as shown in Figure 13b, which depicts how a frame may be transmitted (in time and frequency) by the PHY.

Figure 13b shows an example of the two-dimensional (2D) (time/frequency) structure of the MAC frame that shall consist of an integer number of fixed-size OFDM slots. Each slot shall consist of 4 OFDM symbols by one subchannel (i.e., 1 OFDM slot for DS = 4 symbols $\times$ 1 subchannel) for DS and shall consist of 7 OFDM symbols by subchannel (i.e., 1 OFDM slot for US = 7 symbols $\times$ 1 subchannel) for US (9a.1.3.1). A subchannel consists of 16 subcarriers. In Figure 13b, the MAC packets are assumed to be structured in a linear TDM manner (see Figure 12), and the PHY packets are arranged in a 2D time/frequency domain (symbol in the horizontal direction, logical subchannels in the vertical direction). For the FCH, DS/US-MAP, DCD, UCD, and DS payload, the MAC information is first laid vertically by subchannels and then stepped horizontally in the time direction. This vertical layering allows early scheduling of DS bursts assigned to distant CPEs to compensate for propagation delays and to avoid potential interference at the CPE if overlapping A-WRAN cells with different DS/US capacity split.

IEEE Std 802.22b-2015
IEEE Standard for Wireless Regional Area Networks
Part 22: Cognitive WRAN MAC and PHY Specifications: Policies and Procedures for Operation in the TV Bands
Amendment 2: Enhancement for Broadband Services and Monitoring Applications




Figure 13b—Example of a time/frequency structure of a MAC frame for PHY-OM2

The MAC data elements, starting from the FCH and including the first broadcast burst, shall be entered into the portion between the second OFDM symbol and fifth OFDM symbol, which is based on the number of symbols defined in a tile (9a.1.3.1), as shown in Figure 13b, in the increasing order of logical subchannels until all logical subchannels are occupied. Then, the subsequent data elements, if they have not all been mapped, shall be placed in the same order on the following OFDM symbols. The balance of the last OFDM symbols shall be padded with zeros. The modulation and coding schemes for the padding zeros are defined by the DIUC for the last DS burst in the DS-MAP. Note that the DS-MAP indicates the length of the contiguous DS MAC elements, not their absolute position in the DS subframe.

The MAC data elements that are contained in US bursts shall be mapped to the US subframe in a different order as shown in Figure 13b. They are first mapped horizontally, 7 OFDM symbols by 7 OFDM symbols, in the same logical subchannel. Once a logical subchannel has been filled to the end of the US subframe, the balance of the MAC data elements shall be mapped to the next logical subchannel, in an increasing subchannel order. This process continues until all of the subchannels and symbols allocated to the burst are filled. If the quantity of MAC data elements is insufficient to fill an US burst so that an integer number of OFDMA slots is occupied once encoded, zero padding shall be inserted at the end.

Alternatively, the horizontal laying of the MAC data elements may fill one subchannel with at least 7 OFDM symbols at a time and continue on the following subchannels. However, when all logical subchannels have been filled, the next MAC data elements shall be placed in the first available logical subchannel in the following burst. The width of the last vertical burst will be between 7 and 13 symbols depending on the total number of symbols in the US subframe.

The long US packet structure, where a logical subchannel is completely filled before moving to the next subchannel, is used to maximize the allowed power per subcarrier for a given CPE EIRP limit, i.e., this horizontal laying reduces the EIRP required by the CPE for its US burst by minimizing the number of

subchannels needed. In the US, the shorter burst alternative shown in Figure 13b is used to reduce latency by allowing advance of the US burst in the US subframe to give the base station time to react before the start of the next frame, at the cost of reduced transmit power and efficiency (e.g., video game near real-time versus transmission efficiency).

The format of the FCH MAC burst is described in 7.5.2a. The FCH is modulated using the data mode selected (e.g., Mode 2) (Table 231e). Binary convolutional coding (BCC; 9a.7.2.1) shall also be applied to the FCH burst. The FCH specifies the burst profile and the length of either the DS-MAP, if transmitted, or the US-MAP. If neither the DS-MAP nor the US-MAP is transmitted, the value shall be set to zero. The DS-MAP message, if transmitted, shall be the first MAC PDU in the burst following the FCH. A US-MAP message, if transmitted, shall immediately follow either the DS-MAP message, if transmitted, or the FCH. If DCD and UCD messages are transmitted in the frame, they shall immediately follow the DS-MAP and US-MAP messages. The symbols containing these broadcast MAC control messages shall be modulated using data mode 2 as described in Table 231e with the mandatory BCC mode (see 9a.7.2.1).

In the US direction, if a CPE does not have any data to transmit in its US allocation, it shall transmit an US PHY burst containing a generic MAC header (see 7.6.1.1) with its basic FID, together with a Bandwidth Request subheader (see 7.6.1.2.1). This would allow the A-BS to reclaim this CPE's allocation in the following frames and use the resource for some other purpose.

The A-BS may schedule up to five types of contention windows (see 7.13):

- The Initial Ranging window is used for initializing the association.
- The periodic ranging window is used for regularly adjusting the timing and power at the CPE.
- The BW request window is used by CPEs to request US bandwidth allocation from the A-BS.
- The UCS notification window is used by CPEs to report a UCS with incumbents.
- The SCW is employed by CBP packets for signaling information to adjacent and overlapping A-WRAN cells for self-coexistence, signaling the device identification for resolving interference situations with incumbents when requested by local regulation, and carrying out terrestrial geolocation between CPEs of the same A-WRAN cell.

However, CBP burst transmissions for terrestrial geolocation shall have lower priority than any other coexistence transmission on the CBP burst.

The SCW shall be scheduled at the end of the frame as depicted in Figure 13b. The CBP packets (9a.5) are transmitted by selected CPEs or the A-BS and carry information, among other things, about the A-WRAN cell as a whole and the device that transmits it as well as information to support the self-coexistence mechanism (see 7.20).

A CBP packet shall be transmitted by each CPE associated to an A-BS as specified by the parameter "T34" in Table 272 for periodic identification of its device ID and serial number and the associated base station ID as may be required by local regulations (see Annex A).

Whenever a CPE is neither receiving nor sending data to its A-BS (idle state), it shall be capable of decoding CBP packets transmitted by nearby CPEs belonging to other A-WRAN cells, on the same channel (N), or on adjacent channels ($N\pm 1$), or on alternate channels ($N\pm 2$ and beyond). This capability shall also be available at CPE initialization. In addition, A-BS frame synchronization is based on the absolute local start time of their frame period to the start of every minute referenced to UTC as specified in 7.23. Hence, multiple co-located or nearby A-BS cells can efficiently communicate with each other and align their SCW for CBP exchange as well as their quiet periods for sensing incumbents.

7.4b General frame structure for a relay network

The A-WRAN system on both PHY-OM1 and PHY-OM2 shall support the following frame structure for relay.

A general frame structure has two different modes for relay: a centralized scheduling mode and a distributed scheduling mode.

For centralized scheduling mode, a centralized scheduling A-CPE relays frames including control frames or data frames received from (to) the A-BS to (from) the S-CPE, which will enhance connection reliability between the A-BS and S-CPEs. Moreover, a centralized scheduling A-CPE may relay network management information received from an A-BS such as the preamble, FCH, MAPs, etc., to S-CPEs to assist the network management of the A-BS.

For distributed scheduling mode, a distributed scheduling A-CPE configures a local cell containing more than one S-CPE within an A-WRAN cell and manages the S-CPEs locally by producing and transmitting network management information (such as a local frame preamble, distributed relay zone (DRZ)-FCH (7.5.2b), MAPs, etc.), which allows for reducing the network management overhead of the A-BS as well as could extend the service coverage of A-WRAN.

7.4b.1 General frame structure for a centralized scheduling mode

Each of the DS and US subframes for a centralized scheduling mode may include two zones: access zone (AZ) and centralized relay zone (CRZ) as shown in Figure 13c. Each AZ in the DS and US subframes is used for transmission between an A-BS and CPEs (i.e., centralized scheduling A-CPEs or S-CPEs), and each CRZ in the DS and US subframes is used for transmission between a centralized scheduling A-CPE and S-CPEs.




Figure 13c—Example of a time/frequency structure of a MAC frame for a centralized scheduling mode on PHY-OM2

For centralized scheduling mode, both the AZs and CRZs in the DS and US subframes are managed by an A-BS. The AZ of the DS subframe shall appear earlier than other zones of the AZ of the US subframe or the CRZs of the DS and US subframes. Except for the AZ of the DS, the order of the AZ of the US subframe, the CRZ of the DS subframe, and the CRZ of the US subframe in the frame may be changed during the operations.

7.4b.2 General frame structure for a distributed scheduling mode

Each of the DS and US subframes for a distributed scheduling mode may include two zones: access zone (AZ) and distributed relay zone (DRZ) as shown in Figure 13d. Each AZ in the DS and US subframes is used for transmission between an A-BS and CPEs (i.e., distributed scheduling A-CPEs or S-CPEs), and each DRZ in the DS and US subframe is used for transmission between a distributed scheduling A-CPE and S-CPEs.

Both the AZs and DRZs in the DS and US subframes are scheduled by an A-BS. For distributed scheduling mode, the AZs in the DS and US subframes are managed by an A-BS, and the DRZs in the DS and US subframes are controlled by a distributed scheduling A-CPE, which is capable of configuring and maintaining a local cell within an A-WRAN cell. The AZ of the DS subframe shall appear earlier than other zones of the AZ of the US subframe or the DRZs of the DS and US subframes. Except for the AZ of the DS, the order of the AZ of the US subframe, the DRZ of the DS subframe, and the DRZ of the US subframe in the frame may be changed during the operations.




Figure 13d—Example of a time/frequency structure of a MAC frame for a distributed scheduling mode on PHY-OM2

For the A-WRAN on either PHY operation mode, the subchannels of the DRZs in the DS and US subframes can be grouped by up to three segments with the fixed number of subchannels as shown in Figure 13e. The segment bandwidth is scalable up to the occupied subchannel as shown in Figure 13f. For PHY-OM1 and PHY-OM2, each segment includes the number of subchannels defined in Table A1. For the DS of PH-OM2, the number of tiles per occupied channel bandwidth is not divided by 3. Thus segments 1, 2, and 3 have a different number of tiles, i.e., 72, 68, and 68 tiles, respectively. Figure 13f shows all the combinations of three segment bandwidths and three start positions. As shown in Figure 13g, the number of segment

bandwidth modes is 3, 2, and 1 for the first, second, and third start positions, respectively. The configuration of the segmentation scheme can be identified by local frame preamble as defined in 9.4.1.5 and 9a.4.1.1. The segmentation can be scheduled by the A-BS, and each segment is assigned to the different distributed scheduling A-CPEs. This segmentation is used to increase network capacity.




Figure 13e—Example of a time/frequency structure of a MAC frame for a distributed scheduling mode on segmentation on PHY-OM2





Figure 13f—Segment structure

Table A1—Segment bandwidth

	PHY-OM1		PHY-OM2	
	DS (subchannels)	US (subchannels)	DS (tiles)	US (tiles)
Size of Segment 1	10	20	72	70
Size of Segment 2	10	20	68	70
Size of Segment 3	10	20	68	70

**Figure 13g—Combination of segment start position and segment bandwidth**

7.4b.3 Detail of zones

7.4b.3.1 Access zone (AZ)

At the beginning of every superframe in AZ on PHY-OM1, the A-BS shall transmit the superframe preamble and the SCH on the operating channel using the modulation/coding specified in 9.4.1.2 and Table 202, respectively. At the beginning of every frame in AZ on PHY-OM2, on the other hand, the A-BS shall transmit the frame preamble and the FCH on the operating channel using the modulation/coding specified in 9a.2 and Table 231e, respectively. In order to associate with an A-BS, a CPE must receive the SCH or FCH to establish communication with the A-BS.

An AZ in the US subframe may contain scheduled US PHY PDUs, each transmitted from different CPEs for their US traffic. It may also include contention intervals scheduled for the following:

- CPE association (initial ranging)
- CPE link synchronization, power control, and geolocation (periodic ranging)
- Bandwidth request
- UCS notification
- Quiet period resource adjustment

The 2D (time/frequency) structure of the MAC frame shall consist of an integer number of fixed-size OFDM slots. For PHY-OM1, each slot shall consist of one OFDM symbol by one subchannel (i.e., 1 OFDM slot = 1 symbol $\times$ 1 subchannel) for both DS and US. For PHY-OM2, on the other hand, each slot shall consist of 4 OFDM symbols by one subchannel (i.e., 1 OFDM slot for DS = 4 symbols $\times$ 1 subchannel) for DS and shall consist of 7 OFDM symbols by subchannel (i.e., 1 OFDM slot for US = 7 symbols $\times$ subchannel) for US (9a.1.3.1). For the FCH, DS/US-MAP, DCD, UCD, and DS payload in an AZ, the MAC information is first laid vertically by subchannels and then stepped horizontally in the time direction. This vertical layering allows early scheduling of DS bursts assigned to distant CPEs to compensate for propagation delays and to avoid potential interference at the CPE if overlapping A-WRAN cells with different DS/US capacity split.

In an AZ, the MAC data elements, starting from the SCH/FCH and including the first broadcast burst, shall be mapped to the DS subframe in the manner described in 7.4 for PHY-OM1 and 7.4a.3 for PHY-OM2.

In an AZ, the MAC data elements that are contained in US bursts shall be mapped to the US subframe in the manner described in 7.4 for PHY-OM1 and 7.4a.3 for PHY-OM2.

7.4b.3.2 Centralized relay zone (CRZ)

During a CRZ in the DS subframe, the centralized scheduling A-CPE transmits the MAC frames, which may be transferred from the A-BS during an AZ in the DS subframe, to the S-CPE on the scheduled slots determined by the A-BS.

A CRZ in the US subframe may contain scheduled US PHY PDUs, each transmitted from different S-CPEs for their US traffic, which forwards the centralized scheduling A-CPE. It may also include contention intervals scheduled for the following:

- CPE relay association (7.15.2.3.3)
- CPE link synchronization, relay power control, and geolocation (7.15.2.4.3)
- Relay bandwidth request
- Relay UCS notification
- Quiet period resource adjustment

The 2D (time/frequency) structure of the MAC frame in a CRZ is the same manner as that in an AZ (7.4b.3.1).

If a CRZ appeared in the DS subframe, the CRZ shall be followed by the DS AZ in the MAC frame. The MAC data bursts in the CRZ shall be entered into the first subchannel within the portion, calculated by CRZ Start Offset and Length in CRZDS-MAP IE (7.7.2.1.2.4), in the increasing order of logical subchannels until all logical subchannels are occupied in the portion. Then, the subsequent data elements, if they have not all been mapped, shall be placed in the same order on the following OFDM symbols. The balance of the last OFDM symbols within the portion shall be padded with zeros. The modulation and coding schemes for the padding zeros are defined by the DIUC for the last DS burst in CRZDS-MAP IE.

If a CRZ appeared in the US subframe, the MAC data elements that are contained in relay US bursts shall be mapped to the CRZ in the US subframe in the same manner as US subframe mapping in AZ (7.4b.3.1).

The A-BS may schedule up to four types of contention windows (see 7.13) in the CRZ:

- The relay initial ranging window is used for initializing the relay association.
- The relay periodic ranging window is used for regularly adjusting the timing and power at the CPE.

- The relay BW request window is used by CPEs to request relay US bandwidth allocation from the A-BS.
- The relay UCS notification window is used by CPEs to report a UCS with incumbents.

7.4b.3.3 Distributed relay zone (DRZ)

For local cell operations within an A-WRAN, the A-BS will schedule a DRZ for a distributed scheduling A-CPE, which is capable of managing a local cell. During a DRZ, the distributed scheduling A-CPE shall transmit the local frame preamble (9.4.1.5, 9a.4.1.1) and the DRZ-FCH (7.5.2b) on the operating channel using the modulation/coding specified in 9.2 and Table 202 for PHY-OM1 and 9a.2 and Table 231e for PHY-OM2. In order to associate with the distributed scheduling A-CPE, an S-CPE must receive the DRZ-FCH to establish communication with the distributed scheduling A-CPE. During each DRZ in the DS and US subframes, the distributed scheduling A-CPE shall manage the US and DS operations within its local cell, which may include ordinary data communication, measurement activities, coexistence procedures, and so on.

A DRZ in the US subframe may contain scheduled US PHY PDUs, each transmitted from different CPEs for their US traffic to the distributed scheduling A-CPE. It may also include contention intervals scheduled for the following:

- CPE local association (7.15.2.3.2)
- CPE local link synchronization, power control, and geolocation (7.15.2.4.2)
- Local bandwidth request
- Local UCS notification
- Quiet period resource adjustment

The 2D (time/frequency) structure of the MAC frame in a DRZ is the same manner as that in an AZ (7.4b.3.1).

If a DRZ appeared in the DS subframe, the DRZ shall be followed by the DS AZ in the MAC frame. The MAC data elements that are contained in DS bursts shall be mapped to the DRZ in the DS subframe in the same manner as the AZ in DS subframe mapping.

If a DRZ appeared in the US subframe, the MAC data elements that are contained in US bursts shall be mapped to the DRZ in the US subframe in the same manner as the AZ in US subframe mapping (7.4b.3.1).

The format of the DRZ-FCH MAC burst is described in 7.5.2b. The DRZ-FCH is modulated using the data mode selected. BCC (9.7.2.1 for PHY-OM1, 9a.7.2.1 for PHY-OM2) shall also be applied to the DRZ-FCH burst. The DRZ-FCH specifies the burst profile and the length of either the DS-MAP, if transmitted, or the US-MAP. If neither the DS-MAP nor the US-MAP is transmitted, the value shall be set to zero. The DS-MAP message, if transmitted, shall be the first MAC PDU in the burst following the DRZ-FCH. A US-MAP message, if transmitted, shall immediately follow either the DS-MAP message, if transmitted, or the DRZ-FCH. If DCD and UCD messages are transmitted in the frame, they shall immediately follow the DS-MAP and US-MAP messages. The symbols containing these broadcast MAC control messages shall be modulated using data mode 5 as described in Table 202 for PHY-OM1 or data mode 3 as described in Table 231e for PHY-OM2 with the mandatory BCC mode (see 9.7.2.1).

The distributed scheduling A-CPE may schedule up to four types of contention windows (see 7.13):

- The local Initial Ranging window is used for initializing the association.
- The local periodic ranging window is used for regularly adjusting the timing and power at the CPE.

- The local BW request window is used by CPEs to request local US bandwidth allocation from the distributed scheduling A-CPE.
- The local UCS notification window is used by CPEs to report a UCS with incumbents.

7.4b.3.4 Application of PHY Operation Mode to Zone Type

When the A-BS is operating in PHY-OM1, the DS AZ and DS CRZ shall be operated by PHY-OM1. A-CPEs shall use PHY-OM1 to communicate with the A-BS in the DS AZ and DS CRZ.

When the A-BS is operating in PHY-OM2, the DS AZ and DS CRZ shall be operated by PHY-OM2. A-CPEs shall use PHY-OM2 to communicate with the A-BS in the DS AZ and DS CRZ.

The A-CPEs operating in the DS DRZ, may be operated by either PHY-OM1 or PHY-OM2, independent of what PHY operation mode the A-BS employs in the DS.

The A-BS may switch between PHY operation modes. Switching between PHY operation modes shall be done only on a frame-by-frame basis. The A-BS and A-CPE indicate the PHY operation mode by selecting one of several different local frame preamble types (9.4.1.5, 9a.4.1.1).

The corresponding US portion of a zone shall use the same PHY operation mode as the DS portion of the zone.

WRAN CPEs (called Legacy CPEs) shall operate only in AZs, CRZs, or DRZs that are configured for PHY-OM1. To support Legacy CPEs, which can process only the Frame Preamble defined in 9.4.1, the A-BS and distributed A-CPE shall transmit only the Frame Preamble defined in 9.4.1 in the AZ/DRZ.

7.5 Control header

7.5.1 Superframe Control header

Change the following rows in Table 1:

Table 1—Superframe Control header format

Syntax	Size	Notes
MAC version	8 bits	IEEE 802.22 MAC version to which the message originator conforms. 0x01: IEEE Std 802.22 0x02: <u>IEEE Std 802.22b</u> 0x03–0xFF: <i>Reserved</i>
Padding bits	5648 bits	Padding bits to fill the rest of the 360 bits of the SCH symbol. All bits shall be set to 0.

7.5.2 Frame Control header

Change the first sentence of 7.5.2 as follows:

The format of the FCH for PHY-OM1 is shown in Table 2.

Insert the following subclauses (7.5.2a and 7.5.2b and their subclauses and tables) after 7.5.2:

7.5.2a Frame control header for PHY-OM2

7.5.2a.1 General

The format of the FCH for PHY-OM2 is shown in Table 2a. Since FCH decoding is critical, the FCH shall be encoded using the modulation specified by the PHY-OM2 as described in Table 231e. The FCH contains the length of either the DS-MAP or US-MAP that immediately follows the FCH (note that Length = 0 indicates the absence of any burst in the frame). When the DS-MAP is specified, the US-MAP length information shall be contained in the first DS-MAP information element. When the US-MAP length is indicated in the FCH, there shall be no DS burst in the current frame. DCD and UCD messages, if present, are carried by the next DS bursts specified by the DS-MAP. Location and profile of the data bursts are specified in the rest of the DS-MAP and US-MAP management messages. A HCS field occupies the last byte of the FCH.

Table 2a—Frame control header format for PHY-OM2

Syntax	Size	Note
Frame_Control_Header_Format () {		
A-BS ID	48 bits	MAC address that uniquely identifies the BS transmitting the FCH.
Length of the frame	6 bits	Indicates the length of the frame in number of OFDM symbols from the start of the frame including all preambles.
Length of the MAP message	10 bits	Specifies the length of the MAP information element following the FCH in OFDM slots. A length of 0 (zero) indicates the absence of any burst in the frame.
Frame Number	8 bits	Positive integer that represents the frame number (modulo 256). This field shall be incremented by 1.
CP	2 bits	Cyclic Prefix Factor Specifies the size of the cyclic prefix used by the PHY in the frame transmissions in this frame. Predetermined values are as follows: 00: $1/4 T_{FFT}$ 01: $1/8 T_{FFT}$ 10: $1/16 T_{FFT}$ 11: $1/32 T_{FFT}$
Self-coexistence Capability Indicator	4 bits	0000: no self-coexistence capability supported 0001: only Spectrum Etiquette 0010: Spectrum Etiquette and Frame Contention 0011–1111: <i>Reserved</i>
Extended FCH	2 bits	00: No Extended FCH 01: Extended FCH appears following this FCH 10–11: <i>Reserved</i>

Table 2a—Frame control header format for PHY-OM2 (continued)

Syntax	Size	Note
MAC version	8 bits	IEEE 802.22 MAC version to which the message originator conforms. 0x01: IEEE Std 802.22 0x02: IEEE Std 802.22b 0x03–0xFF: <i>Reserved</i>
HCS	8 bits	Header Check Sequence
}		

7.5.2a.2 Extended frame control header (Ex-FCH)

The Ex-FCH specification is shown in Table 2b. The Ex-FCH decoding is the same as FCH. The Ex-FCH provides information about the A-WRAN cell in order to protect incumbents, support self-coexistence mechanisms, and support the intra-frame and inter-frame mechanisms for management of quiet periods for sensing.

Table 2b—Extended frame control header format

Syntax	Size	Notes
Extended_FCH_Format() {		
Length	8 bits	Length of Extended FCH
Current Intra-frame Quiet Period Cycle Length	8 bits	Specified in number of frames, it indicates the spacing between the frames for which the intra-frame quiet period specification is valid. For example, if this field is set to 1, the Quiet Period Cycle repeats every frame; if it is set to 2, the Quiet Period Cycle repeats every 2 frames; etc. If this field is set to 0, no intra-frame quiet period is scheduled, or the current intra-frame quiet period is canceled.
Current Intra-frame Quiet Period Cycle Offset	8 bits	Valid only if Current Intra-frame Quiet Period Cycle Length > 0. Specified in number of frames, it indicates the offset from this Extended FCH transmission to the beginning of the first frame in the Current Intra-frame Quiet Period Cycle Length.
Current Intra-frame Quiet Period Cycle Frame Bitmap	16 bits	Valid only if Current Intra-frame Quiet Period Cycle Length > 0. Valid for each frame identified by the Current Intra-frame Quiet Period Cycle Length. Each bit in the bitmap corresponds to one frame within the frame. If the bit is set to 0, no intra-frame quiet period shall be scheduled in the corresponding frame. If the bit is set to 1, an intra-frame quiet period shall be scheduled within the corresponding frame for the duration specified by the Current Intra-frame Quiet period Duration.
Current Intra-frame Quiet Period Duration	8 bits	Valid only if Current Intra-frame Quiet Period Cycle Length > 0. If this field is set to a value different from 0 (zero), it indicates the number of symbols starting from the end of the frame during which no transmission shall take place.

Table 2b—Extended frame control header format (*continued*)

Syntax	Size	Notes
Claimed Intra-frame Quiet Period Cycle Length	8 bits	Specified in number of frames, it indicates the spacing between the frames for which the intra-frame quiet period specification claimed by an A-BS would be valid. For example, if this field is set to 1, the Quiet Period Cycle would repeat every frame; if it is set to 2, the Quiet Period Cycle would repeat every 2 frames; etc. If this field is set to 0, no intra-frame quiet period is claimed by the A-BS.
Claimed Intra-frame Quiet Period Cycle Offset	8 bits	Valid only if Claimed Intra-frame Quiet Period Cycle Length > 0. Specified in number of frames, it indicates the offset from this Extended FCH transmission to the time where the Claimed Quiet Period Cycle resulting from the inter-BS negotiation (see 7.21.2) shall become the Current Intra-frame Quiet Period Cycle.
Claimed Intra-frame Quiet Period Cycle Frame Bitmap	16 bits	Valid only if Claimed Intra-frame Quiet Period Cycle Length > 0. Valid for each frames identified by the Claimed Intra-frame Quiet Period Cycle Length. Each bit in the bitmap corresponds to one frame within each specified frame. If the bit is set to 0, no intra-frame quiet period will be scheduled in the corresponding frame. If the bit is set to 1, an intra-frame quiet period will be scheduled within the corresponding frame for the duration specified by Claimed Intra-frame Quiet period Duration.
Claimed Intra-frame Quiet Period Duration	8 bits	Valid only if Claimed Intra-frame Quiet Period Cycle Length > 0. If this field is set to a value different from 0 (zero), it indicates the number of symbols starting from the end of the frame during which no transmission will take place.
Synchronization Counter for Intra-frame Quiet Period Rate	8 bits	Valid only if Claimed Intra-frame Quiet Period Cycle Length > 0. This field is used for synchronizing the Claimed Intra-frame Quiet Period rate among overlapping A-BSs in order to allow dynamic reduction of the Intra-frame Quiet Period rate. This Quiet Period rate is defined as the number of frames with quiet periods identified by the Cycle Frame Bitmap in the frames designated by the Cycle Length, divided by this Quiet Period Cycle Length (see 7.21.2).
Synchronization Counter for Intra-frame Quiet Period Duration	8 bits	Valid only if Claimed Intra-frame Quiet Period Duration > 0. This field is used for synchronizing the Claimed Intra-frame Quiet Period Durations among overlapping A-BSs in order to allow dynamic reduction of the Intra-frame Quiet Period Duration (see 7.21.1).
Inter-frame Quiet Period Duration	4 bits	Duration of Quiet Period Indicates the duration of the next scheduled quiet period in number of frames. If this field is set to a value different from 0 (zero), it indicates the number of frames that shall be used to perform in-band inter-frame sensing.
Inter-frame Quiet Period Offset	12 bits	Time to Quiet Period Indicates the time span between the transmission of this information and the next scheduled quiet period for in-band inter-frame sensing. The 8 leftmost bits (MSB) indicate the frame number and the 4 rightmost bits (LSB) indicate the frame number when the next scheduled quiet.

Table 2b—Extended frame control header format (*continued*)

Syntax	Size	Notes
SCW Cycle Length	8 bits	Specified in number of frames. If this field is set to 0, then no SCW cycle is scheduled. This field has to be 1 or larger to be effective. To limit the number of possibilities, the field shall be one of five following choices {1, 2, 4, 8, 16}. For example, if this field is set to 1, SCW Cycle repeats every frame; if it is set to 2, SCW Cycle repeats every 2 frames; etc.
SCW Cycle Offset	8 bits	Specified in number of frames, it indicates the offset from this Extended FCH transmission to the frame where the SCW cycle starts or repeats (i.e., the frame contains SCWs and is specified by the SCW Cycle Frame Bitmap). For example, if this field is set to 0, the SCW cycle starts from the current frame.
SCW Cycle Frame Bitmap	32 bits	Valid for a unit of frame, each 2-bit in the bitmap corresponds to one frame within the frame. If the 2-bit is set to 00, there is no SCW scheduled for this frame. If the 2-bit is set to 11, a reservation-based SCW (reserved by the current WRAN) is scheduled in the corresponding frame. If the 2-bit is set to 10, a reservation-based SCW has been scheduled by a direct-neighbor WRAN cell in the corresponding frame and needs to be avoided by other WRAN cells receiving this Extended FCH. If the 2-bit is set to 01, a contention-based SCW (that could be shared with other WRANs) is scheduled by the current WRAN cell in the corresponding frame. The number of reservation-based SCWs cannot exceed 2 per WRAN cell per SCW Cycle. At least one contention-based SCW shall be scheduled in one SCW Cycle (code 01). The A-BSs shall start scheduling their contention-based SCWs from the last frame of the frame, going backward for multiple contention-based SCWs. This bitmap applies only to the frames scheduled by the SCW Cycle. NOTE—Quiet period (QP) scheduling should be done prior to the SCW scheduling so that SCWs avoid frames already reserved for QP. If SCW conflicts with QP, QP overrides the SCW.
Current DS/US Split	6 bits	Effective start time (in OFDM symbols from the start of the frame including all preambles) of the first symbol of the US allocation when an A-BS-to-A-BS interference situation has been identified by direct reception of this parameter by an A-BS from a Extended FCH or a CBP burst transmitted by another A-BS. The Allocation Start Time as provided in the US-MAP (see Table 34) shall be equal to this value if A-BS-to-A-BS interference has been identified. This value shall be set to zero if no MA-BS-to-A-BS interference has been identified (i.e., A-BS has not received this parameter from another A-BS). In this case, the Allocation Start Time in the US-MAP (see Table 34) can be defined independently on a frame-by-frame basis by the respective A-BSs based on their traffic requirement.

Table 2b—Extended frame control header format (*continued*)

Syntax	Size	Notes
Claimed US/DS Split	6 bits	Specified by each A-BS for A-BS-to-A-BS interference (i.e., when Extended FCH and/or CBP burst can be received by an A-BS directly from another A-BS) indicating the required DS/US split based in the traffic requirement of the transmitting A-BS and the negotiation process between the A-BSs (see 7.20.3). This value shall be set to zero if no A-BS-to-A-BS interference has been identified.
DS/US Change Offset	12 bits	Indicates the time span between the transmission of this information and the next scheduled change of the DS/US split where the “Claimed DS/US split” value will become the “Current DS/US split” value. The 8 leftmost bits (MSB) indicate the frame number and the 4 rightmost bits (LSB) indicate the frame number when the next DS/US split change shall take place. The value of this parameter is determined by the negotiation process between concerned A-BSs (see 7.20.3). This value shall be set to zero if no A-BS-to-A-BS interference has been identified.
Incumbent detection reporting inhibit timer	32 bits	When the BS is informed by the database service that it can continue operating on the current channel even though its CPEs are repetitively reporting an incumbent detection situation (i.e., on N or $N \pm 1$), the A-BS can use this parameter to inhibit such reporting by the CPEs for a specified period of time. This will avoid the CPEs flooding the US subframe with unnecessary incumbent detection reports. Bit 0–4: Signal type (see Table 237) Bit 5–31: Inhibit Period (number of frames)
HCS	8 bits	Header Check Sequence
}		

7.5.2b Distributed relay zone (DRZ) Frame Control header (DRZ-FCH)

The DRZ-FCH is used in a DRZ for a distributed scheduling mode. The format of the DRZ-FCH is shown in Table 2c. The DRZ-FCH shall have the same encoding as the FCH in each mode of PHY-OM1 or PHY-OM2. The DRZ-FCH contains the length of either the DS-MAP or US-MAP that immediately follows the DRZ-FCH (note that Length = 0 indicates the absence of any burst in the frame). When the DS-MAP is specified, the US-MAP length information shall be contained in the first DS-MAP information element. When the US-MAP length is indicated in the DRZ-FCH, there shall be no DS burst in the current frame. DCD and UCD messages, if present, are carried by the next DS bursts specified by the DS-MAP. Location and profile of the data bursts are specified in the rest of the DS-MAP and US-MAP management messages. A HCS field occupies the last byte of the DRZ-FCH.

Table 2c—DRZ Frame Control header (DRZ-FCH) format

Syntax	Size	Notes
DRZ Frame_Control_Header_Format() {		
Distributed Scheduling A-CPE ID	48 bits	MAC address that uniquely identifies the distributed scheduling A-CPE transmitting the DRZ-FCH.
Length of the MAP message	10 bits	Specifies the length of the MAP information element following the FCH in OFDM slots. A length of 0 (zero) indicates the absence of any burst in the frame.
Frame Number	8 bits	This field is same at the frame number indicated in FCH (Table 2)
CP	2 bits	Cyclic Prefix Factor Specifies the size of the cyclic prefix used by the PHY in the frame transmissions in this frame. Predetermined values are 00: $1/4 T_{FFT}$ 01: $1/8 T_{FFT}$ 10: $1/16 T_{FFT}$ 11: $1/32 T_{FFT}$
MAC version	8 bits	This field is same as the MAC version indicated in the FCH.
HCS	8 bits	Header Check Sequence.
}		

7.6 MAC PDU formats

7.6.1 MAC headers

7.6.1.1 Generic MAC header

Change Table 4 as follows:

Table 4—Encoding of the Type field

Type bit	Values
4	Bandwidth Request subheader Indicates whether this is a bandwidth request frame, and hence contains a special payload related to bandwidth allocation (see Table 5) 1: present 0: absent
3	ARQ feedback payload 1: present 0: absent

Table 4—Encoding of the Type field (*continued*)

Type bit	Values
2	Extended <u>Subheader types</u> Indicates whether the present Packing or Fragmentation Extended Type subheader is extended <u>present</u> 1: Extended 0: not Extended. Applicable to connections where ARQ is not enabled
1	Fragmentation/Packing subheader 1: present 0: absent
0	In the upstream: Grant Management subheader 1: present 0: absent

7.6.1.2 MAC subheaders and special payloads

Change the first paragraph of the preliminary text of 7.6.1.2 as follows:

Five types of subheaders may be present. These subheaders can be categorized into two types: subheaders attached to each PDU (per-PDU) and subheaders attached to each packed SDU (per-SDU). The Fragmentation/Packing subheader is considered to be per-PDU when the “Purpose bit” in Table 6 is set to 0 (e.g., set to Fragmentation). The other per-PDU subheaders (i.e., are the Bandwidth Request, Fragmentation/Packing Extended, Grant Management, and ARQ Feedback. The per-PDU subheaders may be inserted in MAC PDUs immediately following the generic MAC header. If indicated, the Bandwidth Request subheader shall always follow the Generic MAC header. In the upstream, if both the Grant Management subheader and Fragmentation/Packing subheader (set to Fragmentation) are indicated, the Grant Management subheader shall come first. If both the Grant Management subheader and Bandwidth Request subheader are indicated, the Grant Management subheader shall come first. If Extended Subheader and Bandwidth Request subheader are both present, the Extended Subheader comes first.

Insert the following paragraph after the first paragraph of the preliminary text of 7.6.1.2:

For the upstream, the following order for per-PDU subheaders, when multiple subheaders are present in the same MAC PDU, shall be followed: Grant Management, Extended, Bandwidth Request, Fragmentation/Packing (set to Fragmentation), and ARQ Feedback Payload. For the DS, the following order of per-PDU subheaders shall be followed: Extended, Fragmentation/Packing (set to Fragmentation), and ARQ Feedback Payload.

Change the now third paragraph of the preliminary text of 7.6.1.2 as follows:

The only per-SDU subheader is the Fragmentation/Packing subheader set to packing. There can be more than one Fragmentation/Packing subheader in a MAC PDU, all configured for packing. There can only be one Fragmentation/Packing subheader in the MAC PDU if configured for fragmentation. The Fragmentation/Packing subheader may be inserted before each MAC SDU if so indicated by setting Bit 1 in the Type field of the generic MAC Header and by setting the “Purpose bit” in Table 6 to 1.

Insert the following subclauses (7.6.1.2.5, 7.6.1.2.5.1, 7.6.1.2.5.2, and 7.6.1.2.6 and their tables) after 7.6.1.2.4:

7.6.1.2.5 Extended subheader types

7.6.1.2.5.1 General

Two types of Extended Subheaders are defined to be used by A-CPEs. The Extended Bandwidth Request Subheader is used by an A-CPE to request bandwidth to service CPEs in its relay zone. The Channel Aggregation Subheader is used during channel aggregation operation. Each Extended Subheader is defined by a Extended Subheader Type field that identifies the Extended Subheader and its functionality. Only two types (0x00 for Extended Bandwidth Request and 0x01 for Channel Aggregation) are defined; all other types (0x02–0xFF) are reserved.

7.6.1.2.5.2 Extended Bandwidth Request subheader

Extended Bandwidth Request subheaders are transmitted by the centralized scheduling A-CPE to the A-BS to request additional bandwidth for a CRZ connection. They shall be sent in a PDU by itself or in a PDU with other subheaders and/or data. (See Table 7a.)

Table 7a—Extended Bandwidth Request subheader format

Syntax	Size	Notes
Extended_BW_Request_Subheader_Format() {		
Extended Subheader Type	8 bits	0x00 = Extended BW Request Subheader
Request Node	13 bits	SID of Centralized scheduling A-CPE
Number of BR CPEs ; n	8 bits	The number of CPEs, which require bandwidth request
For ($i = 1; i \leq n; i++$){	Variable	
BW Request Type	2 bits	00: CDMA bandwidth request 01: Bandwidth request subheader 10–11: <i>Reserved</i>
SID	13 bits	SID of CPE, which require bandwidth request
Type	1 bit	Indicates the type of the bandwidth request adjustment 0: incremental 1: aggregate
BR	20 bits	The number of bytes of US bandwidth requested by the CPE. The request shall not include any PHY overhead.
CRZ bandwidth ranging code	8 bits	CRZ bandwidth ranging codes when BW Request Type is set to 0
}		
}		

7.6.1.2.5.3 Channel Aggregation subheader

The format of Channel Aggregation subheader is shown in Table 7b. This Channel Aggregation subheader is used to manage the aggregation data sequence during the multi-channel operation. The channel aggregation header with fixed-length size of 3 bytes shall be added to each PDU after the generic MAC header.

Table 7b—Channel Aggregation subheader format

Syntax	Size	Notes
Channel_Aggregation_Subheader_Format() {		
Extended Subheader Type	8 bits	0x01 = Channel Aggregation Extended Subheader
Aggregation ID	16 bits	Indicates the sequence management ID of the transmitted data during multi-channel operation. The value of Aggregation ID is from 0 to 8191. The Aggregation ID shall be incremented by one after each transmission and shall be reset to 0 after the maximum value (8191).
}		

7.6.1.3 CBP MAC PDU format

Change the last sentence of the preliminary text in 7.6.1.3 as follows:

As discussed in 7.20.1, the coexistence beacon MAC PDU described in Table 8 (for PHY-OM1) and Table 8a (for PHY-OM2) is utilized by the CBP packets.

Change the title of Table 8 as follows:

Table 8—CBP_MAC_PDU format (PHY-OM1)

Insert the new Table 8a immediately after Table 8 in 7.6.1.3 as follows:

Table 8a—CBP_MAC_PDU format (PHY-OM2)

Syntax	Size	Notes
CBP_MAC_PDU_Format() {		
Length	8 bits	The length of bytes of the CBP MAC PDU including the MAC header and the CRC.

Table 8a—CBP_MAC_PDU format (PHY-OM2) (continued)

Syntax	Size	Notes
FCH and Extended FCH Index	4 bits	FCH and Extended FCH Data included in the CBP_MAC_PDU contains the sum of the following elements (see Table A1 and Table 2a): 0000: 8 first parameters of the FCH for PHY-OM2 (Table A1) = 11 bytes 1000: 10 parameters related to intra-frame QP of the Extended FCH (Table 2a) = 12 bytes 0100: 2 parameters related to inter-frame QP of the Extended FCH (Table 2a) = 2 bytes 0010: 3 parameters on SCW scheduling of the Extended FCH (Table 2a) = 6 bytes 0001: 3 parameters on DS/US Split of the Extended FCH (Table 2a) = 3 bytes Note that this last 3-parameter segment can be included only in CBP bursts transmitted by A-BSs.
FCH and Extended FCH Data	Variable (integer number of bytes)	Data extracted from the FCH and Extended FCH transmitted by A-BS sourcing this CBP. This data includes the A-BS_ID. Only the useful information contained in the FCH and Extended FCH should be replicated here. This indicates that the FCH and Extended FCH should be built with IEs only present when needed. Table A1 and Table 2a should be modified accordingly.
Frame Number	8 bits	The frame number in which the CBP burst was transmitted.
HCS	8 bits	Header Check Sequence.
IEs	Variable (integer number of bytes)	CBP information elements (see 7.6.1.3.1).
}		

7.6.1.3.1 CBP information elements

Insert the following paragraph after the first paragraph of the preliminary text of 7.6.1.3.1:

If an A-BS is generating a CBP packet to be forwarded by a distributed A-CPE or an S-CPE attached to a distributed S-CPE, it may optionally add a CBP Local Cell ID IE to the CBP MAC PDU. The purpose of the CBP Local Cell ID IE is to provide the identity of the local cell maintained by a distributed A-CPE. The CBP MAC PDU header (which would contain contents of transmission types indicated in 7.20.4) would contain the MAC Address of the A-BS that serves the distributed A-CPE. When the CBP Local Cell ID IE is added to a CBP MAC PDU, the transmissions indicated in 7.20.4 would contain the MAC Address of the A-BS in the CBP MAC PDU header.