



INTERNATIONAL TELECOMMUNICATION UNION

ITU-T

TELECOMMUNICATION
STANDARDIZATION SECTOR
OF ITU

U.24

TELEGRAPH SWITCHING

SIGNALLING OVER RADIO AND MULTIPLEXED CHANNELS

REQUIREMENTS FOR TELEX AND GENTEX OPERATION TO BE MET BY SYNCHRONOUS MULTIPLEX EQUIPMENT DESCRIBED IN RECOMMENDATION R.44

ITU-T Recommendation U.24

(Extract from the *Blue Book*)

NOTES

1 ITU-T Recommendation U.24 was published in Fascicle VII.2 of the *Blue Book*. This file is an extract from the *Blue Book*. While the presentation and layout of the text might be slightly different from the *Blue Book* version, the contents of the file are identical to the *Blue Book* version and copyright conditions remain unchanged (see below).

2 In this Recommendation, the expression “Administration” is used for conciseness to indicate both a telecommunication administration and a recognized operating agency.

© ITU 1988, 1993

All rights reserved. No part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from the ITU.



Documents
Document Sharing Hub

Recommendation U.24

REQUIREMENTS FOR TELEX AND GENTEX OPERATION TO BE MET BY SYNCHRONOUS MULTIPLEX EQUIPMENT DESCRIBED IN RECOMMENDATION R.44

(Mar del Plata, 1968)

The CCITT,

considering

- (a) that it may be desirable to use synchronous systems described in Recommendation R.44 in the teleprinter switching networks;
- (b) that it is essential to transmit the full range of telex signals for types A, B and C signalling;

unanimously declares the view

(1) that where it is necessary to receive signals with a nominal cycle of 7 units (see the Recommendation cited in [1]), it will be necessary to insert suitable storage to reconcile the two character rates (400 and 411 per minute);

(2) that type A and B signals in accordance with Recommendation U.1 and U.2 and type C signals in accordance with Recommendation U.11 should be accepted for transmission through the synchronous system. However, in the case of type A signalling, the delay between the start of the call-confirmation signal and the proceed-to-select signal should be increased to, at least, 150 ms;

(3) that the call signal should be transmitted through the synchronous system with the minimum delay obtainable with the particular method of multiplexing in use, e.g., element interleaving, in order to reduce the incidence of head-on collisions with both-way operation. The maximum delay due to the multiplex equipment should be limited to 60 ms;

(4) that the maximum delay on the call-confirmation signal due to the multiplex equipment should be 60 ms in the case of type A signalling, and 120 ms in the case of type B signalling;

(5) that the maximum delay on the start of the reception-confirmation signal due to the multiplex equipment should be 60 ms in the case of type C signalling;

(6) that the maximum delay on the proceed-to-select signal due to the multiplex equipment should be 450 ms in the case of type A signalling, and 120 ms in the case of type B signalling;

(7) that the maximum delay on the call-connected signal due to the multiplex equipment should be 450 ms (type A and type B signalling);

(8) that the maximum delay on a teleprinter character due to the multiplex equipment should be 450 ms;

(9) that the maximum delay on the clear and clear-confirmation signals due to the multiplex equipment should be 450 ms;

(10) that the tolerance of the type A and B pulse signals after retransmission through the synchronous multiplex system will be stated below:

a) *Call-confirmation and proceed-to-select signal – type B signalling*

The duration of the pulse after transmission through the synchronous system will not be less than 17.5 ms nor more than 50 ms.

b) *Dial pulses – type B signalling*

Speed – $\pm 3\%$ of the mean speed of input measured for digit 0 (normally 9 to 11 pulses per second).

Ratio – The duration of stop polarity pulses will not be less than 32 ms; the duration of start polarity pulses will not be less than 44 ms.

Under certain circumstances the retransmitted dial signals may include pulses of stop polarity having durations of up to 73 ms and pulses of start polarity having durations of up to 98 ms. Where this is so and the incoming switching equipment cannot accept pulses with these characteristics a dial pulse regenerator should be inserted between the output of the multiplex circuit and the input of the switching equipment.