PD IEC/TR 61292-1:2022

BSI Standards Publication

Optical amplifiers

Part 1: Parameters of optical fibre amplifier components

Documents
Document Sharing Hub

Full document details: PD IEC/TR 61292-1:2022

National foreword

This Published Document is the UK implementation of IEC TR 61292-1:2022. It supersedes PD IEC/TR 61292-1:2009, which is withdrawn.

The UK participation in its preparation was entrusted to Technical Committee GEL/86/3, Fibre optic systems and active devices.

A list of organizations represented on this committee can be obtained on request to its committee manager.

Contractual and legal considerations

This publication has been prepared in good faith, however no representation, warranty, assurance or undertaking (express or implied) is or will be made, and no responsibility or liability is or will be accepted by BSI in relation to the adequacy, accuracy, completeness or reasonableness of this publication. All and any such responsibility and liability is expressly disclaimed to the full extent permitted by the law.

This publication is provided as is, and is to be used at the recipient's own risk.

The recipient is advised to consider seeking professional guidance with respect to its use of this publication.

This publication is not intended to constitute a contract. Users are responsible for its correct application.

This publication is not to be regarded as a British Standard.

© The British Standards Institution 2022
Published by BSI Standards Limited 2022

ISBN 978 0 539 18424 2

ICS 33.160.10; 33.180.30

Compliance with a Published Document cannot confer immunity from legal obligations.

This Published Document was published under the authority of the Standards Policy and Strategy Committee on 31 July 2022.

Amendments/corrigenda issued since publication

Date	Text affected

Documents
Document Sharing Hub

Full document details: PD IEC/TR 61292-1:2022

IEC TR 61292-1

Edition 3.0 2022-05

TECHNICAL REPORT

Optical amplifiers –
Part 1: Parameters of optical fibre amplifier components

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 33.160.10; 33.180.30

ISBN 978-2-8322-0299-9

Warning! Make sure that you obtained this publication from an authorized distributor.

® Registered trademark of the International Electrotechnical Commission

Documents
Document Sharing Hub

Full document details: PD IEC/TR 61292-1:2022

CONTENTS

FOREWORD 4
1 Scope 6
2 Normative references 6
3 Terms, definitions, abbreviated terms and symbols 6
3.1 Terms and definitions 6
3.1.1 Parameters for active fibres 6
3.1.2 Parameters for pump lasers 8
3.1.3 Parameters for WDM couplers 11
3.1.4 Parameters for pump WDM couplers 12
3.1.5 Parameters for optical isolators 12
3.1.6 Parameters for ASE rejection filters 14
3.1.7 Parameters for pump rejection filters 14
3.1.8 Parameters for gain flattening filters 15
3.1.9 Parameters for tap couplers 16
3.1.10 Parameters for PIN-photodiodes 17
3.1.11 Parameters for variable optical attenuators (VOAs) 18
3.1.12 Parameters for optical connectors 19
3.2 Abbreviated terms 19
3.3 Symbols 20
4 OFA components 21
5 Parameters of optical fibre amplifier components 24
5.1 Active fibre 24
5.1.1 Function and technical outline 24
5.1.2 Parameters for active fibres 24
5.2 Gain fibre for FRA 25
5.2.1 Function and technical outline 25
5.2.2 Parameters for gain fibres of FRAs 25
5.3 Pump laser 25
5.3.1 Function and technical outline 25
5.3.2 Parameters for pump lasers 25
5.4 WDM coupler (for combining signal light and pump light) 26
5.4.1 Function and technical outline 26
5.4.2 Parameters for WDM couplers 26
5.5 Pump WDM coupler 26
5.5.1 Function and technical outline 26
5.5.2 Parameters for pump WDM couplers 26
5.6 Polarization beam combiner (PBC) 26
5.6.1 Function and technical outline 26
5.6.2 Parameters for PBC 26
5.7 Optical isolator 27
5.7.1 Function and technical outline 27
5.7.2 Parameters for optical isolators 27
5.8 ASE rejection filter 27
5.8.1 Function and technical outline 27
5.8.2 Parameters for ASE rejection filters 27
5.9 Pump rejection filter 27
5.9.1 Function and technical outline 27

AVA Documents
Document Sharing Hub

5.9.2 Parameters for pump rejection filter 27
5.10 Gain flattening filter (GFF) 28
5.10.1 Function and technical outline 28
5.10.2 Parameters for gain flattening filters 28
5.11 Tap coupler 28
5.11.1 Function and technical outline 28
5.11.2 Parameters for tap couplers 28
5.12 PIN-photodiode (PIN-PD) 29
5.12.1 Function and technical outline 29
5.12.2 Parameters for PIN-photodiodes 29
5.13 Variable optical attenuator (VOA) 29
5.13.1 Function and technical outline 29
5.13.2 Parameters for variable optical attenuators 29
5.14 Optical connectors 29
5.14.1 Function and technical outline 29
5.14.2 Parameters for optical connectors 30
Bibliography 31

Figure 1 – Example of the components inside an EDFA operating in a co-propagating pumping scheme 23
Figure 2 – Example of the component layout of a distributed Raman amplifier (DRA) 23
Figure 3 – Example of the component layout of a lumped (or discrete) Raman amplifier 24

Table 1 – Documents defining terms and definitions of each component 22

Documents
Document Sharing Hub

Full document details: PD IEC/TR 61292-1:2022

INTERNATIONAL ELECTROTECHNICAL COMMISSION

OPTICAL AMPLIFIERS –

Part 1: Parameters of optical fibre amplifier components

FOREWORD

1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
6) All users should ensure that they have the latest edition of this publication.
7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

IEC TR 61292-1 has been prepared by subcommittee 86C: Fibre optic systems and active devices, of IEC technical committee 86: Fibre optics. It is a Technical Report.

This third edition cancels and replaces the second edition published in 2009. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

a) Change of document title from "Parameters of amplifier components" to "Parameters of optical fibre amplifier components";
b) Addition of parameters for optical components used in fibre Raman amplifiers;
c) Addition of Table 1, listing various documents that specify terms and definitions for optical components used in optical fibre amplifiers;
d) Addition of Figure 2 and Figure 3, showing typical component layouts for distributed and lumped fibre Raman amplifiers;

Documents
Document Sharing Hub

Full document details: PD IEC/TR 61292-1:2022

e) Harmonization of the descriptions of optical component parameters with the definitions in other standards on optical components.

The text of this Technical Report is based on the following documents:

Draft	Report on voting
86C/1775/DTR	86C/1784/RVDTR

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this Technical Report is English.

A list of all parts of the IEC 61292 series, published under the general title *Optical amplifiers,* can be found on the IEC website.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/publications.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

Documents
Document Sharing Hub

Full document details: PD IEC/TR 61292-1:2022

OPTICAL AMPLIFIERS –

Part 1: Parameters of optical fibre amplifier components

1 Scope

This part of IEC 61292, which is a Technical Report, applies to optical components of optical fibre amplifiers (OFAs). This document provides information about the most relevant parameters of these optical components, especially for erbium doped fibre amplifiers (EDFAs) and fibre Raman amplifiers (FRAs). It provides introductory information for a better understanding operation and applications of EDFAs and FRAs.

NOTE IEC TR 61292-6 provides more technical information on FRAs.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 61291-1:2018, *Fibre amplifiers – Generic specification*

IEC TR 61931, *Fibre optic – Terminology*

3 Terms, definitions, abbreviated terms and symbols

3.1 Terms and definitions

For the purposes of this document, the terms and definitions given in IEC 61291-1, IEC TR 61931, and the following apply.

ISO and IEC maintain terminology databases for use in standardization at the following addresses:

- IEC Electropedia: available at https://www.electropedia.org/
- ISO Online browsing platform: available at https://www.iso.org/obp

3.1.1 Parameters for active fibres

3.1.1.1
maximum input signal power
<active fibres> maximum power of the input signal above which the active fibre gets damaged, causing impossibility of normal operation for a given active fibre

3.1.1.2
insertion loss at out-of-band wavelength
<active fibres> insertion loss for a signal at the specified out-of-band wavelength(s) for a given active fibre

Note 1 to entry: IEC 61290-7-1 defines the measurement procedure of out-of-band insertion loss.

[SOURCE: IEC 61291-1:2018, 3.2.1.59, modified – Term changed from "out-of-band insertion loss", the specific use "active fibres" has been added, and Note 1 to entry has been added.]

AVA Documents
Document Sharing Hub

3.1.1.3
polarization-dependent gain
<active fibres> maximum variation of the active fibre gain due to a variation of the state of polarization of the input signal

[SOURCE: IEC 61291-1:2018, 3.2.1.12, modified – The notes to entry have been deleted and the specific use has been added.]

3.1.1.4
polarization mode dispersion
PMD
<active fibres> maximum PMD at the signal wavelength which is launched into the input port of the active fibre and exits from signal output port of the active fibre

Note 1 to entry: PMD is expressed in ps.

Note 2 to entry: When an optical signal travels through an optical fibre, optical component or subsystem (e.g. an OFA), the change in the shape and width of the pulse due to the differential group delay (DGD) [the propagation delay difference between the two principal states of polarization (PSPs)] and to the waveform distortion for each PSP, is due to PMD. PMD, together with polarization dependent loss (PDL) and polarization dependent gain (PDG), can introduce large waveform distortions leading to an unacceptable bit error ratio increase.

Note 3 to entry: The level of PMD can depend on temperature and operating conditions.

3.1.1.5
mode field diameter
MFD
2*w*
<active fibres> for a given active fibre, a measure of the transverse width of the guided mode of a single-mode fibre, given from the far-field intensity distribution $F(q)$ by:

$$2w = \frac{2}{\pi}\left[\frac{2\int_0^\infty q^3 F(q)^2\,dq}{\int_0^\infty qF(q)^2\,dq}\right]^{-\frac{1}{2}}$$

where

$$q = \sin(\theta)/\lambda$$

Note 1 to entry: For Gaussian distributions in single-mode fibres the mode field diameter is the diameter at the 1/e points of the optical field amplitude distribution, which is also equivalent to the $1/e^2$ points of the optical power distribution.

Note 2 to entry: Sometimes the MFD of active fibres is smaller than that of conventional single-mode fibres in order to concentrate the pump power with the signal optical power.

[SOURCE: IEC TR 61931:1998, 2.4.31, modified – Specific use added and Note 2 to entry has been added.]

3.1.1.6
cut-off wavelength
<active fibres> for a given active fibre, the free space wavelength corresponding to the cut-off normalized frequency of a mode

[SOURCE: IEC TR 61931:1998, 2.4.38, modified – Specific use has been added.]

3.1.1.7
cladding diameter
<active fibres> for a given active fibre, the diameter of the circle defining the cladding outline

AVA Documents
Document Sharing Hub

[SOURCE: IEC TR 61931, 2.3.39]

3.1.1.8
cladding non-circularity
<active fibres> for a given active fibre, the difference between the diameters of the two circles defined by the cladding tolerance field divided by the cladding diameter

[SOURCE: IEC TR 61931:1998, 2.3.51, modified – Specific use has been added.]

3.1.1.9
mode field concentricity error
<active fibres> for a given active fibre, the distance between the mode field centre and the cladding centre

[SOURCE: IEC TR 61931:1998, 2.4.34, modified – Specific use has been added.]

3.1.1.10
composition
<active fibres> composition of the active fibre, intended as the host glass composition as well as the dopant element and its concentration

3.1.1.11
length
<active fibres> length of the active fibre

Note 1 to entry: Changing fibre length can optimize gain characteristics of EDFA.

3.1.1.12
dopant distribution
<active fibres> concentration of dopant rare-earth ions in the active fibre as a function of the fibre radial coordinate

3.1.1.13
slope efficiency
<active fibres> for a given active fibre, the slope of the laser output versus pump power curve under specified operating conditions

Note 1 to entry: IEC TR 63309 defines the measurement procedure of slope efficiency.

3.1.1.14
saturation pump power
<active fibres> for a given active fibre, the minimum pump power above which the small-signal gain shows no further increase

3.1.1.15
threshold pump power
<active fibres> minimum pump power necessary to reach a small-signal gain equal to 1 in a given active fibre when the fibre length is short enough so that the pump optical power remains constant along the fibre

Note 1 to entry: IEC TR 63309 defines the measurement procedure of threshold pump power.

3.1.2 Parameters for pump lasers

3.1.2.1
pumping wavelength
<pump lasers> centroidal or peak wavelength of the emission spectrum of the pump laser

Documents
Document Sharing Hub

Full document details: PD IEC/TR 61292-1:2022

Note 1 to entry: In erbium-doped fibre amplifiers (EDFAs), pumping wavelengths of 980 nm and 1 480 nm are commonly used. In fibre Raman amplifier (FRAs), the pumping wavelength depends on the wavelength of the signal light. In this case, the frequency of the pump laser should be about 13 THz higher than that of the signal light.

Note 2 to entry: Centroidal wavelength is defined in IEC 61280-1-3.

Note 3 to entry: For multi-longitudinal-mode laser diodes (LD), centroidal wavelength is often used. For single-longitudinal-mode LD, peak wavelength is often used.

Note 4 to entry: For 980 nm LD, a wavelength stabilizer by FBG is sometimes used to the output pigtail of the LD.

3.1.2.2
pumping scheme
<pump lasers> set-up of the OFA characterized by the direction of pump optical power propagation with respect to signal direction

Note 1 to entry: Usually, three schemes are used: co-propagating, where the pump and the signal propagate through the active fibre in the same direction; counter-propagating, where the signal and the pump propagate through the active fibre in opposite directions; bi-directional, where two pumps propagate simultaneously through the active fibre in both directions. Regarding pumping schemes other than pump direction, a polarization combining scheme and a wavelength combining scheme are considered in the detailed design to increase pump power. However, a single laser diode pump scheme is described as a classic example in this technical report.

Note 2 to entry: IEC TR 61292-3 describes the pumping method.

3.1.2.3
pumping power
<pump lasers> at the active fibre or at the output of the pump, optical power associated with the pump, injected into the active fibre

3.1.2.4
centroidal wavelength
<pump lasers> mean or average wavelength of an optical spectrum of pump LD

Note 1 to entry: Regarding many pump LDs of 980 nm and 1 480 nm, centroidal wavelength λ_{avg} is applied for centre wavelength λ_c. The definition of centroidal wavelength is described as follows:

$$\lambda_{avg} = \left(\frac{1}{P_0}\right)\sum_{i=1}^{N} P_i\,\lambda_i$$

where

λ_i is the wavelength of the ith peak point (nm);

i corresponds to mode number for output spectra of pump LD;

P_i is the power of the ith peak point (nW); and

P_0 is the total power summed for all peak points (nW):

$$P_0 = \sum_{i=1}^{N} P_i$$

N is the number of peak points.

Note 2 to entry: The pump efficiency of an EDF depends on the overlap integral of the EDF absorption spectrum and the pump LD spectrum, so the centroidal wavelength of the pump laser is crucial for EDF pumping.

3.1.2.5
peak wavelength
<pump lasers> wavelength which corresponds to the maximum power value of the optical spectrum of pump LD

Documents
Document Sharing Hub
Full document details: PD IEC/TR 61292-1:2022