



AEROSPACE INFORMATION REPORT

AIR6540™**REV. D**Issued 2019-01
Revised 2025-03

Superseding AIR6540C

Fundamentals in Wire Selection and Sizing for Aerospace Applications

RATIONALE

Equation 28 was missing a wire length value to the equation.

INTRODUCTION

The selection of aerospace wire sizes per AS50881 is a straightforward process to complete. For electrical power feeders, protection devices, and distribution applications, additional information not found in AS50881, as well as environmental and installation constraints information, is required to size correctly a wire(s) to a precise set of design requirements.

1. SCOPE

The scope of this report is to capture fundamental principles of selecting a wire size for an aerospace application using the method prescribed in AS50881 and additional calculations, not found in AS50881, to ensure the wire selection will adequately perform in the specific physical and environmental conditions.

This report covers wire selection and sizing as part of the electrical wire interconnection systems (EWIS) used in aerospace vehicles. Aerospace vehicles include manned and unmanned airplanes, helicopters, lighter-than-air vehicles, missiles, and external pods. This document does not apply to wiring inside of airborne electronic equipment but shall apply to wiring externally attached to such equipment.

Wire selection must consider physical and environmental factors to size wires such that they have sufficient mechanical strength, do not exceed allowable voltage drop levels, are protected by materials or circuit protection devices, and meet circuit current carrying requirements. For electrical power feeders and distribution or EWIS applications, other information and environmental and installation limitations are also needed to adequately evaluate and select the correct wire size for a specific application and meet design requirements.

This report presents only fundamental principles and guidelines and cannot adequately cover all aspects and complexities associated with wire selection and sizing. Some of the calculations in this report have been simplified to demonstrate the process for validating a wire size selection for a design application. More precise calculations should be investigated and evaluated to ensure proper assessment of each individual calculation in this report.

SAE Executive Standards Committee Rules provide that: "This report is published by SAE to advance the state of technical and engineering sciences. The use of this report is entirely voluntary, and its applicability and suitability for any particular use, including any patent infringement arising therefrom, is the sole responsibility of the user."

SAE reviews each technical report at least every five years at which time it may be revised, reaffirmed, stabilized, or cancelled. SAE invites your written comments and suggestions.

Copyright © 2025 SAE International

All rights reserved. No part of this publication may be reproduced, stored in a retrieval system, transmitted, in any form or by any means, electronic, mechanical, photocopying, recording, or otherwise, or used for text and data mining, AI training, or similar technologies, without the prior written permission of SAE.

TO PLACE A DOCUMENT ORDER: Tel: 877-606-7323 (inside USA and Canada)
Tel: +1 724-776-4970 (outside USA)
Fax: 724-776-0790
Email: CustomerService@sae.org
<http://www.sae.org>

SAE WEB ADDRESS:

Full document details: SAE AIR6540D

For more information on this standard, visit
<https://www.sae.org/standards/content/AIR6540D/>

Documents

Standard, visit Sharing Hub

2. REFERENCES

2.1 Applicable Documents

The following publications form a part of this document to the extent specified herein. The latest issue of SAE publications shall apply. The applicable issue of other publications shall be the issue in effect on the date of the purchase order. In the event of conflict between the text of this document and references cited herein, the text of this document takes precedence. Nothing in this document, however, supersedes applicable laws and regulations unless a specific exemption has been obtained.

2.1.1 SAE Publications

Available from SAE International, 400 Commonwealth Drive, Warrendale, PA 15096-0001, Tel: 877-606-7323 (inside USA and Canada) or +1 724-776-4970 (outside USA), www.sae.org.

AS29606 Wire, Electrical, Stranded, Uninsulated Copper, Copper Alloy, or Aluminum, or Thermocouple Extension, General Specification for

AS50881 Wiring Aerospace Vehicle

2.1.2 ASTM Publications

Available from ASTM International, 100 Barr Harbor Drive, P.O. Box C700, West Conshohocken, PA 19428-2959, Tel: 610-832-9585, www.astm.org.

ASTM B193 Standard Test Method for Resistivity of Electrical Conductor Materials

2.1.3 ECIA Publications

Available from Electronic Components Industry Association, 13873 Park Center Road, Suite 315, Herndon, VA 20171, Tel: 571-323-0294, www.ecianow.org.

EIA Standard RS-214 Method for Calculation of Current Ratings on Hookup Wire, November 1958.

2.1.4 FAA Publications

Available from Federal Aviation Administration, 800 Independence Avenue, SW, Washington, DC 20591, Tel: 866-835-5322, www.faa.gov.

AC 43.13-1B Acceptable Methods, Techniques, and Practices - Aircraft Inspection and Repair

2.1.5 U.S. Government Publications

Copies of these documents are available online at <https://quicksearch.dla.mil>.

MIL-W-5088L Aerospace Vehicle Wiring Specification

NOTE: MIL-W-5088L, dated December 9, 1992, is inactive for new design and is no longer used, except for replacement purposes. Future designs should refer to AS50881.

2.1.6 Other Publications

2.1.6.1 Exner, D.W. and Singer, G.H. (1953). Impedance data for 400-cycle aircraft distribution systems. *Transactions of the American Institute of Electrical Engineers, Part II: Applications and Industry*, 71(6). <https://doi.org/10.1109/TAI.1953.6371310>.

2.1.6.2 Dwight, H.G. (1954). *Electrical Elements of Power Transmission Lines*, Chapter 8. Macmillan.

- 2.1.6.3 Fink, D.G. and Beaty, H.W. (1978). *Standard Handbook for Electrical Engineers* (11th ed.). McGraw Hill.
- 2.1.6.4 Schach, M. and Kidwell, R.E. (1953). Continuous current and temperature rise in bundled cables for aircraft. *Transactions of the American Institute of Electrical Engineers, Part II: Applications and Industry*, 71(6). <https://doi.org/10.1109/TAI.1953.6371304>.
- 2.1.6.5 Stevenson Jr., W.D. (1962). *Elements of Power System Analysis* (2nd ed.), Chapter 4. McGraw Hill.
- 2.1.6.6 Woodruff, L.F. (1953). *Principles of Electric Power Transmission* (2nd ed.), Chapter 2, Item 18. John Wiley & Sons.

2.2 Abbreviations

ASTM	American Society for Testing and Materials
AWG	American Wire Gauge
IACS	International Association of Classification Societies
SI	International System of Units

2.3 Definitions

AIRCRAFT: An airplane, helicopter, or lighter-than-air vehicle.

AIRPLANE: Any heavier-than-air vehicle that is supported for flight by the dynamic action of air on its surfaces.

BRANCH: A section of wire harness that divides off and extends to a point of termination.

BUNDLE: Any number of wire harness groups or branches routed and supported together along some distance within the aircraft.

CHAFING: Repeated relative motion between wiring system components, or between a wiring system component and structure or equipment, that results in a rubbing action that causes wear, which will likely result in mechanical or electrical failure during the aerospace vehicle's specified service life.

COMPONENT: A component is an aircraft article made up of parts and approved for installation on a type-certificated aircraft. Type-certification is awarded when applicable design data has been granted an approval (for example, type certificate, supplemental type certificate, technical standard order authorization, parts manufacturer approval, or equivalent) by the relevant civil aviation authority. Examples of components are motors, gearing assemblies, generators, alternators, inverters, converters, drives, controls, switches, fuses, buses, distribution units, wire harnesses, batteries, solenoids, relays, and others.

CONNECTOR PLUG: The connector containing the coupling ring or active retention device of the mating pair.

CONNECTOR RECEPTACLE: The connector containing the static retention device of the mating pair.

ELECTRICAL CABLE: Two or more insulated conductors, solid or stranded, contained in a common covering, or two or more insulated conductors twisted or molded together without common covering, or one insulated conductor with a metallic covering shield or outer conductor.

ELECTRICAL WIRING INTERCONNECT SYSTEM (WIRING) - EWIS: Wires, electrical or fiber optical cables, groups, harnesses and bundles and their terminations, associated hardware, and support installed in the aircraft. When used as a verb, it is the act of fabricating and installing these items in the vehicle.

FIBER OPTIC CABLE: A cable designed to transmit light waves between a light transmission source and a receiver. In signal applications, the transmitter and receiver include devices that are used to convert between optical and electronic pulses. Typical cables include a glass or plastic core, a layer of cladding having a lower refractor index to refract or totally reflect light inward at the core/cladding boundary, a buffer, strength members, and jacketing to protect the inner cable from environmental damage.

FIREPROOF: The capability of a material or component to withstand a 2000 °F flame (± 150 °F) for 15 minutes minimum while still fulfilling its design purpose. Clarification: The term “fireproof,” when applied to a connector, backshell, or accessory hardware mounted and secured to a structure used to confine fires within designated fire zones, means that the connector system will perform this function (conduct electrical power and prevent flame/heat penetration) under conditions likely to occur in such zones and will withstand a 2000 °F flame (± 150 °F) for 15 minutes minimum. A connector system consists of mated connectors, fully wired, backshells or conduit assemblies, and mounting hardware installed on a structural panel (firewall).

FIRE RESISTANT: The capability of a connector system (as defined in “fireproof”) to perform its intended function in designated fire zone areas under heat and other abnormal conditions, as encountered in power plants and auxiliary power unit (APU) installations, that are likely to occur at the location or area and to withstand a 2000 °F flame (± 150 °F) for 5 minutes minimum.

FIREWALL: A structural panel designed to prevent a hazardous quantity of air, fluid, or flame from exiting a designated fire zone in which a fire may erupt and cause additional hazard to the aircraft. This structural panel permits penetration of fluid carrying lines (fuel and hydraulics), ducts, electrical power, and control cables or rods using suitable fireproof components or fittings. The firewall and the attached components or fittings shall withstand flame penetration and shall not exhibit backside ignition for the required test time (15 minutes). The backside temperature should not exceed 450 °F maximum, and the structural panel should have fireproof insulating material installed to limit the backside temperature.

GROUP: A “wire group” is several wires and/or electrical or optical cables and their terminations secured together within the structure of a bundle or harness. Groups normally contain wires and/or electrical or optical cables pertaining to a single circuit or routed to a single item of equipment.

HARNESS: An assembly of any number of wires, electrical or optical cables, and/or groups and their terminations that is designed and fabricated to allow for installation and removal as a unit. A harness may be an open harness or a protected harness.

HIGH DENSITY HARNESS: A protected harness designed to save weight and space that has a majority of wire types specified for protected wire applications.

OPEN HARNESS: An assembly of wires and/or electrical or optical cables that does not include a protective outer covering.

PROTECTED HARNESS: A harness that employs some overall outer covering to provide additional electromagnetic and/or mechanical protection for the wires and/or electrical or optical cables contained within. The added protection may consist of an overbraid, tape wrap, conduit, or some other form of protection.

WIRE: A single metallic conductor of solid, stranded, or tinsel construction designed to carry current in an electric circuit but not having a metallic covering, sheath, or shield. For this report, “wire” refers to “insulated electric conductor.”

WIRING (see Electrical Wiring Interconnect System - EWIS): The term “wiring,” wherever used throughout this report, shall be interpreted as EWIS.

WIRING DEVICES: The necessary parts and materials that are used in the installation of electrical or optical wiring, such as terminals, connectors, junction boxes, conduit, clamps, insulation, and supports.

WIRING SEGMENT: A length of wire that is continuous and unbroken between its two intended points of termination. A wire segment that has been broken and then repaired is still considered to be one wire segment.

3. WIRE SELECTION PROCEDURE

This report provides fundamental guidelines to simplify the process for selecting the proper wire size based on the AS50881 standard, as well as other equations not found in AS50881. It also provides valuable information for the electrical design engineer to verify the proper wire selection and validate a set of system design requirements, which includes meeting environmental and installation constraints. This report does not make recommendations on insulation system voltage ratings. Some practical examples will be provided, and focus will be on selecting wire sizes for power feeder applications.

Prior to starting the process of wire selection and sizing, all loads must be known not only for steady-state conditions but also for transient or dynamic operations, including faulted conditions. This requires calculating and knowing the nature of the peak and continuous values of the loads in a circuit, including whether the wires connect to flight critical, mission critical, or noncritical loads.

Wire selection must consider physical and environmental factors to size wires such that they have sufficient mechanical strength, do not exceed allowable voltage drop levels, are protected by materials and circuit protection devices, and meet circuit current carrying requirements.

All wire sizes have a maximum continuous current rating; the maximum current of each wire will dictate the size of most wires in an aircraft. Current carrying capacity is related to the effects of heat on wire insulation due to the resistance and current flow; maximum operating temperatures must not be exceeded. If wire materials had zero resistance, then any size wire could carry any amount of current; however, this is not the case. Wire gauge dictates a resistance over the wire length, usually expressed in ohms per foot; longer wires have increased resistance, so larger wire sizes may be required. The ability of a wire to reject heat is a function of the surface area and the availability of a heat transfer path to reject heat; wires in a bundle or harness do not reject heat as efficiently. In this report, the effect of heat conduction in axial direction is not addressed.

Wire selection may follow a straightforward approach; however, it is also important to understand the variables involved and the design and environmental constraints that factor into wire selection and sizing. There are fundamental principles and guidelines captured in numerous references listed, which should be consulted, that provide specific requirements. While basic calculations presented are simplified to illustrate the process, more precise calculations must be investigated and evaluated to ensure accurate assessments. Also, rules of thumb or table lookups in most cases result in underestimated values compared to calculated values, and calculation methodologies also differ, so pick the “best” one for the application.

Wire selection involves either calculating or using table lookups to determine the allowable current carrying capacity (also coined “ampacity”) and maximum acceptable voltage drop in the load circuits between the bus and the utilization equipment ground. Simply, the wire size of a wire is defined by the wire construction and insulation temperature limits, the load current, and the tolerable, allowable voltage drop.

3.1 Background Information

3.1.1 American Wire Gauge (AWG) Sizing Calculations

Two examples are given below for calculating a wire diameter and circular mil (cmil) values for a given size wire. These formulas provide some quick estimating calculations that are used in several popular publications and are only provided as example calculations and are not to be used in the selection of wire in aerospace applications. The wire sizing convention is a simple mathematical law, details of which can be found in the Standard Handbook for Electrical Engineers (see 2.1.6.3).

Equation 1 is a good approximation for determining the wire diameter (WireDia_inch), in inches, based on its wire size.

$$\text{WireDia_inch}(awg) = .3249 * e^{-.116*awg} \quad (\text{Eq. 1})$$

For wire sizes larger than #0, use a negative value to represent wire size in these equations; for instance, use -1, -2, and -3 for 2/0, 3/0, and 4/0 wire sizes, respectively.

For Equation 2, input the wire size number to calculate the cmils of a given wire size. After further inspection of this calculation for this equation, as compared to several M22759 series cmil values, the error amount from this equation should provide the evidence to invalidate this equation as an accurate estimating tool.

$$\text{AWG2Cmil} = [5 * (92^{(36-awg)/39})]^2$$

3.1.2 Current Carrying Capacity Rule

Various rules of thumb are representative by a ratio of wire cross-sectional area to current carrying capacity. The current carrying capacity values vary considerably. These rules of thumb are influenced by conductor material, constraints peculiar to an application (such as ambient temperature range), available cooling, and permissible voltage drop. Equation 3 is one of those “rule of thumb” calculations found on several popular websites. The rule determines that the current carrying capacity based on the cross-sectional of copper conductor’s area should be a value of 700 “circular mils” per amp or below with the parameter Diam in inches.

$$I_{amps}(Diam) = \frac{10^6 * Diam^2}{700/amp} \quad (Eq.3)$$

After reviewing several references, some authors suggested different values for the stated “700 cmil per amp” of 500, 300, or 200 “circular mils” per amp.

Equation 3 was employed to compare the results using two different cross-sectional area values, 700 cmil/A and 500 cmil/A. Table 1 demonstrates that the equation is inappropriate to be applied in an aerospace application when comparing it to the data in Table 1 of AS50881 at 105 °C.

Table 1 - Current carrying capacity comparison in amperes

AWG	Data from AS50881, Table 1 Amps at 105 °C	Using 700 cmil/A	Using 500 cmil/A
20	4	1.46	2.05
10	17	14.8	20.7
1/0	128	150	211

3.1.3 Density and Temperature Coefficient (per Degree Celsius)

The following information was taken from ASTM B193. These values are typically used in calculating resistance value for a wire. Exercise care in selecting the correct values when working with various wire types in aerospace applications.

- 100% IACS Copper at 20 °C
 - Approximate density, $\delta = 8.89 \text{ g/cm}^3$
 - Temperature coefficient of resistance, $\alpha = 0.00393$
- Silver Coated Copper
 - Class B density, $\delta = 8.93 \text{ g/cm}^3$
 - Temperature coefficient of resistance, $\alpha = 0.00393$
- Nickel Coated Copper
 - Class 2 density, $\delta = 8.89 \text{ g/cm}^3$
 - Temperature coefficient of resistance, $\alpha = 0.00395$
- Aluminum 1350 61.0% IACS
 - Approximate density, $\delta = 2.705 \text{ g/cm}^3$
 - Temperature coefficient of resistance, $\alpha = 0.00403$

3.1.4 Pouillet's Law

Pouillet's law states: The resistance of a given material will increase with the length but decrease with increasing cross-sectional area.

Electrical resistivity (ρ) is an intrinsic property that quantifies how strongly a given material opposes the flow of electric current.

Electrical conductivity (σ), or specific conductance, is the reciprocal of electrical resistivity and measures a material's ability to conduct an electric current.

Pouillet's law will show up in different forms when calculating a resistance value for a conductor. Close attention to the use of the numerical units should be exercised, especially when converting from SI to English units.

3.2 Resistance Calculations Examples

Equations 4 and 5 are two equations for calculating DC resistance. Equation 4, the most commonly used, will calculate the DC resistance (R_{dc}) of a given length of wire.

NOTE: Equation 1 calculates the diameter of the wire, which then can be used as an input to calculate the value of area for a wire. Remember to pay attention to the units.

$$R_{dc} = \frac{Length}{Area(awg) * \sigma} \quad (\text{Eq. 4})$$

Equation 5 calculates DC resistance and compensates for increased temperature in the conductor. Conductor conductivity (σ) is typically given at a laboratory temperature of 20 °C, but this should always be verified before being adjusted for a higher or lower temperature. This will provide an accurate value for calculating, for instance, voltage drop value for a given wire length.

$$R_{dc} = \frac{Length}{Area(awg) * \sigma} [1 + (Temp - 20) * \alpha] \quad (\text{Eq. 5})$$

As noted in AC 43.13-1B Chapter 11, Section 5, 11-66: The resistance of the current return path through the structure is generally considered negligible, based on the assumption that adequate bonding to the structure or a dedicated electric current return path has been incorporated that is capable of carrying the required current with negligible voltage drop.

Resistance calculations for AC current can be found in 4.2.

3.3 AS50881 Wire Selection Procedure

This is a brief outline of the process for selecting a wire gauge based on a set of design requirements and environmental and installation constraints.

Wire selection in AS50881 follows the following process:

- Wire ampacity (current carrying capacity) value calculation
- Bundle de-rating factor
- Altitude de-rating factor

Assumed factors taken into account in this process include:

- Heat-storage capacity of the wire and bundle
- Heat-storage capacity of the wire insulation
- Altitude, reduced convective air density