

SEMI E118.1-1104

SPECIFICATION FOR SECS-I AND SECS-II PROTOCOL FOR WAFER ID READER COMMUNICATION INTERFACE STANDARDS

This specification was technically approved by the Global Information and Control Committee and is the direct responsibility of the Japanese Information and Control Committee. Current edition approved by the Japanese Regional Standards Committee on July 23, 2004. Initially available at www.semi.org September 2004; to be published November 2004. Originally published March 2003; last published March 2004.

1 Purpose

1.1 This document maps the services and data of the Wafer ID Reader (WIDR) standard to SECS-II streams and functions and data definitions.

2 Scope

2.1 This document applies to all implementations of WIDR that use the SECS-II message protocol (SEMI E5).

NOTICE: This standard does not purport to address safety issues, if any, associated with its use. It is the responsibility of the users of this standard to establish appropriate safety and health practices and determine the applicability of regulatory or other limitations prior to use.

3 Referenced Standards

3.1 SEMI Standards

SEMI E4 — SEMI Equipment Communications Standard 1 Message Transfer (SECS-I)

SEMI E5 — SEMI Equipment Communications Standard 2 Message Content (SECS-II)

NOTICE: Unless otherwise indicated, all documents cited shall be the latest published versions.

4 Terminology

4.1 Abbreviations and Acronyms

4.1.1 *SECS* — SEMI Equipment Communications Standard

4.1.2 *WIDR* — Wafer ID Reader

5 Physical Requirements

5.1 The WIDR using the SECS-I protocol shall use a 9-pin female connector.

6 Service Message Mapping

6.1 Table 1 shows the specific SECS-II streams and functions that shall be used for SECS-II implementations of the service messages defined in SEMI E118.

6.2 Request and notification messages are mapped to primary (odd-numbered) SECS-II functions and response messages are mapped to secondary (even-numbered) SECS-II functions.

6.3 In some cases, a common set of parameters allows more than one service to be mapped to the same stream and function, with an additional SECS-II data item used to differentiate between the two services.

Table 1 Services Mapped to SECS-II Messages

<i>Message Name</i>	<i>Stream,Function</i>	<i>SECS-II Name</i>
ChangeState	S18,F13/F14	Subsystem Command Request/Acknowledge
Get Attributes	S18,F1/F2	Read Attribute Request/Data
Get Status	S18,F13/F14	Subsystem Command Request/Acknowledge
Perform Diagnostics	S18,F13/F14	Subsystem Command Request/Acknowledge
Read WID	S18,F9/F10	Read ID Request/Data
Reset	S18,F13/F14	Subsystem Command Request/Acknowledge
Set Attributes	S18,F3/F4	Write Attribute Request/Acknowledge
Read WIDC	S18,F15/F16	Read 2D Code Condition Request/Data

7 Service Parameter to Data Item Mapping

7.1 Table 2 shows the mapping between message parameters defined by WIDR and data items defined by SECS-II. For parameters specified in the definitions of a WIDR service, either the parameters themselves, or individual elements of complex parameters, map to a specific data item.

Table 2 Service Parameters to Data Item Mapping

<i>Parameter Name</i>	<i>SECS-II Data Item</i>	<i>Format</i>	<i>Values</i>
Attribute ID	ATTRID	20	Name of attribute
Attribute Value	ATTRVAL	20	
HeadID	TARGETID	20	“00”-“31” Identifies either an individual head (“01”-“31”) or the WIDR subsystem itself (“00”).
PM Information	STATUS	20	“NE” = Normal execution, “MR” = Maintenance required
Result Status	SSACK	20	“NO” = Normal operation; “EE” = Execution error; “CE” = Communication error; “HE” = Hardware error
StateRequest	CPVAL	20	“OP”, “MT”
Status	STATUSLIST	L,4 1. <PMInformation> 2. <AlarmStatus> 3. <OperationalStatus> 4. <HeadStatus>	Current values of PM Information with the corresponding attributes for WIDR and Head (if applicable). See Tables 4 and 5.
Wafer ID	MID	20	
2D Code Read Condition	CONDITIONLIST	L,7 1. <Cell Size> 2. <Contrast> 3. <Damage Percent> 4. <Number Error Bits> 5. <Read Time> 6. <Matrix Style> 7. <Matrix Polarity>	Current values of Cell Size, Contrast, Damage Percent, Number Error Bits, Read Time, Matrix Style, Matrix Polarity with the corresponding attributes for Code Condition. See Table 6. CONDITIONLIST data shall be formatted in the fixed order as in Format column.

NOTE 1: There are also data items used in SECS-II messages that do not map to specific services parameters. Services with the same set of parameters are mapped to the same SECS-II message by adding an additional data item to differentiate between the services. Table 3 contains the SECS-II data items that have not a corresponding WIDR service parameter.

Table 3 Additional Data Requirements Table

<i>SECS-II Data Item</i>	<i>Function</i>	<i>Value</i>
SSCMD	Used to differentiate between different subsystem commands indicated.	“ChangeState” “GetStatus” “Perform Diagnostics” “Reset”