

UL 489

ISBN 0-7629-0091-1

Molded-Case Circuit Breakers, Molded-Case Switches, and Circuit-Breaker Enclosures

Underwriters Laboratories Inc. (UL)
333 Pfingsten Road
Northbrook, IL 60062-2096

UL Standard for Safety for Molded-Case Circuit Breakers, Molded-Case Switches, and Circuit-Breaker Enclosures, UL 489

Ninth Edition, Dated October 31, 1996

Revisions: This Standard contains revisions through and including March 22, 2000.

The revisions dated March 22, 2000 include a reprinted title page (page1) for this Standard.

As indicated on the title page (page1), this UL Standard for Safety has been adopted by the Department of Defense.

The master for this Standard at UL's Northbrook Office is the official document insofar as it relates to a UL service and the compliance of a product with respect to the requirements for that product and service, or if there are questions regarding the accuracy of this Standard.

UL's Standards for Safety are copyrighted by UL. Neither a printed copy of a Standard, nor the distribution diskette for a Standard-on-Diskette and the file for the Standard on the distribution diskette should be altered in any way. All of UL's Standards and all copyrights, ownerships, and rights regarding those Standards shall remain the sole and exclusive property of UL.

All rights reserved. No part of this publication may be reproduced, stored in a retrieval system, or transmitted in any form by any means, electronic, mechanical photocopying, recording, or otherwise without prior permission of UL.

Revisions of UL Standards for Safety are issued from time to time. A UL Standard for Safety is current only if it incorporates the most recently adopted revisions.

UL provides this Standard "as is" without warranty of any kind, either expressed or implied, including but not limited to, the implied warranties of merchantability or fitness for any purpose.

In no event will UL be liable for any special, incidental, consequential, indirect or similar damages, including loss of profits, lost savings, loss of data, or any other damages arising out of the use of or the inability to use this Standard, even if UL or an authorized UL representative has been advised of the possibility of such damage. In no event shall UL's liability for any damage ever exceed the price paid for this Standard, regardless of the form of the claim.

UL will attempt to answer support requests concerning electronic versions of its Standards. However, this support service is offered on a reasonable efforts basis only, and UL may not be able to resolve every support request. UL supports the electronic versions of its Standards only if they are used under the conditions and operating systems for which it is intended. UL's support policies may change from time-to-time without notification.

UL reserves the right to change the format, presentation, file types and formats, delivery methods and formats, and the like of both its printed and electronic Standards without prior notice.

Purchasers of the electronic versions of UL's Standards for Safety agree to defend, indemnify, and hold UL harmless from and against any loss, expense, liability, damage, claim, or judgement (including reasonable attorney's fees) resulting from any error or deviation introduced while purchaser is storing an electronic Standard on the purchaser's computer system.

If a single-user version electronic Standard was purchased, one copy of this Standard may be stored on the hard disk of a single personal computer, or on a single LAN file-server or the permanent storage device of a multiple-user computer in such a manner that this Standard may only be accessed by one user at a time and for which there is no possibility of multiple concurrent access.

If a multiple-user version electronic Standard was purchased, one copy of the Standard may be stored on a single LAN file-server, or on the permanent storage device of a multiple-user computer, or on an Intranet server. The number of concurrent users shall not exceed the number of users authorized.

Electronic Standards are intended for on-line use, such as for viewing the requirements of a Standard, conducting a word search, and the like. Only one copy of the Standard may be printed from each single-user version of an electronic Standard. Only one copy of the Standard may be printed for each authorized user of a multiple-user version of an electronic Standard. Because of differences in the computer/software/printer setup used by UL and those of electronic Standards purchasers, the printed copy obtained by a purchaser may not look exactly like the on-line screen view or the printed Standard.

An employee of an organization purchasing a UL Standard can make a copy of the page or pages being viewed for their own fair and/or practical internal use.

The requirements in this Standard are now in effect, except for those paragraphs, sections, tables, figures, and/or other elements of the Standard having future effective dates as indicated in the note following the affected item. The prior text for requirements that have been revised and that have a future effective date are located after the Standard, and are preceded by a "SUPERSEDED REQUIREMENTS" notice.

New product submittals made prior to a specified future effective date will be judged under all of the requirements in this Standard including those requirements with a specified future effective date, unless the applicant specifically requests that the product be judged under the current requirements. However, if the applicant elects this option, it should be noted that compliance with all the requirements in this Standard will be required as a condition of continued Listing, Recognition, Classification and Follow-Up Services after the effective date, and understanding of this should be signified in writing.

Copyright © 2000 Underwriters Laboratories Inc.

This Standard consists of pages dated as shown in the following checklist:

Page	Date
1-7	March 22, 2000
8	December 4, 1998
9-10B	March 22, 2000
11-18	October 31, 1996
19-20B	March 22, 2000
21-29	October 31, 1996
30-30B	December 4, 1998
31-39	October 31, 1996
40-41	October 28, 1997
42-47	October 31, 1996
48-48B	November 7, 1997
49-65	October 31, 1996
66-67	May 21, 1997
68	October 31, 1996
69	May 21, 1997
70	October 28, 1997
71	October 31, 1996
72-74	May 21, 1997
75	December 4, 1998
76-79	October 31, 1996
80-81	May 21, 1997
82-86	October 31, 1996
87-88H	December 4, 1998
89-92	October 31, 1996
93	October 28, 1997
94-95	October 31, 1996
96-97	October 28, 1997
98-103	October 31, 1996
104	December 4, 1998
105	October 31, 1996
106-108	October 28, 1997
109-112	October 31, 1996
113-114B	December 4, 1998
115-178	October 31, 1996
SA1-SA2	October 31, 1996
SA3-SA4	November 7, 1997
SA5-SA6	October 31, 1996
SB1-SB4	October 31, 1996
SC1	October 28, 1997
SC2-SC4	October 31, 1996
SD1-SD2	October 31, 1996
A1-A2	October 31, 1996
B1-B4	October 31, 1996
B5-B8	December 4, 1998

No Text on This Page

OCTOBER 31, 1996

(Title Page Reprinted: March 22, 2000)

1

UL 489

**Standard for Molded-Case Circuit Breakers, Molded-Case Switches, and
Circuit-Breaker Enclosures**

The Fourth and previous editions were titled Branch-Circuit and Service Circuit-Breakers. The Fifth through Eighth editions were titled Molded-Case Circuit Breakers and Circuit-Breaker Enclosures.

First Edition – June, 1940
Second Edition – August, 1942
Third Edition – November, 1949
Fourth Edition – December, 1954
Fifth Edition – November, 1972
Sixth Edition – October, 1980
Seventh Edition – September, 1986
Eighth Edition – October, 1991

Ninth Edition

October 31, 1996

An effective date included as a note immediately following certain requirements is one established by Underwriters Laboratories Inc.

The Department of Defense (DoD) has adopted UL 489 on January 18, 1985 . The publication of revised pages or a new edition of this Standard will not invalidate the DoD adoption.

NEMA (National Electrical Manufacturers Association) has adopted UL 489 on August 11, 1999 as NEMA Standard AB1. The publication of revised pages or a new edition of this Standard will not invalidate the NEMA adoption.

Revisions of this Standard will be made by issuing revised or additional pages bearing their date of issue. A UL Standard is current only if it incorporates the most recently adopted revisions, all of which are itemized on the transmittal notice that accompanies the latest set of revised requirements.

ISBN 0-7629-0091-1

COPYRIGHT © 1974 , 2000 UNDERWRITERS LABORATORIES INC.

No Text on This Page

CONTENTS

FOREWORD	8
-----------------------	---

INTRODUCTION

1 Scope	9
2 Definitions	10
3 Components	15
4 Units of Measurement	16
5 Reference Publications	16

MOLDED CASE CIRCUIT BREAKERS

6 CONSTRUCTION	16
6.1 All Types	16
6.2 Current-Limiting Circuit Breakers	29
6.3 Instantaneous-Trip Circuit Breakers	29
6.4 Circuit Breaker and Ground-Fault Circuit-Interrupters	30
6.5 Integrally Fused Circuit Breakers and High Fault Protectors	30
6.6 Adjustable Circuit Breakers	31
6.7 Heating, Air Conditioning, and Refrigeration (HACR) Circuit Breakers	32
6.8 Remotely-Operated Circuit Breakers	32
6.9 Switching Duty (SWD) Rated Circuit Breakers	32
6.10 400 Hz Rated Circuit Breakers	32
6.11 Draw-Out Circuit Breakers	32
6.12 Series-Connected Circuit Breakers	33
6.13 Interchangeable-Trip Circuit Breakers	33
7 TESTS	33
7.1 Standard Circuit Breakers	33
7.2 Current-Limiting Circuit Breakers	71
7.3 Instantaneous-Trip Circuit Breakers	77
7.4 Circuit Breaker and Ground-Fault Circuit-Interrupters	78
7.4A Circuit Breakers with Equipment Ground-Fault Protection	87
7.5 Integrally Fused Circuit Breakers and High-Fault Protectors	88G
7.6 Adjustable Circuit Breakers	91
7.7 Heating, Air Conditioning, and Refrigeration (HACR) Circuit Breakers	92
7.8 Remotely-Operated Circuit Breakers	92
7.9 Switching Duty (SWD) Rated Circuit Breakers	93
7.10 400 Hz Rated Circuit Breakers	94
7.11 Draw-Out Circuit Breakers	94
7.12 Series-Connected Circuit Breakers	95
7.13 Interchangeable-Trip Circuit Breakers	103
7.14 High Intensity Discharge (HID) Type Circuit Breakers	103
8 RATINGS	104
9 MARKINGS	105
9.1 General	105
9.2 Current-Limiting Circuit Breakers	112
9.3 Instantaneous-Trip Circuit Breakers	112
9.4 Circuit Breaker and Ground-Fault Circuit-Interrupters	113
9.4A Circuit Breakers with Equipment Ground Fault Protection	114
9.5 Integrally Fused Circuit Breakers and High Fault Protectors	114

9.6 Adjustable Circuit Breakers	114
9.7 Heating, Air Conditioning, and Refrigeration (HACR) Circuit Breakers	114A
9.8 Remotely-Operated Circuit Breakers	114A
9.9 Switching Duty (SWD) Rated Circuit Breakers	115
9.10 400 Hz Rated Circuit Breakers	115
9.11 Draw-Out Circuit Breakers	115
9.12 Series-Connected Circuit Breakers	115
9.13 Interchangeable-Trip Circuit Breakers	115
9.14 High Intensity Discharge (HID) Type Circuit Breakers	116
9.15 Rating Plugs	116

MOLDED CASE SWITCHES

10 CONSTRUCTION	116
10.1 All Types	116
10.2 Draw-Out Switches	117
11 PERFORMANCE	117
11.1 General	117
11.2 Draw-Out Switches	127
12 RATINGS	127
13 MARKINGS	128

ACCESSORIES

14 CONSTRUCTION	132
14.1 General	132
14.2 Shunt-Trip Release Devices	135
14.3 Undervoltage-Trip Release Devices	135
14.4 Overvoltage-Trip Release Devices	136
14.5 Electrical Operators	136
14.6 Alarm and Auxiliary Switches	136
14.7 Mechanical Interlock	137
14.8 Lock-Off Device	137
15 PERFORMANCE	137
15.1 General	137
15.2 Shunt-Trip Release Devices	139
15.3 Undervoltage-Trip Release Devices	140
15.4 Overvoltage-Trip Release Devices	142
15.5 Electrical Operators	143
15.6 Alarm and Auxiliary Switches	144
15.7 Mechanical Interlock	146
15.8 Lock-Off Device	146
16 MARKINGS	147

ENCLOSURES

17 CONSTRUCTION	148
17.1 General	148
17.2 Provision for Locking	150
17.3 Connections for Wiring Systems	150
17.4 Ventilation	151
17.5 External Operating Mechanism	152
17.6 Cases – Insulating Material	153

17.7	Current-Carrying Parts	153
17.8	Spacings	154
17.9	Equipment Grounding Terminals	161
17.10	Enclosures Suitable for Use as Service Equipment	161
18	PERFORMANCE (Short-Circuit Current Ratings)	166
18.1	General	166
18.2	Sample Selection	167
18.3	Sample Preparation	167
18.4	Line Connections	167
18.5	Load Connections	168
18.6	Meter-Mounting Equipment	168
18.7	Short-Circuit Procedure	168
18.8	Short-Circuit Tests	169
18.9	Interpretation of Results	169
18.10	Dielectric Voltage-Withstand Test	170
19	RATINGS	170
20	MARKINGS	170
20.1	General	170
20.2	Position Indication	172
20.3	Short-Circuit Current Rating	173
20.4	Terminations	173
20.5	Environmental-Type Designations	174
20.6	Neutral Assemblies	175
20.7	Back-Fed Hold-Down Kit	175
20.8	Service Equipment Use	175
20.9	Ground-Fault Protection	177
20.10	Permanence of Marking	178
20.11	Installation Instructions for the Testing of Ground-Fault Protection of Equipment ..	178

**SUPPLEMENT SA - MOLDED-CASE CIRCUIT BREAKERS AND CIRCUIT-BREAKER ENCLOSURES
(MARINE USE) FOR USE UNDER USCG ELECTRICAL SYSTEMS REGULATIONS SUBCHAPTER
S (33 CFR, PART 183) AND USCG ELECTRICAL ENGINEERING REGULATIONS SUBCHAPTER J
(46 CFR, PARTS 110 – 113)**

INTRODUCTION

SA1	Scope	SA1
SA2	Glossary	SA1

CONSTRUCTION

SA3	General	SA1
-----	---------------	-----

PERFORMANCE

SA4	General	SA2
SA5	Vibration Test	SA2
SA6	Shock Test	SA4
SA7	Short-Circuit Test	SA4
SA8	Ignition-Protected Devices Test	SA4

MARKINGS

SA9 General	SA5
-------------------	-----

**SUPPLEMENT SB - MOLDED-CASE CIRCUIT BREAKERS AND CIRCUIT-BREAKER ENCLOSURES
(NAVAL USE)****INTRODUCTION**

SB1 Scope	SB1
-----------------	-----

PERFORMANCE

SB2 Vibration Test	SB1
SB2.1 General	SB1
SB2.2 Resonance frequency test	SB1
SB2.3 Variable frequency test	SB2
SB3 Calibration Test	SB3

MARKINGS

SB4 General	SB3
-------------------	-----

**SUPPLEMENT SC - MOLDED-CASE CIRCUIT BREAKERS AND CIRCUIT-BREAKER ENCLOSURES
FOR USE WITH UNINTERRUPTIBLE POWER SUPPLIES****INTRODUCTION**

SC1 Scope	SC1
SC2 Glossary	SC1

PERFORMANCE

SC3 General	SC1
SC4 Calibration Test	SC1
SC5 Overload Test	SC2
SC6 Endurance Test	SC2
SC7 Interrupting Test	SC3
SC8 Dielectric Voltage-Withstand Test	SC3
SC9 High-Available-Fault-Current Testing	SC3

RATINGS

SC10 General	SC3
--------------------	-----

MARKINGS

SC11 General	SC3
--------------------	-----

**SUPPLEMENT SD - CLASSIFIED CIRCUIT BREAKERS FOR USE WITH SPECIFIED PANELBOARDS
AS AN ALTERNATE FOR SPECIFIED CIRCUIT BREAKERS****INTRODUCTION**

SD1 Scope	SD1
SD2 Glossary	SD1

CONSTRUCTION

SD3 General	SD1
-------------------	-----

PERFORMANCE

SD4 General	SD1
SD5 Interrupting Test	SD2

MARKINGS

SD6 Details	SD2
-------------------	-----

APPENDIX A

Standards for Components.....	A1
-------------------------------	----

APPENDIX B**Circuit Calibration and Instrumentation Test Circuits**

B1 Instrumentation	B1
B2 Galvanometers Shall Be Calibrated as Indicated in B2.1 – B2.4	B1
B3 Alternating Current Circuits 10,000 A and Less	B2
B4 Alternating Current Circuits Greater than 10,000 A	B3
B5 Recovery Voltage – AC	B6
B6 Direct Current Circuits	B6

FOREWORD

A. This Standard contains basic requirements for products covered by Underwriters Laboratories Inc. (UL) under its Follow-Up Service for this category within the limitations given below and in the Scope section of this Standard. These requirements are based upon sound engineering principles, research, records of tests and field experience, and an appreciation of the problems of manufacture, installation, and use derived from consultation with and information obtained from manufacturers, users, inspection authorities, and others having specialized experience. They are subject to revision as further experience and investigation may show is necessary or desirable.

B. The observance of the requirements of this Standard by a manufacturer is one of the conditions of the continued coverage of the manufacturer's product.

C. A product which complies with the text of this Standard will not necessarily be judged to comply with the Standard if, when examined and tested, it is found to have other features which impair the level of safety contemplated by these requirements.

D. A product employing materials or having forms of construction which conflict with specific requirements of the Standard cannot be judged to comply with the Standard. A product employing materials or having forms of construction not addressed by this Standard may be examined and tested according to the intent of the requirements and, if found to meet the intent of this Standard, may be judged to comply with the Standard.

E. UL, in performing its functions in accordance with its objectives, does not assume or undertake to discharge any responsibility of the manufacturer or any other party. The opinions and findings of UL represent its professional judgment given with due consideration to the necessary limitations of practical operation and state of the art at the time the Standard is processed. UL shall not be responsible to anyone for the use of or reliance upon this Standard by anyone. UL shall not incur any obligation or liability for damages, including consequential damages, arising out of or in connection with the use, interpretation of, or reliance upon this Standard.

F. Many tests required by the Standards of UL are inherently hazardous and adequate safeguards for personnel and property shall be employed in conducting such tests.

INTRODUCTION

1 Scope

1.1 The requirements of this Standard cover molded case circuit breakers, circuit breaker and ground-fault circuit-interrupters, fused circuit breakers, and accessory high-fault protectors. These circuit breakers are specifically intended to provide service entrance, feeder, and branch circuit protection in accordance with the National Electrical Code, NFPA 70. This Standard also covers instantaneous-trip circuit breakers (circuit interrupters) specifically intended for use as part of a combination motor controller in accordance with the National Electrical Code .

1.1 effective October 31, 2000

1.2 This Standard covers molded case switches and fused molded case switches.

1.2 effective October 31, 2000

1.3 This Standard covers devices rated at 600 volts or less and 6000 amperes or less.

1.3 effective October 31, 2000

1.4 The devices referenced in 1.1 and 1.2 are intended for installation in an overall enclosure or as parts of other devices such as panelboards. The acceptability of the combination will be determined when the complete product is investigated.

1.4 effective October 31, 2000

1.5 This Standard covers circuit breaker enclosures and accessory devices intended for use with the devices described in 1.1 and 1.2.

1.5 effective October 31, 2000

1.6 This Standard does not cover low voltage power circuit breakers covered in ANSI/IEEE C37.13-1990, In Enclosures, Low-Voltage AC Power Circuit Breakers Used, and ANSI/IEEE C37.14-1993, Low-Voltage DC Power Circuit Breakers Used In Enclosures, or supplementary protectors covered by the Standard for Supplementary Protectors for Use in Electrical Equipment, UL 1077.

1.6 effective October 31, 2000

1.7 This Standard contains supplements covering the requirements for molded case circuit breakers for:

- a) Marine Use
- b) Naval Use
- c) Uninterruptible Power Supply Use
- d) Classified Circuit Breakers

1.7 effective October 31, 2000

1.8 A product that contains features, characteristics, components, materials, or systems new or different from those covered by the requirements in this standard, and that involves a risk of fire, electric shock, or injury to persons shall be evaluated using the appropriate additional component and end-product requirements to determine that the level of safety as originally anticipated by the intent of this standard is maintained. A product whose features, characteristics, components, materials, or systems conflict with

specific requirements or provisions of this standard shall not be judged to comply with this standard. Where appropriate, revision of requirements shall be proposed and adopted in conformance with the methods employed for development, revision, and implementation of this standard.

Revised 1.8 effective October 31, 2000

2 Definitions

Section 2 effective October 31, 2000

For the purposes of this Standard, the following definitions apply.

Accessories – a device or devices which perform a secondary or minor duty as an adjunct or refinement to the primary or major duty of a molded case product.

Accessory High-Fault Protector – a self-contained unit housing fuses or high-fault protectors constructed for use with specific molded case products and with provision for connecting directly to the load terminals of the molded case product.

Adjustable Circuit Breaker – a circuit breaker that has adjustable time/current tripping characteristics. These may include:

- a) Inverse-time (such as continuous current, long time, and/or short time);
- b) Instantaneous; and
- c) Ground-fault characteristics.

Adjustable Instantaneous Release (Trip) – that part of an overcurrent trip element that can be adjusted to trip a circuit breaker instantaneously at various values of current within a predetermined range of currents.

Alarm Switch – a switch that operates to open or close a circuit upon the automatic opening of the molded case product with which it is associated.

Ambient-Compensated Circuit Breaker – a circuit breaker in which means are provided for partially or completely neutralizing the effect of ambient temperature upon the tripping characteristics.

Ambient Temperature – the temperature of the surrounding medium that comes in contact with the circuit breaker or switch. For an enclosed device, it is the temperature of the medium outside the enclosure.

Auxiliary Switch – a switch which is mechanically operated by the main device.

Calibration – the factory adjustment of the release mechanism of a circuit breaker to make the circuit breaker perform in accordance with its prescribed characteristics.

Calibration Test – verifies the tripping characteristics of a circuit breaker.

Circuit Breaker – a device designed to open and close a circuit by nonautomatic means, and to open the circuit automatically on a predetermined overcurrent, without damage to itself when properly applied within its rating.

Circuit Breaker and Ground-Fault Circuit-Interrupter – a device that performs all normal circuit breaker functions and provides personnel protection against risk of electric shock as required by the National Electrical Code, ANSI/NFPA 70.

No Text on This Page

Circuit Breaker and Secondary Surge Arrester – a device that performs all normal circuit breaker functions and provides protection against power-distribution system surge related damage to connected circuits and load-connected equipment.

Circuit Breaker and Transient Voltage Surge Suppressor – a device that performs all normal circuit breaker functions and that is intended to limit the maximum amplitude of transient voltage surges on power lines to specified values. It is not intended to function as a surge arrester.

Circuit Breaker with Equipment Ground-Fault Protection – a device that performs all normal circuit breaker functions and provides leakage current protection intended to reduce the likelihood of fire. It is not intended to function as a ground-fault circuit-interrupter.

Circuit Breaker Enclosure – an enclosure intended to house a single, multipole, or two-single pole molded case products.

Circuit Breakers with Ground-Fault Protection for Equipment – circuit breakers which perform all normal circuit breaker functions and also trip when a fault current to ground exceeds a predetermined value.

Class I Ground-Fault Sensing and Relaying Equipment – equipment that does not incorporate means to prevent opening of the disconnecting means at high levels of fault current.

Class II Ground-Fault Sensing and Relaying Equipment – equipment that incorporates means to prevent initiation of opening of the disconnecting device if the fault current exceeds the contact interrupting capability of the disconnecting device.

Class CTL Circuit Breaker – one that, because of its size or configuration, in conjunction with a Class CTL panelboard, prevents more circuit breaker poles from being installed than the number for which the assembly is intended and rated.

Close-Open Operation – a close operation followed immediately by an open operation without purposely delayed action. The letters "CO" signify this operation.

Common Trip Circuit Breaker – a multipole circuit breaker constructed so that all poles will open when any one or more poles open automatically.

Cross-Over Current – the current of a fused circuit breaker at which the function of the fuse coincides with the operation of the trip mechanism of the circuit breaker, i.e., where the fuse clearing time curve crosses the circuit breaker trip characteristic curve.

Current Limiting Circuit Breaker – one that does not employ a fusible element and, when operating within its current-limiting range, limits the let-through I^2t to a value less than the I^2t of a 1/2-cycle wave of the symmetrical prospective current.

Current Limiting Range – the rms symmetrical prospective currents between the threshold current and the maximum interrupting rating current.

Current Setting (I_r) – the rms current an adjustable circuit breaker is set to carry continuously without tripping. It is normally expressed as a percentage of the rated current and is adjustable.

Dielectric Voltage-Withstand Test – determines the ability of the insulating materials and spacings used to withstand overvoltages without breakdown under specified conditions.

Drawout-Mounted Circuit Breaker – an assembly of a circuit breaker together with a supporting structure constructed so that the circuit breaker is supported and can be moved to either the main circuit connected or disconnected position without the necessity of removing connections or mounting supports. The structure includes both self-supporting circuit terminals and an interlocking means which permits movement of the circuit breaker between the main circuit connected and disconnected positions only when the circuit breaker contacts are in the open position.

Electrical Operator – an electrical controlling device which is used to operate the mechanism of a circuit breaker in order to open, close, and if applicable, reset the circuit breaker or switch.

Endurance Test – determines compliance with a specified number of mechanical and electrical operations.

External Operating Mechanism – a mechanism which engages the handle of a circuit breaker and provides a manual means for operating the circuit breaker.

Fixed Instantaneous Release (Trip) – that part of an overcurrent release element which contains a nonadjustable means that is set to trip a circuit breaker instantaneously above a predetermined value of current.

Frame – an assembly consisting of all parts of a circuit breaker except an interchangeable trip unit.

Frame Size – a term applied to a group of circuit breakers of similar physical configuration. Frame size is expressed in amperes and corresponds to the largest ampere rating available in the group. The same frame size designation may be applied to more than one group of circuit breakers.

Fused Circuit Breaker – a circuit breaker that contains replaceable fuses or high-fault protectors assembled as an integral unit in a supportive environment and enclosed housing of insulating material.

Fused Molded Case Switch – a switch with integral replaceable fuses and high fault protectors assembled as an integral unit in a supportive and enclosed housing of insulating material.

Ground-Fault Delay – an intentional time delay in the tripping function of a circuit breaker when a ground-fault occurs.

Ground-Fault Pickup Setting – the nominal value of the ground-fault current at which the ground-fault delay function is initiated.

Heating, Air Conditioning, and Refrigeration (HACR) Circuit Breaker – one intended for use with multi-motor and combination loads such as are found in heating, air conditioning, and refrigeration equipment.

Independent Trip Circuit Breaker – a multipole circuit breaker constructed such that all poles are not intended to open when one or more poles open automatically.

Instantaneous Override – a fixed-current level at which an adjustable circuit breaker will override all settings and will trip instantaneously.

Instantaneous Pickup Setting – the nominal value of current that an adjustable circuit breaker is set to trip instantaneously.

Instantaneous Trip – a qualifying term indicating that no delay is purposely introduced in the automatic tripping of the circuit breaker.

Instantaneous Trip Circuit Breaker (Motor Circuit Protector or Circuit Interrupter) – is one intended to provide short circuit protection only. Although acting instantaneously under short circuit conditions, these circuit breakers are permitted to include a transient dampening action to ride through initial motor transients.

Interchangeable Trip Unit – one which can be interchanged by a user among circuit breaker frames of the same design. See also Rating Plug.

Internal Mechanism – the means by which the main contacts of a circuit breaker are actuated.

Interrupting Rating – the highest current at rated voltage that a device is intended to interrupt under standard test conditions.

Inverse Time – a qualifying term indicating that there is a purposely introduced delayed tripping in which the delay decreases as the magnitude of the current increases.

I^2t (Amperes Squared Seconds) – an expression related to the circuit energy as a result of current flow. With respect to circuit breakers, the I^2t is expressed for the current flow between the initiation of the fault current and the clearing of the circuit.

Lock-Off Device – a device that permits the circuit breaker to be locked in the OFF position.

Long Time Delay – an intentional time delay in the overload tripping of an adjustable circuit breaker's inverse time characteristics. The position of the long time portion of the trip curve is normally referenced in seconds at 600 percent of the current setting (I_r).

Long-Time Pickup – the current at which the long-time delay function is initiated.

Mechanical Interlock – a device or system that mechanically connects two or more circuit breakers or switches so that only selected ones can be closed at the same time.

Molded Case Circuit Breaker – one which is assembled as an integral unit in a supportive and enclosed housing of insulating material.

Molded Case Switch – a device designed to open and close a circuit by nonautomatic means, assembled as an integral unit in a supportive and enclosed housing of insulating material.

Multipole Circuit Breaker – one with two or more poles which provide two or more separate conducting paths.

Neutral (or Solid Neutral) – an assembly consisting of an appropriate number of terminals providing for the connection of the neutral conductors. When used as a component of service equipment, the neutral also includes:

- a) A means for making the required bonding connection between the neutral and the enclosure and
- b) A terminal for the grounding electrode conductor.

Open Operation – the movement of the contacts from the closed to the open position. The letter "O" signifies this operation.

Overvoltage-Trip Release Device – a trip mechanism that causes a circuit breaker to open automatically if the voltage across the terminals of the trip coil rises above a predetermined value.

Peak Current – the maximum instantaneous current that flows in a circuit.

Pilot Duty – the rating assigned to a relay or switch that controls the coil of another relay or switch.

Pole – that portion of a circuit breaker or switch associated exclusively with one electrically separated conducting path of its main circuit.

Prospective Current (Available Current) – is that which would flow in a circuit if a short circuit of negligible impedance were to occur at a given point.

Rated Control Voltage – the designated voltage which is to be applied to the closing or tripping devices to open or close a circuit breaker or switch.

Rated Current (I_n) – is the marked current rating and is the maximum rms current a circuit breaker can carry continuously without tripping and is the maximum current the circuit breaker will carry without changing, deleting, or adding part(s) such as trip units and rating plugs. See current setting (I_r).

Rated Frequency – the service frequency of the circuit for which the circuit breaker is designed and tested.

Rated Voltage – the rated voltage is the nominal rms voltage for which the circuit breaker is designed to operate.

Rating – the designated limit(s) of the rated operating characteristic(s) of a device.

Rating Plug – a self contained portion of a circuit breaker that is interchangeable and replaceable in a circuit breaker trip unit by the user. It sets the Rated Current (I_n) of the circuit breaker.

Recovery Voltage – the voltage that appears across the terminals of a pole of a circuit breaker upon interruption of the circuit.

Remotely Operated Circuit Breaker – a circuit breaker that contains an integral means to remotely open and close the circuit.

Series Rated (Series Connected) – a group of overcurrent devices, connected in cascade, comprised of a circuit breaker or main fuse and one or more downstream circuit breakers that have been tested together to permit the branch or downstream circuit breakers to be applied on circuits where the available short circuit current exceeds the marked interrupting rating on the branch circuit breaker.

Short Circuit Current Rating – the maximum RMS prospective (available) current to which a device can be connected when protected by the specified overcurrent protective devices. The rating is expressed in amperes and volts.

Short-Time Delay – an intentional time delay in the tripping of a circuit breaker between the overload and the instantaneous pick up settings.

Short-Time Pickup – the current at which the short-time delay function is initiated.

Shunt-Trip Release Device – a release mechanism energized by a source of voltage which may be derived either from the main circuit or from an independent source.

Supervisory Circuit – a feature included in a circuit breaker and ground-fault circuit-interrupter that provides a manual method for testing the device by simulating a ground fault.

SWD Circuit Breaker – is one intended to switch fluorescent lighting loads on a regular basis.

Threshold Current – the rms symmetrical prospective current at the threshold of the current limiting range, where:

- a) The peak current let through in each phase is less than the peak of that symmetrical prospective current, and
- b) The I^2t in each phase is less than the I^2t of a 1/2 cycle wave of the symmetrical prospective current.

Trip-Free Circuit Breaker – is one designed so that the contacts cannot be held in the closed position by the operating means during trip command conditions.

Tripping – the opening of a circuit breaker by actuation of the release mechanism.

Trip Unit – a self-contained portion of a circuit breaker that is interchangeable and replaceable in a circuit breaker frame by the user. It actuates the circuit breaker release mechanism and it sets the Rated Current (I_n) of the circuit breaker unless a rating plug is used. See Rating Plug.

Undervoltage Trip Release – a release mechanism which causes a circuit breaker to open automatically if the control voltage falls below a predetermined value.

3 Components

Section 3 effective October 31, 2000

3.1 Except as indicated in 3.2, a component of a product covered by this Standard shall comply with the requirements for that component. See Appendix A for a list of Standards covering components generally used in the products covered by this Standard.

3.2 A component need not comply with a specific requirement that:

- a) Involves a feature or characteristic not needed in the application of the component in the product covered by this Standard; or
- b) Is superseded by a requirement in this Standard.

3.3 A component shall be used in accordance with its ratings for the intended conditions of use.

3.4 Specific components are accepted as being incomplete in construction features, or restricted in performance capabilities. Such components are intended for use only under limited conditions, such as temperatures not exceeding specified limits, and shall be used only under those specified conditions for which they have been investigated.

4 Units of Measurement

Section 4 effective October 31, 2000

4.1 If a value for measurement is followed by a value in other units in parentheses, the second value may be only approximate. The first stated value is the requirement.

5 Reference Publications

Section 5 effective October 31, 2000

5.1 Where undated reference is made to UL Standards, such reference shall be considered to refer to the latest edition and all amendments published to that edition up to the time when this Standard was approved.

MOLDED CASE CIRCUIT BREAKERS

6 CONSTRUCTION

6.1 All Types

Section 6 effective October 31, 2000

6.1.1 General

6.1.1.1 A circuit breaker intended particularly for use in panelboards and the like shall be evaluated with respect to its intended application as well as under these requirements.

6.1.1.2 A circuit breaker shall be provided with means for mounting.

6.1.1.3 A circuit breaker shall have an integral housing for all the mechanism and live parts except the operating handle and the wiring terminals, and shall be manually operable without opening this housing.

6.1.1.4 There shall be no direct opening in the front of a circuit breaker, except that a circuit breaker need not comply if a cotton indicator, as described in 7.1.7.10, does not ignite during the interrupting test described in Interrupting test, 7.1.7.

6.1.1.5 If a circuit breaker requires a specific receiving device, the combination of the circuit breaker and receiving device shall comply with all of the applicable requirements in this Standard.

6.1.1.6 A circuit breaker shall have the strength and rigidity necessary for its intended use and to meet the test requirements of this Standard.

6.1.1.7 A circuit breaker may be manufactured as a circuit breaker frame and an interchangeable trip unit and each shall be plainly marked in accordance with 9.1.1.2 and 9.13.1.

6.1.1.8 A Class CTL circuit breaker shall have a size or configuration that, in conjunction with the physical means provided in a Class CTL panelboard, prevents the installation of more circuit breaker poles than that number for which the assembly is designed and rated. See 9.1.4.2.

6.1.2 Corrosion protection

6.1.2.1 Iron and steel parts, except for thermal elements; magnet-pole faces; and hardened and polished parts such as latching surfaces and the like, where such protection is impractical, shall be protected against corrosion by enamelling, galvanizing, plating, or other equivalent means.

6.1.2.2 Phosphate treatment with an oil or wax coating is acceptable as corrosion protection for magnets and armatures; oil treatment is acceptable as corrosion protection for steel springs; and stainless steel is acceptable without additional protection if polished or treated when necessary.

6.1.2.3 Copper and brass are not acceptable for the plating of steel wire-binding screws, nuts, and stud terminals.

6.1.3 Cases - insulating material

6.1.3.1 A case for mounting uninsulated live parts shall be strong, not easily ignited, moisture-resistant, and insulating. The case shall be of such material that it will withstand the most severe conditions likely to be met in service.

6.1.3.2 Ordinary fiber, rubber, and hot-molded shellac and tar compositions are not acceptable for the mounting of uninsulated live parts.

6.1.3.3 Insulating material including barriers shall have properties acceptable for the particular application.

6.1.3.4 An insulating barrier, which is required for the proper performance or installation of a circuit breaker, shall be an integral part of, or reliably attached to, the circuit breaker, or a marking shall be provided in accordance with 9.1.1.11.

6.1.3.5 Removable lug and terminal covers shall be permitted if specific marking on the circuit breaker housing is provided to indicate the need for replacement. See 9.1.1.12.

6.1.4 Current-carrying parts

6.1.4.1 General

6.1.4.1.1 Current-carrying parts shall be of silver, a silver alloy, copper, a copper alloy, or other metal acceptable for the application. Iron or steel, plain or plated, may be used in multimetallic thermal elements. Screws, nuts, or wire binding screws made of iron or steel and corrosion protected, shall be permitted to be used to secure live parts, but shall not be depended upon to carry current.

6.1.4.1.2 Uninsulated live parts, other than soldering lugs or pressure wire-connectors meeting the requirements of 6.1.6.1.4 shall be so secured to the case or mounting surface that they will be prevented from turning. Friction between surfaces is not acceptable as a means of preventing the turning of live parts.

6.1.4.1.3 If parts are held together by screws, a threaded part shall have no fewer than two full, clean-cut threads engaged. If a screw does not extend all the way through a threaded part, the taper or lead and the first full thread are to be disregarded in a determination of the number of threads engaged.

6.1.4.2 Terminals

6.1.4.2.1 Except as described in 6.1.4.2.4, each field wiring terminal of a circuit breaker shall have a wire connector that has a capacity acceptable for the number, wire size, and type associated with the circuit breaker. See Table 6.1.4.2.1 and Terminations, Section 20.4. A wiring terminal shall be acceptable for the temperatures encountered. See also 6.1.4.2.9, 6.1.4.2.16, and 9.1.2.14.

6.1.4.2.2 A wire connector provided with or specified for use with a circuit breaker shall comply with the appropriate requirements of UL selected from one of the following:

- a) Wire Connectors and Soldering Lugs for Use With Copper Connectors, UL 486A;
- b) Wire Connectors for Use with Aluminum Conductors, UL 486B; or
- c) Equipment Wiring Terminals for Use With Aluminum and/or Copper Conductors, UL 486E. When these connectors are used, an interrupting test for the circuit breaker shall be performed if the interrupting rating of the circuit breaker is greater than 10 kA.

6.1.4.2.3 The tightening torque for a field wiring terminal shall be as specified by the circuit breaker manufacturer and the circuit breaker shall be marked as required by 9.1.2.5. The specified tightening torque shall not be less than 90 percent and not more than 100 percent of the value used in the static heating test as specified in the Standard for Wire Connectors for Use with Aluminum Conductors, UL 486B, for the wire size corresponding to the ampere rating of the circuit breaker. See Mechanical tests, 7.1.10.1. Torque values shall be permitted to be less than 90 percent if the connector is investigated in accordance with the lesser assigned torque value in UL 486B.

6.1.4.2.4 Wire connectors or wire binding terminals for the line or the load, or both, may be omitted if:

- a) Provision is made for a bus bar connection;
- b) Provision is made for a plug-in connection;
- c) Field-installable kits are available from the manufacturer and the conditions in 6.1.4.2.5 are met; or
- d) Circuit breakers having special forms of construction, such as those providing a switching neutral pole or an isolated pole for water heater use, and the like, shall be permitted to have means of connection considered acceptable for the intended purpose in place of a pressure terminal connector.

Table 6.1.4.2.1
Terminal current and conductor size

Terminal current in Amperes ^a	Copper conductor			Aluminum or copper-clad aluminum conductor		
	Number of conductors	Size AWG or kcmil		Number of conductors	Size AWG or kcmil	
		60°C	75°C		60°C	75°C
15 or less	1	14	14	1	12	12
20	1	12	12	1	10	10
25	1	10	10	1	10	10
30	1	10	10	1	8	8
40	1	8	8	1	6	8
50	1	6	8	1	4	6
60	1	4	6	1	3	4
70	1	4	4	1	2	3
80	1	3	4	1	1	2
90	1	2	3	1	1/0	2
100	1	1	3	1	1/0	1
110	1	1	2	1		1/0
125	1	1/0	1	1		2/0
150	1		1/0	1		3/0
175	1		2/0	1		4/0
200	1		3/0	1		250
225	1		4/0	1		300
250	1		250	1		350
275	1		300	1		500
300	1		350	1		500
325	1		400	2		4/0
350	1		500	2		4/0
400	2		3/0	2		250
	1		500	1		750
450	2		4/0	2		300
500	2		250	2		350
550	2		300	2		500
600	2		350	2		500
700	2		500	3		350
800	3		300	3		400
1000	3		400	4		350
				3		600
1200	4		350	4		500
	3		600			
1400	4		500	5		500

Table 6.1.4.2.1 Continued on Next Page

Table 6.1.4.2.1 Continued

Copper conductor								Aluminum or copper-clad aluminum conductor			
Terminal current in Amperes ^a	Number of conductors		Size AWG or kcmil		Number of conductors		Size AWG or kcmil				
			60°C	75°C			60°C	75°C			
1600	5		400		5		600				
	4		600								
2000	6		400		6		600				
	5		600								
2500	8		400		8		600				
	7		500		7		750				
3000	6		600		9		500				
	9		400		10		500				
	8		500		9		600				
	7		600		8		750				
4000	12		400		13		500				
	11		500		12		600				
	10		600		11		750				
5000 ^b	15		400		16		500				
	13		500		15		600				
	12		600		13		750				
6000 ^b	18		400		19		500				
	16		500		18		600				
	15		600		16		750				
^a For terminal current other than indicated, the next higher rating is to be used - for example, if rated 35 A, enter at 40 A.											
^b Circuit breakers rated at more than 4000 A are to be considered as being bus- or cable-connected unless indicated otherwise in marking.											
mm ²		2.1	3.3	5.3	8.4	13.3	21.1	26.7	33.6	42.4	53.5
AWG		14	12	10	8	6	4	3	2	1	1/0
mm ²		67.4	85.0	107.2	127	152	177	203	253	304	380
AWG or kcmil		2/0	3/0	4/0	250	300	350	400	500	600	750

6.1.4.2.5 Field-installable connectors shall meet the following conditions:

- a) Component terminal kits shall be available from the circuit breaker manufacturer or one or more wire connectors shall be specified for field installation on the equipment;
- b) Fastening devices, such as studs, nuts, bolts, springs, and flat washers, or the like, as required for an effective installation, shall either be provided as part of the component terminal kit or mounted on or separately packaged with the circuit breaker;

- c) The installation of the terminal kit shall not involve the loosening or disassembly of parts other than those normally disassembled for installation and wiring;
- d) If the wire connector provided in a component terminal kit requires the use of a special tool for securing the conductor, any necessary instructions shall be included in the component terminal kit package or with the circuit breaker;
- e) Installation of the wire connectors in the intended manner shall result in a product that meets the requirements of this Standard; and
- f) The circuit breaker or circuit breaker frame, and component terminal kit shall be marked in accordance with 9.1.2.11.

No Text on This Page

6.1.4.2.6 A wire binding screw shall be permitted to be used at a field wiring terminal intended for the connection of a No. 10 AWG (5.3 mm²) or smaller wire if upturned lugs or the equivalent are provided to retain the wire under the head of the screw even though the screw becomes loosened.

6.1.4.2.7 A plug-in circuit breaker shall not have a screw or wire connector which can be used simultaneously for the connection of a conductor on the same side as the plug-in connection. A conversion kit with instructions may be provided to accomplish a change in the type of plug-in connection.

6.1.4.2.8 The plug-in connection members on a circuit breaker and on a receiving means shall have the strength necessary for the forces applied during inserting and removing the circuit breaker.

6.1.4.2.9 A plug-in circuit breaker shall be retained on the stabs without depending on the trim or cover of the enclosure.

6.1.4.2.10 If a screw-and-washer construction is used at a field wiring terminal, the screw shall not be smaller than No. 10 (4.8 mm) with no more than 32 threads per inch (per 25.4 mm).

6.1.4.2.11 A terminal plate tapped for a wire-binding screw shall be of metal no less than 1.27 mm (0.050 inch) thick and shall have not less than two full threads in the metal; except that a special alloy plate less than 1.27 mm (0.050 inch) but not less than 0.76 mm (0.030 inch) thick shall be permitted if the tapped threads have the necessary mechanical strength.

6.1.4.2.12 A terminal plate shall be permitted to have the metal extruded at the tapped hole so as to give the thickness necessary for at least two full threads provided that the thickness for the unextruded metal is not less than the pitch of the thread.

6.1.4.2.13 If conductors of the next larger size than that described in Table 6.1.4.2.1 can be inserted into main terminals of a circuit breaker, the terminals shall be capable of securing such larger conductors, unless marked as provided in 9.1.2.7.

6.1.4.2.14 Pressure terminal connectors capable of holding the next larger size wire as described in 6.1.4.2.13 additionally shall be capable of withstanding secureness and pullout tests described in the Standard for Wire Connectors for Use With Aluminum Conductors, UL 486B, with the size conductors described in 6.1.4.2.13 and Table 6.1.4.2.1.

6.1.4.2.15 A terminal for the connection of conductors other than those specified in Table 6.1.4.2.1 shall be acceptable only if found appropriate for the particular application.

6.1.4.2.16 Using normally available tools such as screwdrivers, pliers or wrenches, it shall be possible to retighten the conductor securing means of a wire connector without removal of the connector from the terminal plate or bus or without removal of any conductor from the connector.

6.1.4.2.17 For an interchangeable trip circuit breaker frame rated 100 A or less, a single pressure terminal connector shall be made available by the circuit breaker manufacturer that properly accommodates all sizes of wire for which the frame is intended.

6.1.4.3 Field Wiring Conductors

6.1.4.3.1 Conductors shall not differ by more than two wire sizes from the size referred to in Table 6.1.4.2.1. The wire size shall not be smaller than No. 14 AWG (2.1 mm²).

6.1.4.3.2 Conductors shall consist of wire suitable for the particular application, when considered with respect to the temperature and voltage and conditions of service to which the wiring is likely to be subjected.

6.1.4.3.3 A conductor shall be constructed so as to withstand the stress of normal handling without damage to itself or to the unit. See 7.1.10.1.2.

6.1.4.3.4 Green coloring with or without one or more yellow stripes and white or natural grey coloring shall not be used for the covering of a conductor unless intended for connection to grounding and grounded conductors respectively.

6.1.4.3.5 The free length of a wiring conductor shall be at least 152 mm (6 inches).

6.1.5 Operating mechanism

6.1.5.1 A multipole circuit breaker shall be constructed so that all poles will make and break simultaneously when operated manually or automatically in the intended manner; except that in a 2- or 3-pole circuit breaker rated at 125/250 V or less and having two operating poles intended for use on the outside (ungrounded) wires of a 3-wire, dc or single-phase ac system. The automatic tripping of either pole shall be permitted to be independent of the other if the independent tripping is indicated. See 9.1.4.7.

6.1.5.2 The handle of a circuit breaker shall not be capable of being readily left at or near the OFF position when the contacts are closed.

6.1.5.3 Single-pole circuit breakers rated at 120/240 V ac or 125/250 V dc shall have provision for the use of handle ties. Handle ties, when installed, shall:

- a) Operate both circuit breakers when either circuit breaker handle is manually operated;
- b) Not be readily removable;
- c) Not obscure the ampere marking on either circuit breaker.

6.1.5.4 Screws and nuts serving to attach operating parts to movable members shall be staked, upset, or otherwise locked in position to prevent loosening.

6.1.5.5 An operating handle of conducting material extending into the housing shall have provision for connection to an equipment grounding conductor. If the intended enclosure is of metal, this shall be permitted to be accomplished by having such operating handle of conducting material in electrical connection with the enclosure. The adequacy of such connection shall be determined by the electrical continuity test described in 7.11.1.

6.1.5.6 The means for operation of a circuit breaker shall be such that the contacts cannot be held in the closed position under overcurrent conditions - that is, the circuit breaker shall be trip-free from the operating handle. The construction shall be such that when the operating handle is held in the ON position and the circuit breaker is tripped automatically, the contacts will not automatically return to the closed position.

6.1.5.7 A circuit breaker shall be permitted to have an adjustable instantaneous release. A circuit breaker of frame size 200 A or more and with a current rating (minimum of adjustment range where applicable) of 100 A or more or a circuit breaker rated more than 250 V shall be permitted to have an adjustable inverse time (overload) response. See the requirements for adjustable circuit breakers described in Section 6.6 and Section 7.6. Circuit breakers of other ratings shall not have an adjustable inverse time (overload) response.

6.1.5.8 Except as permitted by 6.1.5.9, access to the trip mechanism of a circuit breaker or trip unit and tampering, changing, or interfering with the calibration of the trip mechanism or of a trip unit, except as noted in 6.1.5.7, shall require dismantling of the circuit breaker, or dismantling or removal of the trip unit, or the breaking of a seal.

6.1.5.9 A hole for a rod or wire shall be permitted in the housing of a circuit breaker or trip unit to permit tripping of the circuit breaker. Such holes shall not permit passage of a rod larger than 3.2 mm (1/8 inch) diameter. A button, lever, or similar member shall be permitted to be added for the same purpose. Any such hole or feature added shall not contribute to the interference with or change in calibration of the circuit breaker, permit blocking of the release mechanism, or permit contact with a live part involving a potential more than 42.4 V peak.

6.1.5.10 A circuit breaker rated at 100 A or less in conjunction with a voltage rating of not more than 240 V ac or 125/250 V dc shall be considered to comply with the interference aspect of 6.1.5.8 and 6.1.5.9, if interference with the automatic operation of the circuit breaker cannot be accomplished by:

- a) Insertion of a 0.8 mm (1/32 inch) diameter straight rod through any opening in the case above a plane 12.7 mm (1/2 inch) below the plane of the trim when the circuit breaker is mounted in the intended manner, and
- b) Insertion of a 2.8 mm (7/64 inch) diameter straight rod through any opening elsewhere in the case.

6.1.5.11 Any means for sealing shall be such that breaking or removing it will be plainly evident. Paper or cloth shall be permitted to be used as a seal indicator, but shall not be used as a means for holding parts together.

6.1.5.12 There shall not be any access, as defined in 6.1.5.13, to a part involving risk of electric shock within an area as indicated in 6.1.5.15:

- a) While changing a trip unit in an interchangeable trip unit circuit breaker,
- b) While replacing fuses or high-fault protectors in a fused circuit breaker, or
- c) While modifying the response of an adjustable circuit breaker.

6.1.5.13 With regard to access to live parts through openings in surfaces, a part is considered to be accessible if it can be contacted by a 51 mm (2 inch) long, 9.5 mm (3/8 inch) diameter rod having a hemispherical end, inserted through openings in the surface.

6.1.5.14 A risk of electric shock is considered to exist if the open circuit voltage between the part in question and earth ground or any other accessible part is more than 42.4 V peak, and the continuous current flow through a 500 ohm resistor connected between the points exceeds 5 mA rms.

6.1.5.15 The areas referred to in 6.1.5.12 are:

- a) The complete area of any opening created by the removal of interchangeable trip units other than line terminals and parts connected thereto.
- b) The complete area of any opening created by the removal of the limiters, and so forth, other than line terminals and parts connected thereto, and
- c) Points within 51 mm (2 inches) of the periphery of any adjustment knob involved in modifying the response of a circuit breaker.

6.1.5.16 A reliability study for electronic circuit components shall be made in accordance with the requirements for tests for safety-related controls employing solid-state devices, UL 991.

6.1.6 Spacings

6.1.6.1 General

6.1.6.1.1 The spacings of a circuit breaker shall not be less than those indicated in Table 6.1.6.1.1. "Grounded Metal" includes circuit breaker mounting screws and fittings for the connection of a wiring system. A "Terminal" includes the terminal proper and associated metal having the same degree of exposure or accessibility. Spacings shall be measured between the bare portions of insulated conductors. The insulation shall be brought up to the wire connector when space for the wire insulation exists.

6.1.6.1.2 The external spacing through air and over surface shall not be less than 3.2 mm (1/8 inch) between uninsulated line and load live parts of the same polarity.

6.1.6.1.3 In the determination of spacings, the overall wire diameters of Table 6.1.6.1.2 shall be used.

6.1.6.1.4 Except as indicated in 6.1.6.1.5, a pressure terminal connector shall be provided with a positive restraint, such as a shoulder or boss, to restrict turning that would reduce spacings to values less than those required. A lock washer alone is not acceptable for this purpose.

6.1.6.1.5 Means to prevent turning as indicated in 6.1.6.1.4 need not be provided if spacings are not less than the minimum acceptable values:

- a) When the connector and any connector of opposite polarity have each been turned 30 degrees toward the other, and
- b) When the connector has been turned 30 degrees toward other opposite polarity live parts or toward grounded dead metal parts.

Table 6.1.6.1.1
Minimum spacings in millimeters^{e,f,g}

Voltage between parts	At terminals				Other than at terminals					
	Between terminals of opposite polarity		Between terminals and any grounded metal ^a		Between uninsulated live parts of opposite polarity ^b		Between uninsulated live parts and any ground metal ^a			
	A		B		C		D ^c		E ^d	
	Through air	Over surface	Through air	Over surface	Through air	Over surface	Through air	Over surface	Through air	Over surface
0 – 125	12.7	19.1	12.7	12.7	6.4	9.5	12.7	12.7	6.4	9.5
126 – 300	19.1	31.8	12.7	12.7	6.4	9.5	12.7	12.7	6.4	9.5
301 – 600	25.4	50.8	12.7	25.4	9.5	12.7	12.7	25.4	9.5	12.7
^a The spacing to the enclosure or mounting means shall be permitted to be reduced if an acceptable liner of insulating material, not less than 0.8 mm (1/32 inch) thick, is used to provide the required spacing through air. ^b Not applicable for spacings between parts of opposite polarity on a control circuit printed wiring board with conformal coating. See Table 6.1.6.2.1 and Printed Circuit and Wiring Board Assembly, 6.1.6.2. ^c If indentation or deformation of the overall enclosure or circuit breaker mounting means could reduce spacings to less than those indicated in Column E. ^d If indentation or deformation of the overall enclosure or circuit breaker mounting means would not affect spacings. ^e An isolated dead metal part (such as a screw head or a washer) interposed between uninsulated live parts of opposite polarity or between an uninsulated live part and a grounded dead metal part is considered to reduce the spacing by an amount equal to the dimension of the interposed part along the path of measurement. ^f In measuring an over surface spacing, any slot, groove, or the like, 0.33 mm (0.013 inch) wide or less in the contour of insulating material shall be disregarded. ^g In measuring spacings, an air spacing of 0.33 mm (0.013 inch) or less between a live part and an insulating surface shall be disregarded, and the live part considered in contact with the insulating material.										
	mm	0.8	6.4	9.5	12.7	19.1	25.4	31.8	50.8	
	Inches	1/32	1/4	3/8	1/2	3/4	1	1-1/4	2	

Table 6.1.6.1.2
Wire diameters (over insulation)

AWG	(mm ²)	Inches	(mm)		kcmil	(mm ²)	Inches	(mm)
14	(2.1)	0.131	(3.33)		250	(127)	0.788	(20.12)
12	(3.3)	0.148	(3.76)		300	(152)	0.843	(21.41)
10	(5.3)	0.168	(4.27)		350	(177)	0.895	(22.73)
8	(8.4)	0.245	(6.22)		400	(203)	0.942	(23.93)
6	(13.3)	0.323	(8.20)		500	(253)	1.029	(26.14)
4	(21.2)	0.372	(9.45)		600	(304)	1.143	(29.03)
3	(26.7)	0.401	(10.19)		750	(380)	1.249	(31.72)
2	(33.6)	0.433	(11.00)		800	(405)	1.282	(32.56)
1	(42.4)	0.508	(12.90)		900	(456)	1.345	(34.16)
1/0	(53.5)	0.549	(13.94)		1000	(507)	1.404	(35.66)
2/0	(67.4)	0.595	(15.11)		1250	(633)	1.577	(40.06)
3/0	(85.0)	0.647	(16.43)		1500	(760)	1.702	(43.23)
4/0	(107.2)	0.705	(17.91)		1750	(887)	1.817	(46.15)
					2000	(1010)	1.922	(48.82)

6.1.6.1.6 The spacings of a circuit breaker shall be measured with the circuit breaker wired with conductors of the size shown in Table 6.1.4.2.1, as appropriate for temperature rating(s) of the wires, see 9.1.2.9. Type TW wire is to be used for sizes No. 8 AWG (8.4 mm²) and smaller; Type THW, TW75 or TW for sizes larger than No. 8 AWG (8.4 mm²). Solid conductors are to be used for wire sizes No. 10 AWG (5.3 mm²) and smaller. For circuit breakers acceptable for use with both copper and aluminum conductors, both types of wire of the proper size for the ampere rating are to be evaluated.

6.1.6.1.7 Except as noted in 6.1.6.1.8 and 6.1.6.1.12, an insulating barrier or liner used as the sole separation between uninsulated live parts and grounded dead metal parts (including the enclosure) or between uninsulated live parts of opposite polarity, shall be of a material which is acceptable for the mounting of uninsulated live parts and not less than 0.71 mm (0.028 inch) thick.

6.1.6.1.8 Fiber not less than 0.71 mm (0.028 inch) thick shall be permitted to be used as the sole separation between the enclosure and an uninsulated metal part electrically connected to a grounded circuit conductor.

6.1.6.1.9 A barrier or liner used in conjunction with an air space shall not be less than 0.71 mm (0.028 inch) thick except as noted in 6.1.6.1.11 and 6.1.6.1.12.

6.1.6.1.10 If the barrier indicated in 6.1.6.1.9 is of fiber, the air space shall not be less than 0.8 mm (1/32 inch).

6.1.6.1.11 A barrier or liner used in conjunction with an air space of one-half or more of the required through-air spacing shall be permitted to have a thickness of not less than 0.33 mm (0.013 inch), see also 6.1.6.1.12, if it is:

- a) Of material acceptable for supporting uninsulated live parts,
- b) Of adequate strength if exposed or otherwise likely to be subjected to damage,
- c) Securely held in place, and
- d) Located so that it shall not be adversely affected by operation of the equipment in service.

6.1.6.1.12 Insulating material having a thickness less than that indicated in 6.1.6.1.7, 6.1.6.1.9 and 6.1.6.1.11 shall be permitted to be used if tested and found acceptable as indicated in 7.1.10.2 and the mechanical strength and flammability is acceptable for the particular application.

6.1.6.1.13 Clamped joints between insulating-material members shall provide tightly-mated surfaces. Adhesives, cements, or the like, if used to effect a seal in place of a tightly-mated joint, shall be acceptable for the purpose.

6.1.6.1.14 The spacing between uninsulated live parts of different circuits (such as between shunt trip release and primary circuits) shall not be less than that required for the circuit of the higher voltage.

6.1.6.1.15 Live screw-heads or nuts on the underside of a case intended for surface mounting shall be suitably insulated or isolated from the enclosure or from a grounded metal mounting-plate in one of the following ways:

- a) Spaced according to Table 6.1.6.1.1 and reliably prevented from turning or loosening by staking, upsetting, or other equivalent means;
- b) Countersunk not less than 3.2 mm (0.125 inch) below the surface of the case; prevented, as in Item (a) above, from turning or loosening; and having under the case a barrier of moisture-absorption-resistant, insulating material fastened to the enclosure or to the metal mounting-plate; the barrier shall have such an area that Table 6.1.6.1.2 spacing will be maintained, or
- c) Countersunk not less than 3.2 mm (0.125 inch) in the clear, and then covered with a waterproof, insulating, sealing compound which will not soften at a temperature 15°C (27°F) higher than the temperature attained in the circuit breaker at the point where it is used, but not lower than 90°C (194°F) in any case. Determination of the softening point of a sealing compound shall be made in accordance with the Test Method for Softening Point by Ring-and-Ball Apparatus, ASTM E28-67 (1982).

6.1.6.2 Printed Circuit and Wiring Board Assembly

6.1.6.2.1 The spacings on a printed wiring board assembly shall be permitted to be less than indicated in Table 6.1.6.1.1 if a conformal coating and spacings are utilized in compliance with the requirements described in Table 6.1.6.2.1. The coated printed wiring assembly shall comply with the requirements for conformal coatings described in 7.1.10.3. A coating shall not be required if the voltage is 50 V or less and the board is located so that it is not readily subject to contamination by dust.

Table 6.1.6.2.1
Minimum opposite polarity spacings on printed-wiring assemblies with conformal coatings^a

Voltage between parts	Power available	Minimum spacings	
		mm	Inch
0 – 600	Unlimited	0.8	(1/32)
0 – 30	Limited ^b	0.4	(1/64)
^a Minimum spacing between live parts of opposite polarity. Spacing between live parts and dead metal shall comply with Table 6.1.6.1.1.			
^b See 6.1.6.3.1 and 6.1.6.3.2.			

6.1.6.2.2 As an alternative to the measurement method specified in 6.1.6.2.1, the minimum acceptable clearances (through air spacings) and creepage distances (over surface spacings) for a printed wiring board assembly may be evaluated as specified in 6.1.6.2.3 – 6.1.6.2.5 using the applicable requirements in the Standard for Insulation Coordination Including Clearances and Creepage Distances for Electrical Equipment, UL 840.

6.1.6.2.3 When applying the requirements in the Standard for Insulation Coordination Including Clearances and Creepage Distances for Electrical Equipment, UL 840, the environment for a printed wiring board assembly within a circuit breaker is considered to be:

- a) Pollution degree 3 for an assembly without a conformal coating,
- b) Pollution degree 2 for an assembly with a conformal coating, or
- c) Pollution degree 1 for an assembly with a conformal coating complying with UL 840, Printed Wiring Board Coating Performance Test.

6.1.6.2.4 For Clearance B (controlled overvoltage) requirements in the Standard for Insulation Coordination Including Clearances and Creepage Distances for Electrical Equipment, UL 840, the applicable overvoltage category for line-voltage circuits is Category III. Category I is applicable to low-voltage circuits if short circuit between the parts involved may result in operation of the controlled equipment that increases the risk of fire or electric shock. Any overvoltage protection device needed to achieve these categories shall be provided as an integral part of the circuit breaker.

6.1.6.2.5 Where measurement of clearances and creepage distances is involved to establish the minimum spacings, the methods specified in Measurement of Clearance and Creepage Distances in the Standard for Insulation Coordination Including Clearances and Creepage Distances for Electrical Equipment, UL 840, shall be used.

6.1.6.3 Class 2 Circuits

6.1.6.3.1 Minimum electrical spacings are not specified for Class 2 circuits that comply with 6.1.6.3.2.

6.1.6.3.2 A low-voltage, limited energy Class 2 circuit is a circuit supplied from an isolated secondary winding of a transformer where the open circuit secondary voltage does not exceed 30 V rms or 42.4 V peak. The transformer shall comply with one of the following:

- a) The transformer complies with the construction and test requirements of the Standard for Class 2 and 3 Transformers, UL 1585,
- b) The transformer has an inherent winding impedance which will limit the secondary short circuit current to 8 A at one minute, or
- c) The VA output capacity of the secondary winding is 250 VA or less, and an overcurrent protective device is connected in the secondary circuit rated at: 5 A or less for voltages up to and including 20 V rms; or 100/V_{max} for voltages over 20 V rms, up to and including 30 V rms. V_{max} is the maximum output voltage regardless of load with rated input applied.

6.1.6.3.3 With regard to the requirement in 6.1.6.3.2, a fixed series impedance in the secondary circuit shall be permitted to be used to limit the output of the transformer and, in such case, the secondary winding of the transformer and the fixed series impedance shall be investigated as part of the line-voltage circuit. The maximum output capacity of the secondary circuit shall be determined as described in the power level determination test of 7.1.10.4.

6.1.6.3.4 An overcurrent-protective device as indicated in 6.1.6.3.2(c) shall,

- a) Not be of an automatically reset type;
- b) Be trip-free from the reclosing mechanism if of the manually reset type; and
- c) Not be interchangeable with one of a larger current rating if it is a renewable device.

6.2 Current-Limiting Circuit Breakers

Section 6.2 effective October 31, 2000

6.2.1 Current-limiting circuit breakers shall comply with the construction requirements in All Types, Section 6.1.

6.3 Instantaneous-Trip Circuit Breakers

Section 6.3 effective October 31, 2000

6.3.1 This section covers additional requirements for instantaneous-trip circuit breakers.

6.3.2 An instantaneous-trip circuit breaker shall have an adjustable instantaneous release.

6.3.3 An adjustable setting means of an instantaneous-trip circuit breaker that is accessible without opening a door or removing a cover shall be constructed so that a stop to limit the maximum setting may be installed.

6.4 Circuit Breaker and Ground-Fault Circuit-Interrupters

Added 6.4 effective October 31, 2000

6.4.1 General

Section 6.4 effective October 31, 2000

6.4.1.1 This section covers additional requirements for circuit breakers and ground-fault circuit-interrupters that provide overcurrent protection and personnel protection against risk of electric shock as required by the National Electrical Code, ANSI/NFPA 70. These devices are rated Class A, single-pole, 120 V ac, 60 Hz and 2-pole, 120/240 V ac, 60 Hz.

6.4.1.2 The ground-fault circuit-interrupter portion shall comply with the construction requirements in the Standard for Ground-Fault Circuit-Interrupters, UL 943, and Section 6.4 of this Standard, except that printed wiring board spacings may be evaluated in accordance with 6.1.6.2.2 - 6.1.6.2.5.

6.4.2 Supervisory circuit

6.4.2.1 If a 120/240 V circuit breaker mechanism is a common-trip type, the supervisory circuit need only be provided from one ungrounded pole. If a 2-pole circuit breaker mechanism is not a common-trip type, the need for more than one supervisory circuit shall be evaluated.

6.4A Circuit Breakers with Equipment Ground-Fault Protection

Added Section 6.4A effective October 31, 2000

6.4A.1 This Section covers additional requirements for circuit breakers with equipment ground-fault protection that provide overcurrent protection and ground-fault protection of equipment.

6.4A.2 A multipole device that receives operating power from the circuit to which it is connected shall provide ground-fault protection with one or more ungrounded line terminals of the circuit breaker energized.

6.5 Integrally Fused Circuit Breakers and High Fault Protectors

Section 6.5 effective October 31, 2000

6.5.1 This Section covers additional requirements for fused circuit breakers and accessory high-fault protectors.

6.5.2 An integrally fused circuit breaker shall automatically trip when the cover over the high-fault protectors or fuses, or their container, if separate, is removed if the cover can be removed with the circuit breaker ON.

6.5.3 An integrally fused circuit breaker shall automatically trip by signal, other than main current let-through, from fuses or high-fault protectors upon the clearing of one or more fuses or protectors, unless the circuit breaker is marked in accordance with 9.5.4.

6.5.4 Spacings at the load terminals of an accessory high-fault protector shall comply with Table 6.1.6.1.1, Columns A and B.

6.5.5 Spacings at other than the load terminals of an accessory high-fault protector shall comply with Table 6.1.6.1.1, Columns C, D, and E.

6.5.6 If two or more high-fault protectors having different let-through characteristics are provided for different ranges of ratings within a frame size, the construction shall be investigated in accordance with 7.5.4, unless a rejection means is provided to prevent the installation of a protector in any lower rated circuit breaker where it is not intended.

6.5.7 If two or more accessory high-fault protectors are provided for different ranges of ratings within a frame size, the combination shall be investigated in accordance with 7.5.4, unless a rejection means is provided to prevent the installation of a protector to any lower rated circuit breaker where it is not intended.

No Text on This Page

6.5.8 Except as indicated in 6.5.9, a high-fault protector or accessory high-fault protector casing shall be of ceramic, melamine impregnated glass fiber, or the equivalent.

6.5.9 Materials other than those specified in 6.5.8 shall be permitted if they are determined to be acceptable for the application.

6.5.10 Among the factors taken into consideration during an investigation, as indicated in 6.5.9, are the following properties of a material:

- a) Physical strength;
- b) Resistance to impact;
- c) Moisture-absorptive properties;
- d) Combustibility; and
- e) Resistance to distortion at temperatures to which the casing may be subjected under conditions of normal or abnormal use.

All of these factors shall be considered with regard to thermal aging.

6.5.11 Connections between the link and the terminals of a protector or accessory protector shall be such that a permanent electrical connection is provided. The connection shall be soldered, brazed, or welded, or shall otherwise be made permanently and adequately secure.

6.5.12 An adhesive used in a protector or accessory protector shall adequately and reliably secure together the parts that it is intended to secure.

6.5.13 To determine whether the adhesive complies with the requirement in 6.5.12 samples of the protector or accessory protector shall be subjected to appropriate interrupting tests, in combination with the circuit breaker after conditioning. Conditioning tests on the adhesive shall not be required if the device performs acceptably during the interrupting tests with the adhesive omitted.

6.6 Adjustable Circuit Breakers

Section 6.6 effective October 31, 2000

6.6.1 This section covers additional requirements for adjustable circuit breakers.

6.6.2 As concerns the current setting, these circuit breakers are classed as either Type A or Type B. See 6.6.3 and 6.6.4.

6.6.3 The current setting (I_r) of a Type A circuit breaker shall not be adjustable to a value greater than the rated current (I_n) of the circuit breaker.

6.6.4 A Type B circuit breaker shall be restricted so that the current setting (I_r), once fixed at a particular value, cannot be changed to one higher, except by the addition or substitution of a part requiring use of a tool.

6.6.5 For a Type A circuit breaker, the current setting (I_r) shall be that which can be inferred from the device's settings, markings, or instruction literature. For a Type B circuit breaker, the current setting shall be that of the marking.

6.7 Heating, Air Conditioning, and Refrigeration (HACR) Circuit Breakers

Section 6.7 effective October 31, 2000

6.7.1 Heating, air conditioning, and refrigeration (HACR) circuit breakers shall comply with the construction requirements in All Types, Section 6.1.

6.8 Remotely-Operated Circuit Breakers

Section 6.8 effective October 31, 2000

6.8.1 This section covers additional requirements for remotely-operated circuit breakers.

6.8.2 A remotely-operated circuit breaker shall be trip free and the operating handle and mechanism shall be independent of the remotely-controlled operation.

6.8.3 In a 2-pole remotely-operated circuit breaker, the remotely controlled operation shall be permitted to operate only one pole.

6.9 Switching Duty (SWD) Rated Circuit Breakers

Section 6.9 effective October 31, 2000

6.9.1 Switching duty (SWD) rated circuit breakers shall comply with the construction requirements in All Types, Section 6.1.

6.10 400 Hz Rated Circuit Breakers

Section 6.10 effective October 31, 2000

6.10.1 Circuit breakers rated 400 Hz shall comply with the construction requirements in All Types, Section 6.1.

6.11 Draw-Out Circuit Breakers

Section 6.11 effective October 31, 2000

6.11.1 This section covers additional requirements for draw-out circuit breakers.

6.11.2 The configuration of the grounding means between a metal part of a draw-out type circuit breaker intended to be grounded and any permanently grounded part shall be such that grounding continuity is established 3.2 mm (1/8 inch) before either primary or secondary disconnects of the draw-out unit are energized; and also be maintained until both primary and secondary disconnects have been de-energized by at least 3.2 mm (1/8 inch). See the electrical continuity test described in 7.11.1.

6.11.3 Draw-out circuit breakers shall be equipped with self-coupling disconnecting devices.

6.11.4 Interlocks shall be provided:

- a) To prevent moving the circuit breaker to or from the connected position when the circuit breaker is in the closed position, and
- b) To prevent closing the circuit breaker unless the primary disconnecting devices are in full contact or are separated by a distance that will withstand a minimum voltage described in 7.11.2.

6.12 Series-Connected Circuit Breakers

Section 6.12 effective October 31, 2000

6.12.1 Series-connected circuit breakers shall comply with the construction requirements in All Types, Section 6.1.

6.13 Interchangeable-Trip Circuit Breakers

Section 6.13 effective October 31, 2000

6.13.1 This section covers additional requirements for interchangeable-trip circuit breakers.

6.13.2 A circuit breaker having a frame size of 100 A or less in conjunction with a voltage rating of not more than 240 V ac or 125/250 V dc, shall not have an interchangeable trip unit.

6.13.3 A circuit breaker having a frame size of more than 100 A in conjunction with a voltage rating of not more than 240 V ac or 125/250 V dc, and any circuit breaker having a voltage rating greater than 240 V ac or 125/250 V dc, shall be permitted to have interchangeable trip units; except that an interchangeable trip unit for use in a circuit breaker having a voltage rating of not more than 240 V ac or 125/250 V dc shall not have a rating of less than 50 A. In any case, an interchangeable trip unit rated at 50 A or less shall be clearly marked in accordance with 9.13.4.

6.13.4 An interchangeable trip unit shall not be capable of being installed in any frame having a current rating less than that of the trip unit.

6.13.5 An interchangeable trip unit shall not be adjustable beyond the limitations imposed by 6.1.5.7 without breaking a seal or a permanent fastening.

6.13.6 An interchangeable trip unit circuit breaker shall have no parts that will fall out of the circuit breaker housing when its cover is removed with the circuit breaker mounted in any position on a vertical surface.

7 TESTS

7.1 Standard Circuit Breakers

Section 7.1 effective October 31, 2000

7.1.1 General

7.1.1.1 The performance of a circuit breaker construction shall be investigated by subjecting representative sets to the test program indicated in Table 7.1.1.2. At the option of the manufacturer, Test Sequences X, Y, and Z may be combined for all frame sizes. When combining X-Y-Z Sequences or Y-Z Sequences, the Interrupting Test in the Y Sequence may be omitted.

7.1.1.2 Samples shall be selected based on Table 7.1.1.1.

Table 7.1.1.1
Sets of samples

Ampere rating of frame	Interchangeable trip unit	Samples per set ^a	
		Test sequence ^b	
		X or X-Y-Z	Y or Z or Y-Z
0 – 225	No	3 or 4 ^c	3 or 4 ^c
0 – 225	Yes	3 frames, 3 trip units	3 frames, 3 trip units
226 – 400	No	3 ^d	2
226 – 400	Yes	2 frames, 3 trip units	2 frames, 2 trip units
401 – 1600	No	3 ^e	1
401 – 1600	Yes	1 frame, 3 trip units	1 frame, 1 trip unit
1601 and Higher	No	1	1
1601 and Higher	Yes	1 frame, 1 trip unit	1 frame, 1 trip unit

^aIf a circuit breaker is not marked "line" and "load," one sample shall be tested with reversed line and load connections or an additional sample of each test set shall be provided. When only one sample constitutes a test set for operating tests, a second sample is required for reversed line-load connection tests. For reversed line-load connections, see 7.1.1.18.

^bOne set per test sequence or combination of test sequences.

^cSee 7.1.1.4 and 7.1.1.12.

^dSee 7.1.1.5 and 7.1.2.1.2.

^eSee 7.1.1.5 and 7.1.2.1.3.

Table 7.1.1.2
Test sequences^a

Circuit-breaker type		Fully magnetic and solid-state trip ^b and uncompensated thermal breakers ^c rates 25°C or 40°C ^{d,e}			Compensated thermal breakers ^f		
Test	Clause	Sequence			Sequence		
		X	Y	Z	X	Y	Z
1. 200 percent Calibration at 25°C (77°F)	7.1.2.2	X	X	X	X	X	X
2. 135 percent Calibration at 25°C (77°F)	7.1.2.3	X			X	X	
3. 200 percent Calibration at 40°C (104°F)	7.1.2.2				X		
4. 135 percent Calibration at 40°C (104°F)	7.1.2.3				X		
5. Calibration of adjustable instantaneous trip	7.1.2.5		X			X	
6. Overload	7.1.3	X			X		
7. 100 percent Calibration at 40C (104F) ^{g,h,j}	7.1.2.4, 7.1.4	X			X		
8. Temperature and 100 percent calibration at 25°C (77°F)	7.1.2.4, 7.1.4	X			X		
9. Endurance	7.1.5		X			X	
10. 200 percent Calibration at 25°C (77°F), repeated	7.1.6		X			X	
11. 135 percent Calibration at 25°C (77°F), repeated	7.1.6		X			X	
12. 135 percent Calibration at 40C (104F), repeated ^l	7.1.6					X	
13. Interrupting	7.1.7		x ^k	x ^l		x ^k	x ^l
14. 200 percent Trip-out at 25°C (77°F)	7.1.8		X	X		X	X
15. Dielectric voltage-withstand	7.1.9	X	X	X	X	X	X
x—Indicates test required.							
^a For circuit breakers rated ac/dc, see 7.1.1.6. ^b Circuit breakers whose automatic operation does not depend on the heating effect of current. ^c Circuit breakers whose automatic operation depends on the heating effect of current and are affected by changes in ambient temperature. ^d If the degree of compensation used in a circuit breaker is such that it will not carry rated current at 40°C(104°), it may, at the option of the manufacturer, be tested as a 25°(77°F) circuit breaker. ^e If a circuit breaker includes any thermal compensation in its tripping mechanism, and if the manufacturer desires to have the circuit breaker marked “40°C,” it shall be subjected to the tests for a compensated thermal breaker. ^f Circuit breakers whose automatic operation depends on the heating effect of current, and which incorporate means for counteracting the effect of change in ambient temperature. ^g This test may be performed after the temperature and 100 percent calibration tests at 25°C (77°F). ^h Applies only to circuit breakers rated 40°C (104°F).							

Table 7.1.1.2 Continued on Next Page

Table 7.1.1.2 Continued

Circuit-breaker type		Fully magnetic and solid-state trip ^b and uncompensated thermal breakers ^c rates 25°C or 40°C ^{d,e}			Compensated thermal breakers ^f		
Test	Clause	Sequence			Sequence		
		X	Y	Z	X	Y	Z
ⁱ For an uncompensated thermal circuit breaker rated 40°C (104°F), the test may be combined with the temperature test if the ambient temperature is 40°C during the temperature test.							
^j May be omitted if the tripping time at 135 percent of rated current in a 25°C (77°F) ambient after the endurance test is no more than it was before the endurance test.							
^k Test current shall be per Table 7.1.7.3 and operations shall be O-t-CO, where t is minimum of 2 minutes, maximum of 1 hour.							
^l Test current shall be per Table 7.1.7.2 and operations shall be per Table 7.1.7.1.							

7.1.1.3 No conditioning of the circuit breaker shall take place during or between tests. During the test program, a circuit breaker shall be mounted with the front of the circuit breaker on a vertical plane in a position which would normally cause the line terminals to be at the top; except that for the 135- and 200-percent calibration test and dielectric voltage-withstand test, a circuit breaker may be mounted in any position in which it can be properly used.

7.1.1.4 The investigation of a circuit breaker of a frame size of 225 A or less of a specific pole construction shall include the testing of sets of samples of the maximum and minimum ratings. Sets of samples of one or more intermediate ratings may be additionally required to be subjected to the complete test program or a partial test program depending on construction differences.

7.1.1.5 The investigation of a circuit breaker of frame size more than 225 A usually requires complete testing of sets of the maximum rating only, unless basic construction differences are present. A set of the minimum rating shall be subjected to 200, 135, and 100 percent calibration and, where applicable to the instantaneous trip calibration, whenever such tests are not required on this rating as part of a more extensive test program. If the frame size includes ampere ratings of 125 A or less, but more than 30 A, that are to be marked for use with 75°C (167°F) wire, ratings shall be selected for the overload and temperature tests based on the use of 75°C (167°F) wire. In selecting the rating(s) for test, consideration shall be given to the relative heat dissipating effect of the 60°C (140°F) versus 75°C (167°F) wire size for the particular ampere rating.

7.1.1.6 If the marked rating of a circuit breaker includes both alternating and direct current, or if the marked rating does not exclude one or the other, the acceptability of the circuit breaker for both ratings shall be determined. The ac rating shall be verified by the test program described in Table 7.1.1.2. To verify the dc rating it will ordinarily be necessary only to additionally subject a previously untested sample set that has the maximum ampere rating of the frame size, to:

- a) All calibration and trip-out tests with either ac or dc, whichever is more convenient;
- b) Overload, endurance, and interrupting tests with dc; and
- c) Dielectric voltage withstand tests with ac.

7.1.1.7 A circuit breaker having an instantaneous response as indicated in 6.1.5.7 shall be capable of passing the 100-percent calibration test with the instantaneous response set at its minimum setting, and the other tests with the instantaneous response set at its maximum setting, except as noted in Adjustable instantaneous trip calibration test, 7.1.2.5, note c of Table 7.1.3.1 and note a of Table 7.1.7.2.

7.1.1.8 For tests made with ac, a circuit having the rated frequency of the circuit breaker shall be used. If the specified frequency is in the range of 50 to 60 Hz, or if no frequency is indicated, a 48 – 62 Hz circuit shall be used. If the specified frequency is 400 Hz, a 380 – 420 Hz circuit shall be used. See 400-Hz Rated Circuit Breakers, Section 7.10 for testing 400 Hz rated circuit breakers.

7.1.1.9 Separately-operable circuit breakers in a common base shall not be considered as multipole circuit breakers but shall be treated throughout as individual circuit breakers. When a 2-pole circuit breaker consists of poles constructed so as to trip independently, not common trip, each pole shall be treated as a single pole circuit breaker during the calibration tests.

7.1.1.10 Separately-operable single-pole circuit breakers shall be treated as individual circuit breakers even though they may have a common housing.

7.1.1.11 While normally 1-, 2-, and 3-pole constructions will require individual representative sets of samples, it may be possible in certain instances, where constructions are basically identical, to represent other than the pole construction being tested.

7.1.1.12 If a single-pole circuit breaker is rated at 120/240 V ac or 125/250 V dc, see 6.1.5.3, two such circuit breakers shall be tested together in the intended manner as a 2-pole, independent-trip circuit breaker in the overload, endurance, interrupting, and dielectric voltage-withstand test described below. Two such "pairs" of circuit breakers constitute a set.

7.1.1.13 In determining if a circuit breaker complies with the test requirements, the device shall be mounted or supported as in service and tested under conditions approximating those of intended operation, except as otherwise noted.

7.1.1.14 If a circuit breaker is marked for use with aluminum conductors only, all tests shall be conducted using aluminum conductors.

7.1.1.15 At the conclusion of any test sequence, there shall be no malfunction of functional parts of the circuit breaker, such as broken welds, and no more than 50 percent breaking of pigtails per pole.

7.1.1.16 When wires are used to connect a circuit breaker for test, the tightening torque applied to the circuit breaker terminals shall not exceed the value marked on the circuit breaker.

7.1.1.17 A 2-pole common trip circuit breaker that has an additional marking to indicate acceptability on a 3-phase, corner-grounded, delta circuit shall be caused to control 3-phase test circuits during the overload and endurance tests and both single and 3-phase circuits during the interrupting test. See 9.1.1.20.

7.1.1.18 Except for single-pole circuit breakers tested singly, if a circuit breaker is not marked "line" and "load," one sample of each set tested, or one additional sample, shall be connected with the line and load connections reversed during the overload, endurance, and interrupting tests. When an additional sample is used, it shall be subjected to the initial 200-percent calibration, the trip-out, and the dielectric voltage-withstand tests.

7.1.1.19 In the overload, endurance, and interrupting tests, a circuit breaker shall be mounted within the smallest metal enclosure that will be used in actual service; except that for the endurance test, an enclosure shall not be required if the vertical surface on which it is mounted is metal, unless there are features which would affect the performance of the circuit breaker if not mounted within an enclosure. The door or cover and any other openings including used and unused openings shall be closed on the outside of the enclosure by means of tape. However, any ventilating openings specified and permitted by this Standard for circuit breakers rated 400 A or more, see 9.1.1.19, need not be closed. If the inside of the enclosure is painted, the paint shall be scraped off on the inside surface of the metal enclosure in areas of the vents of the circuit breaker and where an arc is likely to strike. A nonconducting enclosure shall be used if the circuit breakers are marked as precluding use in a metal enclosure as required by 9.1.1.18.

7.1.1.20 In the overload, endurance, and interrupting tests, a fuse acceptable for branch circuit protection shall be connected between the enclosure or mounting surface, see 7.1.1.19, and one line to indicate arc over as indicated in 7.1.11.3.1.14 and Figures 7.1.3.1, 7.1.5.1 and 7.1.7.1, respectively. The fuse shall be a 30 A nonrenewable type, having a voltage rating not less than the rating of the device being tested. The connection of the fuse shall be made to the load side of the limiting impedance by means of a No. 10 AWG (5.3 mm²) wire not more than 1.829 m (6 feet) in length. The enclosure or mounting surface shall not be otherwise electrically connected.

7.1.2 Calibration tests

7.1.2.1 General

7.1.2.1.1 To determine if a multipole circuit breaker complies with the requirements of 7.1.2.2 for operation on 200 percent of rated current, each pole shall be tested separately. To determine if a multipole circuit breaker complies with the requirements of 7.1.2.3 and 7.1.2.4, all poles shall be loaded equally, except as indicated in 7.1.1.10.

7.1.2.1.2 To determine if a circuit breaker rated 226 – 400 A complies with the requirements of 7.1.2.2 and 7.1.2.3, the procedure shall be as follows. For the X Sequence, if interchangeable trip units are involved, two samples of the frame and three samples of the trip unit shall constitute a set for the 200- and 135-percent initial calibration tests at 25°C (77°F). The two trip units having the shortest tripping time during the 135-percent calibration test at 25°C (77°F) and two frames shall be used for the remainder of the test sequence. For the Y and Z Sequences, two samples of the frame and two samples of the trip unit shall constitute a set. For the X Sequence, if noninterchangeable trip units are involved, three samples shall constitute a set for the 200- and 135-percent tests. The two samples having the shortest tripping time during the 135-percent calibration test at 25°C (77°F) shall be used for the remainder of the test sequence. For the Y and Z Sequences, two samples shall constitute a set. If X-Y-Z Sequences are combined, the procedure described for the X Sequence shall be followed.

7.1.2.1.3 To determine if a circuit breaker rated 401 – 1600 A complies with the requirements of 7.1.2.2 and 7.1.2.3, the procedure shall be as follows. For the X Sequence, if interchangeable trip units are involved, one sample of the frame and three samples of the trip unit shall constitute a set for the 200- and 135-percent initial calibration tests at 25°C (77°F). The trip unit having the shortest tripping time during the 135-percent calibration test at 25°C (77°F) and one frame shall be used for the remainder of the test sequence. For the Y and Z Sequences, one frame and one trip unit shall constitute a set. For the X Sequence, if noninterchangeable trip units are involved, three samples shall constitute a set for the 200- and 135-percent tests. The sample having the shortest tripping time during the 135-percent calibration test at 25°C (77°F) shall be used for the remainder of the test sequence. For the Y and Z Sequences, if noninterchangeable trip units are involved, one sample shall constitute a set. If the X-Y-Z Sequences are combined, the procedure described for the X Sequence shall be followed.

7.1.2.1.4 Calibration tests of a circuit breaker may be made at any voltage, using either ac or dc, taking into consideration the characteristics of the circuit breaker and the possible conditions of use. A device not specifically marked for either dc or ac shall be subjected to the 100-percent test with ac and may be subjected to the 135- and 200-percent test with dc. A circuit breaker rated only for a specific frequency other than in the range of 50/60 Hz, or dc, shall be tested at the rated frequency, or dc, or both, as appropriate.