

UL 60745-1

Hand-Held Motor-Operated Electric Tools – Safety – Part 1: General Requirements

Document Was Downloaded By Rice, Shi SHIMISHENG
For Use By KUANTECH CO LTD
12039 : 8/1/2007 - 10:50 PM

UL COPYRIGHTED MATERIAL –
NOT AUTHORIZED FOR FURTHER REPRODUCTION OR
DISTRIBUTION WITHOUT PERMISSION FROM UL



Documents

Document Sharing Hub

Document Was Downloaded By Rice, Shi SHIMISHENG
For Use By KUANTECH CO LTD
12039 : 8/1/2007 - 10:50 PM

UL COPYRIGHTED MATERIAL –
NOT AUTHORIZED FOR FURTHER REPRODUCTION OR
DISTRIBUTION WITHOUT PERMISSION FROM



Documents

Document Sharing Hub

Underwriters Laboratories Inc. (UL)
333 Pfingsten Road
Northbrook, IL 60062-2096

UL Standard for Safety for Hand-Held Motor-Operated Electric Tools – Safety – Part 1: General Requirements, UL 60745-1

Fourth Edition, Dated July 31, 2007

Summary of Topics

Adoption of the Fourth Edition of IEC 60745-1, Hand-Held Motor-Operated Electric Tools – Safety – Part 1: General Requirements as the Fourth Edition of UL 60745-1, includes the following changes: a) Revised scope to add work stands to equipment covered under the standard; b) Addition of normative references; c) Expanded definitions; d) Clarification of sample requirements; e) Modification of marking and instruction requirements to clarify symbols and markings that may be used, placement of symbols and markings on tools, and general wording and formatting requirements; f) Modification of heating test requirements to specify the switch positions for testing three-phase tools suitable and not suitable for a single-phase supply, to clarify the method for determining the temperature rise of a winding, and to clarify the sequence of tests to be performed on a tool sample after the Humidity Test; g) Modification of leakage current test requirements to specify that tools with heating elements shall have total leakage current within the specified limits of IEC 60335-1 and to specify changes to the test circuit; h) Modification of the moisture resistance test requirements to address tools with liquid systems including residual current devices (RCD) used to provide protection from shock in case of failure of a liquid system; i) Modification of the abnormal temperature test requirements to address hazardous conditions resulting from fault conditions during use of a tool, address test criteria for tools relying on a miniature fuse link, to address current flowing through protective impedance, and to address Class I tools having Class II constructions; j) Modification of mechanical hazard requirements for dust collection openings and tools marked with no-load speeds; k) Addition of mechanical strength requirements for handles or grasping surfaces of a tool; l) Modification of construction requirements to address tools employing a liquid system, to allow for Class I or Class II constructions for tools provided with a RCD or alternate construction requirements, to specify requirements for capacitors complying with protective impedance requirements, and to add requirements for insulating material for handles and other grasping areas of a tool; m) Addition of component requirement to allow a RCD to be an integral part of the construction of a tool; n) Modification of supply connection and flexible cord requirements to clarify the means of power connection for tools, to specify bushings or smooth edges for cord entry, to allow cord guards to be integral with the cord, to specify requirements for separation of conductors of a supply cord for a type X attachment; o) Modification of requirements for creepage and clearances distances through insulation to address lacquered or enameled windings, live parts in contact with dirt deposits, reductions of distances for tools with working voltages less than or equal to 130 V, and distances through insulation between metal parts; p) Modification of resistance to heat, fire, and tracking requirements to reference IEC 60695-2-11 as the applicable glow-wire and hot wire test requirements; q) Addition of requirements to address tools fitted with a laser; r) Deletion of Annexes C, D, and E; s) Modification of Annex F to specify that the Needle Flame Test is to be conducted in accordance with IEC 60695-11-5; t) Modification of Annex G to specify changes to tracking test requirements specified in IEC 60112 that are to be applied for this standard; u) Modification of Annex I to specify changes to switch test requirements specified in IEC 61058-1 to applied for this standard; v)

UL COPYRIGHTED MATERIAL –
NOT AUTHORIZED FOR FURTHER REPRODUCTION OR
DISTRIBUTION WITHOUT PERMISSION FROM



Documents

Document Sharing Hub

Modification to Annex J, Sequence of Tests, to reference Clause 29.2 for the glow-wire and hot wire test requirements; w) Modification of Annexes K and L to clarify marking requirements for battery tools and battery packs; x) Addition of Annex M to specify requirements for work stands; y) Addition of Annex N as an informative annex that provides information on unacceptable variations for manufacturing and production tests.

Future Effective Dates	References
June 1, 2010	Entire Standard

The new requirements are substantially in accordance with UL's Proposal(s) on this subject dated January 2, 2007 and April 6, 2007.

As indicated on the title page (page 1), this UL Standard for Safety is an American National Standard. Attention is directed to the note on the title page of this Standard outlining the procedures to be followed to retain the approved text of this ANSI/UL Standard.

The UL Foreword is no longer located within the UL Standard. For information concerning the use and application of the requirements contained in this Standard, the current version of the UL Foreword is located on ULStandardsInfoNet at: <http://ulstandardsinfonet.ul.com/ulforeword.html>

The master for this Standard at UL's Northbrook Office is the official document insofar as it relates to a UL service and the compliance of a product with respect to the requirements for that product and service, or if there are questions regarding the accuracy of this Standard.

UL's Standards for Safety are copyrighted by UL. Neither a printed copy of a Standard, nor the distribution diskette for a Standard-on-Diskette and the file for the Standard on the distribution diskette should be altered in any way. All of UL's Standards and all copyrights, ownerships, and rights regarding those Standards shall remain the sole and exclusive property of UL.

All rights reserved. No part of this publication may be reproduced, stored in a retrieval system, or transmitted in any form by any means, electronic, mechanical photocopying, recording, or otherwise without prior permission of UL.

Revisions of UL Standards for Safety are issued from time to time. A UL Standard for Safety is current only if it incorporates the most recently adopted revisions.

UL provides this Standard "as is" without warranty of any kind, either expressed or implied, including but not limited to, the implied warranties of merchantability or fitness for any purpose.

In no event will UL be liable for any special, incidental, consequential, indirect or similar damages, including loss of profits, lost savings, loss of data, or any other damages arising out of the use of or the inability to use this Standard, even if UL or an authorized UL representative has been advised of the possibility of such damage. In no event shall UL's liability for any damage ever exceed the price paid for this Standard, regardless of the form of the claim.

UL will attempt to answer support requests concerning electronic versions of its Standards. However, this support service is offered on a reasonable efforts basis only, and UL may not be able to resolve every support request. UL supports the electronic versions of its Standards only if they are used under the conditions and operating systems for which it is intended. UL's support policies may change from time-to-time without notification.

UL reserves the right to change the format, presentation, file types and formats, delivery methods and formats, and the like of both its printed and electronic Standards without prior notice.

Purchasers of the electronic versions of UL's Standards for Safety agree to defend, indemnify, and hold UL harmless from and against any loss, expense, liability, damage, claim, or judgement (including reasonable attorney's fees) resulting from any error or deviation introduced while purchaser is storing an electronic Standard on the purchaser's computer system.

If a single-user version electronic Standard was purchased, one copy of this Standard may be stored on the hard disk of a single personal computer, or on a single LAN file-server or the permanent storage device of a multiple-user computer in such a manner that this Standard may only be accessed by one user at a time and for which there is no possibility of multiple concurrent access.

If a multiple-user version electronic Standard was purchased, one copy of the Standard may be stored on a single LAN file-server, or on the permanent storage device of a multiple-user computer, or on an Intranet server. The number of concurrent users shall not exceed the number of users authorized.

Electronic Standards are intended for on-line use, such as for viewing the requirements of a Standard, conducting a word search, and the like. Only one copy of the Standard may be printed from each single-user version of an electronic Standard. Only one copy of the Standard may be printed for each authorized user of a multiple-user version of an electronic Standard. Because of differences in the computer/software/printer setup used by UL and those of electronic Standards purchasers, the printed copy obtained by a purchaser may not look exactly like the on-line screen view or the printed Standard.

An employee of an organization purchasing a UL Standard can make a copy of the page or pages being viewed for their own fair and/or practical internal use.

The requirements in this Standard are now in effect, except for those paragraphs, sections, tables, figures, and/or other elements of the Standard having future effective dates as indicated in the preface. The prior text for requirements that have been revised and that have a future effective date are located after the Standard, and are preceded by a "SUPERSEDED REQUIREMENTS" notice.

New product submittals made prior to a specified future effective date will be judged under all of the requirements in this Standard including those requirements with a specified future effective date, unless the applicant specifically requests that the product be judged under the current requirements. However, if the applicant elects this option, it should be noted that compliance with all the requirements in this Standard will be required as a condition of continued Listing and Follow-Up Services after the effective date, and understanding of this should be signified in writing.

Copyright © 2007 Underwriters Laboratories Inc.

This Standard consists of pages dated as shown in the following checklist:

Page	Date
1-164.....	July 31, 2007

UL COPYRIGHTED MATERIAL –

NOT AUTHORIZED FOR FURTHER REPRODUCTION OR
DISTRIBUTION WITHOUT PERMISSION FROM UL



Documents

Document Sharing Hub

No Text on This Page

Document Was Downloaded By Rice, Shi SHIMISHENG
For Use By KUANTECH CO LTD
12039 : 8/1/2007 - 10:50 PM

UL COPYRIGHTED MATERIAL –
NOT AUTHORIZED FOR FURTHER REPRODUCTION OR
DISTRIBUTION WITHOUT PERMISSION FROM UL



Documents

Document Sharing Hub



Canadian Standards Association
CAN/CSA-C22.2 No. 60745-1-07
Third Edition
(IEC 60745-1:2006, MOD)



Underwriters Laboratories Inc.
UL 60745-1
Fourth Edition

Hand-Held Motor-Operated Electric Tools – Safety – Part 1: General Requirements

July 31, 2007

This national standard is based on publication IEC 60745-1, 4th Edition (2006).



ANSI/UL 60745-1-2007

Approved
by
Standards Council
of Canada



Documents

Document Sharing Hub

Commitment for Amendments

This standard is issued jointly by the Canadian Standards Association (CSA) and Underwriters Laboratories Inc. (UL). Comments or proposals for revisions on any part of the standard may be submitted to CSA or UL at any time. Revisions to this standard will be made only after processing according to the standards development procedures of CSA and UL. CSA and UL will issue revisions to this standard by means of a new edition or revised or additional pages bearing their date of issue.

ISBN 1-55436-444-2

© 2007

Canadian Standards Association

All rights reserved. No part of this publication may be reproduced in any form whatsoever without the prior permission of the publisher.

To purchase CSA Standards and related publications, visit CSA's Online Store at www.ShopCSA.ca or call toll-free 1-800-463-6727 or 416-747-4044.

Copyright © 2007 Underwriters Laboratories Inc.

Revisions of this Standard will be made by issuing revised or additional pages bearing their date of issue. A UL Standard is current only if it incorporates the most recently adopted revisions, all of which are itemized on the transmittal notice that accompanies the latest set of revised requirements. Comments or proposals for revisions on any part of the Standard may be submitted to UL at any time. Proposals should be submitted via a Proposal Request in UL's On-Line Collaborative Standards Development System (CSDS) at <http://csds.ul.com>.

The most recent designation of ANSI/UL 60745-1 as an American National Standard (ANSI) occurred on July 31, 2007. The ANSI approval for this standard does not include the Cover Page, Transmittal Pages, Title Page, or Preface.

This ANSI/UL Standard for Safety, which consists of the Fourth edition is under continuous maintenance, whereby each revision is ANSI approved upon publication.

To purchase UL Standards, visit COMM 2000 at http://www.comm-2000.com/help/how_to_order.aspx or call toll-free 1-888-853-3503.

CONTENTS

Preface	7
NATIONAL DIFFERENCES	9
FOREWORD	10
INTRODUCTION	12
1 Scope	13
2 Normative references	14
3 Terms and Definitions	22
4 General requirements	26
5 General conditions for the tests	26
6 Void	29
7 Classification	29
8 Marking and instructions	29
9 Protection against access to live parts	42
10 Starting	43
11 Input and current	44
12 Heating	44
13 Leakage current	49
14 Moisture resistance	50
15 Electric strength	54
16 Overload protection of transformers and associated circuits	55
17 Endurance	56
18 Abnormal operation	57
19 Mechanical hazards	63
20 Mechanical strength	64
21 Construction	66
22 Internal wiring	74
23 Components	75
24 Supply connection and external flexible cords	78
25 Terminals for external conductors	86
26 Provision for earthing	89
27 Screws and connections	91
28 Creepage distances, clearances and distances through insulation	94
29 Resistance to heat, fire and tracking	97
30 Resistance to rusting	99
31 Radiation, toxicity and similar hazards	100
 Annex A (normative) Measurement of creepage distances and clearances	
A.1 Measurement of creepage distances and clearances	113

UL COPYRIGHTED MATERIAL –

NOT AUTHORIZED FOR FURTHER REPRODUCTION OR
DISTRIBUTION WITHOUT PERMISSION FROM



Documents

Document Sharing Hub

Annex B (normative) Motors not isolated from the supply mains and having basic insulation not designed for the rated voltage of the tool

B.1 Scope	118
B.9 Protection against access to live parts	118
B.12 Heating	118
B.15 Electric strength	118
B.18 Abnormal operation	118
B.21 Construction	118
B.28 Creepage distances, clearances and distances through insulation	119

Annex C Void

Annex D Void

Annex E Void

Annex F (normative) Needle-flame test

5 Description of test apparatus	124
5.4 Specified layer	124
7 Severities	124
9 Test procedure	124
9.3 Number of test specimens	124
11 Evaluation of test results	124

Annex G (normative) Proof tracking test

3 Test specimen	125
5 Test apparatus	125
8 Basic test procedure	125
9 Determination of erosion	125
10 Determination of proof tracking index (PTI)	125
11 Determination of comparative tracking index (CTI)	125

Annex H Void

Annex I (normative) Switches

8 Marking and documentation	127
13 Mechanism	127
15 Insulation resistance and dielectric strength	127
17 Endurance	127
17.2.4.4 Test at accelerated speed (TC4)	128
20 Clearances, creepage distances, solid insulation and coatings of rigid printed board assemblies	129

Annex J (informative) Selection and sequence of the tests of clause 29

Annex K (normative) Battery tools and battery packs

K.1 Scope	131
K.2 Normative references	131
K.3 Terms and Definitions	131
K.5 General conditions for the tests	132
K.7 Classification	132
K.8 Marking and instructions	132
K.9 Protection against electric shock	133
K.10 Starting	134
K.11 Input and current	134
K.12 Heating	134
K.13 Leakage current	135
K.14 Moisture resistance	135
K.15 Electric Strength	135
K.16 Overload protection of transformers and associated circuits	135
K.17 Endurance	136
K.18 Abnormal operation	136
K.19 Mechanical Hazards	137
K.20 Mechanical strength	137
K.21 Construction	137
K.22 Internal wiring	137
K.23 Components	138
K.24 Supply connection and external flexible cords	138
K.25 Terminals for external conductors	138
K.26 Provision for earthing	138
K.27 Screws and connections	138
K.28 Creepage distances, clearances and distances through insulation	139
K.29 Resistance to heat, fire and tracking	140

Annex L (normative) Battery tools and battery packs provided with mains connection or non-isolated sources

L.1 Scope	142
L.2 Normative References	142
L.3 Terms and definitions	142
L.5 General conditions for the tests	143
L.7 Classification	143
L.8 Marking and Instructions	143
L.9 Protection against electric shock	145
L.10 Starting	145
L.11 Input and current	145
L.12 Heating	146
L.13 Leakage current	146
L.14 Moisture resistance	146
L.15 Electric strength	146
L.16 Overload protection of transformers and associated circuits	146
L.17 Endurance	146
L.18 Abnormal operation	146

UL COPYRIGHTED MATERIAL -
NOT AUTHORIZED FOR FURTHER REPRODUCTION OR
DISTRIBUTION WITHOUT PERMISSION FROM



Documents

Document Sharing Hub

L.19 Mechanical Hazards	147
L.20 Mechanical strength	147
L.21 Construction	148
L.22 Internal wiring	148
L.23 Components	148
L.24 Supply connection and external flexible cords	149
L.25 Terminals for external conductors	149
L.26 Provision for earthing	149
L.28 Creepage distances, clearances and distances through insulation	149
L.29 Resistance to heat, fire and tracking	151

Annex M (normative) Safety of working stands for operation with hand-held motor-operated electric tools

M.1 Scope	153
M.2 Normative references	153
M.3 Definitions	153
M.5 General conditions for the tests	153
M.7 Classification	154
M.8 Marking and instructions	154
M.10 Starting	155
M.11 Input and current	155
M.17 Endurance	155
M.19 Mechanical hazards	155
M.21 Construction	156
M.23 Components	158
M.24 Supply connection and external flexible cords	159
M.25 Terminals for external conductors	159

Annex N (normative) Rules for routine tests

N.1 General	160
N.2 Correct operation test	160
N.3 Electric strength test	160
N.4 Earthing continuity test	161

Addition: Add the following Annex:

Bibliography

Preface

This is the common CSA and UL standard for Hand-Held Motor-Operated Electric Tools – Safety – Part 1. It is the third edition of CAN/CSA-C22.2 No. 60745-1 and the fourth edition of UL 60745-1. This standard is based on IEC 60745-1, fourth edition.

This standard, CAN/CSA-C22.2 No. 60745-1 third edition and UL 60745-1 fourth edition, supercedes CAN/CSA-C22.2 No. 60745-1, second edition and UL 60745-1, third edition.

This common standard was prepared by the Canadian Standards Association (CSA) and Underwriters Laboratories Inc. (UL).

This standard is considered suitable for use for conformity assessment within the stated scope of the standard.

This standard was reviewed by the CSA Subcommittee on Safety of Hand-Held Motor-Operated Electric Tools, under the jurisdiction of the CSA Technical Committee on Consumer and Commercial Products and the CSA Strategic Steering Committee on Requirements for Electrical Safety, and has been formally approved by the CSA Technical Committee.

This standard has been approved as a National Standard of Canada (SCC).

This Standard has been approved by the American National Standards Institute (ANSI) as an American National Standard.

Where reference is made to a specific number of samples to be tested, the specified number is to be considered a minimum quantity.

Note: Although the intended primary application of this standard is stated in its scope, it is important to note that it remains the responsibility of the users of the standard to judge its suitability for their particular purpose.

Level of harmonization

This standard adopts the IEC text with national differences. This standard is published as an equivalent standard for CSA and UL. An equivalent standard is a standard that is substantially the same in technical content, except as follows: Technical national differences are allowed for codes and governmental regulations as well as those recognized as being in accordance with NAFTA Article 905, for example because of fundamental climatic, geographical, technological, or infrastructural factors, scientific justification, or the level of protection that the country considers appropriate. Presentation is word for word except for editorial changes.

All national differences from the IEC text are included in the CSA and UL versions of the standard. While the technical content is the same in each organization's version, the format and presentation may differ.

Interpretations

The interpretation by the standards development organization of an identical or equivalent standard is based on the literal text to determine compliance with the standard in accordance with the procedural rules of the standards development organization. If more than one literal interpretation has been identified, a revision is to be proposed as soon as possible to each of the standards development organizations to more accurately reflect the intent.

CSA Effective Date

The effective date for CSA International will be announced through CSA Informs or a CSA certification notice.

UL Effective Date

The effective date for UL 60745-1, Fourth edition is June 1, 2010.

As of June 1, 2010, all Listed or Recognized products must comply with the requirements in this standard.

Between July 31, 2007 and June 1, 2010, new product submittals to UL must be evaluated under all requirements in this Standard or, if requested in writing, evaluated under presently effective requirements only. The presently effective requirements are contained in the third edition of UL 60745-1.

A UL effective date is one established by Underwriters Laboratories Inc. and is not part of the ANSI approved standard.

General

The text, figures and tables of IEC 60745-1 are used in this standard with the consent of the International Electrotechnical Commission.

The IEC Foreword and Introduction are not a part of the requirements of this standard but are included for information purposes only.

Document Was Downloaded By Rice, Shi SHIMISHENG
For Use By KUANTECH CO LTD
12039 : 8/1/2007 - 10:50 PM
UL COPYRIGHTED MATERIAL –

NOT AUTHORIZED FOR FURTHER REPRODUCTION OR
DISTRIBUTION WITHOUT PERMISSION FROM



Documents

Document Sharing Hub

NATIONAL DIFFERENCES

There are five types of National Differences as noted below. The difference type is noted on the first line of the National Difference in the standard. The standard may not include all types of these National Differences.

In the CSA and UL publications of this standard, National Differences from the text of International Electrotechnical Commission (IEC) Publication 60745-2-3, Safety Requirements for Hand-Held Motor-Operated Electrical Tools – Safety – Part 2-3: Particular Requirements for Grinders, Polishers and Disk-Type Sanders, copyright 2006 are indicated by notations (differences) and are presented in bold text. The national difference type is included in the body.

DR – These are National Differences based on the **national regulatory requirements**.

D1 – These are National Differences which are based on **basic safety principles and requirements**, elimination of which would compromise safety for consumers and users of products.

D2 – These are National Differences based on **safety practices**. These are differences for IEC requirements that may be acceptable, but adopting the IEC requirements would require considerable retesting or redesign on the manufacturer's part.

DC – These are National Differences based on the **component standards** and will not be deleted until a particular component standard is harmonized with the IEC component standard.

DE – These are National Differences based on **editorial comments or corrections**.

Each national difference contains a description of what the national difference entails. Typically one of the following words is used to explain how the text of the national difference is to be applied to the base IEC text:

Addition / Add - An addition entails adding a complete new numbered clause, subclause, table or figure. Addition is not meant to include adding select words to the base IEC text.

Modification / Modify - A modification is an altering of the existing base IEC text such as the addition, replacement or deletion of certain words or the replacement of an entire clause, subclause, table, or figure of the base IEC text.

Deletion / Delete - A deletion entails complete deletion of an entire numbered clause, subclause, table or figure without any replacement text.

INTERNATIONAL ELECTROTECHNICAL COMMISSION

HAND-HELD MOTOR-OPERATED ELECTRIC TOOLS – SAFETY – Part 1: General requirements

FOREWORD

1) The IEC (International Electrotechnical Commission) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of the IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, the IEC publishes International Standards. Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. The IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.

2) The formal decisions or agreements of the IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested National Committees.

3) The documents produced have the form of recommendations for international use and are published in the form of standards, technical reports or guides and they are accepted by the National Committees in that sense.

4) In order to promote international unification, IEC National Committees undertake to apply IEC International Standards transparently to the maximum extent possible in their national and regional standards. Any divergence between the IEC Standard and the corresponding national or regional standard shall be clearly indicated in the latter.

5) The IEC provides no marking procedure to indicate its approval and cannot be rendered responsible for any equipment declared to be in conformity with one of its standards.

6) Attention is drawn to the possibility that some of the elements of this International Standard may be the subject of patent rights. The IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 60745-1 has been prepared by sub-committee 61F: Safety of hand-held motor-operated electric tools, of IEC technical committee 61: Safety of household and similar electrical appliances.

This consolidated version of IEC 60745-1 is based on the third edition (2001) [documents 61 F/422/FDIS and 61 F/427/RVD], its amendment 1 (2002) [documents 61 F/460/FDIS and 61 F/484/RVD], its amendment 2 (2003) [documents 61 F/534/FDIS and 61 F/540/RVD] and the corrigendum of January 2003.

It bears the edition number 3.2.

A vertical line in the margin shows where the base publication has been modified by amendments 1 and 2.

Annexes A, B, C, D, E, F, G, I, K, and L form an integral part of this standard.

UL COPYRIGHTED MATERIAL –

NOT AUTHORIZED FOR FURTHER REPRODUCTION OR
DISTRIBUTION WITHOUT PERMISSION FROM



Documents

Document Sharing Hub

Annex J is for information only.

NOTE In annexes B, K and L, subclauses which are additional to those in the main body of the text are numbered starting from 101.

The committee has decided that the contents of the base publication and its amendments 1 and 2 will remain unchanged until 2006. At this date, the publication will be

- reconfirmed
- withdrawn;
- replaced by a revised edition; or
- amended.

A bilingual version of this publication may be issued at a later date

Document Was Downloaded By Rice, Shi SHIMISHENG
For Use By KUANTECH CO LTD
12039 : 8/1/2007 - 10:50 PM
UL COPYRIGHTED MATERIAL –

NOT AUTHORIZED FOR FURTHER REPRODUCTION OR
DISTRIBUTION WITHOUT PERMISSION FROM



Documents

Document Sharing Hub

INTRODUCTION

This part 1 is to be used in conjunction with the appropriate part 2, which contains clauses to supplement or modify the corresponding clauses in part 1 to provide the relevant requirements for each type of product.

Individual countries may wish to consider its application, so far as is reasonable, to tools not mentioned in part 2, and to tools designed on new principles.

If the functions of a tool are covered by the different parts 2 of IEC 60745, the relevant part 2 is applied to each function separately, so far as is reasonable. If applicable, the influence of one function on the other is taken into account.

Normative references to other IEC and ISO standards are given in clause 2.

NOTE In this standard, the following print types are used:

- Requirements: in roman type
- Test specification: in italic type
- Notes: in smaller roman type

It has been assumed in the drafting of this International Standard that the execution of its provisions is entrusted to appropriately qualified and experienced people.

A product employing materials or having forms of construction differing from those detailed in the requirements of this standard may be examined and tested according to the intention of the requirements and, if found to be substantially equivalent, may be judged to comply with the standard.

Standards dealing with non-safety aspects of hand-held tools are:

- IEC standards published by TC 59 on methods of measuring performance;
- CISPR 11 and 14 on radio interference suppression;
- IEC 61000-3-2 and IEC 61000-3-3 on electromagnetic compatibility.

Document Was Downloaded By Rice, Shi SHIMISHENG
For Use By KUANTECH CO LTD
12039 : 8/1/2007 - 10:50 PM
UL COPYRIGHTED MATERIAL –

NOT AUTHORIZED FOR FURTHER REPRODUCTION OR
DISTRIBUTION WITHOUT PERMISSION FROM



Documents

Document Sharing Hub

HAND-HELD MOTOR-OPERATED ELECTRIC TOOLS – SAFETY –

Part 1: General requirements

1 Scope

This part of IEC 60745 deals with the safety of hand-held motor-operated or magnetically driven electric tools, the rated voltage of the tools being not more than 250 V for single-phase a.c. or d.c. tools, and 440 V for three-phase a.c. tools.

So far as is practicable, this standard deals with the common hazards presented by handheld tools which are encountered by all persons in the normal use and reasonably foreseeable misuse of the tools.

Tools with an electric heating element are within the scope of this standard. They should also comply with relevant parts of IEC 60335.

Requirements for motors not isolated from the supply, and having basic insulation not designed for the rated voltage of the tools, are given in Annex B. Requirements for rechargeable battery-powered motor-operated or magnetically driven tools and the battery packs for such tools are given in Annex K. Those for such tools that are also operated and/or charged directly from the mains or a non-isolated source are given in Annex L.

Hand-held electric tools, hereinafter referred to as tools, which can be mounted on a support or working stand for use as fixed tools without any alteration of the tool itself, are within the scope of this standard. Requirements for such supports or working stands are given in Annex M.

This standard does not apply to:

- hand-held tools intended to be used in the presence of explosive atmosphere (dust, vapour or gas);
- hand-held tools used for preparing and processing food;
- hand-held tools for medical purposes (IEC 60601);
- heating tools which are covered by IEC 60335-2-45.

For hand-held tools intended to be used in vehicles or on board ships or aircraft, additional requirements may be necessary.

For hand-held tools intended to be used in tropical countries, special requirements may be necessary.

NOTE Attention is drawn to the fact that in many countries, additional requirements are specified by the national health authorities, the national authorities responsible for the protection of labour, the national water supply authorities, etc.

1DV DR Addition: Add the following paragraph:

This standard deals with tools used in non-hazardous locations in accordance with the National Electrical Code, NFPA 70, and the Canadian Electric Code, Part 1, CSA C22.1, and General Requirements – Canadian Electrical Code, Part II, CAN/CSA-C22.2 No. 0.

UL COPYRIGHTED MATERIAL –

NOT AUTHORIZED FOR FURTHER REPRODUCTION OR
DISTRIBUTION WITHOUT PERMISSION FROM



Documents

Document Sharing Hub

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

2DV DC Modification: Add the following:

Where the IEC or ISO normative documents are referenced in this standard, U.S. and Canadian standards shall replace the IEC or ISO documents. The following is a matrix that provides a cross-reference between CSA, UL, IEC, and ISO standards for components. The standards listed in this table are not necessarily equivalent.

CSA, UL, IEC, and ISO Standards cross reference

Subclause from this standard	Component type	IEC or ISO publication	UL Standard	CSA Standard (C22.2)
Table 1, 21.36	Audio, Video and Similar Electronic Apparatus	IEC 60065 Audio, video and similar electronic apparatus – Safety requirements	UL 60065 Audio, Video and Similar Electronic Apparatus – Safety Requirements	CAN/CSA- C22.2 No. 60065 Audio, video and similar electronic apparatus – Safety requirements
23.1.5, 23.4, 24.21	Appliance Couplers	IEC 60320 (all parts) Appliance couplers for household and similar general purposes	UL 498 Attachment Plugs and Receptacles	CSA C22.2 No. 182.3 Special use attachment plugs, receptacles, and connectors
23.1.5, 23.4, 24.4, 24.21	Attachment Plugs, Receptacles, and Connectors	IEC 60309 (all parts) Plugs, socket-outlets and couplers for industrial purposes IEC 60320 (all parts) Appliance couplers for household and similar general purposes IEC 60884 (all parts) Plugs and socket-outlets for household and similar purposes	UL 498 Attachment Plugs and Receptacles UL 1682 Plugs, Receptacles, and Cable Connectors, of the Pin and Sleeve Type	CSA C22.2 No. 42 General use receptacles, attachment plugs, and similar wiring devices CSA C22.2 No. 182.1 Plugs, receptacles, and cable connectors of the pin and sleeve type CSA C22.2 No. 182.2 Industrial locking type, special use attachment plugs, receptacles, and connectors
26.4, 26.5	Coatings – Metallic and Oxide – Non-Magnetic Coatings	ISO 1463 Metallic and oxide coatings – Measurement of coating thickness – micro-scopical method ISO 2178 Non-magnetic coatings on magnetic substrates – Measurement of coating thickness – Magnetic method		

CSA, UL, IEC, and ISO Standards cross reference Continued

Subclause from this standard	Component type	IEC or ISO publication	UL Standard	CSA Standard (C22.2)
Annex G	Comparative Tracking Index	IEC 60112 Method for the determination of the proof and comparative tracking indices of solid insulating materials		
Table 1, 18.10.2, 23.1.2	EMI Filters	IEC 60384-14 Fixed capacitors for use in electronic equipment – Part 14: Sectional specification: Fixed capacitors for electromagnetic interference suppression and connection to the supply mains	UL 1283 Electromagnetic Interference Filters	CSA C22.2 No. 8 Electromagnetic interference (EMI) filters CSA E384-14 Fixed Capacitors for use in Electronic Equipment – Part 14: Sectional Specification: Fixed Capacitors for Electromagnetic Interference Suppression and Connection to the Supply Mains
Table 1, 18.10.2, 23.1.2	Capacitors, Double Protection	IEC 60384-14 Fixed capacitors for use in electronic equipment – Part 14: Sectional specification: Fixed capacitors for radio interference suppression and connection to the supply mains	UL 1414 Capacitors and Suppressors for Radio- and Television-Type Appliances	CSA C22.2, No. 1 Audio, video and similar electronic equipment
20.2	Environmental Testing – Hammer Tests	IEC 60068-2-75 Environmental testing – Part 2-75: Tests – Test Eh: Hammer tests		
23.1.3	Flexible Cords and Cables	IEC 60227 (all parts) Polyvinyl chloride insulated cables of rated voltages up to and including 450/750 V IEC 60245 (all parts) Rubber insulated cables – rated voltages up to and including 450/750 V	UL 62 Flexible Cord and Cables	CSA C22.2 No. 49 Flexible cords and cables

CSA, UL, IEC, and ISO Standards cross reference Continued

Subclause from this standard	Component type	IEC or ISO publication	UL Standard	CSA Standard (C22.2)
8.6, 18.10, 18.10.3	Fuses, Low-Voltage	IEC 60127-3 Miniature fuses – Part 3: Sub-miniature fuse-links	UL 248 Sereis UL 248-1 Low-Voltage Fuses – Part 1: General Requirements UL 248-4 Low-Voltage Fuses – Part 4: Class CC Fuses UL 248-8 Low-Voltage Fuses – Part 8: Class J Fuses UL 248-10 Low-Voltage Fuses – Part 10: Class L Fuses UL 248-12 Low-Voltage Fuses – Part 12: Class R Fuses UL 248-15 Low-Voltage Fuses – Part 15: Class T Fuses	CSA C22.2 No. 248 Series CSA C22.2 No. 248.1 Low-Voltage Fuses – Part 1: General Requirements CSA C22.2 No. 248.4 Low-Voltage Fuses – Part 4: Class CC Fuses CSA C22.2 No. 248.8 Low-Voltage Fuses – Part 8: Class J Fuses CSA C22.2 No. 248.10 Low-Voltage Fuses – Part 10: Class L Fuses CSA C22.2 No. 248.12 Low-Voltage Fuses – Part 12: Class R Fuses CSA C22.2 No. 248.15 Low-Voltage Fuses – Part 15: Class T Fuses
12.2, 15.2	Heater Elements	IEC 60335-1 Household and similar electrical appliances – Part 1: General requirements	UL 1030 Sheathed Heating Elements UL 60335-1 Safety of Household and Similar Electrical Appliances – Part 1: General Requirements	CSA C22.2 No. 72 Heater Elements CAN/CSA-E60335-1/4E Safety of Household and Similar Electrical Appliances – Safety – Part 1: General requirements
7.2, 14.1.2, 21.20	Degrees of Protection	IEC 60529 Degrees of protection provided by enclosures (IP Code)		
29.2, Annex J	Glow Wire Test	IEC 60695-2-11 Fire hazard testing – Part 2-11: Glowing/hot-wire based test methods – Glow-wire flammability test method for end-products		
14.6	Portable Residual Current Devices (PRCDs) Ground-Fault Circuit Interruptors (GFCI)	IEC 61540 Electrical accessories – Portable residual current devices without integral overcurrent protection for household and similar use (PRCDs)	UL 943 Ground-Fault Circuit-Interrupters	CSA C22.2 No. 144.1 Ground-fault circuit-interrupters

CSA, UL, IEC, and ISO Standards cross reference Continued

Subclause from this standard	Component type	IEC or ISO publication	UL Standard	CSA Standard (C22.2)
23.1.3	Lampholders	IEC 60238 Edison screw lampholders IEC 60061-1 Lamp caps and holders together with gauges for the control of interchangeability and Safety – Part 1: Lamp Caps	UL 496 Lampholders	CSA C22.2 No. 43 Lampholders
Annex F	Plastics – Flammability	IEC 60695-11-5 Fire hazard testing – Part 11-5: Test flames – Needle flame test method – Apparatus, confirmatory test arrangement and guidance	UL 1694 Tests for Flammability of Small Polymeric Component Materials	CAN/CSA-C22.2 No. 0.17 Evaluation of properties of polymeric materials
29.2	Plastics – Flammability	IEC 60695-11-10 Fire hazard testing Part 11-10: Test flames – 50 W Horizontal and vertical flame test methods		
16, 23.1.4, K.2, K.3.203, L.2, L.3.203	Power Supplies	IEC 61558-1 Safety of power transformers, power supplies, reactors and similar products – Part 1: General requirements and tests IEC 61558-2-6 Safety of power transformers, power supply units and similar – Part 2: particular requirements for safety isolating transformers for general use	UL 1012 Power Units Other Than Class 2 UL 1310 Class 2 Power Units	CSA C22.2 No. 107.1 General use power supplies CAN/CSA-C22.2 No. 107.2 Battery chargers CAN/CSA-C22.2 No. 223 Power supplies with extra-low-voltage class 2 outputs
23.1.10, 23.1.11, I, Clause 8 in Annex I, M.23.1.11	Switches for Appliances	IEC 61058-1 Switches for appliances – Part 1: General requirements	UL 61058-1 Switches for Appliances – Part 1: General Requirements	CAN/CSA-C22.2 No. 61058-1 Switches for appliances – Part 1: General requirements
8.10	Symbols	IEC 60417 DB Graphical symbols for use on equipment – Part 1: overview and application		
Table 1, 12.6	Systems of Insulating Material	IEC 60085 Electrical insulation – Thermal classification	UL 1446 Systems of Insulating Materials – General	CAN/CSA-C22.2 No. 0 General Requirements – Canadian Electrical Code, Part II
26.2	Terminals, Quick Connect	IEC 60760 Flat, quick-connect terminations	UL 310 Electrical Quick-Connect Terminals	CSA C22.2-No. 153 Quick-connect terminals

UL COPYRIGHTED MATERIAL –

NOT AUTHORIZED FOR FURTHER REPRODUCTION OR
DISTRIBUTION WITHOUT PERMISSION FROM THE

CSA, UL, IEC, and ISO Standards cross reference Continued on Next Page

Documents

Document Sharing Hub

CSA, UL, IEC, and ISO Standards cross reference Continued

Subclause from this standard	Component type	IEC or ISO publication	UL Standard	CSA Standard (C22.2)
31.2	Lasers Requirements for Equipment Incorporating Lasers Requirements for Lasers Contained in the Applicable National Codes and Regulations	IEC 60825-1 Safety of laser products – Part 1: Equipment classification, requirements and user's guide	See Note.	CAN/CSA-E60825-1 Safety of laser products – Part 1: Equipment classification, requirements and user's guide
25.1, 25.3, 26.2	Wire Connectors and Soldering Lugs	IEC 60998-2-1 Connecting devices for low-voltage circuits for household and similar purposes – Part 2-1: Particular requirements for connecting devices as separate entities with screw-type clamping units IEC 60998-2-2 Connecting devices for low-voltage circuits for household and similar purposes – Part 2-2: Particular requirements for connecting devices as separate entities with screwless-type clamping units IEC 60999-1 Connecting devices – Electrical copper Conductors – Safety requirements for screw-type and screwless-type clamping units – Part 1: General requirements and particular requirements for clamping units for conductors from 0,2 mm ² up to 35 mm ² (included)	UL 486A-486B Wire Connectors	CSA C22.2 No. 65 Wire connectors

CSA, UL, IEC, and ISO Standards cross reference Continued

Subclause from this standard	Component type	IEC or ISO publication	UL Standard	CSA Standard (C22.2)
22.3, 23.1.3	Wires and Cables	IEC 60227 (all parts) Polyvinyl chloride insulated cables of rated voltages up to and including 450/750 V IEC 60245 (all parts) Rubber insulated cables – rated voltages up to and including 450/750 V	UL 44 Thermoset-Insulated Wires and Cables UL 83 Thermoplastic-Insulated Wires and Cables UL 758 Appliance Wiring Material	CSA C22.2 No. 38 Thermoset insulated wires and cables CSA C22.2 No. 75 Thermoplastic-insulated wires and cables CSA-C22.2 No. 210 Appliance wiring material products
8.13DV	Marking and Labeling Systems		UL 969 Marking and Labeling Systems	CSA C22.2 No. 0.15 Adhesive labels
23.1.6	Temperature-Indicating and -Regulating Equipment	IEC 60730-1 Automatic electrical controls for household and similar Use – Part 1: General requirements	UL 60730-1A Automatic Electrical Controls for Household and Similar Use, Part 1: General Requirements	CSA C22.2 No. 24 Temperature-indicating and -regulating equipment
8.13DV	Tests for Rubber Property – Effect of Liquids		ANSI/ASTM D 471 Tests for Rubber Property – Effect of Liquids	
8.13	Graphical Symbols – Design Principles	ISO 3864-2 Graphical symbols – safety colours and safety signs – Part 2: Design principles for product safety labels		
8.1	Graphical Symbols – Safety Signs	ISO 7010 Graphical symbols – safety colours and safety signs – safety signs used in workplaces and public areas		
29.2	Plastics – Flammability	ISO 9772 Cellular plastics – Determination of horizontal burning characteristics of small specimens subjected to a small flame	UL 94 Tests for Flammability of Plastic Materials for Parts in Devices and Appliances	CAN/CSA C22.2 No. 0.17 Evaluation of properties of polymeric materials
Note: Additional regulatory requirements apply to equipment incorporating lasers, which are contained in the applicable national codes and regulations; for example, in Canada, the Radiation Emitting Devices Regulations, (C.R.C., c. 1370) and in the US, the Code of Federal Regulations (CFR), Title 21, Part 1040.				

IEC 60061-1DB¹:2005

Lamp caps and holders together with gauges for the control of interchangeability and safety

UL COPYRIGHTED MATERIAL –

NOT AUTHORIZED FOR FURTHER REPRODUCTION OR
DISTRIBUTION WITHOUT PERMISSION FROM

Documents

Document Sharing Hub

IEC 60065:2001

Audio, video and similar electronic apparatus – Safety requirements

IEC 60068-2-75:1997

Environmental testing – Part 2: Tests – Test Eh: Hammer tests

IEC 60085

Electrical insulation – Thermal classification

IEC 60112:2003

Method for the determination of the proof and the comparative tracking indices of solid insulating materials

IEC 60127-3

Miniature fuses

IEC 60227 (all parts)

Polyvinyl chloride insulated cables of rated voltages up to and including 450/750 V

IEC 60245 (all parts)

Rubber insulated cables – Rated voltages up to and including 450/750 V

IEC 60309 (all parts)

Plugs, socket-outlets and couplers for industrial purposes

IEC 60320 (all parts)

Appliance couplers for household and similar general purposes

IEC 60335-1:2001

Safety of household and similar electrical appliances – Part 1: General requirements Amendment 1 (2004)²

IEC 60384-14

Fixed capacitors for use in electronic equipment – Part 14: Sectional specification: Fixed capacitors for electromagnetic interference suppression and connection to the supply mains

IEC 60417-DB³:2002

Graphical symbols for use on equipment

IEC 60529:1989

Degrees of protection provided by enclosures (IP Code) Amendment 1 (1999)⁴

IEC 60695-2-11

Fire hazard testing – Part 2-11: Glowing/hot-wire based test methods – Glow-wire flammability test method for end-products

IEC 60695-11-5:2004

Fire hazard testing – Part 11-5: Test flames – Needle-flame test method – Apparatus, confirmatory test arrangement and guidance

IEC 60695-11-10

Fire hazard testing – Part 11-10: Test flames – 50 W horizontal and vertical flame test methods

UL COPYRIGHTED MATERIAL –

NOT AUTHORIZED FOR FURTHER REPRODUCTION OR
DISTRIBUTION WITHOUT PERMISSION FROM



Documents

Document Sharing Hub

IEC 60730-1:1999

Automatic electrical controls for household and similar use – Part 1: General requirements Amendment 1 (2003)⁵

IEC 60760

Flat, quick connect terminations

IEC 60825-1

Safety of Laser Products – Part 1: Equipment classification, requirements and user's guide

IEC 60884 (all parts)

Plugs and socket-outlets for household and similar purposes

IEC 60998-2-1

Connecting devices for low-voltage circuits for household and similar purposes – Part 2-1: Particular requirements for connecting devices as separate entities with screw-type clamping units

IEC 60998-2-2

Connecting devices for low-voltage circuits for household and similar purposes – Part 2-2: Particular requirements for connecting devices as separate entities with screwless-type clamping units

IEC 60999-1:1999

Connecting devices – Electrical copper conductors – Safety requirements for screw-type and screwless-type clamping units – Part 1: General requirements and particular requirements for clamping units for conductors from 0,2 mm² up to 35 mm² (included)

IEC 61058-1:2000

Switches for appliances – Part 1: General requirements Amendment 1 (2001)⁶

IEC 61540:1997

Electrical accessories – Portable residual current devices without integral overcurrent protection for household and similar use (PRCDs) Amendment 1 (1998)⁷

IEC 61558-1

Safety of power transformers, power supplies, reactors and similar products – Part 1: General requirements and tests

ISO 1463

Metallic and oxide coatings – Measurement of coating thickness – Microscopical method

ISO 2178

Non-magnetic coatings on magnetic substrates – Measurement of coating thickness – Magnetic method

ISO 3864-2

Graphical symbols – Safety colours and safety signs – Part 2: Design principles for product safety labels

ISO 7010

Graphical symbols – Safety colours and safety signs – Safety signs used in workplaces and public areas

ISO 9772

Cellular plastics – Determination of horizontal burning characteristics of small specimens subjected to a small flame

UL COPYRIGHTED MATERIAL –

NOT AUTHORIZED FOR FURTHER REPRODUCTION OR
DISTRIBUTION WITHOUT PERMISSION FROM



Documents

Document Sharing Hub

¹ 'DB' refers to the on-line IEC database.

² A consolidated edition (4.1) exists including IEC 60335-1:2001 and its Amendment 1 (2001).

³ 'DB' refers to the on-line IEC database.

⁴ A consolidated edition (2.1) exists including IEC 60529:1989 and its Amendment 1 (1999).

⁵ A consolidated edition (3.1) exists including IEC 60730-1:1999 and its Amendment 1 (2003).

⁶ A consolidated edition (3.1) exists including IEC 61058-1:2000 and its Amendment 1 (2001).

⁷ A consolidated edition (1.1) exists including IEC 61540:1997 and its Amendment 1 (1998).

3 Terms and Definitions

For the purposes of this document, the following terms and definitions apply.

Where the terms voltage and current are used, they imply the r.m.s. values, unless otherwise specified.

Where in this standard the expressions "with the aid of a tool", "without the aid of a tool", and "requires the use of a tool", are used, the word "tool" means a hand tool, for example a screwdriver, which may be used to operate a screw or other fixing means.

3.1 accessible part: part which can be touched by means of the standard test finger in Figure 1, including, for accessible metal parts, any metal part connected to it

3.2 accessory: device that is attached only to the output mechanism of the tool

3.3 all-pole disconnection: disconnection of all supply conductors except the protective earthing (grounding) conductor by a single initiating action

3.4 attachment: device attached to the housing or other component of the tool and which may or may not be attached to the output mechanism and does not modify the normal use of the tool within the scope of this standard

3.5 basic insulation: insulation, not necessarily including insulation used for functional purposes, applied to live parts to provide basic protection against electric shock

3.6 class I tool: tool in which protection against electric shock does not rely on basic, double or reinforced insulation only, but which includes an additional safety precaution in that conductive accessible parts are connected to the protective earthing conductor in the fixed wiring of the installation in such a way that conductive accessible parts cannot become live in the event of a failure of the basic insulation. Also considered as class I tools are tools with double insulation and/or reinforced insulation throughout having an earthing terminal or earthing contact

3.7 class II tool: tool in which protection against electric shock does not rely on basic insulation only, but in which additional safety precautions, such as double insulation or reinforced insulation, are provided, there being no provision for protective earthing or reliance upon installation conditions

3.8 class III tool: tool in which protection against electric shock relies on supply at safety extra-low voltage, and in which voltages higher than those of safety extra-low voltages are not generated

3.9 **class II construction:** part of a tool for which protection against electric shock relies upon double insulation or reinforced insulation

3.10 **class III construction:** part of a tool for which protection against electric shock relies upon safety extra-low voltage, and in which voltages higher than those of safety extra-low voltages are not generated

3.11 **clearance:** shortest distance between two conductive parts, or between a conductive part and the outer surface of the enclosure, considered as though metal foil were pressed into contact with accessible surfaces of insulating material, measured through air

NOTE Examples of clearance distances are given in Annex A.

3.12 **creepage distance:** shortest path between two conductive parts, or between a conductive part and the outer surface of the enclosure, considered as though metal foil were pressed into contact with accessible surfaces of insulating material, measured along the surface of the insulating material

NOTE Examples of creepage distances are given in Annex A.

3.13 **detachable cord:** flexible cord, for supply, intended to be connected to the tool by means of a suitable appliance coupler

3.14 **detachable part:** part which can be removed or opened without the aid of a tool, or a part which is removed in accordance with the instruction for use, except user maintenance items, even if removal requires the use of a tool

3.15 **double insulation:** insulation system comprising both basic insulation and supplementary insulation

3.16 **electronic circuit:** circuit incorporating at least one electronic component

3.17 **electronic component:** part in which conduction is achieved principally by electrons moving through a vacuum, gas or semiconductor, with the exclusion of neon indicators

3.18 **exchange type tool:** tool which is intended not to be repaired at all, or to be repaired by the manufacturer's service organization only

3.19 **extra-low voltage:** voltage supplied from a source within the tool and, which, when the tool is supplied at rated voltage, does not exceed 50 V between conductors and between conductors and earth

3.20 **extra-severe duty conditions of insulating material:** where there is heavy deposition of conductive material and a long period of electrical stress; or an extra heavy deposition of conductive material and a short period of electrical stress

3.21 **hand-held tool (in this standard abbreviated to "tool"):** electric motor-operated or magnetically-driven machine intended to do mechanical work, with or without provisions for mounting on a support, and so designed that the motor and the machine form an assembly which can easily be brought to the place of operation, and which is either held or supported by hand or suspended during operation

NOTE Hand-held tools may be provided with a flexible shaft, the motor being either fixed or portable.

3.22 intermittent operation: operation in a series of specified identical cycles, each cycle being composed of a period of operation under normal load followed by a rest period with the tool running idle or switched off

3.23 liquid system: system that employs water or a water-based liquid from an external or integral supply that is necessary to complete the intended function of the tool

3.24 live part: any conductor or conductive part intended to be energized in normal use, including a neutral conductor but, by convention, not a PEN conductor

3.25 no-load input/current: highest input or current obtained when a tool is operated at rated voltage and frequency with no external load (work) applied to the accessories packaged with the tool by the manufacturer and adjusted according to manufacturer's instructions, ready for use

3.26 non-detachable part: part which can only be removed or opened with the aid of a tool, or a part which fulfils the test of 21.22

3.27 non-self-resetting thermal cut-out: thermal cut-out which requires a manual operation for resetting, or replacement of a part, in order to restore the current

3.28 normal duty conditions of insulating material: where there is virtually no deposition of conductive material and a long period of electrical stress; or a light deposition of conductive material and a short period of electrical stress

3.29 normal load: load to be applied to a tool at rated voltage or at the upper limit of the rated voltage range, to obtain rated input or rated current, any marking of short-time or intermittent operation being observed and, unless otherwise specified, heating elements, if any, being operated as in normal use

3.30 normal use: use of a tool for which it is designed, taking into account the manufacturer's instructions

3.31 protective device: device the operation of which prevents a hazardous situation under abnormal operation conditions

3.32 protective impedance: impedance connected between live parts and accessible conductive parts, and of value so that the current is limited to a safe value

3.33 rated current: current assigned to the tool by the manufacturer. If no current rating is assigned to the tool, the rated current for the purpose of this standard is the current measured when the tool is operated under normal load

3.34 rated frequency: frequency assigned to the tool by the manufacturer

3.35 rated frequency range: frequency range assigned to the tool by the manufacturer, expressed by its lower and upper limits

3.36 rated input: input in watts assigned to the tool by the manufacturer. If no input is assigned to the tool, the rated input for the purpose of this standard is the input measured when the tool is operated under normal load

3.37 rated input range: input range in watts assigned to the tool by the manufacturer, expressed by its lower and upper limits

3.38 **rated no-load speed:** no-load speed at rated voltage or at the upper limit of the rated voltage range assigned to the tool by the manufacturer

3.39 **rated operating time:** operating time assigned to the tool by the manufacturer

3.40 **rated voltage:** voltage assigned to the tool by the manufacturer. For three-phase supply, it is the voltage between phases

3.41 **rated voltage range:** voltage range assigned to the tools by the manufacturer, expressed by its lower and upper limits

3.42 **reinforced insulation:** insulation of hazardous live parts which provides a degree of protection against electric shock equivalent to double insulation

NOTE Examples of reinforced insulation are a single layer or several layers which cannot be tested singly as basic insulation or supplementary insulation.

3.43 **residual current device (RCD):** device intended to detect a diversion of current from a circuit in a way that may expose the user to an electric shock; in such conditions the device opens the circuit

NOTE Such a device is also known as portable residual current device (PRCD), ground fault circuit interrupter (GFCI) or earth leakage circuit breaker (ELCB)

3.44 **routine servicing:** periodic servicing which requires tool disassembly as instructed by the instruction manual and performed by authorized service centre

3.45 **safety extra-low voltage:** rated voltage not exceeding 42 V between conductors and between conductors and earth, the no-load voltage not exceeding 50 V. When safety extra-low voltage is obtained from the supply mains, it is to be through a safety isolating transformer or a convertor with separate windings, the insulation of which complies with double or reinforced insulation requirements

3.46 **safety isolating transformer:** transformer, the input winding of which is electrically separated from the output winding by an insulation at least equivalent to double insulation or reinforced insulation, and which is intended to supply a distribution circuit, a tool or other equipment at safety extra-low voltage

3.47 **self-resetting thermal cut-out:** thermal cut-out which automatically restores the current after the relevant part of the tool has cooled down to a given value

3.48 **severe duty conditions of insulating material:** where there is a light deposition of conductive material and a long period of electrical stress; or a heavy deposition of conductive material and a short period of electrical stress

3.49 **short-time operation:** operation under normal load for a specified period, starting from cold, the intervals between each period of operation being sufficient to allow the tool to cool down approximately to ambient temperature

3.50 **supplementary insulation:** independent insulation applied in addition to the basic insulation, in order to provide protection against electric shock in the event of a failure of the basic insulation

3.51 **supply cord:** flexible cord, for supply purposes, which is fixed to the tool

3.52 temperature limiter: temperature-sensing device, the operating temperature of which may be either fixed or adjustable, and which, during normal operation, operates by opening or closing a circuit when the temperature of the controlled part reaches a predetermined value. It does not make the reverse operation during the normal duty cycle of the tool

3.53 thermal cut-out: device which, during abnormal operation, limits the temperature of the controlled part by automatically opening the circuit, or by reducing the current, and which is so constructed that its setting cannot be altered by the user

3.54 thermal link: thermal cut-out which operates only once, and then requires partial or complete replacement

3.55 thermostat: temperature-sensing device, the operating temperature of which may be either fixed or adjustable; and which, during normal operation, keeps the temperature of the controlled part between certain limits by automatically opening and closing a circuit

3.56 type X attachment: method of attachment of the supply cord so that it can easily be replaced

3.57 type Y attachment: method of attachment of the supply cord such that any replacement is intended to be made by the manufacturer, its service agent or similar qualified person

3.57DV D2 Modification: *Add the following to the end of the definition:*

as recommended in the instruction manual

3.58 type Z attachment: method of attachment of the supply cord so that it cannot be replaced without breaking or destroying the tool

3.59 user maintenance: any maintenance operation stated in the instructions for use or marked on the tool which the manufacturer of the tool intends the user to perform

3.60 working voltage: maximum voltage, without the effect of transient voltages, to which the part under consideration is subjected when the tool is supplied at its rated voltage and operating under normal load

4 General requirements

Tools shall be so constructed that in normal use they function safely so as to cause no danger to persons or surroundings, even in the event of reasonably foreseeable misuse.

In general, this principle is achieved by fulfilling the relevant requirements specified in this standard, and compliance is checked by carrying out all the relevant tests.

NOTE Annex N shows an example of routine tests.

5 General conditions for the tests

5.1 Tests according to this standard are type tests.

5.2 Unless otherwise specified, the tests are made on a single tool, which shall withstand all the relevant tests. However, any test that requires tool modifications or disassembly after the test may be performed on a separate sample.

Additional samples may be required, for example, if the tool is designed for different supply voltages. The testing of components may necessitate the submission of additional samples of these components.

The cumulative stress resulting from successive tests on electronic circuits is to be avoided. It may be necessary to replace components or to use additional samples. The number of additional samples should be kept to a minimum by an evaluation of the relevant electronic circuits.

5.3 Unless otherwise specified, the tests are carried out in the order of the clauses. If it is evident from the construction of the tool that a particular test is not applicable, the test is not made.

5.4 The tests are carried out with the tool, or any movable part of it, placed in the most unfavourable position that may occur in normal use.

5.5 Tools provided with controls or switching devices are tested with these controls or devices adjusted to their most unfavourable settings, if the setting can be altered by the user. Electronic speed control devices are set for the highest speed.

If the adjusting means of the control is accessible without the aid of a tool, this subclause applies whether the setting can be altered by hand or with the aid of a tool. If the adjusting means is not accessible without the aid of a tool, and if the setting is not intended to be altered by the user, this subclause does not apply.

Adequate sealing is regarded as preventing alteration of the setting by the user.

5.6 The tests are made in a draught-free location and, in general, at an ambient temperature of (20 ± 5) °C.

If the temperature attained by any part is limited by a temperature sensitive device, or is influenced by the temperature, the room temperature is, in case of doubt, maintained at (23 ± 2) °C.

5.7.1 Tools for a.c. only are tested with a.c. at rated frequency, if marked, and those for a.c./d.c. are tested at the more unfavourable supply.

Tools for a.c. which are not marked with rated frequency, or marked with a frequency range of 50 Hz to 60 Hz, are tested with either 50 Hz or 60 Hz, whichever is the more unfavourable.

5.7.2 Tools having more than one rated voltage are tested on the basis of the most unfavourable voltage.

When it is specified for tools marked with a rated voltage range that the supply voltage is equal to the rated voltage multiplied by a factor, the supply voltage is equal to:

- the upper limit of the rated voltage range multiplied by this factor, if greater than 1
- the lower limit of the rated voltage range multiplied by this factor, if smaller than 1.

When a factor is not specified, the supply voltage is the most unfavourable within the rated voltage range.

For tools having more than one rated voltage or rated voltage range, it may be necessary to make some of the tests at the minimum, the mean, and the maximum values of the rated voltage, or the rated voltage range, in order to establish the most unfavourable voltage.

5.7.3 For tools marked with a rated voltage range and rated input corresponding to the mean of the rated voltage range, when it is specified that the power input is equal to rated input multiplied by a factor, the input is equal to:

- the calculated input corresponding to the upper limit of the rated voltage range multiplied by this factor, if greater than 1:
- the calculated input corresponding to the lower limit of the rated voltage range multiplied by this factor, if smaller than 1.

When a factor is not specified, the input corresponds to the input at the most unfavourable rated voltage within the range.

5.8 When alternative attachments are made available for the tool by its manufacturer, the tool is tested with those attachments which give the most unfavourable results.

5.9 Unless otherwise specified, tools are tested with the appropriate flexible cord connected to the tool.

5.10 If class I tools have accessible metal parts which are not connected to an earthing terminal or earthing contact, and are not separated from live parts by an intermediate metal part which is connected to an earthing terminal or earthing contact, such parts are checked for compliance with the appropriate requirements specified for class II construction.

If class I tools have accessible non-metallic parts, such parts are checked for compliance with the appropriate requirements specified for class II construction, unless these parts are separated from live parts by an intermediate metal part connected to an earthing terminal or earthing contact.

5.11 If class I or class II tools have parts operating at safety extra-low voltage, such parts are checked for compliance with the appropriate requirements specified for class III tools.

5.12 When testing electronic circuits, the supply is to be free from those perturbations from external sources that can influence the results of the tests.

5.13 If, in normal use, the heating element cannot be operated unless the motor is running, the element is tested with the motor running. If the heating element can be operated without the motor running, the element is tested with or without the motor running, whichever is the more unfavourable. Heating elements incorporated in the tool are connected to a separate supply unless otherwise specified.

5.14 For attachments performing a function which is within the scope of one of the relevant parts 2, the tests are made in accordance with that part 2.

For other attachments, the tests are made in accordance with manufacturer's instructions; in the absence of such instructions, the tool is operated continuously at a load at which rated input or rated current is attained.

5.15 If a torque is to be applied, the method of loading is chosen so as to avoid additional stresses, such as those caused by side thrust. Additional loads necessary for the correct operation of the tool are, however, taken into consideration.

If a brake is used for applying a load, it must be applied gradually to assure that the starting current does not affect the test. Modification of output means for purpose of loading is permitted for the connection to a brake.

5.16 Tools intended to be operated at safety extra-low voltage are tested together with their supply transformer, if this is normally sold with the tool.

6 Void

7 Classification

7.1 Tools shall be of one of the following classes with respect to protection against electric shock:

class I, class II, class III.

Compliance is checked by inspection and by the relevant tests.

7.2 Tools shall have the appropriate degree of protection against harmful ingress of water according to IEC 60529. If a degree other than IPX0 is required this shall be specified in the part 2.

Compliance is checked by inspection and by the relevant tests.

8 Marking and instructions

8.1 Tools shall be marked with:

- rated voltage(s) or rated voltage range(s), in volts. Tools for star-delta connection shall be clearly marked with the two rated voltages (for example 230 Δ / 400 Y);
- symbol for nature of supply, unless the rated frequency is marked. The symbol for nature of supply shall be placed next to the marking for rated voltage;
- rated input, in watts or rated current, in amperes. The rated input or current to be marked on the tool is the total maximum input or current that can be on circuit at the same time. If a tool has alternative components which can be selected by a control device, the rated input or rated current is that corresponding to the highest loading possible;
- name or trade mark or identification mark and address of the manufacturer or any other agent responsible for placing the tool on the market;
- model or type reference;
- symbol for class II construction, for class II tools only;
- IP number according to degree of protection against ingress of water other than IPX0. If the first numeral for the IP numbering is omitted, the omitted numeral shall be replaced by the letter X, for example IPX5;
- “WARNING – To reduce the risk of injury, user must read instruction manual” or the sign M002 of ISO 7010⁸.

If used, the word “WARNING” shall be in capital letters not less than 2,4 mm high and shall not be separated from the cautionary statement.

UL COPYRIGHTED MATERIAL –

NOT AUTHORIZED FOR FURTHER REPRODUCTION OR
DISTRIBUTION WITHOUT PERMISSION FROM



Documents

Document Sharing Hub

If used, the statement shall be verbatim except the term “operator’s manual” or “user guide” may be used for the term “instruction manual”.

Additional markings are allowed, provided they do not give rise to misunderstanding.

Compliance is checked by inspection.

⁸ The future safety sign M002 is currently in DIS stage as ISO 7010:2003/DAmD4.

8.1DV D1 Modification: Add the following:

– date of manufacture.

The date of manufacture may be a dating period not exceeding any one month. The date of manufacture may be abbreviated or in an established, accepted code or a code affirmed by the manufacturer.

8.1DV.1 D1 Addition: Add the following clause:

If a nameplate carries a required marking and is on a part that must be removed for normal servicing of the tool, the construction shall be such that the nameplate shall be returned to its proper location for the tool to be operable.

A cautionary marking shall be permanent and shall be located on a part permanently attached to the tool or on a part that cannot be removed without impairing the operation or the appearance of the tool.

A fold-over label attached to the power supply cord is acceptable.

Cautionary markings shall be used verbatim as stated. Optional cautionary statements may be added to the markings, as deemed necessary, by the manufacturer. Cautionary statements having the same signal word may be combined into one paragraph under one signal word. The order of statements shall be markings required by Part 1, markings required by the applicable Part 2, and any optional markings.

In cases where the words “danger”, “warning”, and “caution” appear together, the cautionary markings shall be in the order of severity, i.e., “danger, warning, and caution”.

8.2 Tools for short-time operation or intermittent operation shall be marked with rated operating time, or rated operating time and rated resting time respectively, unless the operating time is limited by the construction of the tool.

The marking of short-time operation or intermittent operation shall correspond to normal use.

The marking of intermittent operation shall be such that the rated operating time precedes the rated resting time, both markings being separated by an oblique stroke.

Compliance is checked by inspection.

8.3 The marking of tools intended to be operated without adjustment in a rated range of values (voltage, frequency, etc.) shall be differentiated from those intended to be operated with or without adjustment under different values of the same criteria (voltage, frequency, etc.).

The lower and upper limits of the rated range of values shall be separated by a hyphen (-).

The different rated values shall be separated by an oblique stroke (/).

Examples:

115-230 V: The tool is suitable for any value within the marked range.

115/230 V: The tool is only suitable for the marked values.

Compliance is checked by inspection.

8.4 If the tool can be adjusted to suit different rated voltages, the voltage to which the tool is adjusted shall be clearly discernible.

This requirement does not apply to tools for star-delta connection.

For tools where frequent changes in voltage setting are not required, this requirement is considered to be met if the rated voltage to which the tool is adjusted can be determined from a wiring diagram fixed to the tool. The wiring diagram may be on the inside of a cover which has to be removed to connect the supply conductors. It is not to be on a label loosely attached to the tool.


Compliance is checked by inspection.

8.5 For tools marked with more than one rated voltage or with more than one rated voltage range, the rated power input for each of these voltages or ranges shall be marked.

The upper and lower limits of the rated power input shall be marked on the tool so that the relation between input and voltage appears distinctly, unless the difference between the limits of a rated voltage range does not exceed 10% of the mean value of the range, in which case the marking for rated power input may be related to the mean value of the range.

Compliance is checked by inspection.

8.6 If units or technical data are expressed by symbols, the following symbols shall be used:

V	volts
A	amperes
Hz	hertz
W	watts
kW	kilowatts
F	farads
μF	microfarads
l	litres
g	grams
kg	kilograms
bar	bars
Pa	pascals
h	hours
min	minutes
s	seconds
n ₀	no-load speed
.../min or ...min ⁻¹	Revolutions or reciprocations per minute
 or d.c.	direct current
 or a.c.	alternating current
2 	two-phase alternating current
2N 	two-phase alternating current with neutral
3 	three-phase alternating current
3N 	three-phase alternating current with neutral
 A	rated current of the appropriate fuse-link in amperes
 X	time-log miniature fuse-link where X is the symbol for the time/current characteristic, as given in IEC 60127-3
	protective earth
	class II tool
IPXX	IP symbol

S4598b

UL COPYRIGHTED MATERIAL –

NOT AUTHORIZED FOR FURTHER REPRODUCTION OR
DISTRIBUTION WITHOUT PERMISSION FROM

Documents

Document Sharing Hub

The dimensions for the symbol for class II tools shall be such that the length of the sides of the outer square is about twice the length of the sides of the inner square. The length of the sides of the outer square shall not be less than 5 mm, unless the largest dimension of the tool does not exceed 15 cm, in which case the dimensions of the symbol may be reduced, but the length of the sides of the outer square shall not be less than 3 mm.

The symbol for class II tools shall be so placed that it will be obvious that it is a part of the technical information, and is unlikely to be confused with any other marking.

When other units are used, the units and their symbols shall be those of the international standardized system.

Additional symbols other than international symbols are allowed, provided they do not give rise to misunderstanding.

Compliance is checked by inspection and measurement.

8.7 Tools to be connected to more than two supply conductors shall be provided with a connection diagram, fixed to the tool, unless the correct mode of connection is obvious.

The correct mode of connection is deemed to be obvious if the terminals for the supply conductors are indicated by arrows pointing towards the terminals. The earthing conductor is not a supply conductor. For tools for star-delta connection, the wiring diagram should show how the windings are to be connected.

Compliance is checked by inspection.

8.8 Except for type Z attachments, terminals shall be indicated as follows:

- Terminals intended exclusively for the neutral conductor shall be indicated by the letter N.
- Earthing terminals shall be indicated by the symbol ⚡.

These indications shall not be placed on screws, removable washers or other parts which might be removed when conductors are being connected.

Compliance is checked by inspection.

8.9 Unless it is obviously unnecessary, switches which may give rise to a hazard when operated shall be marked, or so placed as to indicate clearly which part of the tool they control.

Indications used for this purpose shall, wherever practicable, be comprehensible without a knowledge of languages, national standards, etc.

Compliance is checked by inspection.

8.10 For tools which might cause danger when started unexpectedly, the "off" position of the mains switch shall be indicated, unless this position is obvious; the indication, if required, shall be the figure O, as given by symbol IEC 60417-5008 (DB:2002-10).

The figure O shall not be used for any other indication.

The position of the moving contacts of the mains switch shall correspond to the indications for the different positions of its operating means.

NOTE The figure O may, for example, also be used on a digital programming keyboard.

Compliance is checked by inspection.

8.11 Regulating devices and the like, intended to be adjusted during operation, shall be provided with an indication for the direction of adjustment to increase or to decrease the value of the characteristic being adjusted. An indication of + and - is considered to be sufficient.

The requirement does not apply to regulating devices provided with an adjusting means, if its fully "on" position is opposite to its "off" position.

If figures are used for indicating the different positions, the "off" position shall be indicated by the figure O and the other position shall be indicated by figures reflecting the greater output, input, speed, etc.

The indication for the different positions of the operating means of a control device need not to be placed on the device itself.

Compliance is checked by inspection.

8.12 An instruction manual and safety instructions shall be provided with the tool and packaged in such a way that is noticed by the user when the tool is removed from the packaging. The safety instructions may be separate from the instruction manual. An explanation of the symbols required by this standard shall be provided in either the instruction manual or the safety instructions.

They shall be written in the official language(s) of the country in which the tool is sold.

They shall be legible and contrast with the background.

They shall include the name and address of the manufacturer or supplier or any other agent responsible for placing the tool on the market.

8.12.1 The subjects of safety instructions are the General Power Tool Safety Warnings of Part 1 as given in 8.12.1.1, the specific tool Safety Warnings of the relevant part 2 and any additional safety warning statements deemed necessary by the manufacturer. The General Power Tool Safety Warnings and the specific tool Safety Warnings, if in English, shall be verbatim and in any other official language to be equivalent.

Format of all Safety Warnings must differentiate, by font highlighting or similar means, the context or clauses as illustrated below.

All notes in the safety instructions are not to be printed, they are information for the designer of the manual.

8.12.1.1 General Power Tool Safety Warnings

⚠ WARNING Read all safety warnings and instructions. Failure to follow the warnings and instructions may result in electric shock, fire and/or serious injury.

Save all warnings and instructions for future reference.

The term "power tool" in the warnings refers to your mains-operated (corded) power tool or battery-operated (cordless) power tool.

UL COPYRIGHTED MATERIAL –

NOT AUTHORIZED FOR FURTHER REPRODUCTION OR
DISTRIBUTION WITHOUT PERMISSION FROM



Documents

Document Sharing Hub

1) Work area safety

- a) **Keep work area clean and well lit.** *Cluttered or dark areas invite accidents.*
- b) **Do not operate power tools in explosive atmospheres, such as in the presence of flammable liquids, gases or dust.** *Power tools create sparks which may ignite the dust or fumes.*
- c) **Keep children and bystanders away while operating a power tool.** *Distractions can cause you to lose control.*

2) Electrical safety

- a) **Power tool plugs must match the outlet. Never modify the plug in any way. Do not use any adapter plugs with earthed (grounded) power tools.** *Unmodified plugs and matching outlets will reduce risk of electric shock.*
- b) **Avoid body contact with earthed or grounded surfaces such as pipes, radiators, ranges and refrigerators.** *There is an increased risk of electric shock if your body is earthed or grounded.*
- c) **Do not expose power tools to rain or wet conditions.** *Water entering a power tool will increase the risk of electric shock.*
- d) **Do not abuse the cord. Never use the cord for carrying, pulling or unplugging the power tool. Keep cord away from heat, oil, sharp edges or moving parts.** *Damaged or entangled cords increase the risk of electric shock.*
- e) **When operating a power tool outdoors, use an extension cord suitable for outdoor use.** *Use of a cord suitable for outdoor use reduces the risk of electric shock.*
- f) **If operating a power tool in a damp location is unavoidable, use a residual current device (RCD) protected supply.** *Use of an RCD reduces the risk of electric shock.*

NOTE The term "residual current device (RCD)" may be replaced by the term "ground fault circuit interrupter (GFCI)" or "earth leakage circuit breaker (ELCB)".

3) Personal safety

- a) **Stay alert, watch what you are doing and use common sense when operating a power tool. Do not use a power tool while you are tired or under the influence of drugs, alcohol or medication.** *A moment of inattention while operating power tools may result in serious personal injury.*
- b) **Use personal protective equipment. Always wear eye protection.** *Protective equipment such as dust mask, non-skid safety shoes, hard hat, or hearing protection used for appropriate conditions will reduce personal injuries.*
- c) **Prevent unintentional starting. Ensure the switch is in the off-position before connecting to power source and/or battery pack, picking up or carrying the tool.** *Carrying power tools with your finger on the switch or energising power tools that have the switch on invites accidents.*

- d) **Remove any adjusting key or wrench before turning the power tool on.** *A wrench or a key left attached to a rotating part of the power tool may result in personal injury.*
- e) **Do not overreach. Keep proper footing and balance at all times.** *This enables better control of the power tool in unexpected situations.*
- f) **Dress properly. Do not wear loose clothing or jewellery. Keep your hair, clothing and gloves away from moving parts.** *Loose clothes, jewellery or long hair can be caught in moving parts.*
- g) **If devices are provided for the connection of dust extraction and collection facilities, ensure these are connected and properly used.** *Use of dust collection can reduce dust-related hazards.*

4) Power tool use and care

- a) **Do not force the power tool. Use the correct power tool for your application.** *The correct power tool will do the job better and safer at the rate for which it was designed.*
- b) **Do not use the power tool if the switch does not turn it on and off.** *Any power tool that cannot be controlled with the switch is dangerous and must be repaired.*
- c) **Disconnect the plug from the power source and/or the battery pack from the power tool before making any adjustments, changing accessories, or storing power tools.** *Such preventive safety measures reduce the risk of starting the power tool accidentally.*
- d) **Store idle power tools out of the reach of children and do not allow persons unfamiliar with the power tool or these instructions to operate the power tool.** *Power tools are dangerous in the hands of untrained users.*
- e) **Maintain power tools. Check for misalignment or binding of moving parts, breakage of parts and any other condition that may affect the power tool's operation. If damaged, have the power tool repaired before use.** *Many accidents are caused by poorly maintained power tools.*
- f) **Keep cutting tools sharp and clean.** *Properly maintained cutting tools with sharp cutting edges are less likely to bind and are easier to control.*
- g) **Use the power tool, accessories and tool bits etc. in accordance with these instructions, taking into account the working conditions and the work to be performed.** *Use of the power tool for operations different from those intended could result in a hazardous situation.*

5) Service

- a) **Have your power tool serviced by a qualified repair person using only identical replacement parts.** *This will ensure that the safety of the power tool is maintained.*

UL COPYRIGHTED MATERIAL –
NOT AUTHORIZED FOR FURTHER REPRODUCTION OR
DISTRIBUTION WITHOUT PERMISSION FROM UL



Documents

Document Sharing Hub

8.12.1.2 The order of the Safety Instructions shall be either in accordance with either item A) or B) and in accordance with item C):

A) The Part 1 warnings are followed by the relevant part 2 warnings. The order of the warnings within the Part 1 and the part 2 warnings shall remain as given above and in the relevant part 2.

B) The Part 1 and the part 2 warnings may be divided into the sections defined by the numbered subtitles and the associated warnings below the numbered subtitle. The order of warnings within each section shall remain as given above and in the relevant part 2.

When warnings are presented in this manner, the title of the Part 1 “General Power Tool Safety Warnings” shall be omitted and the 1st sentence of the warnings in 8.12.1.1 and 8.12.2, if applicable, shall be modified as follows:

⚠ WARNING Read all safety warnings designated by the symbol ⚠ and all instructions.

The sections of the safety warnings shall be presented in the related topic of the Instruction Manual.

The Instruction Manual section titles for part 1 warnings shall have a format:

⚠ General Power Tool Safety Warnings – [Section subtitle]

Example:

⚠ General Power Tool Safety Warnings – Personal Safety

The Instruction Manual section titles for part 2 warnings shall have a format:

⚠ [Tool category name] Safety Warnings – [Section subtitle]

Example:

⚠ Circular Saw Safety Warnings – Cutting Procedures

If particular part 2 warnings do not have a numbered subtitle, then all warnings required by the particular part 2 shall be presented in the given order and the formatting rule above shall be followed without the [Section subtitle].

C) Any additional warnings deemed necessary by the manufacturer, shall not be inserted within any of the part 1 or part 2 warnings. They may be either appended to the section(s) of the Part 1 or part 2 in accordance with the topic of the safety warnings or located in any other part of the instruction manual.

UL COPYRIGHTED MATERIAL –

NOT AUTHORIZED FOR FURTHER REPRODUCTION OR
DISTRIBUTION WITHOUT PERMISSION FROM



Documents

Document Sharing Hub

8.12.2 If the Safety Instructions are separate from the Instruction Manual, then the following warnings shall be included in the Instruction Manual. These warnings, if in English, shall be verbatim and in any other official language to be equivalent.

⚠ WARNING Read all safety warnings and all instructions. *Failure to follow the warnings and instructions may result in electric shock, fire and/or serious injury.*

Save all warnings and instructions for future reference.

The Instruction Manual shall be provided with the following information, if appropriate.

- a) Instructions for putting into use
 - 1) Setting-up or fixing power tool in a stable position as appropriate for power tools which can be mounted on a support
 - 2) Assembly
 - 3) Connection to power supply, cabling, fusing, socket type and earthing requirements
 - 4) Illustrated description of functions
 - 5) Limitations on ambient conditions
 - 6) List of contents
- b) Operating instructions
 - 1) Setting and testing
 - 2) Tool changing
 - 3) Clamping of work
 - 4) Limits on size of workpiece
 - 5) General instructions for use
- c) Maintenance and servicing
 - 1) Regular cleaning, maintenance, method for keeping tools sharp, and lubrication
 - 2) Servicing by manufacturer or agent; list of addresses
 - 3) List of user-replaceable parts
 - 4) Special tools which may be required
 - 5) For power tools with type X attachment, where a specially prepared cord is needed to replace the cord: if the supply cord of this power tool is damaged, it must be replaced by a specially prepared cord available through the service organization.

- 6) For power tools with type Y attachment: if the replacement of the supply cord is necessary, this has to be done by the manufacturer or his agent in order to avoid a safety hazard.
- 7) For power tools with type Z attachment: the supply cord of this power tool cannot be replaced, and the power tool shall be scrapped.
- d) For tools with a liquid system, the substance of the following, as appropriate:
- 1) Instructions for
 - the connection to the liquid supply;
 - the use of the liquid and the use of attachments to comply with 14.4 in order to avoid affection of the tool by liquid;
 - the inspection of hoses and other critical parts which could deteriorate;
 - the maximum permitted pressure of the liquid supply
 - 2) For tools provided with an RCD
 - warning and instruction never to use the tool without the RCD provided with the tool;
 - warning and instruction always to test the correct operation of the RCD before starting work, unless the RCD is of a self-checking type
 - 3) For tools for use in combination with an isolating transformer: warning and instruction never to use the tool without the transformer delivered with the tool or of the type as specified in these instructions
 - 4) Warning and instruction that replacement of the plug or the supply cord shall always be carried out by the manufacturer of the tool or his service organization
 - 5) Warning and instruction to keep liquid clear off the parts of the tool and away from persons in the working area.

8.13 Markings required by the standard shall be easily legible and durable. Signs shall be in contrast such as colour, texture, or relief, to their background such that the information or instructions provided by the signs are clearly legible when viewed by the naked eye from a distance of not less than 500 mm. Signs need not be in accordance with the blue colour requirements of ISO 3864-2.

Compliance is checked by inspection and by rubbing the marking by hand for 15 s with a piece of cloth soaked with water and again for 15 s with a piece of cloth soaked with petroleum spirit.

After all the tests of this standard, the marking shall be easily legible, it shall not be easily possible to remove marking plates, and they shall show no curling.

In considering the durability of the marking, the effect of normal use is taken into account. Thus, for example, marking by means of paint or enamel other than vitreous enamel on containers that are likely to be cleaned frequently is not considered to be durable.

The petroleum spirit to be used for the test is aliphatic solvent hexane having a maximum aromatics content of 0,1% by volume, a kauributanol value of 29, an initial boiling point of approximately 65 °C, a dry point of approximately 69 °C and a specific mass of approximately 0,689 kg/l.

8.13DV D1 Modification: Add the following:

Additional tests are required for adhesive labels to test the durability of the adhesive system.

Compliance is checked by inspection and, if the label is not in compliance with CSA C22.2 No. 0.15 and UL 969, the tests described in this clause shall be performed.

After being subjected to the conditions described below, a pressure-sensitive label or a label secured by cement or adhesive shall be considered to be of a permanent nature if immediately following removal from each test medium and after being exposed to room temperature for 24 hours following removal from each medium:

- a) each sample demonstrates good adhesion and the edges are not curled.
- b) the label resists defacement or removal as demonstrated by scraping across the test panel with a flat steel blade, held at right angles to the test panel. The blade is to be 0,8 mm thick and of any convenient width.
- c) The printing is legible and is not defaced by rubbing with thumb or finger pressure.

Label Heating Test

Three samples of the label applied to test surfaces as in the intended application shall be placed for 240 h in an oven maintained at the temperature specified in Table 8.13DV.

UL COPYRIGHTED MATERIAL –

NOT AUTHORIZED FOR FURTHER REPRODUCTION OR
DISTRIBUTION WITHOUT PERMISSION FROM



Documents

Document Sharing Hub

Table 8.13DV
Maximum surface temperatures

Maximum temperature during temperature test of surface to which applied °C	Oven temperature °C
60 or less	87
80 or less	105
100 or less	121
125 or less	150
150 or less	180
Over 150	^a

^a A label that is applied to a surface attaining a temperature greater than 150°C during the temperature test shall be heated at a temperature representative of the temperatures attained by the appliance during intended use and abnormal use.

Label Immersion Tests

Six samples of the labels applied to test surfaces as in the intended application shall be placed in a controlled atmosphere maintained at $23.0 \pm 2.0^\circ\text{C}$ with a $50 \pm 5\%$ relative humidity for 24 h. Three samples shall then be immersed in water and three samples immersed in ASTM reference oil No. 3 at a temperature of $21.0 \pm 2.0^\circ\text{C}$ for 48 h in each case.

Note: The properties of ASTM reference oil No. 3 are defined in ANSI/ASTM D471.

Label Standard Atmosphere Test

Three samples of the label applied to test surfaces as in the intended application shall be placed for 72 hours in a controlled atmosphere maintained at $23.0 \pm 2.0^\circ\text{C}$ with a $50 \pm 5\%$ relative humidity.

After all the tests of this standard, the marking shall be easily legible; it shall not be easily possible to remove marking plates and they shall show no curling.

8.14 Markings specified in 8.1 to 8.5 shall be on a main part of the tool. Markings specified in 8.1, 8.2, 8.3 and 8.5 shall be placed together.

Markings on the tool shall be clearly discernible from the outside of the tool, but after removal of a cover if necessary. It shall be possible to remove or open this cover without the aid of a tool.

Indications for switches and controls shall be placed on or in the vicinity of these components; they shall not be placed on parts which can be repositioned, or positioned in such a way that the marking is misleading.

Compliance is checked by inspection.

8.15 If compliance with this standard depends upon the operation of a replaceable thermal link or fuse-link, the reference number or other means for identifying the link shall be marked on the link, or in a place that it is clearly visible after the link has failed, when the tool has been dismantled to the extent necessary for replacing the link.

This requirement does not apply to links which can only be replaced together with a part of the tool.

Compliance is checked by inspection.

9 Protection against access to live parts

Tools shall be so constructed and enclosed that there is adequate protection against accidental contact with live parts.

Compliance is checked by inspection, and by the tests of 9.2 to 9.4, as applicable.

9.1 An accessible part is not considered to be live if:

- the part is supplied with safety extra-low voltage, provided that
 - or a.c., the peak value of the voltage does not exceed 42 V;
 - for d.c., the voltage does not exceed 42 V;

or

- the part is separated from live parts by protective impedance.

In the case of protective impedance, the current between the part and the supply source shall not exceed 2 mA for d.c., and its peak value shall not exceed 0,7 mA for a.c., and moreover:

- for voltages having a peak value over 42 V up to and including 450 V, the capacitance shall not exceed 0,1 μ F;
- for voltages having a peak value over 450 V up to and including 15 kV, the discharge shall not exceed 45 μ C.

Compliance is checked by operating the tool at rated voltage. Voltages and currents are measured between the relevant parts and either pole of the supply source. Discharges are measured immediately after the interruption of the supply.

Document Was Downloaded By Rice, Shi CHENSHENG
For Use By KUANTECH CO LTD
12039 : 8/1/2007 - 10:50 PM
UL COPYRIGHTED MATERIAL –

NOT AUTHORIZED FOR FURTHER REPRODUCTION OR
DISTRIBUTION WITHOUT PERMISSION FROM



Documents
Document Sharing Hub

9.2 The requirement of 9.1 applies for all positions of the tool when it is operated as in normal use, even after removal of detachable parts.

Lamps located behind a detachable cover are not removed, provided the tool can be isolated from the supply by means of a plug or an all-pole switch. However, during insertion or removal of lamps which are located behind a detachable cover, protection against contact with live parts of the lamp cap shall be ensured.

This excludes the use of screw type fuses and screw-type miniature circuit breakers which are accessible without the aid of a tool.

The test finger of Figure 1 is applied without appreciable force, the tool being in every possible position.

Through openings, the test finger is applied to any depth that the finger will permit, and it is rotated or angled before, during, and after insertion to any position.

If the opening does not allow the entry of the finger, the force on the finger in the straight position is increased to 20 N and the test with the finger bent repeated.

It shall not be possible to touch with the test finger live parts or live parts protected only by lacquer, enamel, ordinary paper, cotton, oxide film, beads or sealing compound.

Lacquer, enamel, ordinary paper, cotton, oxide film on metal parts, beads and sealing compound, except self-hardening resins, are not considered to give the required protection against contact with live parts.

9.3 For openings in class II tools or class II constructions, except for those giving access to lamp caps or live parts in socket-outlets of class I tools, the test pin of Figure 2 is applied without appreciable force. It shall not be possible to touch live parts with the test pin.

9.4 In addition, class II tools and class II constructions shall be so constructed and enclosed that there is adequate protection against accidental contact with basic insulation, and metal parts separated from live parts by basic insulation only.

Parts which are not separated from live parts by double insulation or reinforced insulation shall not be accessible.

Compliance is checked by inspection and by applying the test finger of Figure 1.

This requirement applies for all positions of the tool when it is operated as in normal use, even after removal of detachable parts.

10 Starting

10.1 Motors shall start under all normal voltage conditions which may occur in use.

Compliance is checked by operating the tool with no-load 10 times at a voltage equal to 0,85 times rated voltage, regulating devices, if any, being set as in normal use.

In all cases, the tool shall function safely and correctly.

10.2 Centrifugal and other automatic starting switches shall operate reliably, and without contact chattering.

Tools provided with a centrifugal or other automatic starting switch are, in addition, operated 10 times at a voltage equal to 1,1 times rated voltage. The interval between consecutive starts is made sufficiently long to prevent undue heating.

In all cases, the tool shall function safely and correctly.

10.3 Overload protection devices shall not operate under normal starting conditions.

The tests of 10.1 and 10.2 check compliance with this requirement.

11 Input and current

The rated power input or rated current shall be at least 110% of the measured no-load input or current.

For tools marked with one or more rated voltage ranges, the test is made at both the upper and lower limits of the ranges, unless the marking or the rated power input is related to the mean value of the relevant voltage range, in which case the test is made at a voltage equal to the mean value of that range.

Compliance is checked by measuring the power input or current of the tool when stabilized while all circuits which can operate simultaneously are in operation.

12 Heating

12.1 Tools shall not attain excessive temperatures under normal load.

Compliance is checked by determining the temperature rise of the various parts under the conditions specified in 12.2 to 12.5 immediately followed by the test of clause 13 with the tool in the "on" position and under the following conditions:

For single-phase tools and for three-phase tools suitable for single-phase supply: S1 of Figure 3 in the "on" position, for three-phase tools with the three sections connected in parallel.

For three-phase tools not suitable for single-phase supply: a, b and c in Figure 4 in the "on" position, repeated with each of the switches a, b, c open in turn, the other two switches being closed.

For heating elements, the measurements are repeated with each of the switches a, b and c open in turn, the other two switches being closed.

12.2 The tool is operated in still air under normal load. While the torque is maintained, the voltage is then adjusted to 0,94 times the rated voltage or 1,06 times the rated voltage, or the mean of the rated voltage range, whichever is the most unfavourable.

Heating elements, if any, are operated under the conditions specified in clause 11 of IEC 60335-1, when the tool is operated at a voltage equal to 1,06 times rated voltage.

UL COPYRIGHTED MATERIAL –

NOT AUTHORIZED FOR FURTHER REPRODUCTION OR
DISTRIBUTION WITHOUT PERMISSION FROM



Documents

Document Sharing Hub