PD IEC/TR 61000-1-7:2016

BSI Standards Publication

Electromagnetic compatibility (EMC)

Part 1–7: General — Power factor in single-phase systems under non-sinusoidal conditions

bsi.

...making excellence a habit.™

Document Sharing Hub

Full document details: PD IEC/TR 61000-1-7:2016

National foreword

This Published Document is the UK implementation of IEC/TR 61000-1-7:2016.

The UK participation in its preparation was entrusted to Technical Committee GEL/210, EMC - Policy committee.

A list of organizations represented on this committee can be obtained on request to its secretary.

This publication does not purport to include all the necessary provisions of a contract. Users are responsible for its correct application.

© The British Standards Institution 2016.
Published by BSI Standards Limited 2016

ISBN 978 0 580 87999 9
ICS 33.100.01

Compliance with a British Standard cannot confer immunity from legal obligations.

This Published Document was published under the authority of the Standards Policy and Strategy Committee on 31 March 2016.

Amendments/corrigenda issued since publication

Date	Text affected

Documents
Document Sharing Hub

Full document details: PD IEC/TR 61000-1-7:2016

IEC TR 61000-1-7

Edition 1.0 2016-02

TECHNICAL REPORT

Electromagnetic compatibility (EMC) – Part 1-7: General – Power factor in single-phase systems under non-sinusoidal conditions

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 33.100.01

ISBN 978-2-8322-3196-8

Warning! Make sure that you obtained this publication from an authorized distributor.

® Registered trademark of the International Electrotechnical Commission

Documents
Document Sharing Hub

Full document details: PD IEC/TR 61000-1-7:2016

CONTENTS

FOREWORD 4
INTRODUCTION 6
0.1 Series overview 6
0.2 Purpose of this document 6
1 Scope 8
2 Normative references 8
3 Terms and definitions 8
4 General 14
5 Electric power quantities under non-sinusoidal conditions 15
5.1 Voltages and currents 15
5.1.1 Instantaneous values 15
5.1.2 Reference fundamental components 16
5.1.3 Total distortion contents 16
5.1.4 RMS values of the voltage and current 16
5.1.5 RMS values of total distortion contents 17
5.1.6 DC ratios 17
5.1.7 Total distortion ratios 17
5.2 Instantaneous power 18
5.3 Definitions related to the active power 18
5.3.1 Active power 18
5.3.2 DC power 18
5.3.3 Fundamental active power 19
5.3.4 Distortion active power 19
5.4 Definitions related to the apparent power 19
5.4.1 Apparent power 19
5.4.2 Fundamental apparent power 20
5.5 Definitions related to the power factor 20
5.5.1 Power factor 20
5.5.2 Fundamental power factor 21
5.5.3 Non-fundamental power factor 21
5.6 Summary 21
6 Electric power quantities with a sinusoidal voltage and a current distorted only with harmonics 22
6.1 Voltages and currents 22
6.1.1 Instantaneous values 22
6.1.2 Fundamental components 22
6.1.3 Harmonic content of the current 23
6.1.4 RMS values of the voltage and current 23
6.1.5 RMS value of the harmonic content of the current 23
6.1.6 Total harmonic ratio of the current 24
6.1.7 Fundamental factor 24
6.2 Instantaneous power 24
6.3 Active power 24
6.4 Definitions related to the apparent power 25
6.4.1 Apparent power 25

AVA Documents
Document Sharing Hub
Full document details: PD IEC/TR 61000-1-7:2016

6.4.2 Fundamental apparent power 25
6.5 Definitions related to the power factor 25
6.5.1 Power factor 25
6.5.2 Fundamental power factor 26
6.5.3 Non-fundamental power factor 26
6.6 Summary 27
Annex A (normative) Electric power quantities under sinusoidal conditions 28
A.1 Instantaneous values of the voltage and current 28
A.2 Instantaneous power 29
A.3 Active power 30
A.4 Reactive power 30
A.5 Apparent power 30
A.6 Power factor 30
Annex B (informative) Fundamental active factor 32
B.1 Fundamental active factor and its use 32
B.2 Consumer convention 32
Bibliography 34

Figure A.1 – Illustration of the displacement angle (φ) when the voltage leads the current, $\varphi > 0$ 28
Figure A.2 – Illustration of the displacement angle (φ) when the voltage lags the current, $\varphi < 0$ 29
Figure B.1 – Consumer sign convention of the fundamental active factor, fundamental active power and fundamental reactive power 33

Table 1 – Summary of the power quantities under non-sinusoidal conditions 21
Table 2 – Summary of the power quantities with a sinusoidal voltage and a current distorted only with harmonics 27

Documents
Document Sharing Hub
Full document details: PD IEC/TR 61000-1-7:2016

INTERNATIONAL ELECTROTECHNICAL COMMISSION

ELECTROMAGNETIC COMPATIBILITY (EMC) –

Part 1-7: General – Power factor in single-phase systems under non-sinusoidal conditions

FOREWORD

1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
6) All users should ensure that they have the latest edition of this publication.
7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

The main task of IEC technical committees is to prepare International Standards. However, a technical committee may propose the publication of a technical report when it has collected data of a different kind from that which is normally published as an International Standard, for example "state of the art".

IEC TR 61000-1-7, which is a Technical Report, has been prepared by subcommittee 77A: *EMC – Low frequency phenomena,* of IEC technical committee 77*: Electromagnetic compatibility*.

Documents
Document Sharing Hub
Full document details: PD IEC/TR 61000-1-7:2016

The text of this technical report is based on the following documents:

Enquiry draft	Report on voting
77A/911/DTR	77A/920/RVC

Full information on the voting for the approval of this technical report can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all parts in the IEC 61000 series, published under the general title *Electromagnetic compatibility (EMC)*, can be found on the IEC website.

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC website under "http://webstore.iec.ch" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

A bilingual version of this publication may be issued at a later date.

Documents
Document Sharing Hub

Full document details: PD IEC/TR 61000-1-7:2016

INTRODUCTION

0.1 Series overview

IEC 61000 is published in separate parts, according to the following structure:

Part 1: General

General considerations (introduction, fundamental principles)

Definitions, terminology

Part 2: Environment

Description levels

Classification of the environment

Compatibility levels

Part 3: Limits

Emission limits

Immunity limits (in so far as they do not fall under the responsibility of the product committees)

Part 4: Testing and measurement techniques

Measurement techniques

Testing techniques

Part 5: Installation and mitigation guidelines

Installation guidelines

Mitigation methods and devices

Part 6: Generic standards

Part 9: Miscellaneous

Each part is further subdivided into sections which are to be published either as international standards, technical specifications, or as technical reports.

These standards and reports will be published in chronological order and numbered accordingly (for example, 61000-6-1).

0.2 Purpose of this document

The prevalence of loads drawing non-sinusoidal current from power systems requires clarification of such concepts as power and power factor, in order to avoid confusion due to

Documents
Document Sharing Hub

implied assumptions of sinusoidal voltage and current. This document specifically addresses the terms related to the power factor of equipment that are applicable regardless of the voltage and current waveforms.

When voltages and currents on power supply networks are perfectly sinusoidal, cos φ corresponds to the power factor. But this is not true anymore when electric quantities are distorted. In some existing documents, cos φ is still used as power factor, leading to an incorrect assessment of the equipment impact to supply networks.

The purpose of this Technical Report is to give clear information on both components in the power factor:

- the fundamental power factor, which is due to the phase difference between the voltage and current at the fundamental frequency (cos φ_1), and
- the non-fundamental power factor, which is related to the distortion of the voltage and/or current.

Documents
Document Sharing Hub

Full document details: PD IEC/TR 61000-1-7:2016

ELECTROMAGNETIC COMPATIBILITY (EMC) –

Part 1-7: General – Power factor in single-phase systems under non-sinusoidal conditions

1 Scope

This part of IEC 61000, which is a Technical Report, provides definitions of various electrical power quantities and the relationship between them under non-sinusoidal conditions, in order to give clear information on both components in the power factor: the fundamental power factor, which is due to the phase difference between the voltage and current at the fundamental frequency, and the non-fundamental power factor, which is related to the distortion of the voltage and/or current. This Technical Report is applicable only to single-phase systems.

This Technical Report provides definitions for the three following cases:

- the general case where the voltage and current are both distorted (Clause 5),
- the case where the voltage is assumed to be sinusoidal and the current is only distorted with harmonic components (Clause 6),
- the particular case where the voltage and current are both sinusoidal (Annex A).

Annex B gives information on the fundamental active factor, which is used to describe the behaviour of a piece of equipment as a load or a generator.

2 Normative references

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

Void.

3 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

3.1
root-mean-square value
r.m.s. value
effective value
for a time-dependent quantity, positive square root of the mean value of the square of the quantity taken over a given time interval

Note 1 to entry: The root-mean-square value of a periodic quantity is usually taken over an integration interval the range of which is the period multiplied by a natural number.

Note 2 to entry: For a sinusoidal quantity $a(t) = \hat{A}\cos(\omega t + \vartheta_0)$, the root-mean-square value is $A_{\text{eff}} = \hat{A}/\sqrt{2}$.

Note 3 to entry: The root-mean-square value of a quantity may be denoted by adding one of the subscripts eff or rms to the symbol of the quantity.

Documents
Document Sharing Hub
Full document details: PD IEC/TR 61000-1-7:2016

Note 4 to entry: In electrical technology, the root-mean-square values of electric current $i(t)$ and voltage $u(t)$are usually denoted I and U, respectively.

[SOURCE: IEC 60050-103:2009, 103-02-03]

3.2
direct component
mean value of a quantity taken over a given time interval

[SOURCE: IEC 60050-103:2009, 103-06-05, modified – definition extended to quantities containing interharmonic components.]

3.3
sinusoidal, adj.
pertaining to an alternating quantity represented by the product of a real constant and a sine or cosine function whose argument is a linear function of the independent variable

Note 1 to entry: The real constant may be a scalar, vector or tensor quantity.

Note 2 to entry: Examples are $a(t) = \hat{A}\cos(\omega t + \vartheta_0)$ and $a(x) = \hat{A}\cos[k(x - x_0)]$.

[SOURCE: IEC 60050-103:2009, 103-07-01]

3.4
initial phase
phase angle
ϑ_0
value of the phase of a sinusoidal quantity when the value of the independent variable is zero

Note 1 to entry: For the quantity $a(t) = \hat{A}\cos(\omega t + \vartheta_0)$, the initial phase is ϑ_0.

[SOURCE: IEC 60050-103:2009, 103-07-05]

3.5
periodic conditions
state of an electric circuit element or electric circuit that is characterized by the electric currents and voltages all being periodic functions of time with the same period T

[SOURCE: IEC 60050-131:2002, 131-11-27, modified – addition of symbol T for the period.]

3.6
sinusoidal conditions
state of a linear electric circuit element or electric circuit that is characterized by the electric currents and voltages all being sinusoidal functions of time with the same frequency

[SOURCE: IEC 60050-131:2002, 131-11-28]

3.7
instantaneous power
$p(t)$
for a two-terminal element or a two-terminal circuit with terminals A and B, product of the voltage u_{AB} between the terminals and the electric current i in the element or circuit

$$p(t) = u_{AB}(t) \cdot i(t)$$

where u_{AB} is the line integral of the electric field strength from A to B, and where the electric current in the element or circuit is taken positive if its direction is from A to B and negative if its direction is from B to A

Documents
Document Sharing Hub
Full document details: PD IEC/TR 61000-1-7:2016

Note 1 to entry: The direction of electric current is as defined in IEC 60050:2002, 131-11-29.

Note 2 to entry: In circuit theory the electric field strength is generally non-rotational and thus $u_{AB} = v_A - v_B$, where v_A and v_B are the electric potentials at terminals A and B, respectively.

Note 3 to entry: The coherent SI unit of instantaneous power is watt, W.

Note 4 to entry: A two-terminal element or circuit refers to a single-phase equipment or system.

[SOURCE: IEC 60050-131:2013, 131-11-30, modified – in note 2, the term irrotational is replaced by non-rotational and a new note 4 has been added.]

3.8
apparent power
S
product of the r.m.s. voltage U between the terminals of a two-terminal element or two-terminal circuit and the r.m.s. electric current I in the element or circuit

$$S = UI$$

Note 1 to entry: The coherent SI unit for apparent power is voltampere, VA.

Note 2 to entry: A two-terminal element or circuit refers to a single-phase equipment or system.

[SOURCE: IEC 60050-131:2013, 131-11-41, modified – the existing note 1 has been removed and a note 2 has been added.]

3.9
active power
P
under periodic conditions, mean value, taken over one period T, of the instantaneous power $p(t)$

$$P = \frac{1}{T}\int_0^T p(t)dt$$

Note 1 to entry: The coherent SI unit for active power is watt, W.

Note 2 to entry: When the voltage or current contain interharmonic components, often their waveforms are no more periodic. In this document, the active power is approximated by the mean value of the instantaneous power, taken over an integer number of periods of the a.c. power supply system (see 5.3.1 and 5.1.4). This definition is also used under periodic conditions in this document (see 6.3 and Clause A.3).

[SOURCE: IEC 60050-131:2013, 131-11-42, modified – the existing note 1 has been removed and a note 2 has been added.]

3.10
non-active power
$Q\sim$
for a two-terminal element or a two-terminal circuit under periodic conditions, quantity equal to the square root of the difference of the squares of the apparent power S and the active power P

$$Q\sim = \sqrt{S^2 - P^2}$$

Note 1 to entry: The coherent SI unit for non-active power is voltampere, VA. The special name "var" and its symbol "var" are also used. See IEC 60050-131:2013, 131-11-45.

Note 2 to entry: A two-terminal element or circuit refers to a single-phase equipment or system.

[SOURCE: IEC 60050-131:2013, 131-11-43, modified – the existing note 1 has been removed and a note 2 has been added.]

Documents
Document Sharing Hub
Full document details: PD IEC/TR 61000-1-7:2016